

The name of the part to create. This will default to the name of the project but can be overwritten here.

A colour picker to enable the user to determine the fill colour for the board. Ideally, the fill should be based on the F.Mask layer of the board definition.

The size of the pads is scaled and seems to be appropriate but there may be a corner case where there is a problem with the render. This option enables the user to reduce the size so that they are visually more appealing and usable. It is a floating point number with one decimal place.

When the silkscreen overlay option is unchecked, this option will be available. The in-house generation of the silkscreen text is not infalable and the scaling may need tweaking. This option allows for that. Once the KiCad-native SVG generation has been proven, then this will be removed

KiCad to Fritzing Part Generation

Output directory  

Part name

Soldermask color  Silkscreen color 

Pad/Pin Scaling

☒ Use KiCad-native silkscreen overlay (recommended)

Text scaling

This will open the file navigator i.e. finder in OSX and point to the path mentioned in the output directory. This is a feature on other KiCad dialogs

Enables the user to locate or create and then select the target directory. If the directory is relative to the project directory, then the user should be asked if they want to make the directory relative and the relative directory name is placed in the output directory field which should be supported by the generation processor.

The path where the Fritzing files should be created.

A colour picker to define the colour that the F.Silks should be in the final render. This is to ensure the user has control over the contrast between the solder mask and the silkscreen as it would appear from the Fab house.

For diagnostics purposes on these initial releases of the plugin - the ability to use an in-house hand crafted SVG file based on the pcb_new design file (unchecked) or use the built in KiCad SVG generation API (checked). This will eventually be removed if this works well.

The close button on the left is the usual name and location of this button. Generally the dialog does not close on generate. Only when the close button is pressed.