



Product Specification

Part Name: EPD Display Module
Customer Part ID:
Zhongjingyuan Part ID: ZJYE420S08W0G01
Ver: A

Customer:

Approved by

From: Zhengzhou Zhongjingyuan Electronic Technology Co., LTD.

Approved by

Zhengzhou Zhongjingyuan Electronic Technology Co., LTD.

302, Building 9, Yida Science and Technology New Town, No. 16, Jinzhan Street,
High-tech Industrial Development Zone, Zhengzhou, Henan, China

Notes:

1. Please contact Zhengzhou Zhongjingyuan Electronic Technology Co., LTD. before assigning your product based on this module specification
2. The information contained herein is presented merely to indicate the characteristics and performance of our products. No responsibility is assumed by Zhengzhou Zhongjingyuan Electronic Technology Co., LTD. for any intellectual property claims or other problems that may result from application based on the module described herein.

DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJY420S08W0G01	Page 1 of 35



REVISION HISTORY

Rev	Date	Item	Page	Remark
1.0	MAY.28.2020	New Creation	ALL	
1.1	OCT.10.2020	Update Mechanical Drawing Update Absolute Maximum Rating Update DC Characteristics Update Panel AC Characteristics Update Command Table Update Optical Specifications Update Typical Application Circuit Update Typical Operating Sequence Add Packaging	P5 P7 P8 P9-11 P12-25 P26 P29 P30-31 P36	Modify IC and add peeling paper
1.2	NOV.06.2020	Update Typical operating current	P8	
1.3	JUN.20.2022	Update Mechanical Drawing of EPD module Delete Block Diagram Update Inspection method and condition Update Packaging	P5 P28 P31-34 P35	
1.4	JUL.18.2022	Update Electrical Characteristics	P8	
1.5	JUL.29.2022	Update Electrical Characteristics Update Reliability test	P8, 11 P27	

DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJY420S08W0G01	Page 2 of 35



LIST

1. Over View -----	(4)
2. Features-----	(4)
3. Mechanical Specifications-----	(4)
4. Mechanical Drawing of EPD module-----	(5)
5. Input /Output Pin Assignment-----	(6-7)
6. Electrical Characteristics-----	(7)
6.1 Absolute Maximum Rating-----	(7)
6.2 Panel DC Characteristics-----	(8)
6.3 Panel AC Characteristics-----	(9)
6.3.1 MCU Interface Selection -----	(9)
6.3.2 MCU Serial Interface(4-wire SPI) -----	(9)
6.3.3 MCU Serial Peripheral Interface (3-wire SPI) -----	(10)
6.3.4 Interface Timing-----	(11)
7. Command Table -----	(12-25)
8. Optical Specifications -----	(26)
9. Handling, Safety and Environment Requirements -----	(26)
10. Reliability test-----	(27)
11. Typical Application Circuit with SPI Interface -----	(28)
12. Typical Operating Sequence -----	(29)
12.1 Normal Operation Flow -----	(29)
12.2 Normal Operation Reference Program Code-----	(30)
13. Part Number Definition-----	(31)
14. Inspection method and condition-----	(31)
14.1 Inspection condition-----	(31)
14.2 Display area-----	(31)
14.3 General inspection standards for product-----	(32-34)
15. Packaging-----	(35)

DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJY400300-042CAAMFGN	Page 3 of 35



1. Over View

ZJYE420S08W0G01 is an Active Matrix Electrophoretic Display (AM EPD), with interface and a reference system design. The display is capable to display images at 1-bit white, black full display capabilities. The 4.2inch active area contains 300×400 pixels. The module is a TFT-array driving electrophoresis display, with integrated circuits including gate driver, source driver, MCU interface, timing controller, oscillator, DC-DC, SRAM, LUT, VCOM. Module can be used in portable electronic devices, such as Electronic Shelf Label (ESL) System.

2.Features

- 300×400 pixels display
- High contrast High reflectance
- Ultra wide viewing angle Ultra low power consumption
- Pure reflective mode
- Bi-stable display
- Commercial temperature range
- Landscape portrait modes
- Hard-coat antiglare display surface
- Ultra Low current deep sleep mode
- On chip display RAM
- Waveform can stored in On-chip OTP or written by MCU
- Serial peripheral interface available
- On-chip oscillator
- On-chip booster and regulator control for generating VCOM, Gate and Source driving voltage
- I²C signal master interface to read external temperature sensor
- Support partial update mode
- Built-in temperature sensor

3. Mechanical Specifications

Parameter	Specifications	Unit	Remark
Screen Size	4.2	Inch	
Display Resolution	400(H)×300(V)	Pixel	Dpi:120
Active Area	84.8×63.6	mm	
Pixel Pitch	0.212×0.212	mm	
Pixel Configuration	Rectangle		
Outline Dimension	91.5 (H)×90.00 (V) ×2.4(D)	mm	
Weight	39±0.3	g	

DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJYE420S08W0G01	Page 4 of 35



5. Input /Output Pin Assignment

No.	Name	I/O	Description	Remark
1	GND	P	Ground	
2	VCC	P	Power Supply for the chip	
3	SCL	I	Serial Clock pin (SPI)	
4	SDA	I/O	Serial Data pin (SPI)	
5	RES#	I	Reset signal input. Active Low.	
6	DC	I	Data /Command control pin	
7	CS	I	Chip select input pin	
8	BUSY	O	Busy state output pin	

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 6 of 35



I = Input Pin, O =Output Pin, I/O = Bi-directional Pin (Input/output), P = Power Pin, C =Capacitor Pin

Note 5-1: This pin (CS#) is the chip select input connecting to the MCU. The chip is enabled for MCU communication only when CS# is pulled LOW.

Note 5-2: This pin is (D/C#) Data/Command control pin connecting to the MCU in 4-wire SPI mode. When the pin is pulled HIGH, the data at SDA will be interpreted as data. When the pin is pulled LOW, the data at SDA will be interpreted as command.

Note 5-3: This pin (RES#) is reset signal input. The Reset is active low.

Note 5-4: This pin is Busy state output pin. When Busy is High, the operation of chip should not be interrupted, command should not be sent. The chip would put Busy pin High when
–Outputting display waveform
–Communicating with digital temperature sensor

Note 5-5: Bus interface selection pin

BS1 State	MCU Interface
L=R2	4-lines serial peripheral interface(SPI) - 8 bits SPI
H=R1	3- lines serial peripheral interface(SPI) - 9 bits SPI

6. Electrical Characteristics

6.1 Absolute Maximum Rating

Parameter	Symbol	Rating	Unit
Logic supply voltage	VCC	2.2 to 3.7	V
Operating Temp range	TOPR	0 to +50	°C
Storage Temp range	TSTG	-25 to+70	°C
Optimal Storage Temp	TSTGo	23±2	°C
Optimal Storage Humidity	HSTGo	55±10	%RH

Note:

Maximum ratings are those values beyond which damages to the device may occur. Functional operation should be restricted to the limits in the Panel DC Characteristics tables.

DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJYE420S08W0G01	Page 7 of 35




6.2 DC Characteristics

The following specifications apply for: VSS=0V, VCI=3.0V, TOPR =25°C.

Parameter	Symbol	Conditions	Applicable pin	Min.	Typ.	Max	Units
Single ground	V _{SS}	-		-	0	-	V
Logic supply voltage	V _{CC}	-	VCC	2.2	3.0	3.7	V
Image update time	-	25 °C	-	-	3	-	sec
Sleep mode current	Islp_VCI	DC/DC off No clock No input load Ram data retain	-	-	25	-	uA
Deep sleep mode current	Idslp_VCI	DC/DC off No clock No input load Ram data not retain	-	-	3	5	uA

Notes: 1. The typical power is measured with following transition from horizontal 2 scale pattern to vertical 2 scale pattern.



2. The deep sleep power is the consumed power when the panel controller is in deep sleep mode.
3. The listed electrical/optical characteristics are only guaranteed under the controller & waveform provided by Zhongjingyuan.

DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJYE420S08W0G01	Page 8 of 35



6.3AC Characteristics

6.3.1 MCU Interface Selection

The IC can support 3-wire/4-wire serial peripheral. MCU interface is pin selectable by BS1 shown in Table 6-1.

Table 6-1 : Interface pins assignment under different MCU interface

MCU Interface	Pin Name					
	BS1	RES#	CS#	D/C#	SCL	SDA
4-wire serial peripheral interface (SPI)	L	RES#	CS#	DC#	SCL	SDA
3-wire serial peripheral interface (SPI) – 9 bits SPI	H	RES#	CS#	L	SCL	SDA

Note : (1) L is connected to VSS and H is connected to VDDIO

6.3.2 MCU Serial Interface (4-wire SPI)

The 4-wire SPI consists of serial clock SCL, serial data SDA, D/C# and CS#. The control pins status in 4-wire SPI in writing command/data is shown in Table 6-2 and the write procedure 4-wire SPI is shown in Table 6-2

Table 6-2 : Control pins status of 4-wire SPI

Function	SCL pin	SDA pin	D/C# pin	CS# pin
Write command	↑	Command bit	L	L
Write data	↑	Data bit	H	L

Note:(1) L is connected to VSS and H is connected to VDDIO

(2) ↑ stands for rising edge of signal

(3) SDA (Write Mode) is shifted into an 8-bit shift register on every rising edge of SCL in the order of D7, D6, ... D0. The level of D/C# should be kept over the whole byte. The data byte in the shift register is written to the Graphic Display Data RAM (RAM)/Data Byte register or command Byte register according to D/C# pin.




Figure 6-1 : Write procedure in 4-wire SPI mode

DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJYE420S08W0G01	Page 9 of 35



6.3.3 MCU Serial Peripheral Interface (3-wire SPI)

MCU Serial Peripheral Interface (3-wire SPI) The 3-wire SPI consists of serial clock SCL, serial data SDA and CS#. The operation is similar to 4-wire SPI while D/C# pin is not used and it must be tied to LOW. The control pins status in 3-wire SPI is shown in Table 6-3.

In the write operation, a 9-bit data will be shifted into the shift register on every clock rising edge. The bit shifting sequence is D/C# bit, D7 bit, D6 bit to D0 bit. The first bit is D/C# bit which determines the following byte is command or data. When D/C# bit is 0, the following byte is command. When D/C# bit is 1, the following byte is data. Table 6-3 shows the write procedure in 3-wire SPI

Table 6-3 : Control pins status of 3-wire SPI

Function	SCL pin	SDA pin	D/C# pin	CS# pin
Write command	↑	Command bit	Tie LOW	L
Write data	↑	Data bit	Tie LOW	L

Note: (1) L is connected to VSS and H is connected to VDDIO

(2) ↑ stands for rising edge of signal





Figure 6-3 : Write procedure in 3-wire SPI

DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJYE420S08W0G01	Page 10 of 35



6.4.4 Interface Timing

The following specifications apply for: VSS=0V, VCI=3.0V, TOPR =25 ℃.



Write mode

Symbol	Parameter	Min	Typ	Max	Unit
fSCL	SCL frequency (Write Mode)	-	-	20	MHz
tCSSU	Time CS# has to be low before the first rising edge of SCLK	60	-	-	ns
tCSSD	Time CS# has to remain low after the last falling edge of SCLK	60	-	-	ns
tCSHLD	Time CS# has to remain high between two transfers	100	-	-	ns
tSCLHIGH	Part of the clock period where SCL has to remain high	25	-	-	ns
tSCLLOW	Part of the clock period where SCL has to remain low	25	-	-	ns
tSISU	Time SI (SDA Write Mode) has to be stable before the next rising edge of SCL	10	-	-	ns
tSIHLD	Time SI (SDA Write Mode) has to remain stable after the rising edge of SCL	40	-	-	ns

Read mode

Symbol	Parameter	Min	Typ	Max	Unit
fSCL	SCL frequency (Read Mode)	-	-	2.5	MHz
tCSSU	Time CS# has to be low before the first rising edge of SCLK	100	-	-	ns
tCSSD	Time CS# has to remain low after the last falling edge of SCLK	50	-	-	ns
tCSHLD	Time CS# has to remain high between two transfers	250	-	-	ns
tSCLHIGH	Part of the clock period where SCL has to remain high	180	-	-	ns
tSCLLOW	Part of the clock period where SCL has to remain low	180	-	-	ns
tSOSU	Time SO (SDA Read Mode) will be stable before the next rising edge of SCL	-	50	-	ns
tSOHLD	Time SO (SDA Read Mode) will remain stable after the falling edge of SCL	-	0	-	ns

Note: All timings are based on 20% to 80% of VDDIO-VSS

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 11 of 35



7. Command Table

Command Table																																																																			
R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0	Command	Description																																																							
0	0	01	0	0	0	0	0	0	0	1	Driver Output control	Gate setting A[8:0]= 12Bh [POR], 300 MUX MUX Gate lines setting as (A[8:0] + 1).																																																							
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																																																									
0	1		0	0	0	0	0	0	0	A ₈																																																									
0	1		0	0	0	0	0	B ₂	B ₁	B ₀		B [2:0] = 000 [POR]. Gate scanning sequence and direction B[2]: GD Selects the 1st output Gate GD=0 [POR], G0 is the 1st gate output channel, gate output sequence is G0,G1, G2, G3, ... GD=1, G1 is the 1st gate output channel, gate output sequence is G1, G0, G3, G2, ... B[1]: SM Change scanning order of gate driver. SM=0 [POR], G0, G1, G2, G3...299 (left and right gate interlaced) SM=1, G0, G2, G4 ...G294, G1, G3, ...G299 B[0]: TB TB = 0 [POR], scan from G0 to G299 TB = 1, scan from G299 to G0.																																																							
0	0	03	0	0	0	0	0	0	1	1	Gate Driving voltage Control	Set Gate driving voltage A[4:0] = 00h [POR] VGH setting from 10V to 20V																																																							
0	1		0	0	0	A ₄	A ₃	A ₂	A ₁	A ₀		<table><tr><th>A[4:0]</th><th>VGH</th><th>A[4:0]</th><th>VGH</th></tr><tr><td>00h</td><td>20</td><td>0Dh</td><td>15</td></tr><tr><td>03h</td><td>10</td><td>0Eh</td><td>15.5</td></tr><tr><td>04h</td><td>10.5</td><td>0Fh</td><td>16</td></tr><tr><td>05h</td><td>11</td><td>10h</td><td>16.5</td></tr><tr><td>06h</td><td>11.5</td><td>11h</td><td>17</td></tr><tr><td>07h</td><td>12</td><td>12h</td><td>17.5</td></tr><tr><td>08h</td><td>12.5</td><td>13h</td><td>18</td></tr><tr><td>07h</td><td>12</td><td>14h</td><td>18.5</td></tr><tr><td>08h</td><td>12.5</td><td>15h</td><td>19</td></tr><tr><td>09h</td><td>13</td><td>16h</td><td>19.5</td></tr><tr><td>0Ah</td><td>13.5</td><td>17h</td><td>20</td></tr><tr><td>0Bh</td><td>14</td><td>Other</td><td>NA</td></tr><tr><td>0Ch</td><td>14.5</td><td></td><td></td></tr></table>	A[4:0]	VGH	A[4:0]	VGH	00h	20	0Dh	15	03h	10	0Eh	15.5	04h	10.5	0Fh	16	05h	11	10h	16.5	06h	11.5	11h	17	07h	12	12h	17.5	08h	12.5	13h	18	07h	12	14h	18.5	08h	12.5	15h	19	09h	13	16h	19.5	0Ah	13.5	17h	20	0Bh	14	Other	NA	0Ch	14.5	
A[4:0]	VGH	A[4:0]	VGH																																																																
00h	20	0Dh	15																																																																
03h	10	0Eh	15.5																																																																
04h	10.5	0Fh	16																																																																
05h	11	10h	16.5																																																																
06h	11.5	11h	17																																																																
07h	12	12h	17.5																																																																
08h	12.5	13h	18																																																																
07h	12	14h	18.5																																																																
08h	12.5	15h	19																																																																
09h	13	16h	19.5																																																																
0Ah	13.5	17h	20																																																																
0Bh	14	Other	NA																																																																
0Ch	14.5																																																																		

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 12 of 35



Command Table

R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0	Command	Description
0	0	04	0	0	0	0	0	1	0	0	Source Driving voltage Control	Set Source driving voltage A[7:0] = 41h [POR], VSH1 at 15V B [7:0] = A8h [POR], VSH2 at 5V. C[7:0] = 32h [POR], VSL at -15V Remark: VSH1>=VSH2
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀		
0	1		B ₇	B ₆	B ₅	B ₄	B ₃	B ₂	B ₁	B ₀		
0	1		C ₇	C ₆	C ₅	C ₄	C ₃	C ₂	C ₁	C ₀		

B[7] = 1,
VSH2 voltage setting from 2.4V to 8.6V

A/B[7:0]	VSH1/VSH2	A/B[7:0]	VSH1/VSH2
8Eh	2.4	AEh	5.6
8Fh	2.5	AFh	5.7
90h	2.6	B0h	5.8
91h	2.7	B1h	5.9
92h	2.8	B2h	6
93h	2.9	B3h	6.1
94h	3	B4h	6.2
95h	3.1	B5h	6.3
96h	3.2	B6h	6.4
97h	3.3	B7h	6.5
98h	3.4	B8h	6.6
99h	3.5	B9h	6.7
9Ah	3.6	BAh	6.8
9Bh	3.7	BBh	6.9
9Ch	3.8	BCh	7
9Dh	3.9	BDh	7.1
9Eh	4	BEh	7.2
9Fh	4.1	BFh	7.3
A0h	4.2	C0h	7.4
A1h	4.3	C1h	7.5
A2h	4.4	C2h	7.6
A3h	4.5	C3h	7.7
A4h	4.6	C4h	7.8
A5h	4.7	C5h	7.9
A6h	4.8	C6h	8
A7h	4.9	C7h	8.1
A8h	5	C8h	8.2
A9h	5.1	C9h	8.3
AAh	5.2	CAh	8.4
ABh	5.3	CBh	8.5
ACH	5.4	CCh	8.6
ADh	5.5	Other	NA

A[7]/B[7] = 0,
VSH1/VSH2 voltage setting from 8.8V to 17V

A/B[7:0]	VSH1/VSH2	A/B[7:0]	VSH1/VSH2
21h	8.8	37h	13
23h	9	38h	13.2
24h	9.2	39h	13.4
25h	9.4	3Ah	13.6
26h	9.6	3Bh	13.8
27h	9.8	3Ch	14
28h	10	3Dh	14.2
29h	10.2	3Eh	14.4
2Ah	10.4	3Fh	14.6
2Bh	10.6	40h	14.8
2Ch	10.8	41h	15
2Dh	11	42h	15.2
2Eh	11.2	43h	15.4
2Fh	11.4	44h	15.6
30h	11.6	45h	15.8
31h	11.8	46h	16
32h	12	47h	16.2
33h	12.2	48h	16.4
34h	12.4	49h	16.6
35h	12.6	4Ah	16.8
36h	12.8	4Bh	17
		Other	NA

C[7] = 0,
VSL setting from -5V to -17V

C[7:0]	VSL
0Ah	-5
0Ch	-5.5
0Eh	-6
10h	-6.5
12h	-7
14h	-7.5
16h	-8
18h	-8.5
1Ah	-9
1Ch	-9.5
1Eh	-10
20h	-10.5
22h	-11
24h	-11.5
26h	-12
28h	-12.5
2Ah	-13
2Ch	-13.5
2Eh	-14
30h	-14.5
32h	-15
34h	-15.5
36h	-16
38h	-16.5
3Ah	-17
Other	NA

0	0	08	0	0	0	0	1	0	0	0	Initial Code Setting OTP Program	Program Initial Code Setting The command required CLKEN=1. Refer to Register 0x22 for detail. BUSY pad will output high during operation.
0	0	09	0	0	0	0	1	0	0	1	Write Register for Initial Code Setting	Write Register for Initial Code Setting Selection A[7:0] ~ D[7:0]: Reserved Details refer to Application Notes of Initial Code Setting
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀		
0	1		B ₇	B ₆	B ₅	B ₄	B ₃	B ₂	B ₁	B ₀		
0	1		C ₇	C ₆	C ₅	C ₄	C ₃	C ₂	C ₁	C ₀		
0	1		D ₇	D ₆	D ₅	D ₄	D ₃	D ₂	D ₁	D ₀		
0	0	0A	0	0	0	0	1	0	1	0	Read Register for Initial Code Setting	Read Register for Initial Code Setting

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 13 of 35



Command Table

Command Table											Command	Description
R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0		
0	0	0C	0	0	0	0	1	1	0	0	Booster Soft start Control	Booster Enable with Phase 1, Phase 2 and Phase 3 for soft start current and duration setting.
0	1		1	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀		A[7:0] -> Soft start setting for Phase1 = 8Bh [POR]
0	1		1	B ₆	B ₅	B ₄	B ₃	B ₂	B ₁	B ₀		B[7:0] -> Soft start setting for Phase2 = 9Ch [POR]
0	1		1	C ₆	C ₅	C ₄	C ₃	C ₂	C ₁	C ₀		C[7:0] -> Soft start setting for Phase3 = 96h [POR]
0	1		0	0	D ₅	D ₄	D ₃	D ₂	D ₁	D ₀		D[7:0] -> Duration setting = 0Fh [POR]
Bit Description of each byte: A[6:0] / B[6:0] / C[6:0]:												
Bit[6:4]		Driving Strength Selection										
000		1(Weakest)										
001		2										
010		3										
011		4										
100		5										
101		6										
110		7										
111		8(Strongest)										
Bit[3:0]		Min Off Time Setting of GDR [Time unit]										
0000 ~ 0011		NA										
0100		2.6										
0101		3.2										
0110		3.9										
0111		4.6										
1000		5.4										
1001		6.3										
1010		7.3										
1011		8.4										
1100		9.8										
1101		11.5										
1110		13.8										
1111		16.5										
D[5:0]: duration setting of phase D[5:4]: duration setting of phase 3 D[3:2]: duration setting of phase 2 D[1:0]: duration setting of phase 1												
Bit[1:0]		Duration of Phase [Approximation]										
00		10ms										
01		20ms										
10		30ms										
11		40ms										

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 14 of 35



Command Table

Command Table											Command	Description								
R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0										
0	0	10	0	0	0	1	0	0	0	0	Deep Sleep mode	Deep Sleep mode Control: <table><tr><td>A[1:0] :</td><td>Description</td></tr><tr><td>00</td><td>Normal Mode [POR]</td></tr><tr><td>01</td><td>Enter Deep Sleep Mode 1</td></tr><tr><td>11</td><td>Enter Deep Sleep Mode 2</td></tr></table> After this command initiated, the chip will enter Deep Sleep Mode, BUSY pad will keep output high. Remark: To Exit Deep Sleep mode, User required to send HWRESET to the driver	A[1:0] :	Description	00	Normal Mode [POR]	01	Enter Deep Sleep Mode 1	11	Enter Deep Sleep Mode 2
A[1:0] :	Description																			
00	Normal Mode [POR]																			
01	Enter Deep Sleep Mode 1																			
11	Enter Deep Sleep Mode 2																			
0	1		0	0	0	0	0	0	A ₁	A ₀										
0	0	11	0	0	0	1	0	0	0	1	Data Entry mode setting	Define data entry sequence A[2:0] = 011 [POR] A [1:0] = ID[1:0] Address automatic increment / decrement setting The setting of incrementing or decrementing of the address counter can be made independently in each upper and lower bit of the address. 00 –Y decrement, X decrement, 01 –Y decrement, X increment, 10 –Y increment, X decrement, 11 –Y increment, X increment [POR] A[2] = AM Set the direction in which the address counter is updated automatically after data are written to the RAM. AM= 0, the address counter is updated in the X direction. [POR] AM = 1, the address counter is updated in the Y direction.								
0	1		0	0	0	0	0	A ₂	A ₁	A ₀										
0	0	12	0	0	0	1	0	0	1	0	SW RESET	It resets the commands and parameters to their S/W Reset default values except R10h-Deep Sleep Mode During operation, BUSY pad will output high. Note: RAM are unaffected by this command.								

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 15 of 35



Command Table

R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0	Command	Description														
0	0	14	0	0	0	1	0	1	0	0	HV Ready Detection	HV ready detection A[7:0] = 00h [POR] The command required CLKEN=1 and ANALOGEN=1. Refer to Register 0x22 for detail. After this command initiated, HV Ready detection starts. BUSY pad will output high during detection. The detection result can be read from the Status Bit Read (Command 0x2F).														
0	1		0	A ₆	A ₅	A ₄	0	A ₂	A ₁	A ₀		A[6:4]=n for cool down duration: 10ms x (n+1) A[2:0]=m for number of Cool Down Loop to detect. The max HV ready duration is 10ms x (n+1) x (m) HV ready detection will be trigger after each cool down time. The detection will be completed when HV is ready. For 1 shot HV ready detection, A[7:0] can be set as 00h.														
0	0	15	0	0	0	1	0	1	0	1	VCI Detection	VCI Detection A[2:0] = 100 [POR] , Detect level at 2.3V A[2:0] : VCI level Detect <table><tr><th>A[2:0]</th><th>VCI level</th></tr><tr><td>011</td><td>2.2V</td></tr><tr><td>100</td><td>2.3V</td></tr><tr><td>101</td><td>2.4V</td></tr><tr><td>110</td><td>2.5V</td></tr><tr><td>111</td><td>2.6V</td></tr><tr><td>Other</td><td>NA</td></tr></table> The command required CLKEN=1 and ANALOGEN=1 Refer to Register 0x22 for detail. After this command initiated, VCI detection starts. BUSY pad will output high during detection. The detection result can be read from the Status Bit Read (Command 0x2F).	A[2:0]	VCI level	011	2.2V	100	2.3V	101	2.4V	110	2.5V	111	2.6V	Other	NA
A[2:0]	VCI level																									
011	2.2V																									
100	2.3V																									
101	2.4V																									
110	2.5V																									
111	2.6V																									
Other	NA																									
0	1		0	0	0	0	0	A ₂	A ₁	A ₀																
0	0	18	0	0	0	1	1	0	0	0	Temperature Sensor Control	Temperature Sensor Selection A[7:0] = 48h [POR], external temperature sensor A[7:0] = 80h Internal temperature sensor														
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																
0	0	1A	0	0	0	1	1	0	1	0	Temperature Sensor Control (Write to temperature register)	Write to temperature register. A[7:0] = 7Fh [POR]														
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																
0	0	1B	0	0	0	1	1	0	1	1	Temperature Sensor Control (Read from temperature register)	Read from temperature register.														
1	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 16 of 35



Command Table

Command Table												
R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0	Command	Description
0	0	1C	0	0	0	1	1	1	0	0	Temperature Sensor Control (Write Command to External temperature sensor)	Write Command to External temperature sensor.
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀		A[7:0] = 00h [POR],
0	1		B ₇	B ₆	B ₅	B ₄	B ₃	B ₂	B ₁	B ₀		B[7:0] = 00h [POR],
0	1		C ₇	C ₆	C ₅	C ₄	C ₃	C ₂	C ₁	C ₀		C[7:0] = 00h [POR],
												A[7:6]
											A[7:6]	Select no of byte to be sent
											00	Address + pointer
											01	Address + pointer + 1st parameter
											10	Address + pointer + 1st parameter + 2nd pointer
											11	Address
											A[5:0] – Pointer Setting	
											B[7:0] – 1 st parameter	
											C[7:0] – 2 nd parameter	
											The command required CLKEN=1.	
											Refer to Register 0x22 for detail.	
											After this command initiated, Write Command to external temperature sensor starts. BUSY pad will output high during operation.	
0	0	20	0	0	1	0	0	0	0	0	Master Activation	Activate Display Update Sequence
											The Display Update Sequence Option is located at R22h.	
											BUSY pad will output high during operation. User should not interrupt this operation to avoid corruption of panel images.	
0	0	21	0	0	1	0	0	0	0	1	Display Update Control 1	RAM content option for Display Update
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀		A[7:0] = 00h [POR]
0	1		B ₇	0	0	0	0	0	0	0		B[7:0] = 00h [POR]
											A[7:4] Red RAM option	
											0000	Normal
											0100	Bypass RAM content as 0
											1000	Inverse RAM content
											A[3:0] BW RAM option	
											0000	Normal
											0100	Bypass RAM content as 0
											1000	Inverse RAM content

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 17 of 35



Command Table																																															
R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0	Command	Description																																			
0	0	22	0	0	1	0	0	0	1	0	Display Update Control 2	Display Update Sequence Option: Enable the stage for Master Activation A[7:0]= FFh (POR)																																			
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀		<table><tr><th>Operating sequence</th><th>Parameter (in Hex)</th></tr><tr><td>Enable clock signal</td><td>80</td></tr><tr><td>Disable clock signal</td><td>01</td></tr><tr><td> </td><td> </td></tr><tr><td>Enable clock signal → Enable Analog</td><td>C0</td></tr><tr><td>Disable Analog → Disable clock signal</td><td>03</td></tr><tr><td> </td><td> </td></tr><tr><td>Enable clock signal → Load LUT with DISPLAY Mode 1 → Disable clock signal</td><td>91</td></tr><tr><td>Enable clock signal → Load LUT with DISPLAY Mode 2 → Disable clock signal</td><td>99</td></tr><tr><td> </td><td> </td></tr><tr><td>Enable clock signal → Load temperature value → Load LUT with DISPLAY Mode 1 → Disable clock signal</td><td>B1</td></tr><tr><td>Enable clock signal → Load temperature value → Load LUT with DISPLAY Mode 2 → Disable clock signal</td><td>B9</td></tr><tr><td> </td><td> </td></tr><tr><td>Enable clock signal → Enable Analog → Display with DISPLAY Mode 1 → Disable Analog → Disable OSC</td><td>C7</td></tr><tr><td>Enable clock signal → Enable Analog → Display with DISPLAY Mode 2 → Disable Analog → Disable OSC</td><td>CF</td></tr><tr><td> </td><td> </td></tr><tr><td>Enable clock signal → Enable Analog → Load temperature value → DISPLAY with DISPLAY Mode 1 → Disable Analog → Disable OSC</td><td>F7</td></tr><tr><td>Enable clock signal → Enable Analog → Load temperature value → DISPLAY with DISPLAY Mode 2 → Disable Analog → Disable OSC</td><td>FF</td></tr></table>	Operating sequence	Parameter (in Hex)	Enable clock signal	80	Disable clock signal	01			Enable clock signal → Enable Analog	C0	Disable Analog → Disable clock signal	03			Enable clock signal → Load LUT with DISPLAY Mode 1 → Disable clock signal	91	Enable clock signal → Load LUT with DISPLAY Mode 2 → Disable clock signal	99			Enable clock signal → Load temperature value → Load LUT with DISPLAY Mode 1 → Disable clock signal	B1	Enable clock signal → Load temperature value → Load LUT with DISPLAY Mode 2 → Disable clock signal	B9			Enable clock signal → Enable Analog → Display with DISPLAY Mode 1 → Disable Analog → Disable OSC	C7	Enable clock signal → Enable Analog → Display with DISPLAY Mode 2 → Disable Analog → Disable OSC	CF			Enable clock signal → Enable Analog → Load temperature value → DISPLAY with DISPLAY Mode 1 → Disable Analog → Disable OSC	F7	Enable clock signal → Enable Analog → Load temperature value → DISPLAY with DISPLAY Mode 2 → Disable Analog → Disable OSC
Operating sequence	Parameter (in Hex)																																														
Enable clock signal	80																																														
Disable clock signal	01																																														
Enable clock signal → Enable Analog	C0																																														
Disable Analog → Disable clock signal	03																																														
Enable clock signal → Load LUT with DISPLAY Mode 1 → Disable clock signal	91																																														
Enable clock signal → Load LUT with DISPLAY Mode 2 → Disable clock signal	99																																														
Enable clock signal → Load temperature value → Load LUT with DISPLAY Mode 1 → Disable clock signal	B1																																														
Enable clock signal → Load temperature value → Load LUT with DISPLAY Mode 2 → Disable clock signal	B9																																														
Enable clock signal → Enable Analog → Display with DISPLAY Mode 1 → Disable Analog → Disable OSC	C7																																														
Enable clock signal → Enable Analog → Display with DISPLAY Mode 2 → Disable Analog → Disable OSC	CF																																														
Enable clock signal → Enable Analog → Load temperature value → DISPLAY with DISPLAY Mode 1 → Disable Analog → Disable OSC	F7																																														
Enable clock signal → Enable Analog → Load temperature value → DISPLAY with DISPLAY Mode 2 → Disable Analog → Disable OSC	FF																																														
0	0	24	0	0	1	0	0	1	0	0	Write RAM (Black White) / RAM 0x24	After this command, data entries will be written into the BW RAM until another command is written. Address pointers will advance accordingly For Write pixel: Content of Write RAM(BW) = 1 For Black pixel: Content of Write RAM(BW) = 0																																			

DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJYE420S08W0G01	Page 18 of 35



Command Table

R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0	Command	Description
0	0	26	0	0	1	0	0	1	1	0	Write RAM (RED) / RAM 0x26	After this command, data entries will be written into the RED RAM until another command is written. Address pointers will advance accordingly. For Red pixel: Content of Write RAM(RED) = 1 For non-Red pixel [Black or White]: Content of Write RAM(RED) = 0
0	0	27	0	0	1	0	0	1	1	1	Read RAM	After this command, data read on the MCU bus will fetch data from RAM. According to parameter of Register 41h to select reading RAM0x24/ RAM0x26, until another command is written. Address pointers will advance accordingly. The 1 st byte of data read is dummy data.
0	0	28	0	0	1	0	1	0	0	0	VCOM Sense	Enter VCOM sensing conditions and hold for duration defined in 29h before reading VCOM value. The sensed VCOM voltage is stored in register The command required CLKEN=1 and ANALOGEN=1 Refer to Register 0x22 for detail. BUSY pad will output high during operation.
0	0	29	0	0	1	0	1	0	0	1	VCOM Sense Duration	Stabling time between entering VCOM sensing mode and reading acquired. A[3:0] = 9h, duration = 10s. VCOM sense duration = (A[3:0]+1) sec
0	1		0	1	0	0	A ₃	A ₂	A ₁	A ₀		
0	0	2A	0	0	1	0	1	0	1	0	Program VCOM OTP	Program VCOM register into OTP The command required CLKEN=1. Refer to Register 0x22 for detail. BUSY pad will output high during operation.

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 19 of 35



Command Table

Command Table											Command	Description																																																																
0	0	2C	0	0	1	0	1	1	0	0	Write VCOM register	Write VCOM register from MCU interface A[7:0] = 00h [POR] <table><tr><td>A[7:0]</td><td>VCOM</td><td>A[7:0]</td><td>VCOM</td></tr><tr><td>08h</td><td>-0.2</td><td>44h</td><td>-1.7</td></tr><tr><td>0Ch</td><td>-0.3</td><td>48h</td><td>-1.8</td></tr><tr><td>10h</td><td>-0.4</td><td>4Ch</td><td>-1.9</td></tr><tr><td>14h</td><td>-0.5</td><td>50h</td><td>-2</td></tr><tr><td>18h</td><td>-0.6</td><td>54h</td><td>-2.1</td></tr><tr><td>1Ch</td><td>-0.7</td><td>58h</td><td>-2.2</td></tr><tr><td>20h</td><td>-0.8</td><td>5Ch</td><td>-2.3</td></tr><tr><td>24h</td><td>-0.9</td><td>60h</td><td>-2.4</td></tr><tr><td>28h</td><td>-1</td><td>64h</td><td>-2.5</td></tr><tr><td>2Ch</td><td>-1.1</td><td>68h</td><td>-2.6</td></tr><tr><td>30h</td><td>-1.2</td><td>6Ch</td><td>-2.7</td></tr><tr><td>34h</td><td>-1.3</td><td>70h</td><td>-2.8</td></tr><tr><td>38h</td><td>-1.4</td><td>74h</td><td>-2.9</td></tr><tr><td>3Ch</td><td>-1.5</td><td>78h</td><td>-3</td></tr><tr><td>40h</td><td>-1.6</td><td>Other</td><td>NA</td></tr></table>	A[7:0]	VCOM	A[7:0]	VCOM	08h	-0.2	44h	-1.7	0Ch	-0.3	48h	-1.8	10h	-0.4	4Ch	-1.9	14h	-0.5	50h	-2	18h	-0.6	54h	-2.1	1Ch	-0.7	58h	-2.2	20h	-0.8	5Ch	-2.3	24h	-0.9	60h	-2.4	28h	-1	64h	-2.5	2Ch	-1.1	68h	-2.6	30h	-1.2	6Ch	-2.7	34h	-1.3	70h	-2.8	38h	-1.4	74h	-2.9	3Ch	-1.5	78h	-3	40h	-1.6	Other	NA
A[7:0]	VCOM	A[7:0]	VCOM																																																																									
08h	-0.2	44h	-1.7																																																																									
0Ch	-0.3	48h	-1.8																																																																									
10h	-0.4	4Ch	-1.9																																																																									
14h	-0.5	50h	-2																																																																									
18h	-0.6	54h	-2.1																																																																									
1Ch	-0.7	58h	-2.2																																																																									
20h	-0.8	5Ch	-2.3																																																																									
24h	-0.9	60h	-2.4																																																																									
28h	-1	64h	-2.5																																																																									
2Ch	-1.1	68h	-2.6																																																																									
30h	-1.2	6Ch	-2.7																																																																									
34h	-1.3	70h	-2.8																																																																									
38h	-1.4	74h	-2.9																																																																									
3Ch	-1.5	78h	-3																																																																									
40h	-1.6	Other	NA																																																																									
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																																																																		

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 20 of 35



Command Table												
R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0	Command	Description
0	0	2F	0	0	1	0	1	1	1	1	Status Bit Read	Read IC status Bit [POR 0x01] A[5]: HV Ready Detection flag [POR=0] 0: Ready 1: Not Ready A[4]: VCI Detection flag [POR=0] 0: Normal 1: VCI lower than the Detect level A[3]: [POR=0] A[2]: Busy flag [POR=0] 0: Normal 1: BUSY A[1:0]: Chip ID [POR=01] Remark: A[5] and A[4] status are not valid after RESET, they need to be initiated by command 0x14 and command 0x15 respectively.
1	1		0	0	A ₅	A ₄	0	0	A ₁	A ₀		
0	0	30	0	0	1	1	0	0	0	0	Program WS OTP	Program OTP of Waveform Setting The contents should be written into RAM before sending this command. The command required CLKEN=1. Refer to Register 0x22 for detail. BUSY pad will output high during operation.
0	0	31	0	0	1	1	0	0	0	1	Load WS OTP	Load OTP of Waveform Setting The command required CLKEN=1. Refer to Register 0x22 for detail. BUSY pad will output high during operation.
0	0	32	0	0	1	1	0	0	1	0	Write LUT register	Write LUT register from MCU interface [227 bytes], which contains the content of VS[nX-LUTm], TP[nX], RP[n], SR[nXY], FR and XON[nXY] Refer to Session 6.7 WAVEFORM SETTING
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀		
0	1		B ₇	B ₆	B ₅	B ₄	B ₃	B ₂	B ₁	B ₀		
0	1		:	:	:	:	:	:	:	:		
0	1		.	..	.	.	.	.	.	.		
0	0	34	0	0	1	1	0	1	0	0	CRC calculation	CRC calculation command For details, please refer to SSD1683 application note. BUSY pad will output high during operation.
0	0	35	0	0	1	1	0	1	0	1	CRC Status Read	CRC Status Read A[15:0] is the CRC read out value
1	1		A ₁₅	A ₁₄	A ₁₃	A ₁₂	A ₁₁	A ₁₀	A ₉	A ₈		
1	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀		

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 21 of 35



Command Table

R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0	Command	Description
0	0	36	0	0	1	1	0	1	1	0	Program OTP selection	Program OTP Selection according to the OTP Selection Control [R37h and R38h] The command required CLKEN=1. Refer to Register 0x22 for detail. BUSY pad will output high during operation.
0	0	37	0	0	1	1	0	1	1	1	Write Register for Display Option	Write Register for Display Option A[7] Spare VCOM OTP selection 0: Default [POR] 1: Spare B[7:0] Display Mode for WS[7:0] C[7:0] Display Mode for WS[15:8] D[7:0] Display Mode for WS[23:16] 0: Display Mode 1 1: Display Mode 2 F[6]: Ping-Pong for Display Mode 2 0: RAM Ping-Pong disable [POR] 1: RAM Ping-Pong enable G[7:0]~J[7:0] module ID /waveform version. Remarks: 1) A[7:0]~J[7:0] can be stored in OTP 2) RAM Ping-Pong function is not support for Display Mode 1
0	1		A ₇	0	0	0	0	0	0	0		
0	1		B ₇	B ₆	B ₅	B ₄	B ₃	B ₂	B ₁	B ₀		
0	1		C ₇	C ₆	C ₅	C ₄	C ₃	C ₂	C ₁	C ₀		
0	1		D ₇	D ₆	D ₅	D ₄	D ₃	D ₂	D ₁	D ₀		
0	1		E ₇	E ₆	E ₅	E ₄	E ₃	E ₂	E ₁	E ₀		
0	1		0	F ₆	0	0	F ₃	F ₂	F ₁	F ₀		
0	1		G ₇	G ₆	G ₅	G ₄	G ₃	G ₂	G ₁	G ₀		
0	1		H ₇	H ₆	H ₅	H ₄	H ₃	H ₂	H ₁	H ₀		
0	1		I ₇	I ₆	I ₅	I ₄	I ₃	I ₂	I ₁	I ₀		
0	1		J ₇	J ₆	J ₅	J ₄	J ₃	J ₂	J ₁	J ₀		
0	0	38	0	0	1	1	1	0	0	0	Write Register for User ID	Write Register for User ID A[7:0]~J[7:0]: UserID [10 bytes] Remarks: A[7:0]~J[7:0] can be stored in OTP
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀		
0	1		B ₇	B ₆	B ₅	B ₄	B ₃	B ₂	B ₁	B ₀		
0	1		C ₇	C ₆	C ₅	C ₄	C ₃	C ₂	C ₁	C ₀		
0	1		D ₇	D ₆	D ₅	D ₄	D ₃	D ₂	D ₁	D ₀		
0	1		E ₇	E ₆	E ₅	E ₄	E ₃	E ₂	E ₁	E ₀		
0	1		F ₇	F ₆	F ₅	F ₄	F ₃	F ₂	F ₁	F ₀		
0	1		G ₇	G ₆	G ₅	G ₄	G ₃	G ₂	G ₁	G ₀		
0	1		H ₇	H ₆	H ₅	H ₄	H ₃	H ₂	H ₁	H ₀		
0	1		I ₇	I ₆	I ₅	I ₄	I ₃	I ₂	I ₁	I ₀		
0	1		J ₇	J ₆	J ₅	J ₄	J ₃	J ₂	J ₁	J ₀		
0	0	39	0	0	1	1	1	0	0	1	OTP program mode	OTP program mode A[1:0] = 00: Normal Mode [POR] A[1:0] = 11: Internal generated OTP programming voltage Remark: User is required to EXACTLY follow the reference code sequences
0	1		0	0	0	0	0	0	A ₁	A ₀		

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 22 of 35



Command Table

R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0	Command	Description
0	0	3C	0	0	1	1	1	1	0	0	Border Waveform Control	Select border waveform for VBD A[7:0] = C0h [POR], set VBD as HiZ.
0	1		A ₇	A ₆	A ₅	A ₄	0	0	A ₁	A ₀		A [7:6] :Select VBD option
												A[7:6] Select VBD as
												00 GS Transition, Defined in A[2] and A[1:0]
												01 Fix Level, Defined in A[5:4]
												10 VCOM
												11[POR] HiZ
												A [5:4] Fix Level Setting for VBD
												A[5:4] VBD level
												00 VSS
												01 VSH1
												10 VSL
												11 VSH2
												A [1:0] GS Transition setting for VBD VBD Level Selection: 00b: VCOM ; 01b: VSH1; 10b: VSL; 11b: VSH2
												A[1:0] VBD Transition
												00 LUT0
												01 LUT1
												10 LUT2
												11 LUT3
0	0	3F	0	0	1	1	1	1	1	1	End Option (EOPT)	Option for LUT end Set this byte to 22h
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀		
0	0	41	0	1	0	0	0	0	0	1	Read RAM Option	Read RAM Option A[0]= 0 [POR] 0 : Read RAM corresponding to RAM0x24 1 : Read RAM corresponding to RAM0x26
0	1		0	0	0	0	0	0	0	A ₀		
0	0	44	0	1	0	0	0	1	0	0	Set RAM X - address Start / End position	Specify the start/end positions of the window address in the X direction by an address unit for RAM A[5:0]: XSA[5:0], XStart, POR = 00h B[5:0]: XEA[5:0], XEnd, POR = 31h
0	1		0	0	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀		
0	1		0	0	B ₅	B ₄	B ₃	B ₂	B ₁	B ₀		
0	0	45	0	1	0	0	0	1	0	1	Set Ram Y- address Start / End position	Specify the start/end positions of the window address in the Y direction by an address unit for RAM A[8:0]: YSA[8:0], YStart, POR = 000h B[8:0]: YEA[8:0], YEnd, POR = 12Bh
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀		
0	1		0	0	0	0	0	0	0	A ₈		
0	1		B ₇	B ₆	B ₅	B ₄	B ₃	B ₂	B ₁	B ₀		
0	1		0	0	0	0	0	0	0	B ₈		
0	0	46	0	1	0	0	0	1	1	0	Auto Write RED RAM for Regular Pattern	Auto Write RED RAM for Regular Pattern A[7:0] = 00h [POR]
0	1		A ₇	A ₆	A ₅	A ₄	0	A ₂	A ₁	A ₀		

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 23 of 35



Command Table

Command Table											Command	Description																																								
												A[7]: The 1st step value, POR = 0 A[6:4]: Step Height, POR= 000 Step of alter RAM in Y-direction according to Gate <table><tr><td>A[6:4]</td><td>Height</td><td>A[6:4]</td><td>Height</td></tr><tr><td>000</td><td>8</td><td>100</td><td>128</td></tr><tr><td>001</td><td>16</td><td>101</td><td>256</td></tr><tr><td>010</td><td>32</td><td>110</td><td>300</td></tr><tr><td>011</td><td>64</td><td>111</td><td>NA</td></tr></table> A[2:0]: Step Width, POR= 000 Step of alter RAM in X-direction according to Source <table><tr><td>A[2:0]</td><td>Width</td><td>A[2:0]</td><td>Width</td></tr><tr><td>000</td><td>8</td><td>100</td><td>128</td></tr><tr><td>001</td><td>16</td><td>101</td><td>256</td></tr><tr><td>010</td><td>32</td><td>110</td><td>400</td></tr><tr><td>011</td><td>64</td><td>111</td><td>NA</td></tr></table> BUSY pad will output high during operation.	A[6:4]	Height	A[6:4]	Height	000	8	100	128	001	16	101	256	010	32	110	300	011	64	111	NA	A[2:0]	Width	A[2:0]	Width	000	8	100	128	001	16	101	256	010	32	110	400	011	64	111	NA
A[6:4]	Height	A[6:4]	Height																																																	
000	8	100	128																																																	
001	16	101	256																																																	
010	32	110	300																																																	
011	64	111	NA																																																	
A[2:0]	Width	A[2:0]	Width																																																	
000	8	100	128																																																	
001	16	101	256																																																	
010	32	110	400																																																	
011	64	111	NA																																																	
0	0	47	0	1	0	0	0	1	1	1	Auto Write B/W RAM for Regular Pattern	Auto Write B/W RAM for Regular Pattern A[7:0] = 00h [POR] A[7]: The 1st step value, POR = 0 A[6:4]: Step Height, POR= 000 Step of alter RAM in Y-direction according to Gate <table><tr><td>A[6:4]</td><td>Height</td><td>A[6:4]</td><td>Height</td></tr><tr><td>000</td><td>8</td><td>100</td><td>128</td></tr><tr><td>001</td><td>16</td><td>101</td><td>256</td></tr><tr><td>010</td><td>32</td><td>110</td><td>300</td></tr><tr><td>011</td><td>64</td><td>111</td><td>NA</td></tr></table> A[2:0]: Step Width, POR= 000 Step of alter RAM in X-direction according to Source <table><tr><td>A[2:0]</td><td>Width</td><td>A[2:0]</td><td>Width</td></tr><tr><td>000</td><td>8</td><td>100</td><td>128</td></tr><tr><td>001</td><td>16</td><td>101</td><td>256</td></tr><tr><td>010</td><td>32</td><td>110</td><td>400</td></tr><tr><td>011</td><td>64</td><td>111</td><td>NA</td></tr></table> During operation, BUSY pad will output high.	A[6:4]	Height	A[6:4]	Height	000	8	100	128	001	16	101	256	010	32	110	300	011	64	111	NA	A[2:0]	Width	A[2:0]	Width	000	8	100	128	001	16	101	256	010	32	110	400	011	64	111	NA
A[6:4]	Height	A[6:4]	Height																																																	
000	8	100	128																																																	
001	16	101	256																																																	
010	32	110	300																																																	
011	64	111	NA																																																	
A[2:0]	Width	A[2:0]	Width																																																	
000	8	100	128																																																	
001	16	101	256																																																	
010	32	110	400																																																	
011	64	111	NA																																																	
0	0	4E	0	1	0	0	1	1	1	0	Set RAM X address counter	Make initial settings for the RAM X address in the address counter (AC)																																								
0	1		0	0	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀																																										

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 24 of 35



Command Table

R/W#	D/C#	Hex	D7	D6	D5	D4	D3	D2	D1	D0	Command	Description
												A[5:0]: 00h [POR].
0	0	4F	0	1	0	0	1	1	1	1	Set RAM Y address counter	Make initial settings for the RAM Y address in the address counter (AC) A[8:0]: 000h [POR].
0	1		A ₇	A ₆	A ₅	A ₄	A ₃	A ₂	A ₁	A ₀		
0	1		0	0	0	0	0	0	0	A ₈		
0	0	7F	0	1	1	1	1	1	1	1	NOP	This command is an empty command; it does not have any effect on the display module. However it can be used to terminate Frame Memory Write or Read Commands.

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 25 of 35



8. Optical Specifications

Measurements are made with that the illumination is under an angle of 45 degree, the detection is perpendicular unless otherwise specified

Symbol	Parameter	Conditions	Min	Typ.	Max	Units	Notes
R	White Reflectivity	White	30	35	-	%	8-1
CR	Contrast Ratio	Indoor	8:1		-		8-2
GN	2Grey Level	-		$DS+(WS-DS)*n(m-1)$			8-3
T update	Image update time	at 25 ℃		3	-	sec	
Life		Topr		1000000times or 5years			

Notes: 8-1. Luminance meter: Eye-One Pro Spectrophotometer.

8-2. CR=Surface Reflectance with all white pixel/Surface Reflectance with all black pixels.

8-3. WS: White state, DS: Dark state

9. Handling, Safety and Environment Requirements

Warning

The display glass may break when it is dropped or bumped on a hard surface. Handle with care. Should the display break, do not touch the electrophoretic material. In case of contact with electrophoretic material, wash with water and soap.

Caution

The display module should not be exposed to harmful gases, such as acid and alkali gases, which corrode electronic components. Disassembling the display module.

Disassembling the display module can cause permanent damage and invalidates the warranty agreements.

Observe general precautions that are common to handling delicate electronic components. The glass can break and front surfaces can easily be damaged. Moreover the display is sensitive to static electricity and other rough environmental conditions.

Data sheet status	
Product specification	This data sheet contains final product specifications.
Limiting values	
Limiting values given are in accordance with the Absolute Maximum Rating System (IEC 134). Stress above one or more of the limiting values may cause permanent damage to the device. These are stress ratings only and operation of the device at these or at any other conditions above those given in the Characteristics sections of the specification is not implied. Exposure to limiting values for extended periods may affect device reliability.	
Application information	
Where application information is given, it is advisory and does not form part of the specification.	

DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJYE420S08W0G01	Page 26 of 35



10. Reliability test


NO	Test items	Test condition
1	Low-Temperature Storage	T = -25 °C, 240 h Test in white pattern
2	High-Temperature Storage	T=60° C, RH=35%, 240h Test in white pattern
3	High-Temperature Operation	T=40° C, RH=35%, 240h
4	Low-Temperature Operation	0° C, 240h
5	High-Temperature, High-Humidity Operation	T=40° C, RH=80%, 240h
6	High Temperature, High Humidity Storage	T=50° C, RH=90%, 240h Test in white pattern
7	Temperature Cycle	1 cycle:[-25° C 30min]→[+60° C 30 min] : 50 cycles Test in white pattern
8	UV exposure Resistance	765W/m ² for 168hrs,40 °C Test in white pattern
9	ESD Gun	Air+/-15KV;Contact+/-8KV (Test finished product shell, not display only) Air+/-8KV;Contact+/-6KV (Naked EPD display, no including IC and FPC area) Air+/-4KV;Contact+/-2KV (Naked EPD display, including IC and FPC area)

Note: Put in normal temperature for 1hour after test finished, display performance is ok.

DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJYE420S08W0G01	Page 27 of 35



11. Typical Application Circuit with SPI Interface



DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD


ZJYE420S08W0G01

Page 28 of 35



12. Typical Operating Sequence

12.1 Normal Operation Flow



DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJYE420S08W0G01	Page 29 of 35



12.2 Normal Operation Reference Program Code

ACTION	VALUE/DATA	COMMENT
POWER ON		
delay	10ms	
PIN CONFIG		
RESE#	low	Hardware reset
delay	200us	
RESE#	high	
delay	200us	
Read busy pin		Wait for busy low
Command 0x12		Software reset
Read busy pin		Wait for busy low
Command 0x01	Data 0x2b 0x01 0x00	Set display size and driver output control
Command 0x11	Data 0x01	Ram data entry mode
Command 0x44	Data 0x00 0x31	Set Ram X address
Command 0x45	Data 0x2b 0x01 0x00 0x00	Set Ram Y address
Command 0x3C	Data 0x01	Set border
LOAD IMAGE AND UPDATE		
Command 0x4E	Data 0x00	Set Ram X address counter
Command 0x4F	Data 0x2b 0x00	Set Ram Y address counter
Command 0x24	Data 0xXX... , 0xXX	Write B/W image data into to Register 0x24 RAM
Command 0x4E	Data 0x00	Set Ram X address counter
Command 0x4F	Data 0x2b 0x00	Set Ram Y address counter
Command 0x26	Data 0xXX... , 0xXX	Write Red image data into Register 0x26 RAM
Command 0x20		
Read busy pin		
Command 0x10	Data 0X01	Enter deep sleep mode
POWER OFF		

DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJYE420S08W0G01	Page 30 of 35




13. Part Number Definition

TBD

14. Inspection method and condition

14. 1 Inspection condition

Item	Condition
Illuminance	800~1500 lux
Temperature	22℃ ± 3℃
Humidity	55 ± 10 %RH
Distance	≥30cm
Angle	Vertical fore and aft 45
Inspection method	By eyes




14. 2 Zone definition

A Zone: Active area

B Zone: Border zone

C Zone: From B zone edge to panel edge





DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJYE420S08W0G01	Page 31 of 35





14. 3 General inspection standards for products

14.3.1 Appearance inspection standard



Inspection item	Figure	A zone inspection standard	B/C zone	Inspection method	MAJ/ MIN
Spot defects	Diameter $D=(L+W)/2$ (L-length, W-width) Measuring method shown in the figure below  $D=(L+W)/2$ The distance between the two spots should not be less than 10mm	7.5"-13.3"Module (Not include 7.5") : $D>1\text{mm}$ N=0 $0.5<D\leq 0.8$ $N\leq 4$ $D\leq 0.5$ Ignore $0.8<D\leq 1$ $N\leq 2$ 4.2"-7.5"Module (Not include 4.2") : $D>0.5$ N=0 $0.4<D\leq 0.5$ $N\leq 2$ $D\leq 0.25$ Ignore $0.25<D\leq 0.4$ $N\leq 4$ Module below 4.2": $D>0.5$ N=0 $0.4<D\leq 0.5$ $N\leq 1$ $D\leq 0.25$ Ignore $0.25<D\leq 0.4$ $N\leq 4$ $0.1\text{mm}<D\leq 0.25$ $N\leq 3/\text{cm}^2$	Foreign matter D≤1mm Pass	Check by eyes Film gauge	MIN

Inspection item	Figure	A zone inspection standard	B/C zone	Inspection method	MAJ/ MIN
Line defects	L-Length, W-Width, $(W/L)<1/4$ Judged by line, $(W/L)\geq 1/4$ Judged by dot  The distance between the two lines should not be less than 5mm	7.5"-13.3"Module (Not include 7.5") : $L>10\text{mm}, N=0$ $W>0.8\text{mm}, N=0$ $5\text{mm}\leq L\leq 10\text{mm}, 0.5\text{mm}\leq W\leq 0.8\text{mm}$ $N\leq 2$ $L\leq 5\text{mm}, W\leq 0.5\text{mm}$ Ignore 4.2"-7.5"Module (Not include 4.2") : $L>8\text{mm}, N=0$ $W>0.2\text{mm}, N=0$ $2\text{mm}\leq L\leq 8\text{mm}, 0.1\text{mm}\leq W\leq 0.2\text{mm}$ $N\leq 4$ $L\leq 2\text{mm}, W\leq 0.1\text{mm}$ Ignore Module below 4.2": $L>5\text{mm}, N=0$ $W>0.2\text{mm}, N=0$ $2\text{mm}\leq L\leq 5\text{mm}, 0.1\text{mm}\leq W\leq 0.2\text{mm}$ $N\leq 4$ $L\leq 2\text{mm}, W\leq 0.1\text{mm}$ Ignore	Ignore	Check by eyes Film gauge	MIN

Inspection item	Figure	Inspection standard	Inspection method	MAJ/ MIN
Panel chipping and crack defects	X the length, Y the width, Z the chipping height, T the thickness of the panel  崩角 崩边	Chipping at the edge: Module over 7.5" (Include 7.5") : $X\leq 6\text{mm}, Y\leq 1\text{mm}$ $Z\leq T$ $N=3$ Allowed Module below 7.5" (Not include 7.5") : $X\leq 3\text{mm}, Y\leq 1\text{mm}$ $Z\leq T$ $N=3$ Allowed Chipping on the corner: IC side $X\leq 2\text{mm}$ $Y\leq 2\text{mm}$, Non-IC side $X\leq 1\text{mm}$ $Y\leq 1\text{mm}$. Allowed Note: Chipping should not damage the edge wiring. If it does not affect the display, allowed	Check by eyes, Film gauge	MIN
Crack	 玻璃裂纹	Crack at any zone of glass , Not allowed	Check by eyes, Film gauge	MIN
Burr edge		No exceed the positive and negative deviation of the outline dimensions $X+Y\leq 0.2\text{mm}$ Allowed	Calliper	MIN
Curl of panel	 H Curl height	Curl height $H\leq$ Total panel length 1% Allowed	Check by eyes	MIN

DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJYE420S08W0G01	Page 32 of 35



Inspection item		Figure	Inspection standard	Inspection method	MAJ / MIN
PS defect	Water proof film		1. Waterproof film damage, wrinkled, open edge, not allowed 2. Exceeding the edge of module(according to the lamination drawing) Not allowed 3. Edge warped exceeds height of technical file, not allowed	Check by eyes	MIN
RTV defect	Adhesive effect		Adhesive height exceeds the display surface, not allowed 1. Overflow, exceeds the panel side edge, affecting the size, not allowed 2. No adhesive at panel edge $\leq 1\text{mm}$, no exposure of wiring, allowed 3. No adhesive at edge and corner $1*1\text{mm}$, no exposure of wiring, allowed Protection adhesive, coverage width within $W \leq 1.5\text{mm}$, no break of adhesive, allowed	Check by eyes	MIN
	Adhesive re-fill		Dispensing is uniform, without obvious concave and breaking, bubbling and swell, not higher than the upper surface of the PS, and the diameter of the adhesive re-filling is not more than 8mm, allowed	Check by eyes	MIN
EC defect	Adhesive bubble		1. Effective edge sealing area of hot melt products $\geq 1/2$ edge sealing area; 2. Bubble $a+b \geq 1/2$ effective width, $N \leq 3$, spacing $\geq 5\text{mm}$, allowed No exposure of wiring, allowed	Check by eyes	MIN

Inspection item		Figure	Inspection standard	Inspection method	MAJ/ MIN
EC defect	Adhesive effect		1. Overflow, exceeds the panel side edge, affecting the size, not allowed 2. No adhesive at panel edge $\leq 1\text{mm}$, no exposure of wiring, allowed 3. No adhesive at edge and corner $1*1\text{mm}$, no exposure of wiring, allowed 4. Adhesive height exceeds the display surface, not allowed	Visual, caliper	MIN
Silver dot adhesive defect	Silver dot adhesive		1. Single silver dot dispensing amount $\geq 1\text{mm}$, allowed 2. One of the double silver dot dispensing amount is $\geq 1\text{mm}$ and the other has adhesive (no reference to 1mm) Allowed	Visual	MIN
			Silver dot dispensing residue on the panel $\leq 0.2\text{mm}$, allowed	Film gauge	MIN
FPC defect	FPC wiring		FPC, TCP damage / gold finger peroxidation, adhesive residue, not allowed	Visual	MIJ
	FPC golden finger		The height of burr edge of TCP punching surface $\geq 0.4\text{mm}$, not allowed	Caliper	MIN
	FPC damage/cr ease		Damage and breaking, not allowed Crease does not affect the electrical performance display, allowed	Check by eyes	MIN

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 33 of 35



Inspection item		Figure	Inspection standard	Inspection method	MAJ/ MIN
Protective film defect	Protective film	Scratch and crease on the surface but no affect to protection function, allowed		Check by eyes	MIN
		Adhesive at edge $L \leq 5\text{mm}$, $W \leq 0.5\text{mm}$, $N=2$, no entering into viewing area		Check by eyes	MIN
Stain defect	Stain	If stain can be normally wiped clean by $> 99\%$ alcohol, allowed		Visual	MIN
Pull tab defect	Pull tab	The position and direction meet the document requirements, and ensure that the protective film can be pulled off.		Check by eyes/ Manual pulling	MIN
Shading tape defect	Shading tape	Tilt $\leq 10^\circ$, flat without warping, completely covering the IC.		Check by eyes/ Film gauge	MIN
Stiffener	Stiffener	Flat without warping, Exceeding the left and right edges of the FPC is not allowed. Left and right can be less than 0.5mm from FPC edge		Check by eyes	MIN
Label	Label/ Spraying code	The content meets the requirements of the work sheet. The attaching position meets the requirements of the technical documents.		Check by eyes	MIN

DATE JUL.29.2022	Version	1.5	TECHNICAL SPECIFICATION
EPD		ZJYE420S08W0G01	Page 34 of 35



15.Packaging

CUSTOMER'S APPROVED:

DATE: 2020.09.25

PAGE: 1/1

PRODUCT PART NO.: YMS400300-042




PACKING TYPE: BY PET TRAY(TPET400300-042A)

PACKLING ORDER:

1) Putting 9 pcs Modules on each PET tray. And cover a dedicated EPE film.

2) Putting 9 pcs PET trays together with 1 empty tray on the top of PET tray. Insert in the ESD bag, add desiccant in the ESD bag.




3) the tray together with rubber band



4) Putting in the inner small carton

5) Putting 5 small cartons into one outcarton

6) Packing finished



Note: 9 pcs in a tray, 9 trays in a inner carton, 5 inner cartons in a out carton, so $9 \times 9 \times 5 = 405$ pcs/Outcarton

Dimension (Small carton): 385*325*87mm

Dimension (Out carton): 394*344*470mm

Drw:

Chk:

Apv:

DATE JUL.29.2022

Version

1.5

TECHNICAL SPECIFICATION

EPD

ZJYE420S08W0G01

Page 35 of 35