Optex LX-402 Outdoor PIR

Wide-angle (120°) outdoor passive infrared detector · IP54

STOCK CODE

07LX402C

Weatherproof outdoor PIR for yards, driveways and fence lines — great for triggering lights, sirens or cameras.



Wall-mounted outdoors

12×15 m	120°	IP54	12 V
coverage	wide angle	weatherproof	DC powered

WHY CUSTOMERS CHOOSE IT

- **Double conductive shielding** — ignores sunlight up to 50,000 lux
- **Multi-level or Pet Alley** detection pattern, switchable
- 3-step sensitivity + day/night mode
- Masking strips to blank out unwanted areas
- Easy wiring with 2 entry holes + weather sponge

BEST FOR

- ✔ Front & back yards, along fences
- ✔ Driveways, parking & delivery doors
- ✔ Switching on lights, sirens or CCTV
- ✔ Homes with small pets (Pet Alley mode)
- ✔ Wall mounting indoors or outdoors

NOT FOR

- ✖ Long narrow corridors — sell the LX-802N (24 m)
- ✖ Aiming at roads, trees or bushes that move
- ✖ Unprotected spots facing direct rain/sun all day

COVERAGE

Area	**12 m × 15 m (120°)**
Zones	**40 multi-level / 18 pet alley**
Mount height	**2.5 m**
Walk speed	**0.3–1.0 m/s**

KEY SPECS

Power input	**10.8 – 13.2 VDC**
Current draw	**25 mA max**
Alarm output	**N.C./N.O. relay, 28 VDC 0.2 A**
Tamper	**Opens when cover removed**
Operating temp	**−20 to +50 °C · 95% RH**
Size / weight	**141 × 74.8 × 53.5 mm · 170 g**

FAMILY — PICK THE RIGHT ONE

LX-402	120° wide, 12 × 15 m — **this unit**
LX-802N	Long range narrow, 24 × 2 m
CA-1W / CA-2C	Optional wall / ceiling brackets (±45°)

COUNTER QUICK ANSWERS

Will my dog set it off? Use Pet Alley mode — it raises the lower beams so small pets pass under.

Wireless? No — wired 12 V to an alarm panel or relay.

Can it switch a light? Yes, via its relay output to a light/relay module.

Source: Optex LX-402/802N datasheet (75064-00-5130-0105).