Sherlotronics 6.4 A Backup Power Supply

12 V 6.4 A battery-backup power supply / charger

STOCK CODE

14SH6.4AMP (W)

Keeps alarms, CCTV, maglocks and door controllers running when the power goes off.



6.4 A	70 W	13–14.4 V	12 mo
output	max power	adjustable	warranty

BEST FOR

- ✔ CCTV camera power with battery backup
- ✔ Maglocks & access control doors
- ✔ Alarm panel backup supply
- ✔ Load-shedding protection for 12 V systems

NOT FOR

- ✖ Loads above 6.4 A / 70 W
- ✖ Outdoor mounting without protection
- ✖ 24 V equipment

WHY CUSTOMERS CHOOSE IT

- **Microprocessor-controlled** battery charging
- **Low-battery cut-out** at 10 V protects the battery
- Buzzer warns on low battery & mains failure
- AC fail output to signal the alarm panel
- Resettable fuse on output, fused mains input

KEY SPECS

Input	**110 – 230 VAC 50 Hz**
Output	**13 – 14.4 VDC adjustable, 6.4 A**
Relay contact	**10 A**
AC fail output	**140 mA positive switching**
Size / weight	**275 × 225 × 97 mm · 1.13 kg**
Operating temp	**−3 to +60 °C**

COUNTER QUICK ANSWERS

Battery included? Check stock — add a 12 V 7 Ah (06AS12-7) or larger.

How many cameras? Add up each device's current — keep the total under 6.4 A.

Tells the alarm power failed? Yes — via the AC fail output.