C-TEC XFP 1-Loop 16-Zone Fire Panel

XFP501E/CA single-loop addressable fire alarm panel · CAST

STOCK CODE

29XFP501E-CA

Cost-effective addressable fire panel — up to 255 devices on one loop, networkable up to 8 panels.



255	16	1 km	8
devices / loop	zones	loop length	panels networked

BEST FOR

- ✔ Small to medium buildings: offices, schools, retail
- ✔ Upgrades from conventional to addressable
- ✔ Multi-building sites (network up to 8 panels)
- ✔ Sites needing phased evacuation

NOT FOR

- ✖ Very large sites needing more than one loop
- ✖ Non-CAST (other protocol) detectors
- ✖ Outdoor or damp plant rooms (IP30)

WHY CUSTOMERS CHOOSE IT

- **255 CAST devices** on one loop, auto or manual addressing
- **Fault location** — shows where shorts/opens are
- 2 sounder circuits, 3 programmable relays + fault relay
- Day/night mode, investigation delay, phased evacuation
- PC upload/download software

KEY SPECS

Mains	**230 VAC, 350 mA max**
Batteries	**2 × 12 V 3.2 Ah VRLA**
Loop	**40 V, 500 mA, 1 km max**
Display	**2 × 40 char backlit + 16 zone LEDs**
Size / weight	**380 × 235 × 96 mm · 1.8 kg**
Approvals	**LPCB EN54-2/4**

COUNTER QUICK ANSWERS

Which detectors? C-TEC CAST range, e.g. CA416 smoke, CA414 multi-sensor.

Batteries included? Order 2 × 12 V 3.2 Ah VRLA.

Repeater? Yes — up to 8 XFP repeaters via the XFP761 network card.

Source: C-TEC XFP501E/CA datasheet.