C-TEC XFP 1-Loop 32-Zone Fire Panel

XFP single-loop addressable panel · 32 zones · CAST

STOCK CODE

29XFP502-CA

The 32-zone XFP — same 255-device loop as the 16-zone, with more zones and a bigger power supply.



255	32	3 A	8
devices / loop	zones	PSU output	panels networked

BEST FOR

- ✔ Buildings needing more than 16 zones on one loop
- ✔ Schools, offices, retail, hotels
- ✔ Networked multi-building sites

NOT FOR

- ✖ Sites needing more than one loop
- ✖ Non-CAST devices
- ✖ Damp plant rooms (IP30)

WHY CUSTOMERS CHOOSE IT

- **32 zone LEDs** + 2×40 character display
- 255 CAST devices, auto or manual addressing
- 2 sounder circuits, 3 relays + fault relay
- Phased evacuation, day/night mode
- Networks up to 8 XFP panels

KEY SPECS

Mains	**230 VAC, 680 mA max**
Batteries	**2 × 12 V 7 Ah VRLA**
Loop	**40 V, 500 mA, 1 km**
Size	**410 × 250 × 80 mm**
Weight	**4.5 kg (no batteries)**
Approvals	**LPCB EN54-2/4**

FAMILY — PICK THE RIGHT ONE

XFP501E/CA	**16 zones**
XFP502/CA	**32 zones — this panel**

COUNTER QUICK ANSWERS

Batteries? 2 × 12 V 7 Ah — e.g. 2 × Forbatt FB7.2-12.

16 or 32 zones? Same loop; choose by how many zones you need to show.

Detectors? C-TEC CAST range (CA402/414/416).