C-TEC CAST Input/Output Module

Addressable I/O · zone monitor · relay output

STOCK CODE

29CA730

Connects other equipment to a CAST fire system — monitor a switch or conventional zone, and switch a relay.



1 in	1 out	20+10	EN54-18
monitored input	relay 1 A	conv. detectors + MCPs	LPCB

BEST FOR

- ✔ Shutting gas valves or roller doors on fire alarm
- ✔ Smoke vents, lift recall, plant shutdown
- ✔ Adding a conventional zone to a CAST loop
- ✔ Monitoring sprinkler flow switches

NOT FOR

- ✖ Switching mains loads above 0.3 A @ 125 VAC
- ✖ Non-CAST panels

COUNTER QUICK ANSWERS

Can it switch mains? Only small loads — use an interposing relay for more.

Conventional detectors? Yes, up to 20 detectors + 10 call points.

Mounting? Standard double-gang back box.

WHY CUSTOMERS CHOOSE IT

- **Monitored input** — switch or conventional zone (20 detectors + 10 MCPs)
- **Volt-free relay** 1 A @ 30 VDC
- Built-in short-circuit isolator
- Status LEDs: polling, fault, active

KEY SPECS

Supply	**27 – 40 VDC (loop)**
Current	**1.3 mA quiet · 5.5 mA active**
Relay	**1 A @ 30 VDC / 0.3 A @ 125 VAC**
Size	**147 × 87 × 22 mm (double-gang box)**