ET Nice RX3 CONDO 2019 Receiver

3-channel ET-Blu Mix receiver · 999 users · display

STOCK CODE

1702262-000

Complex-gate receiver with a digital display — 999 users, 3 relays, edit users one by one.



999	3	10–30 V	404/434
users	relays	AC/DC	MHz

BEST FOR

- ✔ Estates, complexes and shared gates
- ✔ Managing many remotes individually
- ✔ Adding remotes to any gate motor

NOT FOR

- ✖ Non-ET remotes

WHY CUSTOMERS CHOOSE IT

- **Digital display** & push buttons
- Independent user editing · last 30 transactions log
- Relays restore their state after a power cut
- Signal-strength tester · EEPROM memory copier backup

KEY SPECS

Relays	**3 × dry contact 1 A · latch, pulse or momentary (1–255 s)**
Power	**10–30 V AC/DC · <15 mA standby, <50 mA active**
Remotes	**ET-Blu Mix & ET Blue**
Size	**98 × 51 × 27 mm**
Operating temp	**−20 to +50 °C**

COUNTER QUICK ANSWERS

How many remotes? Up to 999 users.

Delete one remote? Yes — independent user editing.

Power? 10–30 V AC or DC.