DSC Neo LCD Keypad with PowerG Receiver

HS2LCDRF8 · 2×16 LCD keypad + built-in PowerG 868 MHz transceiver

STOCK CODE

22HS2LCDRF8E1

Full-message Neo keypad with a PowerG receiver built in — add wireless without an HSM2HOST.

⚠ This is the 868 MHz model. Check it matches the customer's PowerG receiver frequency.



2×16	PowerG	8	125 mA
LCD + icons	built in	partitions	max

WHY CUSTOMERS CHOOSE IT

- **Built-in PowerG transceiver**
- Blue backlit 2×16 message LCD
- 5 programmable function keys
- Zone/PGM I/O · temperature sensor
- Surface or single-gang box mount

BEST FOR

- ✔ Neo systems adding wireless devices
- ✔ Saving an HSM2HOST module
- ✔ Homes and offices

NOT FOR

- ✖ Non-Neo panels
- ✖ Prox tags (not on this model)

KEY SPECS

Size	**168 × 122 × 20 mm**
LCD area	**99 × 24 mm**
Current	**125 mA max**
Compatibility	**PowerSeries Neo HS2016–HS2128**

FAMILY — PICK THE RIGHT ONE

HS2LCD	**LCD keypad, wired only**
HS2LCDRF8	**LCD + PowerG 868 MHz — this unit**
HS2LCDRFP8	**Adds prox tag reader**

COUNTER QUICK ANSWERS

Need an HSM2HOST? No — receiver is built in.

Prox tags? No — HS2LCDRFP8.

Frequency? 868 MHz — match the devices.

Source: DSC PowerSeries Neo Hardwired Keypads with PowerG datasheet.

Elvey Counter Helper · internal reference