Sherlotronics 3 A Lithium Backup PSU

12 V 3 A battery-backup power supply for lithium batteries

STOCK CODE

14SH3AMP-LITHIUM

Backup power supply made to charge lithium batteries — for alarms, CCTV, maglocks and door controllers.



3 A	35 W	Li-ion	12 mo
output	max power	charging	warranty

WHY CUSTOMERS CHOOSE IT

- **Lithium charging**, current limited to 1 A
- **Low-battery cut-out** at 11 V
- Over-voltage protection above 15 V
- AC fail output to the alarm panel
- Resettable output fuse · fused mains input

BEST FOR

- ✔ Systems using a 7 Ah lithium battery
- ✔ Alarm panel or CCTV backup
- ✔ Maglocks and door controllers
- ✔ Load-shedding protection on small 12 V loads

NOT FOR

- ✖ Lead-acid batteries (use the 6.4 A or standard PSU)
- ✖ Loads above 3 A / 35 W
- ✖ Outdoor mounting

KEY SPECS

Input	**110 – 230 VAC 50 Hz**
Output	**13 – 14.4 VDC adjustable, 3 A**
AC fail output	**140 mA positive switching**
Size / weight	**200 × 180 × 87 mm · 0.9 kg**
Operating temp	**−3 to +60 °C**

FAMILY — PICK THE RIGHT ONE

3A Lithium	**3 A, for lithium — this unit**
6A Lithium	**6 A, for lithium (12.8 V)**
6.4 A (14SH6.4AMP)	**6.4 A, for lead-acid**

COUNTER QUICK ANSWERS

Battery? Pair with a 12 V 7 Ah lithium, e.g. Uniross LFP12-7.

Lead-acid? No — this one is set up for lithium.

Tells the panel mains failed? Yes, via the AC fail output.

Source: Sherlotronics 3A Lithium Battery Backup Power-Supply datasheet.

Internal counter reference