DSC PowerSeries Neo HS2016 Panel

Hybrid wired + PowerG wireless alarm panel · 6 to 16 zones

STOCK CODE

22HS2016-4HSLEDZAM0

Entry-level PowerSeries Neo panel — mix wired and PowerG wireless devices, and grow with the same keypads and modules.

⚠ Stock code suggests a kit (likely panel + LED keypad). Confirm exact kit contents before quoting.



Metal cabinet (panel board inside)

6→16	2	48	500
zones	partitions	user codes	event log

WHY CUSTOMERS CHOOSE IT

- **Hybrid** — wired zones plus PowerG wireless (up to 2 km line-of-sight)
- **128-bit AES** encryption on wireless, communicator & bus
- Visual and 2-way audio alarm verification (with add-ons)
- Remote programming & firmware updates via DLS 5
- Alarm.com compatible for app control & home automation

BEST FOR

- ✔ Homes and small businesses up to 16 zones
- ✔ Mixing wired zones with PowerG wireless detectors
- ✔ Retrofits where some cabling is hard to run
- ✔ Control-room monitoring via IP / cellular add-ons
- ✔ Customers wanting app control (Alarm.com compatible)

NOT FOR

- ✖ Large sites over 16 zones — step up to HS2032/HS2064/HS2128
- ✖ Outdoor or damp installs
- ✖ Customers wanting a fully wireless, app-only DIY kit

KEY SPECS

Power supply	**16.5 VAC / 40 VA transformer**
Panel current	**85 mA nominal**
Aux / bell output	**13.75 VDC, 700 mA each**
Keypads	**Up to 8 wired + 8 wireless**
Outputs	**2 on-board PGMs, expandable**
Operating temp	**0 to 49 °C · 93% RH**

FAMILY — PICK THE RIGHT ONE

HS2016	6 → 16 zones, 2 partitions — **this panel**
HS2032	8 → 32 zones, 4 partitions
HS2064 E	8 → 64 zones, 8 partitions
HS2128 E	8 → 128 zones, 8 partitions

COUNTER QUICK ANSWERS

Battery? Yes — a 12 V standby battery is required (order separately unless in the kit).

Wireless? Add an HSM2HOST transceiver or an RF keypad for PowerG devices.

Internet reporting? Add a TL280E (IP) or dual-path cellular communicator.

Source: DSC PowerSeries Neo Control Panels datasheet (PN 330001878).

Internal counter reference