

[On This Page](#) >

Configure Disk

Summary

The disks of the target devices need to be configured before the rollout can start.

Requirements

- SSH access from your setup device to all target devices
- Double check that each machine has a hardware report saved under `machines/YOUR-MACHINE-NAME/facter.json`

Configuring Target Disks

By default clan uses [disko](#) which allows for declarative disk partitioning.

To see what disk templates are available run:

```
1 $ clan templates list
2
3 Available 'clan' templates
4 |— <builtin>
5 |   |— default: Initialize a new clan flake
6 |   |— flake-parts: Flake-parts
7 |   |— flake-parts-minimal: Minimal flake-parts clan template
8 |   |— minimal: for clans managed via (G)UI
9 Available 'disko' templates
10 |— <builtin>
11 |   |— single-disk: A simple ext4 disk with a single partition
```

```
12 Available 'machine' templates
13 |— <builtin>
14 |   |— flash-installer: Initialize a new flash-installer machine
15 |   |— new-machine: Initialize a new machine
```

For this guide we will select the `single-disk` template, that uses `A simple ext4 disk with a single partition`.

♥ Tip

For advanced partitioning, see [Disko templates](#) or [Disko examples](#). You can also [contribute a disk template to clan core](#)

To setup a disk schema for a machine run

```
clan templates apply disk single-disk jon --set mainDisk ""
```

Which should fail and give the valid options for the specific hardware:

```
Invalid value for placeholder mainDisk - Valid options:
/dev/disk/by-id/nvme-WD_PC_SN740_SDDQNQD-512G-1201_232557804368
```

Re-run the command with the correct disk:

```
clan templates apply disk single-disk jon --set mainDisk "/dev/disk/by-id/nvme-WD_PC_SN740_SDDQNQD-512G-1201_232557804368"
```

Should now be successful

```
Applied disk template 'single-disk' to machine 'jon'
```

A `disko.nix` file is created in `machines/jon` You can have a look and customize it if needed.

⚠ Danger

Don't change the `disko.nix` after the machine is installed for the first time, unless you really know what you are doing. Changing disk configuration requires wiping and reinstalling the machine.

Checkpoint

Check your machines/ folders for the disk files. If a machine sub-folder does not contain a disk file, the setup ran into an error and needs to be restarted for the particular machine.

Up Next

After all preparations are done, we can now start the actual deployment process.

← Previous

Prepare Virtual Machines

Next →

Deployment Phase

Need help? Reach out to [our community](#).