

Solstice Home Hub SH-100 -- Product Guide

Overview

The Solstice Home Hub SH-100, made by Solstice Devices Inc., is a smart home hub that connects and controls compatible smart devices from a single app.

Wireless connectivity

The SH-100 supports Wi-Fi 6, Bluetooth 5.2, Zigbee 3.0, and Thread. It does not support Apple HomeKit.

Device capacity

The hub supports up to 150 connected smart devices at once. Connecting more than 150 devices is not supported and can cause connectivity issues; see the Troubleshooting Guide for what to do if you have too many devices connected.

Power

The SH-100 is powered by USB-C using the included 9W adapter. It has no internal battery and must remain plugged in to operate.

Dimensions

120mm x 120mm x 35mm.

App requirements

The Solstice Home app requires iOS 15 or later, or Android 10 or later.

Box contents

The box includes: one SH-100 hub, one USB-C cable, one 9W power adapter, a quick start guide, and a mounting bracket.

Solstice Home Hub SH-100 -- Product Guide (continued)

Setup steps

1. Plug the hub into power using the included USB-C cable and adapter.
2. Open the Solstice Home app and tap "Add Hub".
3. Scan the QR code printed on the base of the hub.
4. Connect the hub to your Wi-Fi network when prompted.
5. Give the hub a name to finish setup.

LED status reference

Solid blue means the hub is powered on and ready to pair.

Blinking blue means the hub is in pairing mode.

Solid green means the hub is connected and running the latest firmware.

Blinking red means a connectivity error.

Solid red means a firmware update failed.

Firmware updates

The hub checks for firmware updates automatically and installs them overnight between 2:00 AM and 4:00 AM local time, unless automatic updates are disabled in the app settings.