



DC V AC V DC A Ω dB

Kyoritsu 1109S Multi Meter

Features at a glance

- Mirrored scale for easy and accurate reading.
- Output terminal to cut off DC component when measuring AC voltage.
- Safety designed input terminals and test leads.

Specifications

DC V	0.1/0.5/2.5/10/50/250/1000V(20k Ω /V) \pm 3% of FS
AC V	10/50/250/1000V(9k Ω /V) \pm 3% of FS
DC A	50 μ A/2.5/25/250mA \pm 3% of FS
Ω	2/20k Ω /2/20M Ω \pm 3% of scale length
Decibel	-10 - +62dB
hFE	0 - 1000($\Omega \times 10$) \pm 3% of scale length
Power source	R6(AA)(1.5V) \times 2, 6F22(9V) \times 1
Dimensions	150(L) \times 100(W) \times 47(D)mm
Weight	330g approx..
Accessories	7066A(Test leads), 8901(Fuse[0.5A/250V]) \times 2, R6(AA) \times 2, 6F22 \times 1, Instruction manual
Optional	9168(Carrying case)