

# US Patent & Trademark Office

## Patent Public Search | Text View

---

|                      |                       |
|----------------------|-----------------------|
| United States Patent | 12407080              |
| Kind Code            | B2                    |
| Date of Patent       | September 02, 2025    |
| Inventor(s)          | Buduson; James et al. |

---

### Systems and methods for autonomously adjustable aerial vehicle antenna

---

#### Abstract

Systems and methods for autonomously operating an antenna assembly. The methods comprise: obtaining, by a processor of the antenna assembly, first information comprising at least one of a value for a variable altitude of the antenna assembly, a value for a variable height of the antenna assembly above ground, a value for a variable height of the antenna assembly above sea level, a value for a variable distance of the antenna assembly from a reference object, and a first value for a variable signal frequency of a communication device; using, by the processor, the information to obtain a desired length of an antenna of the antenna assembly; and controlling, by the processor, an actuator to adjust a length of the antenna until the length reaches the desired length.

---

**Inventors:** Buduson; James (North Chili, NY), Burke; Peter (Hilton, NY), Majkowski; Joseph (Pittsford, NY), Howe; Thomas (Rochester, NY), Blakeney; Megan (Rochester, NY), Fay; Louis (Charlotte, NC)

**Applicant:** L3Harris Global Communications, Inc. (Melbourne, FL)

**Family ID:** 90833125

**Assignee:** L3Harris Global Communications, Inc. (Melbourne, FL)

**Appl. No.:** 17/976479

**Filed:** October 28, 2022

#### Prior Publication Data

|                            |                         |
|----------------------------|-------------------------|
| <b>Document Identifier</b> | <b>Publication Date</b> |
| US 20240145896 A1          | May. 02, 2024           |

---

#### Publication Classification

**Int. Cl.:** H01Q1/28 (20060101); G05D3/20 (20060101); H01Q1/08 (20060101)

## U.S. Cl.:

CPC      **H01Q1/087** (20130101); **G05D3/20** (20130101); **H01Q1/28** (20130101);

## Field of Classification Search

**CPC:**      H01Q (1/087); H01Q (1/28)

---

## References Cited

### U.S. PATENT DOCUMENTS

| Patent No.   | Issued Date | Patentee Name        | U.S. Cl. | CPC             |
|--------------|-------------|----------------------|----------|-----------------|
| 2036456      | 12/1935     | Buschbeck            | N/A      | N/A             |
| 2709220      | 12/1954     | Spector              | N/A      | N/A             |
| 2834012      | 12/1957     | Allen                | N/A      | N/A             |
| 3268903      | 12/1965     | Keucken et al.       | N/A      | N/A             |
| 4117495      | 12/1977     | Hochstein            | 343/901  | H01Q 9/14       |
| 5221930      | 12/1992     | Scott                | N/A      | N/A             |
| 5370334      | 12/1993     | Shinkawa et al.      | N/A      | N/A             |
| 5865390      | 12/1998     | Iveges               | N/A      | N/A             |
| 8473017      | 12/2012     | Milosavljevic et al. | N/A      | N/A             |
| 9407000      | 12/2015     | Willistein           | N/A      | N/A             |
| 2009/0046032 | 12/2008     | Opitz                | N/A      | N/A             |
| 2009/0102705 | 12/2008     | Obermeyer            | 343/705  | G01S 13/9029    |
| 2017/0257165 | 12/2016     | Pescod               | N/A      | H04B<br>10/2575 |
| 2020/0280827 | 12/2019     | Fechtel              | N/A      | H04W 8/08       |

### FOREIGN PATENT DOCUMENTS

| Patent No. | Application Date | Country | CPC |
|------------|------------------|---------|-----|
| 2311419    | 12/1975          | FR      | N/A |

### OTHER PUBLICATIONS

<https://consumer.steppir.com/shop/vertical-antennas/bigir-mark-iv-vertical-antenna-40m-6m-package>. cited by applicant

---

*Primary Examiner:* Salih; Awat M

*Attorney, Agent or Firm:* Fox Rothschild LLP

---

## Background/Summary

### BACKGROUND

#### Statement of the Technical Field

(1) The present document concerns antenna systems. More specifically, the present document concerns systems and methods for autonomously adjustable aerial vehicle antenna.

#### Description of the Related Art

(2) Many ground radios exist for facilitating voice and data communications between users. A clear

Line of Sight (LoS) between two radios is ideal for such communications, but impractical in many applications. For example, the radios may experience Line of Sight (LoS) obstructions effecting the reliability of wireless communications therebetween. The obstructions include distance, terrain (e.g., foliage and mountains) and human made objects (e.g., buildings). Thus, there is a need for a solution to improve the reliability of wireless communications between radios when they do not have clear LoS to each other.

(3) Some solutions address the reliability issue by providing communication relays hosted by Unmanned aerial vehicles (UAVs) to extend the dismounted communication distances between the radios. The performance of these relays is limited because their antennas are required to be compact and flexible to survive take off and landing of the UAVs.

#### SUMMARY

(4) This document concerns systems and methods for autonomously operating an antenna assembly. The methods comprise: obtaining, by a processor of the antenna assembly, first information comprising at least one of a value for a variable altitude of the antenna assembly, a value for a variable height of the antenna assembly above ground, a value for a variable height of the antenna assembly above sea level, a value for a variable distance of the antenna assembly from a reference object, and a first value for a variable signal frequency of a communication device; using, by the processor, the information to obtain a desired length of an antenna of the antenna assembly; and controlling, by the processor, an actuator to adjust a length of the antenna until the length reaches the desired length.

(5) The present document also concerns an antenna assembly. The antenna assembly comprises: an antenna with a variable length; an actuator coupled to the antenna; a processor coupled to the actuator; and a non-transitory computer-readable storage medium comprising programming instructions that are configured to cause the processor to implement a method for autonomously adjusting the variable length of the antenna. The programming instructions comprise instructions to: obtain first information comprising at least one of a value for a variable altitude of the antenna assembly, a value for a variable height of the antenna assembly above ground, a value for a variable height of the antenna assembly above sea level, a value for a variable distance of the antenna assembly from a reference object, and a first value for a variable signal frequency of a communication device; use the information to obtain a desired length of an antenna of the antenna assembly; and control the actuator to cause an adjustment of the variable length of the antenna until the variable length reaches the desired length.

(6) The present document also concerns an unmanned aerial vehicle. The unmanned aerial vehicle comprises a fuselage, avionic electronics disposed in the fuselage, a payload physical joined with the fuselage, and at least one power source configured to supply power to the avionic electronics and payload. The payload comprises a communication relay and an antenna assembly coupled to the communication relay. The communication relay is configured to perform relay operations to extend a range between users of a communication relay link for voice and data communications. The antenna assembly comprises an antenna with a variable length, an actuator coupled to the antenna, a processor coupled to the actuator, and a non-transitory computer-readable storage medium comprising programming instructions that are configured to cause the processor to implement a method for autonomously adjusting the variable length of the antenna.

(7) The programming instructions comprise instructions to: obtain first information comprising at least one of a value for a variable altitude of the antenna assembly, a value for a variable height of the antenna assembly above ground, a value for a variable height of the antenna assembly above sea level, a value for a variable distance of the antenna assembly from a reference object, and a first value for a variable signal frequency of a communication device; use the information to obtain a desired length of an antenna of the antenna assembly; and control the actuator to cause an adjustment of the variable length of the antenna until the variable length reaches the desired length.

---

## Description

### BRIEF DESCRIPTION OF THE DRAWINGS

- (1) This disclosure is facilitated by reference to the following drawing figures, in which like numerals represent like items throughout the figures.
- (2) FIG. 1 provides an illustration of a system.
- (3) FIG. 2 provides an illustration of the Unmanned Aerial Vehicle (UAV) shown in FIG. 1.
- (4) FIG. 3 provides an illustration of electronic components and/or circuits of the UAV shown in FIGS. 1-2.
- (5) FIG. 4 provides a block diagram of an illustrative architecture for a computing device.
- (6) FIG. 5 provides an illustration of an architecture for an assembly with an antenna in a retracted position.
- (7) FIG. 6 provides an illustration of the assembly shown in FIG. 5 with the antenna in the extended position.
- (8) FIGS. 7-9 each provides an illustration of another architecture for an assembly.
- (9) FIGS. 10A-10B (collectively referred to as "FIG. 10") provide a flow diagram of a method for operating an antenna assembly.
- (10) FIG. 11 provides a flow diagram of an illustrative method for determining how much an antenna is to be extended or retracted.
- (11) FIG. 12 provides a flow diagram of an illustrative method for autonomously operating an antenna assembly.

### DETAILED DESCRIPTION

(12) It will be readily understood that the solution described herein and illustrated in the appended figures could involve a wide variety of different configurations. Thus, the following more detailed description, as represented in the figures, is not intended to limit the scope of the present disclosure but is merely representative of certain implementations in different scenarios. While the various aspects are presented in the drawings, the drawings are not necessarily drawn to scale unless specifically indicated.

(13) Reference throughout this specification to features, advantages, or similar language does not imply that all the features and advantages that may be realized should be or are in any single embodiment of the invention. Rather, language referring to the features and advantages is understood to mean that a specific feature, advantage, or characteristic described in connection with an embodiment is included in at least one embodiment of the present invention. Thus, discussions of the features and advantages, and similar language, throughout the specification may, but do not necessarily, refer to the same embodiment.

(14) Many ground radios exist for facilitating voice and data communications between users. A clear LoS between two radios is ideal for such communications, but impractical in many applications. For example, the radios may experience LoS obstructions effecting the reliability of wireless communications therebetween. The obstructions include distance, terrain (e.g., foliage and mountains) and human made objects (e.g., buildings). Thus, there is a need for a solution to improve the reliability of wireless communications between radios when they do not have clear LoS to each other.

(15) The present solution addresses the reliability issue by providing communication relays hosted by UAVs to extend the dismounted communication distances between the radios. The communication relays are designed such that the size, weight and power limitations of the UAVs are satisfied even when the communication relays are disposed therein. The length of an antenna of a communication relay is autonomously adjustable while the UAV is in flight. This autonomous adjustment ensures that the antenna will not be damaged or otherwise deformed during take-off and landing of the UAV. The manner in which the autonomous adjustment of antenna length is achieved

will become evident as the discussion progresses.

(16) Referring now to FIG. 1, there is provided an illustration of a system **100** implementing the present solution. System **100** comprises a plurality of UAV(s) **102**, communication device(s) **104**, **122**, ground control station(s) **110**, and/or a server **118**. The UAV **102** does not have any onboard human pilot, crew members and/or passengers. The UAV can include, but is not limited to, an autonomous aerial vehicle and/or a remotely-piloted aerial vehicle. In the remotely-piloted scenarios, an operator **108** (e.g., a Remote Pilot In Command (RPIC)) can remotely control flight operations of the UAV by using ground control station **110** that is communicatively coupled to an internal circuit **128** of the UAV **102** via command and control link **112**. The internal circuit **128** includes the avionics payload. The avionics payload comprises avionic electronics, i.e., hardware and/or software facilitating positioning, navigation, timing and other functionalities of the UAV. The UAV can have any classification (e.g., a Group 1-5 classification, and/or size classification (e.g., very small, small, medium, and/or large)).

(17) During flight, the UAV **102** can act as an airborne relay to wirelessly connect to communication unit(s) **104** (e.g., terrestrial radios) located on the ground at locations in which wireless communications therefrom are masked or screened by the LoS obstructions (e.g., distance, terrain (e.g., foliage and mountains) and human made objects (e.g., buildings)). In this regard, a communications relay **126** is provided with the UAV. The communications relay **126** may communicate over a secure communications link **116** (e.g., a Small Secure Data Link (SSDL)), use various frequency bands (e.g., Ultra High Frequency (UHF) and Very High Frequency (VHF) bands), support a variety of frequencies and waveforms, and extend the range between users **106** for voice and data communications (e.g., text messages and/or imagery data) beyond the LoS range of the communication unit(s) **104**. The communication unit(s) **104** can include, but is(are) not limited to, radio transceiver(s), personal computer(s), portable computer(s), desktop computer(s), smart device(s) (e.g., a smart phone), tablet(s), and/or wearable device(s) (e.g., a smart watch and/or smart goggles).

(18) The voice and data communications may be provided to remote devices such as computing device(s) **122** and/or server(s) **118** via network **114**. Network **114** can include, but is not limited to, a radio network, a cellular network, and/or the Internet. The remote devices can process and/or output the voice and data communications to users **124** thereof. The voice communications, data communications and/or analytics relating thereto can be stored in a datastore **120**.

(19) Referring now to FIG. 2, there is shown an illustrative architecture for the UAV **102** of FIG. 1. The internal circuit **128** is disposed inside the fuselage **202** of the UAV, and the communication relay **126** may be disposed in an existing compartment **204** formed in the fuselage **202** of the UAV. The compartment **204** may be accessible from the outside of the aircraft (e.g., via a door or removable panel). An antenna assembly **206** may also be disposed in the fuselage **202** of the UAV and/or coupled to the wing(s) **208**, **210** of the UAV. A more detailed block diagram of the internal circuit **128**, communication relay **126** and antenna assembly **206** is provided in FIG. 3.

(20) As shown in FIG. 3, the internal circuit **128** comprises a computing device **302**, sensor(s) **304**, an engine **306**, a flight control system **308**, a communication system **310**, a power source **312**, elevators/flaps/ailerons/rudders **314**, and landing gear **316**. The internal circuit **128** can include more or less components than those shown and listed.

(21) The computing device **302** comprises processor(s) that execute(s) instructions to perform the at least the following operations: receiving and processing Position, Navigation and Timing (PNT) data from the sensor(s) **304**; and/or facilitating flight operations by providing the PNT data and/or a flight plan to the flight control system **308** and/or the ground control station via communication system **310**. The PNT data ensures that the operator and/or the UAV knows the UAV's current position at any given time. The flight plan ensures that the UAV knows its destination relative to its current position which is useful especially in autonomous aircraft applications.

(22) The sensor(s) **304** can include, but are not limited to, a LiDAR system, a radar system, a sonar

system, a camera, a locator (e.g., GPS device), an altitude sensor, and/or an eLORAN device. It should be noted that the locator of internal circuit **128** does provide information that facilitate the operator **108** in determining the location of the UAV.

(23) The communication system **310** provides a means to transmit PTN data and/or other information to the ground control station, and to receive command and control information from the ground control station. The command and control information is passed from the communication system **310** to the computing device **302** and/or the flight control system **308**. The flight control system **308** controls operations of the engine **306**, elevator/flaps/aileron/rudders **314**, and/or landing gear **316** in accordance with the commands and control information received from the ground control station.

(24) The components **302-310**, **314**, **316** are supplied power from a power source **312**. The power source **312** can include, but is not limited to, a battery and/or an energy harvesting circuit (e.g., comprising a super capacitor to store harvested energy from heat, wind, light, RF signals, etc.). The power is supplied from the power source **312** to components **302-310** via a power bus **326**.

(25) The communication relay **126** may be independent from the internal circuit **128** and may consist of a standalone payload for the UAV. As such, the communication relay **126** is provided with another power source **326** such that it is not supplied power from the power source **312** of the UAV via power bus **326**. Power source **326** can include, but is not limited to, a battery (e.g., a Lithium Polymer (LiPo) battery) and/or an energy harvesting circuit. Such a power source arrangement ensures that the components **322**, **324** of the communication relay **126** continue to operate when the internal circuit **128** is no longer being supplied power from the power source **312**. The components include a radio **322** and a locator **324**. The locator **324** can include, but is not limited to, a GPS device. The locator **324** provides a means to allow all users **106**, **124** in a communication relay link to know the location of the UAV at any given time.

(26) The antenna assembly **206** is provided for the communication relay **126**. The antenna assembly **206** includes an antenna for the radio **322** and/or an antenna for the locator **324**. The antenna(s) **350** is(are) retractable into the antenna assembly and/or extendable from the antenna assembly. The transition of the antenna(s) between the retracted position(s) and extended position(s) is selectively, dynamically and/or autonomously controlled by an antenna controller **352** based on certain criteria. The antenna controller **352** can include, but is not limited to, computing device (for example, computing device **400** of FIG. 4), a processor and/or a non-transitory computer-readable storage medium comprising programming instructions that are configured to cause the processor to implement methods for selectively, dynamically and/or autonomously adjusting a length of the antenna(s) **350**.

(27) The criteria can include, but is not limited to, the UAV reaching a threshold altitude, threshold distance to an object, a threshold distance above sea level, a measured frequency of a Radio Frequency (RF) port of the communication relay **126**, a current position of an antenna, and/or a characteristic of an environment (for example, air pressure—air pressure decreased as altitude increases). In this regard, the antenna assembly **206** comprises one or more sensors **354** to detect at least a signal frequency at a communications portion of the communication relay **126**, an altitude, a height above sea level, a time of flight of a signal from the UAV to a surface (for example, a ground surface), a distance from the UAV to an object, an air pressure, and/or an antenna position. Such sensors can include, but are not limited to, altitude sensor(s), pressure sensor(s), radar system(s), Lidar system(s), acoustic system(s), distance sensor(s), and signal frequency sensor(s). The length of each antenna can be automatically adjusted for use with VHF and UHF radio waves.

(28) Referring now to FIG. 4, there is shown an illustrative architecture for a computing device **400**. The communication unit(s) **104** of FIG. 1, ground control station **110** of FIG. 1, server **118** of FIG. 1, computing device(s) **122** of FIG. 1, computing device **302** of FIG. 3 and/or antenna controller **352** of FIG. 3 is/are the same as or similar to computing device **400**. As such, the discussion of computing device **400** is sufficient for understanding the components **104**, **110**, **118**,

**122** of FIG. 1 and components **302**, **352** of FIG. 3.

(29) Computing device **400** may include more or less components than those shown in FIG. 4. However, the components shown are sufficient to disclose an illustrative solution implementing the present solution. The hardware architecture of FIG. 4 represents one implementation of a representative computing device configured to receive information, process the receive information, transmit information and/or control operations of a UAV, as described herein. As such, the computing device **400** of FIG. 4 implements at least a portion of the method(s) described herein.

(30) Some or all components of the computing device **400** can be implemented as hardware, software and/or a combination of hardware and software. The hardware includes, but is not limited to, one or more electronic circuits. The electronic circuits can include, but are not limited to, passive components (e.g., resistors and capacitors) and/or active components (e.g., amplifiers and/or microprocessors). The passive and/or active components can be adapted to, arranged to and/or programmed to perform one or more of the methodologies, procedures, or functions described herein.

(31) As shown in FIG. 4, the computing device **400** comprises a user interface **402**, a Central Processing Unit (CPU) **406**, a system bus **410**, a memory **412** connected to and accessible by other portions of computing device **400** through system bus **410**, a system interface **460**, and hardware entities **414** connected to system bus **410**. The user interface can include input devices and output devices, which facilitate user-software interactions for controlling operations of the computing device **400**. The input devices include, but are not limited to, a physical and/or touch keyboard **450**. The input devices can be connected to the computing device **400** via a wired or wireless connection (e.g., a Bluetooth® connection). The output devices include, but are not limited to, a speaker **452**, a display **454**, and/or light emitting diodes **456**. System interface **460** is configured to facilitate wired or wireless communications to and from external devices (e.g., network nodes such as access points, etc.).

(32) At least some of the hardware entities **414** perform actions involving access to and use of memory **412**, which can be a Random Access Memory (RAM), a disk drive, flash memory, a Compact Disc Read Only Memory (CD-ROM) and/or another hardware device that is capable of storing instructions and data. Hardware entities **414** can include a disk drive unit **416** comprising a computer-readable storage medium **418** on which is stored one or more sets of instructions **420** (e.g., software code) configured to implement one or more of the methodologies, procedures, or functions described herein. The instructions **420** can also reside, completely or at least partially, within the memory **412** and/or within the CPU **406** during execution thereof by the computing device **400**. The memory **412** and the CPU **406** also can constitute machine-readable media. The term “machine-readable media”, as used here, refers to a single medium or multiple media (e.g., a centralized or distributed database, and/or associated caches and servers) that store the one or more sets of instructions **420**. The term “machine-readable media”, as used here, also refers to any medium that is capable of storing, encoding or carrying a set of instructions **420** for execution by the computing device **400** and that cause the computing device **400** to perform any one or more of the methodologies of the present disclosure.

(33) FIGS. 5-6 show an illustrative architecture for the antenna assembly **206** of FIGS. 2-3. Antenna assembly **206** comprises a housing **500** in which a connector **502** is disposed in a manner that allows a cable (not shown) to be connected thereto to facilitate communication of signals to/from an external device (for example, the communication relay **126** of FIGS. 1-3). Housing **500** can be formed of a rigid or semi-rigid material such as metal, plastic and/or rubber.

(34) Various components **504-516** are disposed in the housing **500**. These components include a reel **506**, a motor **508**, an antenna actuator **510**, a control circuit **512** and an antenna **514**. The control circuit **512** can include, but is not limited to, a computing device (for example, computing device **400** of FIG. 4), a processor and/or a non-transitory computer-readable storage medium

comprising programming instructions that are configured to cause the processor to implement methods for selectively, dynamically and/or autonomously adjusting a length of the antenna(s) **514**. (35) A power source **516** may also be provided in the housing **500** for supplying power to components **506-512**. These components can additionally or alternatively be supplied power from a power source (for example, power source(s) **312** and/or **326** of FIG. **3**) of the communication relay **126**. The power source(s) can include, but is(are) not limited to, rechargeable batteries, super capacitors, and/or energy harvesting circuits. Energy harvesting circuits are known and may be configured to harvest energy from, for example, communication signals, wind and/or solar rays. Any known or to be known energy harvesting circuit can be used here.

(36) A wire **504** is provided for mechanically and electrically connecting the antenna **514** to the connector **502**. In this way, the antenna **514** can receive Tx signals from the communication relay **126** that are to be transmitted therefrom and pass Rx signals received thereat to the communication relay **126** for processing.

(37) The antenna **514** is formed of one or more layers of flexible conductive material (for example, a metal layer). A non-conductive layer may be disposed on and/or encompass the flexible conductive material layer(s). The non-conductive layer may be formed of a plastic and/or rubber. The antenna **514** can be ribbon-like as shown in FIGS. **5-6** or alternatively have another shape such as a circular cross-sectional profile. The flexibility and shape of the antenna **514** allows it to be wound on and off the reel **506**.

(38) Reel **506** is coupled to the housing **500** such that it can rotate in two opposing directions **520**, **522** about one or more posts **518** or other coupling means. The antenna **514** is transitionable between a retracted position shown in FIG. **5** and an extended position shown in FIG. **6** via rotation of the reel **506**. For example, the antenna **514** is wound off of the reel **506** when the reel rotates in direction **520** and wound onto the reel **506** when the reel rotates in direction **522**. The antenna **514** travels in direction **530** and out of the housing **500** when being wound off the wheel. In contrast, the antenna **514** travels in direction **604** and into the housing **500** when being wound onto the wheel. The present solution is not limited to the particulars of this example.

(39) An engagement component **510** is provided to frictionally engage the antenna **514** for causing the antenna to transition between its retracted position and its extended position. The engagement component **510** can include, but is not limited to, a wheel or other circular item that is rotatable in two opposing directions **600**, **602**. The engagement component **510** has a surface **524** which is in direct contact with a surface **526** of the antenna **514**. One or both of the surfaces **524**, **526** may optionally have members **528** formed or disposed thereon in a particular pattern, an abrasive stuck (for example, sand) coupled thereto and/or is otherwise made rough to increase the frictional engagement between the engagement component **510** and the antenna **514**.

(40) A motor **508** is provided to controllably and selectively actuate engagement component **510**. The motor **508** may comprise a gear, articulating linkage and/or other means for causing rotation of the engagement member about a post (now visible in FIGS. **5-6**). Operation of the motor **508** is controlled by the control circuit **512**.

(41) Control circuit **512** operates motor **508** so that the antenna **514** is in its retracted position when the UAV is taking off and/or landing. The length **606** of the antenna outside of the housing **500** is adjusted while the UAV is in flight above a threshold altitude. The length **606** is adjustable to ensure that the antenna operates efficiently at any frequency of a plurality of frequencies. The frequencies can be in the VHF band and/or the UHF band.

(42) The amount by which the antenna's length **606** is adjusted at any given time is achieved by monitoring a frequency of a signal at an RF port of the communication relay's radio **322**, an altitude of the UAV, a height of the UAV above sea level, a distance of the UAV from a reference object, an air pressure of a surrounding environment and/or an antenna position. This length adjustment feature of the present solution increases the performance of the antenna at least in the low VHF band as compared to prior solutions.



(43) The present solution is not limited to the particular architecture shown in FIGS. 5-6. For example, the sensors **354** may be disposed outside of the housing **500** and/or separately coupled to the UAV.

(44) In some scenarios, a second engagement component **700** is provided on the other side of the antenna as shown in FIG. 7. Engagement component **700** is operated by the same motor **508** that causes movement of engagement component **528** or alternatively by another motor (not shown).

(45) In other scenarios, the engagement component **800** comprises a clamp which is linearly movable in two opposing directions **802**, **804** via an articulating arm **806** as shown in FIG. 8.

(46) In yet other scenarios, the antenna comprises a telescoping antenna **900** as shown in FIG. 9. The telescoping antenna **900** can be extended to the position shown in FIG. 9 and retracted to a collapsed position (not shown) by actuator **902**. Actuator **902** can include, but is not limited to, a motor and linkage. Actuator **902** can be controlled by the control circuit.

(47) Referring now to FIG. 10, there is provided a flow diagram of an illustrative method **1000** for operating an antenna assembly (for example, antenna assembly **206** of FIGS. 5-6, **706** of FIG. 7, **806** of FIG. 8 or **906** of FIG. 9) of a UAV (for example, UAV **102** of FIG. 1). Method **1000** begins with **1002** and continues with **1004** where the UAV is activated. A communication relay (for example, communication relay **126** of FIG. 1) and/or antenna assembly may also be activated in **1004**. The activated communication relay will perform relay operations while the UAV is in flight to extend a range between users on the ground for voice and data communications.

(48) In optional **1006**, a pre-flight antenna check for the antenna assembly is performed by the control circuit (for example, antenna controller **352** of FIG. 3 and/or control circuit **512** of FIGS. 5-6). The pre-flight antenna check involves detecting a position of an antenna (for example, antenna **514** of FIGS. 5-6) or an extended length the antenna. The extended length can include a length (for example, length **908** of FIG. 9) of the antenna in a partially or fully extended position, a length (for example, length **606** of FIG. 6) of the antenna which is located outside of a housing (for example, housing **500** of FIG. 5), or a length (for example, length **650** of FIG. 6) of the antenna which is wound off of the reel (for example, reel **506** of FIGS. 5-6). If the antenna of the antenna assembly is in a partially or fully extended position, then the antenna can be automatically retracted as shown by optional **1008**.

(49) In **1010**, the UAV is caused to take off from ground to begin a flight mission. The control circuit of the antenna assembly performs operations in **1012** to monitor an altitude of the UAV, an air pressure of a surrounding environment, a distance of the UAV from an external object, and/or a height of the UAV above sea level. The altitude of the UAV can be monitored and obtained using data generated by an altitude sensor of the antenna assembly, data generated by a pressure sensor of the antenna assembly, data from a navigation bus of the UAV, and/or telemetry/GPS data of the UAV. The air pressure of the surrounding environment can be monitored and obtained using a pressure sensor of the antenna assembly. The distance of the UAV from an external object (for example, a building, a ground surface, etc.) can be monitored and obtained using data generated by a proximity sensor of the antenna assembly, a radar system of the antenna assembly, a Lidar system of the antenna assembly, and/or an acoustic signaling system of the Lidar system, and/or other Time of Flight (ToF) system of the antenna system. The height of the UAV above sea level using data generated by a pressure sensor of the antenna assembly.

(50) The control circuit of the antenna assembly also performs operations to determine whether the UAV has reached a threshold altitude, a threshold height above ground or sea level and/or a threshold distance from a reference object. If not [**1012:NO**], then the control circuit continues with its monitoring operations. If so [**1012:YES**], then method **1000** continues with **1014** where the control circuit obtains a last extended length of the antenna. The last extended length of the antenna can be stored in a datastore (for example, memory **412** of FIG. 4) of the control circuit.

(51) Thereafter, a motor (for example, motor **508** of FIG. 5-6 or **702** of FIG. 7) or other actuation mechanism (for example, actuator **802** of FIG. 8 or **902** of FIG. 9) is activated in **1016**. This

activation of the motor/actuation mechanism causes the antenna to be extended out from the housing (for example, housing **500** of FIGS. 5-6) of the antenna assembly by a certain amount as shown by **1018**. This extension can be achieved by, for example, causing the antenna to be wound off of a reel by the certain amount. This amount may be determined, for example, based a difference between the current extended length of the antenna (for example, zero) and the last extended length of the antenna (for example, 1-10 inches). Once the antenna has reached its desired position, the motor or other actuation mechanism is deactivated in **1020**.

(52) Next, in **1022**, the control circuit performs operations to measure a frequency of a signal at a communication port (for example, communication port **350** of FIG. 3) of the communication relay. Any known or to be known techniques for detecting and measuring signal frequency can be used here. The control circuit then uses the measured frequency to obtain an antenna length from a datastore (for example, memory **412** of FIG. 4). A Look Up Table (LUT) operation can be used in this regard. The LUT can include a plurality of antenna lengths that are respectively associated with a plurality of frequency values. Thus, frequency can be used as an index for the LUT to facilitate identification of desired antenna lengths at any time during flight of the UAV. The motor or other actuation mechanism is activated again in **1026** to cause the antenna to be extended or retracted until the antenna length reaches the antenna length obtained in **1024**, as shown by **1028**. Extension of the antenna can be achieved, for example, by causing the antenna to be wound off of a reel. Retraction of the antenna can be achieved, for example, by causing the antenna to be wound onto the reel. The motor or actuation mechanism is deactivated in **1030**. Upon completing **1030**, method **1000** continues with **1032** of FIG. 10B.

(53) As shown in FIG. 10B, **1032** involves performing operations by the control circuit to set the last extended length for the antenna to the current extended length of the antenna. While the UAV is in flight, the communication relay continues to perform relay operations to extend a range between users on the ground for voice and data communications, as shown by **1034**.

(54) In **1036**, the control circuit of the antenna assembly performs operations to obtain another measurement of the signal frequency at the communication port of the communication relay. This signal frequency measurement is compared to the previous frequency measurement obtained in **1022** of FIG. 10A to determine whether the frequency at the communication port has changed by a certain amount (for example, by at least 5-20 MHz). If not [**1038:NO**], the control circuit continues to monitor the signal frequency at the communication port and/or goes to **1048** which will be discussed below. If so [**1038:YES**], operations of **1040-1046** are performed to automatically adjust the length of the antenna while the UAV is in flight and without any human intervention.

Operations of **1040-1046** are the same as or substantially similar to operations **1024-1030** of FIG. 10A. Operations of **1036-1046** can be performed continuously or periodically throughout flight of the UAV.

(55) The control circuit of the antenna assembly also continuously, periodically or responsively to a trigger event monitor the following parameters throughout flight of the UAV: an altitude of the UAV, a height of the UAV above ground, a height of the UAV above sea level, and/or a distance of the UAV from a reference object. The trigger event can include, but is not limited to, the initiation of a descent or landing operations by the UAV. Information about the occurrence of the trigger event can be communicated from the internal circuit (for example, circuit **128** of FIG. 1) to the antenna assembly. Results of this monitoring are used in **1048** to detect when the UAV has reached a threshold altitude, a threshold height above ground, a threshold height above sea level, and/or a threshold distance from an object. These threshold values can be same as or different than those used in **1012** of FIG. 10A. If not [**1048:NO**], the control circuit continues to perform its monitoring operations and/or return to **1038**.

(56) If so [**1048:YES**], the control circuit performs operations of **1050-1054** to: activate the motor or other actuation mechanism of the antenna assembly; cause the antenna to be retracted into the housing of the antenna assembly by a certain amount; and deactivate the motor or other actuation

mechanism of the antenna assembly. The retraction of the antenna can be achieved, for example, by causing the antenna to be wound onto the reel. Subsequently, **1056** is performed where method **1000** ends or other operations are performed (for example, deactivate the antenna assembly and/or return to **1004** of FIG. **10A**).

(57) Referring now to FIG. **11**, there is provided a flow diagram of an illustrative method **1100** for determining how much an antenna (for example, antenna **514** of FIG. **5-6** or **900** of FIG. **9**) is to be extended or retracted. Method **1100** can be performed by the control circuit (for example, control circuit **352** of FIG. **3** or **512** of FIG. **5**) of the antenna assembly in blocks **1024** and/or **1040** of FIG. **10**.

(58) Method **1100** begins with **1102** and continues with **1104** where a signal frequency measurement value is obtained by the control circuit. The signal frequency measurement value is converted to an absolute antenna length in **1106**. This conversion can be achieved using an LUT in which absolute antenna lengths are associated with signal frequency values. In **1108**, the control circuit obtains a last extended length of the antenna for a datastore (for example, memory **412** of FIG. **4**). The last extended length of the antenna is used in **1110** to convert the absolute antenna length to a relative antenna length. The relative antenna length can include, but is not limited to, (i) the difference between the last extended length of the antenna and the absolute antenna length or (ii) the difference between the absolute antenna length and the last extended length of the antenna. In scenario (i), a positive relative antenna length indicates that the antenna should be retracted by a given amount. A negative relative antenna length indicates that the antenna should be extended by the given amount. In scenario (ii), a positive relative antenna length indicates that the antenna should be extended by a given amount. A negative relative antenna length indicates that the antenna should be retracted by the given amount. Subsequent to completing **1110**, **1112** is performed where method **1100** ends or other operations are performed.

(59) Referring now to FIG. **12**, there is provided a flow diagram of an illustrative method **1200** for autonomously operating an antenna assembly (for example, antenna assembly **206** of FIGS. **2-3** and **5-6**, **706** of FIG. **7**, **806** of FIGS. **8**, and/or **906** of FIG. **9**). Method **1200** begins with **1202** and continues with **1204-1216**. All or some of the operations of **1204-1216** may be performed by a processor (for example, antenna controller **352** of FIG. **3**, CPU **406** of FIG. **4**, control circuit **512** of FIGS. **5-6**, controller **808** of FIG. **8**, and/or control circuit **908** of FIG. **9**) of the antenna assembly.

(60) The operations of **1204-1210** comprise: optionally measuring a signal frequency at a port of a communication relay to which the antenna assembly is coupled; obtaining first information comprising at least one of a value for a variable altitude of the antenna assembly, a value for a variable height of the antenna assembly above ground, a value for a variable height of the antenna assembly above sea level, a value for a variable distance of the antenna assembly from a reference object, and a first value for a variable signal frequency of a communication device; using the information to obtain a desired length of an antenna of the antenna assembly; and controlling an actuator (for example, components **508**, **510** of FIGS. **5-6**, components **700**, **702**, **704** of FIG. **7**, components **800**, **802** of FIG. **8**, and/or component **902** of FIG. **9**) to adjust a length of the antenna until the length reaches the desired length.

(61) In some scenarios, the desired length comprises a known last extended length of the antenna. The processor controls the actuator in **1210** to increase the length of the antenna to the known last extended length.

(62) In those or other scenarios, the antenna assembly is coupled to an unmanned aerial vehicle (for example, UAV **102** of FIG. **1**) such that an altitude of the antenna assembly varies along with changes in an altitude of the UAV. The processor may control the actuator in **1210** to: decrease the length of the antenna until the antenna reaches a retracted position when the value of the variable altitude of the antenna assembly is below a threshold altitude; and/or increase the length of the antenna until the antenna reaches an extended position when the value of the variable altitude of the antenna assembly is above a threshold altitude. The antenna resides entirely within a housing of the

antenna assembly when in the retracted position. The antenna at least partially extends out from a housing of the antenna assembly when in the extended position.

(63) The desired length may be obtained, for example, by converting the first value of the variable signal frequency to a first antenna length. In this case, method **1200** may also optionally comprise operations of **1212-1216**. The operations of **1212-1216** comprise: obtaining second information comprising a second value for the variable signal frequency that is different from the first value of the variable signal frequency; converting the second value for the variable signal frequency to a second antenna length different from the first antenna length; and controlling the actuator to adjust the length of the antenna until the length reaches the second antenna length.

(64) Subsequent to completing the operations of **1210** or **1216**, **1218** is performed where method **1200** ends or other operations are performed (for example, return to **1204**).

(65) In view of the forging, the present document also concerns an antenna assembly implementing the above-described methods. The antenna assembly comprises: an antenna with a variable length; an actuator coupled to the antenna; a processor coupled to the actuator; and a non-transitory computer-readable storage medium comprising programming instructions that are configured to cause the processor to implement a method for autonomously adjusting the variable length of the antenna. The programming instructions comprise instructions to: obtain first information comprising at least one of a value for a variable altitude of the antenna assembly, a value for a variable height of the antenna assembly above ground, a value for a variable height of the antenna assembly above sea level, a value for a variable distance of the antenna assembly from a reference object, and a first value for a variable signal frequency of a communication device; use the information to obtain a desired length of an antenna of the antenna assembly; and control the actuator to cause an adjustment of the variable length of the antenna until the variable length reaches the desired length.

(66) In some scenarios, the desired length comprises a known last extended length of the antenna. The programming instructions may also comprise instructions to control the actuator to cause an increase in the variable length of the antenna to the known last extended length.

(67) In those or other scenarios, the antenna assembly is coupled to an unmanned aerial vehicle such that an altitude of the antenna assembly varies along with changes in an altitude of the unmanned aerial vehicle.

(68) As such, the programming instructions may also comprise instructions to control the actuator to: cause a decrease in the length of the antenna until the antenna reaches a retracted position when the value of the variable altitude of the antenna assembly is below a threshold altitude; and/or cause an increase in the length of the antenna until the antenna reaches an extended position when the value of the variable altitude of the antenna assembly is above a threshold altitude. The antenna resides entirely within a housing of the antenna assembly when in the retracted position. The antenna at least partially extends out from a housing of the antenna assembly when in the extended position.

(69) In those or other scenarios, the antenna assembly also comprises a device configured to measure a signal frequency at a port of a communication relay when the antenna assembly is coupled to the communication relay. The desired length is obtained by converting the first value of the variable signal frequency to a first antenna length. The programming instructions may further comprise instructions to: obtain second information comprising a second value for the variable signal frequency that is different from the first value of the variable signal frequency; convert the second value for the variable signal frequency to a second antenna length different from the first antenna length; and control the actuator to cause an adjustment to the length of the antenna until the length reaches the second antenna length.

(70) The present document also concerns an unmanned aerial vehicle implementing the above-described methods. The unmanned aerial vehicle comprises a fuselage, avionic electronics disposed in the fuselage, a payload physical joined with the fuselage, and at least one power source

configured to supply power to the avionic electronics and payload. The payload comprises a communication relay and an antenna assembly coupled to the communication relay. The communication relay is configured to perform relay operations to extend a range between users of a communication relay link for voice and data communications. The antenna assembly comprises an antenna with a variable length, an actuator coupled to the antenna, a processor coupled to the actuator, and a non-transitory computer-readable storage medium comprising programming instructions that are configured to cause the processor to implement a method for autonomously adjusting the variable length of the antenna.

(71) The programming instructions comprise instructions to: obtain first information comprising at least one of a value for a variable altitude of the antenna assembly, a value for a variable height of the antenna assembly above ground, a value for a variable height of the antenna assembly above sea level, a value for a variable distance of the antenna assembly from a reference object, and a first value for a variable signal frequency of a communication device; use the information to obtain a desired length of an antenna of the antenna assembly; and control the actuator to cause an adjustment of the variable length of the antenna until the variable length reaches the desired length.

(72) In some scenarios, the desired length comprises a known last extended length of the antenna. The programming instructions also comprise instructions to control the actuator to cause an increase in the variable length of the antenna to the known last extended length.

(73) In those or other scenarios, the antenna assembly is coupled to an unmanned aerial vehicle such that an altitude of the antenna assembly varies along with changes in an altitude of the unmanned aerial vehicle.

(74) The programming instructions may also comprise instructions to control the actuator to: cause a decrease in the length of the antenna until the antenna reaches a retracted position when the value of the variable altitude of the antenna assembly is below a threshold altitude; and/or cause an increase in the length of the antenna until the antenna reaches an extended position when the value of the variable altitude of the antenna assembly is above a threshold altitude. The antenna resides entirely within a housing of the antenna assembly when in the retracted position. The antenna at least partially extends out from a housing of the antenna assembly when in the extended position.

(75) In those or other scenarios, the antenna assembly also comprises a device configured to measure a signal frequency at a radio frequency port of the communication. The desired length may be obtained by converting the first value of the variable signal frequency to a first antenna length.

(76) The programming instructions may further comprise instructions to: obtain second information comprising a second value for the variable signal frequency that is different from the first value of the variable signal frequency; convert the second value for the variable signal frequency to a second antenna length different from the first antenna length; and control the actuator to cause an adjustment to the length of the antenna until the length reaches the second antenna length.

(77) The described features, advantages and characteristics disclosed herein may be combined in any suitable manner. One skilled in the relevant art will recognize, in light of the description herein, that the disclosed systems and/or methods can be practiced without one or more of the specific features. In other instances, additional features and advantages may be recognized in certain scenarios that may not be present in all instances.

(78) As used in this document, the singular form “a”, “an”, and “the” include plural references unless the context clearly dictates otherwise. Unless defined otherwise, all technical and scientific terms used herein have the same meanings as commonly understood by one of ordinary skill in the art. As used in this document, the term “comprising” means “including, but not limited to”.

(79) Although the systems and methods have been illustrated and described with respect to one or more implementations, equivalent alterations and modifications will occur to others skilled in the art upon the reading and understanding of this specification and the annexed drawings. In addition, while a particular feature may have been disclosed with respect to only one of several implementations, such feature may be combined with one or more other features of the other

implementations as may be desired and advantageous for any given or particular application. Thus, the breadth and scope of the disclosure herein should not be limited by any of the above descriptions. Rather, the scope of the invention should be defined in accordance with the following claims and their equivalents.

## Claims

1. A method for autonomously operating an antenna assembly, comprising: obtaining, by a processor of the antenna assembly, first information comprising at least one of a value for a variable altitude of the antenna assembly, a value for a variable height of the antenna assembly above ground, and a value for a variable height of the antenna assembly above sea level; using, by the processor, the first information to obtain a desired length of an antenna of the antenna assembly; controlling, by the processor, an actuator to move while in frictional driving contact with the antenna; and using friction between a surface of the actuator and a surface of the antenna to cause the antenna to travel in a direction for adjusting a length of the antenna until the length reaches the desired length.
2. The method according to claim 1, wherein the desired length comprises a known last extended length of the antenna and the processor controls the actuator to increase the length of the antenna to the known last extended length.
3. The method according to claim 1, wherein the antenna assembly is coupled to an unmanned aerial vehicle such that an altitude of the antenna assembly varies along with changes in an altitude of the unmanned aerial vehicle.
4. The method according to claim 3, wherein the processor controls the actuator to decrease the length of the antenna until the antenna reaches a retracted position when the value of the variable altitude of the antenna assembly is below a threshold altitude, the antenna residing entirely within a housing of the antenna assembly when in the retracted position.
5. The method according to claim 3, wherein the processor controls the actuator to increase the length of the antenna until the antenna reaches an extended position when the value of the variable altitude of the antenna assembly is above a threshold altitude, the antenna at least partially extending out from a housing of the antenna assembly when in the extended position.
6. The method according to claim 1, further comprising measuring, by a component of the antenna assembly, a signal frequency at a port of a communication relay to which the antenna assembly is coupled.
7. The method according to claim 1, wherein the desired length is obtained by converting the first value of the variable signal frequency to a first antenna length.
8. The method according to claim 7, further comprising: obtaining, by the processor, second information comprising a second value for the variable signal frequency that is different from the first value of the variable signal frequency; converting, by the processor, the second value for the variable signal frequency to a second antenna length different from the first antenna length; and controlling, by the processor, the actuator to adjust the length of the antenna until the length reaches the second antenna length.
9. An antenna assembly, comprising: an antenna with a variable length; an actuator in frictional driving contact with the antenna; a processor coupled to the actuator; and a non-transitory computer-readable storage medium comprising programming instructions that are configured to cause the processor to implement a method for autonomously adjusting the variable length of the antenna, wherein the programming instructions comprise instructions to: obtain first information comprising at least one of a value for a variable altitude of the antenna assembly, a value for a variable height of the antenna assembly above ground, and a value for a variable height of the antenna assembly above sea level; use the first information to obtain a desired length of an antenna of the antenna assembly; and control the actuator to move while in frictional driving contact with

the antenna; wherein friction between a surface of the actuator and a surface of the antenna causes the antenna to travel in a direction so as to adjust the variable length of the antenna until the variable length reaches the desired length.

10. The antenna assembly according to claim 9, wherein the desired length comprises a known last extended length of the antenna and the programming instructions comprise instructions to control the actuator to cause an increase in the variable length of the antenna to the known last extended length.

11. The antenna assembly according to claim 9, wherein the antenna assembly is coupled to an unmanned aerial vehicle such that an altitude of the antenna assembly varies along with changes in an altitude of the unmanned aerial vehicle.

12. The antenna assembly according to claim 11, wherein the programming instructions further comprise instructions to control the actuator to cause a decrease in the length of the antenna until the antenna reaches a retracted position when the value of the variable altitude of the antenna assembly is below a threshold altitude, the antenna residing entirely within a housing of the antenna assembly when in the retracted position.

13. The antenna assembly according to claim 11, wherein the programming instructions further comprise instructions to control the actuator to cause an increase in the length of the antenna until the antenna reaches an extended position when the value of the variable altitude of the antenna assembly is above a threshold altitude, the antenna at least partially extending out from a housing of the antenna assembly when in the extended position.

14. The antenna assembly according to claim 9, further comprising a device configured to measure a signal frequency at a port of a communication relay when the antenna assembly is coupled to the communication relay.

15. The antenna assembly according to claim 9, wherein the desired length is obtained by converting the first value of the variable signal frequency to a first antenna length.

16. The antenna assembly according to claim 15, wherein the programming instructions further comprise instructions to: obtain second information comprising a second value for the variable signal frequency that is different from the first value of the variable signal frequency; convert the second value for the variable signal frequency to a second antenna length different from the first antenna length; and control the actuator to cause an adjustment to the length of the antenna until the length reaches the second antenna length.

17. The method according to claim 1, wherein the processor obtains the desired length of the antenna further using a value for a variable distance of the antenna assembly from a reference object, a first value for a variable signal frequency of a communication device, an air pressure of an external environment, and/or an antenna position.

18. An unmanned aerial vehicle, comprising: a fuselage; avionic electronics disposed in the fuselage; a payload physical joined with the fuselage and comprising a communication relay configured to perform relay operations to extend a range between users of a communication relay link for voice and data communications, and an antenna assembly coupled to the communication relay and comprising an antenna with a variable length, an actuator in frictional driving contact with the antenna, a processor coupled to the actuator, and a non-transitory computer-readable storage medium comprising programming instructions that are configured to cause the processor to implement a method for autonomously adjusting the variable length of the antenna, wherein the programming instructions comprise instructions to: obtain first information comprising at least one of a value for a variable altitude of the antenna assembly, a value for a variable height of the antenna assembly above ground, and a value for a variable height of the antenna assembly above sea level; use the first information to obtain a desired length of an antenna of the antenna assembly; and control the actuator to move while in frictional driving contact with the antenna; wherein friction between a surface of the actuator and a surface of the antenna causes the antenna to travel in a direction so as to adjust the variable length of the antenna until the variable length reaches the

desired length; at least one power source configured to supply power to the avionic electronics and payload.

19. The unmanned aerial vehicle according to claim 18, wherein the desired length comprises a known last extended length of the antenna and the programming instructions comprise instructions to control the actuator to cause an increase in the variable length of the antenna to the known last extended length.

20. The unmanned aerial vehicle according to claim 18, wherein the antenna assembly is coupled to an unmanned aerial vehicle such that an altitude of the antenna assembly varies along with changes in an altitude of the unmanned aerial vehicle.

21. The unmanned aerial vehicle according to claim 20, wherein the programming instructions further comprise instructions to control the actuator to cause a decrease in the length of the antenna until the antenna reaches a retracted position when the value of the variable altitude of the antenna assembly is below a threshold altitude, the antenna residing entirely within a housing of the antenna assembly when in the retracted position.

22. The unmanned aerial vehicle according to claim 20, wherein the programming instructions further comprise instructions to control the actuator to cause an increase in the length of the antenna until the antenna reaches an extended position when the value of the variable altitude of the antenna assembly is above a threshold altitude, the antenna at least partially extending out from a housing of the antenna assembly when in the extended position.

23. The unmanned aerial vehicle according to claim 18, wherein the antenna assembly further comprises a device configured to measure a signal frequency at a radio frequency port of the communication.

24. The unmanned aerial vehicle according to claim 18, wherein the desired length is obtained by converting the first value of the variable signal frequency to a first antenna length.

25. The unmanned aerial vehicle according to claim 24, wherein the programming instructions further comprise instructions to: obtain second information comprising a second value for the variable signal frequency that is different from the first value of the variable signal frequency; convert the second value for the variable signal frequency to a second antenna length different from the first antenna length; and control the actuator to cause an adjustment to the length of the antenna until the length reaches the second antenna length.

---