

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413198
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Inoue; Kazunori et al.

Acoustic wave device

Abstract

An acoustic wave device includes a support including a support substrate with a thickness in a first direction, a piezoelectric layer on the support in the first direction, and resonators each including a functional electrode on the piezoelectric layer in the first direction. The support includes first and second space portions at positions where the respective resonators at least partially overlap in plan view in the first direction, the second space portion with an area larger than an area of the first space portion in plan view in the first direction. The piezoelectric layer includes first and second through-holes respectively communicating with the first and second space portions, and the first through-hole has an area larger than an area of the second through-hole in plan view in the first direction.

Inventors: Inoue; Kazunori (Nagaokakyo, JP), Suzuki; Katsumi (Nagaokakyo, JP), Kimura; Tetsuya (Nagaokakyo, JP)

Applicant: Murata Manufacturing Co., Ltd. (Nagaokakyo, JP)

Family ID: 83459579

Assignee: MURATA MANUFACTURING CO., LTD. (Kyoto, JP)

Appl. No.: 18/370653

Filed: September 20, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240014795 A1	Jan. 11, 2024

Related U.S. Application Data

continuation parent-doc WO PCT/JP2022/016229 20220330 PENDING child-doc US 18370653
us-provisional-application US 63168338 20210331

Publication Classification

Int. Cl.: H03H9/02 (20060101); H03H9/205 (20060101)

U.S. Cl.:

CPC H03H9/02015 (20130101); H03H9/02086 (20130101); H03H9/205 (20130101);

Field of Classification Search

CPC: H03H (9/02015); H03H (9/02086); H03H (9/205); H03H (9/02157); H03H (9/174); H03H (9/564); H03H (9/568); H03H (9/02228)

USPC: 333/186; 333/187; 333/188; 333/193-196

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
10469053	12/2018	Omura	N/A	H03H 3/08
2011/0284995	12/2010	Kuypers et al.	N/A	N/A
2014/0009032	12/2013	Takahashi	29/25.35	H03H 9/02559
2014/0152145	12/2013	Kando	29/25.35	H03H 9/02574
2021/0091747	12/2020	Turner et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2012257019	12/2011	JP	N/A
2019009671	12/2018	JP	N/A
2019201305	12/2018	JP	N/A

OTHER PUBLICATIONS

International Search Report in PCT/JP2022/016229, mailed Jun. 28, 2022, 3 pages. cited by applicant

Written Opinion in PCT/JP2022/016229, mailed Jun. 28, 2022, 3 pages. cited by applicant

Primary Examiner: Salazar, Jr.; Jorge L

Attorney, Agent or Firm: Keating & Bennett, LLP

Background/Summary

CROSS REFERENCE TO RELATED APPLICATIONS (1) This application claims the benefit of priority to Provisional Application No. 63/168,338 filed on Mar. 31, 2021 and is a Continuation Application of PCT Application No. PCT/JP2022/016229 filed on Mar. 30, 2022. The entire contents of each application are hereby incorporated herein by reference.

BACKGROUND OF THE INVENTION

1. Field of the Invention

(1) The present disclosure relates to an acoustic wave device.

2. Description of the Related Art

(2) Japanese Unexamined Patent Application Publication No. 2012-257019 describes an acoustic wave device.

(3) In the acoustic wave device described in Japanese Unexamined Patent Application Publication No. 2012-257019, a through-hole communicating with a space portion may be provided in a piezoelectric layer as an etching hole to provide space portions having different areas. In the case above, there is a possibility that an etching liquid does not dry at a speed suitable for the size of the space portion, and sticking occurs in a large space portion and the etching liquid dries slowly in a small space portion.

SUMMARY OF THE INVENTION

(4) Preferred embodiments of the present invention simultaneously achieve reduction or prevention of sticking in a space portion and reduction of drying time.

(5) An acoustic wave device according to a preferred embodiment of the present invention includes a support including a support substrate with a thickness in a first direction, a piezoelectric layer on the support in the first direction, and resonators each including a functional electrode on the piezoelectric layer in the first direction. The support includes space portions at positions where the respective resonators at least partially overlap in plan view in the first direction, the space portions include a first space portion and a second space portion with an area larger than an area of the first space portion in plan view in the first direction, the piezoelectric layer includes a first through-hole communicating with the first space portion and a second through-hole communicating with the second space portion, and the first through-hole has an area larger than an area of the second through-hole in plan view in the first direction.

(6) According to preferred embodiments of the present invention, reduction or prevention of sticking in a space portion and reduction of a drying time is simultaneously achieved.

(7) The above and other elements, features, steps, characteristics and advantages of the present invention will become more apparent from the following detailed description of the preferred embodiments with reference to the attached drawings.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1A is a perspective view of an acoustic wave device of a first preferred embodiment of the present invention.

(2) FIG. 1B is a plan view of an electrode structure of the first preferred embodiment of the present invention.

(3) FIG. 2 is a sectional view of a portion taken along line II-II in FIG. 1A.

(4) FIG. 3A is a schematic sectional view for describing a Lamb wave propagating through a piezoelectric layer of a comparative example.

(5) FIG. 3B is a schematic sectional view for describing a bulk wave of a thickness-shear primary mode propagating through a piezoelectric layer of the first preferred embodiment of the present invention.

(6) FIG. 4 is a schematic sectional view for describing an amplitude direction of a bulk wave of a thickness-shear primary mode propagating through the piezoelectric layer of the first preferred embodiment of the present invention.

(7) FIG. 5 is a graph illustrating an example of a resonance characteristic of the acoustic wave device of the first preferred embodiment of the present invention.

(8) FIG. 6 is a graph illustrating a relationship between $d/2p$ and a fractional bandwidth as a resonator in the acoustic wave device of the first preferred embodiment, where p represents a

center-to-center distance or an average center-to-center distance between electrodes adjacent to each other and d represents an average thickness of a piezoelectric layer.

(9) FIG. 7 is a plan view of the acoustic wave device of the first preferred embodiment of the present invention illustrating an example in which a pair of electrodes is provided.

(10) FIG. 8 is a reference graph illustrating an example of a resonance characteristic of the acoustic wave device of the first preferred embodiment of the present invention.

(11) FIG. 9 is a chart illustrating a relationship between a fractional bandwidth and a phase rotation amount of impedance of a spurious component normalized by about 180 degrees as a magnitude of the spurious component, when a large number of acoustic wave resonators are included in the acoustic wave device of the first preferred embodiment of the present invention.

(12) FIG. 10 is a chart illustrating a relationship between $d/2p$, a metallization ratio MR, and a fractional bandwidth.

(13) FIG. 11 is a chart illustrating a map of a fractional bandwidth relative to Euler angles (0° , θ , ψ) of LiNbO₃ when d/p is as close to 0 as possible.

(14) FIG. 12 is a partially cutaway perspective view for describing an acoustic wave device according to another preferred embodiment of the present invention.

(15) FIG. 13 is a sectional view for describing the acoustic wave device according to the other preferred embodiment of the present invention.

(16) FIG. 14 is a plan view of the acoustic wave device according to the first preferred embodiment of the present invention illustrating an example thereof.

(17) FIG. 15 is a sectional view taken along line XV-XV in FIG. 14.

(18) FIG. 16 is a circuit diagram of the acoustic wave device according to the first preferred embodiment of the present invention in FIG. 14.

(19) FIG. 17 is a plan view of the acoustic wave device according to the first preferred embodiment of the present invention illustrating a portion of a first modification thereof.

(20) FIG. 18 is a plan view of the acoustic wave device according to the first preferred embodiment of the present invention illustrating a portion of a second modification thereof.

(21) FIG. 19 is a sectional view of the acoustic wave device according to the first preferred embodiment of the present invention illustrating a third modification thereof.

(22) FIG. 20 is a sectional view of the acoustic wave device according to the first preferred embodiment of the present invention illustrating a fourth modification thereof.

(23) FIG. 21 is a sectional view of the acoustic wave device according to the first preferred embodiment of the present invention illustrating a fifth modification thereof.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

(24) Hereinafter, preferred embodiments of the present invention will be described in detail with reference to the drawings. The present disclosure is not limited to the preferred embodiments. Each preferred embodiment described in the present disclosure is exemplary, and in different preferred embodiments, such as modifications thereof in which partial replacement or combination of configurations is possible and the subsequent preferred embodiments and modifications, a description of matters common to the first preferred embodiment will be omitted and only differences will be described. In particular, the same or similar advantageous operational effects obtained by the same or similar configurations will not be described in each preferred embodiment.

First Preferred Embodiment

(25) FIG. 1A is a perspective view of an acoustic wave device of a first preferred embodiment of the present invention. FIG. 1B is a plan view of an electrode structure of the first preferred embodiment.

(26) An acoustic wave device 1 of the first preferred embodiment includes a piezoelectric layer 2 made of, for example, LiNbO₃. The piezoelectric layer 2 may be made of, for example, LiTaO₃. A cut angle of each of LiNbO₃ and LiTaO₃ is a Z-cut in the first preferred embodiment. The cut angle of LiNbO₃ or LiTaO₃ may be a rotated Y-cut or an X-cut.

Preferably, the propagation orientation of Y-propagation and X-propagation of about $\pm 30^\circ$ is preferred.

(27) A thickness of the piezoelectric layer **2** is not particularly limited, but is preferably, for example, about 50 nm or more and about 1000 nm or less in order to effectively excite a thickness-shear primary mode.

(28) The piezoelectric layer **2** includes a first main surface **2a** and a second main surface **2b** opposed to each other in a Z-direction. An electrode finger **3** and an electrode finger **4** are provided on the first main surface **2a**.

(29) Here, the electrode finger **3** is an example of a “first electrode finger”, and the electrode finger **4** is an example of a “second electrode finger”. In FIGS. **1A** and **1B**, electrode fingers **3** are the “first electrode fingers” connected to a first busbar electrode **5**. Electrode fingers **4** are the “second electrode fingers” connected to a second busbar electrode **6**. The electrode fingers **3** and the electrode fingers **4** are interdigitated with each other. As a result, an interdigital transducer (IDT) electrode including the electrode finger **3**, the electrode finger **4**, the first busbar electrode **5**, and the second busbar electrode **6** is provided.

(30) Each of the electrode finger **3** and the electrode finger **4** has a rectangular or substantially rectangular shape and a length direction. In a direction orthogonal or substantially orthogonal to the length direction, the electrode finger **3** and the electrode finger **4** adjacent to the electrode finger **3** face each other. Both of the length direction of the electrode fingers **3** and **4**, and a direction orthogonal or substantially orthogonal to the length direction of the electrode fingers **3** and **4** are directions intersecting a thickness direction of the piezoelectric layer **2**. Therefore, it can be said that the electrode finger **3** and the electrode finger **4** adjacent to the electrode finger **3** face each other in the direction intersecting the thickness direction of the piezoelectric layer **2**. In the following description, the thickness direction of the piezoelectric layer **2** may be referred to as the Z-direction (or a first direction), the length direction of the electrode fingers **3** and **4** may be referred to as a Y-direction (or a second direction), and a direction orthogonal to the length direction of the electrode fingers **3** and **4** may be referred to as an X-direction (or a third direction).

(31) Further, the length direction of the electrode fingers **3** and **4** may be replaced with the direction orthogonal or substantially orthogonal to the length direction of the electrode fingers **3** and **4** illustrated in FIGS. **1A** and **1B**. That is, the electrode fingers **3** and **4** may extend in a direction in which the first busbar electrode **5** and the second busbar electrode **6** extend in FIGS. **1A** and **1B**. In the case above, the first busbar electrode **5** and the second busbar electrode **6** extend in a direction in which the electrode fingers **3** and **4** extend in FIGS. **1A** and **1B**. A structure of a pair in which the electrode finger **3** connected to one electric potential and the electrode finger **4** connected to the other electric potential are adjacent to each other is configured, and multiple pairs are provided in the direction orthogonal or substantially orthogonal to the length direction of the electrode fingers **3** and **4**.

(32) Here, the electrode finger **3** and the electrode finger **4** being adjacent to each other does not refer to a case that the electrode finger **3** and the electrode finger **4** are disposed to be in direct contact with each other, but refers to a case that the electrode finger **3** and the electrode finger **4** are disposed with a gap therebetween. Further, when the electrode finger **3** and the electrode finger **4** are adjacent to each other, an electrode connected to a hot electrode or a ground electrode including other electrode fingers **3** and **4** is not disposed between the electrode finger **3** and the electrode finger **4**. The number of pairs need not be integer pairs, but may be 1.5 pairs, 2.5 pairs, or the like.

(33) A center-to-center distance between the electrode fingers **3** and **4**, that is, a pitch is preferably, for example, in a range of about 1 μm or more and about 10 μm or less. Further, the center-to-center distance between the electrode fingers **3** and **4** is a distance connecting a center of a width dimension of the electrode finger **3** in a direction orthogonal or substantially orthogonal to the length direction of the electrode finger **3** and a center of a width dimension of the electrode finger **4** in a direction orthogonal or substantially orthogonal to the length direction of the electrode finger

4.

(34) Furthermore, when at least one of the electrode finger **3** and the electrode finger **4** includes multiple electrode fingers (in a case that 1.5 or more of electrode pairs are present when the electrode fingers **3** and **4** are defined as an electrode pair), the center-to-center distance between the electrode fingers **3** and **4** refers to an average value of the respective center-to-center distances between the electrode fingers **3** and **4** adjacent to each other out of 1.5 or more pairs of the electrode fingers **3** and **4**.

(35) A width of each of the electrode fingers **3** and **4**, that is, a dimension of each of the electrode fingers **3** and **4** in a facing direction is preferably, for example, in a range of about 150 nm or more and about 1000 nm or less. The center-to-center distance between the electrode fingers **3** and **4** is a distance connecting a center of a dimension (width dimension) of the electrode finger **3** in the direction orthogonal or substantially orthogonal to the length direction of the electrode finger **3** and a center of a dimension (width dimension) of the electrode finger **4** in the direction orthogonal to the length direction of the electrode finger **4**.

(36) In the first preferred embodiment, since the Z-cut piezoelectric layer is used, the direction orthogonal or substantially orthogonal to the length direction of the electrode fingers **3** and **4** is a direction orthogonal or substantially orthogonal to a polarization direction of the piezoelectric layer **2**. This is not the case when a piezoelectric body with another cut angle is used for the piezoelectric layer **2**. Here, “orthogonal” is not limited to strictly orthogonal but may be substantially orthogonal (an angle formed by the direction orthogonal to the length direction of the electrode fingers **3** and **4**, and the polarization direction may be about $90^\circ \pm 10^\circ$, for example).

(37) A support substrate **8** is laminated on the piezoelectric layer **2** on a second main surface **2b** side with a dielectric layer **7** interposed therebetween. The dielectric layer **7** and the support substrate **8** each have a frame shape, and include openings **7a** and **8a**, respectively, as illustrated in FIG. 2. Thus, a space portion (air gap) **9** is provided.

(38) The space portion **9** is provided so as not to disturb vibration of an excitation region C of the piezoelectric layer **2**. Therefore, the support substrate **8** is laminated on the second main surface **2b** with the dielectric layer **7** interposed therebetween at a position not overlapping a portion where at least one pair of the electrode fingers **3** and **4** is provided. The dielectric layer **7** is not necessarily provided. Therefore, the support substrate **8** may directly or indirectly be laminated on the second main surface **2b** of the piezoelectric layer **2**.

(39) The dielectric layer **7** is made of, for example, silicon oxide. The dielectric layer **7** may be made of an appropriate insulation material such as, for example, silicon nitride or alumina in addition to silicon oxide.

(40) The support substrate **8** is made of, for example, Si. A plane orientation of a surface of Si on the piezoelectric layer **2** side may be (100), (110), or (111). Preferably, high-resistance Si having resistivity of, for example, about 4 k Ω or more is preferable. However, the support substrate **8** as well may be made using an appropriate insulation material or semiconductor material. Examples of the material of the support substrate **8** include piezoelectric materials such as aluminum oxide, lithium tantalate, lithium niobate, and quartz; various ceramics such as alumina, magnesia, sapphire, silicon nitride, aluminum nitride, silicon carbide, zirconia, cordierite, mullite, steatite, and forsterite; dielectrics such as diamond and glass; and semiconductors such as gallium nitride.

(41) The electrode fingers **3** and **4**, the first busbar electrode **5**, and the second busbar electrode **6** are made of an appropriate metal or an alloy such as, for example, Al and an AlCu alloy. In the first preferred embodiment, the electrode fingers **3** and **4**, the first busbar electrode **5**, and the second busbar electrode **6** each have a structure in which, for example, an Al film is laminated on a Ti film. An adhesion layer other than the Ti film may be used.

(42) At the time of driving, an AC voltage is applied between the electrode fingers **3** and the electrode fingers **4**. More specifically, an AC voltage is applied between the first busbar electrode **5** and the second busbar electrode **6**. It is said that resonance characteristics using a bulk wave of a

thickness-shear primary mode excited in the piezoelectric layer **2** may be obtained by the operation described above.

(43) Further, in the acoustic wave device **1**, d/p is, for example, about 0.5 or less when d represents the thickness of the piezoelectric layer **2** and p represents a center-to-center distance between any electrode fingers **3** and **4** adjacent to each other out of multiple pairs of the electrode fingers **3** and **4**. Therefore, a bulk wave of a thickness-shear primary mode is effectively excited, and good resonance characteristics may be obtained. More preferably, d/p is, for example, about 0.24 or less, and further good resonance characteristics may be obtained in that case.

(44) In a case that at least one of the electrode fingers **3** and **4** includes multiple electrode fingers as in the first preferred embodiment, that is, in a case that 1.5 or more pairs of electrode fingers **3** and **4** are present when the electrode fingers **3** and **4** are defined as an electrode pair, the center-to-center distance p between the electrode fingers **3** and **4** adjacent to each other is an average distance of the respective center-to-center distances between the electrode fingers **3** and **4** adjacent to each other.

(45) Since the acoustic wave device **1** according to the first preferred embodiment has the above-described configuration, even when the number of pairs of the electrode fingers **3** and **4** is decreased in order to reduce in size, a Q factor is less likely to be reduced. This is because a resonator does not require reflectors on both sides and has small propagation loss. Further, the reason why the reflectors are not required is that a bulk wave of a thickness-shear primary mode is used.

(46) FIG. 3A is a schematic sectional view for describing a Lamb wave propagating through a piezoelectric layer of a comparative example. FIG. 3B is a schematic sectional view for describing a bulk wave of a thickness-shear primary mode propagating through a piezoelectric layer of the first preferred embodiment. FIG. 4 is a schematic sectional view for describing an amplitude direction of a bulk wave of a thickness-shear primary mode propagating through the piezoelectric layer of the first preferred embodiment.

(47) As illustrated in FIG. 3A, a Lamb wave propagates through a piezoelectric layer in an acoustic wave device as described in Japanese Unexamined Patent Application Publication No. 2012-257019. A wave propagates through a piezoelectric layer **201** as described by an arrow as illustrated in FIG. 3A. Here, the piezoelectric layer **201** has a first main surface **201a** and a second main surface **201b**, and a thickness direction connecting the first main surface **201a** and the second main surface **201b** is the Z-direction. The X-direction is a direction in which the electrode fingers **3** and **4** of the IDT electrode are arranged. In the Lamb wave, a wave propagates in the X-direction as illustrated in FIG. 3A. Because of a plate wave, the wave propagates in the X-direction although the entire piezoelectric layer **201** vibrates, and reflectors are disposed on both sides to obtain resonance characteristics. Propagation loss of the wave occurs as a result, and when the size is reduced, that is, when the number of pairs of the electrode fingers **3** and **4** is decreased, the Q factor lowers.

(48) Meanwhile, since a vibration displacement is in a thickness-shear direction in the acoustic wave device of the first preferred embodiment as illustrated in FIG. 3B, the wave substantially propagates in a direction connecting the first main surface **2a** and the second main surface **2b** of the piezoelectric layer **2**, that is, the Z-direction, and resonates. That is, an X-direction component of a wave is significantly smaller than a Z-direction component. Since resonance characteristics are obtained by the propagation of a wave in the Z-direction, reflectors are not required. As a result, propagation loss does not occur when a wave propagates to the reflectors. Therefore, even when the number of electrode pairs constituted of the electrode fingers **3** and **4** is decreased in order to reduce in size, the Q factor is less likely to be reduced.

(49) The amplitude direction of a bulk wave of a thickness-shear primary mode in a first region **251** included in the excitation region C (see FIG. 1B) is opposite to the amplitude direction thereof in a second region **252** included in the excitation region C of the piezoelectric layer **2** as illustrated in

FIG. 4. FIG. 4 schematically illustrates a bulk wave when a voltage is applied between the electrode fingers 3 and 4 such that the electrode finger 4 has a higher electric potential than the electrode finger 3. The first region 251 is a region of the excitation region C between the first main surface 2a and a virtual plane VP1 that is orthogonal or substantially orthogonal to the thickness direction of the piezoelectric layer 2 and divides the piezoelectric layer 2 into two. The second region 252 is a region of the excitation region C between the virtual plane VP1 and the second main surface 2b.

(50) In the acoustic wave device 1, at least one pair of electrodes including the electrode fingers 3 and 4 is provided. However, a wave is not intended to propagate in the X-direction. Thus, the number of electrode pairs of the electrode fingers 3 and 4 does not necessarily need to include multiple pairs. That is, at least one pair of electrodes needs to be provided.

(51) For example, the electrode finger 3 is an electrode connected to a hot electric potential, and the electrode finger 4 is an electrode connected to a ground electric potential. However, the electrode finger 3 may be connected to the ground electric potential and the electrode finger 4 may be connected to the hot electric potential. In the first preferred embodiment, at least one pair of electrodes is an electrode connected to the hot electric potential or an electrode connected to the ground electric potential as described above, and a floating electrode is not provided.

(52) FIG. 5 is a graph illustrating an example of a resonance characteristic of the acoustic wave device of the first preferred embodiment. Design parameters of the acoustic wave device 1 having the resonance characteristics in FIG. 5 are as follows. Piezoelectric layer 2: LiNbO₃ with Euler angles (0°, 0°, 90°) Thickness of piezoelectric layer 2: about 400 nm Length of excitation region C (see FIG. 1B): about 40 μm Number of pairs of electrodes constituted of electrode fingers 3 and 4: 21 pairs Center-to-center distance (pitch) between electrode fingers 3 and 4: about 3 μm Width of each of electrode fingers 3 and 4: about 500 nm d/p: about 0.133 Dielectric layer 7: silicon oxide film of about 1 μm thickness Support substrate 8: Si

(53) The excitation region C (see FIG. 1B) is a region where the electrode fingers 3 and 4 overlap each other when viewed in the X-direction orthogonal or substantially orthogonal to the length direction of the electrode fingers 3 and 4. The length of the excitation region C is a dimension of the excitation region C in the length direction of the electrode fingers 3 and 4. Here, the excitation region C is an example of an “intersecting region”.

(54) In the first preferred embodiment, inter-electrode distances of the electrode pairs each including the electrode fingers 3 and 4 are set to be equal or substantially equal in all the pairs. That is, the electrode fingers 3 and 4 are arranged with equal or substantially equal pitches.

(55) As is apparent from FIG. 5, good resonance characteristics with a fractional bandwidth of, for example, about 12.5% are obtained even though no reflector is provided.

(56) In the first preferred embodiment, d/p is, for example, about 0.5 or less, more preferably about 0.24 or less when d represents the thickness of the piezoelectric layer 2 and p represents the center-to-center distance between electrodes of the electrode fingers 3 and 4. This will be explained with reference to FIG. 6.

(57) Multiple acoustic wave devices were obtained in the same manner as the acoustic wave device having the resonance characteristics illustrated in FIG. 5, except that d/2p was changed. FIG. 6 is a graph illustrating a relationship between d/2p and a fractional bandwidth as a resonator in the acoustic wave device of the first preferred embodiment, where p represents a center-to-center distance or an average center-to-center distance between electrodes adjacent to each other and d represents an average thickness of the piezoelectric layer 2.

(58) As illustrated in FIG. 6, when d/2p exceeds, for example, about 0.25, that is, when d/p > about 0.5, the fractional bandwidth is less than about 5% even when d/p is adjusted. Meanwhile, when d/2p about 0.25, that is d/p ≤ about 0.5, the fractional bandwidth may be set to about 5% or more by changing d/p within that range, that is, a resonator having a high coupling coefficient may be provided. When d/2p is, for example, about 0.12 or less, that is, d/p is about 0.24 or less, the

fractional bandwidth may be increased to about 7% or more. Further, when d/p is adjusted within that range, a resonator having an even wider fractional bandwidth may be obtained, that is, a resonator having an even higher coupling coefficient may be achieved. Therefore, it is understood that a resonator having a high coupling coefficient using the above-described bulk wave of a thickness-shear primary mode may be provided by setting d/p to about 0.5 or less, for example.

(59) The at least one pair of electrodes may be one pair, and in a case of one pair of electrodes, the above-described p is the center-to-center distance between the electrode fingers **3** and **4** adjacent to each other. Further, in a case of 1.5 or more pairs of electrodes, the average center-to-center distance between the electrode fingers **3** and **4** adjacent to each other is set to p .

(60) Furthermore, as for the thickness d of the piezoelectric layer **2**, when the piezoelectric layer **2** has variations in thickness, a value obtained by averaging the thicknesses is used.

(61) FIG. **7** is a plan view of the acoustic wave device of the first preferred embodiment illustrating an example in which a pair of electrodes is provided. In an acoustic wave device **101**, a pair of electrodes including electrode fingers **3** and **4** is provided on the first main surface **2a** of the piezoelectric layer **2**. K in FIG. **7** is an intersecting width. As described above, in the acoustic wave device of the present preferred embodiment, the number of pairs of electrodes may be one. In the case above as well, when d/p is, for example, about 0.5 or less, a bulk wave of a thickness-shear primary mode may effectively be excited.

(62) In the acoustic wave device **1**, it is preferable that the metallization ratio MR satisfies, for example, $MR \text{ about } 1.75 (d/p) + 0.075$ in the electrode fingers **3** and **4**. The metallization ratio MR is a ratio of the electrode fingers **3** and **4** adjacent to each other to the excitation region C being a region where any electrode fingers **3** and **4** adjacent to each other overlap each other when viewed in the facing direction. In the case above, the spurious component may be effectively reduced. This will be explained with reference to FIG. **8** and FIG. **9**.

(63) FIG. **8** is a reference graph illustrating an example of a resonance characteristic of the acoustic wave device of the first preferred embodiment. A spurious component indicated by an arrow B appears between a resonant frequency and an anti-resonant frequency. Note that $d/p = \text{about } 0.08$, and Euler angles of LiNbO_3 were set to $(0^\circ, 0^\circ, 90^\circ)$. Further, the metallization ratio MR was set to about 0.35, for example.

(64) The metallization ratio MR is explained with reference to FIG. **1B**. When attention is paid to one pair of the electrode fingers **3** and **4** in an electrode structure in FIG. **1B**, it is assumed that only the one pair of the electrode fingers **3** and **4** is provided. In the case above, a portion surrounded by a dashed-and-dotted line is the excitation region C . The excitation region C is a region of the electrode finger **3** overlapping the electrode finger **4**, a region of the electrode finger **4** overlapping the electrode finger **3**, and a region where the electrode finger **3** and the electrode finger **4** overlap each other in a region between the electrode fingers **3** and **4**, when the electrode fingers **3** and **4** are viewed in the direction orthogonal or substantially orthogonal to the length direction of the electrode fingers **3** and **4**, that is, in the facing direction. An area of the electrode fingers **3** and **4** in the excitation region C relative to an area of the excitation region C is the metallization ratio MR . That is, the metallization ratio MR is a ratio of the area of a metallization portion to the area of the excitation region C .

(65) When multiple pairs of electrode fingers **3** and **4** are provided, MR may be defined as a ratio of the metallization portion included in the entire excitation region C to the total area of the excitation region C .

(66) FIG. **9** is a chart illustrating a relationship between a fractional bandwidth and a phase rotation amount of impedance of a spurious component normalized by about 180 degrees as a magnitude of the spurious component, when a large number of acoustic wave resonators are included in the acoustic wave device of the first preferred embodiment. The fractional bandwidth was adjusted by variously changing the thickness of the piezoelectric layer **2** and dimensions of the electrode fingers **3** and **4**. Further, although the results obtained by using the piezoelectric layer **2** made of the

Z-cut LiNbO₃ are illustrated in FIG. 9, the same tendency is obtained when the piezoelectric layer 2 having another cut angle is used.

(67) In a region surrounded by an ellipse J in FIG. 9, the spurious component is as large as about 1.0, for example. As is apparent from FIG. 9, when the fractional bandwidth exceeds 0.17, that is, when the fractional bandwidth exceeds about 17%, a large spurious component having a spurious level of about 1 or more appears in a pass band even when the parameters constituting the fractional bandwidth are changed. That is, as in the resonance characteristics illustrated in FIG. 8, a large spurious component indicated by the arrow B appears in the band. Therefore, the fractional bandwidth is preferably, for example, about 17% or less. In the case above, the spurious component may be reduced by adjusting the thickness of the piezoelectric layer 2, the dimensions of the electrode fingers 3 and 4, and the like.

(68) FIG. 10 is a chart illustrating a relationship between $d/2p$, metallization ratio MR, and a fractional bandwidth. In the acoustic wave device 1 of the first preferred embodiment, various acoustic wave devices 1 having different $d/2p$ and different MR were provided, and the fractional bandwidth was measured. A hatched portion on the right side of a broken line D in FIG. 10 is a region where the fractional bandwidth is, for example, about 17% or less. The boundary between the hatched region and the non-hatched region is represented by, for example, $MR \approx 3.5(d/2p) + 0.075$. That is, $MR \approx 1.75(d/p) + 0.075$. Therefore, MR about $1.75(d/p) + 0.075$ is preferable. In the case above, the fractional bandwidth is likely to be about 17% or less. The region on the right side of $MR \approx 3.5(d/2p) + 0.05$ indicated by the dashed-and-dotted line D1 in FIG. 10 is more preferable. That is, when MR about $1.75(d/p) + 0.05$, the fractional bandwidth may reliably be set to about 17% or less.

(69) FIG. 11 is a chart illustrating a map of a fractional bandwidth relative to Euler angles (0° , θ , ψ) of LiNbO₃ when d/p is as close to 0 as possible. A hatched portion in FIG. 11 is a region where a fractional bandwidth of at least about 5% or more is obtained. When the range of the region is approximated, the range is expressed by formula (1), formula (2), and formula (3) below.

($0^\circ \pm 10^\circ, 0^\circ$ to 20° , any ψ) Formula (1)

($0^\circ \pm 10^\circ, 20^\circ$ to $80^\circ, 0^\circ$ to $60^\circ(1 - (\theta - 50)^{\sup.2/900})^{\sup.1/2}$) or ($0^\circ \pm 10^\circ, 20^\circ$ to $80^\circ, [180^\circ - 60^\circ(1 - (\theta - 50)^{\sup.2/900})^{\sup.1/2}]$ to 180°) Formula (2)

($0^\circ \pm 10^\circ, [180^\circ - 30^\circ(1 - (\psi - 90)^{\sup.2/8100})^{\sup.1/2}]$ to 180° , any ψ) Formula (3)

(70) Therefore, in a case that Euler angles are in the range of formula (1), formula (2) or formula (3) described above, the fractional bandwidth may preferably sufficiently be widened.

(71) FIG. 12 is a partially cutaway perspective view for describing an acoustic wave device according to a preferred embodiment of the present invention. An outer peripheral edge of the space portion 9 is indicated by a broken line in FIG. 12. The acoustic wave device of the present preferred embodiment may use a plate wave. In the case above, an acoustic wave device 301 includes reflectors 310 and 311 as illustrated in FIG. 12. The reflectors 310 and 311 are provided on both sides of the electrode fingers 3 and 4 of the piezoelectric layer 2 in an acoustic wave propagation direction. A Lamb wave as a plate wave is excited by applying an AC voltage to the electrode fingers 3 and 4 above the space portion 9 in the acoustic wave device 301. At this time, since the reflectors 310 and 311 are provided on both sides, resonance characteristics by a Lamb wave as a plate wave may be obtained.

(72) As described above, in the acoustic wave devices 1 and 101, a bulk wave of a thickness-shear primary mode is used. Further, in the acoustic wave devices 1 and 101, the first electrode finger 3 and the second electrode finger 4 are electrodes adjacent to each other, and d/p is, for example, about 0.5 or less when d represents the thickness of the piezoelectric layer 2 and p represents the center-to-center distance between the first electrode finger 3 and the second electrode finger 4. As a result, even when an acoustic wave device is reduced in size, the Q factor may be higher.

(73) In the acoustic wave devices 1 and 101, the piezoelectric layer 2 is made of, for example, lithium niobate or lithium tantalate. On the first main surface 2a or the second main surface 2b of

the piezoelectric layer **2**, the first electrode finger **3** and the second electrode finger **4** facing each other in a direction intersecting the thickness direction of the piezoelectric layer **2** are provided, and the first electrode finger **3** and the second electrode finger **4** are preferably covered with a protection film.

(74) FIG. **13** is a sectional view for describing the acoustic wave device according to a preferred embodiment of the present invention. The acoustic wave device of the present preferred embodiment may be a device using a bulk wave as illustrated in FIG. **13**, that is, a bulk acoustic wave (BAW) element. In the case above, an acoustic wave device **401** includes functional electrodes **410** and **411**. The functional electrodes **410** and **411** are electrodes provided on both sides in the thickness direction of the piezoelectric layer **2**. In the example of FIG. **13**, the support substrate **8** includes a space portion **9** on the piezoelectric layer **2** side, and the functional electrode **411** is provided in the space portion **9**.

(75) In the example of FIG. **13**, a through-hole **11** is provided in the piezoelectric layer **2**. The through-hole **11** is a hole extending through the piezoelectric layer **2** in the Z-direction. The through-hole **11** communicates with the space portion **9**. Providing the through-hole **11** in the piezoelectric layer **2** makes it possible to etch a sacrificial layer provided in the space portion **9** in advance before bonding, by pouring an etching liquid from the through-hole **11** after bonding the piezoelectric layer **2** to the support substrate **8**.

(76) FIG. **14** is a plan view of an example of the acoustic wave device according to the first preferred embodiment. FIG. **15** is a sectional view taken along line XV-XV in FIG. **14**. As illustrated in FIG. **14** and FIG. **15**, an acoustic wave device **500** according to the first preferred embodiment includes multiple resonators **501A** to **501G**. The acoustic wave device **500** includes a support **520**, a piezoelectric layer **502**, wiring electrodes **512A** to **512C**, an input terminal **513**, an output terminal **514**, and grounds **515A** and **515B**.

(77) The piezoelectric layer **502** is provided on the support **520**. The piezoelectric layer **502** includes a first main surface **502a** and a second main surface **502b**. In the present preferred embodiment, the first main surface **502a** is a surface on which the resonators **501A** to **501F** and the wiring electrodes **512A** to **512C** are provided. Meanwhile, the second main surface **502b** is a surface on which the support **520** is provided. A material of the piezoelectric layer **502** may include, for example, lithium niobate (LiNbO₃) or lithium tantalate (LiTaO₃) and an impurity.

(78) The support **520** includes a support substrate **521** and a dielectric layer **522** as illustrated in FIG. **15**. A material of the support substrate **521** is silicon, for example. The dielectric layer **522** is provided on the support substrate **521** on a piezoelectric layer **502** side. A material of the dielectric layer **522** is silicon oxide, for example.

(79) Each of the resonators **501A** to **501F** includes a functional electrode and a portion of a multilayer body at least partially overlapping the functional electrode in plan view in the Z-direction. Here, the functional electrode refers to an IDT electrode including a first electrode finger, a second electrode finger, a first busbar electrode, and a second busbar electrode. Further, the multilayer body includes a portion of the piezoelectric layer **502** and a portion of the support **520**. Hereinafter, the resonators **501A** and **501C** may be referred to as a first resonator, and the resonators **501B** and **501D** may be referred to as a second resonator.

(80) In the present preferred embodiment, the resonators **501A** and **501B** include electrode fingers **503A** and **503B** as the first and second electrode fingers of the functional electrodes. That is, the electrode fingers **503A** and **503B** correspond to the first electrode finger and the second electrode finger of the resonators **501A** and **501B**, respectively. The electrode fingers **503A** and **503B** each have a length direction in the Y-direction. End portions in the Y-direction are connected to the first busbar electrode and the second busbar electrode.

(81) An electrode area of the resonator **501A** is larger than an electrode area of the resonator **501B**, and an electrode area of the resonator **501C** is smaller than an electrode area of the resonator **501D**.

Here, the electrode area of each of the resonators **501A** to **501D** refers to an area of each of intersecting regions **C1** to **C4** in which multiple first and second electrode fingers of the resonators overlap each other when viewed in a direction in which the electrode fingers are arranged. That is, the area of the intersecting region **C1** of the resonator **501A** is larger than the area of the intersecting region **C2** of the resonator **501B**, and the area of the intersecting region **C3** of the resonator **501C** is smaller than the area of the intersecting region **C4** of the resonator **501D**.

(82) The wiring electrodes **512A** to **512C** are wiring lines to electrically connect the resonators **501A** to **501F**. The wiring electrodes **512A** to **512D** are provided on the piezoelectric layer **502**. The wiring electrodes **512A** to **512D** are electrically connected to the busbar electrodes of the resonators **501A** to **501F**.

(83) FIG. **16** is a circuit diagram of the acoustic wave device according to the first preferred embodiment illustrated in FIG. **14**. As illustrated in FIG. **16**, the acoustic wave device **500** is a ladder filter including a series arm resonator, inserted in series in a signal path from the input terminal **513** to the output terminal **514**, and a parallel arm resonator, inserted in a path between the signal path and the ground. In FIG. **16**, the series arm resonators are resonators **501A**, **501E**, and **501C**. In each of the resonators **501A**, **501E**, and **501C** which are series arm resonators, one terminal is electrically connected to the input terminal **513** and the other terminal is electrically connected to the output terminal **514**. Here, the resonators **501A**, **501E** and **501C** are electrically connected in series. Meanwhile, the parallel arm resonators are resonators **501B**, **501F**, **501D**, and **501G** in FIG. **16**. In the resonator **501B**, one terminal is electrically connected to the input terminal **513** via the wiring electrode **512A**, and the other terminal is electrically connected to the ground **515A**. In the resonator **501F**, one terminal is electrically connected to the wiring electrode **512B** connecting the resonator **501A** and the resonator **501E**, and the other terminal is electrically connected to the ground **515A**. In the resonator **501D**, one terminal is electrically connected to the wiring electrode **512C** connecting the resonator **501E** and the resonator **501C**, and the other terminal is electrically connected to the ground **515B**. In the resonator **501G**, one terminal is electrically connected to the output terminal **514** via the wiring electrode **512D**, and the other terminal is electrically connected to the ground **515B**.

(84) In the acoustic wave device **500** according to the present preferred embodiment, the first resonators **501A** and **501C** are not limited to series arm resonators, and the second resonators **501B** and **501D** are not limited to parallel arm resonators. For example, the first resonators **501A** and **501C** may be parallel arm resonators, and the second resonators **501B** and **501D** may be series arm resonators. Further, the acoustic wave device **500** may include a resonator for transmission and a resonator for reception. In the case above, the first resonators **501A** and **501C** may be resonators for transmission, and the second resonators **501B** and **501D** may be resonators for reception. Further, the first resonators **501A** and **501C** may be resonators for reception, and the second resonators **501B** and **501D** may be resonators for transmission.

(85) Here, the resonators **501A** to **501D** respectively include space portions **509A** to **509D** and extended portions **510A** to **510D** provided to the support **520** being a portion of a multilayer body on the piezoelectric layer **502** side. For example, the space portion **509A** and the extended portion **510A** are provided to the support **520** being a portion of the multilayer body of the resonator **501A** on the piezoelectric layer **502** side.

(86) The space portions **509A** to **509D** are cavities provided to the support **520** on the piezoelectric layer **502** side. The space portions **509A** to **509D** are provided at respective positions at least partially overlapping the functional electrode of the resonators **501A** to **501D** in plan view in the Z-direction. That is, each of the resonators **501A** to **501D** includes a corresponding one of the space portions **509A** to **509D** in the support **520** of the multilayer body. Here, the space portions **509A** and **509C** are an example of a “first space portion”, and the space portions **509B** and **509D** are an example of a “second space portion”.

(87) An area of the space portion **509A** in plan view in the Z-direction is smaller than an area of the

space portion **509B** in plan view in the Z-direction. In the example of FIG. **15**, a length $Cw1$ of the space portion **509A** in the X-direction is smaller than a length $Cw2$ of the space portion **509B** in the X-direction. As a result, since the resonator **501A** having the electrode area larger than the resonator **501B** includes the space portion **509A** having the area smaller than the space portion **509B**, a heat dissipation property may be improved.

(88) In the example of FIG. **14**, an area of the space portion **509C** in plan view in the Z-direction is smaller than an area of the space portion **509D** in plan view in the Z-direction. As a result, since the resonator **501D** having the electrode area larger than the resonator **501C** includes the space portion **509D** having the area larger than the space portion **509C**, the excitation space may be easily secured.

(89) The space portion **509A** and the space portion **509B**, or the space portion **509C** and the space portion **509D** may have different depths, that is, different lengths in the Z-direction. For example, the depths of the second space portions **509B** and **509D** having a large area in plan view in the Z-direction may be deeper than the depths of the first space portions **509A** and **509C** having a small area in plan view in the Z-direction.

(90) The extended portions **510A** to **510D** are cavities provided to the support **520** on the piezoelectric layer **502** side. The extended portions **510A** to **510D** are provided at respective positions not overlapping the space portions **509A** to **509D** in plan view in the Z-direction. The extended portions **510A** to **510D** communicate with the space portions **509A** to **509D**, respectively. In the example of FIG. **14**, the extended portions **510A** to **510D** are provided so as to communicate with the respective space portions **509A** to **509D** on both sides in the X-direction. Hereinafter, the extended portions **510A** and **510C** may be described as a first extended portion, and the extended portions **510B** and **510D** may be described as a second extended portion.

(91) Through-holes **511A** to **511D** which are holes extending through in the Z-direction are provided to the piezoelectric layer **502**. The through-holes **511A** to **511D** are provided so as to overlap the respective extended portions **510A** to **510D** in plan view in the Z-direction. That is, the through-holes **511A** to **511D** respectively communicate with the extended portions **510A** to **510D** in the Z-direction. Here, the through-holes **511A** and **511C** are an example of a “first through-hole”, and the through-holes **511B** and **511D** are an example of a “second through-hole”.

(92) An area of each of the first through-holes **511A** and **511C** is larger than an area of each of the second through-holes **511B** and **511D**. Here, an area of a through-hole refers to the total sum of areas occupied by openings of the through-holes provided to the piezoelectric layer **502** in plan view in the Z-direction. For example, since two through-holes **511A** are provided in the piezoelectric layer **502** in the example of FIG. **14**, the area of the through-hole **511A** is the sum of the areas occupied by the openings of the two through-holes in plan view in the Z-direction. In the example illustrated in FIG. **15**, a width $Ew1$ of the first through-hole **511A** in the X-direction is larger than a width $Ew2$ of the second through-hole **511B**. Here, a width of a through-hole refers to a length of an opening of one through-hole in the X-direction.

(93) Here, in the manufacturing process of the acoustic wave device **500**, sticking, being a phenomenon in which the piezoelectric layer **502** is bent and sticks to an inner wall of a space portion due to surface tensions, is likely to occur when the liquid in the space portion is dried during etching, since the second space portions **509B** and **509D** each have a large area. The second space portions **509B** and **509D** according to the present preferred embodiment respectively communicate with the second through-holes **511B** and **511D** having a small area. As a result, the evaporation of the liquid in the second space portions **509B** and **509D** through the second through-holes **511B** and **511D** may be slow, and the inside of the second space portions **509B** and **509D** may be dried slowly. Therefore, the occurrence of sticking may be reduced or prevented.

(94) Meanwhile, in the manufacturing process of the acoustic wave device **500**, the sticking is less likely to occur in the first space portions **509A** and **509C**, having a small area, when the liquid in the space portion is dried during etching. The first space portions **509A** and **509C** according to the

present preferred embodiment respectively communicate with the first through-holes **511A** and **511C** having a large area. As a result, the evaporation of the liquid in the first space portions **509A** and **509C** through the first through-holes **511A** and **511C** may be promoted, and the inside of the first space portions **509A** and **509C** may be dried rapidly. Therefore, manufacturing efficiency may be improved.

(95) The acoustic wave device according to the present preferred embodiment is not limited to the acoustic wave device **500** illustrated in FIG. **14**. Hereinafter, modifications of the acoustic wave device according to the present preferred embodiment will be described with reference to the drawings. The same or corresponding components are denoted by the same reference signs, and a description thereof will be omitted.

(96) FIG. **17** is a plan view of the acoustic wave device according to the first preferred embodiment illustrating a portion of a first modification thereof. FIG. **18** is a plan view of the acoustic wave device according to the first preferred embodiment illustrating a portion of a second modification thereof. As illustrated in FIG. **17** and FIG. **18**, the first through-hole **511A** and the second through-hole **511B** may include openings with the same or substantially the same area in plan view in the Z-direction, and the width $Ew1$ of the first through-hole and the width $Ew2$ of the second through-hole may be equal or substantially equal to each other. In the case above, the number of first through-holes **511A** is greater than the number of second through-holes **511B**.

(97) In an acoustic wave device **500A** according to the first modification, three first through-holes **511AA** are provided so as to communicate with the first space portion **509A**, and two second through-holes **511BA** are provided so as to communicate with the second space portion **509B**. Here, two first through-holes **511AA** are provided on one side of the first space portion **509A** in the X-direction. As a result, sticking in the second space portion **509B** may be reduced or prevented and the drying time of the first space portion **509A** may be shortened in manufacturing the acoustic wave device **500A**, since an area of the first through-hole **511AA** is larger than an area of the second through-hole **511BA**.

(98) In an acoustic wave device **500B** according to the second modification, two first through-holes **511AB** are provided so as to communicate with the first space portion **509A**, and one second through-hole **511BB** is provided so as to communicate with the second space portion **509B**. Here, the second through-hole **511BB** is provided only on one side of the second space portion **509B** in the X-direction. As a result, sticking in the second space portion **509B** may be reduced or prevented and the drying time of the first space portion **509A** may be shortened in manufacturing the acoustic wave device **500B**, since an area of the first through-hole **511AB** is larger than an area of the second through-hole **511BB**.

(99) FIG. **19** is a sectional view of the acoustic wave device according to the first preferred embodiment illustrating a third modification thereof. FIG. **20** is a sectional view of the acoustic wave device according to the first preferred embodiment illustrating a fourth modification thereof. FIG. **21** is a sectional view of the acoustic wave device according to the first preferred embodiment illustrating a fifth modification thereof. Here, FIG. **19** to FIG. **21** are sectional views of the acoustic wave device according to respective modifications corresponding to FIG. **15**. As illustrated in FIG. **19** to FIG. **21**, the configuration of the support **520** is not limited to the configuration illustrated in FIG. **15**.

(100) In an acoustic wave device **500C** according to the third modification, a first space portion **509AC**, a second space portion **509BC**, a first extended portion **510AC**, and a second extended portion **510BC** are provided to a dielectric layer **522C** on the piezoelectric layer **502** side in the Z-direction as illustrated in FIG. **19**. In the case above as well, the sticking in the second space portion **509BC** may be reduced or prevented, and the drying time of the first space portion **509AC** may be shortened in manufacturing the acoustic wave device **500C**.

(101) In an acoustic wave device **500D** according to the fourth modification, a first space portion **509AD** and a second space portion **509BD** are provided to a support substrate **521D** on the

piezoelectric layer **502** side in the Z-direction as illustrated in FIG. **20**. Further, a first extended portion **510AD** and a second extended portion **510BD** are provided to a support **520D** so as to extend through a dielectric layer **522D** in the Z-direction. In the case above as well, the sticking in the second space portion **509BD** may be reduced or prevented and the drying time of the first space portion **509AD** may be shortened in manufacturing the acoustic wave device **500D**.

(102) In the acoustic wave device **500E** according to the fifth modification, the support is only a support substrate **521E** as illustrated in FIG. **21**. In the case above, a first space portion **509AE**, a second space portion **509BE**, a first extended portion **510AE**, and a second extended portion **510BE** are provided on a support substrate **521E** on the piezoelectric layer **502** side in the Z-direction. In the case above as well, the sticking in the second space portion **509BE** may be reduced or prevented and the drying time of the first space portion **509AE** may be shortened in manufacturing the acoustic wave device **500E**.

(103) As described above, the acoustic wave device **500** according to the first preferred embodiment includes the support **520** including the support substrate **521** having a thickness in the first direction, the piezoelectric layer **502** provided on the support **520** in the first direction, and the resonators **501A** to **501G** each having a functional electrode provided on the piezoelectric layer **502** in the first direction. The support **520** includes the space portions **509A** to **509D** at positions where the respective resonators at least partially overlap in plan view in the first direction, and the space portions **509A** to **509D** include the first space portions **509A** and **509C** and the second space portions **509B** and **509D** having an area larger than an area of the first space portions **509A** and **509C** in plan view in the first direction. The piezoelectric layer **502** includes the first through-holes **511A** and **511C** communicating with the first space portions **509A** and **509C**, and the second through-holes **511B** and **511D** communicating with the second space portions **509B** and **509D**. The first through-holes **511A** and **511C** have an area larger than an area of the second through-holes **511B** and **511D** in plan view in the first direction.

(104) As a result, the inside of the second space portions **509B** and **509D** may be dried slowly in manufacturing of the acoustic wave device **500** since the second space portions **509B** and **509D** having a large area communicate with the second through-holes **511B** and **511D** having a small area, and thus, the sticking may be prevented. Meanwhile, the inside of the first space portions **509A** and **509C** may be dried quickly in manufacturing the acoustic wave device **500** since the first space portions **509A** and **509C** having a small area communicate with the first through-holes **511A** and **511C** having a large area, and thus, the drying time may be shortened. Therefore, reduction or prevention of the sticking in the space portion and reduction of the drying time may simultaneously be achieved.

(105) Further, an area of the resonator **501B** overlapping the second space portion **509B** in plan view in the first direction may be larger than an area of the resonator **501A** overlapping the first space portion **509A**. In the case above, since the resonator **501A** includes the first space portion **509A** having the area smaller than the area of the second space portion **509B**, the resonator **501A** may improve the heat dissipation property.

(106) Further, an area of the resonator **501C** overlapping the first space portion **509C** in plan view in the first direction may be larger than an area of the resonator **501D** overlapping the second space portion **509D**. In the case above, since the resonator **501D** includes the second space portion **509D** having the area larger than the area of the first space portion **509C**, the resonator **501D** may easily secure the excitation space.

(107) Further, the resonators **501A** and **501C** overlapping the first space portions **509A** and **509C** and the resonators **501B** and **501D** overlapping the second space portions **509B** and **509D** in plan view in the first direction may be either series arm resonators or parallel arm resonators. In the case above as well, reduction or prevention of the sticking in the space portion and reduction of the drying time may simultaneously be achieved.

(108) Further, the resonators **501A** and **501C** overlapping the first space portions **509A** and **509C**

and the resonators **501B** and **501D** overlapping the second space portions **509B** and **509D** in plan view in the first direction may be either reception resonators or transmission resonators. In the case above as well, reduction or prevention of the sticking in the space portion and reduction of the drying time may simultaneously be achieved.

(109) Preferably, the support **520** includes the extended portion **510A** communicating with at least one space portion **509A** out of the space portions **509A** and **509B** at a position not overlapping at least the one space portion **509A** in plan view in the first direction, and the piezoelectric layer **502** includes the through-hole **511A** extending through the piezoelectric layer **502** at a position overlapping the extended portion **510A** in plan view in the first direction. In the case above as well, reduction or prevention of the sticking in the space portion and reduction of the drying time may simultaneously be achieved.

(110) Preferably, the support **520** includes the dielectric layer **522**, and the dielectric layer **522** includes at least one of the space portions **509A** to **509D**. As a result, an acoustic wave device capable of obtaining good resonance characteristics may be provided.

(111) Preferably, the functional electrode includes one or more first electrode fingers extending in a second direction intersecting the first direction, and one or more second electrode fingers extending in the second direction and facing any of the one or more first electrode fingers in a third direction orthogonal or substantially orthogonal to the second direction. As a result, an acoustic wave device capable of obtaining good resonance characteristics may be provided.

(112) Preferably, the thickness of the piezoelectric layer **2** is, for example, about $2p$ or less where p represents the center-to-center distance between the first electrode finger **3** and the second electrode finger **4** adjacent to each other out of the first electrode fingers **3** and the second electrode fingers **4**. As a result, the acoustic wave device **1** may be reduced in size, and the Q factor may be higher.

(113) Preferably, the piezoelectric layer **2** includes, for example, lithium niobate or lithium tantalate. As a result, an acoustic wave device capable of obtaining good resonance characteristics may be provided.

(114) Preferably, Euler angles (φ , θ , ψ) of lithium niobate or lithium tantalate forming the piezoelectric layer **2** are in a range of formula (1), formula (2), or formula (3) below. In the case above, the fractional bandwidth may sufficiently be widened.

$(0^\circ \pm 10^\circ, 0^\circ \text{ to } 20^\circ, \text{any } \psi)$ Formula (1)

$(0^\circ \pm 10^\circ, 20^\circ \text{ to } 80^\circ, 0^\circ \text{ to } 60^\circ (1 - (\theta - 50) \cdot \sup.2/900) \cdot \sup.1/2) \text{ or } (0^\circ \pm 10^\circ, 20^\circ \text{ to } 80^\circ, [180^\circ - 60^\circ (1 - (\theta - 50) \cdot \sup.2/900) \cdot \sup.1/2] \text{ to } 180^\circ)$ Formula (2)

$(0^\circ \pm 10^\circ, [180^\circ - 30^\circ (1 - (\psi - 90) \cdot \sup.2/8100) \cdot \sup.1/2] \text{ to } 180^\circ, \text{any } \psi)$ Formula (3)

(115) Preferably, the acoustic wave device is configured to be capable of using a bulk wave in a thickness-shear mode. As a result, a coupling coefficient is increased, and it is possible to provide an acoustic wave device in which good resonance characteristics are obtained.

(116) Preferably, for example, d/p is about 0.5 or less where d represents the thickness of the piezoelectric layer **2**, and p represents the center-to-center distance between the first electrode finger **3** and second electrode finger **4** adjacent to each other. As a result, the acoustic wave device **1** may be reduced in size, and the Q factor may be higher.

(117) More preferably, d/p is, for example, about 0.24 or less. As a result, the acoustic wave device **1** may be reduced in size, and the Q factor may be higher.

(118) Preferably, $MR \leq \text{about } 1.75 (d/p) + 0.075$ is satisfied where MR represents a metallization ratio of the electrode fingers **3** and **4** to the excitation region C being a region where electrode fingers **3** and **4** adjacent to each other overlap each other in the facing direction. In the case above, the fractional bandwidth may reliably be set to about 17% or less.

(119) Preferably, the acoustic wave device it is structured to use a plate wave. As a result, an acoustic wave device capable of obtaining good resonance characteristics may be provided.

(120) While preferred embodiments of the present invention have been described above, it is to be understood that variations and modifications will be apparent to those skilled in the art without

departing from the scope and spirit of the present invention. The scope of the present invention, therefore, is to be determined solely by the following claims.

Claims

1. An acoustic wave device, comprising: a support including a support substrate with a thickness in a first direction; a piezoelectric layer on the support in the first direction; and resonators each including a functional electrode on the piezoelectric layer in the first direction; wherein the support includes space portions at positions where the respective resonators at least partially overlap in plan view in the first direction; the space portions include a first space portion and a second space portion with an area larger than an area of the first space portion in plan view in the first direction; the piezoelectric layer includes a first through-hole communicating with the first space portion and a second through-hole communicating with the second space portion; and the first through-hole has an area larger than an area of the second through-hole in plan view in the first direction.
2. The acoustic wave device according to claim 1, wherein an area of a resonator of the resonators overlapping the second space portion in plan view in the first direction is larger than an area of a resonator of the resonators overlapping the first space portion.
3. The acoustic wave device according to claim 1, wherein an area of a resonator of the resonators overlapping the first space portion in plan view in the first direction is larger than an area of a resonator of the resonators overlapping the second space portion.
4. The acoustic wave device according to claim 1, wherein a resonator of the resonators overlapping the first space portion and a resonator of the resonators overlapping the second space portion in plan view in the first direction are either a series arm resonator or a parallel arm resonator.
5. The acoustic wave device according to claim 1, wherein a resonator of the resonators overlapping the first space portion and a resonator of the resonators overlapping the second space portion in plan view in the first direction are either a reception resonator or a transmission resonator.
6. The acoustic wave device according to claim 1, wherein the support includes an extended portion communicating with at least one of the space portions at a position not overlapping the at least one of the space portions in plan view in the first direction; and the piezoelectric layer includes a through-hole extending through the piezoelectric layer at a position overlapping the extended portion in plan view in the first direction.
7. The acoustic wave device according to claim 1, wherein the support includes a dielectric layer; and the dielectric layer includes at least one of the space portions.
8. The acoustic wave device according to claim 1, wherein the functional electrode includes one or more first electrode fingers extending in a second direction intersecting the first direction, and one or more second electrode fingers extending in the second direction and facing any of the one or more first electrode fingers in a third direction orthogonal or substantially orthogonal to the second direction.
9. The acoustic wave device according to claim 8, wherein a thickness of the piezoelectric layer is about $2p$ or less, where p represents a center-to-center distance between the first electrode finger and the second electrode finger adjacent to each other of the one or more first electrode fingers and the one or more second electrode fingers.
10. The acoustic wave device according to claim 9, wherein the center-to-center distance between the first electrode finger and the second electrode finger adjacent to each other is in a range of about $1\text{ }\mu\text{m}$ or more and about $10\text{ }\mu\text{m}$ or less.
11. The acoustic wave device according to claim 8, wherein the piezoelectric layer includes lithium niobate or lithium tantalate.
12. The acoustic wave device according to claim 11, wherein Euler angles (ϕ , θ , ψ) of the lithium

niobate or the lithium tantalate are in a range of formula (1), formula (2), or formula (3):

$(0^\circ \pm 10^\circ, 0^\circ \text{ to } 20^\circ, \text{any } \psi)$ Formula (1);

$(0^\circ \pm 10^\circ, 20^\circ \text{ to } 80^\circ, 0^\circ \text{ to } 60^\circ(1-(\theta-50).sup.2/900).sup.1/2)$ or $(0^\circ \pm 10^\circ, 20^\circ \text{ to } 80^\circ, [180^\circ-60^\circ(1-(\theta-50).sup.2/900).sup.1/2] \text{ to } 180^\circ)$ Formula (2); and

$(0^\circ \pm 10^\circ, [180^\circ-30^\circ(1-(\psi-90).sup.2/8100).sup.1/2] \text{ to } 180^\circ, \text{any } \psi)$ Formula (3).

13. The acoustic wave device according to claim 8, wherein the acoustic wave device is structured to generate a bulk wave in a thickness-shear mode.

14. The acoustic wave device according to claim 13, wherein $d/p \leq \text{about } 0.5$ is satisfied, where d represents a thickness of the piezoelectric layer, and p represents a center-to-center distance between the first electrode finger and the second electrode finger adjacent to each other of the one or more first electrode fingers and the one or more second electrode fingers.

15. The acoustic wave device according to claim 14, wherein d/p is about 0.24 or less.

16. The acoustic wave device according to claim 8, wherein a width of each of the one or more first electrode fingers and the one or more second electrode fingers is in a range of about 150 nm or more and about 1000 nm or less.

17. The acoustic wave device according to claim 1, wherein the functional electrode includes an upper electrode and a lower electrode with the piezoelectric layer interposed therebetween in the first direction.

18. The acoustic wave device according to claim 1, wherein a thickness of the piezoelectric layer is about 50 nm or more and about 1000 nm or less.

19. The acoustic wave device according to claim 1, wherein the functional electrode includes one or more first electrode fingers extending in a second direction intersecting the first direction and one or more second electrode fingers extending in the second direction and facing any of the one or more first electrode fingers in a third direction orthogonal or substantially orthogonal to the second direction; and $MR \leq \text{about } 1.75(d/p) + 0.075$ is satisfied, where MR represents a metallization ratio of the one or more first electrode fingers and the one or more second electrode fingers to an excitation region being a region where the first electrode finger and the second electrode finger adjacent to each other overlap each other when viewed in a direction in which the first electrode finger and the second electrode finger adjacent to each other face each other.

20. The acoustic wave device according to claim 1, wherein the acoustic wave device is structured to generate a plate wave.
