

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12388270
Kind Code	B2
Date of Patent	August 12, 2025
Inventor(s)	Woll; Christoph et al.

Method for operating an electrical energy store, electrical energy store and device

Abstract

A method for operating an electrical energy store, which includes at least two electrical energy store modules connected in parallel and a connector. It is initially queried which electrical energy store modules are operational. A first voltage of an operational electrical energy store module is then determined, which is greater than or equal to the voltage of all operational electrical energy store modules. Those operational electrical energy store modules are then selected, whose voltage is within a voltage range below the first voltage. The selected electrical energy store modules are then electroconductively connected to the connector.

Inventors:	Woll; Christoph (Gerlingen, DE), Handte; Gunther (Unterensingen, DE)
Applicant:	Robert Bosch GmbH (Stuttgart, DE)
Family ID:	70681804
Assignee:	ROBERT BOSCH GMBH (Stuttgart, DE)
Appl. No.:	17/614721
Filed (or PCT Filed):	May 07, 2020
PCT No.:	PCT/EP2020/062701
PCT Pub. No.:	WO2020/244880
PCT Pub. Date:	December 10, 2020

Prior Publication Data

Document Identifier	Publication Date
US 20220231517 A1	Jul. 21, 2022

Foreign Application Priority Data

DE

10 2019 208 042.1

Jun. 03, 2019

Publication Classification

Int. Cl.: **H02J7/00** (20060101); **B60L58/22** (20190101); **G01R31/3835** (20190101); **H01M10/42** (20060101); **H01M10/48** (20060101); **H01M50/512** (20210101); **B60L50/60** (20190101); **B60L58/24** (20190101); **B60R16/033** (20060101)

U.S. Cl.:

CPC **H02J7/0013** (20130101); **B60L58/22** (20190201); **G01R31/3835** (20190101); **H01M10/425** (20130101); **H01M10/482** (20130101); **H01M50/512** (20210101); **H02J7/0048** (20200101); **B60L50/60** (20190201); **B60L58/24** (20190201); **B60R16/033** (20130101); **H01M2010/4271** (20130101)

Field of Classification Search

CPC: G01R (31/3835); B60L (58/22); H02J (7/0013); H02J (7/0025); H02J (7/0048); H01M (50/512); H01M (10/425); H01M (10/482)

USPC: 320/126

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5592067	12/1996	Peter	320/118	H02J 7/0018
5869950	12/1998	Hoffman, Jr. et al.	N/A	N/A
6137262	12/1999	Hauer	320/132	H02J 7/00047
6404165	12/2001	Shinpo	320/124	B60L 58/10
6420852	12/2001	Sato	320/134	H01M 10/482
7417405	12/2007	Carrier	320/116	H01M 10/4257
7564216	12/2008	Carrier	320/116	H01M 10/4257
9415699	12/2015	Morioka	N/A	H01M 10/482
9543767	12/2016	Wada	N/A	B60L 58/12
9620969	12/2016	Kobayashi	N/A	H02J 7/0016
9722435	12/2016	Park	N/A	H02J 7/0014
9748777	12/2016	Owen	N/A	B60L 50/51
9849803	12/2016	Morioka	N/A	B60L 58/13
9899856	12/2017	Lee	N/A	H02J 7/34
9960611	12/2017	Toya	N/A	H02J 7/0048
10224739	12/2018	Kaag	N/A	H01M 10/441
10263434	12/2018	Miyamoto	N/A	H01M 10/441
10270265	12/2018	Owen	N/A	B60L 3/04
10297877	12/2018	Kagawa	N/A	H02J 7/0048
10491007	12/2018	Kim	N/A	H02J 7/0018
10576840	12/2019	Naidu	N/A	B60L 58/21

11133677	12/2020	Tabuchi	N/A	H02J 7/34
11865925	12/2023	Weber	N/A	B60L 7/10
11888334	12/2023	Sergott	N/A	H02J 7/0013
2002/0070707	12/2001	Sato	320/134	H01M 10/482
2006/0071643	12/2005	Carrier	320/132	H01M 10/4257
2008/0185995	12/2007	Carrier	320/134	H02J 7/0048
2008/0272739	12/2007	Carrier	320/134	H02J 7/0014
2012/0133333	12/2011	Morioka	320/134	H02J 7/0049
2013/0169038	12/2012	King	307/66	H02J 7/0031
2015/0002095	12/2014	Wada	320/112	H02J 7/0013
2015/0048794	12/2014	Park	320/118	H02J 7/345
2015/0194707	12/2014	Park	429/61	H01M 10/425
2015/0229140	12/2014	Kim	320/118	H02J 7/0016
2015/0280466	12/2014	Owen	320/137	B60L 50/51
2015/0314701	12/2014	Morioka	320/134	H02J 7/0049
2015/0357843	12/2014	Kobayashi	320/118	H02J 7/0016
2016/0043578	12/2015	Miyamoto	320/118	H01M 10/482
2016/0156220	12/2015	Kaag	307/20	H05B 47/165
2016/0190821	12/2015	Lee	320/134	H02J 7/007
2017/0117721	12/2016	Toya	N/A	H02J 7/0016
2017/0141588	12/2016	Kim	N/A	H02J 7/0018
2017/0317508	12/2016	Owen	N/A	B60L 3/04
2017/0373355	12/2016	Kagawa	N/A	H02J 7/0048
2018/0029588	12/2017	Naidu	N/A	B60L 58/10
2020/0373760	12/2019	Tabuchi	N/A	H02J 7/35
2022/0131388	12/2021	Sergott	N/A	H02J 3/32
2022/0250478	12/2021	Weber	N/A	B60L 50/60
2023/0050505	12/2022	Magadi	N/A	B60L 58/16
2024/0088691	12/2023	Chung	N/A	H02J 7/007182

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
203103992	12/2012	CN	N/A
106329640	12/2017	CN	H02J 7/0014
102018108041	12/2018	DE	H01M 10/441
2463981	12/2011	EP	N/A

OTHER PUBLICATIONS

International Search Report for PCT/EP2020/062701 Issued Jun. 24, 2020. cited by applicant

Primary Examiner: Trischler; John T

Attorney, Agent or Firm: NORTON ROSE FULBRIGHT US LLP

Background/Summary

FIELD

(1) The present invention relates to a method for operating an electrical energy store, to an electrical energy store and to a device, in particular a vehicle.

BACKGROUND INFORMATION

(2) U.S. Patent Application Publication No. 2013/0169038 shows a device for the uninterrupted power supply of an electric vehicle from serially interconnected batteries, which includes a bridging switch.

(3) China Patent Publication No. CN 203103992 U shows a control system for a battery charging management and battery discharging management.

SUMMARY

(4) In accordance with an example embodiment of the present invention, in a method for operating an electrical energy store which includes at least two electrical energy store modules connected in parallel and a connection means (i.e., connector), it is initially queried which electrical energy store modules are operational, a first voltage of an operational electrical energy store module then being determined, which is greater than or equal to voltage U of all operational electrical energy store modules, those operational electrical energy store modules then being selected, whose voltage is within a voltage range below the first voltage, the selected electrical energy store modules then being electroconductively connected to the connection means.

(5) With the aid of the method of the example embodiment of the present invention, it is possible to put into operation electrical energy store modules of an electrical energy store, which have various charge states and/or various voltages and/or various points in time of operational readiness.

(6) The electrical energy store in this case is advantageously switched on with reduced power as compared to its maximum power and the power of the electrical energy store is gradually increased during the method by connecting further electrical energy store modules. The voltage range includes the voltage of the operational electrical energy store module having the maximum first voltage. As a result, the number of the connected electrical energy store modules may be maximized during the method, since the voltage of the electrical energy store modules decreases during discharge.

(7) Further advantageous specific embodiments of the present invention are disclosed herein.

(8) According to one advantageous embodiment of the present invention, if not all electrical energy store modules have been connected to the connection means of the electrical energy store, it is queried again at a later point in time during the operation of the electrical energy store which electrical energy store modules are operational and that electrical energy store module is selected, whose voltage is within the voltage range below a mean voltage of the electrical energy store module electrically connected to the connection means, and is electroconductively connected to the connection means. Thus, electrical energy store modules, which were not yet operable or whose voltage was too low at the start of the method, are connected at a later point in time and thus the available power of the electrical energy store is increased during the method.

(9) In this case, it is advantageous if the aforementioned method steps are repeated until all electrical energy store modules are electroconductively connected to the connection means or the electrical energy store is switched off, the method steps being repeated, in particular, temporally recurrently, in particular, periodically. In this way, further electrical energy store modules may be connected in the course of the method during the operation of the electrical energy store.

(10) It is further advantageous if the number of electrical energy store modules connected to the connection means remains constant if the voltage of a non-operable electrical energy store module is greater than the mean voltage and less than the sum of the mean voltage and of half the voltage range, until this electrical energy store module becomes operational, whereupon it is connected to the connection means, or until the voltage of this electrical energy store module is greater than the sum of the mean voltage and of half the voltage range. Thus, an electrical energy store module, which only later becomes operational and has a high voltage, may still also be put into operation. In this case, it is important that a voltage limiting value is not exceeded, in order to limit the compensating currents between the electrical energy store modules and to thereby protect the switching means (i.e., switch).

- (11) It is advantageous in this case if an electrical energy store module, whose voltage is greater than the mean voltage, in particular, greater than the sum of the mean voltage and of half the voltage range, is not electroconductively connected to the connection means, if it becomes operational during the method, in particular, during the entire method. This prevents the switching means from being overloaded during the connection of this electrical energy store module by excessively high compensating currents between the electrical energy store modules.
- (12) When switching off the electrical energy store, all electrical energy store modules are advantageously separated from the connection means. In this case, it is advantageous that the connection means of the electrical energy store is voltage-free after the electrical energy store is switched off.
- (13) It is further advantageous if the expansion of the voltage range is a function of the electrical energy store, in particular, of switching means of the electrical energy store and/or is constant during the method.
- (14) An electrical energy store module is advantageously operational if its temperature and/or its voltage is/are below a maximum limiting value and/or above a minimum limiting value.
- (15) In accordance with the present invention, in the electrical energy store including connection means and at least two electrical energy store modules, which are connected in parallel, the electrical energy store is configured to be operated with the aid of a method as described above or as further disclosed herein.
- (16) In accordance with the present invention, the electrical energy store modules may have various charge states and points in time of operational readiness. The electrical energy store may be put into operation with a subset of the electrical energy store modules, the available power of the electrical energy store being increasable.
- (17) According to one advantageous embodiment of the present invention, the electrical energy store includes a control unit, each electrical energy store module including at least one sensor, in particular, one voltage sensor and/or one temperature sensor, and a switching means for electroconductively connecting the respective electrical energy store module to the connection means of the electrical energy store, the control unit being configured to evaluate signals of the sensors and to activate the switching means. It is advantageous in this case that a central control unit is configured to control the method.
- (18) The electrical energy store modules are advantageously designed to be interchangeable. The electrical energy store may, for example, include electrical energy store modules that are variously aged.
- (19) In accordance with an example embodiment of the present invention, in the case of the device, in particular, the vehicle, the device includes an electrical energy store as described above and as disclosed hereinafter relating to the electrical energy store.
- (20) In accordance with an example embodiment of the present invention, the availability of the device may be improved by being able to connect individual electrical energy store modules in succession and/or in that electrical energy store modules are interchangeable.
- (21) The above embodiments and refinements may, if meaningful, be arbitrarily combined with one another. Further possible embodiments, refinements and implementations of the present invention also include not explicitly mentioned combinations of features of the present invention described previously or below with respect to the exemplary embodiments. Those skilled in the art will, in particular, also add individual aspects as improvements on or additions to the respective basic form of the present invention, in view of the disclosure herein.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) Below, the present invention is explained with reference to exemplary embodiments, from which further inventive features may result which, however, do not limit the scope of the present invention. The exemplary embodiments are represented in the figures.
- (2) FIG. 1 shows a representation of voltage U and the operational readiness of various electrical energy store modules M1, M2, M3, M4, M5, M6, M7, M8, M9, M10 of an electrical energy store according to an example embodiment of the present invention at a first point in time t1.
- (3) FIG. 2 shows a representation of voltage U and the operational readiness of electrical energy store modules M1, . . . M10 of the electrical energy store at a second point in time t2.
- (4) FIG. 3 shows a representation of voltage U and of the operational readiness of various electrical energy store modules M1, . . . M10 of the electrical energy store at a third point in time t3.
- (5) FIG. 4 schematically shows a flowchart of method 100 according to an example embodiment of the present invention for operating an electrical energy store.
- (6) FIG. 5 illustrates a schematic representation of an electrical energy store according to an example embodiment of the present invention.

DETAILED DESCRIPTION OF EXAMPLE EMBODIMENTS

- (7) The electrical energy store according to the present invention includes a plurality of electrical energy store modules M1, . . . M10, which are connected in parallel, two connection means (i.e., connectors) and a control unit. Each electrical energy store module M1, . . . M10 includes at least one sensor, in particular, one voltage sensor and/or one temperature sensor, and switching means (i.e., switch) for electroconductively connecting respective energy store module M1, . . . M10 to the connection means of the electrical energy store. The control unit is configured to evaluate signals of the sensor and to activate the switching means.
- (8) The voltages of various electrical energy store modules M1, . . . M10, in this exemplary embodiment ten electrical energy store modules M1, . . . M10 at a first point in time t1 are represented in FIG. 1. In this case, voltage U of an operational electrical energy store module M1, . . . M10 is represented with the aid of a white bar and voltage U of a non-operational electrical energy store module M1, . . . M10 is represented with the aid of a hatched bar.
- (9) First point in time t1 is temporally prior to the start-up of the electrical energy store.
- (10) At first point in time t1, electrical energy store modules M1, . . . M10 have different voltages. Seven electrical energy store modules M1, M3, M4, M5, M7, M8, M10 are operational. Three further electrical energy store modules M2, M6, M9 are not operational.
- (11) A first electrical energy store module M1 has a first voltage U1, which is greater than the voltages of other electrical energy store modules M2, . . . M10 of the electrical energy store. The electrical energy store has a voltage range ΔU , within which electrical energy store modules M1, . . . M10 having various voltages U may be put into operation. Those electrical energy store modules M1, . . . M10, which are operational and which have the highest voltages, are preferably initially put into operation. These are operational electrical energy store modules M1, . . . M10, whose voltage is between first voltage U1 and a second voltage U2. First voltage U1 in this case limits voltage range ΔU upwardly and second voltage U2 limits voltage range ΔU downwardly. Second voltage U2 is therefore lower by ΔU than first voltage U1.
- (12) The expansion of voltage range ΔU in this case is a function of the electrical energy store, in particular, of the switching means of the electrical energy store, and unchangeable during the method. It is based on the maximally allowed current strength at the switching means under load, which includes compensating currents between the interconnected electrical energy store modules. Voltage range ΔU has an expansion, which is less than 5 V, in particular, less than 3 V, preferably approximately 1 V. As a result, the compensating currents between electrical energy store modules M1, . . . M10 are limited to less than 25 A. These values correspond to a variance of the charge state of 5% between the electrical energy store modules.

- (13) In this exemplary embodiment, first electrical energy store module **M1**, fourth electrical energy store module **M4**, fifth electrical energy store module **M5** and eighth electrical energy store module **M8** each have a voltage U , which is within voltage range ΔU between first voltage U_1 and second voltage U_2 , and are operational. Voltage U of second electrical energy store module **M2** is in fact within voltage range ΔU , but second electrical energy store module **M2** is not operational. Voltages U of remaining electrical energy store modules **M3**, **M6**, **M7**, **M9**, **M10** are below second voltage U_2 .
- (14) The voltages of various electrical energy store modules **M1**, . . . **M10** at a second point in time t_2 are represented in FIG. 2. In this case, the voltage of one operational electrical energy store module **M1**, . . . **M10** is represented with the aid of a white bar and the voltage of a non-operational electrical energy store module **M1**, . . . **M10** is represented with the aid of a hatched bar.
- (15) Second point in time t_2 is temporally after first point in time t_1 and shortly after the start-up of the electrical energy store.
- (16) At second point in time t_2 , those electrical energy store modules **M1**, . . . **M10** are electroconductively connected to one another and to the connection means and/or to a device, which were operational at first point in time t_1 and whose voltage was between first voltage U_1 and second voltage U_2 . These are first electrical energy store module **M1**, fourth electrical energy store module **M4**, fifth electrical energy store module **M5** and eighth electrical energy store module **M8**. When connecting these electrical energy store modules **M1**, **M4**, **M5**, **M8**, the voltage of these electrical energy store modules is equalized so that these electrical energy store modules **M1**, **M4**, **M5**, **M8** each have a mean voltage U_m .
- (17) The voltages of various electrical energy store modules **M1**, . . . **M10** at a third point in time t_3 are represented in FIG. 3. In this case, the voltage of an operational electrical energy store module **M1**, . . . **M10** is represented with the aid of a white bar and the voltage of a non-operational electrical energy store model **M1**, . . . **M10** is represented with the aid of a hatched bar.
- (18) Third point in time t_3 is temporally after first point in time t_1 and after second point in time t_2 .
- (19) At third point in time t_3 , those electrical energy store modules **M1**, **M4**, **M5**, **M8** are electroconductively connected to one another and to the connection means and/or to the device, which were electroconductively connected to one another and to the connection means and/or to the device at second point in time t_2 . These are first electrical energy store module **M1**, fourth electrical energy store module **M4**, fifth electrical energy store module **M5** and eighth electrical energy store module **M8**.
- (20) The electrical energy store module **M1**, . . . **M10** having the highest voltage U at third point in time t_3 is second energy store module **M2**, however, the second energy store module is also not operational at third point in time t_3 .
- (21) The operational electrical energy store module **M1**, . . . **M10** having the highest voltage are first, fourth, fifth and eighth electrical energy store module **M1**, **M4**, **M5**, **M8**, all of which have mean voltage U_m .
- (22) Voltage range ΔU no longer extends from first voltage U_1 up to second voltage U_2 at third point in time t_3 , but from mean voltage U_m to a third voltage U_3 , which is lower than second voltage U_2 . Third voltage U_3 in this case is lower by ΔU than mean voltage U_m .
- (23) All operational electrical energy store modules **M1**, . . . **M10**, whose voltage U is between mean voltage U_m and third voltage U_3 , may be put into operation at third point in time t_3 . That is, in addition to first electrical energy store module **M1**, fourth electrical energy store module **M4**, fifth electrical energy store module **M5** and eighth electrical energy store module **M8**, seventh electrical energy store module **M7**.
- (24) Voltages U of sixth electrical energy store module **M6** and of ninth electrical energy store module **M9** are also in voltage range ΔU between mean voltage U_m and third voltage U_3 , however, sixth electrical energy store module **M6** and ninth electrical energy store module **M9** are not operational.

- (25) An electrical energy store module **M1**, . . . **M10**, whose voltage U is within voltage range ΔU may, once it becomes operational, also be switched on. Should an electrical energy store module **M1**, . . . **M10**, whose voltage is above mean voltage U_m , in particular, above the sum of mean voltage U_m and of half the voltage range ΔU , become operational, it may be switched on only after the next start of the electrical energy store.
- (26) A flowchart of method **100** according to the present invention for operating an electrical energy store is represented in FIG. 4. Method **100** for operating an electrical energy store includes the following steps:
- (27) In a first method step **101**, the electrical energy store is initialized. In the process, respective operating parameters, in particular, a respective voltage U and/or a respective temperature and/or the respective charge state and, if necessary, further parameters, of respective energy store modules **M1**, . . . **M10** are detected.
- (28) In a second method step **102** after first method step **101**, it is queried whether all electrical energy store modules **M1**, . . . **M10** of the electrical energy store are operational.
- (29) If not all electrical energy store modules **M1**, . . . **M10** are operational, operational electrical energy store modules **M1**, . . . **M10** are selected in a third method step **103** after second method step **102**.
- (30) In a fourth method step **104** after third method step **103**, that electrical energy store module **M1**, . . . **M10** is selected from operational electrical energy store modules **M1**, . . . **M10**, which has a maximum first voltage U_1 . In this case, maximum first voltage U_1 is greater than all other voltages U of operational electrical energy store modules **M1**, . . . **M10**. Those operational electrical energy store modules **M1**, . . . **M10** are then selected, whose respective voltage U is within a voltage range ΔU below first voltage U_1 .
- (31) In a fifth method step **105** after fourth method step **104** or after eleventh method step **111**, electrical energy store modules **M1**, . . . **M10** selected in fourth method step **104** or in tenth method step **110** are electroconductively connected to one another and to the connection means and/or to a device.
- (32) In a sixth method step **106** after fifth method step **105**, the electrical energy store and/or the device is started with electrical energy store module **M1**, . . . **M10** selected in fourth method step **104** or in tenth method step **110**. The power of the electrical energy store in this case is reduced as compared to an operation including all electrical energy store modules **M1**, . . . **M10**. Voltages U of electrical energy store modules **M1**, . . . **M10** are then equalized and a mean voltage U_m occurs in all electrical energy store modules **M1**, . . . **M10** electroconductively connected to one another.
- (33) In a seventh method step **107** after sixth method step **106**, it is queried whether further electrical energy store modules **M1**, . . . **M10** are operational and have a voltage U , which is within a voltage range ΔU below mean voltage U_m of selected electrical energy store modules **M1**, . . . **M10** and, if necessary, this electrical energy store module **M1**, . . . **M10** is selected.
- (34) If in seventh method step **107** no electrical energy store module **M1**, . . . **M10** has been selected, seventh method step **107** is repeated temporally recurrently, in particular, periodically.
- (35) If in seventh method step **107** an electrical energy store module **M1**, . . . **M10** has been selected, in an eighth method step **108**, this electrical energy store module **M1**, . . . **M10** is electroconductively connected to electrical energy store modules **M1**, . . . **M10** already electroconductively connected to one another and to the connection means and/or to the device.
- (36) Seventh method step **107** and eighth method step **108** are repeated until all electrical energy store modules **M1**, . . . **M10** are electroconductively connected to one another and to the connection means and/or to the device, or method **100** is terminated in a ninth method step **109** and the electrical energy store and/or the device is/are switched off.
- (37) If in second method step **102** all electrical energy store modules **M1**, . . . **M10** are operational, that energy store module **M1**, . . . **M10** of electrical energy store modules **M1**, . . . **M10** having a maximum first voltage U_1 is selected in a tenth method step **110** after second method step **102**. In

this case, maximum first voltage **U1** is greater than all other voltages **U** of electrical energy store modules **M1**, . . . **M10**. Those electrical energy store modules **M1**, . . . **M10** are thereafter selected, whose respective voltage **U** is within a voltage range ΔU below first voltage **U1**.

(38) In an eleventh method step **111** after tenth method step **110**, it is queried whether all electrical energy store modules **M1**, . . . **M10** have been selected in tenth method step **110**.

(39) If not all electrical energy store modules **M1**, . . . **M10** have been selected in tenth method step **110**, the method is continued after eleventh method step **111** with fifth method step **105**.

(40) If in tenth method step **110** all electrical energy store modules **M1**, . . . **M10** of the electrical energy store have been selected, all electrical energy store modules **M1**, . . . **M10** are electroconductively connected to one another in a twelfth method step **112** and to the connection means and/or to the device.

(41) In a thirteenth method step **113** after twelfth method step **112**, the electrical energy store and/or the device is started with all electrical energy store modules **M1**, . . . **M10**.

(42) After thirteenth method step **113**, the method is terminated in ninth method step **109** and the electrical energy store and/or the device is/are switched off.

(43) The respective electroconductive connection between respective electrical energy store modules **M1**, . . . **M10** and the connection means and/or the device is preferably separated after the ninth method step.

(44) An electrical energy store in this case is understood to mean a rechargeable energy store, in particular, including an electrochemical energy store cell and/or an energy store module including at least one electrochemical energy store cell and/or one energy store pack including at least one energy store module. The energy store cell is implementable as a lithium-based battery cell, in particular, a lithium ion battery cell. Alternatively, the energy store cell is designed as a lithium polymer battery cell or a nickel metal hydride battery cell or a lead acid battery cell or a lithium air battery cell or a lithium sulfur battery cell.

(45) According to an example embodiment of the present invention, as illustrated in FIG. 5, an electrical energy store **500** includes a control unit **510**, a main switch **504** by which the electrical energy store is connectable to a load and/or energy source, a plurality of electrical energy store modules **M1-M10**, and, for each of the electrical energy store modules **M1-M10**, a respective module switch **502** and sensor **506**, such as a voltmeter or temperature sensor. The control unit **510** can obtain signals from the sensors **506**, control the switch **504** for connecting to a load or energy source, and control the switches **502** for selective parallel interconnections of the electrical energy store modules **M1-M10**. The electrical energy store **500** is shown as being incorporated in a vehicle **550**.

Claims

1. A method for operating an electrical energy store, which includes at least two electrical energy store modules interconnectable in parallel, the method comprising the following steps: initially querying which electrical energy store modules of the electrical energy store modules of the energy store are operational; determining a first voltage which is a greatest of all voltages of all of the operational electrical energy store modules; and based on the determination: selecting all of those of the operational electrical energy store modules whose respective voltages are within a voltage range, the voltage range being obtained by applying a predefined voltage difference to the first voltage, with the first voltage forming a highest voltage of the voltage range; and selectively electroconductively interconnecting to one another only the selected ones of the operational electrical energy store modules, so that each of the operational electrical energy store modules whose respective voltage is outside of the voltage range is not connected, wherein the connecting reduces the greatest of all voltages, so that the voltage range having the predefined voltage difference is lowered, thereby causing additional ones of the operational electrical energy store

modules to be connected; wherein the method includes at least one of the following features (I)-(II): (I) when a particular one of the electrical energy store modules which is non-operational has a voltage which is greater than a mean voltage of the interconnected ones of the operational electrical energy stores and less than a sum of the mean voltage and of half the predefined voltage difference, a number of the electrical energy store modules that are interconnected remains constant until (a) the particular electrical energy store module becomes operational whereupon the particular electrical energy store is interconnected with the previously interconnected ones of the operational electrical energy stores, or (b) a voltage of the particular electrical energy store module is greater than the sum of the mean voltage and of half the predefined voltage difference; and (II) when a particular electrical energy store module, of the electrical energy store modules, whose voltage is greater than a sum of the mean voltage and of half the predefined voltage difference, becomes operational during performance of a first instance of the method, the particular electrical energy store module is not electroconductively interconnected to the previously interconnected ones of the operational electrical energy stores until completion of an entirety of the first instance of the method.

2. The method as recited in claim 1, wherein all of the electrical energy store modules are separated from one another when the electrical energy store is switched off.

3. The method as recited in claim 1, wherein an extent of the predefined voltage difference is a function of a switch of the electrical energy store.

4. The method as recited in claim 1, wherein an electrical energy store module of the electrical energy stores is operational when its temperature and/or its voltage and/or its charge state, is below a maximum limiting value and/or above a minimum limiting value.

5. The method as recited in claim 1, further comprising: (i) based on not all electrical energy store modules having been interconnected, querying again at a later point in time during operation of the electrical energy store, which of the electrical energy store modules are operational and that electrical energy store module is selected, whose voltage is within the predefined voltage difference below a mean voltage of the interconnected ones of the electrical energy store modules, and is electroconductively interconnected to the previously interconnected ones of the electrical energy stores.

6. The method as recited in claim 5, wherein the method steps of (i) are repeated until all electrical energy store modules are electroconductively interconnected or the electrical energy store is switched off, the method steps of (i) being repeated periodically.

7. The method as recited in claim 5, wherein when the particular one of the electrical energy store modules which is non-operational has the voltage which is greater than the mean voltage of the interconnected ones of the operational electrical energy stores and less than a sum of the mean voltage and of half the predefined voltage difference, the number of the electrical energy store modules that are interconnected remains constant until (a) the particular electrical energy store module becomes operational whereupon the particular electrical energy store is interconnected with the previously interconnected ones of the operational electrical energy stores, or (b) the voltage of the particular electrical energy store module is greater than the sum of the mean voltage and of half the predefined voltage difference.

8. The method as recited in claim 5, wherein when the particular electrical energy store module, of the electrical energy store modules, whose voltage is greater than the sum of the mean voltage and of half the predefined voltage difference, becomes operational during the performance of the first instance of the method, the particular electrical energy store module is not electroconductively interconnected to the previously interconnected ones of the operational electrical energy stores until the completion of the entirety of the first instance of the method.

9. An electrical energy store comprising: at least two energy store modules which are interconnectable in parallel; wherein the electrical energy store is configured to be operated by performance of a method that includes: initially querying which electrical energy store modules of

the electrical energy store modules of the energy store are operational; determining a first voltage which is a greatest of all voltages of all of the operational electrical energy store modules; and based on the determination: selecting all of those of the operational electrical energy store modules whose respective voltages are within a voltage range, the voltage range being obtained by applying a predefined voltage difference to the first voltage, with the first voltage forming a highest voltage of the voltage range; and selectively electroconductively interconnecting to one another only the selected ones of the operational electrical energy store modules, so that each of the operational electrical energy store modules whose respective voltage is outside of the voltage range is not connected, wherein the connecting reduces the greatest of all voltages, so that the voltage range having the predefined voltage difference is lowered, thereby causing additional ones of the operational electrical energy store modules to be connected; wherein the method further includes at least one of the following features (I)-(II): (I) when a particular one of the electrical energy store modules which is non-operational has a voltage which is greater than a mean voltage of the interconnected ones of the operational electrical energy stores and less than a sum of the mean voltage and of half the predefined voltage difference, a number of the electrical energy store modules that are interconnected remains constant until (a) the particular electrical energy store module becomes operational whereupon the particular electrical energy store is interconnected with the previously interconnected ones of the operational electrical energy stores, or (b) a voltage of the particular electrical energy store module is greater than the sum of the mean voltage and of half the predefined voltage difference; and (II) when a particular electrical energy store module, of the electrical energy store modules, whose voltage is greater than a sum of the mean voltage and of half the predefined voltage difference, becomes operational during performance of a first instance of the method, the particular electrical energy store module is not electroconductively interconnected to the previously interconnected ones of the operational electrical energy stores until completion of an entirety of the first instance of the method.

10. The electrical energy store as recited in claim 9, wherein the electrical energy store includes a control unit, each of the electrical energy store modules includes at least one sensor, the at least one sensor being a voltage sensor and/or a temperature sensor, and the electrical energy store further includes a switching arrangement configured to implement the electroconductive interconnection, and wherein the control unit is configured to evaluate signals of the sensors and to activate the switching arrangement.

11. A device, comprising: an electrical energy store including at least two energy store modules which are interconnectable in parallel; wherein the electrical energy store is configured to be operated by performance of a method that includes: initially querying which electrical energy store modules of the electrical energy store modules of the energy store are operational; determining a first voltage which is a greatest of all voltages of all of the operational electrical energy store modules; and based on the determination: selecting all of those of the operational electrical energy store modules whose respective voltages are within a voltage range, the voltage range being obtained by applying a predefined voltage difference to the first voltage, with the first voltage forming a highest voltage of the voltage range; and selectively electroconductively interconnecting to one another only the selected ones of the operational electrical energy store modules, so that each of the operational electrical energy store modules whose respective voltage is outside of the voltage range is not connected, wherein the connecting reduces the greatest of all voltages, so that the voltage range having the predefined voltage difference is lowered, thereby causing additional ones of the operational electrical energy store modules to be connected; wherein the method further includes at least one of the following features (I)-(II): (I) when a particular one of the electrical energy store modules which is non-operational has a voltage which is greater than a mean voltage of the interconnected ones of the operational electrical energy stores and less than a sum of the mean voltage and of half the predefined voltage difference, a number of the electrical energy store modules that are interconnected remains constant until (a) the particular electrical energy store

module becomes operational whereupon the particular electrical energy store is interconnected with the previously interconnected ones of the operational electrical energy stores, or (b) a voltage of the particular electrical energy store module is greater than the sum of the mean voltage and of half the predefined voltage difference; and (II) when a particular electrical energy store module, of the electrical energy store modules, whose voltage is greater than a sum of the mean voltage and of half the predefined voltage difference, becomes operational during performance of a first instance of the method, the particular electrical energy store module is not electroconductively interconnected to the previously interconnected ones of the operational electrical energy stores until completion of an entirety of the first instance of the method.

12. The device as recited in claim 11, wherein the device is a vehicle.
