

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413081
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Karanasios; Evripidis et al.

Multiport battery

Abstract

A battery includes at least one battery cell, a bidirectional port configured to provide current output to a load from the at least one battery cell and to receive a charge current from a battery charger to charge the at least one battery cell, a charge only port configured to receive charge current from the battery charger to charge the at least one battery cell, and a battery control system. The battery control system is configured to detect a connection status of the bidirectional port and/or the charge only port and, based on the connection status of each port, to control the battery between a power delivery mode where current can flow from the at least one battery cell out of the bidirectional port, a charge mode where current can from the bidirectional port or the charge only port to the at least one battery cell, and a disconnected mode where current cannot flow between the bidirectional port or the charge only port and the at least one battery cell.

Inventors:	Karanasios; Evripidis (Nieuw-Vennep, NL), Vila; Ramon Ferre (Les Borges del Camp, ES)
Applicant:	Brunswick Corporation (Mettawa, IL)
Family ID:	88793041
Assignee:	Brunswick Corporation (Mettawa, IL)
Appl. No.:	17/985682
Filed:	November 11, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20240162729 A1	May. 16, 2024

Publication Classification

Int. Cl.: B60L53/16 (20190101); B60L53/62 (20190101); B60L58/19 (20190101); H01M10/42 (20060101); H01M10/44 (20060101); H01M50/296 (20210101); H02J7/00 (20060101)

U.S. Cl.:

CPC H02J7/0036 (20130101); B60L53/16 (20190201); B60L53/62 (20190201); B60L58/19 (20190201); H01M10/425 (20130101); H01M10/441 (20130101); H01M50/296 (20210101); H02J7/0013 (20130101); H02J7/0045 (20130101); H02J7/0047 (20130101); H02J7/0063 (20130101); B60L2200/32 (20130101); H01M2010/4271 (20130101); H01M2220/20 (20130101)

Field of Classification Search

CPC: H02J (7/0036); H02J (7/0013); H02J (7/0045); H02J (7/0047); H02J (7/0063); H02J (7/0042); H02J (2310/42); H02J (7/0031); H02J (7/00); B60L (53/16); B60L (53/62); B60L (58/19); B60L (2200/32); H01M (10/425); H01M (10/441); H01M (50/296); H01M (2010/4271); H01M (2220/20); H01M (10/42); H01M (10/44)

USPC: 307/9.1

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
6507164	12/2002	Healey et al.	N/A	N/A
6902446	12/2004	Healey	N/A	N/A
7104856	12/2005	Krupp et al.	N/A	N/A
8043132	12/2010	Wyant	N/A	N/A
8944865	12/2014	Krabacher et al.	N/A	N/A
10017136	12/2017	Waisanen et al.	N/A	N/A
10202180	12/2018	Amerling et al.	N/A	N/A
10511121	12/2018	Milroy et al.	N/A	N/A
10710691	12/2019	Amerling et al.	N/A	N/A

11046405	12/2021	Groeschel et al.	N/A	N/A
11377186	12/2021	Ahlswede et al.	N/A	N/A
2007/0024219	12/2006	Aoyagi	318/801	H02J 7/14
2021/0024192	12/2020	Blomdahl	N/A	B63H 20/14
2021/0234402	12/2020	Sultenfuss	N/A	G06F 1/263
2022/0194542	12/2021	Kirchhoff et al.	N/A	N/A
2022/0200070	12/2021	Gonring	N/A	N/A
2022/0328912	12/2021	Gonring	N/A	N/A
2023/0202317	12/2022	Wiegman	320/108	B60L 53/16
2024/0063643	12/2023	Loacker	N/A	H02J 7/0024

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2021216912	12/2020	WO	N/A

OTHER PUBLICATIONS

Extended European Search Report for corresponding European Application No. 23209263.5, mailed May 13, 2024. cited by applicant

Park et al., “Outboard Motor,” U.S. Appl. No. 29/848,875, filed Aug. 5, 2022 (drawings, specification, and claims only). cited by applicant

Johnson et al., “Battery,” U.S. Appl. No. 29/855,548, filed Oct. 4, 2022 (drawings, specification, and claims only). cited by applicant

Futuronics, High voltage connector FTP18 Series, admitted prior art, available at <https://en.futuronics.com.cn/product/106.html>. cited by applicant

Futuronics, Multi-core connector-(2+8/2+14) IP67, admitted prior art, available at <https://en.futuronics.com.cn/product/75.html>. cited by applicant

Avertronics, C2 waterproof connector & wire hareness assy', admitted prior art, available at <https://avertronics.com/en/product/c2-waterproof-connector-2021-e-1/>. cited by applicant

Avertronics, D1 waterproof connector & wire hareness assy'(80A), admitted prior art, available at <https://avertronics.com/en/product/d1-waterproof-connector-2021-e-1/>. cited by applicant

Unicon, E Vehicles Waterproof Power Connector M23 Push Locking 2 Power 1 Grouding 5 Data, admitted prior art, available at <https://www.jniconconnector.com/sale-12168416-e-vehicles-waterproof-power-connector-m23-push-locking-2-power-1-grouding-5-data.html>. cited by applicant

A&C Solutions, Female Panel Mount Connector—Manual Locking, admitted prior art, available at <https://www.higoconnector.com/products/s835am-c-00-hb-0300/L099K#title>. cited by applicant

A&C Solutions, Female Panel Mount Connector—Charging & discharging in 1, self-locking, admitted prior art, available at <https://www.higoconnector.com/products/s828bm-c-00-gm-0300/0099K#title>. cited by applicant

A&C Solutions, Male Angled Plug Connector—Charging & discharging in 1, self-locking, admitted prior art, available at <https://www.higoconnector.com/products/s828bg-a-00-cd-1000/v099K#title>. cited by applicant

A&C Solutions, Female Panel Mount Connector—Self-locking, admitted prior art, available at <https://www.higoconnector.com/products/s526am-c-00-b9-0300/P099K#title>. cited by applicant

A&C Solutions, Male Angled Plug Connector, admitted prior art, available at <https://www.higoconnector.com/products/z718ag-a-00-gg-1000/Hv99K#title>. cited by applicant

A&C Solutions, Male Cable Connector, Self-Locking, Button Release—Self-locking, button release, admitted prior art, available at <https://www.higoconnector.com/products/s824bg-a-00-fr-1000/0v99K#title>. cited by applicant

A&C Solutions, Female Panel Mount Connector, Self-Locking—Self-locking, button release, admitted prior art, available at <https://www.higoconnector.com/products/s824am-c-03-fq-0300/5v99K#title>. cited by applicant

Amphenol Sine Systems, AHDP04-24-09PR-SRA, product data sheet, May 8, 2020, available at <https://www.amphenol-sine.com/pdf/datasheet/AHDP04-24-09PR-SRA.pdf>. cited by applicant

Amphenol Sine Systems, AHDP06-24-09PR-SRA, product data sheet, May 12, 2020, available at <https://www.amphenol-sine.com/pdf/datasheet/AHDP06-24-09PR-SRA.pdf>. cited by applicant

Amphenol Sine Systems, AHDP06-24-09SR-SRA, product data sheet, May 12, 2020, available at <https://www.amphenol-sine.com/pdf/datasheet/AHDP06-24-09SR-SRA.pdf>. cited by applicant

Amphenol Sine Systems, AHDP04-24-09SR-SRA, product data sheet, May 8, 2020, available at <https://www.amphenol-sine.com/pdf/datasheet/AHDP04-24-09SR-SRA.pdf>. cited by applicant

Amphenol Sine Systems, AHDP02-24-07PN-WTACL22, product data sheet, Sep. 1, 2020, available at <https://www.amphenol-sine.com/pdf/datasheet/AHDP02-24-07PN-WTACL22.pdf>. cited by applicant

Amphenol Sine Systems, AHDP06-24-07SN-SRACL22, product data sheet, May 8, 2020, available at <https://www.amphenol-sine.com/pdf/datasheet/AHDP06-24-07SN-SRACL22.pdf>. cited by applicant

Amphenol Sine Systems, AHDP04-24-07PN-WTACL22, product data sheet, Jul. 6, 2019, available at <https://www.amphenol-sine.com/pdf/datasheet/AHDP04-24-07PN-WTACL22.pdf>. cited by applicant

Amphenol Ltw, PWMU-04BFMB-TL7001, admitted prior art, available at <https://www.amphenolltw.com/product-Info/Power/Power.PWMU/PWMU-04BFMB-TL7001.html>. cited by applicant

Amphenol Ltw, PWMU-04RMFS-TS7001, admitted prior art, available at <https://www.amphenolltw.com/product-Info/Power/Power.PWMU/PWMU-04RMFS-TS7001.html>. cited by applicant

Epropulsion, EPropulsion Spirit 1.0 Plus 3HP Electric Outboard Motor, admitted prior art, available at https://tbnation.net/products/epropulsion-spirit-1-0-plus-3hp-electric-outboard-motor?variant=39585207648391¤cy=USD&utm_medium=cpc&utm_source=google&gclid=CjwKCAjwwL6aBhBIEiwADycBIDOC4V7czgl1ST5foKhCsF3KCBgqHskNiuwW1sn1oeKx5EfOjQqHOC6RkQAvD_BwE. cited by applicant

Epropulsion, Epropulsion Navy Evo 6.0 LongShaft, admitted prior art, available at https://liquidsurfsandsail.com/epropulsion-navy-evo-6-0-longshaft/?sku=NE-6000-L0&utm_source=google&utm_medium=cpc&adpos=&scid=scplpNE-6000-L0&sc_intid=NE-6000-L0&gclid=CjwKCAjwwL6aBhBIEiwADycBIP5gTVPPII1YYGbLWTypeM9Maysj1l3Wu9pUQ2i4HJmecnKz-WzRFhoCQ1EQAvD_BwE. cited by applicant

Fergus et al., U.S. Appl. No. 17/487,116, filed Sep. 28, 2021, “Outboard Motor That Is Removable From Transom Clamp Bracket” (specification, claims, and drawings only). cited by applicant

Schrank et al., U.S. Appl. No. 17/509,739, filed Oct. 25, 2021, “Integrated Copilot And Locking Mechanism For Marine Drives” (specification, claims, and drawings only). cited by applicant

Nickols et al., U.S. Appl. No. 17/884,355, filed Aug. 9, 2022, “Transom Bracket Assemblies For Supporting A Marine Drive On A Vessel” (specification, claims, and drawings only). cited by applicant

Kalnins et al., U.S. Appl. No. 17/695,200, filed Mar. 15, 2022, “Electric Marine Propulsion System And Control Method” (specification, claims, and drawings only). cited by applicant

Park et al., U.S. Appl. No. 29/848,875, filed Aug. 5, 2022, "Outboard Motor" (specification, claim, and drawings only). cited by applicant
Johnson et al., U.S. Appl. No. 29/855,548, filed Oct. 4, 2022, "Battery" (specification, claims, and drawings only). cited by applicant
Fletcher, U.S. Appl. No. 17/939,474, filed Sep. 7, 2022, "Marine Drives And Apparatuses For Steering Marine Drives And For Routing Flexible Rigging Connectors On Marine Drives" (specification, claims, and drawings only). cited by applicant
McEathron et al., U.S. Appl. No. 17/972,691, filed Oct. 25, 2022, "Marine Drives and Apparatuses for Steering Marine Drives and for Routing Flexible Rigging Connectors on Marine Drives" (specification, claims, and drawings only). cited by applicant
Amphenol Sine Systems, AHDP04-24-08PN-M1WTA, product data sheet, Sep. 22, 2021. cited by applicant
Amphenol Sine Systems, AHDP06-24-08SN-M1WTA, product data sheet, Sep. 22, 2021. cited by applicant
Amphenol Sine Systems, AHDP02-24-08PN-M1SRA, product data sheet, Sep. 22, 2021. cited by applicant

Primary Examiner: Barnie; Rexford N

Assistant Examiner: Ly; Xuan

Attorney, Agent or Firm: Andrus Intellectual Property Law, LLP

Background/Summary

FIELD

(1) The present disclosure generally relates to rechargeable batteries, such as to marine batteries for electric marine propulsion systems having electric motors and methods for controlling power modes.

BACKGROUND

(2) The following U.S. patents and applications provide background information and are each incorporated herein by reference in entirety.

(3) U.S. Pat. No. 6,507,164 discloses a trolling motor having current-based power management including: an electric motor; a motor controller having an output for providing voltage to the motor; and a current sensor for measuring the electrical current flowing through the motor. Upon determining that the trolling motor has been operating above its continuous duty limit for a predetermined period of time, the motor controller begins reducing the voltage output to the motor until reaching an acceptable output voltage. In another embodiment, the controller is operated in three distinct modes with three distinct sets of operating parameters, namely: a normal mode wherein the output is set to a commanded level; a current limit mode wherein the output is set to a safe, predetermined level; and a transitional mode wherein the output is incrementally changed from the predetermined level to the commanded level.

(4) U.S. Pat. No. 6,902,446 discloses a DC motor having a motor housing and a motor controller housed within the motor housing. In a preferred embodiment the heat-producing components of the motor controller are in thermal communication with the housing such that the majority of the heat produced by such components will be readily conducted to the environment in which the motor is operating. When incorporated into a trolling motor, the motor housing of the present invention will be submerged so that controller-produced heat will be dissipated into the water in which the trolling motor is operated.

(5) U.S. Pat. No. 11,377,186 discloses an apparatus for operably connecting a marine drive to a marine vessel. A transom bracket is configured for fixed attachment to the marine vessel and for attachment to the marine drive such that the marine drive is trimmable up and down relative to the marine vessel about a trim axis. The transom bracket has a sidewall with a rigging opening through which at least one elongated rigging member extends for operably connecting the marine drive to the marine vessel, wherein the rigging opening is located along the trim axis. The rigging device has an elbow conduit with an inlet end and an outlet end, wherein the outlet end is positionable into a plurality of clock positions relative to the inlet end.

(6) U.S. Publication No. 2022/0194542 discloses a method of controlling an electric marine propulsion system configured to propel a marine vessel including measuring at least one parameter of an electric motor in the electric marine propulsion system and determining that the parameter measurement indicates an abnormality in the electric marine propulsion system. A reduced operation limit is then determined based on the at least one parameter measurement, wherein the reduced operation limit includes at least one of a torque limit, an RPM limit, a current limit, and a power limit. The electric motor is then controlled such that the reduced operation limit is not exceeded.

(7) U.S. Publication No. 2022/0328912 discloses a marine battery system configured to provide energy to a marine vessel load. The marine battery system includes a main enclosure body and an auxiliary enclosure body that is detachably coupled to the main enclosure body to define a sealed battery volume. The auxiliary enclosure body is configured to perform a pressure accommodation action responsive to an increase in a temperature within the sealed battery volume. The marine battery system further includes a battery disposed within the sealed battery volume.

(8) U.S. Publication No. 2022/0200070 discloses a marine battery system configured to provide energy to a marine vehicle load is provided. The marine battery system includes a battery, an enclosure configured to at least partially encapsulate the battery, a temperature sensor configured to detect temperature information within the enclosure, a pressure sensor configured to detect pressure information within the enclosure, and a controller coupled to the temperature sensor and the pressure sensor. The controller is configured to receive the temperature information from the temperature sensor, receive the pressure information from the pressure sensor, determine whether an enclosure breach condition has occurred based on a comparison of the temperature information and the pressure information, and in response to a determination that the enclosure breach condition has occurred, perform an enclosure breach mitigation action.

(9) U.S. patent application Ser. No. 17/487,116, filed Sep. 28, 2021, discloses an outboard motor having a transom clamp bracket configured to be supported on a transom of a marine vessel and a swivel bracket configured to be supported by the transom clamp bracket. A propulsion unit is supported by the swivel bracket, the propulsion unit comprising a head unit, a midsection below the head unit, and a lower unit below the midsection. The head unit, midsection, and lower unit are generally vertically aligned with one another when the outboard motor is in a neutral tilt/trim position. The propulsion unit is detachable from the transom clamp bracket.

(10) U.S. patent application Ser. No. 17/509,739, filed Oct. 25, 2021, discloses an apparatus for removably supporting a marine drive on a marine vessel. The apparatus has a transom bracket assembly for mounting to the marine vessel, a steering bracket for coupling the marine drive to the transom bracket assembly so the marine drive is steerable relative to the transom bracket assembly and the marine vessel; and an integrated copilot and locking mechanism configured to retain the steering bracket in a plurality of steering orientations. The mechanism is further configured to lock and alternately unlock the steering bracket relative to the transom bracket assembly such that in a locked position the marine drive is retained on the transom bracket assembly and such that in an unlocked position the marine drive is removable from the transom bracket assembly.

(11) U.S. patent application Ser. No. 17/884,355, filed Aug. 9, 2022, discloses a transom bracket assembly for supporting a marine drive on a marine vessel. The assembly comprises a transom bracket comprising a swivel cylinder, a steering arm extending from the marine drive, a swivel tube having a first end coupled to the steering arm and a second end seated in the swivel cylinder so that steering of the steering arm relative to the transom bracket rotates the swivel tube in the swivel cylinder about a steering axis for the marine drive, and a yoke which couples the second end of the swivel tube to the marine drive.

(12) U.S. patent application Ser. No. 17/695,200, filed Mar. 15, 2022, discloses an electric marine propulsion system configured to propel a marine vessel includes a power storage system comprising a plurality of batteries and at least one electric motor powered by the power storage system and configured to rotate a propulsor to propel the marine vessel. A control system is configured to identify a charge level for each of the plurality of batteries and determine which of the plurality of batteries are active batteries based at least in part on the charge level on each of the plurality of batteries. A minimum power limit is then identified for the active batteries and a system power limit is determined based on the minimum power limit and the number of active batteries. The at least one electric motor is then controlled based on the system power limit such that the system power limit is not exceeded.

(13) U.S. patent application Ser. No. 29/848,875, filed on Aug. 5, 2022, discloses an ornamental design for an outboard motor.

(14) U.S. patent application Ser. No. 29/855,548, filed on Oct. 4, 2022, discloses an ornamental design for a battery.

(15) U.S. patent application Ser. No. 17/939,474, filed Sep. 7, 2022, discloses a marine drive including a frame configured to support the marine drive with respect to the marine vessel, a cowling enclosing a portion of the frame in a cowling interior, a steering arm configured such that movement of the steering arm causes rotation of the marine drive with respect to the steering axis, and a flexible rigging connector extending from the cowling interior to a location in the marine vessel. The flexible rigging connector may extend through a guide passage in the steering arm. Additionally or alternatively, the steering arm may include a base member and a mounting member selectively movable relative to the base member to adjust the length of the steering arm.

SUMMARY

(16) This Summary is provided to introduce a selection of concepts that are further described below in the Detailed Description. This Summary is not intended to identify key or essential features of the claimed subject matter, nor is it intended to be used as an aid in limiting the scope of the claimed subject matter.

(17) In one aspect, a battery includes at least one battery cell, a bidirectional port configured to provide current output to a load from the at least one battery cell and to receive a charge current from a battery charger to charge the at least one battery cell, a charge only port configured to receive charge current from the battery charger to charge the at least one battery cell, and a battery control system. The battery control system is configured to detect a connection status of the bidirectional port and/or the charge only port and, based on the connection status of each port, to control the battery between a power delivery mode where current can flow from the at least one battery cell out of the bidirectional port, a charge mode where current can from the bidirectional port or the charge only port to the at least one battery cell, and a disconnected mode where current cannot flow between the bidirectional port or the charge only port and the at least one battery cell.

(18) In one embodiment, the battery control system is configured to enable the power delivery mode only if the connection status of the bidirectional port is connected and the connection status of the charge only port is disconnected, and to enable the charge mode only if the connection status of only one of the bidirectional port and the charge only port is connected.

(19) In another embodiment, the battery control system is further configured to enable the disconnected mode if the connection status of the bidirectional port is disconnected and the connection status of the charge only port is disconnected or if the connection status of the bidirectional port is connected and the connection status of the charge only port is connected.

(20) In another embodiment, the battery includes a plurality of switches controlled by the battery control system and positioned between the bidirectional port, the charge only port, and the at least one battery cell, wherein controlling the battery between the power delivery mode, the charge mode, and the disconnected mode includes separately controlling each of the plurality of switches.

(21) In another embodiment, the battery control system is configured to detect the connection status of the bidirectional port and the charge only port based on at least one of a resistance measurement across sockets in each of the of the bidirectional port and the charge only port and a voltage measurement across sockets in each of the of the bidirectional port and the charge only port.

(22) In one aspect, a rechargeable battery system includes a plurality of batteries each having at least one battery cell, a bidirectional port configured to provide current output to a load from the at least one battery cell and to receive a charge current from a battery charger to charge the at least one battery cell in the battery, a charge only port configured to receive charge current from the battery charger to charge the at least one battery cell, a battery control system, and a switch box configured to connect the plurality of batteries in parallel to a load and provide for simultaneous charging of all of the plurality of batteries. The battery control system is configured to detect a connection status of the bidirectional port and/or the charge only port and, based on the connection status of each port, to control the battery between a power delivery mode where current can flow from the at least one battery cell out of the bidirectional port, a charge mode where current can from the bidirectional port or the charge only port to the at least one battery cell, and a disconnected mode where current cannot flow between the bidirectional port or the charge only port and the at least one battery cell.

(23) In one embodiment, each of the plurality of batteries is configured to receive a charge current through the bidirectional port from a battery charger connected through the switch box.

(24) In one embodiment, each of the plurality of batteries is configured to receive a charge current through the charge only port from a battery charger connected directly to the charge only port.

(25) In one embodiment, each of the plurality of batteries is configured to permit receipt of the charge current through only one of the bidirectional port or the charge only port at a time.

(26) In one aspect, a method of controlling charging of a battery is provided, wherein the battery includes at least one battery cell, a bidirectional port, and a charge only port. The method includes detecting a connection status of the bidirectional port and/or the charge only port, and based on the connection status of each port, controlling the battery between a power delivery mode where current can flow from the at least one battery cell out of the bidirectional port, a charge mode where current can from the bidirectional port or the charge only port to the at least one battery cell, and a disconnected mode where current cannot flow between the bidirectional port or the charge only port and the at least one battery cell.

(27) In one embodiment, detecting the connection status of the bidirectional port and the charge only port includes measuring at least one of a resistance across sockets in each of the of the bidirectional port and the charge only port and a voltage across sockets in each of the of the bidirectional port and the charge only port and determining the connection status of each of the of the bidirectional port and the charge only port based on the resistance and/or the voltage measured therein.

(28) In another embodiment, the method includes determining a connected indicator for the bidirectional port based on the voltage at the bidirectional port indicating whether a connector is or is not connected to the bidirectional port, and determining a permitted load indicator for the bidirectional port based on the resistance at the bidirectional port indicating whether a permitted load is or is not connected to the bidirectional port or determining a permitted charger indicator for the bidirectional port based on the resistance at the bidirectional port indicating whether a permitted charger is or is not connected to the bidirectional port, wherein the connection status of the bidirectional port is based on the connected indicator and the permitted load indicator for the bidirectional port.

(29) In another embodiment, the method includes determining a connected indicator for the charge only port based on the voltage at the charge only port whether a connector is or is not connected to the charge only port, and determining a permitted charger indicator for the charge only port based on the resistance at the charge only port whether the permitted charger is or is not connected to the charge only port, wherein the connection status of the charge only port is based on the connected indicator and the permitted charger indicator for the charge only port.

(30) In another embodiment, the battery comprises a plurality of switches positioned between the bidirectional port, the charge only port, and the at least one battery cell, and wherein controlling the battery between the power delivery mode, the charge mode, and the disconnected mode includes separately controlling the plurality of switches.

(31) Various other features, objects, and advantages of the invention will be made apparent from the following description taken together with the drawings.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) The present disclosure is described with reference to the following Figures.

(2) FIG. 1 illustrates a marine vessel having an electric marine propulsion system according to the present disclosure, in which an electric marine drive is controlled by a tiller.

(3) FIG. 2 is a schematic representation of another electric marine propulsion system according to the present disclosure, in which an electric marine drive is controlled at a helm.

(4) FIG. 3 illustrates an electric marine propulsion system like that of FIG. 1, in which an electric marine drive is connected to a pair of batteries by way of a switch box.

(5) FIG. 4 illustrates yet another electric marine propulsion system according to the present disclosure, in which an electric marine drive is connected to a battery with no intervening switch box.

(6) FIG. 5 is a perspective view of a first connector for a marine device of the electric marine propulsion systems of the present disclosure.

(7) FIG. 6 is a view looking into a housing of the first connector of FIG. 5.

(8) FIG. 7 illustrates the first connector coupled to a cable.

(9) FIG. 8 is a cross section of the cable taken along the line 8-8 in FIG. 7.

(10) FIG. 9 is a perspective view of a second connector for a marine device of the electric marine propulsion systems of the present disclosure.

(11) FIG. 10 is a view looking into a housing of the second connector of FIG. 9.

(12) FIG. 11 illustrates the second connector coupled to a cable and wires.

(13) FIG. 12 shows an aperture that may be provided in a cowling of an electric marine drive to install the second connector of FIGS. 9-11 therein.

(14) FIG. 13 shows an adapter that may be used to provide the aperture in the cowling of the electric marine drive.

(15) FIG. 14 shows a portion of an electric marine drive with the second connector of FIGS. 9-11 installed therein.

(16) FIG. 15 shows a portion of the electric marine drive of FIG. 14 with the first connector of FIGS. 5-7 mated with the second connector of FIGS. 9-11.

(17) FIG. 16 is a cross section of the mated first and second connectors taken along the line 16-16 in FIG. 15.

(18) FIG. 17 is a cross section of the first and second connectors taken perpendicular to the cross section of FIG. 16, with the first and second connectors not being mated together.

(19) FIG. 18 illustrates an embodiment of battery according to the present disclosure.

(20) FIG. 19 illustrates a third connector that can be provided on the battery of FIG. 18.

(21) FIG. 20 is a schematic representation of another electric marine propulsion system according to the present disclosure, in which a power circuit and a signal circuit are illustrated.

(22) FIGS. 21-23 are exterior views of an exemplary switch box for a marine device of the electric marine propulsion systems of the present disclosure.

(23) FIGS. 24-25 are schematic representations of another electric marine propulsion system according to the present disclosure, in which a power circuit and an interlock circuit are illustrated.

(24) FIGS. 26-27 are interior views of an exemplary switch box for a marine device of the electric marine propulsion systems of the present disclosure.

(25) FIG. 28 is a flow chart illustrating one embodiment of a method of controlling a power circuit of an electric marine propulsion system according to the present disclosure.

(26) FIG. 29 illustrates another battery according to the present disclosure.

(27) FIG. 30 schematically depicts a plurality of switches for one embodiment of a battery according to the present disclosure.

(28) FIG. 31 is a simplified circuit diagram of a system including a battery having a plurality of switches according to an exemplary embodiment of the present disclosure.

(29) FIGS. 32-34 are flow diagrams illustrating embodiments of a method of controlling charging of a battery according to an embodiment of the present disclosure.

DETAILED DESCRIPTION

(30) The inventors have further recognized a need for a power control system that enables central charging and discharging of marine batteries connected in parallel within the system, and for the marine batteries to each detect connection of a load or a battery charger at a remote location, such as connection of a power-consuming device (e.g., a marine drive) or battery charger to a central switch box configured to provide multi-battery power distribution. In view of the forgoing, the inventors further developed the disclosed system comprising a switch box configured to connect a plurality of batteries in parallel to a load or to a battery charger. In examples described herein, the load is an electric marine drive having an electric motor powerhead. However, in other embodiments the load may be any electric-powered device.

(31) The inventors have further recognized a need for a battery having two ports that enable charging of the battery—one high current port that enables bidirectional current flow and one lower current port that only permits inward flow of current to charge the battery. The bidirectional port permits flow of current from the battery to a load and permits flow of charging current from a battery charger to the battery cell pack. The charge only port is configured for lower current flow and only permits inflow of charge current from a battery charger to charge the cells of the battery and does not permit current to flow in the opposite direction out of the charge only port. The disclosed system is configured to connect each battery to a load, such as the marine drive, via the bidirectional port of each battery. Where multiple batteries are utilized, a switch box connects the drives in parallel with a connection cable connecting between the bidirectional port on each battery to a respective port on the switch box.

(32) However, the inventors have recognized that only allowing charging via the bidirectional port is undesirable because it requires use of a large and specialized data and power connector that is configured for high current flow. Charging the battery requires a lower maximum current than the maximum amount of discharge current required for powering a large load (such as a marine drive) because typical battery charging is a slower process that occurs over several hours and conditions the battery. The inventors recognized that requiring charging through the bidirectional port via the specialized connector (e.g., connector 100) significantly increases the cost of the charging system. Thus, the inventors devised the disclosed battery and system having a charge only port configured to accept a smaller connector, e.g., having a standardized shape, thereby reducing the cost of the charging system. Each battery is configured to receive and detect connection of a permitted battery charger to the bidirectional port, either directly or through the switch box, and also to receive and detect connection of a permitted battery charger directly to the batteries' charge only port. The battery mode is then controlled accordingly between a power delivery mode, a charge mode, and a disconnected mode based on the detected connection.

(33) FIGS. 1 through 4 exemplify electric marine propulsion systems 2 in accordance with the present disclosure. Each electric marine propulsion system 2 includes an electric marine drive 3 powered by one marine battery 18 or a plurality of marine batteries 18 connected in parallel through a

switch box 7. The switch box 7 enables multi-battery power distribution, as well as other safety, power control, and charging features. Any number of batteries 18 can be connected to the switch box 7 between one and the maximum number of ports on the switch box 7, which in various embodiments may be four, six, or more ports. The switch box 7 enables connection and disconnection of a plurality of marine batteries (e.g., 18a-d), including the addition or disconnection of a subset of marine batteries 18a-d without disrupting operation of the marine drive 3. The system 2 is also configured to enable direct connection of the electric marine drive 3 and a single battery 18, as shown in FIG. 4, eliminating the switch box 7 where only one battery 18 is used.

(34) FIG. 1 depicts an exemplary embodiment of the disclosed electric marine propulsion system 2 on a marine vessel 1, which electric marine propulsion system 2 is modular and configured for quick and easy installation on a small marine vessel 1. Each marine battery 18 and the switch box 7 may be portable and configured to be easily transported on and off the marine vessel 1. Each marine battery 18 is separately housed in a marine-safe housing adapted for operation in a marine environment, including for preventing water ingress. For example, each battery housing 22 may have a handle 23 that enables easy carrying on and off the marine vessel 1. The switch box 7 is also contained in a marine-safe housing that is sealed against water ingress (see FIG. 27) and likewise may have a handle configured for easy carrying on and off the marine vessel 1.

(35) The switch box 7 removably connects to each of the batteries 18 in parallel via connection cables 90 that each include a cable 122 with a connector 99, 100 (see FIG. 2) on each end. A connection cable 90 also connects the electric marine drive 3 to the switch box 7. Each connector 99, 100 connects to a port on the switch box 7, the battery 18, or the electric marine drive 3 to provide an all-in-one power, data, and interlock connection between the switch box 7 and each of the batteries 18 and between the switch box 7 and the electric marine drive 3. The connectors 99, 100 are twist-to-lock connectors that are easily connected and disconnected from the batteries 18, switch box 7, and electric marine drive 3 so that the system 2 is easily assembled and disassembled. Connection between the electric marine drive 3, the switch box 7, and the batteries 18 via the connection cables 90 is all that is required to install the electrical and data aspects of the electric marine propulsion system 2 on a vessel. Thus, in addition to mounting the electric marine drive 3, installing the electric marine propulsion system 2 only requires plugging in a few connectors 99, 100. The electric marine drive 3 may be connected to the marine vessel 1 via a detachable transom bracket 49, such as those shown and described in U.S. patent application Ser. Nos. 17/487,116; 17/509,739; 17/884,335, incorporated by reference herein.

(36) In some embodiments, the connection cable 90 comprises identical elbow connectors 100 on each end of the cable 122 and identical ports are provided on each of the battery 18, switch box 7, and/or on the electric marine drive 3, such that the connection cables 90 between the various devices are reversible (direction agnostic) and interchangeable. This maximizes flexibility and modularity of the system 2, in that the same connection cable 90 can be used to connect any two devices—i.e., between the battery 18 and the switch box 7, between the switch box 7 and the electric marine drive 3, or between the battery 18 and the electric marine drive 3.

(37) The connection cables 90 may be available in various sizes so that a user can customize the system 2 based on their needs and the size constraints of a particular marine vessel. This enables placement of the switch box 7 and each of the one or more batteries 18 at whatever location is convenient. In the example illustrated in FIG. 1, the batteries 18 are placed toward the bow of the marine vessel 1 and the switch box 7 is located toward the stern near the electric marine drive 3. The batteries 18 are mounted at distance d from the switch box 7, which may be 6 to 7 feet or further. Here, a first battery is closer to the switch box 7 than the second battery. Each of the connection cables 90 may be appropriately sized to enable such connection without excess cable length that takes up space, gets caught or tangled. The connection cable 90 between the switch box 7 and the electric marine drive 3 is also appropriately sized, being shorter since it spans a shorter distance. In other vessels, a different location arrangement of the switch box 7 and/or the batteries 18 may be preferable, such as locating the elements in the middle or towards the sides of the marine vessel, and the system 2 is configured to enable any such arrangement.

(38) The systems 2 illustrated in FIGS. 1-4 include an outboard electric marine drive 3 having an electric motor 4 powerhead housed therein, such as housed within the cowl 50 of the outboard electric marine drive 3 or in the torpedo housing 51 or other location near the propeller 10. Although the propulsion systems 2 illustrated in the figures comprise an electric marine drive 3 being an outboard, a person of ordinary skill in the art will understand in view of the present disclosure that embodiments of the electric marine propulsion system 2 may include other types of electric marine drives 3, such as inboard drives or stern drives. The electric motor 4 powerhead is operably connected to and configured to rotate the propeller 10. As will be known to the ordinary skilled person in the relevant art, the propeller 10 may include one or more propellers, impellers, or other propulsor devices and the term “propeller” may be used to refer to all such devices. In certain embodiments, the electric motor 4 includes a rotor and a stator in a known configuration. The electric motor 4 may be, for example, a brushless electric motor, such as a brushless DC motor. In other embodiments, the electric motor may be a DC brushed motor, an AC brushless motor, a direct drive, a permanent magnet synchronous motor, an induction motor, or any other device that converts electric power to rotational motion. The motor 4 provides sufficiently high output to propel the marine vessel 1, such as such as up to 250 amps-350 amps at of voltage less than or equal to 60 Vdc.

(39) The electric marine drive 3 is powered by the scalable power storage system 16 that includes one battery 18 or a plurality of batteries 18 connected in parallel. For example, each battery 18 may be a nominal 36 volt or 48 volt battery, or any battery with a maximum operating voltage at or below 60 volts DC. For example, each battery 18 has a maximum operating voltage when fully charged that does not exceed 60 volts, such as 58 volts. The inventors recognized that providing a system configured for operation in the 50 to 60 volt range has advantages of enabling sufficient output, such as powering motors in the 3-5 horsepower range, while also providing a system at voltage levels that are safe and easy for novice users to manage. Each battery 18 is rechargeable, such as by connection to a battery charger 490 when the electric motor 4 is not in use. Various battery devices and systems are known in the relevant art. For example, the power storage system 16 may include one or a plurality of lithium-ion (LI) batteries 18, each LI battery 18 comprised of multiple battery cells. In other embodiments, each battery 18 may be a lead-acid battery, fuel cell, flow battery, ultracapacitor, and/or other devices capable of storing and outputting electric energy.

(40) Referring particularly to FIG. 2, the switch box 7 is configured to accommodate up to four batteries 18a-18d. Batteries may be connected or disconnected from switch box 7 without interrupting the power connection of the remaining batteries to the electric marine drive 3. This allows a user to add and remove batteries to the system 2 depending on the distance of travel, and to remove low-charge batteries and add fully charged batteries into the system 2 as needed. In FIG. 2, two batteries 18a and 18b are shown connected, and two batteries 18c and 18d are not currently connected but are available to be added to power the electric marine drive 3 as needed.

(41) Each battery 18a-18d is connected to the switch box 7 via a respective connection cable 90b. Each connection cable comprises a cable 122a-122b (only two are shown) having a connector 99, 100 on each end, where one end connects to one battery 18a-18d and the other end connects to a port on the switch box 7. Each connection cable 90 may comprise identical connectors on each end, or the connectors on either end may be different from one another. In the example shown, the connection cables 90b connecting each of the batteries 18a-18d to the switch box 7 comprise a battery-end connector being an elbow connector 100a-100d and a switch box-end connector being a straight connector 99a-99b (only two are shown). The connectors 99, 100 are described in more detail below.

(42) Referring also to FIG. 3, the connection cable 90d connecting the electric marine drive 3 to the switch box 7 has elbow connectors 100y and 100z on each end. In one embodiment, the connectors 100y and 100z on cable 122z are identical, and thus the connection cable 90d can be connected in either orientation. The elbow connectors 100y and 100z may also be identical with elbow connectors 100a-100d, and likewise the ports on each of the electric marine drive 3 and batteries 18 may be identical. Thus, the drive connection cable 90d (and likewise the battery connection cables 90b if they also have two identical elbow connectors 100) can also be utilized to connect the electric marine drive 3 directly to the battery 18.

(43) This arrangement is shown in FIG. 4, where the same drive connection cable 90d is connected to a battery 18. Specifically, elbow connector 100y is moved from the switch box 7 and is connected to the battery 18 instead. This enables a simplified system if only one battery 18 is being used. It also enables easy and direct connection to a battery 18 in a situation where the switch box 7 has a failure.

(44) Each battery **18a-18d** may include an associated battery control system **20a-20d**. Each battery control system **20a-20d** (e.g., battery management system (BMS)), includes one or more controllers configured to monitor and/or control the respective battery, including being configured to monitor parameters measured within the battery housing **22a-22d**—such as current, voltage, temperature, pressure, etc.—and determine battery charge level (e.g., battery state of charge and/or battery voltage), battery temperature, battery state of health, etc. Each battery control system **20a-20d** may be further configured to determine a power limit for the battery **18a-18d**, which is an amount of power that the battery **18a-18d** can supply without overheating, over-discharging, or otherwise compromising the battery.

(45) The battery control systems **20a-20d** may be configured to communicate those values via a communication link **34** to other control devices in the system **2**, including a central controller **12**, which in the embodiment shown in FIG. 2 is a propulsion control module (PCM) located in the electric marine drive **3**. Other devices, such as steering wheel **36** and throttle lever **38** may also communicate with the central controller **12** via the communication link **34**, which may be the same communication means or different. To provide one example, the communication link(s) **34** may be one or more CAN buses, such as operating via a Kingdom Network protocol. As explained in more detail below, the communication link **34** between the batteries **18a-18d** and the electric marine drive **3** runs through the connection cables **90** and the switch box **7**.

(46) Each battery control system **20a-20d** may also be configured to control whether the respective battery **18a-18d** is connected to deliver power, and thus is in a power delivery mode, or is inactive and in a disconnected mode in which the battery is disconnected from and not delivering power to the electric marine drive **3**. Each battery **18a-18d** includes an internal disconnect switch or plurality of switches that internally disconnects the battery cells or other storage elements from the battery output terminals **18+**, **18-**. Where a battery **18a-18d** is in an inactive state, the respective battery control system **20a-20d** may be configured to communicate a power limit of zero and/or to communicate an error or disconnected status indicating that the battery **18a-18d** is not active or available to provide power.

(47) The electric marine propulsion system **2** is configured to propel the marine vessel **1** in a direction instructed by an operator. In the depicted embodiment, the electric marine drive **3** is an outboard drive steered and controlled by a tiller handle **5**, such as one of various tiller arrangements that are well-known in the relevant art. FIG. 2 shows an embodiment including an outboard electric marine drive **3** connected to steering and throttle control devices at the helm, including a steering wheel **36** and a throttle lever **38**. Alternatively or additionally, the helm devices may include a joystick, push buttons, a touch screen, or other user input device enabling throttle and/or steering control. Alternatively or additionally, the helm devices may include a computing system and/or a hand-held mobile device, such as a cell phone, communicatively connected to the electric marine drive **3**, for example, as part of an onboard management system, such as the VesselView™ and/or VesselView Mobile™ system by Mercury Marine of Fond du Lac, Wisconsin.

(48) A control system of the electric marine propulsion system **2** may include a plurality of control devices configured to cooperate to provide the method of controlling the electric marine propulsion system **2** and the marine batteries **18a-d**, including power mode selection. For example, the control system includes a central controller **12**, a plurality of battery control systems **20a-20d**, and one or more motor controllers, trim controllers, steering controllers, etc. communicatively connected, such as by a communication bus. A person of ordinary skill in the art will understand in view of the present disclosure that other control arrangements could be implemented and are within the scope of the present disclosure, and that the control functions described herein may be combined into a single controller or divided into any number of a plurality of distributed controllers that are communicatively connected.

(49) Each controller may comprise a processor and a storage device, or memory, configured to store software and/or data utilized for controlling and/or tracking operation of the electric marine propulsion system **2**. The memory may include volatile and/or non-volatile systems and may include removable and/or non-removable media implemented in any method or technology for storage of information. The storage media may include non-transitory and/or transitory storage media, including random access memory, read-only memory, or any other medium which can be used to store information and be accessed by an instruction execution system, for example. An input/output (I/O) system provides communication between the control system and peripheral devices.

(50) FIGS. 5-19 show details of the connection cables **90**, including the connectors **100** and cables **122**. FIGS. 5-19 also show details of connectors **200**, **300** that may serve as the ports on the electric marine drive **3**, switch box **7**, and batteries **18**, and how the connectors **100** can be mated with the connectors **200**, **300** to connect the various devices in the electric marine propulsion system **2**.

(51) FIG. 5 shows a perspective view of a connector for a marine device, here, the elbow connector **100** provided as part of the connection cables **90** shown in FIGS. 1-4. Thus, the connector **100** of FIG. 5 can be provided on either or both ends of the cables **122** connecting the electric marine drive **3** to the switch box **7** or to the battery **18**, or the cables **122** connecting the switch box **7** to the battery **18**. As will be described further herein below, the connector **100** is configured to be mated with a connector **200** as shown in FIGS. 9-11 or a connector **300** as shown in FIG. 19. The connector **100** has a barrel-shaped housing **102** having an open first end **104** and an opposite second end **106** (see FIGS. 16 and 17, which show cross sections through the connector **100**). FIG. 6 shows a view looking straight into the connector **100** from the first end **104**. A plug **108** is provided within the housing **102**. The plug **108** comprises a plurality of electrical pins **110a-h** supported within a base surface **126** of the plug **108**. A sleeve **112** surrounds the housing **102** and is rotatable with respect to the housing **102** for reasons that will be described herein below. A perimetral seal **114**, which may be an elastomeric gasket, is provided about an outer surface of the housing **102**. A backshell **120**, which will be described further herein below, is provided at the second end **106** of the housing **102** between the housing **102** and a cable **122**.

(52) The plurality of electrical pins **110a-h** includes first and second power pins **110g**, **110h**. The power pins **110g**, **110h** are configured to be electrically connected to the battery **18** to carry electrical power through the cable **122**. The power pins **110g**, **110h** may have insulators on their distal ends to prevent a user or another device from unintentionally grounding the circuit with a battery **18**. The first and second power pins **110g**, **110h** are aligned along a diameter DP of the plug **108** and a remainder of the electrical pins **110a-f** in the plurality of electrical pins are symmetrically located on either side of the diameter DP of the plug **108**. Specifically, in the present example there are three electrical pins on either side of the diameter DP of the plug **108**: electrical pins **110a-c** on a first side of the diameter DP and electrical pins **110d-f** on a second side of the diameter DP. Electrical pin **110a** is symmetrically located with electrical pin **110d** with respect to the diameter DP. Electrical pin **110b** is symmetrically located with electrical pin **110e** with respect to the diameter DP. Electrical pin **110c** is symmetrically located with electrical pin **110f** with respect to the diameter DP. The remainder of the electrical pins **110a-f** may include one or more signal pins, interlock pins, and/or drain pins. The signal pins are configured to be connected to signal wire(s) (e.g., three pins in a CAN bus arrangement CAN high, CAN low, CAN ground) forming part of communication link **34**, the interlock pins are configured to be connected to wires forming part of an interlock circuit **500** (see FIGS. 24 and 25 described below), and the drain pin is configured to be connected to a ground wire.

(53) The present inventors placed the power pins **110g**, **110h** along the diameter DP of the plug **108** in order to allow the diameter DP of the plug **108** to have as small a dimension as possible. To maximize the space around the power pins **110g**, **110h**, the remainder of the electrical pins **110a-f** may be arranged symmetrically with respect to the diameter DP. Such a placement allows the electrical pins **110c**, **110f** to be placed as close to the power pins **110g**, **110h** as possible to maintain the plug **108** compact. However, the inventors realized that the symmetry of the electrical pins **110a-f** about the diameter DP could result in a mating connector **200** (FIG. 9-11) or **300** (FIG. 19) being incorrectly connected to the connector **100**. Thus, keys may be provided on the connector **100** to prevent such incorrect connection.

(54) In the depicted examples, an asymmetrical key **124** is provided within the housing **102** and divides the first and second power pins **110g**, **110h**. The key **124** has the shape of two “C”s situated back-to-back, each “C” partially surrounding the power pins **110g**, **110h**. The key **124** projects from the base surface **126** of the plug **108** toward the first end **104** of the housing. Asymmetry is provided by the inclusion of nubs **125** on the top of each “C,” which nubs are not provided on the bottom of each “C.” Thus, the key **124** is asymmetrical with respect to the diameter DP of the plug **108**. The location, shape, and/or number of nubs **125** could vary from that shown. The key **124** is configured to be received within a corresponding keyway

224 (FIGS. 9, 10) provided in a first portion of the mating connector 200, 300 as will be described herein below. An additional keyway is provided on the outer surface of the housing 102 of the first connector 100. More specifically, as best shown in FIG. 6, three additional keys 128a-c are provided on the outer surface of the housing 102. The keys 128a and 128b have the same size, but the key 128c is wider. In other examples, the keys 128a-c all have the same size, or the keys 128a and 128b are wider than the key 128c. The additional key (e.g., keys 128a-c) is configured to be received within a corresponding additional keyway (e.g., keyways 228a-c, FIGS. 9, 10) formed in a second portion of the mating connector 200, 300.

(55) Referring now also to FIG. 7, a plurality of wires 130 is respectively connected to the plurality of electrical pins 110a-h. The plurality of wires 130 includes at least a first power wire 130g and a second power wire 130h, connected respectively within the plug 108 to power pins 110g and 110h. As noted, the power wires 130g, 130h carry electrical power through the cable 122. The backshell 120 has a first end 132 that interfaces with the second end 106 of the housing 102 and surrounds the plurality of wires 130. A first cable jacket 136 extends from an opposite second end 134 of the backshell 120. The first cable jacket 136 surrounds the plurality of wires 130. A second cable jacket 138 surrounds a subset of the plurality of wires 130, such as the wires that are respectively connected within the plug 108 to the electrical pins 110a-f. This subset of pins/wires can be for signal, interlock, and/or drain purposes as noted herein above. The second cable jacket 138 extends through the first cable jacket 136 and shields the signal wires and other wires within the second cable jacket 138 from the power wires 130g, 130h. A schematic cross-section of the cable 122 is provided in FIG. 8, showing the wires 130a-f surrounded by the second cable jacket 138 and showing the second cable jacket 138 and the wires 130g, 130h surrounded by the first cable jacket 136.

(56) FIG. 9 shows a perspective view of another connector 200 for a marine device, such as for the electric marine drive 3 shown in FIGS. 1-4. In one example, the connector 200 forms the port provided on the electric marine drive 3 to which the elbow connector 100 can be mated. The connector 200 includes a housing 202 configured to pass through an aperture in the outer cowling 50 of the electric marine drive 3, as will be described further herein below. The housing 202 has an open first end 204 and an opposite second end 206 (see FIGS. 16 and 17, which show cross sections through the connector 200). FIG. 10 shows a view looking straight into the connector 200 from the first end 204. A receptacle 208 is located within the housing 202. The receptacle 208 comprises a plurality of electrical sockets 210a-h formed in an end surface 226 of the receptacle 208. A plurality of wires, including wires 230g, 230h, is respectively connected to the plurality of electrical sockets (e.g., wire 230g is connected to electrical socket 210g and wire 230h is connected to electrical socket 210h). A backshell 220 interfaces with the second end 206 of the housing 202 and surrounds the plurality of wires 230g, 230h and a cable jacket 238, which in turn surrounds additional wires, as will be described further herein below.

(57) In the present example, the plurality of electrical sockets 210a-h includes first and second power sockets 210g, 210h. As noted, the power sockets 210g, 210h are configured to be connected to power wires 230g, 230h, which are configured to conduct electrical power when a battery 18 is electrically connected to the connector 200 as shown in FIGS. 1-4. The power wires 230g, 230h are configured to be connected to the electric motor 4 to provide power thereto. The receptacle 208 is generally cylindrical and the first and second power sockets 210g, 210h are aligned along a diameter DR of the receptacle 208. A remainder of the electrical sockets 210a-f in the plurality of electrical sockets are symmetrically located on either side of the diameter DR of the receptacle 208. Specifically, in the present example there are three electrical sockets on either side of the diameter DR of the receptacle 208: electrical sockets 210a-c on a first side of the diameter DR and electrical sockets 210d-f on a second side of the diameter DR. Electrical socket 210a is symmetrically located with electrical socket 210d with respect to the diameter DR. Electrical socket 210b is symmetrically located with electrical socket 210e with respect to the diameter DR. Electrical socket 210c is symmetrically located with electrical socket 210f with respect to the diameter DR. The remainder of the electrical sockets 210a-f may include one or more signal sockets, interlock sockets, and/or drain sockets, which are configured to be connected to signal wires, interlock wires, and/or drain wires, respectively.

(58) The present inventors placed the power sockets 210g, 210h along the diameter DR of the receptacle 208 in order to allow the diameter DR of the receptacle 208 to have as small a dimension as possible. In order to fill the space around the power sockets 210g, 210h, the present inventors then placed the remainder of the electrical sockets 210a-f symmetrically with respect to the diameter DR. Such a placement allows the electrical sockets 210c, 210f to be placed as close to the power sockets 210g, 210h as possible to maintain the receptacle 208 compact. However, the present inventors then realized that the symmetry of the electrical sockets 210a-f about the diameter DR could result in a mating connector 100 (FIGS. 5-7) being incorrectly connected to the connector 200. Thus, the present inventors provided keyways on the connector 200 to prevent such incorrect connection.

(59) Specifically, the connector 200 comprises an asymmetrical keyway 224 provided in the receptacle 208 and dividing the first and second power sockets 210g, 210h. The keyway 224 is recessed from the end surface 226 of the receptacle 208 and has the shape of two "C's" situated back-to-back, each "C" partially surrounding a respective power socket 210g or 210h. Asymmetry is provided by the inclusion of recesses 225 on the bottom of each "C," which recesses are not provided on the top of each "C." Thus, the keyway 224 is asymmetrical with respect to the diameter DR of the receptacle 208. The location, shape, and/or number of recesses 225 could vary from that shown, but should match the location, shape, and/or number of nubs in the plug 108. The keyway 224 is configured to receive the corresponding key 124 provided on a portion of the mating connector 100 (FIGS. 5-6). An additional keyway is formed in an inner surface of the housing 202. More specifically, three additional keyways 228a-c are provided in the inner surface of the housing 202. Keyways 228a, 228b are narrower than keyway 228c, but in other examples, all keyways 228a-c could have the same width, or keyway 228c could be narrower than keyways 228a and 228b. The additional keyway (e.g., keyways 228a-c) is configured to receive the corresponding additional key (e.g., keys 128a-c) provided on a portion of the mating connector 100.

(60) Referring now also to FIG. 11, as noted hereinabove, a plurality of wires 230 is respectively connected to the plurality of electrical sockets 210a-h in the receptacle 208. The plurality of wires 230 includes at least a first power wire 230g and a second power wire 230h, connected respectively within the receptacle 208 to power sockets 210g and 210h. These power wires 230g, 230h are configured to carry electrical power when a battery 18 is connected to the receptacle 208 via the plug 108 of a given connection cable 90. The backshell 220 has a first end 232 that interfaces with the second end 206 of the housing 202 (see also FIGS. 16 and 17) and surrounds the plurality of wires 230. A subset of the plurality of wires 230 is provided within a separate cable jacket 238. The subset of wires in the cable jacket 238 may include the signal, interlock, and drain wires, which may have the same purposes as the signal, interlocks and drain wires described hereinabove with respect to the first connector 100.

(61) Referring back to FIGS. 9 and 10, the housing 202 comprises a geometrical feature extending outwardly from an outer surface of the housing 202. Specifically, the housing 202 comprises four geometrical features 240a-d, each in the form of a triangle. The geometric features 240a-d are raised with respect to a flange 242 that surrounds the housing 202 at the second end 206 of the housing 202. The geometric features 240a-d are equally spaced and together form four points of a square centered on the housing 202. However, the geometric features could instead form three points of a triangle or could be unequally spaced.

(62) Referring to FIGS. 12-14, as noted hereinabove, the housing 202 of the connector 200 is configured to pass through an aperture 502 in an outer cowling 50 of the electric marine drive 3. The geometrical feature on the housing 202 of the second connector 200 is configured to be received in a corresponding geometrical feature in the aperture 502 in the outer cowling 50 in a manner that prevents rotation of the housing 202 with respect to the aperture 502 and thus the cowling 50. Specifically, the geometrical features 240a-d on the housing 202 are configured to be received in corresponding geometrical features 504a-d in the aperture 502 in the outer cowling 50 in a manner that prevents rotation of the housing 202 with respect to the aperture 502. The geometrical features 504a-d are also in the shape of triangles spaced equally apart and forming the corners of a square centered on what is otherwise a generally circular aperture 502 having a diameter slightly larger than the diameter of the housing 202. The geometrical features 504a-d can be made directly in the cowling 50 as shown in FIG. 12 or can be made in an adapter 506 as shown in FIG. 13. If the adapter 506 is used, the geometrical features 504a'-d' are preformed in the adapter 506, the cowling 50 is cut or formed to the outside shape of the adapter 506 (here, a circle), and the adapter 506 is inserted in the appropriately sized space in the cowling 50. Using an adapter may 506 make manufacturing of the cowling 50 easier and/or may allow for more precise forming of the aperture 502' and geometrical features 504a'-d'.

(63) FIG. 14 shows a portion of the electric marine drive 3 with the cowling 50 on the near side of the electric marine drive 3 removed so that the location of the adapter 506 and connector 200 situated therein can be seen. With the connector 200 placed inside the cowling 50 and the first end 204 of the housing 202 facing outwardly, the geometrical features 240a-d and 504a-d or 504a'-d' are respectively aligned and the housing 202 of the connector 200 is pushed through the aperture 502 or 502' from the inside of the cowling 50. The connector 200 is configured to be installed through the aperture 502 or 502' in the outer cowling 50 such that the backshell 220 and a portion of the housing 202 are located internally of the outer cowling 50 and a remainder of the housing 202 (e.g., at least the first end 204 thereof) is located externally of the outer cowling 50. The flange 242 on the connector 200 sits just internally of the cowling 50, while the geometric features 240a-d sit directly within the corresponding geometric features 504a-d or 504a'-d' of the aperture 502 or 502'. A washer and nut may be placed over the first end 204 of the housing 202 and the nut tightened via the threads 244 (FIG. 9) on the outer surface of the housing 202 until the washer contacts the cowling 50 or the adapter 506. The adapter 506 is then held in place between the washer and nut on the outside of the cowling 50 and the flange 242 of the housing 202 on the inside of the cowling 50. The situating of the geometric features 240a-d within geometrical features 504a-d or 504a'-d' ensures that the connector 200 will not rotate with respect to the cowling 50 when external forces (such as connection/disconnection of the connector 100 or jiggling of the cable 122 during use) tend to place a torque on the connector 200. Such an anti-rotation feature goes beyond that already provided by the D-flat 246 on the housing 202 (FIG. 10) and the corresponding D-flat 508 or 508' in the aperture 502 (FIGS. 12 and 13).

(64) As shown in FIG. 14, the electric marine drive 3 is more or less in a vertically upright position. In other words, its steering shaft is more or less perpendicular with respect to the surface of the water in which the electric marine drive 3 is operating. This may be the case when, for example, the electric marine drive 3 is in a neutral trim position, not trimmed in or trimmed out. The connector 200 is configured to be installed in the electric marine drive 3 such that the first and second power sockets 210g, 210h are not vertically aligned with one another when the electric marine drive 3 is in the upright position. This clocking correlates to an intuitive and ergonomic connection of the connector 100 of FIGS. 5-7 with the connector 200 of FIGS. 9-11, as shown in FIG. 15. Specifically, the connector 100 is configured to connect with the connector 200 in a manner such that the second end 134 of the backshell 120 is located forwardly (with respect to the marine vessel) of the housing 102 where connection is made to the electric marine drive 3. Such an orientation of the elbow-shaped connector 100 makes it easy for a user to grip the connector 100 with their right hand to connect/disconnect the connector 100 to/from the connector 200 while on the marine vessel. In terms of human-machine interaction, it would be counterintuitive for a user to flip the connector 100 in an opposite direction in which the backshell 120 cannot be used as a "handle" of sorts to hold the connector 100. This intuitive "handle" feature of the elbow connector 100 thus also prevents attempts to incorrectly mate the connectors 100, 200.

(65) FIGS. 14 and 15 also show how the connector 200 is used to create a power/signal port on the cowling 50 of the electric marine drive 3 that is aesthetically pleasing and prevents water ingress. The port sheds water due to its vertical orientation and does not hang off of the electric marine drive 3 as do current pigtail-style assemblies. This makes it easier for a user to remove the electric marine drive 3 from the marine vessel and transport and/or store it elsewhere, as the user does not need to worry about electronic equipment hanging off of or out of the cowling 50 being damaged. The port on the electric marine drive 3 can be provided with a waterproof cap that mates to the connector 200 and/or with a hatch-type door on the cowling 50.

(66) As shown in FIGS. 16 and 17, according to the present disclosure, the housing 102 of the connector 100 is configured to receive a first portion (here, the receptacle 208) of the mating connector 200 via the first end 104 of the housing 102. An annular gap 148 (see also FIG. 6) between the outer surface of the housing 102 and the sleeve 112 is configured to receive a second portion (here, a distal portion of the housing 202) of the mating connector 200, and the perimetral seal 114 is configured to contact the second portion (i.e., the annular inside surface of the housing 202) of the mating connector 200. Simultaneously, the housing 202 of the connector 200 is configured to receive a portion (here, the distal portion of the housing 102) of the mating connector 100 via the first end 204 of the housing 202. Once the two connectors 100, 200 have been mated, the sleeve 112 can be twisted about the housings 102 and 202 such that keys 252 on the outer surface of the housing 202 ride within slots 152 in the sleeve 112 to lock the connectors 100, 200 together against accidental disconnection.

(67) Note that the power pins 110g, 100h are longer than the electrical pins 110a-f (see FIGS. 5-6) and therefore the power pins 110g, 100h mate with the power sockets 210g, 210h (see FIG. 16) before the electrical pins 110a-f mate with the electrical sockets 210a-f. The connectors are thus designed such that the power pins 100g, 100h can carry 100% rated current from the battery 18 to the electric motor 4 after the signal pins (which are a subset of the pins 100a-e) mate with their respective sockets provided that the interlock circuit 500 is completed, as described in more detail below.

(68) Thus, the present disclosure is of a pair of connectors 100, 200 for marine devices, the pair of connectors 100, 200 comprising a first connector 100 and a second connector 200. The first connector 100 comprises a first housing 102 having an open first end 104 and an opposite second end 106. A plug 108 is provided within the first housing 102, the plug 108 comprising a plurality of electrical pins 110a-h. First and second electrical pins 110g, 110h of the plurality of electrical pins are aligned along a diameter DP of the plug 108 and a remainder of the electrical pins 110a-f in the plurality of electrical pins are symmetrically located on either side of the diameter DP of the plug. The first connector 100 also comprises a sleeve 112 surrounding the first housing 102 and an asymmetrical key 124 provided within the first housing 102 and dividing the first and second electrical pins 110g, 110h. The second connector 200 comprises a second housing 202 having an open first end 204 and an opposite second end 206. A receptacle 208 is located within the second housing 202, the receptacle 208 comprising a plurality of electrical sockets 210a-h. First and second electrical sockets 210g, 210h of the plurality of electrical sockets are aligned along a diameter DR of the receptacle 208 and a remainder of the electrical sockets 210a-f in the plurality of electrical sockets are symmetrically located on either side of the diameter DR of the receptacle 208. The second connector 200 also comprises an asymmetrical keyway 224 provided in the receptacle 208 and dividing the first and second electrical sockets 210g, 210h.

(69) The first housing 102 of the first connector 100 is configured to receive the receptacle 208 of the second connector 200 via the first end 104 of the first housing 102. A gap 148 between an outer surface of the first housing 102 and the sleeve 112 is configured to receive the second housing 202 of the second connector 200. Further, the keyway 224 of the second connector 200 is configured to receive the key 124 of the first connector 100. An additional key 128a-c is provided on the outer surface of the first housing 102 and an additional keyway 228a-c is formed in an inner surface of the second housing 202. The additional keyway 228a-c is configured to receive the additional key 128a-c. The keys and keyways prevent incorrect connection of the connectors 100, 200 as the connectors 100, 200 are physically incapable of mating unless all keys are aligned with all corresponding keyways.

(70) The second connector 200 further comprises a plurality of wires 230 respectively connected to the plurality of electrical sockets 210a-h and a backshell 220 interfacing with the second end 206 of the second housing 202 and surrounding the plurality of wires 230. The second connector 200 is configured to be installed through an aperture 502 in an outer cowling 50 of an electric marine drive 3 such that the backshell 220 and a portion of the second housing 202 are located internally of the outer cowling 50 and a remainder of the second housing 202 is located externally of the outer cowling 50. The second connector 200 is configured to be installed in the electric marine drive 3 such that the first and second electrical sockets 210g, 210h are not vertically aligned with one another when the electric marine drive 3 is in an upright position. The second housing 202 comprises a geometrical feature 240a-d extending outwardly from an outer surface of the second housing 202. The geometrical feature 240a-d on the second housing 202 is configured to be received in a corresponding geometrical feature 504a-d or 504a'-d' in the aperture 502 or 502' in the outer cowling 50 in a manner that prevents rotation of the second housing 202 with respect to the aperture 502 or 502'.

(71) A plurality of wires 130 is respectively connected to the plurality of electrical pins 110a-h of the first connector 100. A backshell 120 has a first end 132 interfacing with the second end 106 of the first housing 102 and surrounds the plurality of wires 130. A first cable jacket 136 extends from an opposite second end 134 of the backshell 120. The first cable jacket 136 surrounds the plurality of wires 130. A second cable jacket 138 surrounds

a subset **130a-f** of the plurality of wires. The second cable jacket **138** extends through the first cable jacket **136** to shield the wires in the second cable jacket **138** from those outside the second cable jacket **138**.

(72) FIGS. **16** and **17** also show a first perimetral seal **250** located within the second housing **202** around an outer surface of the receptacle **208**. The first perimetral seal **250** is configured to abut the first end **104** of the first housing **102** when the connectors **100**, **200** are mated. A second perimetral seal **114** is provided about an outer surface of the first housing **102**. The second perimetral seal **114** is configured to contact an inner surface of the second housing **202** when the connectors **100**, **200** are mated. The second perimetral seal **114** is located between the first and second ends **104**, **106** of the first housing **102**. While the first perimetral seal **250** can provide a watertight seal when the connectors **100**, **200** are mated perfectly and one is not tilted with respect to the other, the second perimetral seal **114** is able to provide a watertight seal even when the first connector **100** is tilted with respect to the second connector **200**.

(73) FIG. **18** shows a battery **18** according to the present disclosure, on which a battery port is provided as noted hereinabove with respect to FIGS. **1-4**. The battery port is itself a connector **300** very similar to the connector **200** provided on the electric marine drive **3**. The connector **300** has a flange **342** providing for connection to the battery housing **22**. Other than the shape of this flange **342**, the lack of a D-flat **246**, threads **244**, or geometrical features **240a-d** on the connector **300** (all of which may be particular to a connector **200** to be installed on the cowling **50**), the remainder of the connector **300** is identical to the connector **200**. Parts of the connector **300** that are labeled with a "3" in the hundreds place correspond to the same parts labeled with a "2" in the hundreds place and the same two numerals in the tens and ones places. Therefore, each of the parts of the connector **300** will not be described further herein. The connector **100** can be mated to the connector **300** in the same way as described with respect to FIGS. **16** and **17** regarding mating of the connectors **100** and **200**. Thus, the same connector **100** can be used to mate to the connector **300**.

(74) Referring now to all the figures, one of ordinary skill in the relevant art would understand that various configurations of connectors **100**, **200**, **300** and cables could be provided for any given connection cable **90** in the electric marine propulsion system **2**. For instance, the connection cable **90d** of FIG. **2** has an elbow connector **100y**, **100z** on either end, each connector **100y**, **100z** being the same as the connector **100** described with respect to FIGS. **5-7**. In other examples, it may be beneficial to use a connector cable **90x** like that shown in FIG. **7**, with ring terminals **131g**, **131h** on the ends of the power wires **130g**, **130h** for connection to the switch box **7** or to the battery **18**. In still other examples, straight connectors can be used on one or both ends of a connection cable **90**, such as the straight connectors **99a**, **99b** shown on the switch box **7** in FIG. **2**. These straight connectors would have the same connective configuration (i.e., plug **108**) as those of the elbow connector **100** described with respect to FIGS. **5-7**, but a different backshell shape to allow for connection of multiple connectors **99** immediately adjacent one another on the switch box **7**. Thus, each of the ports on the electric marine drive **3**, the switch box **7**, and the batteries **18** may have the female configuration of the receptacle **208** described with respect to FIGS. **9-11**, while each of the elbow and straight connectors on the ends of connection cables **90** may have the male configuration of the plug **108** described with respect to FIGS. **5-7**. It is contemplated that any given connection cable **90** can have one of the following configurations: elbow connectors on both ends; elbow connector on one end and straight connector on the other end; straight connectors on both ends; elbow connector on one end and ring terminals on the other end; straight connector on one end and ring terminals on the other end. In the case where ring terminals are provided on a connection cable **90**, the marine device to which the ring terminals are to be connected includes screws for connection of the ring terminal to the device's circuit. A receptacle for the separate signal cable is then also provided.

(75) FIG. **20** graphically depicts the power and signal connections of one embodiment of the propulsion system **2** having four marine batteries **18a-d** connected in parallel to a switch box **7**, which in turn connects to the marine drive **3**. Four connection cables **90a** connect each battery **18a-d** to the switch box **7** and one connection cable **90d** connects between the switch box **7** and the marine drive **3**. The connection cables **90d** and **90b** each comprise a cable **122** having a connector **400** on each end, wherein the connector **400** is a unified power and signal connector, such as the elbow connector **100** or the straight connector **99** described above. In this example, each of the connection cables **90b** and connection cable **90d** have the same connector **400** arrangement and thus are all interchangeable. For example, the connectors **400** at the switch box end of the cables **90b,d** may each be straight connectors **99** and the connectors **400** at the drive end of the cables **90b,d** may each be elbow connectors **100**. In an alternative example, all connectors at both ends of the cables may be straight connectors **99** or may be elbow connectors **100**. In such an embodiment where the connectors **400** at both ends are identical, the cables **90b,d** are reversible (direction agnostic) and interchangeable. In still other embodiments, the connectors **400** at different locations on the connection cables **90b,d** may differ from one another, taking on any of the various embodiments described herein.

(76) The unified power and signal connector **400** may have a pin, or terminal, arrangement similar to that shown and described with respect to FIGS. **5-6**. The connector includes power terminals **400g-h** (e.g., power pins **110g-h** in FIGS. **5-6**) and one or more signal terminals **400a-f** (e.g., electrical pins **110a-f** in FIGS. **5-6**). The power terminals **400g-h** connect a power circuit **443**, where when connected, current flows from each of the batteries **18a-d** to the marine drive **3** through the switch box **7**. The signal terminals **400a-f** connect to signal circuit **444**. The signal terminals **400a-f** include at least two interlock circuit terminals (e.g., electrical pins **110a-b** or pins **110c-d** in FIGS. **5-6**). The power circuit **443**, signal circuit **444**, and the interlock circuit **500** are described in detail below.

(77) Each connection cable **90b** connects between a respective battery port **408a-d** on each marine battery **18a-d** and switch box port **418a-d** on the switch box **7**. For example, each of the battery ports **408a-d** may be formed by mating connectors **300** on the battery housing **18** as shown in FIG. **18**. FIGS. **21-23** and **26-27** depict an exemplary embodiment of the switch box **7**. FIG. **21** shows the switch box **7** with housing **407** connected to two connection cables **90b** each having a straight connector **99b** at the switch-box-end of the cable **122b**. Referring in particular to FIGS. **21-23**, each of the switch box ports **418a-d** may be formed by mating connectors **419** having receptacles **519** on the switch box housing **407** configured to receive the mating end of each connector **400**. For example, the mating connectors **419**, being configured to provide electrical sockets for power and data connections (and in some embodiments interlock circuit connections or other safety control connections), may be the same or similar to the connectors **200**, **300** having the same or similar receptacles as described above.

(78) In the depicted example, the housing **407** is a rectangular-box-shape having a first side **407a** and a second side **407b**. Though the first side **407a** is shown on top and the second side **407b** is shown on bottom, the switch box housing **407** is configured to be mounted at any possible orientation such that any of the sides **407a-f** are oriented upwards. The housing **407** has a third side **407c**, fourth side **407d**, fifth side **407e**, and sixth side **407f**. Here, the connection ports and other features are located on the sides **407c-f**. As best shown in FIG. **22**, switch box ports **418a-d** are located together on one side, here the third side **407c**. Four switch box ports **418a-d** are shown, but in other embodiments a different number of switch box ports **418** may be provided, such as two ports, three ports, five ports, six ports, etc. In other embodiments, the switch box ports **418a-d** may be distributed around the sides **407c-f** of the housing **407**, or even on the first or second sides **407a-b**. The switch box ports **418a-d** are centered along the width *w* of the housing **407** to provide symmetry, optimizing the switch box **7** design to be mounted or placed in any orientation on the vessel. The housing **407** comprises two pieces **407x** and **407y** that are connected together as described below with respect to FIG. **27**.

(79) Referring again to FIGS. **20** and **21**, connection cable **90d** connects between the switch box **7** and the marine drive **3**, and more specifically between the drive port **428** and a switch box port **418** (e.g., dedicated port **418y**) on the switch box housing **407**. The drive port **428** may be on the outer housing, or cowling **50**, of the marine drive **3**, such as formed by the mating connector **200** shown in FIGS. **14** and **15** above. The other connector **400** of the cable **90d** connects to the switch box **7**. This is illustrated in FIGS. **21** and **23** as a straight connector **99d** of switch box port **418y**. FIG. **23** shows the corresponding side **407e** of the switch box housing **407**, where switch box port **418y** is positioned (again centered in the width as described above). Thus, the switch box port **418y** dedicated for connection to the marine drive **3** is on an opposing side **407e** from the side **407c** where the switch box ports **418a-d** are located.

(80) The switch box port **418y** is formed by mating connector **429** having receptacle **430**. The mating connector **429** is configured to receive and

mate connector **400**, which on cable **90d**, shown in straight connector **99d**. The mating connector **429**, being configured to provide electrical sockets for power and data connections (and in some embodiments interlock circuit connections or other safety control connections), may be the same or similar to the connectors **200**, **300** having the same or similar receptacles as described above. Likewise, the mating connector **429** may be identical to the mating connectors **419** configured to connect to the batteries, thereby facilitating the use of identical connectors **400** and interchangeable connection cables **90d** and **90b** and the ability to use either of the cables **90d** or **90b** to connect the marine drive **3** directly to one of the batteries **18a-18d**. This arrangement of one drive connected by connection cable **90b,d** is schematically shown in FIG. **24** and also the arrangement depicted in FIG. **4**.

(81) Referring again to FIG. **20**, the switch box **7** and connection cables **90b** and **90d** enable completion of a power circuit **443** which delivers power and sufficiently high current levels from the one or more connected batteries **18a-18d** to power the marine drive **3**. In this example, the power circuit **443** includes a battery power circuit portion **409**, a drive power circuit portion **417**, and a switch box power circuit portion **416** connecting therebetween. As also shown in FIG. **25**, the battery power circuit portion **409** includes sets of positive power connection legs **410** and ground power connection legs **413** (one set housed in each connection cable **90b**) between each marine battery **18a-d** and the switch box **7**. More specifically, each positive power connection leg **410** connects from one of the positive battery terminals **18a+** through **18d+** to a positive power pin in a respective switch box port **418a-d** and each ground/negative power connection leg **413** connects from one of the negative battery terminals **18a-** through **18d-** to a ground power pin in the respective switch box port **418a-d**. The drive power circuit portion **417** includes a positive power connection leg **412** and a ground power connection leg **415** connecting between sets of positive power pins and between sets of negative power pins, respectively, on the switch box ports and drive ports (and ultimately to the positive power input **4+** and the negative power input **4-** to the motor **4**).

(82) Where switch box **7** is included to connect a plurality of batteries **18a-d**, the switch box **7** houses the switch box power circuit portion **416** that connects the drive power circuit portion **417** and the battery power circuit portion **409**. However, as explained above, the system is configured to also enable direct connection of a marine drive **3** to a single battery **18**. Also referencing FIG. **24**, where the switch box is eliminated, the power circuit **443** includes overlapping power and drive circuit portions, where one cable **90b,d** connects the positive and negative pins on the drive **3** (and ultimately the positive and negative inputs **4+** and **4-** on the motor **4**) to the positive and negative battery terminal **18+** and **18-**, respectively.

(83) Returning to FIGS. **20** and **25**, the switch box power circuit portion **416** includes a positive power connection **411** and a ground power connection **414**. The positive power connection **411** in the switch box **7** connects between the plurality of positive power connection legs **410** and the positive power connection leg **412**. The plurality of plurality of positive power connection legs **410** are joined together within the switch box **7**, electrically connected at power block **420**. Power block **420** electrically connects to each of the positive power connection terminals **400h** (when connector **400** is plugged into the respective port **418a-d**) leading from the plurality of batteries **18a-d** into one positive power connection output.

(84) Referring also to FIG. **26**, an interior view of the switch box **7** is shown with the first cover piece **407x** removed. As shown here, the power block **420** includes a fuse bus **460** that includes a bus bar with a fuse connecting to each switch box port **418**, including each port **418a-d** providing a battery connection and each port **418y** providing a drive connection. Thus, in this example where the switch box **7** is configured to provide parallel connections for up to four batteries **18a-d**, the fuse bus includes five fuses **461a-e**. Fuses **461a-d** each connect to the positive power input from batteries **18a-d** through switch box ports **418a-d**. For visual clarity, FIG. **26** shows connection of only one connector, connector **419a** of port **418a**, which is connected to the fuse bus **460** via positive power connection portion **411a**. Each remaining port **418b-d** has a mating connector identical to connector **419a** (not shown for visual clarity) that connects to a respective fuse **461b-d** on the fuse bus **460**. A fifth fuse **461** connects to output switch box port **418y** via providing the output connection to the marine drive **3** via positive power connection portions **411b** and **411c**. As explained further below, positive power connection portions **411b** and **411c** are connected/disconnected by a user-operated switch **470**.

(85) The ground power connection **414** in the switch box **7** connects the plurality of ground power connection legs **413** to the ground power connection leg **415** via ground block **421**. Ground block **421** includes ground bus bar **464** that electrically connects each of the ground terminals **400g** (when connector **400** is plugged into the respective port **418a-d**) together to one ground output to the dedicated switch box port **418y** for the drive. Again, only one connector is shown for visual clarity, connector **419a** of port **418a**, which is connected to the ground bus bar **464** via ground power connection portion **414a**. Each remaining port **418b-d** is also connected to the ground bus bar **464**, which in turn connects to ground power connection portion **414b** leading to switch box port **418y**.

(86) A user-operable switch **470** is positioned in the positive power connection **411**, positive power connection portions **411b** and **411c** to enable a user to disconnect the power circuit **443**. For example, the user-operable switch **470** is a switch configured to provide a central connection/disconnection point for the power circuit **443** (and also, as explained more below, the interlock circuit). In the depicted embodiment, the user-operable switch **470** is a two-position rotary switch having a knob **471** on the exterior of the housing **407** movable by a user between an "ON" position and an "OFF" position (see FIG. **21**). In other embodiments, the user-operable switch **470** may be a different type of switch mechanism, such as a button, a slider, etc.

(87) Referring again to FIG. **20**, the switch box **7** enables a central location for charging all of the connected marine batteries **18a-d**. Charging port **480** in the switch box housing **407** is configured to receive a battery charger connector, such as a battery charger **490** connected to 120V AC grid power, or any standard shore power or wall power supply. The charging port **480** is connected to the charger block **423**. Referring also to FIG. **26**, the charger block **423** includes fuse block **483** providing fuses for isolation of the charger. Each battery **18a-d** also has a charging port **481** (see FIGS. **18** and **20**) configured to receive the same battery charger connector such that the charger **490** can connect directly to any of the batteries **18a-d**. As shown in described in more detail below with respect to the interlock circuit, the system **2** is configured such that the user-operable switch **470** must be open (in the "OFF" position) for charging current to be delivered to the batteries **18a-d**.

(88) As shown in FIGS. **21-23**, the switch box **7** may include a bracket **600** configured to enable mounting the switch box **7** at any location on the marine vessel, such as under a seat, on a floor surface of the vessel **1** (as shown in FIG. **1**), on a sidewall surface of the vessel **1**, etc. The bracket **600** includes a plurality of flanges **610** with holes **611** configured to be screwed or otherwise fastened to a surface. The bracket **600** is configured to securely hold the housing **407** in place, covering at least a portion of three sides **407a,d,f** thereof. In some embodiments, the bracket **600** and housing **407** may be configured such that the housing **407** can be oriented in either direction in the bracket **600** (i.e., the planar side **601** can contact the first side **407a** or the second side **407b**) to allow maximum flexibility for mounting the switch box **7**. Alternatively, the switch box **7** may simply be set in the vessel during use and may be carried on and off the vessel **1** with each use. In some embodiments, the housing **407** or the bracket **600** may be configured with a handle to facilitate easy carrying.

(89) Referring again to FIG. **20**, signal circuit **444** communicates data between the battery control systems **20a-d** and the central controller **12**, such as configured as a CAN bus connection. Signal circuit **444** also includes the interlock circuit, as described in more detail below. Signal circuit **444** is formed by signal connection legs **440** connecting between each of the batteries **18a-d**, signal connection leg **441a-b** in the switch box, and signal connection leg **442** connecting to the marine drive **3**. Each of signal connection legs **440** and **442** is housed in a respective connection cable **90b,d**, which as described above is a multi-wire and multi-pin connection for power and signal (data and interlock). The switch box **7** houses signal connection leg **441a-b** between each of the switch box ports **418a-d** and switch box port **418y**. Signal connection portion **441a** connects between connector **419a** of port **418a** (again, only one connector is shown for visual clarity) and signal block **422**, thus connecting each of the signal terminals **400a-f** (when connector **400** is plugged into the respective switch box port **418a-d**) to a junction point. Referring also to FIG. **26**, signal block **422** includes a CAN bus junction **466** and a breakout connection **467**. CAN bus junction **466** is a six-way junction that connects data communication wires (e.g., CAN high, CAN low, CAN ground/reference) and two interlock circuit wires, as well as a shield wire into an output **441x** that connects to the breakout connection **467**. The breakout connection **467** splits the two interlock circuit wires to connect the interlock circuit **500** (see FIG. **25**) to the user-operable switch **470** and the charger port harness, as well as to an auxiliary port **640**.

(90) As best shown in FIGS. 21, 23, 25, and 26, the switch box 7 may also include an auxiliary port 640 providing an interface connector for connecting low voltage auxiliary items, such as depth monitors, fish finders, and other electronic devices. The auxiliary port 640 may be configured to deliver a 12 V charge current to connected devices, and in some embodiments may be configured with one or more communication pins, such as configured to communicate on the signal bus (e.g., CAN bus) of the signal circuit.

(91) The housing 407 is water-tight and configured to withstand marine environments, and also to provide protection and shock absorption for the electrical elements encapsulated therein. As shown in FIGS. 26 and 27, the housing 407 is double-walled, having an outer wall 701 and an inner wall 702 to provide protection and an attractive outer appearance. The housing 407 is formed by connecting two pieces 407x and 407y, each being double-walled pieces, that are connected by six screws 710. The deeper piece 407y is shown in FIGS. 26 and 27 with the shallower piece 407x removed. Along the inner wall 702 between the two pieces 407x and 407y is a gasket 720 to discourage water ingress through the joint between the two pieces.

(92) The system 2 may include an interlock circuit 500 configured to provide a control signal by which the marine batteries 18a-d can determine an appropriate mode between a power delivery mode, a charge mode, and a disconnected mode and operate an internal disconnect accordingly. The interlock circuit 500 is configured to provide a completed circuit when the at least one battery 18 and the marine drive 3 are connected via connection cable(s) 90b,d (directly or through the switch box 7). FIGS. 24 and 25 depict an exemplary interlock circuit 500 that is adaptable to accommodate a direct connection to a single battery (FIG. 24) or a connection through the switch box 7 (FIG. 25) to enable connection and disconnection of any number of one or more marine batteries 18. The interlock circuit 500 runs parallel to but is independent from the power circuit 443 such that circuits 500 and 443 are not electrically connected. Accordingly, interlock circuit portions run through the connection cable(s) 90b,d incorporated in the system 2. The interlock circuit 500 is configured for lower current than the power circuit 443—e.g., with a lower gauge wire than that of the power circuit 443 which carries a much higher current to power the motor 4.

(93) Each battery control system 20 is configured to measure a resistance of the interlock circuit 500 across the receiving terminals 509a-b at the battery port (e.g., 408a-d in FIGS. 20 and/or 300 in FIGS. 18-19). The receiving terminals 509a-b connect to the two interlock circuit terminals 400a-b in the connection cable 90b connecting to the battery 18, whether directly or through a switch box 7. A resistance measurement unit 510 measures a resistance across the receiving terminals 509a-b and communicates the value to the battery control system 20. For example, resistance measurement unit 510 may be an interlock detection circuit configured to inject a small current into the interlock circuit 500 at a known voltage, and measuring the voltage drop across the interlock sockets 781c-d and 788c-d so as to determine the resistance. The battery control system 20 is configured to perform comparison logic comparing the resistance to one or more thresholds to identify which operation mode—power delivery mode, charge mode, or disconnected mode—is appropriate.

(94) The interlock circuit 500 includes a drive circuit portion 520 and battery circuit portion 522. The battery circuit portion 522 connects to the battery port (e.g., 408a-d in FIGS. 20 and/or 300 in FIGS. 18-19), including the receiving terminals 509a-b. The drive circuit portion 520 connects to the drive port (e.g., 428 in FIGS. 20 and/or 200 in FIGS. 14-15) on the marine drive 3, including the receiving terminals 569a-b. In the depicted embodiment, the drive circuit portion 520 of the interlock circuit 500 terminates in a short 570 between the receiving terminals 569a-b in the drive port. Thus, when the connection cable 90d is connected to the drive port, the drive circuit portion 520 is shorted and adds little to no resistance to the interlock circuit 500. In other embodiments, a resistor of a known fixed resistance may separate the receiving terminals 569a-b at the drive end.

(95) Based on a low measured resistance (or the appropriate known fixed resistance at the drive end) of the interlock circuit 500 by the resistance measurement unit 510, the battery control system 20 determines that the battery 18 and the marine drive 3 are connected together and engages a power delivery mode by controlling the internal disconnect 550 to connect to the power circuit 443—namely, to connect the power storing battery cell(s) to the output terminals 18+, 18-. On the other hand, if the resistance of the interlock circuit 500 is significantly higher (e.g., orders of magnitude greater or more) then the controller determines that the interlock circuit 500 is open, such as because the marine drive 3 and/or the battery 18 are not connected. When the interlock circuit 500 is open, the battery control system 20 engages the disconnected mode where the internal disconnect 550 disconnects the battery cells from the terminals 18+, 18- thereby removing the battery from the power circuit 443.

(96) When the system 2 includes a switch box 7, the interlock circuit 500 includes a switch box circuit portion 521 that connects between the drive circuit portion 520 and the battery circuit portion 522. As shown in FIG. 25, the switch box circuit portion 521 routes through the switch 470a, which here is a double pole double throw switch that simultaneously disconnects both the power circuit 443 and the interlock circuit 500. When the switch 470a is opened, the resistance sensed at the battery end by the resistance measurement unit 510 becomes very high because it is sensing resistance across the open circuit. Based on the sudden drastic change in resistance on the interlock circuit 500, the battery control system 20 knows that the switch 470a has been opened. It then switches to the disconnected mode to disconnect from the power circuit 443.

(97) The interlock circuit 500 may also be configured to enable multi-battery charging through the switch box 7. The battery charger 490 may be configured to connect to the interlock circuit 500 such that its connection to the charging port 480 (see FIGS. 20 and 26) can be detected by the battery 18 (or all connected batteries 18a-d) to enable charging. Thus, the battery charger has a connector (not shown) configured with pins for the interlock circuit and the charging port 480 has interlock circuit receptacles, similar to the connectors described above. Here, the charger 490 is configured to connect a predefined charge indicator resistance 499 to the interlock circuit 500, and specifically to the battery circuit portion 522 between the battery 18 and the switch box 7. For example, the charge indicator resistance may be a relatively large resistance value, such as 5 kOhms. Thereby, when the switch 470a is open, the resistance of the interlock circuit 500 measured by the resistance measurement unit 510 is close to or within a range of the predefined charge indicator resistance 499. The battery control system 20 then switches the battery to charge mode enabling the battery 18 to receive a charge current via terminals 18+, 18-. However, when the switch 470a is closed and the interlock circuit 500 is completed between the battery 18 and the drive 3, then the resistance measured by the resistance measurement unit 510 will be low because current will travel the path of least resistance through the short 570. Thus, the battery control system 20 will remain in power delivery mode and will not enable charging even if the battery charger 490 is connected.

(98) FIG. 28 depicts one embodiment of a method 800 of controlling a power circuit for an electric marine propulsion system 2, and particularly for controlling connection of one or more batteries to the power circuit 443 with an interlock circuit 500. The resistance of the interlock circuit 500 is measured at step 802, such as by the resistance measurement unit 510 in the battery 18. The resistance is provided to the battery control system 20 which conducts the following comparative logic. If the resistance is less than a predetermined low resistance at step 804, then the battery is operated in the power delivery mode (shown as step 806). For example, the predetermined low resistance may be set based on the expected resistance of the completed interlock circuit 500 when both the marine drive 3 and the battery 18 are connected, allowing for a buffer. Additionally, the predetermined low resistance may be sufficiently below the low end of the threshold charge indicator resistance range such that fluctuations in resistance or measurement error will not erroneously trigger operation in the power delivery mode. To provide one example where the drive end of the interlock circuit 500 is a short 570 or low resistance and the predefined charge indicator resistance 499 is 5 kOhms, the predetermined low resistance may be 500 Ohms. Thus, if the resistance measurement unit 510 measures anything less than 500 Ohms then the battery control system operates in the power delivery mode.

(99) If the measured resistance is not less than the predetermined low resistance at step 804, then step 808 is executed to determine whether the resistance is within a threshold charge indicator resistance range. If so, then the controller 20 operates the battery 18 in the charge mode at step 810 enabling receipt of charge current from a battery charger 490. The threshold charge indicator resistance range is a threshold range of resistances that includes the predefined charge indicator resistance 499. Thus, if the battery charger 490 connects to the charging port 480 of the switch box 7 and is configured to connect a predefined charge indicator resistance 499 to the interlock circuit 500, and the drive circuit portion 520 is disconnected, then the measured resistance by the resistance measurement unit 510 will be within range of the predefined charge indicator resistance 499 and the charge

mode is triggered. To provide one example where the predetermined charge indicator resistance **499** is 5 kOhms, the threshold charge indicator resistance range may be 4 kOhms to 6 kOhms. Thus, if the resistance measurement unit **510** measures a resistance of the interlock circuit **500** that is within that range, then the battery control system operates in the charge mode.

(100) If the resistance is not within the threshold charge indicator resistance range at step **808** (and not less than the predetermined low resistance as described above), then the battery control system **20** operates in the battery **18** in the disconnected mode at step **812** where the battery internal disconnect **550** is controlled to remove the battery **18** from the power circuit **443** such that power delivery from and power receipt to the battery cells are disabled. Thereby, the battery power is conserved, and shock hazards are reduced, when the marine drive **3** is not connected. In the example above, if the resistance measurement unit **510** measures a resistance of the interlock circuit **500** that is greater than 6 kOhms, then the battery control system operates the battery in the disconnected mode.

(101) FIG. **29** shows a perspective view of a battery **718** having a bidirectional port **781** and a charge only port **788** on the housing **722**. The bidirectional port **781** enables current delivery out of the battery, providing current output to a load from the one or more battery cells within the battery **718**. The bidirectional port **781** is configured to provide power and signal sockets housing power and signal pins, respectively, configured to receive and provide power, data, and interlock signal. For example, the bidirectional port **781** may be the battery connector **300** described and shown above, including in FIGS. **18** and **19**. A person of ordinary skill in the art will understand in view of the present disclosure that the bidirectional port and corresponding connector may be constructed with a different pin and socket configuration providing power connection and the same or similar signal connections as described above.

(102) The charge only port **788** is configured to provide power sockets for receiving a charge current that is significantly lower than the discharge current provided through the power sockets of the bidirectional port **781**, and thus the power sockets and corresponding pins of the charge only port **788** arrangement have a smaller diameter and a lower current rating. The charge only port **788** may have, for example, a six pin arrangement, including two power pins configured to deliver a charge current from a battery charger, two interlock pins configured to connect to an interlock circuit **500**, and two data pins such as configured for CAN communication. The bidirectional port **781** and the charge only port **788** are adjacent to one another, positioned next to each other on the top side of the battery housing **722** having the handle **733**. More particularly, the ports **781** and **788** are positioned next to one another in a valley **723** in the housing **722**. The valley **723** is configured to provide some protection for the ports **781** and **788** and for protecting the connection of connectors mated to the ports. In other embodiments, the ports may be positioned elsewhere on the housing **722** and may be positioned together or separated onto different sides and/or portions of the housing **722**. Indicators lights **750** are also located on the top side of the housing **722**, such as configured to illuminate in colors and/or patterns indicating operation and operation mode of the battery **718**.

(103) As described above, the battery **718** is configured to operate in at least three modes, including between a power delivery mode, a charge mode, and a disconnected mode. The battery **718** includes a plurality of switches within the housing **722** and controllable between open and closed states and configured to connect and disconnect each of the ports **781** and **788** from the battery cells within the battery **718**. FIG. **30** shows one example where a battery control system **780** controls three switches SW1, SW2, and SW3 to enable or disable current flow between each of the ports **781** and **788** and the one or more rechargeable battery cells **790** (e.g., a cell pack). Here, the main port switch SW2 controls disconnection of the bidirectional port **781** and charge port switch SW3 controls disconnection of the charge only port **788**. Switch SW1 commonly controls disconnection of both ports **781** and **788** to disable current flow in at least one direction between the ports **781** and **788** and the battery cells **790**.

(104) In the power delivery mode, the battery control system **780** controls the switches SW1-SW3 to permit current flow from the battery cells **790** to the bidirectional port **781** but to prevent current flow from the battery cells **790** to the charge only port **788**. This prevents charge accumulation at the power terminals of the charge only port **788** if no connector is connected, and otherwise prevents current flow into any circuit connected to the charge only port **788**. In the charge mode, the battery control system **780** controls the switches SW1-SW3 to permit current flow from at least one of the ports **781** and **788** to the battery cells **790**. In one embodiment, only one of the bidirectional port **781** and the charge only port **788** is permitted to provide charge current to the battery cells **790** to enable control over the charging rate and prevent multiple chargers from feeding charge current to the cells **790** simultaneously. Thus, only one of the switches SW2 or SW3 are activated to allow current flow and the other is open to prevent current from flowing to the inactive one of the ports **781**, **788**. In the disconnected mode, the battery control system **780** controls the switches SW1-SW3 to prevent any current flow between either of the ports **781** and **788** and the battery cells **790**, thus disconnecting the battery **718** from the output terminals and preventing any connection to a load or any power circuit.

(105) The switches SW1-SW3 may be bidirectional switches, such as relays, operable to (i.e., openable to) prevent any current flow between the ports **781** and **788** and the battery cells **790**. Alternatively, the switches SW1-SW3 may be unidirectional switches, such as unidirectional MOSFET switches comprising a metal oxide field effect transistor (MOSFET), or other semiconductor devices or arrangements operable to prevent only one direction of current flow. Unidirectional switches may be desirable because it enables control over the direction of current flow. The use of MOSFET switches may be desirable due to space and cost constraints. Where MOSFET switches or other unidirectional switches are used, the arrangement in FIG. **30** has particular benefits in that it provides the ability to disconnect current flow into and out of each port **781**, **788** with only three low-cost reliable switches that occupy a small footprint. While the three-switch arrangement shown in FIG. **30** has benefits, particularly where unidirectional switches are used, other switch arrangements may be implemented that enable cutting off current flow to the unused one of the ports **781**, **788**. In other embodiments, two or four switches (or more than four switches) may be used, depending on the type of switch used—e.g., whether the switch prevents bidirectional current flow or prevents unidirectional current flow. For example, in one embodiment where bidirectional switches such as relays are implemented, two switches may be utilized instead of three, including one at the bidirectional port **781** (SW2) and one at the charge only port **788** (SW3). In such an embodiment, the switch SW3 at the charge only port will be open when the power delivery mode is engaged and when the charge mode is engaged and the charge current is being delivered through the bidirectional port **781**. The switch SW2 at the bidirectional port will be open when the charge mode is engaged and a charge current is being delivered through the charge only port **788**.

(106) FIG. **31** provides one example of a battery **718** where three MOSFET switches **901-903** are positioned in the arrangement depicted in FIG. **30**. The diagram illustrates components of the system connectable to the battery **718**, including a load/charger **813** which is alternatively a load or a charger connectable to the bidirectional port **781** of the battery **718**, which may be through the switch box **7**. A battery charger **815** is connectable to the charge only port **788** of the battery **718**. Each of the ports **781**, **788** includes at least four sockets, including at least two power sockets **781a-b** and **788a-b** each configured to mate with power pins in a received connector and at least two interlock circuit sockets **781c-d** and **788c-d** configured to mate with interlock circuit pins, as in the examples described above.

(107) Each MOSFET switch **901-903** includes a MOSFET arranged to selectively block current flow towards or out of the battery cells **790** when the switch is open. The switch **901** is configured as a charge enable switch operable to prevent flow of charge current to the battery cells **790**. Switch **901** is positioned between both of the ports **781** and **788** and the battery cells **790** such that when it is open (e.g., an enhancement mode MOSFET that is not powered), charge current cannot flow from either port **781**, **788** to the battery cells **790** and closing the switch **901** permits charge current to flow from either port **781**, **788** to the cells **790**. Switch **902**, referred to here as the main port switch **902**, is positioned between the bidirectional port **781** and the battery cells **790** and oriented such that when it is open, charge current cannot flow to the bidirectional port **781**. Switch **903**, referred to here as the charge port switch **903**, is positioned between the charge only port **788** and the battery cells **790** and oriented such that when it is open, charge current cannot flow out of the charge only port **788**. The diodes of the main port switch **902** and the charge port switch **903** will allow charge current to flow through to the battery. However, such current will be blocked by the charge enable switch **901** when it is open.

(108) The battery **718** includes a control system **780**, which includes one or more controllers configured to control the charge mode of the battery **718** and thus to control the switches **901-903**. The controllers **820**, **822**, **826** in the battery control system **780** may be communicatively connected and/or some of the controllers may act independently as described below. In the depicted example, the control system **780** includes a main controller

820 (e.g., a battery supervisor and a secondary controller **822**, in conjunction with input from the secondary controller, is configured to receive information regarding the interlock circuit from the interlock detection circuit **824** which is configured to measure a resistance of the interlock circuit, and thus includes a resistance measurement unit as described above. The main controller **820**, in conjunction with input from the secondary controller, is configured to control the charge enable switch **901** and the main port switch **902**. In addition, the control system **780** includes an ideal diode integrated circuit (idIC) **826** configured to control the charge port switch **903**. In contrast to the charge enable switch and the main port switch **902**, which are configured to enable current flow in both directions when the switch is closed, the charge port switch **903** is configured to only permit current to flow in one direction—i.e., to only ever permit current to flow in the direction from the charge only port **788** toward the cells **790**. The idIC **826** is a standalone IC that blocks reverse current flow toward the charge only port **788**.

(109) The battery control system **780** is configured to control the battery mode and battery functions in a way that manages safety and protection of the battery, and is also configured to account for the connection status of each port **781**, **788**. The battery control system **780** is configured to determine the connection status for each of the bidirectional port **781** and the charge only port **788**—i.e., whether a connector is connected to the port and/or whether a permitted load or charge device is connected—based at least in part on a voltage and/or resistance measurements across pairs of sockets in each port **781**.

(110) In the depicted example, voltage sensors **881** and **888** are configured to measure the voltage across respective power sockets **781a-b** and **788a-b**. When a bidirectional connector gets connected to the bidirectional port **781**, the voltage will increase across the power sockets **781a-b**. Likewise, when a charger connector gets connected to the charge only port **788**, the voltage measured across the power sockets **788a-b** will increase. The voltage measurements by the voltage sensors are received and monitored by the main controller **820**, which determines a connected indicator for each port **781** and **788** indicating whether a connector is or is not connected to the respective port. If the voltage measurement for a port **781**, **788** exceeds a threshold, then the main controller **820** determines that the connected indicator for that port is “connected”—i.e., that a connector is connected to, or engaged, in the port such that power could be transferred through the port **781**, **788**. With reference to the embodiments described above, for example, the connected indicator for the bidirectional port **781** indicates whether a connector **100**, **400** of a charger or a load is engaged in the port. If the voltage is less than the threshold, then the main controller **820** determines that the connected indicator for the respective port **781**, **788** is “disconnected.” Alternatively or additionally, the connected indicator may be determined based on the interlock circuit, such as whether a measurable resistance across the interlock sockets **781c-d** and **788c-d** is detected.

(111) The connection status of each port may include the connected indicator indicating whether a connector is connected thereto, as well as a permitted load indicator or permitted charger indicator indicating that a permitted device is connected to the charger. In the depicted example, the permitted load indicator or permitted charger indicator is determined for each port **781**, **788** based on the resistance measurement for the interlock circuit. For example, the resistance across each of the interlock circuit sockets **781c-d** and **788c-d** measured by the interlock detection circuit **824** is compared to one or more thresholds to assess whether the device end of the interlock circuit **500** (see e.g., FIGS. 24-25) provides an expected resistance value. Exemplary logic for such as resistance threshold assessment is described above. For example, a permitted load indicator may be determined for the bidirectional port if the resistance at the interlock circuit sockets **781c-d** is less than a low resistance threshold. A permitted charger indicator may be determined for the bidirectional port or the charge only port, since a charger can be connected to either port, such as if the resistance at the interlock circuit sockets **781c-d** or **788c-d** is within a threshold charge indicator resistance range.

(112) If a connected indicator for one of the ports **781**, **788** indicates connection and a permitted load or charger is indicated, then the battery control system **780** will engage the power delivery mode or the charge mode accordingly, and the switches **901-903** are controlled accordingly as described above. The battery control system **780** may be configured to engage the disconnected mode if the connected indicator for both of the ports **781**, **788** indicates that no connector is connected or if the permitted load indicator or permitted charger indicator does not indicate that a permitted device is connected. Additionally, the control system **780** may be configured to engage the disconnected mode if the connected indicator for both ports **781**, **788** indicates that both ports are connected. In other words, if a connector is engaged at each of the bidirectional port **781** and the charge only port **788**, then the control system **780** engages the disconnected mode and opens all three switches **901-903** to disable charge and discharge of the battery. Thereby, the control system **780** is able to ensure protection of the battery, including being able to control the charge rate of the battery by only enabling connection of one charger at a time and including ensuring that a charger **815** connected to the charge only port **788** is not delivering charge current when the power delivery mode is engaged (and thus the switches **901** and **902** are closed).

(113) The battery control system **780** may also be configured to control the switches **901** and **902** based on current flow measured in the battery **718**, which in the depicted embodiment is at the shunt resistor **840**. When the current flow reaches a threshold level, and depending on the mode and which port is being used (e.g., based on the connected indicators described above), the main controller **820** will close one or both of the switches **901** and **902** to enable power transfer (charge or discharge) without incurring a voltage drop over the diodes. In the power delivery mode, for example, the control system **780** may close both switches **901** and **902** (not just the main port switch **902**) to avoid a voltage drop over the diode of charge enable switch **901**. In the charge mode where the bidirectional port **781** is being used for charging, the control system **780** may close both switches **901** and **902** (not just the charge enable switch **901**) to avoid the voltage drop over the diode of the main port switch **902**.

(114) FIGS. 32 and 33 are flow charts demonstrating embodiments of methods of controlling charging of the battery **718** with a bidirectional port **781** and a charge only port **788**. Turning first to FIG. 32, the connection status of the bidirectional port is detected at step **912**, such as whether that port **781** is connected to something and whether that something is a load or a charger. The connection status of the charge only port **788** is detected at step **914**, such as whether that port **788** is connected to a charger. For example, the battery control system **780** may be configured to detect the connection status of the bidirectional port **781** and the charge only port **788** based on at least one of a resistance measurement across two sockets **781a-d** and **788a-d** in each of the of the bidirectional port and the charge only port and a voltage measurement across two sockets in each of the of the bidirectional port and the charge only port. An operation mode is selected for the battery at step **916** based on the connection status of each of the ports **781** and **788**, such as selecting one of the power delivery mode, the charge mode, and the disconnected mode. The plurality of switches are then controlled at step **918** to effectuate the selected battery mode, and thus to discharge of the battery in power delivery mode, intake of charge current in charge mode, or disconnection of the battery cell pack **790** from the ports **781**, **788**.

(115) FIG. 33 depicts another embodiment of a method wherein the connection status of each port **781**, **788** are detected based on voltage and current measurements at that port and the mode is selected accordingly. A voltage differential across the power sockets **781a-b** at the bidirectional port **781** is measured at step **920**. A connection status of the bidirectional port is then determined at step **922** based on the voltage, such as by comparing the voltage to a voltage threshold indicating that the power sockets **781a-b** are connected to a power circuit. The connection status is assessed at step **924**. If the bidirectional port is connected, then further analysis is conducted to assess what device is connected. If the bidirectional port is not connected at step **924**, then the logic proceeds to step **926** and begins assessing the charge only port **788**.

(116) Assuming that the bidirectional port **781** is connected, step **926** is executed to measure the resistance across the interlock circuit pins **781c-d**, which provides the resistance of the interlock circuit **500**. As described above, the interlock circuit is designed to include predefined resistances in each of a permitted load (e.g., short circuit **570** in marine drive **3**) and a permitted charger (e.g., 500 kOhm or other predefined large resistance **499** in charger **490**). Accordingly, step **928** is executed to determine whether a permitted charger is connected based on the measured resistance, such as whether the measured resistance is within a threshold charge indicator resistance range. If not, then step **930** is executed to determine whether the measured resistance indicates that a permitted load is detected, such as whether the measured resistance is less than a predetermined low resistance or within some range associated with the predefined resistance of a permitted load. If a permitted charger is detected at step **928** or a permitted load is detected at step **930**, then step **930** is executed to make sure that the charge only port **788** is not connected. If both ports are connected, then the disconnected mode is engaged to protect the battery **718** and to prevent unintended current backflow through either port **781**, **788**. Thereby, the logic

is configured to allow connection to power exchange with only one port at a given time. Provided that both ports are not connected at step **932**, then the plurality of switches SW1-SW3 or **801-803** are controlled at step **934** to engage the power delivery mode. If the bidirectional port **781** is connected but neither a permitted charger or a permitted load are detected, then the battery engages the disconnected mode at step **950** such that it does not permit any power transfer with the non-permitted device. For example, engaging the disconnected mode may include opening all of the switches SW1-SW3 or **801-803**.

(117) Assuming that the bidirectional port **781** has a “disconnected” status at step **924**, then the voltage across the power sockets **788a-b** is measured at step **936** and the connected status is determined at step **938** for the charge only port **788**. If the charge only port **788** is also disconnected, then the disconnected mode is engaged at step **950**. If the charge only port is connected at step **940**, then the resistance at the interlock circuit sockets **788c-d** is measured at step **942**. The resistance is compared to one or more thresholds at step **946** to determine whether the permitted charger is connected. If not, then the disconnected mode is engaged at step **950**. If a permitted charger is connected, then the charge mode is engaged at step **948**. For example, the switches SW1-SW3 or **901-903** are operated to permit flow of charge current from the charge only port **788** to the cell pack **790** and to prevent backflow of current to the bidirectional port **781**, as described above.

(118) FIG. **34** depicts another embodiment of a method **910** for mode selection, wherein the connection status of each port **781**, **788** are detected based on voltage and current measurements at each port and the battery selects its mode accordingly. Thereby, determination of connection of a proprietary device configured to connect to the interlock circuit **500** is prioritized in the connection status detection logic. In this embodiment, the connection status is initially determined based on resistance across the interlock sockets **781c-d** and **788c-d**. The method **910** is initiated at step **1000** when the connected status for the bidirectional port **781** or the charge only port **788** becomes “connected”—i.e., a device is connected by a connector engaged in the port **781**. For example, the “connected” status may be identified when a measurable resistance is detected across the interlock sockets **781c-d** and **788c-d**. Alternatively, the connected indicator may be determined based on a voltage measurement across the power sockets as described above. Step **1002** is then executed to determine whether a load or a charger are connected, such as based on comparison of the measured resistance of the interlock circuit to one or more thresholds as described above. If a load is connected (e.g., the resistance of the interlock circuit is less than a predetermined low resistance), then it is assumed that the port is the bidirectional port **781** and step **1004** is executed to check whether the charge only port **788** is also connected. Namely, if the connected indicator for the charge only port **788** indicates a connection (and thus connectors are in both ports **781**, **788**), then an error is detected and the disconnected mode is engaged.

(119) If the connected indicator for the charge only port **788** indicates that there is not a connection there, then the power delivery mode is engaged at step **1006** to begin providing power to a load, such as a marine drive **3** (or other permitted load) that is detected based on the interlock circuit—i.e., detection of a specified resistance. Here, steps are then executed to determine whether the battery executing the logic is the only one present, or whether one or more additional batteries (e.g., **18b-d**) are present. Battery information is requested at step **1008**. Namely, charge level and mode information is communicated between the batteries so that power provision operations can be coordinated as necessary. If other batteries are present at step **1010**, then the parallel battery power delivery mode is engaged at step **1012**. If no other batteries are present, then the single battery power delivery mode **1011** is engaged.

(120) Returning to step **1002**, if the resistance of the interlock circuit does not fall within any of the expected ranges for a permitted load or a permitted charger, then the battery is not mated and is maintained in disconnected mode at step **1003**. If, on the other hand, a charger is detected based on the interlock circuit (e.g., the measured resistance of the interlock circuit is within the threshold charge indicator resistance range described above), then a permitted charger is determined to be mated at step **1114**. Logic is then executed at step **1116** to determine which port is connected to a charger. If the charge only port **788** is connected, then a check is performed to ensure that the bidirectional port **781** is not also connected. Here, the voltage across sockets (e.g., power sockets **781a-b**) in the bidirectional port **781** is measured at step **1117** and logic is performed at step **1118** to determine whether the bidirectional port **781** is also connected (e.g., the voltage across the power sockets **781a-b** is non-zero and within an expected range for connection to a charger (or a load)). If so, then both ports **781** and **788** are connected and the disconnected mode **1119** is engaged to protect the battery **18**. Assuming that the bidirectional port **781** is not also connected, then the charge mode is engaged at step **1120** where charging is performed via the charge only port **788**—e.g., the switches SW1 and SW3 are operated to accept a charge current from the charge only port **788** to the battery cell pack **790** and SW2 is open to prevent current flow to the bidirectional port **781**. Logic is performed at step **1122** to assess the charge state of the battery. Provided that the bidirectional port **781** remains disconnected, then charging continues via the charge only port **788** until the battery is fully charged at step **1122**, at which point the disconnected mode is engaged at step **1123**.

(121) Returning to step **1116**, if the interlock circuit connection indicator assessment indicates that the charge only port **788** is not connected, then the bidirectional port **781** is determined to be the port connected for charging. Here, steps are executed to determine whether the battery executing the logic is the only one present or whether one or more additional batteries (e.g., **18b-d**) are present and whether this battery is at or below the charge level of the other batteries. Battery information is requested at step **1028**. Namely, charge level and mode information is communicated between the batteries so that charging operations can be coordinated as necessary. Logic is performed at step **1130** to determine whether this battery's charge level (e.g., SOC, battery voltage level, etc.) is less than or equal to any other battery reporting in the group that is not disconnected. Only the battery or batteries with the lowest charge levels will be operated in charging mode to avoid current flow between batteries **18a-d** connected in parallel. Logic is then executed at step **1132** to double check that there are no other batteries already charging (i.e., in charge mode) that have a higher charge level. If so, then a delay is engaged before requesting and reassessing the cluster information from the other batteries.

(122) If no other batteries with a higher charge level are present at step **1032**, then then a check is performed to ensure that the charge only port **788** is not also connected. Here, the voltage across sockets (e.g., power sockets **788a-b**) in the charge only port **788** is measured at step **1137** and logic is performed at step **1138** to determine whether the charge only port **781** is also connected (e.g., the voltage across the power sockets **788a-b** is non-zero and within an expected range for connection to a charger (or a load)). If so, then both ports **781** and **788** are connected and the disconnected mode **1139** is engaged to protect the battery **18**. Assuming that the charge only port **788** is not also connected, then the charge mode is engaged at step **1140** where charging is performed via the bidirectional port **781**—e.g., the switches SW2 and SW3 are operated to accept a charge current from the port **781** to the battery cell pack **790** and SW1 is open to prevent current flow to the charge only port **788**. Logic is performed at step **1142** to assess the charge state of the battery. Provided that the charge only port **788** remains disconnected, then charging continues via the bidirectional port **781** until the battery is fully charged at step **1142**, at which point the disconnected mode is engaged at step **1143**.

(123) If a new battery **18** is connected in parallel at any time during the above-described process (e.g., connected to the switch box **7**), then upon connection detected at step **1150** all batteries in the cluster may be pulled out of their existing modes and the mode logic may be reperformed to guarantee safe and proper operation of the batteries **18a-d**. For example, additional battery detection may be based on information communicated between the batteries (e.g., via CAN), and the batteries may be configured such that when a new battery is added it communicates a message and/or when any one battery sees a new battery it communicates a notice to all of the other batteries. The mode reassessment may be performed quickly so that no noticeable disruption to battery operation is detected by the user.

(124) Unless otherwise specified or limited, the phrases “at least one of A, B, and C,” “one or more of A, B, and C,” and the like, are meant to indicate A, or B, or C, or any combination of A, B, and/or C, including combinations with multiple instances of A, B, and/or C. Likewise, unless otherwise specified or limited, the terms “mounted,” “connected,” “linked,” “supported,” and “coupled” and variations thereof are used broadly and encompass both direct and indirect mountings, connections, supports, and couplings. Further, unless otherwise specified or limited, “connected” and “coupled” are not restricted to physical or mechanical connections or couplings and can include electrical couplings. “Electrical” couplings or connections can include, but are not limited to, power and signal connections.

(125) In the present description, certain terms have been used for brevity, clarity, and understanding. No unnecessary limitations are to be implied

therefrom beyond the requirement of the prior art because such terms are used for descriptive purposes only and are intended to be broadly construed. It is to be understood that the invention is not limited in its application to the details of construction and the arrangement of components set forth in the foregoing description or illustrated in the drawings. The invention is capable of other embodiments and of being practiced or of being carried out in various ways. The different assemblies described herein may be used alone or in combination with other systems. Various equivalents, alternatives, and modifications are possible within the scope of the appended claims. The methods herein are not limited to being performed in the order described and could be performed in any logical order.

Claims

1. A marine battery configured to removably connect to a load to power at least one electric motor, the marine battery comprising: at least one battery cell; a bidirectional port configured to provide current output to the load from the at least one battery cell and to receive a charge current from a battery charger to charge the at least one battery cell; a charge only port configured to receive charge current from the battery charger to charge the at least one battery cell; a plurality of switches positioned between the bidirectional port, the charge only port, and the at least one battery cell; and a battery control system configured to detect a connection status of at least one of the bidirectional port and/or the charge only port and, based on the connection status, to control the plurality of switches to transition the marine battery between a power delivery mode where current can flow from the at least one battery cell out of the bidirectional port, a charge mode where current can flow from the bidirectional port or the charge only port to the at least one battery cell, and a disconnected mode where current cannot flow between the bidirectional port or the charge only port and the at least one battery cell.
2. The marine battery of claim 1, wherein the battery control system is further configured to: enable the power delivery mode only if the connection status of the bidirectional port is connected and the connection status of the charge only port is disconnected; and enable the charge mode only if the connection status of only one of the bidirectional port and the charge only port is connected.
3. The marine battery of claim 1, wherein the battery control system is further configured to enable the disconnected mode if the connection status of the bidirectional port is disconnected and the connection status of the charge only port is disconnected or if the connection status of the bidirectional port is connected and the connection status of the charge only port is connected.
4. The marine battery of claim 1, wherein the battery control system is configured to detect the connection status of the bidirectional port and the charge only port based on at least one of a resistance measurement across sockets in each of the of the bidirectional port and the charge only port and a voltage measurement across sockets in each of the of the bidirectional port and the charge only port.
5. The marine battery of claim 4, wherein the connection status of the bidirectional port is based on a connected indicator indicating whether a connector is or is not connected to the bidirectional port, and a permitted load indicator indicating whether a permitted load is or is not connected to the bidirectional port or a permitted charger indicator indicating whether a permitted charger is or is not connected to the bidirectional port, and wherein the connection status of the charge only port includes a connected indicator indicating whether a connectors is or is not connected to the charge only port and a permitted charger indicator indicating whether a permitted charger is or is not connected to the charge only port.
6. The marine battery of claim 4, wherein each of the bidirectional port and the charge only port include two power sockets configured to receive two power pins from a respective connector, and wherein the battery control system is configured to determine the connection status for each of the bidirectional port and the charge only port based at least in part on a voltage measurement across the respective power sockets.
7. The marine battery of claim 4, wherein each of the bidirectional port and the charge only port include two interlock circuit sockets configured to receive two interlock circuit pins from a respective connector to connect to an interlock circuit, and wherein the battery control system is configured to determine the connection status for each of the bidirectional port and the charge only port based at least in part on a resistance measurement across the respective interlock circuit sockets.
8. The marine battery of claim 1, wherein the plurality of switches comprises three unidirectional switches, including a main port switch operable to prevent current flow out of the bidirectional port, a charge port switch operable to prevent current flow out of the charge only port, and a charge enable switch operable to prevent current flow to the at least on battery cell.
9. The marine battery of claim 8, wherein each of the three unidirectional switches is a MOSFET.
10. The marine battery of claim 1, wherein the load is a marine drive comprising an electric motor powerhead.
11. A rechargeable marine battery system configured to removably connect to a load comprising at least one electric motor, the system comprising: a plurality of marine batteries each marine battery comprising: at least one battery cell; a bidirectional port configured to provide current output to the load from the at least one battery cell and to receive a charge current from a battery charger to charge the at least one battery cell in the marine battery; a charge only port configured to receive charge current from the battery charger to charge the at least one battery cell; a plurality of switches positioned between the bidirectional port, the charge only port, and the at least one battery cell; and a battery control system configured to detect a connection status of at least one of the bidirectional port and the charge only port and, based on the connection status, to control the plurality of switches to transition the marine battery between a power delivery mode where current can flow from the at least one battery cell out of the bidirectional port, a charge mode where current can flow from the bidirectional port or the charge only port to the at least one battery cell, and a disconnected mode where current cannot flow between the bidirectional port or the charge only port and the at least one battery cell; and a switch box configured to connect the plurality of marine batteries in parallel to the load and provide for simultaneous charging of all of the plurality of batteries.
12. The system of claim 11, wherein each of the plurality of marine batteries is configured to receive a charge current through the bidirectional port from a battery charger connected through the switch box, and to receive a charge current through the charge only port from a battery charger connected directly to the charge only port.
13. The system of claim 11, wherein each of the plurality of marine batteries is configured to permit receipt of the charge current through only one of the bidirectional port or the charge only port at a time.
14. A method of controlling a marine battery, wherein the marine battery includes at least one battery cell, a bidirectional port, and a charge only port and a plurality of switches positioned between the bidirectional port, the charge only port, and the at least one battery cell, the method comprising: detecting a connection status of at least one of the bidirectional port and/or the charge only port; and based on the connection status of each port, controlling the plurality of switches to transition the marine battery between a power delivery mode where current can flow from the at least one battery cell out of the bidirectional port, a charge mode where current can flow from the bidirectional port or the charge only port to the at least one battery cell, and a disconnected mode where current cannot flow between the bidirectional port or the charge only port and the at least one battery cell.
15. The method of claim 14, wherein detecting the connection status of the bidirectional port and the charge only port includes measuring at least one of a resistance across sockets in each of the of the bidirectional port and the charge only port and a voltage across sockets in each of the of the bidirectional port and the charge only port and determining the connection status of each of the of the bidirectional port and the charge only port based on the resistance and/or the voltage measured therein.
16. The method of claim 15, further comprising: determining a connected indicator for the bidirectional port based on the voltage at the bidirectional port indicating whether a connector is or is not connected to the bidirectional port; determining a permitted load indicator for the bidirectional port based on the resistance at the bidirectional port indicating whether a permitted load is or is not connected to the bidirectional port or determining a permitted charger indicator for the bidirectional port based on the resistance at the bidirectional port indicating whether a permitted charger is or is

not connected to the bidirectional port; wherein the connection status of the bidirectional port is based on the connected indicator for the bidirectional port and the permitted load indicator for the bidirectional port; determining a connected indicator for the charge only port based on the voltage at the charge only port indicating whether a connector is or is not connected to the charge only port; determining a permitted charger indicator for the charge only port based on the resistance at the charge only port indicating whether the permitted charger is or is not connected to the charge only port; and wherein the connection status of the charge only port is based on the connected indicator for the charge only port and the permitted charger indicator.

17. The method of claim 14, wherein the plurality of switches comprises three unidirectional switches, including a main port switch operable to prevent current flow out of the bidirectional port, a charge port switch operable to prevent current flow out of the charge only port, and a charge enable switch operable to prevent current flow to the at least one battery cell, wherein controlling the marine battery between the power delivery mode, the charge mode, and the disconnected mode includes controlling the main port switch, the charge port switch, and the charge enable switch.

18. The method of claim 17, further comprising closing the main port switch and opening the charge port switch to enable the power delivery mode.

19. The method of claim 18, further comprising closing the charge enable switch in the power delivery mode.

20. A method of controlling charging of a battery, wherein the battery includes at least one battery cell, a bidirectional port, and a charge only port, the method comprising: determining a connected indicator for the bidirectional port indicating whether a connector is or is not connected to the bidirectional port based on a voltage at the bidirectional port; determining a permitted load indicator indicating whether a permitted load is or is not connected to the bidirectional port based on a resistance at the bidirectional port, or determining a permitted charger indicator indicating whether a permitted charger is or is not connected to the bidirectional port based on the resistance at the bidirectional port; determining a connected indicator for the charge only port indicating whether a connector is or is not connected to the charge only port based on the voltage at the charge only port; determining a permitted charger indicator for the charge only port indicating whether the permitted charger is or is not connected to the charge only port based on the resistance at the charge only port; determining a connection status of the bidirectional port based on the connected indicator for the bidirectional port and the permitted load indicator for the bidirectional port; determining a connection status of the charge only port based on the connected indicator and the permitted charger indicator for the charge only port, based on the connection status of the bidirectional port and the connection status of the charge only port, controlling the battery between a power delivery mode where current can flow from the at least one battery cell out of the bidirectional port, a charge mode where current can flow from the bidirectional port or the charge only port to the at least one battery cell, and a disconnected mode where current cannot flow between the bidirectional port or the charge only port and the at least one battery cell.
