

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413027
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Ridgeway; David et al.

Shallow electrical protection device (GFCI, AFCI, and AFCI/GFCI) system and method

Abstract

A device may include a housing including a face plate. A device may include a plurality of sensing cores each configured to receive a current flow through a center cavity, the current flow defining a current flow direction through the center cavity, wherein the current flow direction is parallel to the face plate.

Inventors:	Ridgeway; David (Milford, CT), Padro; Kenny (Hamden, CT)
Applicant:	Hubbell Incorporated (Shelton, CT)
Family ID:	66697393
Assignee:	Hubbell Incorporated (Shelton, CT)
Appl. No.:	18/397717
Filed:	December 27, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240128693 A1	Apr. 18, 2024

Related U.S. Application Data

continuation parent-doc US 18096813 20230113 US 11862906 child-doc US 18397717
continuation parent-doc US 17698690 20220318 US 11557862 20230117 child-doc US 18096813
division parent-doc US 16212141 20181206 US 11309667 20220419 child-doc US 17698690
us-provisional-application US 62595760 20171207

Publication Classification

Int. Cl.: H01R13/713 (20060101); G01R11/04 (20060101); H01H71/50 (20060101); H01H71/58 (20060101); H01H83/04 (20060101); H01H83/14 (20060101); H01R13/71 (20060101); H01R24/76 (20110101); H01R24/78 (20110101); H01R25/00 (20060101); H01R103/00 (20060101)

U.S. Cl.:

CPC H01R13/7135 (20130101); G01R11/04 (20130101); H01H71/505 (20130101); H01H71/58 (20130101); H01H83/04 (20130101); H01R13/71 (20130101); H01H83/144 (20130101); H01R13/713 (20130101); H01R24/76 (20130101); H01R24/78 (20130101); H01R25/006 (20130101); H01R2103/00 (20130101)

Field of Classification Search

CPC: H01R (13/7135); H01R (13/71); H01R (13/713); H01R (24/78); H01R (25/006); H01R (2103/00); H01R (24/76); H01H (83/04); H01H (71/505); H01H (71/58); H01H (83/144); G01R (11/04)

USPC: 361/42

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
4521824	12/1984	Morris	361/45	H01H 71/50
4549241	12/1984	Morris	361/45	H01H 83/04
6246558	12/2000	DiSalvo et al.	N/A	N/A
6282070	12/2000	Ziegler et al.	N/A	N/A
7944331	12/2010	Porter et al.	N/A	N/A
8830015	12/2013	Padro et al.	N/A	N/A
8861146	12/2013	McMahon	361/45	H01H 47/22
9543742	12/2016	Weeks et al.	N/A	N/A
9774181	12/2016	Bonasia	N/A	H01H 83/04
11309667	12/2021	Ridgeway	N/A	H01H 83/04
2004/0218316	12/2003	Germain et al.	N/A	N/A
2007/0133136	12/2006	Germain	N/A	N/A
2007/0168635	12/2006	Allen et al.	N/A	N/A
2008/0158788	12/2007	Darr et al.	N/A	N/A
2009/0184787	12/2008	Weeks	335/18	H01H 83/04
2010/0026426	12/2009	Mortun	N/A	N/A
2012/0199668	12/2011	Gesicki et al.	N/A	N/A
2013/0057990	12/2012	Finlay, Sr. et al.	N/A	N/A
2013/0241677	12/2012	Padro et al.	N/A	N/A
2014/0322049	12/2013	Graybill	N/A	N/A
2015/0200533	12/2014	Simonin	361/49	H02H 3/05
2019/0181594	12/2018	Ridgeway	N/A	H01R 13/71

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
1162576	12/1983	CA	N/A

2809057	12/2012	CA	H01H 83/144
2439127	12/2000	CN	N/A
1397973	12/2002	CN	N/A
1489168	12/2003	CN	N/A
1759513	12/2005	CN	N/A
1815664	12/2005	CN	N/A
101752152	12/2009	CN	N/A
201541122	12/2009	CN	N/A
202550296	12/2011	CN	N/A
105164881	12/2014	CN	N/A
H0785769	12/1994	JP	N/A
2016085738	12/2015	WO	N/A

OTHER PUBLICATIONS

Padro Kenny; Title: Compact latching mechanism for switched electrical device; entire specification and drawings (Year: 2013). cited by examiner

PCT/US2018/064269 International Search Report and Written Opinion dated Apr. 25, 2019 (13 pages). cited by applicant

European Application No. 18886862 extended European search report and European search opinion dated Jul. 19, 2021. cited by applicant

Chinese Patent Application No. 20188081926.4 First Office Action issued by the China National Intellectual Property Administration (and translation) dated Jul. 7, 2021. cited by applicant

Chinese Patent Application No. 20188081926.4 Second Office Action issued by the China National Intellectual Property Administration (and translation) dated Dec. 3, 2021. cited by applicant

European Patent Application No. 24180288.3 extended European search report and European search opinion dated Sep. 11, 2024. cited by applicant

Chinese Patent Application No. 202210812062.7 First Office Action issued by the China National Intellectual Property Administration (and translation) dated Mar. 28, 2025. cited by applicant

Primary Examiner: Patel; Dharti H

Attorney, Agent or Firm: Michael Best & Friedrich LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION(S) (1) This application claims priority to U.S. patent application Ser. No. 18/096,813, filed Jan. 13, 2023, which claims priority to U.S. patent application Ser. No. 17/698,690, filed Mar. 18, 2022, which claims priority to, and is a divisional of, U.S. patent application Ser. No. 16/212,141, filed Dec. 6, 2018, which claims priority to U.S. Provisional Patent Application No. 62/595,760, filed Dec. 7, 2017, the entire contents of both of which are expressly incorporated herein by reference. (2) This application contains subject matter related to subject matter contained in U.S. Pat. No. 8,830,015 B2 entitled, “COMPACT LATCHING MECHANISM FOR SWITCHED ELECTRICAL DEVICE,” by Kenny Padro et al., which is assigned to the assignee hereof, and the entire contents of which are expressly incorporated herein by reference.

FIELD

(1) Embodiments relate to switched electrical devices, more particularly to circuit interrupting

devices.

SUMMARY

(2) Circuit interrupting devices, such as ground fault circuit interrupter (GFCI) devices, switch to a “tripped” or unlatched state from a “reset” or latched state when one or more conditions is detected. GFCI devices having contacts that are biased toward the open position require a latching mechanism for setting and holding the contacts in a closed position. Likewise, switched electrical devices having contacts that are biased toward the closed position require a latching mechanism for setting and holding the contacts in an open position. Examples of conventional types of devices include devices of the circuit interrupting type, such as circuit breakers, arc fault interrupters, and GFCIs, to name a few.

(3) Many electrical receptacles have built-in ground fault protection circuitry, i.e., GFCI receptacles. Such protection circuitry and the associated mechanisms normally take up a substantial amount of the physical space within a receptacle housing, the size of which is limited by the standard junction boxes in which they must fit. The embodiments disclosed in the present application attempt to solve these problems by providing more compact devices, allowing for shallower receptacles and more space for other elements and/or features.

(4) One embodiment discloses an electrical outlet receptacle comprises a housing including a face plate and a plurality of sensing cores each configured to receive a current flow through a center cavity. The current flow defines a current flow direction through the center cavity, wherein the current flow direction is parallel to the face plate, and the plurality of sensing cores are placed symmetrically in a translational direction across the electrical outlet receptacle.

(5) Another embodiment discloses an electrical outlet receptacle comprises a housing including a face plate and a sensing core configured to receive a current flow through a center cavity. The current flow defines a current flow direction through the center cavity of the sensing core, wherein the current flow direction is parallel to the face plate.

(6) Another embodiment discloses an electrical outlet receptacle comprises a circuit board defining a first plane, a set of fixed contacts, a set of movable contacts, a solenoid having a central axis perpendicular to the first plane, a carriage movable axially along the solenoid and configured to interact with the set of movable contacts, a lifting shelf slidably coupled to a slot in the carriage and movable in a translational direction perpendicular to the central axis of the solenoid, a slide mechanism coupled to the lifting shelf and movable in the translational direction of the lifting shelf, a reset plunger with a portion extending through a first end of the solenoid and axially movable therein, and an armature movable axially along the portion of the reset plunger extending through the solenoid. The circuit board includes at least one contact pad. The solenoid includes a second end opposite the first end. The carriage is adapted to advance the set of movable contacts to form electrical communication with the set of fixed contacts during resetting of the electrical outlet receptacle. The lifting shelf includes a latching portion. The slide mechanism includes a cam surface to transform a downward force to a translational force applied to the coupled lifting shelf. The reset plunger includes an intermediate collar configured to engage to the latching portion of the lifting shelf. The armature includes a slanted projection configured to contact the cam surface of the slide mechanism and provide the downward force on the cam surface.

(7) Other aspects of the application will become apparent by consideration of the detailed description and accompanying drawings.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) The aspects and features of various exemplary embodiments will be more apparent from the description of those exemplary embodiments taken with reference to the accompanying drawings,

in which:

- (2) FIG. 1 is a front perspective view of a receptacle incorporating the resettable switching apparatus of the application;
- (3) FIG. 2 is a front perspective view of the receptacle of FIG. 1, with the front and rear covers and tamper-resistant mechanisms removed;
- (4) FIG. 3 is a front perspective view showing a configuration of a set of movable contacts and a set of fixed contacts according to one embodiment;
- (5) FIG. 4A is a front perspective view of the carrier assembly of the receptacle according to one embodiment;
- (6) FIG. 4B is a front perspective view of the carrier assembly of the receptacle according to another embodiment;
- (7) FIG. 5A is a front perspective view of the core assembly of the receptacle;
- (8) FIG. 5B is a front perspective view showing a configuration of a sense transformer core according to one embodiment;
- (9) FIG. 5C is a front perspective view showing a configuration of a sense transformer core according to another embodiment;
- (10) FIG. 6A is a side perspective view of the core assembly of the receptacle according to one embodiment;
- (11) FIG. 6B is a side perspective view of the core assembly of the receptacle according to another embodiment;
- (12) FIG. 7 is an exploded front perspective view of a solenoid assembly according to one embodiment;
- (13) FIG. 8 is an assembled front perspective view of the solenoid assembly of FIG. 7;
- (14) FIG. 9 is a side perspective view of the reset plunger assembly and carriage of the solenoid assembly according to one embodiment;
- (15) FIG. 10 is another side perspective view from a different angle of the reset plunger assembly and carriage similar to FIG. 9;
- (16) FIG. 11 is a side perspective view of the reset plunger assembly and latching mechanism according to one embodiment;
- (17) FIG. 12A shows a two-piece latching mechanism design according to one embodiment of the present application;
- (18) FIGS. 12B-12C show a one-piece latching mechanism design according to one embodiments of the present application;
- (19) FIG. 13 is a bottom perspective view of the solenoid assembly of FIG. 7;
- (20) FIG. 14A is a side perspective view of the solenoid assembly in a resting position;
- (21) FIG. 14B is a side perspective view of the reset plunger assembly and latching mechanism of the solenoid assembly shown in FIG. 14A;
- (22) FIGS. 15-18 are side perspective views of the reset plunger assembly and latching mechanism in progressive states during the resetting process; and
- (23) FIG. 19 is a cross-sectional view of the solenoid assembly in a reset position.
- (24) FIG. 20 is a perspective view of a printed circuit board and coils of a receptacle according to some embodiments.
- (25) FIG. 21 is a perspective view of the printed circuit board and coils of FIG. 20 coupled to a manifold of a receptacle according to some embodiments.

DETAILED DESCRIPTION OF EXEMPLARY EMBODIMENTS

- (26) Before any embodiments of the application are explained in detail, it is to be understood that the application is not limited in its application to the details of construction and the arrangement of components set forth in the following description or illustrated in the following drawings. The application is capable of other embodiments and of being practiced or carried out in various ways.
- (27) As described herein, terms such as “front,” “rear,” “side,” “top,” “bottom,” “above,” “below,”

“upwardly,” and “downwardly” are intended to facilitate the description of the electrical receptacle of the application, and are not intended to limit the structure of the application to any particular position or orientation.

(28) Exemplary embodiments of devices consistent with the present application include one or more of the novel mechanical and/or electrical features described in detail below. Such features may include a compactly positioned sensing core, a vertical solenoid, and a latching mechanism including a lifting shelf, a slide mechanism, an intermediate collar, and a cam surface. In some exemplary embodiments of the present application, multiple features listed above are incorporated into one element whereas in other exemplary embodiments, each feature is distinct from one another and coupled to interact with each other. The novel mechanical and/or electrical features detailed herein efficiently utilize the space within the device housing to provide more area for additional features and/or components.

(29) FIG. 1 illustrates a perspective view of a GFCI receptacle **10** according to one embodiment of the application. The GFCI receptacle **10** includes a front cover **12** having an outlet face **14** with phase **16**, neutral **18**, and ground **20** openings. The outlet face **14** also has a central opening **22** for a reset button **24** adjacent to an opening **26** for a test button **28**. Rear cover **36** is secured to front cover **12** by screws (not shown or enumerated). Screw terminals **38** mechanically and/or electrically couple wires when wiring the receptacle **10**. A ground yoke/bridge assembly **40** includes standard mounting ears **42** that protrude from the ends of the receptacle **10**.

(30) Referring to FIG. 2, the GFCI receptacle **10** with the front cover **12**, rear cover **36**, and tamper-resistant mechanisms (not enumerated) removed shows phase terminal **30**, neutral terminal **32**, ground terminal **34**, and a circuit board **58**. The phase, neutral, and ground terminals **30**, **32**, **34** are respectively configured to receive electrical plugs **35** of a connecting electrical device, such as a power cord. The circuit board **58** provides control and physical support for most of the working components of the receptacle **10**. The phase and neutral terminals **30**, **32** may be movable, supported and energized through bus bars **44**, **46**, respectively. Bus bars **44**, **46** act as cantilevered arms that support a set of contacts **48**. As shown in the embodiment of FIG. 3, the set of contacts **48** include a set of movable contacts **48A** and a set of fixed contacts **48B**. Bus bars **44**, **46** respectively serve as cantilevered support for the set of movable contacts **48A** while the set of fixed contacts **48B** is supported by a carrier assembly **8**. This configuration may be reversed or changed in other embodiments of the application not described in detail herein. In various embodiments, an indicator light **L** may be included in the GFCI receptacle **10** and configured to indicate the state of the GFCI receptacle **10**.

(31) The resiliency of the cantilevered support provided by the bus bars **44**, **46** bias the set of movable contacts **48A** away from the set of fixed contacts **48B**. A latching mechanism including a movable carriage, described in further detail in the following figures, is used to engage with the set of movable contacts **48A**, thereby pushing the set of movable contacts **48A** in an upward direction to engage the set of fixed contacts **48B** in a closed position during resetting of the GFCI receptacle **10**. This upward movement of the set of movable contacts **48A** also causes corresponding upward movement in the attached phase and neutral terminals **30**, **32** closer to the front cover **12** of the receptacle **10**. Electricity may then be delivered from an external power source to the receptacle openings **16**, **18**, **20**. In other embodiments, the resiliency of the cantilevered bus bars **44**, **46** may bias the set of movable contacts **48A** toward the set of fixed contacts **48B**, and a latching mechanism may be employed in reverse to engage and hold the set of movable contacts **48A** away from the set of fixed contacts **48B** in an open position during tripping of the GFCI receptacle **10**. The phase and neutral terminals **30**, **32** will likewise increase in distance from the front cover **12**, thereby prohibiting the flow of electricity between the external power source and the receptacle openings **16**, **18**, **20**. Various embodiments of the latching mechanism may be used by various application designs, the details of each are not disclosed in detail herein.

(32) Referring to FIG. 4A, in addition to providing structural support for the set of fixed contacts

48B, the carrier assembly **8** also provides structural support for a sense transformer core **50** and conductor windings **52**, **54**. In another embodiment shown in FIG. **4B**, the carrier assembly **8** may provide structural support for multiple sets of sense transformer cores **50**, **51**, as described in further detail below. Various placements of sense transformer core(s) **50**, **51** may be possible and will be further described in the following figures.

(33) FIG. **5A** illustrates a perspective view of a core assembly **2** of the GFCI receptacle **10** depicted in FIG. **1**. A solenoid **60** is oriented to define a central axis **A**. Multiple sense transformer cores **50** may be stacked together and configured to receive a phase conductor winding **52** and a neutral conductor winding **54** through a common central cavity **56**. Additional sets of stacked sense transformer cores **51** may be added to the carrier assembly **8** (see FIG. **4B**) to provide further measurements, such as arc fault measurements, to the GFCI receptacle **10**. The phase and neutral conductor windings **52**, **54** respectively direct AC current from the phase and neutral terminals **30**, **32** through the central cavity **56**, where the current may be measured for potential ground faults or arc faults. The AC current flow through the central cavity **56** defines a direction **B**, which is perpendicular to the central axis **A** of the solenoid **60**. In the embodiment of FIG. **5A**, the two sets of sense transformer cores **50**, **51** are placed symmetrically at two ends of the circuit board **58** with current flow directions parallel to each other. This symmetrical placement allows less or essentially no interference of the sense transformer cores **50**, **51** with the phase, neutral, or ground openings **16**, **18**, **20**, respectively. It would be appreciated by those skilled in the art that other positioning configurations of the sets of sense transformer cores may be possible and not exhaustively described herein. For example, the current flow directions defined by multiple sets of sense transformer cores **50**, **51** may be at an angle to each other and both parallel to the circuit board **58**. The angle defined by the current flow directions may be acute, right, or obtuse. In another example shown in FIGS. **5B-C**, only one sense transformer core **50** may be included in the GFCI receptacle **10**. The sense transformer core **50** may be placed at either ends of the circuit board **58** and with various orientations to allow less or essentially no interference with the phase, neutral, and ground openings **16**, **18**, **20**.

(34) Referring to FIGS. **6A-B**, the solenoid **60** is coupled to a carriage **62** that is axially movable along the solenoid **60**. On one side, the carriage **62** is coupled to a set of carriage springs **64**, the compression force of which distances the carriage **62** from the circuit board **58** in a rest position. On the other side, the carriage **62** is configured to engage the set of movable contacts **48A**, which presses down on the carriage **62** when in an unbiased resting position. During the resetting process of the GFCI receptacle **10**, the carriage **62** will oppose the resiliency of the abutting set of movable contacts **48A** to advance the set movable contacts **48A** in an upward direction and form electrical communication with the set of fixed contacts **48B**. The upward movement of the set of movable contacts **48A** stops once electrical communication is formed with the set of fixed contacts **48B**. During the tripping process of the GFCI receptacle **10**, the resiliency of the abutting set of movable contacts **48A** pushes the carriage **62** in a downward direction back to its original rest position, thereby effectively breaking the electrical connection between the set of movable contacts **48A** and the set of fixed contacts **48B**. The downward movement range of the set of movable contacts **48A** is limited by a stopping plane in the solenoid support structure **61**. Once the set of movable contacts **48A** hits the stopping plane or returns to the unbiased resting position, push force is no longer exerted on the carriage **62**, thereby effectively halting the downward movement and limiting the maximum range of movement of the carriage **62**. Resetting and latching of the GFCI receptacle **10** may be controlled by the circuit board **58** that receives ground fault and arc fault signal inputs from the sense transformer cores **50**, **51**.

(35) FIG. **7** shows an exploded view of a solenoid assembly **4** of the GFCI receptacle **10** according to one embodiment of the present application. The solenoid assembly **4** includes a reset button **24**, a reset spring **68**, a solenoid **60**, a reset plunger assembly **6**, a solenoid support structure **61**, and a circuit board **58**. In some embodiments, the solenoid support structure **61** is coupled to the circuit

board **58** and supports the solenoid **60**. When assembled as shown in FIG. **8**, the reset button **24** is biased away from the solenoid **60** via the reset spring **68** as long as no push force is exerted on the reset button **24**. When a push force is exerted and subsequently released on the reset button **24**, the compression force of the reset spring **68** returns the reset plunger **66** and the reset button **24** to an original resting position biased away from the solenoid support structure **61**. Likewise, without an externally exerted downward force, the carriage **62** is biased away from the circuit board **58** via the set of carriage springs **64**. The compression force of the carriage springs **64** returns the carriage **62** to an original position biased away from the circuit board **58** when external forces are removed.

(36) Referring to FIGS. **9-11**, the reset plunger assembly **6** includes a reset plunger **66** with an intermediate collar **78** and an armature **70** that is axially movable along the length of the reset plunger **66**. The armature **70** contains a slanted projection feature **71** that is energized by the solenoid **60** through which the armature **70** extends. The slanted projection feature **71** is configured to engage with the latching mechanism, which is structurally supported by the carriage **62** and the set of carriage springs **64**. The latching mechanism includes a cam surface **72** coupled to a lifting plate **74**. The lifting plate **74** is coupled through a slot **75** in the carriage **62**, as shown in FIG. **10**. The lifting plate **74** includes a latching portion **80** configured to receive and engage the intermediate collar **78** of the reset plunger **66** during resetting and tripping of the GFCI receptacle **10**, as shown in FIG. **11**. A return spring **76** is coupled to one end of the lifting plate **74** and is configured to apply a compression force against one side of the carriage **62**.

(37) Two exemplary embodiments of the latching mechanism are shown in FIGS. **12A-C**. In the two-piece latching mechanism design of FIG. **12A**, the cam surface **72A** is configured as a separate triangular plate coupled to channels (not enumerated) in the lifting plate **74A**. Additionally, a set of tabs **73A** at one end of the lifting plate **74A** is configured to engage with edges of the cam surface **72A** to transfer a translational force from the cam surface **72A** to the lifting plate **74A**. The return spring **76A** is positioned between the other end of the lifting plate **74A** and one side of the carriage **62A**. The latching portion **80A** is configured as the only opening in the lifting plate **74A** and receives/engages with the intermediate collar **78**.

(38) In the one-piece latching mechanism of FIGS. **12B-C**, the cam surface **72B** is integrated into the lifting plate **74B** as one element. Since the cam surface **72B** does not move independent of the lifting plate **74B**, coupling mechanism including channels (not enumerated) and tabs **74A** are not necessary in the lifting plate **74B**. The lifting plate **74B** includes an opening **77B** and a latching portion **80B**. The return spring **76B** is situated in the opening **77B** and exerts a compression force between edges of the opening **77B** and one side of the carriage **62B**. The latching portion **80B** is configured to receive/engage with the intermediate collar **78**. It would be appreciated by those skilled in the art that other design possibilities not detailed herein may serve to achieve essentially the same results and do not deviate from the teachings of the present application.

(39) According to one embodiment shown in FIG. **13**, a contact spring **82** is coupled to the bottom of the lifting plate **74**. When in an unlatched pushing state as described in further detail below, the contact spring **82** will form electrical communication with at least one contact pads (not shown or enumerated) on the circuit board **58**. This electrical communication will provide a communication signal and power from the circuit board **58** to the solenoid **60**, thereby energizing the armature **70** and resetting the GFCI receptacle **10**.

(40) The GFCI receptacle **10** according to embodiments of the present application has four different states: 1) unlatched state or tripped state, 2) unlatched pushing state, 3) latched pulling state, and 4) latched state or reset state. During the tripped state of FIGS. **14A-B**, the carriage **62** is in a resting position biased away from the circuit board **58** via carriage springs **64**, so the contact spring **82** (not shown) does not form electrical communication with at least one contact pads (not shown or enumerated) on the circuit board **58**. The set of movable contacts **48A** does not engage with the set of fixed contacts **48B** (not shown), and the receptacle terminals **30**, **32**, **34** remain biased away from the receptacle openings **16**, **18**, **20** via cantilevered bus lines **44**, **46**. Therefore,

the solenoid **60** does not receive external power and is not energized, causing the slanted projection feature **71** of the armature **70** to bias away from cam surface **72** (FIG. **14B**). There is no compression force in the return spring **76**, and the engaging portion **80** of the lifting plate **74** is not aligned to receive the intermediate collar **78** biased away from the lifting plate **74**.

(41) Once a downward pushing force is received on the reset plunger **66** from a user pushing down on the reset button **24**, the GFCI receptacle **10** enters the unlatched pushing state of FIG. **15**. In the unlatched pushing state, the downward force pushes the reset plunger **66** towards the lifting plate **74** until the intermediate collar **78** engages with an upper surface of the engaging portion **80**.

Because the engaging portion **80** is misaligned with the intermediate collar **78** from the previous tripped state, the intermediate collar **78** engages with but does not latch to the upper surface of engaging portion **80**. Thus, the downward force from the intermediate collar **78** transfers to the engaging portion **80** and the lifting plate **74**, which results in downward movement of the carriage **62** via the slot **75** (FIG. **10**). This downward movement continues until the contact springs **82** (not shown) form electrical communication with at least one contact pads (not shown or enumerated) on the circuit board **58**. Upon contact, electrical power and communication is sent from the circuit board **58** to the solenoid **60**, energizing the solenoid on a positive half cycle of the input AC power and moving the armature **70** axially along the reset plunger **66**. Referring to FIG. **16**, the slanted projection feature **71** of the armature **70** engages with the cam surface **72**, which translates the downward force to a translational force parallel to the circuit board **58**. Translational movement of the cam surface **72** also translationally moves the coupled lifting plate **74** against the compression force of the return spring **76**, thus aligning the engaging portion **80** with the intermediate collar **78**. Referring to FIG. **17**, the continued downward force on the reset plunger **66** applied by the user causes the intermediate collar **78** to travel through the aligned engaging portion **80**. At this point, the solenoid **60** de-energizes on a negative half cycle of the input AC power and retracts axially along the reset plunger **66**, as shown in FIG. **18**. The compression force of the return spring **76** pushes the side of the carriage **62** and returns the lifting plate **74** and cam surface **72** back to the original position. In this original position, the intermediate collar **78** is once again misaligned with the engaging portion **80**. When the user releases the downward pushing force on the reset plunger **66**, the reset spring **68** provides an upward pulling force on the reset plunger **66** and intermediate collar **78**, thereby latching and locking the intermediate collar **78** to a lower surface of the engaging portion **80**. Hence, the GFCI receptacle **10** enters the latched pulling state of the resetting process.

(42) When the GFCI receptacle **10** is in the latched pulling state shown in FIG. **19**, the compression force of the reset spring **68** creates an upward force on the reset button **24** and the coupled reset plunger **66**. This upward force pulls the intermediate collar **78** along with the latched lifting plate **74**, which is coupled to the carriage **62** via the slot **75**, causing the carriage **62** to move axially upward along the solenoid **60**. The axially upward movement of the carriage **62** opposes the resiliency of the abutting set of movable contacts **48A** and disconnects the contact springs **82** (not shown) from the at least one contact pads (not shown or enumerated) on the circuit board **58**, thus preventing continued energizations of the solenoid **60**. The carriage **62** engages with the set of movable contacts **48A** to form electrical connection with the set of fixed contacts **48B**.

Correspondingly, the receptacle terminals **30**, **32**, **34** also resist the cantilevered bus lines **44**, **46** and move closer to the front cover **12**. Once electrical communication between the set of movable contacts **48A** and the set of fixed contacts **48B** is formed, electricity may be delivered from the receptacle terminals **30**, **32**, **34** to the receptacle openings **16**, **18**, **20** via the bus lines **44**, **46**.

Hence, the GFCI receptacle **10** is fully reset.

(43) When the sense transformer cores **50**, **51** detect the present of a fault, the GFCI receptacle **10** completes a tripping process. During the tripping process, the GFCI receptacle **10** experiences the states of the resetting process in reverse order, thereby unlatching the intermediate collar **78** from the latching portion **80** and breaking the electrical communication between the set of movable contacts **48A** and the set of fixed contacts **48B**.

(44) FIGS. 20 & 21 illustrate a GFCI receptacle 10 according to some embodiments. In the illustrated embodiment, the GFCI receptacle 10 includes a printed circuit board 90. In some embodiments, the printed circuit board 90 includes one or more slots, or apertures, 92. As illustrated, the slots 92 may be configured receive, or be placed over, line conductors 94 and/or the neutral conductors 96, or a portion thereof (for example, bus bars 44, 46). The printed circuit board 90 may further include, or be coupled to, coils (for example, transformer cores 50, 51), which may be used to sense and/or monitor a current. In such an embodiment, the coils may also include a slot, aperture, configured to receive, or be placed over, the line conductors and/or the neutral conductors, or a portion thereof (for example, bus bars 44, 46).

(45) In certain other embodiments, additional elements, such as springs, contacts, etc., may be included in various places within the GFCI receptacle 10 to accomplish resetting or tripping of the device. All combinations of embodiments and variations of design are not exhaustively described in detail herein. Said combinations and variations are understood by those skilled in the art as not deviating from the teachings of the present application.

Claims

1. An electrical outlet receptacle comprising: a housing including a face plate; and a solenoid having a central axis perpendicular to the face plate; a plurality of sensing cores each configured to receive a current flow through a center cavity, the current flow defining a current flow direction through the center cavity, wherein the current flow direction is parallel to the face plate; and wherein the plurality of sensing cores are placed symmetrically in a translational direction across the electrical outlet receptacle.
2. The electrical outlet receptacle of claim 1, further comprising: a set of fixed contacts and a set of movable contacts; a solenoid having a central axis perpendicular to the face plate, the solenoid having a first end and a second end opposite the first end; a carriage movable axially along the solenoid and configured to interact with the set of movable contacts, the carriage configured to advance the set of movable contacts to form electrical communication with the set of fixed contacts during resetting of the electrical outlet receptacle; a reset plunger with a portion extending through the first end of the solenoid and axially movable therein, the reset plunger being biased toward a rest position away from the carriage; and an armature movable axially along the portion of the reset plunger extending through the solenoid, the armature being biased toward a rest position away from the carriage, wherein the reset plunger includes an engaging portion and the carriage includes a latching portion, the engaging portion of the reset plunger being configured to connect to the latching portion of the carriage.
3. The electrical outlet receptacle of claim 2, wherein the solenoid includes a coil bobbin with an inner coil and an outer coil.
4. The electrical outlet receptacle of claim 2, wherein the reset plunger further includes a spring configured to bias the reset plunger toward the rest position.
5. The electrical outlet receptacle of claim 2, wherein the armature interacts with the latching portion of the carriage when the solenoid is momentarily energized to cause engagement of the engaging portion to the latching portion in a latched state.
6. The electrical outlet receptacle of claim 5, wherein in the latched state, the armature interacts with the latching portion of the carriage when the solenoid is momentarily energized to cause disengagement of the engaging portion from the latching portion in an unlatched state.
7. The electrical outlet receptacle of claim 5, wherein pressing of the reset plunger causes the engaging portion to apply a downward force on the carriage at least until the electrical outlet receptacle is in the latched state, and subsequent release of the reset plunger causes the engaging portion to apply an upward force on the carriage to close the set of movable contacts and the set of fixed contacts.

8. The electrical outlet receptacle of claim 2, further comprising at least one sensing core configured to receive a current flow through a center cavity, the current flow defining a current flow direction through the center cavity.
 9. The electrical outlet receptacle of claim 8, wherein the at least one sensing core includes a ground fault circuit interrupter (GFCI) core and an arc fault circuit interrupter (AFCI) core, the GFCI core having a first current flow direction and the AFCI core having a second current flow direction.
 10. The electrical outlet receptacle of claim 9, wherein the first current flow direction and the second current flow direction are identical to each other.
 11. The electrical outlet receptacle of claim 9, wherein the first current flow direction and the second current flow direction are substantially parallel to each other.
 12. The electrical outlet receptacle of claim 9, wherein the first current flow direction and the second current flow direction are at an oblique angle to each other.
 13. The electrical outlet receptacle of claim 9, wherein the first current flow direction and the second current flow direction are at a right angle to each other.
 14. The electrical outlet receptacle of claim 9, wherein the GFCI core and AFCI core are positioned in a symmetrical placement across a translational direction of the electrical outlet receptacle, the symmetrical placement allowing for no interference of the GFCI core and the AFCI core with contact terminals connectable to an external device.
-