

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413729
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Leleannec; Fabrice et al.

Chroma quantization parameter adjustment in video encoding and decoding

Abstract

A video coding system uses a value of a chroma quantization parameter table to quantize or de-quantize chroma values of a block of the video, the chroma quantization parameter table being directly coded in a set of parameters at the picture level or at the sequence level of the coded video stream. A corresponding encoding method, encoding device, decoding method, decoding device, and non-transitory readable medium are proposed.

Inventors: Leleannec; Fabrice (Cesson-Sevigne, FR), Galpin; Franck (Cesson-Sevigne, FR), Poirier; Tangi (Cesson-Sevigne, FR), Francois; Edouard (Cesson-Sevigne, FR)

Applicant: InterDigital VC Holdings, Inc. (Wilmington, DE)

Family ID: 66794064

Assignee: InterDigital VC Holdings, Inc. (Wilmington, DE)

Appl. No.: 18/512368

Filed: November 17, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240089437 A1	Mar. 14, 2024

Foreign Application Priority Data

EP	18305386	Mar. 30, 2018
EP	18305412	Apr. 06, 2018
EP	18305848	Jul. 02, 2018

Related U.S. Application Data

Publication Classification

Int. Cl.: **H04N19/124** (20140101); **H04N19/176** (20140101); **H04N19/186** (20140101);
H04N19/51 (20140101); **H04N19/70** (20140101)

U.S. Cl.:

CPC **H04N19/124** (20141101); **H04N19/176** (20141101); **H04N19/186** (20141101);
H04N19/51 (20141101); **H04N19/70** (20141101);

Field of Classification Search

USPC: None

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
8208564	12/2011	Bossen et al.	N/A	N/A
9877019	12/2017	Chen et al.	N/A	N/A
10462462	12/2018	Chien et al.	N/A	N/A
10812798	12/2019	Chien et al.	N/A	N/A
10958907	12/2020	Tu et al.	N/A	N/A
11039175	12/2020	Zhao	N/A	H04N 19/96
11909974	12/2023	Leleannec	N/A	H04N 19/70
2013/0259118	12/2012	Fu et al.	N/A	N/A
2013/0329785	12/2012	Lim et al.	N/A	N/A
2014/0254661	12/2013	Saxena et al.	N/A	N/A
2015/0003518	12/2014	Nguyen	375/240.03	H04N 19/46
2015/0071344	12/2014	Tourapis	375/240.03	H04N 19/13
2015/0358631	12/2014	Zhang et al.	N/A	N/A
2015/0373327	12/2014	Zhang	375/240.03	H04N 19/176
2016/0057419	12/2015	Francois et al.	N/A	N/A
2016/0234492	12/2015	Li et al.	N/A	N/A
2016/0366422	12/2015	Yin et al.	N/A	N/A
2017/0064302	12/2016	Na et al.	N/A	N/A
2017/0127059	12/2016	Kim et al.	N/A	N/A
2017/0345187	12/2016	Sato	N/A	N/A
2018/0020218	12/2017	Zhao et al.	N/A	N/A
2018/0020241	12/2017	Li et al.	N/A	N/A
2018/0048901	12/2017	Zhang	N/A	H04N 19/124
2018/0176596	12/2017	Jeong	N/A	H04N 19/593

2018/0192069	12/2017	Chen et al.	N/A	N/A
2019/0068969	12/2018	Rusanovskyy	N/A	H04N 19/117
2019/0124330	12/2018	Chien	N/A	H04N 19/124
2019/0124366	12/2018	Zhao	N/A	H04N 19/126
2019/0191172	12/2018	Rusanovskyy et al.	N/A	N/A
2019/0289291	12/2018	Sullivan	N/A	N/A
2020/0221091	12/2019	Tu et al.	N/A	N/A
2020/0228803	12/2019	Sullivan	N/A	N/A
2020/0382780	12/2019	Xu et al.	N/A	N/A
2020/0404275	12/2019	Hsiang	N/A	N/A
2021/0136380	12/2020	Sullivan et al.	N/A	N/A
2021/0185319	12/2020	Tu et al.	N/A	N/A
2021/0211669	12/2020	Sullivan	N/A	N/A
2024/0089437	12/2023	Leleanec	N/A	H04N 19/51

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
101208957	12/2007	CN	N/A
103392338	12/2012	CN	N/A
104427339	12/2014	CN	N/A
104584559	12/2014	CN	N/A
2143279	12/2009	EP	N/A
2143279	12/2009	EP	N/A
2816805	12/2013	EP	N/A
2988503	12/2015	EP	N/A
2010187302	12/2009	JP	N/A
2016518762	12/2015	JP	N/A
2016528768	12/2015	JP	N/A
2017511045	12/2016	JP	N/A
2017520991	12/2016	JP	N/A
2017216687	12/2016	JP	N/A
2010123862	12/2009	WO	N/A
2014205561	12/2013	WO	N/A
2017008678	12/2016	WO	N/A
2017/206826	12/2016	WO	N/A

OTHER PUBLICATIONS

“Predicting Chroma from Luma with Frequency Domain Intra Prediction”—Egge et al., Proceedings of SPIE 9410, Visual Information Processing and Communication VI, 941009 (Mar. 4, 2015) (Year: 2015). cited by examiner

Li et al, Non CE4: Fine granularity QP offset, Document: JCTVC-G850, Joint Collaborative Team on Video Coding (JCT-VC) of ITU-T SG 16 WP3 and ISO/IEC JTC 1/SC29/WG11, 7.SUP.th .Meeting: Geneva, CH, Nov. 21-30, 2011, 11 pages. cited by applicant

“English Language Translation, CN 104584559 A”. cited by applicant

“English Language Translation, CN104427339A”. cited by applicant

Ahmadianpour, et al., “Novel Techniques for Reducing Blocking Artifacts in Motion Compensated Frame”, Journal of Electronic Imaging, vol. 15, No. 1, Listed in Global Dossier as SPIE

XP040214388 dated May 31, 2006, Jan.-Mar. 2006, 8 pages. cited by applicant

Bordes, P. et al., “Description of SDR, HDR and 360° Video Coding Technology Proposal by Qualcomm and Technicolor—Medium Complexity Version”, JVET-J0022R1, Qualcomm, Technicolor, Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11, 10th Meeting: San Diego, US, Apr. 10-20, 2018, 83 pages. cited by applicant

Chen, et al., “Algorithm Description of Joint Exploration Test Model 2”, JVET-B1001_V3, Editors, Joint Video Exploration Team (JVET) of ITU-T SG16 WP3 and ISO/IEC JTC1/SC29/WG11, 2nd Meeting, San Diego, California, USA, Feb. 20-26, 2016, 32 pages. cited by applicant

Chen, et al., “Algorithm Description of Joint Exploration Test Model 6 (JEM 6)”, JVET-F1001-V3, Editors, Joint Video Exploration Team (JVET) of ITU-T SG 16 WP3 and ISO/IEC JTC 1/SC 29/WG 11, 6th Meeting: Hobart, AU, Mar. 31-Apr. 7, 2017, 48 pages. cited by applicant

Chen, et al., “Variable Block-Size Overlapped Block Motion Compensation in the Next Generation Open-source Video Codec”, IEEE International Conference on Image Processing (ICIP), Sep. 17, 2017, 5 pages. cited by applicant

Chen, et al., “Algorithm Description of Joint Exploration Test Model 5 (JEM 5)”, JVET-E1001-V2, Editors, Joint Video Exploration Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11, 5th Meeting: Geneva, CH, Feb. 12-20, 2017, 44 pages. cited by applicant

Chen, Jianle, et al., “Algorithm Description of Joint Exploration Test Model 7 (JEM 7)”, Joint Video Exploration Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11, 7th Meeting: Torino, IT; Editors; JVET-G1001-V1, Jul. 13-21, 2017, 50 pages. cited by applicant

Cho, et al., “Fast CU Splitting and Pruning for Suboptimal CU Partitioning in HEVC Intra Coding”, IEEE Transactions on Circuits and Systems for Video Technology, vol. 23, No. 9, Sep. 2013, 10 pages. cited by applicant

Francois, Edouard et al., “AHG5: on chroma QP for HEVC RExt”, JCT-VC of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11; 14th Meeting: Vienna, AT; Canon, JCTVC-N0141, Jul. 25-Aug. 2, 2013, 12 pages. cited by applicant

Fu, et al., “Sample Adaptive Offset for HEVC”, IEEE 13th International Workshop on Multimedia Signal Processing, Hangzhou, 2011, 5 pages. cited by applicant

Grecos, “Beyond the High Efficiency Video Coding Standard: An Overview”, Proceedings of SPIE, vol. 10223, May 1, 2017, 18 pages. cited by applicant

Guo, et al., “Gradient Based Fast CU Splitting and Mode Decision Algorithm for HEVC Intra Prediction”, IEEE 2014 International Conference on Anti-Counterfeiting, Security and Identification, Dec. 12, 2014, 5 pages. cited by applicant

Har-Noy, et al., “Adaptive In-Loop Prediction Refinement for Video Coding”, Multimedia Signal Processing, 9th Workshop on IEEE, Piscataway, Oct. 1, 2007, 4 pages. cited by applicant

Huang, et al., “Affine Skip and Direct Modes for Efficient Video Coding”, Visual Communications and Image Processing (VCIP), IEEE, Nov. 27, 2012, 6 pages. cited by applicant

ITU-T, “High Efficiency Video Coding”, Recommendation ITU-T H.265, Series H: Audiovisual and Multimedia Systems, Infrastructure of Audiovisual Services—Coding of Moving Video, Apr. 2015, 636 pages. cited by applicant

ITU-T, “Reference Software for ITU-T H.265 High Efficiency Video Coding”, Recommendation ITU-T H.265.2, Series H: Audiovisual and Multimedia Systems, Infrastructure of Audiovisual Services—Coding of Moving Video, Oct. 2014, 12 pages. cited by applicant

Leleannec, et al., “Asymmetric Coding Units in QTBT”, JVET-D0064, Technicolor, Joint Video Exploration Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11, 4th Meeting: Chengdu, CN, Oct. 15-21, 2016, 10 pages. cited by applicant

Li, et al., “Non CE4: Fine Granularity QP Offset”, JCTVC-G850, MediaTek Inc., Qualcomm Inc., Joint Collaborative Team on Video Coding (JCT-VC) of ITU-T SG16 WP3 and ISO/IEC JTC1/SC29/WG11, 7th Meeting: Geneva, CH, Nov. 21-30, 2011, 3 Pages. cited by applicant

Li, Xiang, et al., “Multi-Type-Tree”, Joint Video Exploration Team (JVET) of ITU-T SG 16 WP 3

and ISO/IEC JTC 1/SC 29/WG 11; Qualcomm Inc.; 4th Meeting: Chengdu, CN; JVET-D0117, Oct. 15-21, 2016, 3 pages. cited by applicant

Li, Xiang, et al., “Non CE4: Fine granularity QP offset”, Document: JCTVC-G850, Joint Collaborative Team on Video Coding (JCT-VC) of ITU-T SG16 WP3 and ISO/IEC JTC1/SC29/WG11; 7th Meeting: Geneva, CH, Nov. 21-30, 2011, 9 pages. cited by applicant

Lin, et al., “Affine Transform Prediction for Next Generation Video Coding”, Huawei Technologies, ISO/IEC JTC1/SC29/WG11 MPEG2015/m37525, Geneva, Switzerland, Oct. 2015, 10 pages. cited by applicant

Reichel, “Joint Scalable Video Model JSVM-12 Text”, JVT-Y202, JVT, Joint Video Team (JVT) of ISO/IEC MPEG & ITU-T VCEG (ISO/IEC JTC1/SC29/WG11 and ITU-T SG16 Q.6), 25th Meeting: Shenzhen, CN, Oct. 21-26, 2007, 113 pages. cited by applicant

Reznik, Yuriy A, “Relationship Between DCT-II, DCT-VI, and DST-VII Transforms”, IEEE, May 26-31, 2013, 5 pages. cited by applicant

Wang, et al., “Image Quality Assessment: From Error Visibility to Structural Similarity”, IEEE Transactions on Image Processing, vol. 13, No. 4, Apr. 2004, 13 pages. cited by applicant

Wei, et al., “Modified Winner Update with Adaptive Block Partition for Fast Motion Estimation”, 2006 IEEE International Conference on Multimedia and Expo (ICME 2006), Ontario, Canada, Jul. 9, 2006, 4 pages. cited by applicant

Wen, et al., “Parallel Merge/Skip Mode for HEVC”, JCTVC-G387, Hong Kong University of Science and Technology, Joint Collaborative Team on Video Coding (JCT-VC) of ITU-T SG16 WP3 and ISO/IEC JTC1/SC29/WG11, 7th Meeting: Geneva, CH, Nov. 21-30, 2011, 13 pages. cited by applicant

Xu, et al., “Chroma QP Extension and Signaling Enhancement”, JCTVC-I0265r1, Sony Electronics Inc., Magnum Semiconductor Inc., Sony Corp., Joint Collaborative Team on Video Coding (JCT-VC) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11, 9th Meeting: Geneva, CH, Apr. 27-May 7, 2012, 11 pages. cited by applicant

Zhou, et al., “New Rate-Complexity-Quantization Modeling and Efficient Rate Control for H.264/AVC”, 2008 IEEE International Conference on Multimedia and Expo, Hannover, Germany, Jun. 23, 2008, 4 pages. cited by applicant

Primary Examiner: Hasan; Mainul

Attorney, Agent or Firm: Condo Roccia Koptiw LLP

Background/Summary

CROSS REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. patent application Ser. No. 17/043,280 (now U.S. Pat. No. 11,909,974), which is the National Stage Entry under 35 U.S.C. § 371 of Patent Cooperation Treaty Application No. PCT/US2019/024262 filed Mar. 27, 2019, which claims priority from European Patent Application No. 18305386.7, filed Mar. 30, 2018, European Patent Application No. 18305412.1, filed Apr. 6, 2018, and European Patent Application No. 18305848.6, filed Jul. 2, 2018, the disclosures of each of which are incorporated by reference herein in their entireties.

TECHNICAL FIELD

(1) At least one of the present embodiments generally relates to video encoding or decoding. At least one embodiment relates, more particularly, to a method, an apparatus and a signal for adjusting chroma quantization parameters in video encoding or decoding.

BACKGROUND

(2) To achieve high compression efficiency, image and video coding schemes usually employ prediction and transform to leverage spatial and temporal redundancy in the video content. Generally, intra or inter prediction is used to exploit the intra or inter frame correlation, then the differences between the original block and the predicted block, often denoted as prediction errors or prediction residuals, are transformed, quantized, and entropy coded. To reconstruct the video, the compressed data are decoded by inverse processes corresponding to the entropy coding, quantization, transform, and prediction.

SUMMARY

(3) According to a first aspect of at least one embodiment, a method for encoding video data is presented, comprising: selecting, for a block of an image, at least one chroma quantization parameter from among multiple sets of chroma quantization parameters based on an encoding performance level, wherein the sets of chroma quantization parameters are different depending on whether the image is motion-predicted or not; encoding said block based on at least one selected chroma quantization parameter, wherein the encoding includes quantizing chroma values of said block according to said at least one selected chroma quantization parameter, and generating a bitstream comprising at least said encoded block and metadata representative of said at least one selected chroma quantization parameter.

(4) According to a second aspect of at least one embodiment, a method for decoding video data is presented, comprising: accessing metadata of a block of an image or video, said metadata being representative of a selection of at least one chroma quantization parameter from among multiple sets of chroma quantization parameters, said selection being based on an encoding performance level; and de-quantizing chroma values of the block according to said metadata representative of said selection of at least one chroma quantization parameter.

(5) According to a third aspect of at least one embodiment, a signal for encoded image is presented, comprising information representative of at least one chroma quantization parameter selected from among multiple sets of chroma quantization parameters based on an encoding performance level, wherein the sets of chroma quantization parameters are different depending on whether the image is motion-predicted or not, wherein said selecting is for at least one block of an image.

(6) According to a fourth aspect of at least one embodiment, a device for encoding video data is presented, comprising: means for selecting, for a block of an image, at least one chroma quantization parameter from among multiple sets of chroma quantization parameters based on an encoding performance level, wherein the sets of chroma quantization parameters are different depending on whether the image is motion-predicted or not; means for encoding said block based on at least one selected chroma quantization parameter, wherein the encoding includes quantizing chroma values of said block according to said at least one selected chroma quantization parameter, and means for generating a bitstream comprising at least said encoded block and metadata representative of said at least one selected chroma quantization parameter.

(7) According to a fifth aspect of at least one embodiment, a device for decoding video data is presented, comprising: means for accessing metadata of a block of an image or video, said metadata being representative of a selection of at least one chroma quantization parameter from among multiple sets of chroma quantization parameters, said selection being based on an encoding performance level; and means for de-quantizing chroma values of the block according to said metadata representative of said selection of at least one chroma quantization parameter.

(8) According to a sixth aspect of at least one embodiment, a device for displaying video data is presented, comprising one or more processors configured to: access metadata of a block of an image or video, said metadata being representative of a selection of at least one chroma quantization parameter from among multiple sets of chroma quantization parameters, said selection being based on an encoding performance level; de-quantize chroma values of the block according to said metadata representative of said selection of at least one chroma quantization parameter; and produce a reconstructed image based on the de-quantized chroma values of a plurality of blocks of

the image; and a display configured to display the reconstructed image.

(9) According to a seventh aspect of at least one embodiment, a device for receiving video data is presented, comprising: an antenna configured to receive a signal over the air comprising an image or a video; one or more processors configured to: access metadata of a block of the received image or video, said metadata being representative of a selection of at least one chroma quantization parameter from among multiple sets of chroma quantization parameters, said selection being based on an encoding performance level; de-quantize chroma values of the block according to said metadata representative of said selection of at least one chroma quantization parameter; and produce a reconstructed image based on the de-quantized chroma values of a plurality of blocks of the image; and an output configured to provide the reconstructed image.

(10) According to another aspect of at least one embodiment, a non-transitory computer readable medium is presented comprising data content generated according to the method or the apparatus of any of the preceding claims.

(11) According to another aspect of at least one embodiment, a computer program is presented comprising program code instructions executable by a processor for implementing the steps of a method according to at least the first aspect.

(12) According to another aspect of at least one embodiment, a computer program is presented, which is stored on a non-transitory computer readable medium and comprises program code instructions executable by a processor for implementing the steps of a method according to at least the first aspect.

(13) According to variant embodiments of first and fourth aspects, the encoding performance level is automatically chosen according to information related to coding, said information being related to the coding tree configuration or the coding mode or the partitioning mode.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 illustrates an example of video encoder **100**, such as a High Efficiency Video Coding (HEVC) encoder.

(2) FIG. 2 illustrates a block diagram of an example of video decoder **200**, such as an HEVC decoder.

(3) FIG. 3 illustrates an example of Quad-Tree plus Binary-Tree (QTBT) CTU representation.

(4) FIG. 4 illustrates an example of extended set of Coding Unit partitioning.

(5) FIG. 5 illustrates the coding efficiency increase by using a QTBT+ABT coding structure.

(6) FIG. 6 illustrates the coding efficiency increase from using a QTBT+ABT coding structure in an embodiment implementing the chroma quantization adaptation.

(7) FIG. 7A illustrates an example of process used on the decoder side to determine the QP parameter used for the coding and the decoding of the chroma components.

(8) FIG. 7B illustrates maximum Quad-tree and Binary-tree depths allowed for each picture of a random-access sequence.

(9) FIG. 8 illustrates a block diagram of an example of a system in which various aspects and embodiments are implemented.

(10) FIG. 9A illustrates a flowchart of an example of a part of an encoding method according to an embodiment implementing the chroma quantization adaptation.

(11) FIG. 9B illustrates a flowchart of an example of a part of a decoding method according to an embodiment implementing the chroma quantization adaptation.

DETAILED DESCRIPTION

(12) In at least one embodiment, a coding efficiency improvement results from the use of topologies for block division described below. In particular, in some embodiments, a larger gain is

obtained in the chroma components than in the luma component. As a consequence, it is of interest to balance the coding gain obtained, by shifting some gain from one or more chroma components to the luma component. This is particularly beneficial in certain embodiments because at a certain level of quality, no additional visual benefit typically results from additional coding efficiency improvement in the chroma components. Therefore, at least one embodiment proposes to employ a quantization parameter in such a way to trade off further quality improvement between the chroma components and the luma component. At least one such embodiment reduces the overall bit-rate of the whole coded bit-stream including chroma components and luma component.

(13) FIG. 1 illustrates an example of video encoder **100**, such as a High Efficiency Video Coding (HEVC) encoder. FIG. 1 may also illustrate an encoder in which improvements are made to the HEVC standard or an encoder employing technologies similar to HEVC, such as a JEM (Joint Exploration Model) encoder under development by JVET (Joint Video Exploration Team).

(14) In the present application, the terms “reconstructed” and “decoded” may be used interchangeably, the terms “encoded” or “coded” may be used interchangeably, and the terms “image,” “picture” and “frame” may be used interchangeably. Usually, but not necessarily, the term “reconstructed” is used at the encoder side while “decoded” is used at the decoder side.

(15) Before being encoded, the video sequence can go through pre-encoding processing (**101**). This is for example performed by applying a color transform to the input color picture (for example, conversion from RGB 4:4:4 to YCbCr 4:2:0) or performing a remapping of the input picture components in order to get a signal distribution more resilient to compression (for instance using a histogram equalization of one of the color components). Metadata can be associated with the pre-processing and attached to the bitstream.

(16) In HEVC, to encode a video sequence with one or more pictures, a picture is partitioned (**102**) into one or more slices where each slice can include one or more slice segments. A slice segment is organized into coding units, prediction units, and transform units. The HEVC specification distinguishes between “blocks” and “units,” where a “block” addresses a specific area in a sample array (for example, luma, Y), and the “unit” includes the collocated blocks of all encoded color components (Y, Cb, Cr, or monochrome), syntax elements, and prediction data that are associated with the blocks (for example, motion vectors).

(17) For coding in HEVC, a picture is partitioned into coding tree blocks (CTB) of square shape with a configurable size, and a consecutive set of coding tree blocks is grouped into a slice. A Coding Tree Unit (CTU) contains the CTBs of the encoded color components. A CTB is the root of a quadtree partitioning into Coding Blocks (CB), and a Coding Block may be partitioned into one or more Prediction Blocks (PB) and forms the root of a quadtree partitioning into Transform Blocks (TBs). Corresponding to the Coding Block, Prediction Block, and Transform Block, a Coding Unit (CU) includes the Prediction Units (PUs) and the tree-structured set of Transform Units (TUs), a PU includes the prediction information for all color components, and a TU includes residual coding syntax structure for each color component. The size of a CB, PB, and TB of the luma component applies to the corresponding CU, PU, and TU. In the present application, the term “block” can be used to refer, for example, to any of CTU, CU, PU, TU, CB, PB, and TB. In addition, the “block” can also be used to refer to a macroblock and a partition as specified in H.264/AVC or other video coding standards, and more generally to refer to an array of data of various sizes.

(18) In the example of encoder **100**, a picture is encoded by the encoder elements as described below. The picture to be encoded is processed in units of CUs. Each CU is encoded using either an intra or inter mode. When a CU is encoded in an intra mode, it performs intra prediction (**160**). In an inter mode, motion estimation (**175**) and compensation (**170**) are performed. The encoder decides (**105**) which one of the intra mode or inter mode to use for encoding the CU and indicates the intra/inter decision by a prediction mode flag. Prediction residuals are calculated by subtracting (**110**) the predicted block from the original image block.

(19) CUs in intra mode are predicted from reconstructed neighboring samples within the same

slice. A set of 35 intra prediction modes is available in HEVC, including a DC, a planar, and 33 angular prediction modes. The intra prediction reference is reconstructed from the row and column adjacent to the current block. The reference extends over two times the block size in the horizontal and vertical directions using available samples from previously reconstructed blocks. When an angular prediction mode is used for intra prediction, reference samples can be copied along the direction indicated by the angular prediction mode.

(20) The applicable luma intra prediction mode for the current block can be coded using two different options. If the applicable mode is included in a constructed list of three most probable modes (MPM), the mode is signaled by an index in the MPM list. Otherwise, the mode is signaled by a fixed-length binarization of the mode index. The three most probable modes are derived from the intra prediction modes of the top and left neighboring blocks.

(21) For an inter CU, the corresponding coding block is further partitioned into one or more prediction blocks. Inter prediction is performed on the PB level, and the corresponding PU contains the information about how inter prediction is performed. The motion information (for example, motion vector and reference picture index) can be signaled in two methods, namely, “merge mode” and “advanced motion vector prediction (AMVP)”.

(22) In the merge mode, a video encoder or decoder assembles a candidate list based on already coded blocks, and the video encoder signals an index for one of the candidates in the candidate list. At the decoder side, the motion vector (MV) and the reference picture index are reconstructed based on the signaled candidate.

(23) In AMVP, a video encoder or decoder assembles candidate lists based on motion vectors determined from already coded blocks. The video encoder then signals an index in the candidate list to identify a motion vector predictor (MVP) and signals a motion vector difference (MVD). At the decoder side, the motion vector (MV) is reconstructed as MVP+MVD. The applicable reference picture index is also explicitly coded in the PU syntax for AMVP.

(24) The prediction residuals are then transformed **(125)** and quantized **(130)**, including at least one embodiment for adapting the chroma quantization parameter described below. The transforms are generally based on separable transforms. For instance, a DCT transform is first applied in the horizontal direction, then in the vertical direction. In recent codecs such as the JEM, the transforms used in both directions may differ (for example, DCT in one direction, DST in the other one), which leads to a wide variety of 2D transforms, while in previous codecs, the variety of 2D transforms for a given block size is usually limited.

(25) The quantized transform coefficients, as well as motion vectors and other syntax elements, are entropy coded **(145)** to output a bitstream. The encoder may also skip the transform and apply quantization directly to the non-transformed residual signal on a 4×4 TU basis. The encoder may also bypass both transform and quantization, that is, the residual is coded directly without the application of the transform or quantization process. In direct PCM coding, no prediction is applied and the coding unit samples are directly coded into the bitstream.

(26) The encoder decodes an encoded block to provide a reference for further predictions. The quantized transform coefficients are de-quantized **(140)** and inverse transformed **(150)** to decode prediction residuals. Combining **(155)** the decoded prediction residuals and the predicted block, an image block is reconstructed. In-loop filters **(165)** are applied to the reconstructed picture, for example, to perform deblocking/SAO (Sample Adaptive Offset) filtering to reduce encoding artifacts. The filtered image is stored at a reference picture buffer **(180)**.

(27) FIG. 2 illustrates a block diagram of an example of video decoder **200**, such as an HEVC decoder. In the example of decoder **200**, a bitstream is decoded by the decoder elements as described below. Video decoder **200** generally performs a decoding pass reciprocal to the encoding pass as described in FIG. 1, which performs video decoding as part of encoding video data. FIG. 2 may also illustrate a decoder in which improvements are made to the HEVC standard or a decoder employing technologies similar to HEVC, such as a JEM decoder.

(28) In particular, the input of the decoder includes a video bitstream, which may be generated by video encoder **100**. The bitstream is first entropy decoded (**230**) to obtain transform coefficients, motion vectors, picture partitioning information, and other coded information. The picture partitioning information indicates the size of the CTUs, and a manner a CTU is split into CUs, and possibly into PUs when applicable. The decoder may therefore divide (**235**) the picture into CTUs, and each CTU into CUs, according to the decoded picture partitioning information. The transform coefficients are de-quantized (**240**) including at least one embodiment for adapting the chroma quantization parameter described below and inverse transformed (**250**) to decode the prediction residuals.

(29) Combining (**255**) the decoded prediction residuals and the predicted block, an image block is reconstructed. The predicted block may be obtained (**270**) from intra prediction (**260**) or motion-compensated prediction (that is, inter prediction) (**275**). As described above, AMVP and merge mode techniques may be used to derive motion vectors for motion compensation, which may use interpolation filters to calculate interpolated values for sub-integer samples of a reference block. In-loop filters (**265**) are applied to the reconstructed image. The filtered image is stored at a reference picture buffer (**280**).

(30) The decoded picture can further go through post-decoding processing (**285**), for example, an inverse color transform (for example conversion from YCbCr 4:2:0 to RGB 4:4:4) or an inverse remapping performing the inverse of the remapping process performed in the pre-encoding processing (**101**). The post-decoding processing may use metadata derived in the pre-encoding processing and signaled in the bitstream.

(31) New emerging video compression tools include a Coding Tree Unit representation in the compressed domain are proposed to represent picture data in a more flexible way. The advantage of this more flexible representation of the coding tree is that it provides increased compression efficiency compared to the CU/PU/TU arrangement of the HEVC standard.

(32) FIG. 3 illustrates an example of Quad-Tree plus Binary-Tree (QTBT) CTU representation. The Quad-Tree plus Binary-Tree (QTBT) coding tool provides such increased flexibility. QTBT consists in a coding tree where coding units can be split both in a quad-tree and in a binary-tree fashion. The splitting of a coding unit is decided on the encoder side through a rate distortion optimization procedure, that determines the QTBT representation of the CTU with minimal rate distortion cost. In the QTBT technology, a CU has either square or rectangular shape. The size of coding unit is always a power of 2, and typically goes from 4 to 128. In addition to this variety of rectangular shapes for a coding unit, such CTU representation has the following different characteristics compared to HEVC. The QTBT decomposition of a CTU is made of two stages: first the CTU is split in a quad-tree fashion, then each quad-tree leaf can be further divide in a binary fashion. This is illustrated on the right side of the figure where solid lines represent the quad-tree decomposition phase and dashed lines represent the binary decomposition that is spatially embedded in the quad-tree leaves. In intra slices, the Luma and Chroma block partitioning structure is separated, and decided independently. No more CU partitioning into predictions units or transform unit is employed. In other words, each Coding Unit is systematically made of a single prediction unit ($2N \times 2N$ prediction unit partition type) and single transform unit (no division into a transform tree).

(33) FIG. 4 illustrates an example of extended set of Coding Unit partitioning. In an asymmetric binary and tree split modes (ABT), a rectangular coding unit with size (w, h) (width and height) that would be split through one of the asymmetric binary splitting modes, for example HOR_UP (horizontal-up), would lead to 2 sub-coding units with respective rectangular sizes

(34) $(w, \frac{h}{4})$ and $(w, \frac{3h}{4})$.

In addition, a so-called triple tree partitioning of a CU may be used, leading to the set of possible partitions given in FIG. 5. Triple tree consists in splitting a CU into tree sub-CU with size $(\frac{1}{4}, \frac{1}{2}, \frac{1}{4})$ relative to the parent CU, in the considered orientation (for example: HOR_TRIPLE for the

horizontal split mode).

(35) FIG. 5 illustrates the coding efficiency increase by using a QTBT+ABT coding structure. Such coding structure is proposed in JVET-J0022. The table of FIG. 5 shows the coding results for a subset of selected images listed in the first column. In the second column entitled “Reference”, the numbers represent encoding performance of the reference encoder, according to some encoding parameters, showing respectively the bit rate, the PSNR for Y, U and V components, the encoding time and the decoding time. In the third column entitled “Tested”, the numbers represent encoding performance of the reference encoder modified to use QTBT+ABT coding structure with the same encoding parameters as for the “Reference” encoding. This third column shows respectively the bit rate, the PSNR for Y, U and V components, the encoding time and the decoding time. In the fifth column, the numbers represent the bitrate improvement for Y, U and V components.

(36) A coding efficiency improvement is shown in the last columns, compared to standard coding. In particular, in some embodiments, a larger gain is obtained in the chroma components than in the luma component.

(37) To fully benefit from such improvement, it is of interest to balance the coding gain obtained, by shifting some gain from one or more chroma components to the luma component. This is particularly beneficial in certain embodiments because at a certain level of quality, no additional visual benefit typically results from additional coding efficiency improvement in the chroma component(s). Therefore, at least one embodiment proposes to employ a quantization parameter in such a way to trade off further quality improvement between the chroma components and the luma component. At least one such embodiment reduces the overall bit-rate of the whole coded bit-stream including chroma components and luma component.

(38) FIG. 6 illustrates the coding efficiency increase from using a QTBT+ABT coding structure in an embodiment implementing the chroma quantization adaptation. FIG. 6 shows the coding efficiency performances obtained by using the video codec of JVET-J0022 used in the configuration of FIG. 5 but with the addition of the chroma quantization adaptation. The table of FIG. 6 shows the coding results for a subset of selected images listed in the first column, according to some parameters listed in the second column. In the third column, the numbers represent encoding performance of the reference encoder, showing respectively the bit rate, the PSNR for Y, U and V components. In the fourth column, the numbers represent encoding performance of the reference encoder modified to use QTBT-FABT coding structure. This fourth column shows respectively the bit rate, the PSNR for Y, U and V components. In the fifth column, the numbers represent the bitrate improvement for Y, U and V components.

(39) The table shows a noticeable coding efficiency improvement in the luma, with a moderate relative loss in chroma coding efficiency, compared to FIG. 5. Moreover, since the luma component is typically much more important from a perceptual viewpoint, prioritizing the luma over the chroma in terms of coding efficiency is of great interest.

(40) In an embodiment, the chroma quantization parameter adaptation allows to trade off the bitrate allocation between the luma and the chroma components in a video coding scheme, so that the coding efficiency of the luma component is being adjusted with a controlled penalty in the coding efficiency in the chroma components. Moreover, in at least one embodiment, the use of a luma/chroma bitrate allocation is made independently from the coding tools that are being used in the coding and decoding.

(41) A first approach considers using the well-known chroma QP (quantization parameter) offset sequence level parameter, which is being signaled in the high level syntax (Sequence Parameter Set) of the coded bit-stream. A drawback of such an approach is that the loss in chroma coding efficiency may be too high, and difficult to control. Another approach considers using a so-called chroma QP table, which is used to derive the QP of a slice in chroma, given the QP used in the luma slice of same picture, in Inter Slices. In the JEM, given the QP associated with the luma slice, the QP of the chroma slice is calculated via a lookup table, which we call a chroma QP table here.

A chroma QP table is used to derive the QP for the chroma components of a slice, given the QP used in the luma component of the slice of same picture. The index value to this table is the so-called baseQP (that is, base chroma QP) associated with the considered chroma component, which is obtained as the sum of the corresponding luma slice QP and the chroma QP offset of the considered slice. This chroma QP offset of the considered slice is obtained as the sum of the sequence level chroma QP offset and the slice level chroma QP delta associated to considered slice. The output value corresponding to an index value can then be used as the QP value for encoding or decoding the chroma slice. It should be noted that the slice QP may be further modified by block-level QP adjustment, for example, because of rate control.

(42) In the JEM, the used chroma QP table only depends on the chroma format, for example 4:0:0, 4:2:0, 4:2:2, etc., thus preventing any flexibility.

(43) In an example embodiment, it is proposed to use different chroma QP tables for different encoding configurations. Indeed, the configuration of the coding system, to reach a certain level of coding efficiency, may include the adjustment of encoding parameters, which would include the set of partitions used, and some other parameters. Typically, the maximum tree depth allowed in CTU coding tree representation also impact the overall coding efficiency and allows reaching a desired trade-off between coding efficiency and computational complexity at the encoder side.

(44) One principle of various embodiments is to signal the use of a desired chroma QP table by some means that are independent from the coding tools used to code or decode the sequence. Therefore, the chroma QP table is chosen as a coding configuration parameter in the encoder side. It typically takes the form of a “coding performance level” high level syntax element, which is signaled in the Sequence Parameter Set (SPS) or Picture Parameter Set (PPS). It is decoded by the decoder, which then switches to the same chroma QP table that has been used on the encoder side. In an embodiment, two set of tables are proposed and thus a simple binary flag is sufficient to carry the information. In other embodiments, more than two set of tables are proposed and thus an integer value (or other way to signal one set among others) would be needed. The example illustrated below shows a set of two tables.

(45) The QP value used in JEM ranges from -6 to 51. The chroma QP table used in the JEM for the 4:2:0 color format is made of 58 elements (that is, one entry for each possible QP value) and is typically the following one: chromaQPTableJEM[0 . . . 57]=[0, 1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 26, 27, 28, 29, 29, 30, 31, 32, 33, 33, 34, 34, 35, 35, 36, 36, 37, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51]

(46) In an embodiment, it is proposed to use several sets of chroma QP tables. Tables are differentiated firstly regarding the targeted efficiency of coding and secondly regarding their slice type (for I slice type or non-I slice type). The standard coding efficiency level chroma QP table set is the following, and comprises the values for both I slice type and non-I slice type:

chromaQPTableStandardPerf [2][0 . . . 57]=[[0, 1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 26, 27, 28, 29, 29, 30, 31, 32, 33, 33, 34, 34, 35, 35, 36, 36, 37, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51], [0, 1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 26, 27, 28, 29, 29, 30, 31, 32, 33, 33, 34, 35, 36, 36, 37, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53]]

(47) The high performance coding efficiency level chroma QP table set is the following:

chromaQPTableHighPerf [2][0 . . . 57]=[[0, 1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 26, 27, 28, 29, 29, 30, 31, 32, 33, 33, 34, 34, 35, 35, 36, 36, 37, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51], [0, 1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 26, 27, 28, 29, 29, 30, 31, 32, 33, 34, 35, 35, 36, 37, 38, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54]]

(48) The chroma QP tables comprise output QP that are greater or equal to zero, and non-decreasing as a function of the input index. Therefore, for each non-zero input index to a chroma QP table, its output integer value is higher or equal to the output QP value associated with the

preceding input index to the table.

(49) The difference between the standard and the high performance table sets is the following one. The output QP value contained in the high performance table set is always greater or equal to the output with the same input index value in the standard performance table set. In practice, this concerns the high QP value in particular.

(50) In the shown example, for the tables corresponding to the non-I slice type, from output QP value 34 in the high performance table set, the output QP value with same input index in the standard performance table set is equal to 33. Then, from that input index in the two tables, the output QP value in high performance QP table of non-I slice are strictly higher than the corresponding output QP value in the standard performance chroma QP table set. This is explained by the fact that as the coding efficiency is increased for the high performance case, the bitrate in chroma components can be reduced while keeping comparable PSNR value in the chroma components. This way, the overall bitrate is reduced, while the objective quality (PSNR) in the luma slice is preserved. Overall some coding gain is obtained in luma, without any penalty, or with limited penalty on the coding efficiency for chroma.

(51) For the two above table sets, two-dimensional arrays are used. The first dimension of the array corresponds to the slice type (for example, 0.fwdarw.I_SLICE; 1.fwdarw.B_SLICE (more generally, non-I slice)) and second dimension corresponds to the base chroma QP in the considered slice.

(52) As will be described further below, the chroma QP table sets can be stored in both the encoder and decoder, and the encoder can indicate to the decoder which table set is to be selected by the decoder, for example, through a flag or an index. Alternatively, the table sets can be encoded directly in the bitstream.

(53) At the encoder side, the encoder chooses which chroma QP table set to use. The selection can be done by the user through an encoding configuration parameter (typically a flag), which indicates if the high performance chroma QP table set is to be used or not during the encoding and then the decoding processes. In an example embodiment, the selection is done by setting a value of a value in a file, the flag being read by an encoding device that interprets the value of the flag to select which chroma QP table to use. In an example embodiment, the selection is done by a manual operation of a user selecting encoding configuration parameters using a graphical user interface that handles the encoder device.

(54) In another embodiment, it can be automatically selected by the encoder, as a function of the measured coding efficiency obtained in the luma and chroma slices. Typically, this may consist in checking the PSNR values obtained in Cb and Cr components. If these two values are sufficiently higher than the PSNR obtained in the corresponding luma slice, then it may be of interest to increase the QP in the chroma components, to save some bits. To do so, the encoder would select the high performance chroma QP table sets, and would indicate its use in the next SPS, PPS or even slice header.

(55) In an example embodiment, two performance levels are considered: standard and high, and for each setting, two chroma QP tables are used for difference slice types. It should be noted that the present techniques can be used for other number of settings or slice types. In this case, signaling the table cannot be done anymore with a single one-bit flag but requires a parameter providing a larger choice of values, for example an integer number. In addition, the size of the chroma QP table can also be different from 58, for example, the table size can be adapted to the QP range.

(56) FIG. 7A illustrates an example of process used on the decoder side to determine the QP parameter used for the coding and the decoding of the chroma components. The inputs to this process are chromaQP that corresponds to the base chroma QP value for the considered slide (and is the value that will be adapted), a “I-SLICE” flag indicating the type of slice and a “HighPerformanceCodingFlag” indicating if high performance encoding efficiency is expected or not. In step **700**, the type of slice is checked and in the case of a I-SLICE, in step **710**, an index

value is set to 0 to point to the set corresponding to the I-SLICE set. In the other case, in step 711, the index value is set to 1 to point to the set corresponding to the non-I-SLICE set. In step 720, the “HighPerformanceCodingFlag” is checked. When the flag is set to true, in step 731 the outputChroma value is then determined from the set of values of the chromaQPTableHighPerf according to the index and the input value. When the “HighPerformanceCodingFlag” is set to false, in step 730 the outputChroma value is then determined from the set of values of the chromaQPTableStandardPerf according to the index and the input value. For example, if the initial chromaQP value is 57 (thus the “highest” value possible), for an I-SLICE in high performance, the chromaQP value will be set to 54 (the last entry of the last table). This will result in reducing the bitrate for the Chroma component. Conventional decoding process is used to produce a decoded image.

(57) As can be seen, this flag is used to drive the use of a chroma QP table in a normative way.

(58) According to at least one embodiment, the choice between the at least two table of chroma QP tables is achieved as a function of some other coding parameters. These coding parameters may be related to the coding tree configuration or on et of activated coding modes, or on the set of activated partitioning modes chosen for the coding of the considered video sequence.

(59) As an example, the coding parameters that may produce a standard performance level with the considered video codec may be the following one. The coding tree configuration used varies according to the slice type and the temporal layer. The maximum Quad-tree and Binary-tree depths allowed for each picture of a random-access sequence is shown in FIG. 7B and is detailed on ABT and coding tree configuration for the standard performance level.

(60) Table 1 illustrates the Maximum Quad-Tree depth and Binary-Tree depth used in the medium complexity profile, for each slice type, temporal layer, component, for Random-Access coding structure. As can be seen on this table, the maximum allowed quad-tree depth varies according to the slice type, temporal level and component. Moreover, the maximum allowed Binary Tree depth varies according to the slice type, slice temporal layer and quad-tree depth level.

(61) TABLE-US-00001 TABLE 1 Max BT depth for each QT depth = 0 . . . 5 QT QT QT QT QT QT QT Slice Min/Max Component Depth 0 Depth 1 Depth 2 Depth 3 Depth 4 Depth 5 Type T-Id QT depth type SizeY 256 SizeY 128 SizeY 64 SizeY 32 SizeY 16 SizeY 8 I 0 0/3 Luma 0 0 2 6 Chroma 0 2 8 0 B 0 0/5 Luma/Chroma 0 3 3 3 3 3 B 1 0/5 Luma/Chroma 0 2 2 2 2 2 B 2 0/5 Luma/Chroma 0 2 2 2 2 2 8 3 0/5 Luma/Chroma 0 2 2 2 2 2 B 4 0/5 Luma/Chroma 0 2 2 2 2 2

(62) Furthermore, in the standard performance level encoding process, the Quad-Tree and Binary-Tree multiple depths configuration of ABT and coding tree configuration for Medium Complexity (Random Access) is used as the starting configuration when coding a Random-Access intra period. It may be used as the starting coding tree configuration for each Intra period, in the case parallel coding of intra periods is desired.

(63) In addition to that starting configuration, a dynamic adaptation process of the maximum quad-tree and binary-tree depth for subsequent pictures is employed, based on the average quad- and binary-coding trees used in already coded picture in the same temporal level, in the considered intra period.

(64) Furthermore, the coding parameters that may produce a high-performance level with the considered video codec are typically the following ones. The coding tree configuration when starting to code an Intra period is modified for B slices compared to the standard performance configuration. The maximum BT depth is always equal to 3, except for the quad-tree depth level 0. This corresponds to following table.

(65) TABLE-US-00002 TABLE 2 Max BT depth for each QT depth = 0 . . . 5 QT QT QT QT QT QT QT Slice Min/Max Component Depth 0 Depth 1 Depth 2 Depth 3 Depth 4 Depth 5 Type T-Id QT depth type SizeY 256 SizeY 128 SizeY 64 SizeY 32 SizeY 16 SizeY 8 I 0 0/3 Luma 0 0 2 6 Chroma 0 2 6 0 B 0 0/5 Luma/Chroma 0 3 3 3 3 3 B 1 0/5 Luma/Chroma 0 3 3 3 3 3 B 2 0/5 Luma/Chroma 0 3 3 3 3 3 B 3 0/5 Luma/Chroma 0 3 3 3 3 3 B 4 0/5 Luma/Chroma 0 3 3 3 3 3

(66) In other words, Max BT depth is one parameter related to the coding tree configuration that can be used to select the coding performance level and thus select the correspond chroma QP table. According to table 1 and 2 for example, when Max BT depth is equal to 2, the standard performance level chroma QP table is selected and when Max BT depth is greater than 2, the high performance level chroma QP table is selected.

(67) According to a further embodiment, an additional low complexity encoder configuration may be used. In this case, the chroma QP table presented before, which is linked to the standard encoder performance level, may be employed in this low encoder complexity configuration. Alternatively, a dedicated third chroma QP table may be used in the case of the low complexity encoder configuration.

(68) The low complexity encoder configuration introduced here correspond to the following typical encoding parameters. The combinatory level of the partitioning mode rate distortion search may be further reduced in some slices compared to the standard performance level configuration. Typically, the Asymmetric Binary Tree split mods may be deactivated in B slices with a temporal layer strictly higher than 0. Furthermore, some other coding modes, which involve some encoder side rate distortion choice, hence encoder complexity, may be deactivated in the low complexity encoder profile/configuration. For instance, some inter coding tools, like template-based motion search or template based affine motion model search for temporal prediction, may be deactivate in the case of the low complexity profile. In other words, when the tools used are of lower performance level, a chroma QP table with low performance is also chosen.

(69) According to at least one embodiment, the choice of the chroma QP table, between the standard performance one, the high performance one and optionally a low complexity additional one, may be chosen dynamically in each slice, according to the coding tree configuration, and possibly according to the partitioning modes allowed in the considered slice. Therefore, in this embodiment, the chroma QP table used may vary from slice to slice. In that case, the chroma QP table used may be signaled in the slice header, picture header or slice group header.

(70) According to a further alternative of the last embodiment, the chroma QP table may not be explicitly signaled in the slice, picture or tile group header, but may be inferred by the decoder according to the coding tree configuration used in the considered slice, and also, optionally, the coding modes allowed in the considered slice.

(71) In the same way as last embodiment, in the case the same chroma QP table is used in the whole sequence, GOP (Group of Pictures) or intra period, the chroma QP table used in this sequence, intra period or GOP may also be inferred by the decoder, as a function of the coding tree configuration used and signaled in header data, and also, optionally, as a function of the coding mode allowed in the coding/decoding of the considered sequence, intra period or GOP.

(72) The above methods of adapting the chroma quantization parameter can be used to modify the quantization and de-quantization modules (**130, 140, 240**) of the JVET or HEVC encoder and decoder as shown in FIG. 1 and FIG. 2. Moreover, the present embodiments are not limited to JVET or HEVC, and can be applied to other standards, recommendations, and extensions thereof. Various embodiments described above can be used individually or in combination.

(73) FIG. 8 illustrates a block diagram of an example of a system in which various aspects and embodiments are implemented. In at least one embodiment, system **800** can be embodied as a device including the various components described below and is configured to perform one or more of the aspects described in this application. Examples of such devices, include, but are not limited to, various electronic devices such as personal computers, laptop computers, smartphones, tablet computers, digital multimedia set top boxes, digital television receivers, personal video recording systems, connected home appliances, and servers. Elements of system **800**, singly or in combination, can be embodied in a single integrated circuit, multiple ICs, and/or discrete components. For example, in at least one embodiment, the processing and encoder/decoder elements of system **800** are distributed across multiple ICs and/or discrete components. In various

embodiments, the system **800** is communicatively coupled to other similar systems, or to other electronic devices, via, for example, a communications bus or through dedicated input and/or output ports. In various embodiments, the system **800** is configured to implement one or more of the aspects described in this document.

(74) The system **800** includes at least one processor **810** configured to execute instructions loaded therein for implementing, for example, the various aspects described in this document. Processor **810** can include embedded memory, input output interface, and various other circuitries as known in the art. The system **800** includes at least one memory **820** (e.g., a volatile memory device, and/or a non-volatile memory device). System **800** includes a storage device **840**, which can include non-volatile memory and/or volatile memory, including, but not limited to, EEPROM, ROM, PROM, RAM, DRAM, SRAM, flash, magnetic disk drive, and/or optical disk drive. The storage device **840** can include an internal storage device, an attached storage device, and/or a network accessible storage device, as non-limiting examples.

(75) System **800** includes an encoder/decoder module **830** configured, for example, to process data to provide an encoded video or decoded video, and the encoder/decoder module **830** can include its own processor and memory. The encoder/decoder module **830** represents module(s) that can be included in a device to perform the encoding and/or decoding functions. As is known, a device can include one or both of the encoding and decoding modules. Additionally, encoder/decoder module **830** can be implemented as a separate element of system **800** or can be incorporated within processor **810** as a combination of hardware and software as known to those skilled in the art.

(76) Program code to be loaded onto processor **810** or encoder/decoder **830** to perform the various aspects described in this document can be stored in storage device **840** and subsequently loaded onto memory **820** for execution by processor **810**. In accordance with various embodiments, one or more of processor **810**, memory **820**, storage device **840**, and encoder/decoder module **830** can store one or more of various items during the performance of the processes described in this document. Such stored items can include, but are not limited to, the input video, the decoded video or portions of the decoded video, the bitstream, matrices, variables, and intermediate or final results from the processing of equations, formulas, operations, and operational logic.

(77) In several embodiments, memory inside of the processor **810** and/or the encoder/decoder module **830** is used to store instructions and to provide working memory for processing that is needed during encoding or decoding. In other embodiments, however, a memory external to the processing device (for example, the processing device can be either the processor **810** or the encoder/decoder module **830**) is used for one or more of these functions. The external memory can be the memory **820** and/or the storage device **840**, for example, a dynamic volatile memory and/or a non-volatile flash memory. In several embodiments, an external non-volatile flash memory is used to store the operating system of a television. In at least one embodiment, a fast external dynamic volatile memory such as a RAM is used as working memory for video coding and decoding operations, such as for MPEG-2, HEVC, or VC (Versatile Video Coding).

(78) The input to the elements of system **800** can be provided through various input devices as indicated in block **866**. Such input devices include, but are not limited to, (i) an RF portion that receives an RF signal transmitted, for example, over the air by a broadcaster, (ii) a Composite input terminal, (iii) a USB input terminal, and/or (iv) an HDMI input terminal.

(79) In various embodiments, the input devices of block **866** have associated respective input processing elements as known in the art. For example, the RF portion can be associated with elements necessary for (i) selecting a desired frequency (also referred to as selecting a signal, or band-limiting a signal to a band of frequencies), (ii) downconverting the selected signal, (iii) band-limiting again to a narrower band of frequencies to select (for example) a signal frequency band which can be referred to as a channel in certain embodiments, (iv) demodulating the downconverted and band-limited signal, (v) performing error correction, and (vi) demultiplexing to select the desired stream of data packets. The RF portion of various embodiments includes one or

more elements to perform these functions, for example, frequency selectors, signal selectors, band-limiters, channel selectors, filters, downconverters, demodulators, error correctors, and demultiplexers. The RF portion can include a tuner that performs various of these functions, including, for example, downconverting the received signal to a lower frequency (for example, an intermediate frequency or a near-baseband frequency) or to baseband. In one set-top box embodiment, the RF portion and its associated input processing element receives an RF signal transmitted over a wired (for example, cable) medium, and performs frequency selection by filtering, downconverting, and filtering again to a desired frequency band. Various embodiments rearrange the order of the above-described (and other) elements, remove some of these elements, and/or add other elements performing similar or different functions. Adding elements can include inserting elements in between existing elements, such as, for example, inserting amplifiers and an analog-to-digital converter. In various embodiments, the RF portion includes an antenna.

(80) Additionally, the USB and/or HDMI terminals can include respective interface processors for connecting system **800** to other electronic devices across USB and/or HDMI connections. It is to be understood that various aspects of input processing, for example, Reed-Solomon error correction, can be implemented, for example, within a separate input processing IC or within processor **810** as necessary. Similarly, aspects of USB or HDMI interface processing can be implemented within separate interface ICs or within processor **810** as necessary. The demodulated, error corrected, and demultiplexed stream is provided to various processing elements, including, for example, processor **810**, and encoder/decoder **830** operating in combination with the memory and storage elements to process the data stream as necessary for presentation on an output device.

(81) Various elements of system **800** can be provided within an integrated housing. Within the integrated housing, the various elements can be interconnected and transmit data therebetween using suitable connection arrangement, for example, an internal bus as known in the art, including the I2C bus, wiring, and printed circuit boards.

(82) The system **800** includes communication interface **850** that enables communication with other devices via communication channel **870**. The communication interface **850** can include, but is not limited to, a transceiver configured to transmit and to receive data over communication channel **870**. The communication interface **850** can include, but is not limited to, a modem or network card and the communication channel **870** can be implemented, for example, within a wired and/or a wireless medium.

(83) Data is streamed to the system **800**, in various embodiments, using a Wi-Fi network such as IEEE 802.11. The Wi-Fi signal of these embodiments is received over the communications channel **870** and the communications interface **850** which are adapted for Wi-Fi communications. The communications channel **870** of these embodiments is typically connected to an access point or router that provides access to outside networks including the Internet for allowing streaming applications and other over-the-top communications. Other embodiments provide streamed data to the system **800** using a set-top box that delivers the data over the HDMI connection of the input block **866**. Still other embodiments provide streamed data to the system **800** using the RF connection of the input block **866**.

(84) The system **800** can provide an output signal to various output devices, including a display **880**, speakers **882**, and other peripheral devices **884**. The other peripheral devices **884** include, in various examples of embodiments, one or more of a stand-alone DVR, a disk player, a stereo system, a lighting system, and other devices that provide a function based on the output of the system **800**. In various embodiments, control signals are communicated between the system **800** and the display **880**, speakers **882**, or other peripheral devices **884** using signaling such as AV Link, CEC, or other communications protocols that enable device-to-device control with or without user intervention. The output devices can be communicatively coupled to system **800** via dedicated connections through respective interfaces **860**, **862**, and **864**. Alternatively, the output devices can be connected to system **800** using the communications channel **870** via the communications

interface **850**. The display **880** and speakers **882** can be integrated in a single unit with the other components of system **800** in an electronic device such as, for example, a television. In various embodiments, the display interface **860** includes a display driver, such as, for example, a timing controller (T Con) chip.

(85) The display **880** and speaker **882** can alternatively be separate from one or more of the other components, for example, if the RF portions of input **866** is part of a separate set-top box. In various embodiments in which the display **880** and speakers **882** are external components, the output signal can be provided via dedicated output connections, including, for example, HDMI ports, USB ports, or composite (COMP) outputs.

(86) The implementations described herein may be implemented in, for example, a method or a process, an apparatus, a software program, a data stream, or a signal. Even if only discussed in the context of a single form of implementation (for example, discussed only as a method), the implementation of features discussed may also be implemented in other forms (for example, an apparatus or a program). An apparatus may be implemented in, for example, appropriate hardware, software, and firmware. The methods may be implemented in, for example, an apparatus such as, for example, a processor, which refers to processing devices in general, including, for example, a computer, a microprocessor, an integrated circuit, or a programmable logic device. Processors also include communication devices, such as, for example, computers, cell phones, portable/personal digital assistants ("PDAs"), and other devices that facilitate communication of information between end-users.

(87) FIG. **9A** illustrates a flowchart of an example of encoding method according to an embodiment implementing the chroma quantization adaptation. Such an encoding method can be performed by the system **800** described in FIG. **8** and more precisely can be implemented by the processor **810**. In at least one embodiment, in step **910**, the processor **810** selects which chroma QP table set should be used. As described above, the selection can be done using different techniques, for example manually by the user or automatically by the encoder, for example dynamically in each slice according to the coding tree configuration. Once this selection is done, the encoding is performed in step **920** according to the selected quantization parameters for the chroma components and the selection of the chroma QP table is signaled in the high-level syntax elements (for example in the next SPS, PPS or even slice header).

(88) FIG. **9B** illustrates a flowchart of an example of a part of a decoding method according to an embodiment implementing the chroma quantization adaptation. Such a decoding method can be performed by the system **800** described in FIG. **8** and more precisely can be implemented by the processor **810**. In at least one embodiment, in step **950**, the signal is accessed (for example received on an input interface or read from a media support). The high level syntax elements are extracted and analyzed to determine the quantization parameters for the chroma components that have been selected at the encoding device. In step **960**, these parameters are used to dequantize the chroma components. Conventional decoding process is used to produce a decoded image (not illustrated in the FIG. **9B**) that can be for example provided to a device or displayed on a device.

(89) According to another embodiment the number of the coding performance levels used to drive the switch between different chroma QP tables takes a value $N \geq 2$. The SPS syntax element introduced here then takes the form of an integer value

(90) According to an embodiment, because the temporal level usually affects the performance level, the value of the coding performance level depends on the temporal layer to which the slice belongs to. As a consequence, different temporal levels can use different chroma QP tables. This typically applies to the random access temporal coding structure. The SPS element introduced here then includes one coding level value per temporal level.

(91) According to another embodiment, the chroma QP table set is directly coded in the SPS or PPS, under the form of a series of chroma QP values, for each entry of the table. In one example of this embodiment, the table is only coded and decoded for some slice type, typically B slices.

(92) According to another embodiment, the chroma QP table is directly coded in the SPS or PPS, as a series of differential (residual) integer values, indicates the delta between the base chroma QP and the output chroma QP, for each entry in the table.

(93) According to a further embodiment, when the chroma QP table is directly encoded, the chroma QP values are coded only for a limited range (or subset) of the input baseQP values.

(94) According to another embodiment, the chroma QP table is directly coded in the SPS or PPS, as a series of differential (residual) integer values. The first QP delta is coded relatively to the base chroma QP, while following values are coded differentially with the previous value. In another embodiment, the delta with the previous value is assumed to be always positive (no sign to encode).

(95) Reference to “one embodiment” or “an embodiment” or “one implementation” or “an implementation”, as well as other variations thereof, mean that a particular feature, structure, characteristic, and so forth described in connection with the embodiment is included in at least one embodiment. Thus, the appearances of the phrase “in one embodiment” or “in an embodiment” or “in one implementation” or “in an implementation”, as well any other variations, appearing in various places throughout the specification are not necessarily all referring to the same embodiment.

(96) Additionally, this application or its claims may refer to “determining” various pieces of information. Determining the information may include one or more of, for example, estimating the information, calculating the information, predicting the information, or retrieving the information from memory.

(97) Further, this application or its claims may refer to “accessing” various pieces of information. Accessing the information may include one or more of, for example, receiving the information, retrieving the information (for example, from memory), storing the information, moving the information, copying the information, calculating the information, predicting the information, or estimating the information.

(98) Additionally, this application or its claims may refer to “receiving” various pieces of information. Receiving is, as with “accessing”, intended to be a broad term. Receiving the information may include one or more of, for example, accessing the information, or retrieving the information (for example, from memory or optical media storage). Further, “receiving” is typically involved, in one way or another, during operations such as, for example, storing the information, processing the information, transmitting the information, moving the information, copying the information, erasing the information, calculating the information, determining the information, predicting the information, or estimating the information.

(99) It is to be appreciated that the use of any of the following “/”, “and/or”, and “at least one of”, for example, in the cases of “A/B”, “A and/or B” and “at least one of A and B”, is intended to encompass the selection of the first listed option (A) only, or the selection of the second listed option (B) only, or the selection of both options (A and B). As a further example, in the cases of “A, B, and/or C” and “at least one of A, B, and C”, such phrasing is intended to encompass the selection of the first listed option (A) only, or the selection of the second listed option (B) only, or the selection of the third listed option (C) only, or the selection of the first and the second listed options (A and B) only, or the selection of the first and third listed options (A and C) only, or the selection of the second and third listed options (B and C) only, or the selection of all three options (A and B and C). This may be extended, as readily apparent by one of ordinary skill in this and related arts, for as many items listed.

(100) As will be evident to one of skill in the art, implementations may produce a variety of signals formatted to carry information that may be, for example, stored or transmitted. The information may include, for example, instructions for performing a method, or data produced by one of the described implementations. For example, a signal may be formatted to carry the bitstream of a described embodiment. Such a signal may be formatted, for example, as an electromagnetic wave

(for example, using a radio frequency portion of spectrum) or as a baseband signal. The formatting may include, for example, encoding a data stream and modulating a carrier with the encoded data stream. The information that the signal carries may be, for example, analog or digital information. The signal may be transmitted over a variety of different wired or wireless links, as is known. The signal may be stored on a processor-readable medium.

(101) According to a variant embodiment according to first aspect, a method is presented, further comprising generating a bitstream comprising at least said encoded block and metadata representative of said at least one selected chroma quantization parameter.

(102) According to a variant embodiment according to second aspect, a method is presented, further comprising producing a reconstructed image based on the de-quantized chroma values of a plurality of blocks of the image.

(103) According to a variant embodiment according to third aspect, a signal is presented, further comprising an encoding of at least one block of the image.

(104) According to a variant embodiment according to fourth aspect, a device is presented, further comprising means for generating a bitstream comprising at least said encoded block and metadata representative of said at least one selected chroma quantization parameter.

(105) According to a variant embodiment according to fifth aspect, a device is presented, further comprising producing a reconstructed image based on the de-quantized chroma values of a plurality of blocks of the image.

Claims

1. A method for decoding video from a codec video stream comprising: obtaining information representative of a chroma quantization parameter table; and de-quantizing chroma values of a block of the video according to a value of the obtained chroma quantization parameter table, wherein the chroma quantization parameter table is directly coded in a set of parameters at the picture level or at the sequence level of the coded video stream and is coded as a series of differential integer values, each a quantization parameter delta, a first quantization parameter delta being coded relatively to a base chroma quantization parameter while each of the following quantization parameter deltas that follow the first quantization parameter delta are coded differentially with a preceding quantization parameter delta.
2. The method of claim 1, wherein the table is only coded for B slices of the video.
3. The method of claim 1, wherein the chroma quantization parameter values are coded only for a limited range of input base chroma quantization parameter values.
4. The method of claim 1, wherein the quantization parameter delta value is always positive.
5. The method of claim 4, wherein no sign for the quantization parameter delta is encoded.
6. A non-transitory processor readable medium having stored therein instructions for causing a processor to perform the method of claim 1.
7. An apparatus for decoding video from a codec video stream comprising: a processor configured to: obtain information representative of a chroma quantization parameter table; and de-quantize chroma values of a block of the video according to a value of the obtained chroma quantization parameter table, wherein the chroma quantization parameter table is directly coded in a set of parameters at the picture level or at the sequence level of the coded video stream and is coded as a series of differential integer values, each a quantization parameter delta, a first quantization parameter delta being coded relative to a base chroma quantization parameter while each of the following quantization parameter deltas that follow the first quantization parameter delta are coded differentially with a preceding quantization parameter delta.
8. The apparatus of claim 7, wherein the table is only coded for B slices of the video.
9. The apparatus of claim 7, wherein the chroma quantization parameter values are coded only for a limited range of input base chroma quantization parameter values.

10. The apparatus of claim 7, wherein the quantization parameter delta value is always positive.
 11. The apparatus of claim 10, wherein no sign for the quantization parameter delta is encoded.
 12. A method for encoding video comprising: selecting a chroma quantization parameter table; quantizing chroma values of a block of the video according to a value of the obtained chroma quantization parameter table; and encoding the quantized value and high-level syntax information representative of the selected chroma quantization parameter table into a coded video stream, wherein the table is directly coded in a set of parameters at the picture level or at the sequence level of the coded video stream and is coded under the form of a series of differential integer values, each a quantization parameter delta, a first quantization parameter delta being coded relative to a base chroma quantization parameter, while each of the following quantization parameter deltas that follows the first quantization parameter delta are coded differentially with a preceding quantization parameter delta.
 13. The method of claim 12, wherein the quantization parameter delta value is always positive.
 14. The method of claim 13, wherein no sign for the quantization parameter delta is encoded.
 15. A non-transitory processor readable medium having stored therein instructions for causing a processor to perform the method of claim 12.
 16. An apparatus for encoding video comprising: a processor configured to: select a chroma quantization parameter table; quantize chroma values of a block of the video according to a value of the obtained chroma quantization parameter table, and encode the quantized value and high-level syntax information representative of the selected chroma quantization parameter table into a coded video stream, wherein the table is directly coded in a set of parameters at the picture level or at the sequence level of the coded video stream and is coded under the form of a series of differential integer values, each a quantization parameter delta, a first quantization parameter delta being coded relative to a base chroma quantization parameter, while each of the following quantization parameter deltas that follows the first quantization parameter delta are coded differentially with a preceding quantization parameter delta.
 17. The apparatus of claim 16, wherein the quantization parameter delta value is always positive.
 18. The apparatus of claim 17, wherein no sign for the quantization parameter delta is encoded.
-