

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250278481

Kind Code

A2

Publication Date

September 04, 2025

Inventor(s)

Eckel; Nathan A. et al.

ROW HAMMER MITIGATION FOR STACKED MEMORY ARCHITECTURES

Abstract

Methods, systems, and devices for row hammer mitigation for stacked memory architectures are described. A semiconductor system, such as a memory system, may distribute operations for row hammer mitigation across circuitry of the semiconductor system. A first interface block of a first die of the semiconductor system may exchange signaling with a second interface block of a second die of the semiconductor system to perform row hammer mitigation operations. The second die may implement counters to track quantities of access operations associated with respective rows of memory cells of the second die. The second interface block may transmit alert signaling to the first interface block based on a value of a counter, and the first interface block may evaluate the alert signaling and transmit refresh signaling to the second interface block to perform one or more refresh operations.

Inventors: Eckel; Nathan A. (Lufkin, TX), Liu; Chun-Yi (Rancho Cordova, CA), Johnson; Lance P. (Saint Paul, MN), Johnson; James Brian (Boise, ID), Lu; Yang (Boise, ID)

Applicant: Micron Technology, Inc. (Boise, ID)

Family ID: 94387430

Appl. No.: 18/763963

Filed: July 03, 2024

Prior Publication Data

Document Identifier

Publication Date

US 20250045388 A1

Feb. 06, 2025

Related U.S. Application Data

Publication Classification

Int. Cl.: G06F21/55 (20130101)

U.S. Cl.:

CPC G06F21/554 (20130101); G06F2221/034 (20130101)

Background/Summary

CROSS REFERENCE [0001] The present application for patent claims priority to U.S. Patent Application No. 63/517,849 by Eckel et al., entitled “ROW HAMMER MITIGATION FOR STACKED MEMORY ARCHITECTURES,” filed Aug. 4, 2023, which is assigned to the assignee hereof, and which is expressly incorporated by reference in its entirety herein.

TECHNICAL FIELD

[0002] The following relates to one or more systems for memory, including row hammer mitigation for stacked memory architectures.

BACKGROUND

[0003] Memory devices are widely used to store information in devices such as computers, user devices, wireless communication devices, cameras, digital displays, and others. Information is stored by programming memory cells within a memory device to various states. For example, binary memory cells may be programmed to one of two supported states, often denoted by a logic 1 or a logic 0. In some examples, a single memory cell may support more than two states, any one of which may be stored. To access the stored information, the memory device may read (e.g., sense, detect, retrieve, determine) states from the memory cells. To store information, the memory device may write (e.g., program, set, assign) states to the memory cells.

[0004] Various types of memory devices exist, including magnetic hard disks, random access memory (RAM), read-only memory (ROM), dynamic RAM (DRAM), synchronous dynamic RAM (SDRAM), static RAM (SRAM), ferroelectric RAM (FeRAM), magnetic RAM (MRAM), resistive RAM (RRAM), flash memory, phase change memory (PCM), self-selecting memory, chalcogenide memory technologies, not-or (NOR) and not-and (NAND) memory devices, and others. Memory cells may be described in terms of volatile configurations or non-volatile configurations. Memory cells in a non-volatile configuration may maintain stored logic states for extended periods of time even in the absence of an external power source. Memory cells in a volatile configuration may lose stored states when disconnected from an external power source.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0005] FIG. 1 shows an example of a system that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein.

[0006] FIG. 2 shows an example of a system that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein.

[0007] FIG. 3 shows an example of an interface architecture that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein.

[0008] FIG. 4 shows an example of a system that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein.

[0009] FIG. 5 shows an example of an architecture that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein.

[0010] FIG. 6 shows a block diagram of a logic die that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein.

[0011] FIG. 7 shows a block diagram of an array die that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein.

[0012] FIGS. 8 and 9 show flowcharts illustrating methods that support row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein.

DETAILED DESCRIPTION

[0013] Some memory systems may include a stack of semiconductor dies, including one or more memory dies above a logic die that is operable to access a set of memory arrays distributed across the one or more memory dies. Such an architecture may be implemented as part of a coupled dynamic random access memory (DRAM) system, and may support solutions for memory-centric logic, such as graphics processing units (GPUs), among other implementations. In some examples, a 3D stacked memory system may be closely coupled (e.g., physically coupled, electrically coupled) with a processor, such as a GPU or other host, as part of a physical memory map accessible to the processor. Such coupling may include one or more processors being implemented in a same semiconductor die as at least a portion of a 3D stacked memory system (e.g., as part of a logic die), or a processor being implemented in a die that is directly coupled (e.g., fused) with another die that includes at least a portion of a 3D stacked memory system. Unlike cache-based memory, a 3D stacked memory system may not be backed by a level of external memory with the same physical addresses. For example, a 3D stacked memory system may be associated with and located within a dedicated base address, where each portion of the 3D stacked memory system may be non-overlapping within the address.

[0014] In some memory systems that implement a stack of semiconductor dies, memory access circuitry may be distributed among (e.g., across, between) multiple semiconductor dies. For instance, multiple semiconductor dies of a 3D stacked memory system may include a stack of semiconductor dies (e.g., a stack of multiple directly-coupled semiconductor die), including a first die (e.g., a logic die) that is operable to access a set of memory arrays distributed across one or more second dies (e.g., array dies). The logic die may access the set of memory arrays via a first interface block (e.g., memory interface block (MIB)) included in the logic die. The first interface block may communicate with one or more second interface blocks of one or more array dies to access one or more memory arrays. In some cases, a memory array may be organized with multiple rows, and the rows may be physically located near (e.g., adjacent to) each other in the memory array. Each row may include a set of memory cells and may be accessed via a respective address (e.g., a physical address). In some cases, a row (e.g., and its associated memory cells) may be subject to adverse accessing, such as row hammer attacks. Row hammer attacks may include repeated access operations to one or more first rows (e.g., an aggressor row), which may adversely affect one or more neighboring rows (e.g., victim rows, adjacent rows). For example, repeatedly accessing a row may disturb memory cells of one or more neighboring rows such that data stored by the memory cells may be modified (e.g., compromised, corrupted).

[0015] In accordance with examples as disclosed herein, a semiconductor system, such as a 3D stacked memory system or other memory system, may distribute functionality for row hammer mitigation among multiple dies of the semiconductor system. In some examples, a first interface block (e.g., a memory interface block (MIB)) of a first die (e.g., a logic die) of the semiconductor system and a second interface block of a second die (e.g., an array die) of the semiconductor system may exchange signaling (e.g., one or more signals, one or more indications) to coordinate and perform row hammer mitigation operations. For example, a first interface block may transmit

access signaling to the second interface block to access a row of a memory array of the second die. The second die may include counters (e.g., at or associated with a memory array of the array die) that are each associated with a respective row of the memory array (e.g., as per-row counters). For example, each counter may be operable to track (e.g., count, monitor) a quantity of access operations (e.g., activations) associated with the respective row.

[0016] If a value of a counter satisfies one or more threshold values, the second interface block may transmit alert signaling to the first interface block. Such alert signaling may be indicative of a row hammer attack on a row (e.g., aggressor row) associated with the counter. To mitigate adverse effects of the row hammer attack, the first interface block may evaluate the alert signaling and may transmit refresh signaling to the second interface block. The refresh signaling may include one or more refresh commands for one or more neighboring rows (e.g., varying quantities of rows, victim rows) that are located near (e.g., adjacent to) the row. By distributing the operations for row hammer mitigation across multiple semiconductor dies in accordance with one or more of the described techniques, a system may be configured with more robust row hammer mitigation procedures, increased system security, and increased reliability, among other benefits, compared with other techniques for row hammer mitigation in a memory system.

[0017] Features of the disclosure are illustrated and described in the context of systems and dies (e.g., logic die, array dies). Features of the disclosure are further illustrated and described in the context of architectures, block diagrams, and flowcharts.

[0018] FIG. 1 illustrates an example of a system **100** that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein. The system **100** may include portions of an electronic device, such as a computing device, a mobile computing device, a wireless communications device, a graphics processing device, a vehicle, or other systems. The system **100** includes a host system **105**, a memory system **110**, and one or more channels **115** coupling the host system **105** with the memory system **110** (e.g., to provide a communicative coupling). The system **100** may include one or more memory systems **110**, but aspects of the one or more memory systems **110** may be described in the context of a single memory system **110**.

[0019] The host system **105** may be an example of a processor (e.g., circuitry, processing circuitry, one or more processing components) that uses memory to execute processes, such as a processing system of a computing device, a mobile computing device, a wireless communications device, a graphics processing device, a wearable device, an internet-connected device, a vehicle controller, a system on a chip (SoC), or other stationary or portable electronic device, among other examples. The host system **105** may include one or more of an external memory controller **120**, a processor **125**, a basic input/output system (BIOS) component **130**, or other components (e.g., a peripheral component, an input/output controller, not shown). The components of the host system **105** may be coupled with one another using a bus **135**.

[0020] An external memory controller **120** may be configured to enable communication of information (e.g., data, commands, control information, configuration information) between components of the system **100** (e.g., between components of the host system **105**, such as the processor **125**, and the memory system **110**). An external memory controller **120** may process (e.g., convert, translate) communications exchanged between the host system **105** and the memory system **110**. In some examples, an external memory controller **120**, or other component of the system **100**, or associated functions described herein, may be implemented by or be part of the processor **125**. For example, an external memory controller **120** may be hardware, firmware, or software (e.g., instructions), or some combination thereof implemented by a processor **125** or other component of the system **100** or the host system **105**. Although an external memory controller **120** is illustrated outside the memory system **110**, in some examples, an external memory controller **120**, or its functions described herein, may be implemented by one or more components of a memory system **110** (e.g., a memory system controller **155**, a local memory controller **165**) or vice

versa. In various examples, the host system **105** or an external memory controller **120** may be referred to as a host.

[0021] A processor **125** may be operable to provide functionality (e.g., control functionality) for the system **100** or the host system **105**. A processor **125** may be a general-purpose processor, a digital signal processor (DSP), an application-specific integrated circuit (ASIC), a field-programmable gate array (FPGA) or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof. In some examples, a processor **125** may be an example of a central processing unit (CPU), a graphics processing unit (GPU), a general-purpose GPU (GPGPU), or an SoC, among other examples.

[0022] In some examples, the system **100** or the host system **105** may include an input component, an output component, or a combination thereof. Input components may include a sensor, a microphone, a keyboard, another processor (e.g., on a printed circuit board), an interface (e.g., a user interface, an interface between other devices), or a peripheral that interfaces with system **100** via one or more peripheral components, among other examples. Output components may include a display, audio speakers, a printing device, another processor on a printed circuit board, or a peripheral that interfaces with the system **100** via one or more peripheral components, among other examples.

[0023] The memory system **110** may be a component of the system **100** that is operable to provide physical memory locations (e.g., addresses) that may be used or referenced by the system **100**. The memory system **110** may include a memory system controller **155** and one or more memory dies **160** (e.g., memory chips) to support a capacity for data storage. The memory system **110** may be configurable to work with one or more different types of host systems **105**, and may respond to and execute commands provided by the host system **105** (e.g., via an external memory controller **120**). For example, the memory system **110** (e.g., a memory system controller **155**) may receive a write command indicating that the memory system **110** is to store data received from the host system **105**, or receive a read command indicating that the memory system **110** is to provide data stored in a memory die **160** to the host system **105**, or receive a refresh command indicating that the memory system **110** is to refresh data stored in a memory die **160**, among other types of commands and operations.

[0024] A memory system controller **155** may include components (e.g., circuitry, logic) operable to control operations of the memory system **110**. A memory system controller **155** may include hardware, firmware, or instructions that enable the memory system **110** to perform various operations, and may be operable to receive, transmit, or execute commands, data, or control information related to operations of the memory system **110**. A memory system controller **155** may be operable to communicate with one or more of an external memory controller **120**, one or more memory dies **160**, or a processor **125**. In some examples, a memory system controller **155** may control operations of the memory system **110** in cooperation with a local memory controller **165** of a memory die **160**.

[0025] Each memory die **160** may include a local memory controller **165** and a memory array **170**. A memory array **170** may be a collection of memory cells, with each memory cell being operable to store one or more bits of data. A memory die **160** may include a two-dimensional (2D) array of memory cells, or a three-dimensional (3D) array of memory cells. In some examples, a 2D memory die **160** may include a single memory array **170**. In some examples, a 3D memory die **160** may include two or more memory arrays **170**, which may be stacked or positioned beside one another (e.g., relative to a substrate).

[0026] A local memory controller **165** may include components (e.g., circuitry, logic) operable to control operations of a memory die **160**. In some examples, a local memory controller **165** may be operable to communicate (e.g., receive or transmit data or commands or both) with a memory system controller **155**. In some examples, a memory system **110** may not include a memory system controller **155**, and a local memory controller **165** or an external memory controller **120** may

perform various functions described herein. As such, a local memory controller **165** may be operable to communicate with a memory system controller **155**, with other local memory controllers **165**, or directly with an external memory controller **120**, or a processor **125**, or any combination thereof. Examples of components that may be included in a memory system controller **155** or a local memory controller **165** or both may include receivers for receiving signals (e.g., from the external memory controller **120**), transmitters for transmitting signals (e.g., to the external memory controller **120**), decoders for decoding or demodulating received signals, encoders for encoding or modulating signals to be transmitted, sense components for sensing states of memory cells of a memory array **170**, write components for writing states to memory cells of a memory array **170**, or various other components operable for supporting described operations of a memory system **110**.

[0027] A host system **105** (e.g., an external memory controller **120**) and a memory system **110** (e.g., a memory system controller **155**) may communicate information (e.g., data, commands, control information, configuration information) using one or more channels **115**. Each channel **115** may be an example of a transmission medium that carries information, and each channel **115** may include one or more signal paths (e.g., a transmission medium, an electrical conductor, an electrically conductive path) between terminals associated with the components of the system **100**. For example, a channel **115** may be associated with a first terminal (e.g., including one or more pins, including one or more pads) at the host system **105** and a second terminal at the memory system **110**. A terminal may be an example of a conductive input or output point of a device of the system **100**, and a terminal may be operable to act as part of a channel **115**. In some implementations, at least the channels **115** between a host system **105** and a memory system **110** may include or be referred to as a host interface (e.g., a physical host interface). In some implementations, a host interface may include or be associated with interface circuitry (e.g., signal drivers, signal latches) at the host system **105** (e.g., at an external memory controller **120**), or at the memory system **110** (e.g., at a memory system controller **155**), or both.

[0028] In some examples, a channel **115** (e.g., associated signal paths and terminals) may be dedicated to communicating one or more types of information. For example, the channels **115** may include one or more command and address channels, one or more clock signal channels, one or more data channels, among other channels or combinations thereof. In some examples, signaling may be communicated via the channels **115** using single data rate (SDR) signaling or double data rate (DDR) signaling. In SDR signaling, one modulation symbol (e.g., signal level) of a signal may be registered for each clock cycle (e.g., on a rising or falling edge of a clock signal). In DDR signaling, two modulation symbols of a signal may be registered for each clock cycle (e.g., on both a rising edge and a falling edge of a clock signal).

[0029] In some examples, at least a portion of the system **100** may implement a stacked die architecture in which multiple semiconductor dies are physically and communicatively coupled. In some implementations, one or more semiconductor dies may include multiple instances of interface circuitry (e.g., of a memory system **110**, memory interface blocks) that are each associated with accessing a respective set of one or more memory arrays **170** of one or more other semiconductor dies. In some cases, circuitry for accessing one or more memory arrays **170** may be distributed among multiple semiconductor dies of a stack (e.g., a stack of multiple directly-coupled semiconductor dies). For example, a first die may include a logic block (e.g., a common logic block, a central logic block, logic circuitry) operable to configure a set of multiple first interface blocks (e.g., MIBs, instances of first interface circuitry) of the first die. In some examples, the system may include a respective controller (e.g., a memory controller, a host interface controller, at least a portion of a memory system controller **155**, at least a portion of an external memory controller **120**, or a combination thereof) for each first interface block to support access operations (e.g., to access one or more memory arrays **170**) via the first interface block. The system **100** may also include non-volatile storage, one or more sensors, or a combination thereof to support various

operations of the system **100**.

[0030] In accordance with examples as disclosed herein, multiple semiconductor dies of a memory system **110** (e.g., a 3D stacked memory system) may include one or more second dies (e.g., memory dies **160**, array dies) stacked with a first die (e.g., a logic die that includes the host system **105**, a logic die that is coupled with a third die that includes the host system **105**) that includes interface blocks operable to access a set of memory arrays **170** distributed across the one or more second dies. In some cases, memory cells in the set of memory arrays **170** may be subject to adverse access operations, such as a row hammer attack. To mitigate (e.g., avoid, reduce) adverse effects resulting from row hammer attacks, the operations for row hammer mitigation may be distributed across circuitry of the system **100**.

[0031] In some examples, a first interface block of the first die and a second interface block of a second die of the one or more second dies may exchange signaling to perform row hammer mitigation operations. For example, the memory system **110** may implement counters to track respective quantities of access operations (e.g., activation operations) for respective addresses of respective memory arrays **170**, such as respective rows of memory cells of the respective memory arrays **170**. In some examples, the second interface block may transmit alert signaling to the first interface block based on a value of a counter satisfying one or more threshold values. The first interface block may evaluate the alert signaling and may issue one or more refresh commands to the second interface block in response to the alert signaling. A refresh command may indicate one or more addresses for refreshing, such as rows (e.g., victim rows) that are neighboring (e.g., adjacent to) a row (e.g., an aggressor row) associated with the alert signaling. By exchanging signaling associated with row hammer mitigation between multiple semiconductor dies in accordance with one or more of the described techniques, a system may be configured with more robust row hammer mitigation procedures, increased security, and increased reliability, among other advantages, compared with other techniques for row hammer mitigation.

[0032] In addition to applicability in systems as described herein, interface techniques for stacked memory architectures may be generally implemented to support artificial intelligence applications. As the use of artificial intelligence increases to support machine learning, analytics, decision making, or other related applications, electronic devices that support artificial intelligence applications and processes may be desired. For example, artificial intelligence applications may be associated with accessing relatively large quantities of data for analytical purposes and may benefit from memory systems capable of effectively and efficiently storing relatively large quantities of data or accessing stored data relatively quickly. Implementing the techniques described herein may support artificial intelligence or machine learning techniques by supporting robust protection and efficient accessing of information via a relatively high quantity of closely-coupled interfaces (e.g., channels, data paths, support stacks) between a host and memory arrays of one or more semiconductor dies that are stacked over a logic die, such as by implementing robust row hammer mitigation procedures in a system that includes the stacked logic die and semiconductor dies, among other benefits.

[0033] FIG. 2 illustrates an example of a system **200** (e.g., a semiconductor system, a system of coupled semiconductor dies) that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein. The system **200** illustrates an example of a die **205** (e.g., a semiconductor die, a host die, a processor die, a logic die) that is coupled with one or more dies **240** (e.g., dies **240-a-1** and **240-a-2**, semiconductor dies, memory dies, array dies). A die **205** or a die **240** may be formed using a respective semiconductor substrate (e.g., a substrate of crystalline semiconductor material such as silicon, germanium, silicon-germanium, gallium arsenide, or gallium nitride), or a silicon-on-insulator (SOI) substrate (e.g., silicon-on-glass (SOG), silicon-on-sapphire (SOS)), or epitaxial semiconductor materials formed on another substrate, among other examples. Although the illustrated example of a system **200** includes two dies **240**, a system **200** in accordance with the described techniques may include any

quantity of one or more dies **240** coupled with a die **205**. Further, although non-limiting examples of the system **200** herein are generally described in terms of applicability to memory systems, memory sub-systems, memory devices, or a combination thereof, examples of the system **200** are not so limited. For example, aspects of the present disclosure may be applied as well to any computing system, computing sub-system, processing system, processing sub-system, component, device, structure, or other types of systems or sub-systems used for applications such as data collecting, data processing, data storage, networking, communication, power, artificial intelligence, system-on-a-chip, control, telemetry, sensing and monitoring, digital entertainment, or any combination thereof.

[0034] The system **200** illustrates an example of interface circuitry between a host and memory (e.g., via a host interface, via a physical host interface) that is implemented in (e.g., divided between) multiple semiconductor dies (e.g., a stack of directly coupled dies). For example, the die **205** may include a set of one or more interface blocks **220** (e.g., interface blocks **220-a-1** and **220-a-2**, memory interface blocks), and each die **240** may include a set of one or more interface blocks **245** and one or more memory arrays **250** (e.g., die **240-a-1** including an interface block **245-a-1** coupled with a set of one or more memory arrays **250-a-1**, die **240-a-2** including an interface block **245-a-2** coupled with a set of one or more memory arrays **250-a-2**). The memory arrays **250** may be examples of memory arrays **170**, and may include memory cells of various architectures, such as RAM, DRAM, SDRAM, SRAM, FeRAM, MRAM, RRAM, PCM, chalcogenide, NOR, or NAND memory cells, or any combination thereof.

[0035] Although the example of system **200** is illustrated with one interface block **245** included in each die **240**, a die **240** in accordance with the described techniques may include any quantity of one or more interface blocks **245**, each coupled with a respective set of one or more memory arrays **250**, and each coupled with a respective interface block **220** of a die **205**. Thus, the interface circuitry of a system **200** may include one or more interface blocks **220** of a die **205**, with each interface block **220** being coupled with (e.g., in communication with) a corresponding interface block **245** of a die **240** (e.g., external to the die **205**). In some examples, a coupled combination of an interface block **220** and an interface block **245** (e.g., coupled via a bus associated with one or more channels, such as one or more data channels, one or more control channels, one or more clock channels, or a combination thereof) may include or be referred to as a data path associated with a respective set of one or more memory arrays **250**.

[0036] In some implementations, the die **205** may include a host processor **210**. A host processor **210** may be an example of a host system **105**, or a portion thereof (e.g., a processor **125**, aspects of an external memory controller **120**, or both). The host processor **210** may be configured to perform operations that implement storage of the memory arrays **250**. For example, the host processor **210** may receive data read from the memory arrays **250**, or may transmit data to be written to the memory arrays **250**, or both (e.g., in accordance with an application or other operations of the host processor **210**). Additionally, or alternatively, a host processor **210** may be external to a die **205**, such as in another semiconductor die or other component that is coupled with (e.g., communicatively coupled with, directly coupled with, bonded with) the die **205** via one or more contacts **212**.

[0037] A host processor **210** may be configured to communicate (e.g., transmit, receive) signaling with the interface blocks **220** via one or more host interfaces **216** (e.g., a physical host interface), which may implement aspects of channels **115** described with reference to FIG. **1**. For example, the host processor **210** may be configured to transmit access signaling (e.g., control signaling, access command signaling, configuration signaling) via host interfaces **216**, which may be received by the interface blocks **220** to support access operations (e.g., read operations, write operations) on the memory arrays **250**. In some examples, a host interface **216** may include a respective set of one or more signal paths for each interface block **220**, such that the host processor **210** may communicate with each interface block **220** via the respective set of signal paths (e.g., in accordance with a

selection of the respective set to perform access operations via an interface block **220** that is selected by the host processor **210**). Additionally, or alternatively, a host interface **216** may include one or more signal paths that are shared among multiple interface blocks **220** (not shown), and an interface block **220**, or a host processor **210**, or both may interpret, ignore, respond to, or inhibit response to signaling via shared signal paths of the host interface **216** based on a logical indication (e.g., an addressing indication associated with the interface block **220** or an interface enable signal, which may be provided by the host processor **210** or the corresponding interface block **220**, depending on signaling direction).

[0038] In some examples, a respective host interface **216** may be coupled between a set of one or more interface blocks **220** and a controller **215** (e.g., host interface **216-a-1** coupled between interface block **220-a-1** and controller **215-a-1**, host interface **216-a-2** coupled between interface block **220-a-2** and controller **215-a-2**). The one or more interface blocks **220** and the controller **215** may communicate (e.g., collaborate) to perform one or more operations (e.g., scheduling operations, access operations, operations initiated by a host processor **210**) associated with a memory array **250**. A controller **215** may be an example of control circuitry (e.g., memory controller circuitry, host interface control circuitry), and may be associated with implementing respective instances of one or more aspects of an external memory controller **120**, or of a memory system controller **155**, or a combination thereof for each interface block **220**. In some examples, controllers **215** may be implemented in a die **205** whether a host processor **210** is included in the die **205**, or is external to the die **205**, and the interface block **220** may communicate with the host processor **210** via one or more controllers **215**. In some other examples, controllers **215** may be implemented external to a die **205** (e.g., in another die, not shown, coupled with respective interface blocks **220** via respective terminals for each of the respective host interfaces **216**), which may be in a same die as or a different die from a die that includes a host processor **210**. In some other examples, aspects of one or more controllers **215** may be included in the host processor **210**. Although the example of system **200** is illustrated as including a controller **215** for each interface block **220**, in various examples, a controller **215** may be coupled with any quantity of one or more interface blocks **220**, and a given interface block **220** may be operable based on single controller **215**, or by one or more of a set of multiple controllers **215** (e.g., in accordance with a controller multiplexing scheme).

[0039] In some examples, a host processor **210** may determine to access an address (e.g., a logical address of a memory array **250**, a physical address of a memory array **250**, an address of an interface block **220**), and determine which controller **215** to transmit access signaling to for accessing the address (e.g., a controller **215** or interface block **220** corresponding to the address). In some examples, the address may be associated with a row of memory cells of the memory array **250**. The host processor **210** may transmit access signaling to the determined controller **215** and, in turn, the determined controller **215** may transmit access signaling to the corresponding interface block **220**. The corresponding interface block **220** may subsequently transmit access signaling to the coupled interface block **245** to access the determined address (e.g., in a corresponding memory array **250**).

[0040] A die **205** may also include a logic block **230** (e.g., a shared logic block, a central logic block, common logic circuitry), which may be configured to communicate (e.g., transmit, receive) signaling with the interface blocks **220** of the die **205**. In some cases, the logic block **230** may be configured to communicate information (e.g., commands, instructions, indications, data) with one or more interface blocks **220** to facilitate operations of the system **200**. For example, a logic block **230** may be configured to transmit configuration signaling (e.g., initialization signaling, evaluation signaling), which may be received by interface blocks **220** to support configuration of the interface blocks **220** or other aspects of operating the dies **240** (e.g., via the respective interface blocks **245**). A logic block **230** may be coupled with each interface block **220** via a respective bus **231** (e.g., bus **231-a-1** associated with the interface block **220-a-1**, bus **231-a-2** associated with the interface

block **220-a-2**). In some examples, respective buses **231** may each include a respective set of one or more signal paths, such that a logic block **230** may communicate with each interface block **220** via the respective set of signal paths. Additionally, or alternatively, respective buses **231** may include one or more signal paths that are shared among multiple interface blocks **220** (not shown).

[0041] In some implementations, a logic block **230** may be configured to communicate (e.g., transmit, receive) signaling with a host processor **210** (e.g., via a bus **232**, via a contact **212** for a host processor **210** external to a die **205**) such that the logic block **230** may support an interface between the interface blocks **220** and the host processor **210**. For example, a host processor **210** may be configured to transmit initialization signaling (e.g., boot commands), or other configuration or operational signaling, which may be received by a logic block **230** to support initialization, configuration, or other operations of the interface blocks **220**. Additionally, or alternatively, in some implementations, a logic block **230** may be configured to communicate (e.g., transmit, receive) signaling with a component outside the system **200** via a bus **233** (e.g., and via a contact **234**), such that the logic block **230** may support an interface that bypasses a host processor **210**. Additionally, or alternatively, a logic block **230** may communicate with a host processor **210**, and may communicate with one or more memory arrays **250** of one or more dies **240** (e.g., to perform self-test operations for the memory arrays **250**). In some examples, such implementations may support evaluations, configurations, or other operations of the system **200**, via contacts **234** that are accessible at a physical interface of the system, during manufacturing, assembly, validation, or other operation associated with the system **200** (e.g., before coupling with a host processor **210**, without implementing a host processor **210**, for operations independent of a host processor).

[0042] Each interface block **220** may be coupled with at least a respective bus **221** of the die **205**, and a respective bus **246** of a die **240**, that are configured to communicate signaling with a corresponding interface block **245** (e.g., via one or more associated signal paths). For example, the interface block **220-a-1** may be coupled with the interface block **245-a-1** via a bus **221-a-1** and a bus **246-a-1**, and the interface block **220-a-2** may be coupled with the interface block **245-a-2** via a bus **221-a-2** and a bus **246-a-2**. In some examples, a die **240** may include a bus that bypasses operational circuitry of the die **240** (e.g., bypasses interface blocks **245** of a given die **240**), such as a bus **255**. For example, the interface block **220-a-2** may be coupled with the interface block **245-a-2** of the die **240-a-2** via a bus **255-a-1** of the die **240-a-1**, which may bypass interface blocks **245** of the die **240-a-1**. Such techniques may be extended for interconnection among more than two dies **240** (e.g., for interconnection via a respective bus **255** of multiple dies **240**).

[0043] The respective signal paths of buses **221**, **246**, and **255** may be coupled with one another, from one die to another, via various arrangements of contacts at the surfaces of interfacing dies. For example, the bus **221-a-1** may be coupled with the bus **246-a-1** via a contact **222-a-1** of (e.g., at a surface of) the die **205** and a contact **247-a-1** of the die **240-a-1**, the bus **221-a-2** may be coupled with the bus **255-a-1** via a contact **222-a-2** of the die **205** and a contact **256-a-1** of the die **240-a-1**, the bus **255-a-1** may be coupled with the bus **246-a-2** via a contact **257-a-1** of the die **240-a-1** and a contact **247-a-2** of the die **240-a-2**, and so on. Although each respective bus is illustrated with a single line, coupled via singular contacts, it is to be understood that each signal path of a given bus may be associated with respective contacts to support a separate communicative coupling via each signal path of the given bus. In some examples, a bus **255** may traverse a portion of a die **240** (e.g., in an in-plane direction, along a direction different from a thickness direction, in a waterfall arrangement), which may support an arrangement of contacts **222** along a surface of a die **205** being coupled with interface blocks **245** of different dies **240** along a stack direction (e.g., via respective contacts **256** and **257** that are non-overlapping when viewed along a thickness direction).

[0044] The interconnection of interfacing contacts may be supported by various techniques. For example, in a hybrid bonding implementation, interfacing contacts may be coupled by a fusion of conductive materials (e.g., electrically conductive materials) of the interfacing contacts (e.g., without solder or other intervening material between contacts). For example, in an assembled

condition, the coupling of the die **205** with the die **240-a-1** may include a conductive material of the contact **222-a-2** being fused with a conductive material of the contact **256-a-1**, and the coupling of the die **240-a-1** with the die **240-a-2** may include a conductive material of the contact **257-a-1** being fused with a conductive material of the contact **247-a-2**, and so on. In some examples, such coupling may include an inoperative fusion of contacts (e.g., a non-communicative coupling, a physical coupling), such as a fusion of the contact **260-a-1** with the contact **256-a-2**, neither of which are coupled with operative circuitry of the dies **240-a-1** or **240-a-2**. In some examples, such techniques may be implemented to improve coupling strength or uniformity (e.g., implementing contacts **260**, which may not be operatively coupled with an interface block **245** or an interface block **220**), or such a coupling may be a byproduct of a repetition of components that, in various configurations, may be operative or inoperative. (e.g., where, for dies **240** with a common arrangement of contacts **256** and **257**, contacts **256-a-1** and **257-a-1** provide a communicative path between the interface block **245-a-2** and the interface block **220-a-2**, but the contacts **256-a-2** and **257-a-2** do not provide a communicative path between an interface block **245** and an interface block **220**).

[0045] In some examples, a fusion of conductive materials between dies (e.g., between contacts) may be accompanied by a fusion of other materials at one or more surfaces of the interfacing dies. For example, in an assembled condition, the coupling of the die **205** with the die **240-a-1** may include a dielectric material **207** (e.g., an electrically non-conductive material) of the die **205** being fused with a dielectric material **242** of the die **240-a-1**, and the coupling of the die **240-a-1** with the die **240-a-2** may include a dielectric material **242** of the die **240-a-1** being fused with a dielectric material **242** of the die **240-a-2**. In some examples, such dielectric materials may include an oxide, a nitride, a carbide, an oxide-nitride, an oxide-carbide, or other conversion or doping of a semiconductor material of the die **205** or dies **240**, among other materials that may support such fusion. However, coupling among dies **205** and dies **240** may be implemented in accordance with other techniques, which may implement solder, adhesives, thermal interface materials, and other intervening materials.

[0046] In some examples, dies **240** may be coupled in a stack (e.g., forming a “cube” or other arrangement of dies **240**), and the stack may subsequently be coupled with a die **205**. In some examples, a respective set of one or more dies **240** may be coupled with each die **205** of multiple dies **205** formed in a wafer (e.g., in a chip-to-wafer bonding arrangement, before cutting the wafer of dies **205**), and the dies **205**, coupled with their respective set of dies **240**, may be separated from one another (e.g., by cutting at least the wafer of dies **205**). In some other examples, a respective set of one or more dies **240** may be coupled with a respective die **205** after the die **205** is separated from a wafer of dies **205** (e.g., in a chip-to-chip bonding arrangement).

[0047] The buses **221**, **246**, and **255** may be configured to provide a configured signaling (e.g., a coordinated signaling, a logical signaling, modulated signaling, digital signaling, one or more signals) between an interface block **220** and a corresponding interface block **245**, which may involve various modulation or encoding techniques by a transmitting interface block (e.g., via a driver component of the transmitting interface block). In some examples, such signaling may be supported by (e.g., accompanied by) clock signaling communicated via the respective buses (e.g., in coordination with signal transmission). For example, the buses may be configured to convey one or more clock signals transmitted by the interface block **220** for reception by the interface block **245** (e.g., to trigger signal reception by a latch or other reception component of the interface block **245**, to support clocked operations of the interface block **245**). Additionally, or alternatively, the buses may be configured to convey one or more clock signals transmitted by the interface block **245** for reception by the interface block **220** (e.g., to trigger signal reception by a latch or other reception component of the interface block **220**, to support clocked operations of the interface block **220**). Such clock signals may be associated with the communication (e.g., unidirectional communication, bidirectional communication) of various signaling, such as control signaling,

command signaling, data signaling, or any combination thereof. For example, the buses may include one or more signal paths for communications of a data bus (e.g., one or more data channels, a DQ bus, via a data interface of the interface blocks) in accordance with one or more corresponding clock signals (e.g., data clock signals), or one or more signal paths for communications of a control bus (e.g., a command/address (C/A) bus, via a command interface of the interface blocks) in accordance with one or more clock signals (e.g., control clock signals), or any combination thereof.

[0048] Interface blocks **220**, interface blocks **245**, and logic block **230** each may include circuitry (signaling circuitry, multiplexing circuitry, processing circuitry, controller circuitry) in various configurations (e.g., hardware configurations, logic configurations, software or instruction configurations) that support the functionality allocated to the respective block for accessing or otherwise operating a corresponding set of memory arrays **250**. For example, interface blocks **220** may include circuitry configured to perform a first subset of operations that support access of the memory arrays **250**, and interface blocks **245** may include circuitry configured to support a second subset of operations that support access of the memory arrays **250**. In some examples, the interface blocks **220** and **245** may support a functional split or distribution of functionality associated with a memory system controller **155**, a local memory controller **165**, or both across multiple dies (e.g., a die **205** and at least one die **240**). In some implementations, a logic block **230** may be configured to coordinate or configure aspects of the operations of the interface blocks **220**, of the interface blocks **245**, or both, and may support implementing one or more aspects of a memory system controller **155**. Such operations, or subsets of operations, may include operations performed in response to commands from the host processor **210**, or operations performed without commands from the host processor **210** (e.g., operations determined or initiated by an interface block **220**, operations determined or initiated by an interface block **245**, operations determined or initiated by a logic block **230**), or various combinations thereof.

[0049] In some implementations, the system **200** may include one or more instances of non-volatile storage (e.g., non-volatile storage **235** of a die **205**, non-volatile storage **270** of one or more dies **240**, or a combination thereof). In some examples, a logic block **230**, interface blocks **220**, interface blocks **245**, or a combination thereof may be configured to communicate signaling with one or more instances of non-volatile storage. For example, a logic block **230**, interface blocks **220**, or interface blocks **245** may be coupled with one or more instances of non-volatile storage via one or more buses (not shown), or respective contacts (not shown), where applicable, which may each include one or more signal paths operable to communicate signaling (e.g., command signaling, data signaling). In some examples, a logic block **230**, one or more interface blocks **220**, one or more interface blocks **245**, or a combination thereof may configure one or more operations based on information stored in one or more instances of non-volatile storage. Additionally, or alternatively, in some examples, a logic block **230**, one or more interface blocks **220**, one or more interface blocks **245**, or a combination thereof may write information (e.g., configuration information) to be stored in one or more instances of non-volatile storage.

[0050] In some implementations, the system **200** may include one or more sensors (e.g., one or more sensors **237** of a die **205**, one or more sensors **275** of one or more dies **240**, or a combination thereof). In some implementations, a logic block **230**, interface blocks **220**, interface blocks **245**, or a combination thereof may be configured to receive one or more indications based on measurements of one or more sensors of the system **200**. For example, a logic block **230**, interface blocks **220**, or interface blocks **245** may be coupled with one or more sensors via one or more buses (not shown), or respective contacts (not shown). Such sensors may include temperature sensors, current sensors, voltage sensors, counters, and other types of sensors. In some examples, a logic block **230**, one or more interface blocks **220**, one or more interface blocks **245**, or a combination thereof may configure one or more operations based on output of the one or more sensors. For example, a logic block **230** may configure one or more operations of interface blocks

220 based on signaling (e.g., indications, data) received from the one or more sensors. Additionally, or alternatively, an interface block **220** may generate access signaling for transmitting to a corresponding interface block **245** based on one or more sensors.

[0051] In some examples, circuitry of interface blocks **220**, interface blocks **245**, or a logic block **230**, or any combination thereof may include components (e.g., transistors) formed at least in part from doped portions of a substrate of the respective die. In some examples, a substrate of a die **205** may have characteristics that are different from those of a substrate of a die **240**. Additionally, or alternatively, in some examples, transistors formed from a substrate of a die **205** may have characteristics that are different from transistors formed from a substrate of a die **240** (e.g., in accordance with different transistor architectures).

[0052] In some examples, the interface blocks **220** may support a layout for one or more components within the **220**. For example, the layout may include pairing components to share an access port (e.g., a command port, a data port). Further, in some examples, the layout may support interfaces for a controller **215** (e.g., a host interface **216**) that are different from interfaces for an interface block **245** (e.g., via the buses **221**). For instance, a host interface **216** may be synchronous and have separate channels for read and write operations, while an interface via buses **221** and **246** may be asynchronous and support both read and write operations with a same channel.

[0053] A die **240** may include one or more units **265** (e.g., modules) that are separated from a semiconductor wafer having a pattern (e.g., a two-dimensional pattern) of units **265**. Although each die **240** of the system **200** is illustrated with a single unit **265** (e.g., unit **265-a-1** of die **240-a-1**, unit **265-a-2** of die **240-a-2**), a die **240** in accordance with the described techniques may include any quantity of units **265**, which may be arranged in various patterns (e.g., sets of one or more units **265** along a row direction, sets of one or more units **265** along a column direction, among other patterns). Each unit **265** may include at least the circuitry of a respective interface block **245**, along with memory array(s) **250**, a bus **251**, a bus **246**, and one or more contacts **247** corresponding to the respective interface block **245**. In some examples, where applicable, each unit **265** may also include one or more buses **255**, contacts **256**, contacts **257**, or contacts **260** (e.g., associated with a respective interface block **245** of a unit **265** of a different die **240**), which may support various degrees of stackability or modularity among or via units **265** of other dies **240**.

[0054] In some examples, the interface blocks **220** may include circuitry configured to receive first access command signaling from a host processor **210** or a controller **215** (e.g., via a host interface **216**, via one or more contacts **212** from a host processor **210** or controller **215** external to a die **205**), and to transmit second access command signaling to the respective (e.g., coupled) interface block **245** based on (e.g., in response to) the received first access command signaling. The interface blocks **245** may accordingly include circuitry configured to receive the second access command signaling from the respective interface block **220** and, in some examples, to access a respective set of one or more memory arrays **250** based on (e.g., in response to) the received second access command signaling. In various examples, the first access command signaling may include access commands that are associated with a type of operation (e.g., a read operation, a write operation, a refresh operation, a memory management operation), which may be associated with an indication of an address of the one or more memory arrays **250** (e.g., a logical address, a physical address). In some examples, the first access command signaling may include an indication of a logical address associated with the memory arrays **250**, and circuitry of an interface block **220** may be configured to generate the second access command signaling to indicate a physical address associated with the memory arrays **250** (e.g., a row address, a column address, using a logical-to-physical (L2P) table or other mapping or calculation functionality of the interface block **220**).

[0055] In some examples, to support write operations of the system **200**, circuitry of the interface blocks **220** may be configured to receive (e.g., from a host processor **210**, from a controller **215**, via a host interface **216**, via one or more contacts **212** from a host processor **210** or controller **215** external to a die **205**) first data signaling associated with the first access command signaling, and to

transmit second data signaling (e.g., associated with second access command signaling) based on received first access command signaling and first data signaling. The interface blocks **245** may accordingly be configured to receive second data signaling, and to write data to one or more memory arrays **250** (e.g., in accordance with an indicated address associated with the first access command signaling) based on the received second access command signaling and second data signaling. In some examples, the interface blocks **220** may include an error control functionality (e.g., error detection circuitry, error correction circuitry, error correction code (ECC) logic, an ECC engine) that supports the interface blocks **220** generating the second data signaling based on performing an error control operation using the received first data signaling (e.g., detecting or correcting an error in the first data signaling, determining one or more parity bits to be conveyed in the second data signaling and written with the data).

[0056] In some examples, to support read operations of the system **200**, circuitry of the interface blocks **245** may be configured to read data from the memory arrays **250** based on received second access command signaling, and to transmit first data signaling based on the read data. The interface blocks **220** may accordingly be configured to receive first data signaling, and to transmit second data signaling (e.g., to a host processor **210**, to a controller **215**, via a host interface **216**, via one or more contacts **212** to a host processor **210** or controller **215** external to a die **205**) based on the received first data signaling. In some examples, the interface blocks **220** may include an error control functionality that supports the interface blocks **220** generating the second data signaling based on performing an error control operation using the received first data signaling (e.g., detecting or correcting an error in the first data signaling, which may include a calculation involving one or more parity bits received with the first data signaling).

[0057] In some examples, access command signaling that is transmitted by the interface blocks **220** to the interface blocks **245**, among other signaling, may be generated (e.g., based on access command signaling received from a host processor **210**, based on initiation signaling received from a host processor **210**, without receiving or otherwise independent from signaling from a host processor **210**) in accordance with various determination or generation techniques configured at the interface blocks **220** (e.g., based on a configuration for accessing memory arrays **250** that is modified at the interface blocks **220**). In some examples, such techniques may involve signaling or other coordination with a logic block **230**, a host processor **210**, one or more controllers **215**, one or more instances of non-volatile storage, one or more sensors, or any combination thereof. Such techniques may support the interface blocks **220** configuring aspects of the access operations performed on the memory arrays **250** by a respective interface block **245**, among other operations. For example, interface blocks **220** may include evaluation circuitry, access configuration circuitry, signaling circuitry, scheduling circuitry, repair circuitry, refresh circuitry, error control circuitry, adverse access circuitry, and other circuitry operable to configure operations associated with one or more dies (e.g., operations associated with accessing memory arrays **250** of the dies **240**).

[0058] In some cases, memory cells in the memory arrays **250** may be subject to adverse access operations, such as a row hammer attack, which may modify (e.g., compromise, corrupt) data stored by the memory cells. As part of a row hammer attack, a row of memory cells (e.g., an aggressor row) of a memory array **250** may undergo repeated (e.g., a quantity exceeding a threshold) access operations, such as within a relatively short duration. To reduce adverse effects associated with row hammer attacks, the system **200** may distribute operations for row hammer mitigation across multiple dies of the system **200**, such across a die **205** and one or more dies **240**. For instance, an interface block **220** and an interface block **245** may exchange signaling to perform row hammer mitigation operations. For example, the system **200** may utilize counters (e.g., at or coupled with a memory array **250**) to track quantities of access operations on (e.g., activations of) respective rows of one or more memory arrays **250**. In some examples, the interface block **245** may transmit alert signaling to the interface block **220** based on a value of one of the counters satisfying one or more threshold values. The interface block **220** may evaluate the received alert signaling and

may issue one or more refresh commands to the interface block **245** in response to the alert signaling. For example, the alert signaling may include a value that indicates which of the one or more thresholds is satisfied by the value of the counter or whether there is an error associated with the counter. A refresh command may indicate one or more rows (e.g., victim rows) for refreshing that are neighbors (e.g., adjacent) to a row associated with the alert signaling (e.g., an aggressor row). By exchanging signaling associated with row hammer mitigation between multiple semiconductor dies in accordance with one or more of the described techniques, interfacing circuitry of the multiple semiconductor dies may support row hammer mitigation within a 3D stacked memory system and may be configured with more robust row hammer mitigation procedures, increased reliability, among other advantages, compared with other techniques for row hammer mitigation.

[0059] FIG. **3** illustrates an example of an interface architecture **300** that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein. The interface architecture **300** illustrates an example of an interface block **245-b** (e.g., of a die **240**) coupled with an interface block **220-b** (e.g., of a die **205**). The interface block **245-b** may be communicatively coupled with the interface block **220-b** via one or more of a bus **301**, a bus **302**, a bus **303**, and a bus **304**, each of which may be examples of one or more signal paths of a bus **221** and a bus **246**, as well as a bus **255**, where applicable.

[0060] The interface block **245-b** includes a control interface **310** (e.g., a command interface), which may be configured to communicate signaling with the interface block **220-b**. For example, the control interface **310** may include circuitry (e.g., a receiver, one or more latches) configured to receive control signaling (e.g., modulated control signaling, access command signaling, configuration signaling, address signaling, such as row address signaling or column address signaling) via the bus **301-a**. The control interface **310** also may include circuitry configured to receive clock signaling (e.g., clock signaling associated with the control interface **310**, clock signaling having one or more phases, such as true and complement phases, *dk_t/c* signaling from the interface block **220-b**) via the bus **302-a**, which the control interface **310** may use for receiving the control signaling of the bus **301-a** (e.g., for triggering the one or more latches). The control interface **310** may transmit (e.g., forward) the control signaling the clock signaling (e.g., for timing of other operations of the interface block **245-b**) to an interface controller **320**.

[0061] The interface block **245-b** also includes two data interfaces **330** (e.g., data interfaces **330-a-1** and **330-a-2**), which also may be configured to communicate signaling with the interface block **220-b**. Each data interface **330** may include corresponding buses and circuitry, the operation of which may be associated with (e.g., controlled by, coordinated with, operated based on) control signaling via the control interface **310**. Although the example of interface block **245-b** includes two such data interfaces **330** associated with the control interface **310** (e.g., in a “channel pair” arrangement), the described techniques for an interface block **245** may include any quantity of one or more data interfaces **330**, and associated buses and circuitry, for a given control interface **310** of the interface block **245**. Each data interface **330** may be associated with respective data path circuitry, which may include respective first-in-first-out (FIFO) and serialization/deserialization (SERDES) circuitry (e.g., FIFO/SERDES **340**), respective write/sense circuitry **350**, respective synchronization and sequencing circuitry (e.g., sync/seq logic **360**), and respective timing circuitry **370**, along with interconnecting signal paths (e.g., one or more buses). However, in some other examples, data path circuitry may be arranged in a different manner, or may include different circuitry components, which may include circuitry that is dedicated to respective data paths, or shared among data paths, or various combinations thereof. Each data interface **330** also may be associated with a respective set of one or more memory arrays **250**. In some examples, each memory array **250** may be understood to include respective addressing circuitry such as bank logic or decoders (e.g., a row decoder, a column decoder), among other array circuitry. However, in some other examples, at least a portion of such circuitry may be included in an interface block **245**.

[0062] Each data interface **330** may include circuitry (e.g., one or more latches, one or more drivers) configured to communicate (e.g., receive, transmit) data signaling (e.g., modulated data signaling, DQ signaling) via a respective bus **303**. Each data interface **330** also may include circuitry to communicate clock signaling via a respective bus **304**, which may support clock signal reception by the data interface **330** (e.g., first clock signaling associated with the data interface **330**, clock signaling having one or more phases, such as true and complement phases, DQS_t/c signaling from the interface block **220-b**, clock signaling associated with data reception or write operations), or clock signal transmission by the data interface **330** (e.g., second clock signaling associated with the data interface **330**, RDQS_t/c signaling to the interface block **220-b**, clock signaling associated with data transmission or read operations), or both. Each data interface **330** may transmit clock signaling (e.g., received clock signaling, DQS_t/c signaling) to sync/seq logic **360** via a respective bus (e.g., for timing of other operations of the interface block **245-b**).

[0063] The interface controller **320** may support various control or configuration functionality of the interface block **245-b** for accessing or otherwise managing operations of the coupled memory arrays **250**. For example, the interface controller **320** may support access command coordination or configuration, latency or timing compensation, access command buffering (e.g., in accordance with a FIFO or other organizational scheme), mode registers or logic for configuration settings, or test functionality, among other functions or combinations thereof. For each data path of the interface block **245** (e.g., associated with a respective data interface **330**), the interface controller **320** may be configured to transmit signaling to the respective memory arrays **250** via a bus **321** (e.g., address signaling, such as a row address or row activation signaling). For each data path of the interface block **245**, the interface controller **320** may communicate signaling (e.g., timing signaling, which may be based on clock signaling received from the control interface **310**, configuration signaling) with respective timing circuitries **370** and sync/seq logic **360** via respective buses.

[0064] For each data path, the respective timing circuitry **370** may support timing of various operations (e.g., activations, coupling operations, signal latching, signal driving) relative to timing signaling received from the interface controller **320**. For example, timing circuitry **370** may include a timing chain (e.g., a global column timing chain) configured to generate one or more clock signals or other initiation signals for controlling operations of the respective data path, and such signaling may include transitions (e.g., rising edge transitions, falling edge transitions, on/off transitions) that are offset from, at a different rate than, or otherwise different from transitions of signaling from the interface controller **320** to support a given operation or combination of operations. For example, timing circuitry **370** may be configured to transmit signaling (e.g., column selection signaling, column address signaling) to the respective memory arrays **250**, to transmit signaling to the respective write/sense circuitry **350** (e.g., latch or driver timing signaling), and to transmit signaling to the respective sync/seq logic (e.g., timing signaling).

[0065] For each data path, the respective FIFO/SERDES **340** may be configured to convert between data signaling of a first bus width (e.g., a relatively wide bus width, a data read/write (DRW) bus, a bus for communications with write/sense circuitry **350** having a relatively larger quantity of signal paths) and a second bus width (e.g., a relatively narrow bus width, a bus for communications with a data interface **330** having a relatively smaller quantity of signal paths). In some examples, such a conversion may be accompanied by changing a rate of signaling between signaling from the data interface **330** and the write/sense circuitry **350** (e.g., to maintain a given throughput). In various examples, the FIFO/SERDES **340** may receive data signaling from the data interface **330** and transmit data signaling to the write/sense circuitry **350** (e.g., to support a write operation), or may receive data signaling from the sense circuitry **350** and transmit data signaling to the data interface **330** (e.g., to support a read operation). In some examples (e.g., to support a read operation), the FIFO/SERDES **340** may be configured to transmit clock signaling (e.g., RDQS_t/c signaling) to the data interface **330**, which may be forwarded to the interface block **220-b**.

[0066] The timing or other synchronization of operations performed by the FIFO/SERDES **340**

may be supported by one or more clock signals, among other signaling, received from the respective sync/seq logic **360**. For example, the sync/seq logic **360** may generate or otherwise coordinate clock signaling to support the different rates of signaling of different buses (e.g., based on received clock signaling). Additionally, or alternatively, the FIFO/SERDES **340** may operate in a direction (e.g., for data transmission to a data interface **330**, for data reception from a data interface **330**) or other mode based on configuration signaling received from the sync/seq logic **360**.

[0067] For each data path, the respective write/sense circuitry **350** may be configured to support the accessing (e.g., data signaling, write signaling, read signaling) of the respective set of one or more memory arrays **250**. For example, the write/sense circuitry **350** may be coupled with the memory arrays **250** via a bus (e.g., a global input/output (GIO) bus), which may include respective signal paths associated with each memory array **250**, or may include signal paths that are shared for all of the memory arrays **250** of the set, in which case the memory array circuitry may include multiplexing circuitry operable to couple the bus with a selected one of the memory arrays **250**. In some examples, a bus between the write/sense circuitry and the set of one or more memory arrays **250** may include a same quantity of signal paths as a bus between the write/sense circuitry **350** and the FIFO/SERDES **340** (e.g., for signaling GIO[287:0]) or a same quantity of signal paths as a quantity of columns in each memory array **250**. In some other examples, the memory arrays **250** may include a quantity of columns that is an integer multiple of the quantity of signal paths of the bus, in which case the memory array circuitry (e.g., each memory array **250**) may include decoding circuitry operable to couple a subset of columns of memory cells, or associated circuitry, with the bus.

[0068] To support write operations, the write/sense circuitry **350** may be configured to drive signaling that is operable to write one or more logic states to memory cells of the memory arrays **250** (e.g., based on received data, based on received timing signaling, based on data signaling received via a bus **303** and on control signaling received via a bus **301-a**). In some examples, such signaling may be transmitted to supporting circuitry of or otherwise associated with the memory arrays **250** (e.g., as an output of signals corresponding to logic states to be written), such as sense amplifier circuitry, voltage sources, current sources, or other driver circuitry operable to apply a bias across a storage element of the memory cells (e.g., across a capacitor, across a ferroelectric capacitor), or apply a charge, a current, or other signaling to a storage element of the memory cells (e.g., to apply a current to a chalcogenide or other configurable memory material, to apply a charge to a gate of a NAND memory cell), among other examples.

[0069] To support read operations, the write/sense circuitry **350** may be configured to receive signaling that the write/sense circuitry **350** may further amplify for communication through the interface block **245-b**. For example, the write/sense circuitry **350** may be configured to receive signaling corresponding to logic states read from the memory arrays **250**, but at a relatively low driver strength (e.g., relatively ‘analog’ signaling, which may be associated with a relatively low drive strength of sense amplifiers of the memory arrays **250**). The write/sense circuitry **350** may thus include further sense amplification (e.g., a data sense amplifier (DSA) between signal paths between the write/sense circuitry and the set of one or more memory arrays and respective signal paths between the write/sense circuitry and the FIFO/SERDES), which each may have a relatively high drive strength (e.g., for driving relatively ‘digital’ signaling).

[0070] The features of the interface architecture **300** may be duplicated in various quantities and arrangements to support a semiconductor system having multiple dies, such as various examples of a system **200**. In an example implementation, each die **240** may be configured with 64 instances of the interface block **245-b**, which may support a data signaling width of 9,216 signal paths for each die **240** (e.g., where each bus **303** of a channel pair is associated with 72 signal paths). For a system **200** having a stack of eight dies **240** coupled with a die **205**, the die **205** may thus be configured with 512 instances of the interface block **220-b**, thereby supporting an overall data signaling width

of 73,738 signal paths for the system **200**. However, in other implementations, dies **205** and dies **240** may be configured with different quantities of interface blocks **220** and **245**, respectively, and a system **200** may be configured with different quantities of dies **240** per die **205**.

[0071] In some examples, each memory array **250** may be organized with rows of memory cells, each row associated with an address of the memory array **250**. Each memory array **250** may be associated with (e.g., coupled with, include) a set counters **380** (e.g., located in a die **240**). A set of counters **380** may track access operations associated with the memory array **250** and may include a respective counter **380** for each row of the memory array **250**. For example, each counter **380** may track a respective quantity of access operations on (e.g., activations of) a respective row of the memory array **250**. In some examples, the interface controller **320** may operate (e.g., read, increment, write, reset) the counters **380** via the bus **321**. Additionally, or alternatively, the interface controller **320** may operate the counters **380** via a dedicated bus **322** (e.g., a dedicated GIO bus, dedicated access lines). By tracking quantities of access operations on the memory arrays **250**, the counters **380** may be used by the interface controller **320** to detect row hammer attacks on the memory arrays **250**. For example, the interface controller **320** may compare a value of a counter **380** to one or more threshold values and determine, based on the comparison, that a row associated with the counter **380** is under row hammer attack based on the value satisfying at least one of the one or more threshold values.

[0072] In some examples, the interface block **220-b** and the interface block **245-b** may exchange signaling (e.g., via one or more signal paths of the bus **301**, via one or more alert pins of the bus **301**) to perform row hammer mitigation operations. For example, the interface block **245-b** (e.g., the interface controller **320**) may detect a row hammer attack associated with a memory array **250** (e.g., on a row of the memory array **250**) and may transmit alert signaling to the interface block **220-b**. The interface block **220** may evaluate the received alert signaling and may issue one or more refresh commands (e.g., via the bus **301**) to the interface block **245-b** in response to the alert signaling. A refresh command may indicate for the interface block **245-b** (e.g., the interface controller **320**) to refresh one or more rows (e.g., victim rows) of the memory array **250** that are neighboring to a row associated with the alert signaling (e.g., an aggressor row) based on a value included in the alert signaling. By exchanging signaling associated with row hammer mitigation between multiple semiconductor dies (e.g., a die **205** and one or more dies **240**) in accordance with one or more of the described techniques, a system may support row hammer mitigation within a 3D stacked memory system and may be configured with more robust row hammer mitigation procedures, increased reliability, among other advantages, compared with other techniques for row hammer mitigation.

[0073] FIG. 4 shows an example of a block diagram of a system **400** that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein. The system **400** illustrates an example of an interface block **245-c** (e.g., of a die **240**) coupled with an interface block **220-c** (e.g., of a die **205**). The interface block **245-c** may be communicatively coupled with the interface block **220-c**. The interface block **245-c** may be coupled with one or more memory arrays **250**, including a memory array **250-c**. The one or more memory arrays **250** may each include multiple rows **405** (e.g., rows **405-a-1** through **405-a-7**), and each row **405** may include a set of memory cells. Each row **405** of the one or more memory arrays **250** may be associated with a respective counter **380-b** (e.g., counters **380-b-1** through a counter **380-b-7**, corresponding to rows **405-a-1** through **405-a-7**). The interface block **245-c** and the interface block **220-c** may communicate signaling (e.g., access signaling **410**, alert signaling **415**, refresh signaling **420**, or other signaling, such as via a bus **301**) to support row hammer mitigation procedures as described herein to increase system security and reliability, for example, by protecting data stored at the memory array **250-c** from undesired or malicious data modification.

[0074] In some cases, the system **400** may be subject to row hammer attacks, where a large quantity of access commands (e.g., via an interface block **220-c**, within a relatively small amount

of time) are issued to a row **405** of a memory array **250**, which may be referred to as an aggressor row **405**. Due to the successive access commands, electrical charge from the aggressor row **405** may leak to or from one or more memory cells of other rows **405** nearby the aggressor row **405** (e.g., neighboring rows **405** not associated with an address in the access command), which may be referred to as victim rows **405**. An electrical charge leakage or other associated disturbance may affect the state (e.g., the electrical charge) of the memory cells in the victim rows, which may lead to modification of data stored in the memory cells of the victim rows. Thus, the system **400** may perform row hammer mitigations procedures to reduce (e.g., avoid) such adverse effects, which may include refreshing the state (e.g., logic state, electrical state) of the memory cells of the victim rows (e.g., to restore their correct state).

[0075] According to techniques described herein, an interface block **245-c** and an interface block **220-c** may communicate signaling (e.g., one or more signals) to perform one or more mitigation procedures, for example, to support row hammer mitigation in systems where memory access circuitry is divided among multiple semiconductor dies (e.g., 3D stacked memory systems). For example, the interface block **220-c** may transmit access signaling **410** (e.g., an activate (ACT) command, an access command, one or more signals, an access signal) that indicates to the interface block **245-c** to activate a row **405-a** of the memory array **250-c** (e.g., of a die **240**, as part of an access operation on the row **405-a**). In some examples, the access signaling **410** may indicate parameters (e.g., a pseudo-channel (PC), a bank address, a row address) associated with the row **405-a** to be activated. For example, a bus **221** via which the interface block **220-c** and the interface block **245-c** communicate may include multiple PCs, where different PCs may be associated with common command signal paths and respective data signal paths. For instance, a first PC and a second PC of the bus **221** may share the same command signal paths (e.g., a bus **301**, a bus **302**) but may include separate data signal paths (e.g., buses **303**, buses **304**). To indicate (e.g., identify) the row **405-a** for activation, the parameters of the access signaling **410** may indicate the PC via which the row **405-a** is accessed, the bank address of the bank that includes the row **405-a**, and the row address of the row **405-a** within the bank.

[0076] In accordance with the access signaling **410**, the interface block **245-c** may activate the row **405-a** of the memory array **250-c**, such as part of or independent of an access operation on the row **405-a**. Each counter **380-b** may be used (e.g., maintained, incremented) to track (e.g., count) a respective quantity of activations of (e.g., a respective quantity of access operations on) a corresponding row **405-a**. For example, the counters **380-b** may be implemented as per-row counters to count respective quantities of activations of each row **405-a**. For example, the counter **380-b-1** may be used to track a quantity of activations of the row **405-a-1**, the counter **380-b-2** may be used to track a quantity of activations of the row **405-a-2**, and so on. Accordingly, based on accessing the row **405-a**, the interface block **245-c** may read a value of the counter **380-b** used to track the quantity of activations of the row **405-a** and may increment the value. The interface block **245-c** may compare the value of the counter **380-b** to one or more threshold values and may generate alert signaling **415** (e.g., row hammer alert signaling, one or more signals, an alert signal) based on the comparison. For example, based on the comparison, the interface block **245-c** may determine whether the value of the counter **380-b** satisfies one of the one or more threshold values. In some examples, the interface block **245-c** may write the incremented value back to the counter **380-b**. In some other examples, if the value of the counter satisfies one of the one or more threshold values, the interface block **245-c** may reset at least a portion of the counter **380-b**. In some cases, the interface block **245-c** may detect an error associated with the value of the counter **380-b** based on reading the value of the counter. In some such examples, the interface block **245-c** may generate the alert signaling **415** based on detecting the error and may reset the counter **380-b**.

[0077] In some cases, the interface block **245-c** may implement one or more procedures associated with the counter **380-b** (e.g., reading the counter **380-b**, incrementing the counter **380-b**, transmitting the alert signaling **415**, writing the counter **380-b**, resetting one or more portions of the

counter **380-b**) concurrently with one or more access operations associated with processing (e.g., servicing) the access signaling **410** request (e.g., performing a read operation or a write operation on the row **405-a**). For example, the interface block **245-c** may perform one or more access operations on the row **405-a** concurrent with performing one or more operations to track a respective quantity of activations of (e.g., access operations on) the row **405-a**.

[0078] To perform an access operation on the row **405-a**, the interface block **245-c** may issue signaling (e.g., to write/sense circuitry **350-a**), such as row activation signaling, column activation signaling, or a combination thereof. In some cases, a duration between successively signaled row activations by the interface block **245-c** may be based on the internal operations of the interface block **245-c** associated with the counter **380-b** (e.g., per-row internal operations). For example, the operations of reading a value of a counter **380-b**, incrementing the value of the counter **380-b**, and writing the incremented value to the counter **380-b** may cause an increase in the duration (e.g., by an additional 8 nanoseconds) between successively issued row activations. Thus, in some examples, to accommodate performing the internal operations associated with the counter **380-b**, the interface block **245-c** may delay issuing subsequent row activation signaling at least until the internal operations (e.g., writing the incremented value to the counter **380-b**) are complete.

[0079] In some examples, the counters **380-b** may be multi-bit (e.g., 14 bit) counters, and different subsets of bits of the counters **380-b** may be used to determine whether a value of a counter **380-b** satisfies one or more threshold values or to identify an error associated with the counter **380-b**. For example, each counter **380-b** may include multiple portions **425** (e.g., a portion **425-a**, a portion **425-b**, a portion **425-c**) that correspond to respective subsets of one or more bits of the counter **380-b**. The interface block **245-c** may use the portions **425** to determine whether a value of a counter **380-b** satisfies the one or more threshold values or to identify an error associated with the counter **380-b**. For example, a counter **380-b** may include a portion **425-a** (e.g., a row hammer 1 (RH1) counter) to track a quantity of activations of (e.g., access operations on) a corresponding row **405-a**, which may indicate whether the value of the counter **380-b** satisfies a first threshold value. If the value of the counter **380-b** satisfies the first threshold, the interface block **245-c** may reset the portion **425-a**.

[0080] The counter **380-b** may also include a portion **425-b** (e.g., a row hammer 2 (RH2) counter) that may track a quantity of occurrences that the counter **380-b** (e.g., the portion **425-a**) satisfies the first threshold value. For example, the interface block **245-c** may increment the portion **425-b** based on the value of the counter **380-b** satisfying the first threshold value, such as incrementing the portion **425-b** each time the portion **425-a** satisfies the first threshold value (e.g., each time the portion **425-a** is reset). The portion **425-b** may indicate whether the value of the counter **380-b** satisfies a second threshold value. If the counter **380-b** satisfies the second threshold value, the interface block **245-c** may reset the portion **425-b** (e.g., and the portion **425-a**). The counter **380-b** may also include a portion **425-c** (e.g., one or more parity bits, a cyclic redundancy check (CRC) portion, error correction code (ECC) portion) that the interface block **245-c** may use to identify an error associated with the counter **380-b**. In some examples, if the portion **425-c** indicates a counter error, the interface block **245-c** may reset both the portions **425-a** and the portion **425-b**. Reading the value of the counter **380-b** may include reading the portions **425-a**, **425-b**, and **425-c**. The interface block **245-c** may compare the portions **425-a** and **425-b** to the first and second threshold value, respectively, and use the portion **425-c** to determine whether there is an error associated with the counter **380-b**.

[0081] The interface block **245-c** may generate the alert signaling **415** according to various alert types based on comparing a value of the counter **380-b** to the one or more threshold values or identifying an error with the counter **380-b**. A first alert type (e.g., RH1 alert, RHALERT1) may be associated with the value of the counter **380-b** (e.g., in the portion **425-a**) satisfying the first threshold value. A second alert type (e.g., RH2 alert, RHALERT2) may be associated with the value of the counter **380-b** (e.g., in the portion **425-b**) satisfying the second threshold value. In

some examples, the second threshold value may be greater than the first threshold value (e.g., may be a multiple of the first threshold value), for example, based on the RH2 counter being incremented in response to the first threshold value being satisfied. A third alert type (e.g., a counter error alert, RHALERTERR) may be associated with the interface block **245-c** identifying an error (e.g., a permanent error, a transient error) with the counter **380-b** (e.g., indicated by the portion **425-c**). A fourth alert type may be associated with the value of the counter **380-b** failing to satisfy the one or more threshold values (e.g., the first threshold value and the second threshold value) and that no error is identified for the counter **380-b**. The interface block **245-c** may transmit different alert values (e.g., via alert pins, such as of a bus **301**) via the alert signaling **415** according to the different alert types as described herein. In some examples, if the value of the counter **380-b** fails to satisfy the one or more thresholds, the interface block **245-c** may refrain from generating alert signaling **415** according to the fourth alert type (e.g., no alert). For example, the fourth alert type may correspond to no alert being sent.

[0082] In some examples, the interface block **245-c** and the interface block **220-c** may support the implementation of other alert types in addition to the four alert types described (e.g., RH1 alert, RH2 alert, a counter error alert, a fourth alert). For example, one or more additional alert types (e.g., a row hammer 3 (RH3) alert, a row hammer 4 (RH4) alert, and so on) may be associated with respective values of the counter satisfying one or more additional respective threshold values (e.g., a third threshold value, a fourth threshold value, and so on). In some examples, the counter **380-b** may include one or more additional portions **425** to track respective quantities of row activations, respective quantities of occurrences that a value of the counter satisfies one or more threshold values, or both. For instance, an additional portion **425** may track a quantity of occurrences that the counter **380-b** (e.g., the portion **425-b**) satisfies the second threshold value.

[0083] The interface block **220-c** may receive the alert signaling **415** and may evaluate the alert signaling **415**. For example, the alert signaling **415** may include different values for different alert types (e.g., RH1ALERT, RH2ALERT, RHALERTERR), and the interface block **220-c** may generate and transmit refresh signaling **420** (e.g., for one or more refresh operations) to the interface block **245-c** based on the alert type. For instance, if the alert signaling **415** indicates a two-bit value for an alert, a '00' value may correspond to (e.g., indicate) the fourth alert type (e.g., no alert, continue operation), a '01' value may correspond to the first alert type, a '10' may correspond to the second alert type, and a '11' value may correspond to the third alert type (e.g., an error), although other quantities of bits and other combinations of bit values to indicate the alert types may be implemented.

[0084] The interface block **220-c** may determine which row **405-a** is associated with the alert signaling **415** (e.g., an aggressor row) based on a duration (e.g., a quantity of clock cycles) between transmitting the access signaling **410** and receiving the alert signaling **415** (e.g., the timing for the alert signaling **415** may be deterministic). For example, a row hammer alert may be asserted (e.g., the alert signaling **415** may be transmitted to the interface block **220-c**) in accordance with a deterministic duration (e.g., quantity of clock cycles, such as 13 command clock cycles) after the access signaling **410** (e.g., an activate command) is transmitted to the interface block **245-c**. Accordingly, the interface block **220-c** may determine the row **405-a** for which the alert signaling **415** is indicating an alert based on having issued the access signaling **410** for the row **405-a** (e.g., a quantity of clock cycles prior to receiving the alert signaling **415**).

[0085] The refresh signaling **420** may include one or more refresh commands (e.g., a target auto refresh (TAREF) command) for one or more rows **405-a** based on the alert type. Each refresh command may indicate one or more parameters (e.g., PC, bank address, victim row address) associated with the one or more rows **405-a** to be refreshed. In some examples, if the alert type is a first alert type (e.g., RH1ALERT), the refresh signaling **420** may include multiple refresh commands (e.g., at least two refresh commands) to refresh multiple rows **405-a** that are near (e.g., directly adjacent to, neighboring) the row **405-a** (e.g., the aggressor row) associated with the alert

signaling 415 (e.g., the row 405-a that is under row hammer attack). For example, if the alert signaling 415 indicates the first alert type associated with row 405-a-4, the interface block 220-c may issue respective refresh commands for row 405-a-3 and row 405-a-5 that are directly adjacent to the row 405-a-4. In some examples, a single refresh command may indicate multiple rows 405 to be refreshed, and the interface block 220-c may issue a single refresh command for the rows 405-a-3 and 405-a-5.

[0086] If the alert type indicates a second alert type (e.g., RH2ALERT) or a third alert type (e.g., RHALERTERR), the refresh signaling 420 may include multiple sets of refresh commands (e.g., at least four respective refresh commands for four rows 405-a). For example, in response to the second alert type being associated with the row 405-a-4, the interface block 220-c may issue respective refresh commands for row 405-a-2, row 405-a-3, row 405-a-5, and row 405-a-6. In some examples, a single refresh command may indicate multiple rows 405 to be refreshed, and the interface block 220-c may issue one or more refresh commands to indicate a refresh of the rows 405-a-2, 405-a-3, 405-a-5, and 405-a-6. In some examples, the second alert type may cause additional rows 405-a to be refreshed relative to the first alert type due to the higher quantity of activations (e.g., of the row 405-a-4) associated with indicating the second alert type relative to the first alert type. For example, the higher quantity of activations may be associated with additional electrical charge leakage from an aggressor row 405-a, which may modify data in additional rows 405-a, for example, located further away from the aggressor row 405-a than adjacent victim rows 405-a associated with the first alert type. For example, the second alert type may indicate that rows 405-a that are not directly adjacent to the aggressor row 405-a may be affected by a row hammer attack on the aggressor row 405-a. As such, the rows 405-a that are not directly adjacent to an aggressor row 405-a may be indicated by the alert signaling 415 to be refreshed. In some examples, if the alert type indicates an additional alert type (e.g., an RH3 alert, an RH4 alert, and so on), the refresh signaling 420 may indicate refreshes for other rows 405-a in addition to the rows 405-a indicated for refresh in association with the second alert type (e.g., rows 405-a-1, 405-a-7, and so on), for example, due to an even higher quantity of activations of the aggressors row 405-a associated with the additional alert type.

[0087] In some examples, it may be unclear whether the first threshold value is satisfied, the second threshold value is satisfied, or neither the first nor the second threshold values are satisfied if the third alert type is indicated, for example, due to an error in reading the value of a counter 380-b. As such, the interface block 245-c may assume that the second threshold value is satisfied (e.g., as a conservative assumption) and issue refresh commands to refresh both the directly adjacent and non-directly adjacent rows 405-a, for example, to support robust row hammer mitigation in case of an error. If the alert type is a fourth alert type (e.g., indicating no alert and no counter error), the interface block 220-c may not generate the refresh signaling 420.

[0088] Supporting various alert types for row hammer mitigation operations as described herein may increase a robustness of row hammer mitigation techniques, increase system security and data protection against row hammer attacks, and increase a performance of row hammer mitigation operations. For example, supporting the second alert type and issuance of refresh commands for non-directly adjacent rows 405-a may protect against relatively longer and sustained row hammer attacks on an aggressor row 405-a that may affect the non-directly adjacent rows 405-a in addition to directly adjacent rows 405-a. Additionally, or alternatively, supporting the first alert type and issuance of refresh commands for directly adjacent rows 405-a may reduce a quantity of rows 405-a that are refreshed relative to the second alert type, which may reduce a latency or power consumption associated with row hammer mitigation. Further, supporting the third type of alert may provide protection against row hammer attacks in case of counter error.

[0089] The interface block 220-c may receive multiple alerts for multiple rows 405-a. In some examples, the multiple rows 405-a associated with the multiple alerts may have addresses that are nearby (e.g., adjacent) to each other. In such examples, the interface block 220-c may reduce a

quantity of refresh commands for the refresh signaling **420**. For example, the interface block **220-c** may receive a first alert having the first alert type for row **405-a-4** and a second alert having the first alert type for row **405-a-5**, which may result in refresh commands for row **405-a-3** and row **405-a-5** (associated with row **405-a-4**) and for row **405-a-4** and row **405-a-6** (associated with row **405-a-5**). However, the interface block **220-c** may exclude refresh commands for the row **405-a-4** and the row **405-a-5** from the refresh signaling **420** based on the row **405-a-4** being adjacent to the row **405-a-5**.

[0090] In some examples, the refresh signaling **420** may additionally, or alternatively, include a refresh command that is not targeted to a specific row **405-a** (e.g., an auto refresh (AREF) command), but may indicate the interface block **245-c** to refresh multiple rows **405-a** (e.g., of a bank). For example, the interface block **220-c** may issue such refresh commands periodically to maintain the state of multiple rows (e.g., as part of a system maintenance procedure). Such refresh commands may indicate one or more parameters (e.g., PC, bank address) for multiple rows **405-a**.

[0091] In some examples, the refresh signaling **420** may be based on whether the row **405-a** is associated with the alert signaling **415** is a spare row (e.g., a repaired row). For example, the access signaling **410** may indicate to access a row **405-a** that is a spare row (e.g., a redundant row, a replacement row), which may be located physically apart from other rows **405-a** of the memory array **250-c** (e.g., in a different memory array **250**, in a different portion of the memory array **250**), but which may be located logically adjacent to one or more of the other rows **405-a**.

[0092] In response to receiving the refresh signaling **420**, the interface block **245-c** may perform one or more refresh operations based on indications included in the refresh signaling **420**. In some examples, the interface block **245-c** may also increment respective counters **380-b** associated with rows **405-a** refreshed in accordance with the one or more refresh commands. For instance, if the refresh signaling **420** includes a targeted refresh command (e.g., TAREF command) for row **405-a-3**, the interface block **245-c** may also increment the associated counter **380-b-3**, as performing the refresh of the row **405-a-3** may include activating the row **405-a-3**. In some cases, if the refresh command is an auto refresh command (e.g., AREF command), the interface block **245-c** may reset the counters **380-b** (e.g., both RH1 counters and RH2 counters) corresponding to the rows **405-a** associated with the auto refresh command (e.g., and may not increment the counters **380-b**).

[0093] FIG. 5 shows an example of an architecture **500** that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein. The architecture **500** may illustrate a portion of a die **240**. For example, the architecture **500** illustrates an example of a control region **505** (e.g., of an interface block **245**) that includes control logic **510**. In some examples, the control logic **510** may include or be an example of a control interface **310**, an interface controller **320**, or a combination thereof. In some examples, the control region **505** may be a region of a die **240** (e.g., an interface block **245**) that includes bank logic. The control region **505** may be associated with one or more memory arrays **250-d** (e.g., according to a channel pair arrangement). For example, the control logic **510** may control accessing of various regions of a memory array **250-d**, such as one or more counter regions **515-a**, one or more redundant regions **520-a**, one or more ECC regions **525-a**, and one or more memory regions **540-a**, with each region being associated with respective access lines **530-a** (e.g., GIOs).

[0094] A counter region **515-a** may be a portion of a memory array **250-d** used to maintain counters **380**. For example, memory cells of the counter region **515-a** may be accessed to read and write values of counters **380** to support row hammer mitigation operations as described herein. A redundant region **520-a** may be a portion of a memory array **250-d** that includes redundant memory cells, such as spare rows. An ECC region **525-a** may be a portion of a memory array **250-d** in which information associated with ECC operations (e.g., parity bits) may be stored. A memory region **540-a** may be a portion of a memory array **250-d** used to store data to memory cells of the memory region **540-a**.

[0095] In some implementations, memory arrays **250-d** may include one or more counters **380**

(e.g., to support row hammer mitigations operations). In some cases, to access the one or more counters **380**, a device may use access lines **530-a** that are shared with data signaling associated with the memory array **250-d** (e.g., access lines **530-a-1**), or other access lines **530-a** associated with other regions. However, using shared access lines (e.g., access lines **530-a**) may increase latency and signaling overhead in a memory system.

[0096] According to techniques described herein, the control logic **510** may be operable to couple (e.g., directly couple) with counter regions **515-a** via conductive lines **535-a** coupled with dedicated access lines **530-a**. For example, a memory array **250-d** may include dedicated access lines **530-a** (e.g., dedicated GIO lines, dedicated column lines, dedicated buses) coupled with memory cells of a counter region **515-a**, which the control logic **510** may access via conductive lines **535-a**. For instance, the control logic **510** may use the conductive lines **535-a** and access lines **530-a** (e.g., access lines **530-a-4** coupled with a counter region **515-a-1**, access lines **530-a-5** coupled with a counter region **515-a-2**) to directly access the counters **380** (e.g., rather than accessing the counters **380** via access lines **530-a** of other regions).

[0097] In some examples, an interface block **245** may use the control logic **510** to read a counter **380** via the conductive lines **535-a** and access lines **530-a** based on receiving access signaling for a row of a memory array **250-d**. In some examples, a counter region **515-a** may include a column decoder (e.g., a dedicated column decoder) via which the control logic **510** may access a counter **380** of the counter region **515-a** using the dedicated access lines **530-a**. The control logic **510** may increment the value of the counter **380** based on the interface block **245** accessing a row of the memory array **250-d** associated with the counter **380** (e.g., using a word line that spans a memory region **540**, an ECC region **525**, a redundant region **520**, and a counter region **515**). The control logic **510** may compare a value of the counter **380** (e.g., after incrementing) to one or more threshold values (e.g., as described with reference to FIG. 4), and the interface block **245** may transmit alert signaling (e.g., to an interface block **220**) based on the comparing. The control logic **510** may write the incremented value back to the counter **380** via the conductive lines **535-a** and access lines **530-a**. Thus, the dedicated conductive lines **535-a** and access lines **530-a** may increase reliability and decrease latency associated with row hammer mitigation procedures.

[0098] FIG. 6 shows a block diagram **600** of a logic die **620** (e.g., a die **205**) that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein. The logic die **620** may be an example of aspects of a logic die as described with reference to FIGS. 1 through 5. The logic die **620**, or various components thereof (e.g., an interface block **220**), may be an example of means for performing various aspects of row hammer mitigation for stacked memory architectures as described herein. For example, the logic die **620** (e.g., an interface block **220**) may include an access signaling component **625**, an alert signaling component **630**, a refresh signaling component **635**, a command generation component **640**, a row determination component **645**, or any combination thereof. Each of these components, or components of subcomponents thereof (e.g., one or more processors, one or more memories), may communicate, directly or indirectly, with one another (e.g., via one or more buses).

[0099] The access signaling component **625** may be configured as or otherwise support a means for transmitting, from a first interface (e.g., an interface block **220**) of a first semiconductor die (e.g., the logic die **620**) to a second interface (e.g., an interface block **245**) of a second semiconductor die (e.g., an array die, a die **240**) coupled with the first semiconductor die, first signaling (e.g., one or more first signals, a first signal) including a first command to activate a row of a memory array of the second semiconductor die. The alert signaling component **630** may be configured as or otherwise support a means for receiving, at the first interface from the second interface based on transmitting the first signaling, second signaling (e.g., one or more second signals, a second signal) including an alert message associated with a row hammer mitigation operation associated with the row of the memory array. The refresh signaling component **635** may be configured as or otherwise support a means for transmitting, from the first interface to the second interface based on the alert

message, third signaling (e.g., one or more third signals, a third signal) including a second command to refresh one or more rows of the memory array adjacent to the row of the memory array.

[0100] In some examples, the command generation component **640** may be configured as or otherwise support a means for generating, by the first interface, the third signaling including the second command, the second command indicating to refresh a first row of the memory array and a second row of the memory array that are adjacent to the row based on the alert message indicating that a quantity of activations of the row satisfies a first threshold.

[0101] In some examples, the command generation component **640** may be configured as or otherwise support a means for generating, by the first interface, the third signaling including the second command, the second command indicating to refresh a first set of rows of the memory array and a second set of rows that are adjacent to the row based on the alert message indicating that a quantity of activations of the row satisfies a second threshold greater than a first threshold or indicating an error associated with a counter for counting activations of the row.

[0102] In some examples, the row determination component **645** may be configured as or otherwise support a means for determining, by the first interface, that the second signaling is associated with the row based on a duration between transmitting the first signaling and receiving the second signaling.

[0103] In some examples, the alert signaling component **630** may be configured as or otherwise support a means for receiving, at the first interface from the second interface, a second alert message associated with a second row hammer mitigation operation associated with a second row adjacent to the row. In some examples, the third signaling is transmitted based on receiving the alert message and the second alert message.

[0104] In some examples, the second command to refresh the one or more rows is based on whether the row is a spare row of the memory array.

[0105] In some examples, the described functionality of the logic die **620**, or various components thereof, may be supported by or may refer to at least a portion of at least one processor, where such at least one processor may include one or more processing elements (e.g., a controller, a microprocessor, a microcontroller, a digital signal processor, a state machine, discrete gate logic, discrete transistor logic, discrete hardware components, or any combination of one or more of such elements). In some examples, the described functionality of the logic die **620**, or various components thereof, may be implemented at least in part by instructions (e.g., stored in memory, non-transitory computer-readable medium) executable by such at least one processor.

[0106] FIG. 7 shows a block diagram **700** of an array die **720** (e.g., a die **240**) that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein. The array die **720** may be an example of aspects of an array die as described with reference to FIGS. 1 through 5. The array die **720**, or various components thereof (e.g., an interface block **245**), may be an example of means for performing various aspects of row hammer mitigation for stacked memory architectures as described herein. For example, the array die **720** (e.g., an interface block **245**) may include an access signaling component **725**, a counter operation component **730**, an alert signaling component **735**, a refresh component **740**, or any combination thereof. Each of these components, or components of subcomponents thereof (e.g., one or more processors, one or more memories), may communicate, directly or indirectly, with one another (e.g., via one or more buses).

[0107] The access signaling component **725** may be configured as or otherwise support a means for receiving, at a second interface (e.g., an interface block **245**) of a second semiconductor die (e.g., the array die **720**) from a first interface (e.g., an interface block **220**) of a first semiconductor die (e.g., a logic die, a die **205**) operable to couple with the second semiconductor die, first signaling (e.g., one or more first signals, a first signal) including a first command to activate a row of a memory array of the second semiconductor die. The counter operation component **730** may be

configured as or otherwise support a means for incrementing, by the second interface, a value of a counter associated with the row based on activating the row in accordance with the first signaling. In some examples, the counter operation component **730** may be configured as or otherwise support a means for reading, by the second interface, the value of the counter after incrementing the value of the counter. The alert signaling component **735** may be configured as or otherwise support a means for transmitting, from the second interface to the first interface based on reading the value of the counter, second signaling (e.g., one or more second signals, a second signal) including an alert message associated with a row hammer mitigation operation associated with the row.

[0108] In some examples, the refresh component **740** may be configured as or otherwise support a means for receiving, at the second interface from the first interface based on the alert message, third signaling (e.g., one or more third signals, a third signal) including a second command to refresh one or more rows of the memory array adjacent to the row of the memory array. In some examples, the refresh component **740** may be configured as or otherwise support a means for refreshing the one or more rows based on the second command.

[0109] In some examples, the alert message indicates that the value of the counter satisfies a first threshold value. In some examples, the counter operation component **730** may be configured as or otherwise support a means for resetting a first portion of the counter based on the value of the counter satisfying the first threshold value and incrementing a second portion of the counter based on resetting the first portion of the counter.

[0110] In some examples, the alert message indicates that the value of the counter satisfies a second threshold value greater than a first threshold value. In some examples, the counter operation component **730** may be configured as or otherwise support a means for resetting the counter based on the value of the counter satisfying the second threshold value.

[0111] In some examples, the alert message indicates an error associated with the counter. In some examples, the counter operation component **730** may be configured as or otherwise support a means for resetting the counter based on identifying the error.

[0112] In some examples, the described functionality of the array die **720**, or various components thereof, may be supported by or may refer to at least a portion of at least one processor, where such at least one processor may include one or more processing elements (e.g., a controller, a microprocessor, a microcontroller, a digital signal processor, a state machine, discrete gate logic, discrete transistor logic, discrete hardware components, or any combination of one or more of such elements). In some examples, the described functionality of the array die **720**, or various components thereof, may be implemented at least in part by instructions (e.g., stored in memory, non-transitory computer-readable medium) executable by such at least one processor.

[0113] FIG. **8** shows a flowchart illustrating a method **800** that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein. The operations of method **800** may be implemented by a logic die (e.g., a die **205**) or its components as described herein (e.g., an interface block **220**). For example, the operations of method **800** may be performed by a logic die as described with reference to FIGS. **1** through **6**. In some examples, a logic die may execute a set of instructions to control the functional elements of the device to perform the described functions. Additionally, or alternatively, the logic die may perform aspects of the described functions using special-purpose hardware.

[0114] At **805**, the method may include transmitting, from a first interface of a first semiconductor die (e.g., the logic die) to a second interface of a second semiconductor die coupled with the first semiconductor die, one or more first signals including a first command to activate a row of a memory array of the second semiconductor die. For example, a die **205** may include an interface block **220** that transmits access signaling **410** (e.g., via buses **221**, buses **301**) to an interface block **245** of a die **240** to activate a row **405** of a memory array **250**. In some examples, aspects of the operations of **805** may be performed by an access signaling component **625** as described with reference to FIG. **6**.

[0115] At **810**, the method may include receiving, at the first interface from the second interface based on transmitting the one or more first signals, one or more second signals including an alert message associated with a row hammer mitigation operation associated with the row of the memory array. For example, an interface block **220** of a die **205** may receive alert signaling **415** from an interface block **245** (e.g., via buses **221**, buses **301**) of a die **240** for a row hammer mitigation operation associated with a row **405** of a memory array **250**. In some examples, aspects of the operations of **810** may be performed by an alert signaling component **630** as described with reference to FIG. 6.

[0116] At **815**, the method may include transmitting, from the first interface to the second interface via based on the alert message, one or more third signals including a second command to refresh one or more rows of the memory array adjacent to the row of the memory array. For example, an interface block **220** of a die **205** may transmit refresh signaling **420** (e.g., via buses **221**, buses **301**) to an interface block **245** of a die **240** indicating a refresh operation for one or more rows **405** of a memory array **250**. In some examples, aspects of the operations of **815** may be performed by a refresh signaling component **635** as described with reference to FIG. 6.

[0117] In some examples, an apparatus as described herein may perform a method or methods, such as the method **800**. The apparatus may include features, circuitry, logic, means, or instructions (e.g., a non-transitory computer-readable medium storing instructions executable by a processor), or any combination thereof for performing the following aspects of the present disclosure:

[0118] Aspect 1: A method, apparatus, or non-transitory computer-readable medium including operations, features, circuitry, logic, means, or instructions, or any combination thereof for transmitting, from a first interface of a first semiconductor die to a second interface of a second semiconductor die coupled with the first semiconductor die, one or more first signals including a first command to activate a row of a memory array of the second semiconductor die; receiving, at the first interface from the second interface based on transmitting the one or more first signals, one or more second signals including an alert message associated with a row hammer mitigation operation associated with the row of the memory array; and transmitting, from the first interface to the second interface based on the alert message, one or more third signals including a second command to refresh one or more rows of the memory array adjacent to the row of the memory array.

[0119] Aspect 2: The method, apparatus, or non-transitory computer-readable medium of aspect 1, further including operations, features, circuitry, logic, means, or instructions, or any combination thereof for generating, by the first interface, the one or more third signals including the second command, the second command indicating to refresh a first row of the memory array and a second row of the memory array that are adjacent to the row based on the alert message indicating that a quantity of activations of the row satisfies a first threshold.

[0120] Aspect 3: The method, apparatus, or non-transitory computer-readable medium of any of aspects 1 through 2, further including operations, features, circuitry, logic, means, or instructions, or any combination thereof for generating, by the first interface, the one or more third signals including the second command, the second command indicating to refresh a first set of rows of the memory array and a second set of rows that are adjacent to the row based on the alert message indicating that a quantity of activations of the row satisfies a second threshold greater than a first threshold or indicating an error associated with a counter for counting activations of the row.

[0121] Aspect 4: The method, apparatus, or non-transitory computer-readable medium of any of aspects 1 through 3, further including operations, features, circuitry, logic, means, or instructions, or any combination thereof for determining, by the first interface, that the one or more second signals are associated with the row based on a duration between transmitting the one or more first signals and receiving the one or more second signals.

[0122] Aspect 5: The method, apparatus, or non-transitory computer-readable medium of any of aspects 1 through 4, further including operations, features, circuitry, logic, means, or instructions,

or any combination thereof for receiving, at the first interface from the second interface, a second alert message associated with a second row hammer mitigation operation associated with a second row adjacent to the row and where the one or more third signals are transmitted based on receiving the alert message and the second alert message.

[0123] FIG. 9 shows a flowchart illustrating a method **900** that supports row hammer mitigation for stacked memory architectures in accordance with examples as disclosed herein. The operations of method **900** may be implemented by an array die (e.g., a die **240**) or its components (e.g., an interface block **245**) as described herein. For example, the operations of method **900** may be performed by an array die as described with reference to FIGS. 1 through 5 and 7. In some examples, an array die may execute a set of instructions to control the functional elements of the device to perform the described functions. Additionally, or alternatively, the array die may perform aspects of the described functions using special-purpose hardware.

[0124] At **905**, the method may include receiving, at a second interface of a second semiconductor die (e.g., the array die) from a first interface of a first semiconductor die operable to couple with the second semiconductor die, one or more first signals including a first command to activate a row of a memory array of the second semiconductor die. For example, an interface block **245** of a die **240** may receive (e.g., via buses **246**, buses **301**) access signaling **410** from an interface block **220** of a die **205** to activate a row **405** of a memory array **250**. In some examples, aspects of the operations of **905** may be performed by an access signaling component **725** as described with reference to FIG. 7.

[0125] At **910**, the method may include incrementing, by the second interface, a value of a counter associated with the row based on activating the row in accordance with the one or more first signals. For example, an interface block **245** of a die **240** may increment a value of a counter **380** based on activating a row **405** in accordance with access signaling **410**. In some examples, aspects of the operations of **910** may be performed by a counter operation component **730** as described with reference to FIG. 7.

[0126] At **915**, the method may include reading, by the second interface, the value of the counter after incrementing the value of the counter. For example, an interface block **245** of a die **240** may read the value of a counter **380** after incrementing the counter **380**. In some examples, aspects of the operations of **915** may be performed by a counter operation component **730** as described with reference to FIG. 7.

[0127] At **920**, the method may include transmitting, from the second interface to the first interface based on reading the value of the counter, one or more second signals including an alert message associated with a row hammer mitigation operation associated with the row. For example, an interface block **245** of a die **240** may transmit (e.g., via buses **246**, buses **301**) alert signaling **415** indicating an alert message associated with a row hammer mitigation operation to an interface block **220** of a die **205** based on reading a value of a counter **380**. In some examples, aspects of the operations of **920** may be performed by an alert signaling component **735** as described with reference to FIG. 7.

[0128] In some examples, an apparatus as described herein may perform a method or methods, such as the method **900**. The apparatus may include features, circuitry, logic, means, or instructions (e.g., a non-transitory computer-readable medium storing instructions executable by a processor), or any combination thereof for performing the following aspects of the present disclosure:

[0129] Aspect 6: A method, apparatus, or non-transitory computer-readable medium including operations, features, circuitry, logic, means, or instructions, or any combination thereof for receiving, at a second interface of a second semiconductor die from a first interface of a first semiconductor die operable to couple with the second semiconductor die, one or more first signals including a first command to activate a row of a memory array of the second semiconductor die; incrementing, by the second interface, a value of a counter associated with the row based on activating the row in accordance with the one or more first signals; reading, by the second

interface, the value of the counter after incrementing the value of the counter; and transmitting, from the second interface to the first interface based on reading the value of the counter, one or more second signals including an alert message associated with a row hammer mitigation operation associated with the row.

[0130] It should be noted that the methods described herein describe possible implementations, and that the operations and the steps may be rearranged or otherwise modified and that other implementations are possible. Further, portions from two or more of the methods may be combined.

[0131] An apparatus is described. The following provides an overview of aspects of the apparatus as described herein:

[0132] Aspect 7: An apparatus, including: a first semiconductor die including: a first interface, the first interface including first circuitry operable to transmit one or more access signals; and a second semiconductor die coupled with the first semiconductor die, the second semiconductor die including: one or more memory arrays; and a second interface coupled with the first interface and the one or more memory arrays, the second interface including second circuitry operable to access the one or more memory arrays based on receiving the one or more access signals, where the apparatus is operable to: transmit, from the second interface to the first interface, one or more first signals based on a value of a counter associated with a quantity of access operations on the one or more memory arrays; transmit, from the first interface to the second interface based on the first interface receiving the one or more first signals, one or more second signals indicating a refresh operation associated with one or more addresses of the one or more memory arrays; and perform, by the second interface, the refresh operation based on the second interface receiving the one or more second signals.

[0133] Aspect 8: The apparatus of aspect 7, where the second circuitry of the second interface is further operable to: compare the value of the counter to one or more threshold values; and transmit the one or more first signals to the first interface based on the comparing.

[0134] Aspect 9: The apparatus of aspect 8, where the second circuitry of the second interface is further operable to: read the value of the counter based on receiving the one or more access signals from the first interface; increment the value of the counter based on accessing the one or more memory arrays, where the value of the counter is compared to the one or more threshold values after the incrementing; and write the incremented value to the counter.

[0135] Aspect 10: The apparatus of any of aspects 7 through 9, where the second circuitry of the second interface is further operable to: perform one or more access operations on an address of the one or more memory arrays; and perform, concurrently with performing the one or more access operations, one or more operations to track, using the counter, a quantity of access operations on the address.

[0136] Aspect 11: The apparatus of any of aspects 7 through 10, where the one or more first signals are transmitted based on the value of the counter indicating that a quantity of access operations on an address of the one or more memory arrays satisfies one or more threshold values.

[0137] Aspect 12: The apparatus of aspect 11, where the one or more first signals indicate that the value of the counter satisfies a first threshold value of the one or more threshold values, the apparatus further operable to: reset, by the second interface, a first portion of the counter based on the value of the counter satisfying the first threshold value; increment, by the second interface, a second portion of the counter based on the value of the counter satisfying the first threshold value; and generate, by the first interface, the one or more second signals indicating the refresh operation, where the refresh operation is for a second address different from the address and a third address different from the address based on the one or more first signals indicating that the value of the counter satisfies the first threshold value.

[0138] Aspect 13: The apparatus of aspect 11, where the one or more first signals indicate that the value of the counter satisfies a second threshold value of the one or more threshold values greater

than a first threshold value of the one or more threshold values, the apparatus further operable to: reset, by the second interface, the counter based on the value of the counter satisfying the second threshold value; and generate, by the first interface, the one or more second signals indicating the refresh operation for a first set of addresses that are different from the address and a second set of addresses that are different from the address based on the one or more first signals indicating that the value of the counter satisfies the second threshold value.

[0139] Aspect 14: The apparatus of aspect 11, where the one or more first signals indicate an error associated with the counter, the apparatus further operable to: reset, by the second interface, the counter based on the error; and generate, by the first interface, the one or more second signals indicating the refresh operation for a first set of addresses that are different from the address and a second set of addresses that are different from the address based on the one or more first signals indicating the error.

[0140] Aspect 15: The apparatus of any of aspects 7 through 14, where the first circuitry of the first interface is further operable to determine an address of the one or more memory arrays associated with the one or more first signals based on a duration between transmitting the one or more access signals from the first interface and receiving the one or more first signals from the second interface.

[0141] Aspect 16: The apparatus of any of aspects 7 through 15, where the one or more first signals are associated with a first address of the one or more memory arrays and a second address of the one or more memory arrays adjacent to the first address, and where the first circuitry of the first interface is operable to: determine the one or more addresses for the refresh operation to be adjacent to the first address or the second address and to exclude the first address and the second address based on the first address and the second address being adjacent.

[0142] Aspect 17: The apparatus of any of aspects 7 through 16, where the apparatus is further operable to: transmit, from the first interface to the second interface, one or more third signals indicating a second refresh operation associated with a set of addresses of the one or more memory arrays; and reset, by the second interface, respective counters associated with each address of the set of addresses based on the one or more third signals.

[0143] Aspect 18: The apparatus of any of aspects 7 through 17, where the second signaling indicating the refresh operation is based on the one or more addresses being associated with a spare row of the one or more memory arrays.

[0144] Aspect 19: The apparatus of any of aspects 7 through 18, where the second semiconductor die includes: the counter; and one or more dedicated access lines coupled with the second interface for accessing the counter.

[0145] An apparatus is described. The following provides an overview of aspects of the apparatus as described herein:

[0146] Aspect 20: An apparatus, including: a first semiconductor die including a first interface, the first interface including circuitry operable to: transmit, to a second interface of a second semiconductor die coupled with the first semiconductor die, one or more first signals including a first command to activate a row of a memory array of the second semiconductor die; receive, from the second interface based on transmitting the one or more first signals, one or more second signals including an alert message associated with a row hammer mitigation operation associated with the row of the memory array; and transmit, to the second interface based on the alert message, one or more third signals including a second command to refresh one or more rows of the memory array adjacent to the row of the memory array.

[0147] Aspect 21: The apparatus of aspect 20, where the circuitry of the first interface is operable to: generate the third signaling including the second command, the second command indicating to refresh a first row of the memory array and a second row of the memory array that are different from the row based on the alert message indicating that a quantity of activations of the row satisfies a first threshold.

[0148] Aspect 22: The apparatus of aspect 20, where circuitry of the first interface is operable to:

generate the third signaling including the second command, the second command indicating to refresh a first set of rows of the memory array and a second set of rows that are different from the row based on the alert message indicating that a quantity of activations of the row satisfies a second threshold greater than a first threshold or indicating an error associated with a counter for counting activations of the row.

[0149] Aspect 23: The apparatus of any of aspects 20 through 22, where the circuitry of the first interface is operable to: determine that the second signaling is associated with the row based on a duration between transmitting the first signaling and receiving the second signaling.

[0150] Aspect 24: The apparatus of any of aspects 20 through 23, where the circuitry operable to transmit the third signaling is further operable to: transmit the third signaling based on receiving the alert message and receiving a second alert message associated with a second row hammer mitigation operation associated with a second row adjacent to the row.

[0151] Aspect 25: The apparatus of any of aspects 20 through 24, where the second command to refresh the one or more rows is based on whether the row is a spare row of the memory array.

[0152] An apparatus is described. The following provides an overview of aspects of the apparatus as described herein:

[0153] Aspect 26: An apparatus, including: a second semiconductor die including a second interface, the second interface including circuitry operable to: receive, from a first interface of a first semiconductor die, first signaling including a command to activate a row of a memory array of the second semiconductor die; increment a value of a counter associated with the row based on activating the row in accordance with the first signaling; read the value of the counter after incrementing the value of the counter; and transmit, to the first interface based on reading the value of the counter, second signaling including an alert message associated with a row hammer mitigation operation associated with the row.

[0154] Aspect 27: The apparatus of aspect 26, where the circuitry of the second interface further operable to: receive, from the first interface based on the alert message, third signaling including a second command to refresh one or more rows of the memory array adjacent to the row of the memory array; and refresh the one or more rows based on the second command.

[0155] Aspect 28: The apparatus of any of aspects 26 through 27, where the alert message indicates that the value of the counter satisfies a first threshold value, the circuitry of the second interface further operable to: reset a first portion of the counter based on the value of the counter satisfying the first threshold value; and increment a second portion of the counter based on resetting the first portion of the counter.

[0156] Aspect 29: The apparatus of any of aspects 26 through 27, where the alert message indicates that the value of the counter satisfies a second threshold value greater than a first threshold value, the circuitry of the second interface further operable to: reset the counter based on the value of the counter satisfying the second threshold value.

[0157] Aspect 30: The apparatus of any of aspects 26 through 27, where the alert message indicates an error associated with the counter, the circuitry of the second interface further operable to: reset the counter based on identifying the error.

[0158] Information and signals described herein may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, or symbols of signaling that may be referenced throughout the above description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof. Some drawings may illustrate signals as a single signal; however, the signal may represent a bus of signals, where the bus may have a variety of bit widths.

[0159] The terms “electronic communication,” “conductive contact,” “connected,” and “coupled” may refer to a relationship between components that supports the flow of signals between the components. Components are considered in electronic communication with (e.g., in conductive

contact with, connected with, coupled with) one another if there is any electrical path (e.g., conductive path) between the components that can, at any time, support the flow of signals (e.g., charge, current, voltage) between the components. At any given time, a conductive path between components that are in electronic communication with each other (e.g., in conductive contact with, connected with, coupled with) may be an open circuit or a closed circuit based on the operation of the device that includes the connected components. A conductive path between connected components may be a direct conductive path between the components or the conductive path between connected components may be an indirect conductive path that may include intermediate components, such as switches, transistors, or other components. In some examples, the flow of signals between the connected components may be interrupted for a time, for example, using one or more intermediate components such as switches or transistors.

[0160] The term “coupling” (e.g., “electrically coupling”) may refer to condition of moving from an open-circuit relationship between components in which signals are not presently capable of being communicated between the components (e.g., over a conductive path) to a closed-circuit relationship between components in which signals are capable of being communicated between components (e.g., over the conductive path). When a component, such as a controller, couples other components together, the component initiates a change that allows signals to flow between the other components over a conductive path that previously did not permit signals to flow.

[0161] The term “isolated” refers to a relationship between components in which signals are not presently capable of flowing between the components. Components are isolated from each other if there is an open circuit between them. For example, two components separated by a switch that is positioned between the components are isolated from each other when the switch is open. When a controller isolates two components, the controller affects a change that prevents signals from flowing between the components using a conductive path that previously permitted signals to flow.

[0162] As used herein, including in the claims, the article “a” before a noun is open-ended and understood to refer to “at least one” of those nouns or “one or more” of those nouns. Thus, the terms “a,” “at least one,” “one or more,” and “at least one of one or more” may be interchangeable. For example, if a claim recites “a component” that performs one or more functions, each of the individual functions may be performed by a single component or by any combination of multiple components. Thus, “a component” having characteristics or performing functions may refer to “at least one of one or more components” having a particular characteristic or performing a particular function. Subsequent reference to a component introduced with the article “a” using the terms “the” or “said” may refer to any or all of the one or more components. For example, a component introduced with the article “a” may be understood to mean “one or more components,” and referring to “the component” subsequently in the claims may be understood to be equivalent to referring to “at least one of the one or more components.”

[0163] The description set forth herein, in connection with the appended drawings, describes example configurations and does not represent all the examples that may be implemented or that are within the scope of the claims. The term “exemplary” used herein means “serving as an example, instance, or illustration,” and not “preferred” or “advantageous over other examples.” The detailed description includes specific details to provide an understanding of the described techniques. These techniques, however, may be practiced without these specific details. In some instances, well-known structures and devices are shown in block diagram form to avoid obscuring the concepts of the described examples.

[0164] In the appended figures, similar components or features may have the same reference label. Further, various components of the same type may be distinguished by following the reference label by a dash and a second label that distinguishes among the similar components. If just the first reference label is used in the specification, the description is applicable to any one of the similar components having the same first reference label irrespective of the second reference label.

[0165] The functions described herein may be implemented in hardware, software executed by a

processor, firmware, or any combination thereof. If implemented in software executed by a processor, the functions may be stored on or transmitted over as one or more instructions (e.g., code) on a computer-readable medium. Other examples and implementations are within the scope of the disclosure and appended claims. For example, due to the nature of software, functions described herein can be implemented using software executed by a processor, hardware, firmware, hardwiring, or combinations of any of these. Features implementing functions may also be physically located at various positions, including being distributed such that portions of functions are implemented at different physical locations.

[0166] For example, the various illustrative blocks and modules described in connection with the disclosure herein may be implemented or performed with a processor, such as a DSP, an ASIC, an FPGA, discrete gate logic, discrete transistor logic, discrete hardware components, other programmable logic device, or any combination thereof designed to perform the functions described herein. A processor may be an example of a microprocessor, a controller, a microcontroller, a state machine, or any type of processor. A processor may also be implemented as a combination of computing devices (e.g., a combination of a DSP and a microprocessor, multiple microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration).

[0167] As used herein, including in the claims, “or” as used in a list of items (for example, a list of items prefaced by a phrase such as “at least one of” or “one or more of”) indicates an inclusive list such that, for example, a list of at least one of A, B, or C means A or B or C or AB or AC or BC or ABC (i.e., A and B and C). Also, as used herein, the phrase “based on” shall not be construed as a reference to a closed set of conditions. For example, an exemplary step that is described as “based on condition A” may be based on both a condition A and a condition B without departing from the scope of the present disclosure. In other words, as used herein, the phrase “based on” shall be construed in the same manner as the phrase “based at least in part on.”

[0168] Computer-readable media includes both non-transitory computer storage media and communication media including any medium that facilitates transfer of a computer program from one place to another. A non-transitory storage medium may be any available medium that can be accessed by a computer. By way of example, and not limitation, non-transitory computer-readable media can comprise RAM, ROM, electrically erasable programmable read-only memory (EEPROM), compact disk (CD) ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other non-transitory medium that can be used to carry or store desired program code means in the form of instructions or data structures and that can be accessed by a computer, or a processor. Also, any connection is properly termed a computer-readable medium. For example, if the software is transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave are included in the definition of medium. Disk and disc, as used herein, include CD, laser disc, optical disc, digital versatile disc (DVD), floppy disk and Blu-ray disc where disks usually reproduce data magnetically, while discs reproduce data optically with lasers.

Combinations of the above are also included within the scope of computer-readable media.

[0169] The description herein is provided to enable a person skilled in the art to make or use the disclosure. Various modifications to the disclosure will be apparent to those skilled in the art, and the generic principles defined herein may be applied to other variations without departing from the scope of the disclosure. Thus, the disclosure is not limited to the examples and designs described herein but is to be accorded the broadest scope consistent with the principles and novel features disclosed herein.

Claims

1. A system, comprising: a first semiconductor die comprising: a first interface, the first interface comprising first circuitry operable to transmit one or more access signals; and a second semiconductor die coupled with the first semiconductor die, the second semiconductor die comprising: one or more memory arrays; and a second interface coupled with the first interface and the one or more memory arrays, the second interface comprising second circuitry operable to access the one or more memory arrays based on receiving the one or more access signals, wherein the system is operable to: transmit, from the second interface to the first interface, one or more first signals based on a value of a counter associated with a quantity of access operations on the one or more memory arrays; transmit, from the first interface to the second interface based on the first interface receiving the one or more first signals, one or more second signals indicating a refresh operation associated with one or more addresses of the one or more memory arrays; and perform, by the second interface, the refresh operation based on the second interface receiving the one or more second signals.
2. The system of claim 1, wherein the second circuitry of the second interface is further operable to: compare the value of the counter to one or more threshold values; and transmit the one or more first signals to the first interface based on the comparing.
3. The system of claim 2, wherein the second circuitry of the second interface is further operable to: read the value of the counter based on receiving the one or more access signals from the first interface; increment the value of the counter based on accessing the one or more memory arrays, wherein the value of the counter is compared to the one or more threshold values after the incrementing; and write the incremented value to the counter.
4. The system of claim 1, wherein the second circuitry of the second interface is further operable to: perform one or more access operations on an address of the one or more memory arrays; and perform, concurrently with performing the one or more access operations, one or more operations to track, using the counter, a quantity of access operations on the address.
5. The system of claim 1, wherein the one or more first signals are transmitted based on the value of the counter indicating that a quantity of access operations on an address of the one or more memory arrays satisfies one or more threshold values.
6. The system of claim 5, wherein the one or more first signals indicate that the value of the counter satisfies a first threshold value of the one or more threshold values, the system further operable to: reset, by the second interface, a first portion of the counter based on the value of the counter satisfying the first threshold value; increment, by the second interface, a second portion of the counter based on the value of the counter satisfying the first threshold value; and generate, by the first interface, the one or more second signals indicating the refresh operation, wherein the refresh operation is for a second address different from the address and a third address different from the address based on the one or more first signals indicating that the value of the counter satisfies the first threshold value.
7. The system of claim 5, wherein the one or more first signals indicate that the value of the counter satisfies a second threshold value of the one or more threshold values greater than a first threshold value of the one or more threshold values, the system further operable to: reset, by the second interface, the counter based on the value of the counter satisfying the second threshold value; and generate, by the first interface, the one or more second signals indicating the refresh operation for a first set of addresses that are different from the address and a second set of addresses that different from the address based on the one or more first signals indicating that the value of the counter satisfies the second threshold value.
8. The system of claim 5, wherein the one or more first signals indicate an error associated with the counter, the system further operable to: reset, by the second interface, the counter based on the

error; and generate, by the first interface, the one or more second signals indicating the refresh operation for a first set of addresses that are different from the address and a second set of addresses that are different from the address based on the one or more first signals indicating the error.

9. The system of claim 1, wherein the first circuitry of the first interface is further operable to determine an address of the one or more memory arrays associated with the one or more first signals based on a duration between transmitting the one or more access signals from the first interface and receiving the one or more first signals from the second interface.

10. The system of claim 1, wherein the one or more first signals are associated with a first address of the one or more memory arrays and a second address of the one or more memory arrays adjacent to the first address, and wherein the first circuitry of the first interface is operable to: determine the one or more addresses for the refresh operation to be adjacent to the first address or the second address and to exclude the first address and the second address based on the first address and the second address being adjacent.

11. The system of claim 1, wherein the system is further operable to: transmit, from the first interface to the second interface, one or more third signals indicating a second refresh operation associated with a set of addresses of the one or more memory arrays; and reset, by the second interface, respective counters associated with each address of the set of addresses based on the one or more third signals.

12. The system of claim 1, wherein the one or more second signals indicating the refresh operation is based on the one or more addresses being associated with a spare row of the one or more memory arrays.

13. The system of claim 1, wherein the second semiconductor die comprises: the counter; and one or more dedicated access lines coupled with the second interface for accessing the counter.

14. An apparatus, comprising: a first semiconductor die comprising a first interface, the first interface comprising circuitry operable to: transmit, to a second interface of a second semiconductor die coupled with the first semiconductor die, one or more first signals comprising a first command to activate a row of a memory array of the second semiconductor die; receive, from the second interface based on transmitting the one or more first signals, one or more second signals comprising an alert message associated with a row hammer mitigation operation associated with the row of the memory array; and transmit, to the second interface based on the alert message, one or more third signals comprising a second command to refresh one or more rows of the memory array adjacent to the row of the memory array.

15. The apparatus of claim 14, wherein the circuitry of the first interface is operable to: generate the one or more third signals comprising the second command, the second command indicating to refresh a first row of the memory array and a second row of the memory array that are different from the row based on the alert message indicating that a quantity of activations of the row satisfies a first threshold.

16. The apparatus of claim 14, wherein circuitry of the first interface is operable to: generate the one or more third signals comprising the second command, the second command indicating to refresh a first set of rows of the memory array and a second set of rows that are different from the row based on the alert message indicating that a quantity of activations of the row satisfies a second threshold greater than a first threshold or indicating an error associated with a counter for counting activations of the row.

17. The apparatus of claim 14, wherein the circuitry of the first interface is operable to: determine that the one or more second signals are associated with the row based on a duration between transmitting the one or more first signals and receiving the one or more second signals.

18. The apparatus of claim 14, wherein the circuitry operable to transmit the one or more third signals is further operable to: transmit the one or more third signals based on receiving the alert message and receiving a second alert message associated with a second row hammer mitigation

operation associated with a second row adjacent to the row.

19. The apparatus of claim 14, wherein the second command to refresh the one or more rows is based on whether the row is a spare row of the memory array.

20. A method, comprising: transmitting, from a first interface of a first semiconductor die to a second interface of a second semiconductor die coupled with the first semiconductor die, one or more first signals comprising a first command to activate a row of a memory array of the second semiconductor die; receiving, at the first interface from the second interface based on transmitting the one or more first signals, one or more second signals comprising an alert message associated a row hammer mitigation operation associated with the row of the memory array; and transmitting, from the first interface to the second interface based on the alert message, one or more third signals comprising a second command to refresh one or more rows of the memory array adjacent to the row of the memory array.

21. The method of claim 20, further comprising: generating, by the first interface, the one or more third signals comprising the second command, the second command indicating to refresh a first row of the memory array and a second row of the memory array that are adjacent to the row based on the alert message indicating that a quantity of activations of the row satisfies a first threshold.

22. The method of claim 20, further comprising: generating, by the first interface, the one or more third signals comprising the second command, the second command indicating to refresh a first set of rows of the memory array and a second set of rows that are adjacent to the row based on the alert message indicating that a quantity of activations of the row satisfies a second threshold greater than a first threshold or indicating an error associated with a counter for counting activations of the row.

23. The method of claim 20, further comprising: determining, by the first interface, that the one or more second signals is associated with the row based on a duration between transmitting the one or more first signals and receiving the one or more second signals.

24. The method of claim 20, further comprising: receiving, at the first interface from the second interface, a second alert message associated with a second row hammer mitigation operation associated with a second row adjacent to the row, wherein the one or more third signals is transmitted based on receiving the alert message and the second alert message.

25. An apparatus, comprising: a second semiconductor die comprising a second interface, the second interface comprising circuitry operable to: receive, from a first interface of a first semiconductor die, one or more first signals comprising a command to activate a row of a memory array of the second semiconductor die; increment a value of a counter associated with the row based on activating the row in accordance with the one or more first signals; read the value of the counter after incrementing the value of the counter; and transmit, to the first interface based on reading the value of the counter, one or more second signals comprising an alert message associated a row hammer mitigation operation associated with the row.

26. The apparatus of claim 25, wherein the circuitry of the second interface further operable to: receive, from the first interface based on the alert message, one or more third signals comprising a second command to refresh one or more rows of the memory array adjacent to the row of the memory array; and refresh the one or more rows based on the second command.

27. The apparatus of claim 25, wherein the alert message indicates that the value of the counter satisfies a first threshold value, the circuitry of the second interface further operable to: reset a first portion of the counter based on the value of the counter satisfying the first threshold value; and increment a second portion of the counter based on resetting the first portion of the counter.

28. The apparatus of claim 25, wherein the alert message indicates that the value of the counter satisfies a second threshold value greater than a first threshold value, the circuitry of the second interface further operable to: reset the counter based on the value of the counter satisfying the second threshold value.

29. The apparatus of claim 25, wherein the alert message indicates an error associated with the counter, the circuitry of the second interface further operable to: reset the counter based on

identifying the error.

30. A method, comprising: receiving, at a second interface of a second semiconductor die from a first interface of a first semiconductor die operable to couple with the second semiconductor die, one or more first signals comprising a first command to activate a row of a memory array of the second semiconductor die; incrementing, by the second interface, a value of a counter associated with the row based on activating the row in accordance with the one or more first signals; reading, by the second interface, the value of the counter after incrementing the value of the counter; and transmitting, from the second interface to the first interface based on reading the value of the counter, one or more second signals comprising an alert message associated a row hammer mitigation operation associated with the row.
