

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12411631
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Lee; Eric N. et al.

Status polling based on die-generated pulsed signal

Abstract

A memory system includes a ready busy pin coupled with a plurality of dice and a processing device coupled with the ready busy pin. The processing device is to perform controller operations including waiting to perform any status checks until after assertion of a pulse on a status indicator signal received from the ready busy pin; detecting the pulse being asserted is an extended pulse comprising at least a partial overlap of a first pulse asserted by a first die and a second pulse asserted by a second die of the plurality of dice; initiating a polling delay period in response to detecting assertion of the extended pulse, wherein the polling delay period is greater than a pulse width of the first pulse; and initiating a first status check of dice operations being performed by the plurality of dice in response to detecting expiration of the polling delay period.

Inventors:	Lee; Eric N. (San Jose, CA), Srinivasan; Dheeraj (San Jose, CA)
Applicant:	Micron Technology, Inc. (Boise, ID)
Family ID:	84784586
Assignee:	Micron Technology, Inc. (Boise, ID)
Appl. No.:	18/611094
Filed:	March 20, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240231675 A1	Jul. 11, 2024

Related U.S. Application Data

continuation parent-doc US 17590650 20220201 US 11972135 child-doc US 18611094
us-provisional-application US 63224270 20210721

Publication Classification

Int. Cl.: G06F3/06 (20060101)

U.S. Cl.:

CPC G06F3/0653 (20130101); G06F3/0604 (20130101); G06F3/0673 (20130101);

Field of Classification Search

USPC: None

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2016/0292092	12/2015	Gavens et al.	N/A	N/A
2019/0354317	12/2018	Fenghai	N/A	G06F 3/0679
2021/0182141	12/2020	Balb et al.	N/A	N/A
2022/0091775	12/2021	Shridhar	N/A	G06F 3/0655

Primary Examiner: Rutz; Jared I

Assistant Examiner: Yoon; Alexander J

Attorney, Agent or Firm: Lowenstein Sandler LLP

Background/Summary

REFERENCE TO RELATED APPLICATION (1) This application is a continuation of U.S. patent application Ser. No. 17/590,650, filed Feb. 1, 2022, which claims the benefit of U.S. Provisional Patent Application No. 63/224,270, filed Jul. 21, 2021, the entireties of which are incorporated herein by this reference.

TECHNICAL FIELD

(1) Embodiments of the disclosure are generally related to memory sub-systems, and more specifically, relate to status polling based on die-generated pulsed signal.

BACKGROUND

(2) A memory sub-system can include one or more memory devices that store data. The memory devices can be, for example, non-volatile memory devices and volatile memory devices. In general, a host system can utilize a memory sub-system to store data at the memory devices and to retrieve data from the memory devices.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) The present disclosure will be understood more fully from the detailed description given below and from the accompanying drawings of some embodiments of the disclosure.

- (2) FIG. 1A illustrates an example computing system that includes a memory sub-system according to some embodiments.
- (3) FIG. 1B is a block diagram of memory device(s) in communication with a memory sub-system controller of a memory sub-system according to an embodiment.
- (4) FIG. 2A is a schematic block diagram of an example of the memory device(s) including multiple dice and other sensor hardware that provide indicator pulses to control logic according to some embodiments.
- (5) FIG. 2B is a schematic block diagram illustrating a multi-plane memory device configured for noise reduction during parallel plane access in accordance with some embodiments of the present disclosure.
- (6) FIG. 3 is a graph of a status indicator signal that include pulses generated by planes of multiple dice of the memory device(s) according to some embodiments.
- (7) FIG. 4A is a graph of a status indicator signal including pulses generated by planes of multiple dice of the memory device(s) and timing of performing status checks according to an embodiment.
- (8) FIG. 4B is a graph of a status indicator signal including pulses generated by planes of multiple dice of the memory device(s) and timing of performing status checks according to another embodiment.
- (9) FIG. 5 is a flow diagram of an example method of performing status checks based on a plane-generated pulsed signal according to an exemplary embodiment.
- (10) FIG. 6 is a flow diagram of an example method of performing status checks based on a die-generated pulsed signal according to an exemplary embodiment.
- (11) FIG. 7 is a block diagram of an example computer system in which embodiments of the present disclosure can operate.

DETAILED DESCRIPTION

- (12) Embodiments of the present disclosure are directed to status polling based on a die-generated pulsed signal. Certain memory sub-systems include a memory sub-system controller that determines when and how often to poll for statuses from multiple dice of a memory device. Polling is required because the controller needs to know which dice are available to perform a next memory operation such as an erase operation, a read operation, or a program operation. The controller polls the multiple dice and receives, in response, status updates to know when one or more dice of the multiple dice are ready to perform a next operation.
- (13) In certain memory sub-systems, for example, the memory sub-system controller waits a certain polling delay period after the start of each operation to perform a first status request, followed by subsequent status request at a polling interval thereafter. The controller blindly triggers the timing and frequency of these status requests on a per-operation basis, which, therefore, causes the status checks to be performed more often than necessary. Such repetitive status requests between the controller and the memory device causes congestion on a communication bus and/or interface between the controller and the memory device, which consumes significant overhead in communication bandwidth that could otherwise be used for other control signals and data. The consumption of overhead can slow down and impact performance of the memory sub-system.
- (14) Aspects of the present disclosure address the above and other deficiencies through causing the memory sub-system controller to perform status checks according to pulses on a status indicator signal received from the multiple dice. In some embodiments, the pulses are generated by an aggregate of multiple planes across the multiple dice and communicated over a ready busy (RB) pin that is coupled with the multiple dice and the controller (e.g., processing device). More specifically, the status indicator signal can remain deasserted (which can, for example, be a logical 0 or 1 in different embodiments) and be asserted (e.g., the opposite logical value from being deasserted) by pulses from the planes and dice to indicate a status change, such as to indicate a completion of a memory operation (program, erase, read), among other information such as reaching a temperature trigger, detection of an error, detection of a security event, or the like, which

will be discussed in more detail. In some embodiments, the pulses from different planes and dice can be asserted in a way that partially overlaps, thus the pulses during which status checks are performed can be extended for periods of time. Further, when the status indicator signal is deasserted, no status checks are performed. In this way, the controller performs status checks in response to changes in status and when there is new status information to be received.

(15) In at least some embodiments, the memory sub-system controller performs operations that include receiving a status indicator signal with a pulse that is asserted by one or more planes of the multiple dice or simply by one or more of the multiple dice. In response to detecting the pulse, the operations include performing at least one of a first status check of dice operations being performed by the dice at an expiration of a polling delay period or a second status check of the dice operations in response to detecting the pulse be deasserted. If the pulse is longer than the polling delay period, then the controller performs both the first status check and the second status check. In some embodiments, the polling delay period is set to be greater than or equal to a pulse width of the pulses received from the dice, thus minimizing status checks for a single completion situation. In cases of extended pulses where status pulses are generated that overlap on the status indicator signal, the operations further include performing one or more additional status checks of the dice operations at a polling interval after expiration of the polling delay period and before detecting the pulse be deasserted. The operations further include terminating performances of status checks while the status indicator signal remains deasserted.

(16) Therefore, advantages of the systems and methods implemented in accordance with some embodiments of the present disclosure include, but are not limited to, the controller performing status polling only when an operation on the memory device has completed or had a change in status. This practice by the controller increases polling efficiency, particularly for program and erase operations, and reduces bus (or other communication interface) congestion due to the polling. The controller hardware is also simplified in having no need to keep track of timers for each operation in execution. Other advantages will be apparent to those skilled in the art as discussed hereinafter.

(17) FIG. 1A illustrates an example computing system **100** that includes a memory sub-system **110** in accordance with some embodiments of the present disclosure. The memory sub-system **110** can include media, such as one or more volatile memory devices (e.g., memory device **140**), one or more non-volatile memory devices (e.g., one or more memory device(s) **130**), or a combination of such media or memory devices. The memory sub-system **110** can be a storage device, a memory module, or a hybrid of a storage device and memory module.

(18) The memory device(s) **130** can be non-volatile memory device(s). One example of non-volatile memory devices is a negative-and (NAND) memory device. A non-volatile memory device is a package of one or more dice or logic units (LUNs). Thus, each memory device **130** can be a die (or LUN) or can be a multi-dice package that includes multiple dice (or LUNs) on a chip, e.g., an integrated circuit package of dice. Each die can include one or more planes. For some types of non-volatile memory devices (e.g., NAND devices), each plane includes a set of physical blocks. Each block includes a set of pages. Each page includes a set of memory cells (“cells”). A cell is an electronic circuit that stores information. Depending on the cell type, a cell can store one or more bits of binary information, and has various logic states that correlate to the number of bits being stored. The logic states can be represented by binary values, such as “0” and “1”, or combinations of such values.

(19) Each memory device **130** can be made up of bits arranged in a two-dimensional or three-dimensional grid, also referred to as a memory array. Memory cells are formed onto a silicon wafer in an array of columns (also hereinafter referred to as bitlines) and rows (also hereinafter referred to as wordlines). A wordline can refer to one or more rows of memory cells of a memory device that are used with one or more bitlines to generate the address of each of the memory cells. The intersection of a bitline and wordline constitutes the address of the memory cell.

(20) A memory sub-system **110** can be a storage device, a memory module, or a combination of a storage device and memory module. Examples of a storage device include a solid-state drive (SSD), a flash drive, a universal serial bus (USB) flash drive, an embedded Multi-Media Controller (eMMC) drive, a Universal Flash Storage (UFS) drive, a secure digital (SD) card, and a hard disk drive (HDD). Examples of memory modules include a dual in-line memory module (DIMM), a small outline DIMM (SO-DIMM), and various types of non-volatile dual in-line memory modules (NVDIMMs).

(21) The computing system **100** can be a computing device such as a desktop computer, laptop computer, network server, mobile device, a vehicle (e.g., airplane, drone, train, automobile, or other conveyance), Internet of Things (IOT) enabled device, embedded computer (e.g., one included in a vehicle, industrial equipment, or a networked commercial device), or such computing device that includes memory and a processing device.

(22) The computing system **100** can include a host system **120** that is coupled to one or more memory sub-systems **110**. In some embodiments, the host system **120** is coupled to multiple memory sub-systems **110** of different types. FIG. 1A illustrates one example of a host system **120** coupled to one memory sub-system **110**. The host system **120** can provide data to be stored at the memory sub-system **110** and can request data to be retrieved from the memory sub-system **110**. As used herein, “coupled to” or “coupled with” generally refers to a connection between components, which can be an indirect communicative connection or direct communicative connection (e.g., without intervening components), whether wired or wireless, including connections such as electrical, optical, magnetic, etc.

(23) The host system **120** can include a processor chipset and a software stack executed by the processor chipset. The processor chipset can include one or more cores, one or more caches, a memory controller (e.g., NVDIMM controller), and a storage protocol controller (e.g., PCIe controller, SATA controller). The host system **120** uses the memory sub-system **110**, for example, to write data to the memory sub-system **110** and read data from the memory sub-system **110**.

(24) The host system **120** can be coupled to the memory sub-system **110** via a physical host interface. Examples of a physical host interface include, but are not limited to, a serial advanced technology attachment (SATA) interface, a peripheral component interconnect express (PCIe) interface, universal serial bus (USB) interface, Fibre Channel, Serial Attached SCSI (SAS), a double data rate (DDR) memory bus, Small Computer System Interface (SCSI), a dual in-line memory module (DIMM) interface (e.g., DIMM socket interface that supports Double Data Rate (DDR)), etc. The physical host interface can be used to transmit data between the host system **120** and the memory sub-system **110**. The host system **120** can further utilize an NVM Express (NVMe) interface to access components (e.g., the one or more memory device(s) **130**) when the memory sub-system **110** is coupled with the host system **120** by the physical host interface (e.g., PCIe bus). The physical host interface can provide an interface for passing control, address, data, and other signals between the memory sub-system **110** and the host system **120**. FIG. 1A illustrates a memory sub-system **110** as an example. In general, the host system **120** can access multiple memory sub-systems via a same communication connection, multiple separate communication connections, and/or a combination of communication connections.

(25) The memory devices **130**, **140** can include any combination of the different types of non-volatile memory devices and/or volatile memory devices. The volatile memory devices (e.g., memory device **140**) can be, but are not limited to, random access memory (RAM), such as dynamic random access memory (DRAM) and synchronous dynamic random access memory (SDRAM).

(26) Some examples of non-volatile memory devices (e.g., memory device(s) **130**) include a negative-and (NAND) type flash memory and write-in-place memory, such as a three-dimensional cross-point (“3D cross-point”) memory device, which is a cross-point array of non-volatile memory cells. A cross-point array of non-volatile memory cells can perform bit storage based on a change

of bulk resistance, in conjunction with a stackable cross-gridded data access array. Additionally, in contrast to many flash-based memories, cross-point non-volatile memory can perform a write in-place operation, where a non-volatile memory cell can be programmed without the non-volatile memory cell being previously erased. NAND type flash memory includes, for example, two-dimensional NAND (2D NAND) and three-dimensional NAND (3D NAND).

(27) Each of the memory device(s) **130** can include one or more arrays of memory cells. One type of memory cell, for example, single-level cells (SLC) can store one bit per cell. Other types of memory cells, such as multi-level cells (MLCs), triple level cells (TLCs), quad-level cells (QLCs), and penta-level cells (PLCs) can store multiple bits per cell, e.g., by way of additional threshold voltage ranges. In some embodiments, each of the memory device(s) **130** can include one or more arrays of memory cells such as SLCs, MLCs, TLCs, QLCs, PLCs or any combination of such. In some embodiments, a particular memory device can include an SLC portion, and an MLC portion, a TLC portion, a QLC portion, or a PLC portion of memory cells. The memory cells of the memory device(s) **130** can be grouped as pages that can refer to a logical unit of the memory device used to store data. With some types of memory (e.g., NAND), pages can be grouped to form blocks.

(28) Although non-volatile memory components such as a 3D cross-point array of non-volatile memory cells and NAND type flash memory (e.g., 2D NAND, 3D NAND) are described, the memory device **130** can be based on any other type of non-volatile memory, such as read-only memory (ROM), phase change memory (PCM), self-selecting memory, other chalcogenide based memories, ferroelectric transistor random-access memory (FeTRAM), ferroelectric random access memory (FeRAM), magneto random access memory (MRAM), Spin Transfer Torque (STT)-MRAM, conductive bridging RAM (CBRAM), resistive random access memory (RRAM), oxide based RRAM (OxRAM), negative-or (NOR) flash memory, or electrically erasable programmable read-only memory (EEPROM).

(29) A memory sub-system controller **115** (or controller **115** or processing device for simplicity) can communicate with the memory device(s) **130** to perform operations such as reading data, writing data, or erasing data at the memory devices **130** and other such operations. The memory sub-system controller **115** can include hardware such as one or more integrated circuits and/or discrete components, a buffer memory, or a combination thereof. The hardware can include a digital circuitry with dedicated (i.e., hard-coded) logic to perform the operations described herein. The memory sub-system controller **115** can be a microcontroller, special purpose logic circuitry (e.g., a field programmable gate array (FPGA), an application specific integrated circuit (ASIC), etc.), or other suitable processor.

(30) The memory sub-system controller **115** can include a processing device, which includes one or more processors (e.g., processor **117**), configured to execute instructions stored in a local memory **119**. In the illustrated example, the local memory **119** of the memory sub-system controller **115** includes an embedded memory configured to store instructions for performing various processes, operations, logic flows, and routines that control operation of the memory sub-system **110**, including handling communications between the memory sub-system **110** and the host system **120**.

(31) In some embodiments, the local memory **119** can include memory registers storing memory pointers, fetched data, etc. The local memory **119** can also include read-only memory (ROM) for storing micro-code. While the example memory sub-system **110** in FIG. 1A has been illustrated as including the memory sub-system controller **115**, in another embodiment of the present disclosure, a memory sub-system **110** does not include a memory sub-system controller **115**, and can instead rely upon external control (e.g., provided by an external host, or by a processor or controller separate from the memory sub-system).

(32) In general, the memory sub-system controller **115** can receive commands or operations from the host system **120** and can convert the commands or operations into instructions or appropriate commands to achieve the desired access to the memory device(s) **130**. The memory sub-system controller **115** can be responsible for other operations such as wear leveling operations, garbage

collection operations, error detection and error-correcting code (ECC) operations, encryption operations, caching operations, and address translations between a logical address (e.g., a logical block address (LBA), namespace) and a physical address (e.g., physical block address) that are associated with the memory device(s) **130**. The memory sub-system controller **115** can further include host interface circuitry to communicate with the host system **120** via the physical host interface. The host interface circuitry can convert the commands received from the host system into command instructions to access the memory device(s) **130** as well as convert responses associated with the memory device(s) **130** into information for the host system **120**.

(33) The memory sub-system **110** can also include additional circuitry or components that are not illustrated. In some embodiments, the memory sub-system **110** can include a cache or buffer (e.g., DRAM) and address circuitry (e.g., a row decoder and a column decoder) that can receive an address from the memory sub-system controller **115** and decode the address to access the memory device(s) **130**.

(34) In some embodiments, the memory device(s) **130** include local media controllers **135** that operate in conjunction with memory sub-system controller **115** to execute operations on one or more memory cells of the memory device(s) **130**. An external controller (e.g., memory sub-system controller **115**) can externally manage a memory device **130** (e.g., perform media management operations on the memory device **130**). In some embodiments, memory sub-system **110** is a managed memory device, which is a raw memory device having control logic (e.g., local media controller **135**) on the die and a controller (e.g., memory sub-system controller **115**) for media management within the same memory device package. An example of a managed memory device is a managed NAND (MNAND) device.

(35) In some embodiments, each memory device **130** further includes a ready busy pin **152** (or RB pin **152**) that is coupled with multiple dice of the memory device(s) **130** as well as being coupled with the memory sub-system controller **115**, e.g., over a communication bus **125**. In various embodiments, the communication bus **125** is or includes an open NAND flash interface (ONFI). The communication bus **125** can also include other command, address, and data interface, including but not limited to a shared bus, configurable channels, and separate command/address bus schemes, over which the polling occurs.

(36) In these embodiments, the controller **115** further includes a status polling component **113**. The status polling component **113** can monitor a status indicator signal received over the RB pin **152** (or other status input/output (I/O) pins that will be discussed) in order to detect pulses being asserted and deasserted on the status indicator signal by one or more planes and/or dice of the memory device(s) **130**. The status polling component **113** can manage polling the multiple planes and/or dice depending on detection of these pulses being asserted and deasserted throughout operation, as will be discussed in more detail with reference to FIGS. 2A-3, FIGS. 4A-4B, and FIGS. 5-6. In some embodiments, the status polling component is integrated in whole or in part within the host system **120**.

(37) FIG. 1B is a simplified block diagram of a first apparatus, in the form of the one or more memory device(s) **130**, in communication with a second apparatus, in the form of a memory sub-system controller **115** of a memory sub-system (e.g., the memory sub-system **110** of FIG. 1A), according to an embodiment. Some examples of electronic systems include personal computers, personal digital assistants (PDAs), digital cameras, digital media players, digital recorders, games, appliances, vehicles, wireless devices, mobile telephones and the like. The memory sub-system controller **115** (e.g., a controller external to each memory device **130**), can be a memory controller or other external host device.

(38) Each memory device **130** includes an array of memory cells **104** logically arranged in rows and columns. Memory cells of a logical row are typically connected to the same access line (e.g., a wordline) while memory cells of a logical column are typically selectively connected to the same data line (e.g., a bitline). A single access line can be associated with more than one logical row of

memory cells and a single data line can be associated with more than one logical column. Memory cells (not shown in FIG. 1B) of at least a portion of the array of memory cells **104** are capable of being programmed to one of at least two target data states.

(39) Row decode circuitry **108** and column decode circuitry **111** are provided to decode address signals. Address signals are received and decoded to access the array of memory cells **104**. Each memory device **130** also includes input/output (I/O) control circuitry **112** to manage input of commands, addresses and data to the memory device **130** as well as output of data and status information from each memory device **130**. An address register **114** is in communication with the I/O control circuitry **112** and row decode circuitry **108** and column decode circuitry **111** to latch the address signals prior to decoding. A command register **124** is in communication with the I/O control circuitry **112** and local media controller **135** to latch incoming commands.

(40) A controller (e.g., the local media controller **135** internal to each memory device **130**) controls access to the array of memory cells **104** in response to the commands and generates status information for the external memory sub-system controller **115**, i.e., the local media controller **135** is configured to perform access operations (e.g., read operations, programming operations and/or erase operations) on the array of memory cells **104**. The local media controller **135** is in communication with row decode circuitry **108** and column decode circuitry **111** to control the row decode circuitry **108** and column decode circuitry **111** in response to the addresses.

(41) The local media controller **135** is also in communication with a cache register **118** and a data register **121**. The cache register **118** latches data, either incoming or outgoing, as directed by the local media controller **135** to temporarily store data while the array of memory cells **104** is busy writing or reading, respectively, other data. During a program operation (e.g., write operation), data can be passed from the cache register **118** to the data register **121** for transfer to the array of memory cells **104**; then new data can be latched in the cache register **118** from the I/O control circuitry **112**. During a read operation, data can be passed from the cache register **118** to the I/O control circuitry **112** for output to the memory sub-system controller **115**; then new data can be passed from the data register **121** to the cache register **118**. The cache register **118** and/or the data register **121** can form (e.g., can form at least a portion of) a page buffer of each memory device **130**. The page buffer can further include sensing devices such as a sense amplifier, to sense a data state of a memory cell of the array of memory cells **104**, e.g., by sensing a state of a data line connected to that memory cell. A status register **122** can be in communication with I/O control circuitry **112** and the local memory controller **135** to latch the status information for output to the memory sub-system controller **115**.

(42) Each memory device **130** receives control signals at the memory sub-system controller **115** from the local media controller **135** over a control link **132**. For example, the control signals can include a chip enable signal CE #, a command latch enable signal CLE, an address latch enable signal ALE, a write enable signal WE #, a read enable signal RE #, and a write protect signal WP #. Additional or alternative control signals (not shown) can be further received over control link **132** depending upon the nature of each memory device **130**. In one embodiment, each memory device **130** receives command signals (which represent commands), address signals (which represent addresses), and data signals (which represent data) from the memory sub-system controller **115** over a multiplexed input/output (I/O) bus **134** and outputs data to the memory sub-system controller **115** over I/O bus **134**.

(43) For example, the commands can be received over input/output (I/O) pins [7:0] of I/O bus **134** at I/O control circuitry **112** and can then be written into a command register **124**. The addresses can be received over input/output (I/O) pins [7:0] of I/O bus **134** at I/O control circuitry **112** and can then be written into address register **114**. The data can be received over input/output (I/O) pins [7:0] for an 8-bit device or input/output (I/O) pins [15:0] for a 16-bit device at I/O control circuitry **112** and then can be written into cache register **118**. The data can be subsequently written into data register **121** for programming the array of memory cells **104**.

(44) In an embodiment, cache register **118** can be omitted, and the data can be written directly into data register **121**. Data can also be output over input/output (I/O) pins [7:0] for an 8-bit device or input/output (I/O) pins [15:0] for a 16-bit device. Although reference can be made to I/O pins, they can include any conductive node providing for electrical connection to each memory device **130** by an external device (e.g., the memory sub-system controller **115**), such as conductive pads or conductive bumps as are commonly used.

(45) It will be appreciated by those skilled in the art that additional circuitry and signals can be provided, and that each memory device **130** of FIG. **1B** has been simplified. It should be recognized that the functionality of the various block components described with reference to FIG. **1B** may not necessarily be segregated to distinct components or component portions of an integrated circuit device. For example, a single component or component portion of an integrated circuit device could be adapted to perform the functionality of more than one block component of FIG. **1B**. Alternatively, one or more components or component portions of an integrated circuit device could be combined to perform the functionality of a single block component of FIG. **1B**. Additionally, while specific I/O pins are described in accordance with popular conventions for receipt and output of the various signals, it is noted that other combinations or numbers of I/O pins (or other I/O node structures) can be used in the various embodiments.

(46) FIG. **2A** is a schematic block diagram of an example of the memory device(s) **130**, e.g., memory device(s) **130A**, including multiple dice **230** (e.g., die_0, die_1, die_2, . . . die_N) and other sensor hardware that provide indicator pulses to control logic according to some embodiments. The memory device(s) **130A** can further include, in addition to the ready busy (RB) pin **152** coupled with the multiple dice **230** and the local media controller **135**, one or more status I/O pins **252** coupled between die sensor hardware **256** and the local media controller **135**. Thus, each die and/or plane (see FIG. **2B**) of the multiple dice **230** can assert a pulse at the RB pin **152** to indicate the die/plane has completed an operation and is ready, or keep the status indicator signal sent over the RB pin **152** deasserted to indicate that the die/plane is busy.

(47) Similarly, in at least some embodiments, other hardware and/or control logic of the memory device(s) **130A** can assert a pulse at one or more status I/O pins **252** to indicate completion or triggering of a particular device status that may not be directly related to program/erase/read operations performed at the multiple dice, but nonetheless are associated with dice functionality. For example, the particular status can be associated with the die sensor hardware **256** or statuses tracked directly by the local media controller **135**. These particular statuses received from the die sensor hardware **256** can include, but not be limited to, a temperature status (e.g., a thermocouple reaching a particular temperature threshold limit), a power event or power status (e.g., supply voltages out of range, supply noise out of specification), or a security event (e.g., unauthorized access, secure area access, fail authentication, or the like). Further, the particular statuses received from the local media controller **135** can include a suspend completion of dice operation, an error status (e.g., program fail, erase fail, or read errors that exceed a threshold bit error rate (BER)), or similar type of operational statuses beyond memory operation completion.

(48) In various embodiments, therefore, the operations can further include receiving a second status indicator signal with a second pulse that is asserted by sensor hardware of the memory device, e.g., the device sensor hardware **256**. In response to detecting the second pulse, the operations further include performing at least one of a third status check of device operations being performed by the memory device(s) **130** at expiration of the polling delay period or a fourth status check of the device operations in response to detecting the second pulse be deasserted. The operations can further include terminating performances of status checks while the second status indicator signal remains deasserted. In some embodiments, the device operations include one of a suspend completion of a memory operation, a power event status, a security event status, or a temperature status associated with the memory device.

(49) FIG. **2B** is a schematic block diagram illustrating a multi-plane memory device **130B**

configured for noise reduction during parallel plane access in accordance with some embodiments of the present disclosure. The memory planes **272(0)-272(3)** can each be divided into blocks of data, with a different relative block of data from two or more of the memory planes **272(0)-272(3)** concurrently accessible during memory access operations. For example, during memory access operations, two or more of data block **282** of the memory plane **272(0)**, data block **283** of the memory plane **272(1)**, data block **284** of the memory plane **272(2)**, and data block **285** of the memory plane **272(3)** can each be accessed concurrently.

(50) The memory device **130B** includes a memory array **270** divided into memory planes **272(0)-272(3)** that each includes a respective number of memory cells. In various embodiments, the memory array **270** is included in one or more dice of the multiple dice **230** (FIG. 2A). The multi-plane memory device **130B** can further include the local media controller **135**, including a power control circuit and access control circuit for concurrently performing memory access operations for different memory planes **272(0)-272(3)**. The memory cells can be non-volatile memory cells, such as NAND flash cells, or can generally be any type of memory cells.

(51) The memory planes **272(0)-272(3)** can each be divided into blocks of data, with a different relative block of data from each of the memory planes **272(0)-272(3)** concurrently accessible during memory access operations. For example, during memory access operations, data block **282** of the memory plane **272(0)**, data block **283** of the memory plane **272(1)**, data block **284** of the memory plane **272(2)**, and data block **285** of the memory plane **272(3)** can each be accessed concurrently.

(52) Each of the memory planes **272(0)-272(3)** can be coupled to a respective page buffer **276(0)-276(3)**. Each page buffer **276(0)-276(3)** can be configured to provide data to or receive data from the respective memory plane **272(0)-272(3)**. The page buffers **276(0)-276(3)** can be controlled by local media controller **135**. Data received from the respective memory plane **272(0)-272(3)** can be latched at the page buffers **276(0)-276(3)**, respectively, and retrieved by local media controller **135**, and provided to the memory sub-system controller **115** via the NVMe interface.

(53) Each of the memory planes **272(0)-272(3)** can be further coupled to a respective access driver circuit **274(0)-274(3)**, such as an access line driver circuit. The driver circuits **274(0)-274(3)** can be configured to condition a page of a respective block of an associated memory plane **272(0)-272(3)** for a memory access operation, such as programming data (i.e., writing data), reading data, or erasing data. Each of the driver circuits **274(0)-274(3)** can be coupled to a respective global access lines associated with a respective memory plane **272(0)-272(3)**. Each of the global access lines can be selectively coupled to respective local access lines within a block of a plane during a memory access operation associated with a page within the block. The driver circuits **274(0)-274(3)** can be controlled based on signals from local media controller **135**. Each of the driver circuits **274(0)-274(3)** can include or be coupled to a respective power circuit, and can provide voltages to respective access lines based on voltages provided by the respective power circuit. The voltages provided by the power circuits can be based on signals received from local media controller **135**.

(54) The local media controller **135** can control the driver circuits **274(0)-274(3)** and page buffers **276(0)-276(3)** to concurrently perform memory access operations associated with each of a group of memory command and address pairs (e.g., received from memory sub-system controller **115**). For example, local media controller **135** can control the driver circuits **274(0)-274(3)** and page buffer **276(0)-276(3)** to perform the concurrent memory access operations. Local media controller **135** can include a power control circuit that serially configures two or more of the driver circuits **274(0)-274(3)** for the concurrent memory access operations, and an access control circuit configured to control two or more of the page buffers **276(0)-276(3)** to sense and latch data from the respective memory planes **272(0)-272(3)**, or program data to the respective memory planes **272(0)-272(3)** to perform the concurrent memory access operations.

(55) In operation, the local media controller **135** can receive a group of memory command and address pairs via the NVMe interface, with each pair arriving in parallel or serially. In some

examples, the group of memory command and address pairs can each be associated with different respective memory planes **272(0)-272(3)** of the memory array **270**. The local media controller **135** can be configured to perform concurrent memory access operations (e.g., read operations or program operations) for the different memory planes **272(0)-272(3)** of the memory array **270** responsive to the group of memory command and address pairs. For example, the power control circuit of local media controller **135** can serially configure, for the concurrent memory access operations based on respective page type (e.g., upper page (UP), middle page (MP), lower page (LP), extra page (XP), SLC/MLC/TLC/QLC page), the driver circuits **274(0)-274(3)** for two or more memory planes **272(0)-272(3)** associated with the group of memory command and address pairs. After the access line driver circuits **274(0)-274(3)** have been configured, the access control circuit of the local media controller **135** can concurrently control the page buffers **276(0)-276(3)** to access the respective pages of each of the two or more memory planes **272(0)-272(3)** associated with the group of memory command and address pairs, such as retrieving data or writing data, during the concurrent memory access operations. For example, the access control circuit can concurrently (e.g., in parallel and/or contemporaneously) control the page buffers **276(0)-276(3)** to charge/discharge bitlines, sense data from the two or more memory planes **272(0)-272(3)**, and/or latch the data.

(56) Based on the signals received from local media controller **135**, the driver circuits **274(0)-274(3)** that are coupled to the memory planes **272(0)-272(3)** associated with the group of memory command and address command pairs can select blocks of memory or memory cells from the associated memory plane **272(0)-272(3)**, for memory operations, such as read, program, and/or erase operations. The driver circuits **274(0)-274(3)** can drive different respective global access lines associated with a respective memory plane **272(0)-272(3)**. As an example, the driver circuit **274(0)** can drive a first voltage on a first global access line associated with the memory plane **272(0)**, the driver circuit **274(1)** can drive a second voltage on a third global access line associated with the memory plane **272(1)**, the driver circuit **274(2)** can drive a third voltage on a seventh global access line associated with the memory plane **272(2)**, etc., and other voltages can be driven on each of the remaining global access lines. In some examples, pass voltages can be provided on all access lines except an access line associated with a page of a memory plane **272(0)-272(3)** to be accessed. The driver circuits **274(0)-274(3)** and the page buffers **276(0)-276(3)** can allow access to different respective pages within different respective blocks of memory cells to be accessed concurrently. For example, a first page of a first block of a first memory plane can be accessed concurrently with a second page of a second block of a second memory plane, regardless of page type.

(57) The page buffers **276(0)-276(3)** can provide data to or receive data from the local media controller **135** during the memory access operations responsive to signals from the local media controller **135** and the respective memory planes **272(0)-272(3)**. The local media controller **135** can provide the received data to memory sub-system controller **115**.

(58) It will be appreciated that the memory device **130B** can include more or less than four memory planes, driver circuits, and page buffers. It will also be appreciated that the respective global access lines can include 8, 16, 32, 64, 128, etc., global access lines. In another embodiment, memory device **130B** can include fewer driver circuits than there are planes. In such an embodiment, memory device **130B** can further include a plane selection circuit (e.g., a number of bi-directional multiplexer circuits) controlled by control signals received from local media controller **135**. The plane selection circuit allows any of the driver circuits to be selectively coupled to any of the memory planes in memory device **130B**. In this manner, there is not a fixed association between any of the driver circuits and any of the planes.

(59) Additionally, in at least some embodiments, each of processors **254(0)-254(3)** can receive instructions from a plane driver manager **260**, such as whether to permit, suspend, or resume quiet events or high noise events during the operations being performed by the corresponding one of driver circuits **274(0)-274(3)**, to manage timing of execution such operations, e.g., program, erase,

or read operations at the memory planes **272(0)-272(3)**, and/or handling of errors detected in such memory operations. For example, each of the processors **254(0)-254(3)** can monitor the status of operations being performed by the corresponding one of driver circuits **274(0)-274(3)** and report that status to plane driver manager **260**.

(60) In at least some embodiments, each of processors **254(0)-254(3)** also detects when a particular plane of the memory planes **272(0)-272(3)** becomes available due to completion of a previous operation, such as an erase operation, a program operation, or a read operation at the plane driven by the particular driver circuit **274(0)-274(3)** that is coupled with one of the processors **254(0)-254(3)**, respectively. Thus, each processor **254(0)-254(3)** can detect activity of a respective driver circuit **274(0)-274(3)** to determine the completion status, for example. In response to detecting completion of a memory operation, a respective processor **254(0)-254(3)** or the plane driver manager **260** can assert a pulse on the status indicator signal of the RB pin **152**. In this way, the local media controller **135** can provide plane-specific status pulses to the memory sub-system controller **115**, which include asserting and deasserting pulses to indicate read/busy status associated with completion or continuation of a memory operation.

(61) FIG. 3 is a graph of a status indicator signal that include pulses generated by planes of multiple dice of the memory device(s) according to some embodiments. In various embodiments, the ready busy signal (RB #) can now be pulsed low (e.g., asserted) for status changes from ready (RDY) equal to a logical one to ready equal to a logical zero for a duration of about a ready busy signal pulse width ($\sim$ tRBPW). Thus, the pulse indicates a transition to a ready state in some embodiments. In at least some embodiments, there is a common read busy signal (e.g., on ready busy pin **152**) across the multiple dice **230** and plane groups discussed with reference to FIGS. 2A-2B. Thus, each pulse on the ready busy signal (referred to generally herein as a status indicator signal) can correspond to anywhere from 1 to N dice per channel times a number of independent wordline threads, providing an ability to track status of any plane/die, group of planes/dice, or of any individual die regardless of plane.

(62) With reference to FIG. 3, a first operation **302** completes first while a second operation **304** and a third operation **306** complete next, all being performed concurrently at a first die (DIE0), but at different planes, plane_0 (P0) and plane_1 (P1), respectively. Finally a group of operations **308** complete that are being performed concurrently at a second die (DIE1). While the status indicator signal (e.g., RB #) is deasserted (e.g., at a logical high value in this example), there is no change in status of these operations. However, upon completion of the first operation **302**, control logic (e.g., the local media controller **135**) asserts a pulse on the status indicator signal. As illustrated, this is a standard pulse with a standard pulse width ($\sim$ tRBPW).

(63) In response to the second operation **304** and the third operation **306** completing, the respective control logic of each plane (P1, P3) asserts a separate pulse to indicate completion of the respective operation. Because these separate pulses partially overlap, what is sent over the status indicator signal is an extended pulse, e.g., of length of a standard pulse ($\sim$ tRBPW) plus a difference in completion time of the second and third operations (tP3-tP1). Thus, when operations of different planes/dice complete close in time to each other, the aggregation of their respective pulses assert a pulse of potentially variable length. Further, when the group of operations **308** of the second die completes, the control logic again asserts a pulse of a standard width ($\sim$ tRBPW), following which the status indicator signal is again deasserted.

(64) FIG. 4A is a graph of a status indicator signal including pulses generated by planes of multiple dice of the memory device(s) **130** and timing of performing status checks according to an embodiment. A polling delay period can be set for the controller **115** to wait, after detecting a pulse being asserted on the status indicator signal, before the start of performing status checks of the multiple planes and dice of the memory device(s) **130**. To minimize status checks for a single completion situation, the polling delay period can be set to be greater than or equal to the standard pulse width of the pulses being asserted by the multiple dice **230**.

(65) In these embodiments, once status checks are started after the polling delay period, the controller **115** can perform additional status checks at a polling interval as long as the pulse remains asserted, e.g., in the case of an extended pulse. Further, the controller **115** can perform a final status check upon detecting the status indicator signal be deasserted. This final status check can be performed to ensure capturing all completion transitions from the multiple dice **230** before terminating performing status checks while the status indicator signal remains deasserted. While the illustrated embodiments show a pulse being asserted as going from high to low and a pulse being deasserted as going from low to high, the opposite can be implemented in alternative embodiments.

(66) Thus, with reference to embodiments of FIG. **4A**, a first operation **402** completes first followed by a second operation **404** and a third operation **406** that complete sometime later. When the controller **115** detects a first pulse **452** being asserted on the status indicator signal, the controller begins waiting the polling delay period. But, because the first pulse **450** is deasserted early (e.g., in the case that the pulse width of a standard pulse is shorter than the polling delay period), then the controller **115** performs only one status check (ST) in response to detecting the first pulse **450** be deasserted.

(67) Further, the second operation **404** and the third operation **406** complete close in time to each other and their respective pulses are aggregated to generate an extended pulse **454**. Thus, in this embodiment, the controller **115** starts performing a status check after expiration of the polling delay period, which was triggered at the beginning of the assertion of the extended pulse **454**. Finally, shortly thereafter, the controller **115** detects the extended pulse **454** be deasserted and thus performs a final status check.

(68) FIG. **4B** is a graph of a status indicator signal including pulses generated by planes of multiple dice of the memory device(s) and timing of performing status checks according to another embodiment. In some embodiments, this graph can also represent dice that generate these pulses where each operation is performed by a different die. As illustrated, however, a first operation **412** completes early on while a third operation **416** completes next, followed by completion of a second operation **414**, followed by completion of a fifth operation **424**, followed ultimately by completion of a fourth operation **420**, where the operations are labeled sequentially by when the operation starts compared to start times of the other operations for simplicity of explanation. While plane of DIE0 are especially active, the fifth operation is being performed by DIE1. Again, each pulse is an indication that a status in at least one of the operations has changed, e.g., has completed and therefore the plane/die performing the operation is now ready to perform another operation.

(69) In this embodiment, because a first pulse **462** being asserted by a first die and plane (DIE0 P0) has a width of the polling delay period, only a single status check (ST) need be performed in response to either of the expiration of the polling delay period or detection of the first pulse **462** being deasserted. As is evident, a second pulse **464** is an extended pulse that is substantially longer than the first pulse **462** on the status indicator signal (RB #). When each of the remaining operations completes, the corresponding die/plane issues a pulse onto the status indicator signal, resulting in an aggregation of multiple overlapping pulses that generates an extended pulse. Thus, the controller **115** can perform (e.g., initiate) multiple status checks, one after expiration of the polling delay period, then four additional status checks at polling intervals. As mentioned, each of the polling delay period and each polling interval can be set to be greater than or equal to a pulse width of the pulse.

(70) Further, the controller **115** can perform a sixth (and final) status check in response to detecting the second pulse **464** be deasserted, e.g., go back high again. Thus, while many status checks are performed, some of these status checks gathered additional status information because so many operations were completing close in time to each other. For example, the first status check determined that the second operation **414** and third operation **416** both completed. Further, the fourth status check determined that the fourth operation **420** and the fifth operation **424** both

completed. While the sixth status check did not obtain additional information, it was performed to ensure securing any final status of any active operation in response to the second pulse **464** being deasserted, and thus terminating initiation any further status checks.

(71) FIG. 5 is a flow diagram of an example method **500** of performing status checks based on a plane-generated pulsed signal according to an exemplary embodiment. The method **500** can be performed by processing logic that can include hardware (e.g., processing device, circuitry, dedicated logic, programmable logic, microcode, hardware of a device, integrated circuit, etc.), software (e.g., instructions run or executed on a processing device), or a combination thereof. In some embodiments, the method **500** is performed by a processing device such as the memory sub-system controller **115** of FIG. 1A. In one embodiment, the method **500** is performed by the status polling component **113** of the memory sub-system controller **115**. Although shown in a particular sequence or order, unless otherwise specified, the order of the processes can be modified. Thus, the illustrated embodiments should be understood only as examples, and the illustrated processes can be performed in a different order, and some processes can be performed in parallel. Additionally, one or more processes can be omitted in various embodiments. Thus, not all processes are required in every embodiment. Other process flows are possible.

(72) At operation **510**, a signal is received. For example, the processing logic (e.g., status polling component **113**) receives the signal, such as a status indicator signal having a pulse that is asserted by one or more planes of the multiple dice **230**.

(73) At operation **520**, a status check is performed. For example, the processing logic, in response to detecting the pulse, performs at least one status check. For example, at operation **525**, the processing logic performs a first status check of dice operations being performed by the multiple dice at expiration of a polling delay period. Or, at operation **530**, the processing logic performs a second status check of the dice operations in response to detecting the pulse being deasserted.

(74) If the pulse is longer than the polling delay period, at operation **540**, additional status checks are performed. For example, the processing logic also performs zero or more additional status checks of the dice operations at a polling interval after expiration of the polling delay period and before detecting the pulse being deasserted. No additional status check is performed if the longer pulse does not reach at least one polling interval, and will perform at least one additional status check if the longer pulse extends beyond the polling delay period plus the duration of at least one polling interval. The zero or more additional status checks, if performed, can be performed before initiating the second status check at operation **530**.

(75) In the case of operation **540**, receiving the status indicator signal can include receiving a first pulse from a first plane of the one or more planes corresponding to an end of a first die operation and receiving a second pulse from a second plane of the one or more planes corresponding to an end of a second die operation. The first pulse and the second pulse partially overlap to cause the pulse to be an extended pulse.

(76) At operation **550**, status checks are terminated. For example, the processing logic terminates performances of status checks while the status indicator signal remains deasserted. This default behavior of polling for status checks enables reducing congestion, and thus conserving bandwidth, across a communication bus or other interface between the controller **115** and the memory device(s) **130**. The method **500** can then loop back to operation **510** to monitor for pulse(s) on the status indicator signal.

(77) FIG. 6 is a flow diagram of an example method **600** of performing status checks based on a die-generated pulsed signal according to an exemplary embodiment. The method **600** can be performed by processing logic that can include hardware (e.g., processing device, circuitry, dedicated logic, programmable logic, microcode, hardware of a device, integrated circuit, etc.), software (e.g., instructions run or executed on a processing device), or a combination thereof. In some embodiments, the method **600** is performed by a processing device such as the memory sub-system controller **115** of FIG. 1A. In one embodiment, the method **600** is performed by the status

polling component **113** of the memory sub-system controller **115**. Although shown in a particular sequence or order, unless otherwise specified, the order of the processes can be modified. Thus, the illustrated embodiments should be understood only as examples, and the illustrated processes can be performed in a different order, and some processes can be performed in parallel. Additionally, one or more processes can be omitted in various embodiments. Thus, not all processes are required in every embodiment. Other process flows are possible.

(78) At operation **610**, waiting is performed. For example, the processing logic waits to perform any status checks until after assertion of a pulse on a status indicator signal by one or more dice of the multiple dice **230**. This default behavior of polling for status checks enables reducing congestion, and thus conserving bandwidth, across a communication bus or other interface between the controller **115** and the memory device(s) **130**.

(79) At operation **620**, a pulse is detected. For example, the processing logic detects the pulse being asserted by the one or more dice of the multiple dice.

(80) At operation **625**, a status check is performed. For example, in response to detecting the pulse, perform at least one status check. For example, at operation **630**, the processing logic performs an initial status check associated with dice operations being performed by the multiple dice at expiration of a polling delay period.

(81) Further, at operation **635**, additional status checks are performed. For example, the processing logic performs zero or more additional status checks associated with dice operations at a polling interval after the expiration of the polling delay period and before the pulse is deasserted. As with operation **540** (FIG. 5), if the pulse width is sufficiently longer than the polling delay period, the controller **115** performs at least one additional status check in response to reaching a polling interval period after the polling delay period.

(82) At operation **640**, a final status check is performed. For example, the processing logic performs a final status check of the dice operations in response to detecting the pulse being deasserted.

(83) At operation **650**, status checks are terminated. For example, the processing logic terminates performances of status checks while the status indicator signal remains deasserted. This default behavior of polling for status checks enables reducing congestion, and thus conserving bandwidth, across a communication bus or other interface between the controller **115** and the memory device(s) **130**. The method **600** can then loop back to operation **510** to monitor for pulse(s) on the status indicator signal.

(84) FIG. 7 illustrates an example machine of a computer system **700** within which a set of instructions, for causing the machine to perform any one or more of the methodologies discussed herein, can be executed. In some embodiments, the computer system **700** can correspond to a host system (e.g., the host system **120** of FIG. 1A) that includes, is coupled to, or utilizes a memory sub-system (e.g., the memory sub-system **110** of FIG. 1A) or can be used to perform the operations of a controller (e.g., to execute an operating system to perform operations corresponding to the status polling component **113** of FIG. 1A). In alternative embodiments, the machine can be connected (e.g., networked) to other machines in a LAN, an intranet, an extranet, and/or the Internet. The machine can operate in the capacity of a server or a client machine in client-server network environment, as a peer machine in a peer-to-peer (or distributed) network environment, or as a server or a client machine in a cloud computing infrastructure or environment.

(85) The machine can be a personal computer (PC), a tablet PC, a set-top box (STB), a Personal Digital Assistant (PDA), a cellular telephone, a web appliance, a server, a network router, a switch or bridge, or any machine capable of executing a set of instructions (sequential or otherwise) that specify actions to be taken by that machine. Further, while a single machine is illustrated, the term “machine” shall also be taken to include any collection of machines that individually or jointly execute a set (or multiple sets) of instructions to perform any one or more of the methodologies discussed herein.

(86) The example computer system **700** includes a processing device **702**, a main memory **704** (e.g., read-only memory (ROM), flash memory, dynamic random access memory (DRAM) such as synchronous DRAM (SDRAM) or Rambus DRAM (RDRAM), etc.), a static memory **710** (e.g., flash memory, static random access memory (SRAM), etc.), and a data storage system **718**, which communicate with each other via a bus **730**.

(87) Processing device **702** represents one or more general-purpose processing devices such as a microprocessor, a central processing unit, or the like. More particularly, the processing device can be a complex instruction set computing (CISC) microprocessor, reduced instruction set computing (RISC) microprocessor, very long instruction word (VLIW) microprocessor, or a processor implementing other instruction sets, or processors implementing a combination of instruction sets. Processing device **702** can also be one or more special-purpose processing devices such as an application specific integrated circuit (ASIC), a field programmable gate array (FPGA), a digital signal processor (DSP), network processor, or the like. The processing device **702** is configured to execute instructions **728** for performing the operations and steps discussed herein. The computer system **700** can further include a network interface device **712** to communicate over the network **720**.

(88) The data storage system **718** can include a machine-readable storage medium **724** (also known as a computer-readable storage medium) on which is stored one or more sets of instructions **728** or software embodying any one or more of the methodologies or functions described herein. The data storage system **718** can further include the local media controller **135**, cache, and page buffers. The instructions **728** can also reside, completely or at least partially, within the main memory **704** and/or within the processing device **702** during execution thereof by the computer system **700**, the main memory **704** and the processing device **702** also constituting machine-readable storage media. The machine-readable storage medium **724**, data storage system **718**, and/or main memory **704** can correspond to the memory sub-system **110** of FIG. **1A**.

(89) In one embodiment, the instructions **728** include instructions to implement functionality corresponding to the status polling component **113** of FIG. **1A**. While the machine-readable storage medium **724** is shown in an example embodiment to be a single medium, the term “machine-readable storage medium” or “non-transitory computer-readable storage medium” should be taken to include a single medium or multiple media that store the one or more sets of instructions. The term “machine-readable storage medium” shall also be taken to include any medium that is capable of storing or encoding a set of instructions for execution by the machine and that cause the machine to perform any one or more of the methodologies of the present disclosure. The term “machine-readable storage medium” shall accordingly be taken to include, but not be limited to, solid-state memories, optical media, and magnetic media.

(90) Some portions of the preceding detailed descriptions have been presented in terms of algorithms and symbolic representations of operations on data bits within a computer memory. These algorithmic descriptions and representations are the ways used by those skilled in the data processing arts to most effectively convey the substance of their work to others skilled in the art. An algorithm is here, and generally, conceived to be a self-consistent sequence of operations leading to a desired result. The operations are those requiring physical manipulations of physical quantities. Usually, though not necessarily, these quantities take the form of electrical or magnetic signals capable of being stored, combined, compared, and otherwise manipulated. It has proven convenient at times, principally for reasons of common usage, to refer to these signals as bits, values, elements, symbols, characters, terms, numbers, or the like.

(91) It should be borne in mind, however, that all of these and similar terms are to be associated with the appropriate physical quantities and are merely convenient labels applied to these quantities. The present disclosure can refer to the action and processes of a computer system, or similar electronic computing device, that manipulates and transforms data represented as physical (electronic) quantities within the computer system's registers and memories into other data

similarly represented as physical quantities within the computer system memories or registers or other such information storage systems.

(92) The present disclosure also relates to an apparatus for performing the operations herein. This apparatus can be specially constructed for the intended purposes, or it can include a general purpose computer selectively activated or reconfigured by a computer program stored in the computer. Such a computer program can be stored in a computer readable storage medium, such as, but not limited to, any type of disk including floppy disks, optical disks, CD-ROMs, and magnetic-optical disks, read-only memories (ROMs), random access memories (RAMs), EPROMs, EEPROMs, magnetic or optical cards, or any type of media suitable for storing electronic instructions, each coupled to a computer system bus.

(93) The algorithms and displays presented herein are not inherently related to any particular computer or other apparatus. Various general purpose systems can be used with programs in accordance with the teachings herein, or it can prove convenient to construct a more specialized apparatus to perform the method. The structure for a variety of these systems will appear as set forth in the description below. In addition, the present disclosure is not described with reference to any particular programming language. It will be appreciated that a variety of programming languages can be used to implement the teachings of the disclosure as described herein.

(94) The present disclosure can be provided as a computer program product, or software, that can include a machine-readable medium having stored thereon instructions, which can be used to program a computer system (or other electronic devices) to perform a process according to the present disclosure. A machine-readable medium includes any mechanism for storing information in a form readable by a machine (e.g., a computer). In some embodiments, a machine-readable (e.g., computer-readable) medium includes a machine (e.g., a computer) readable storage medium such as a read only memory ("ROM"), random access memory ("RAM"), magnetic disk storage media, optical storage media, flash memory devices, etc.

(95) In the foregoing specification, embodiments of the disclosure have been described with reference to specific example embodiments thereof. It will be evident that various modifications can be made thereto without departing from the broader spirit and scope of embodiments of the disclosure as set forth in the following claims. The specification and drawings are, accordingly, to be regarded in an illustrative sense rather than a restrictive sense.

Claims

1. A memory system comprising: a ready busy pin coupled with a plurality of dice; and a processing device coupled with the ready busy pin, the processing device to perform controller operations comprising: waiting to perform any status checks until after assertion of a pulse on a status indicator signal received from the ready busy pin; detecting the pulse being asserted is an extended pulse comprising at least a partial overlap of a first pulse asserted by a first die and a second pulse asserted by a second die of the plurality of dice; initiating a polling delay period in response to detecting assertion of the extended pulse, wherein the polling delay period is greater than a pulse width of the first pulse; and initiating a first status check of dice operations being performed by the plurality of dice in response to detecting expiration of the polling delay period.
2. The memory system of claim 1, further comprising the plurality of dice to cause assertion of pulses, including the extended pulse, over the status indicator signal.
3. The memory system of claim 1, further comprising a memory device comprising: the plurality of dice; a status input/output (I/O) pin coupled with the processing device; and control logic coupled with the status I/O pin, wherein the control logic is configured to transmit, to the processing device over the status I/O pin, a device status indicator with a status of the dice operations comprising one of an error status, a power event status, a security event status, or a temperature status.
4. The memory system of claim 1, wherein the operations further comprise initiating one or more

additional status checks of the dice operations at a polling interval after expiration of the polling delay period and before detecting the extended pulse being deasserted, wherein each polling interval is set to be greater than or equal to the pulse width of either of the first pulse or the second pulse.

5. The memory system of claim 1, wherein the operations further comprise: initiating a final status check of the dice operations in response to detecting the extended pulse being deasserted; and terminating, by the processing device, performances of status checks while the status indicator signal remains deasserted.

6. The memory system of claim 1, wherein the operations further comprise: receiving a second status indicator signal comprising a third pulse that is asserted by sensor hardware of a third die of the plurality of dice; and in response to detecting the third pulse, initiating a second status check of device operations being performed by one or more memory devices, which include the plurality of dice, at one of expiration of a second polling delay period after assertion of the second pulse or in response to detecting the third pulse being deasserted.

7. The memory system of claim 6, wherein the operation further comprise terminating performances of status checks while the second status indicator signal remains deasserted.

8. The memory system of claim 6, wherein the device operations comprise one of a suspend completion of a memory operation, a power event status, a security event status, or a temperature status associated with the one or more memory devices.

9. A memory system comprising: a memory device comprising a plurality of planes and a ready busy pin; and a processing device coupled with the ready busy pin, the processing device to perform controller operations comprising: receiving, over the ready busy pin, a status indicator signal comprising a first pulse asserted in association with a first plane and a second pulse asserted in association with a second plane of the plurality of planes, wherein the first pulse and the second pulse partially overlap to comprise an extended pulse; initiating a polling delay period in response to detecting assertion of the extended pulse, wherein the polling delay period is greater than a pulse width of the first pulse; and initiating a first status check of memory access operations being performed by the plurality of planes in response to detecting expiration of the polling delay period.

10. The memory system of claim 9, further comprising a memory array comprising a plurality of dice that form the plurality of planes.

11. The memory system of claim 9, further comprising a local media controller coupled with the plurality of planes and the ready busy pin, the local media controller comprising: a first processor coupled with the first plane of the plurality of planes, the first processor configured to detect completion of a first memory operation and assert the first pulse of the status indicator signal; and a second processor coupled with the second plane of the plurality of planes, the second processor configured to detect completion of a second memory operation that overlaps in time with the first memory operation and assert the second pulse of the status indicator signal.

12. The memory system of claim 9, wherein the controller operations further comprise: initiating a final status check of the memory access operations in response to detecting the extended pulse being deasserted; and terminating performances of status checks while the status indicator signal remains deasserted.

13. The memory system of claim 9, wherein the controller operations further comprise initiating one or more additional status checks of the memory access operations at a polling interval after expiration of the polling delay period and before detecting the extended pulse being deasserted.

14. The memory system of claim 9, wherein the memory access operations comprise one of a read operation, a program operation, an erase operation, or an error status.

15. A non-transitory computer-readable storage medium that stores instructions, which when executed by a processing device of a memory sub-system, perform operations comprising: waiting to perform any status checks until after assertion of a pulse on a status indicator signal received from a ready busy pin coupled with a plurality of dice; detecting the pulse being asserted is an

extended pulse comprising at least a partial overlap of a first pulse asserted by a first die and a second pulse asserted by a second die of the plurality of dice; initiating a polling delay period in response to detecting assertion of the extended pulse, wherein the polling delay period is greater than a pulse width of the first pulse; and initiating a first status check of dice operations being performed by the plurality of dice in response to detecting expiration of the polling delay period.

16. The non-transitory computer-readable storage medium of claim 15, wherein the operations further comprise initiating one or more additional status checks of the dice operations at a polling interval after expiration of the polling delay period and before detecting the extended pulse being deasserted, wherein each polling interval is set to be greater than or equal to the pulse width of either of the first pulse or the second pulse.

17. The non-transitory computer-readable storage medium of claim 15, wherein the operations further comprise: initiating a final status check of the dice operations in response to detecting the extended pulse being deasserted; and terminating, by the processing device, performances of status checks while the status indicator signal remains deasserted.

18. The non-transitory computer-readable storage medium of claim 15, wherein the operations further comprise: receiving a second status indicator signal comprising a third pulse that is asserted by sensor hardware of a third die of the plurality of dice; and in response to detecting the third pulse, initiating a second status check of device operations being performed by one or more memory devices, which include the plurality of dice, at one of expiration of a second polling delay period after assertion of the second pulse or in response to detecting the third pulse being deasserted.

19. The non-transitory computer-readable storage medium of claim 18, wherein the operations further comprise terminating performances of status checks while the second status indicator signal remains deasserted.

20. The non-transitory computer-readable storage medium of claim 18, wherein the device operations comprise one of a suspend completion of a memory operation, a power event status, a security event status, or a temperature status associated with the one or more memory devices.
