

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12403548
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Yokoyama; Jun et al.

Laser processing apparatus and laser processing method

Abstract

A laser processing apparatus includes a laser oscillator that oscillates processing laser light to be incident on a processing point on a processing surface of a workpiece, a coupling mirror that deflects or transmits the processing laser light and measurement light to be incident on the processing point toward the processing point, a measurement light deflection unit that changes an incident angle of the measurement light on the coupling mirror, a lens that concentrates the processing laser light and the measurement light on the processing point, a controller that controls the laser oscillator and the measurement light deflection unit, a measurement processor that measures a depth of a keyhole generated at the processing point by the processing laser light by using an optical interference signal based on an interference generated by an optical path difference between the measurement light reflected at the processing point and reference light, and a beam position measurement unit that measures positions of the processing laser light and the measurement light.

Inventors: Yokoyama; Jun (Osaka, JP), Urashima; Takashi (Osaka, JP), Takechi; Yohei (Osaka, JP)

Applicant: Panasonic Intellectual Property Management Co., Ltd. (Osaka, JP)

Family ID: 80112810

Assignee: PANASONIC INTELLECTUAL PROPERTY MANAGEMENT CO., LTD. (Osaka, JP)

Appl. No.: 17/378815

Filed: July 19, 2021

Prior Publication Data

Document Identifier	Publication Date
US 20220055147 A1	Feb. 24, 2022

Foreign Application Priority Data

Publication Classification

Int. Cl.: **B23K26/03** (20060101); **B23K26/082** (20140101); **G01B11/00** (20060101); **G02B19/00** (20060101); **G02B26/08** (20060101); **G02B26/10** (20060101)

U.S. Cl.:

CPC **B23K26/032** (20130101); **B23K26/082** (20151001); **G01B11/002** (20130101); **G02B19/0014** (20130101); **G02B19/009** (20130101); **G02B26/0816** (20130101); **G02B26/105** (20130101);

Field of Classification Search

CPC: B23K (26/032); B23K (26/082); G01B (11/002); G02B (19/0014); G02B (19/009); G02B (26/0816); G02B (26/105)

USPC: 219/121.85

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
4532402	12/1984	Overbeck	219/121.79	G02B 26/101
5045679	12/1990	Suzuki	430/327	B23K 26/043
5227910	12/1992	Khattak	359/209.1	G02B 26/108
5463202	12/1994	Kurosawa	372/29.014	B23K 26/04
5763853	12/1997	Shimomura	219/121.72	B23K 26/032
5864114	12/1998	Fukuda	219/121.69	B23K 26/032
5910260	12/1998	Gerber	219/121.72	B23K 26/082
6163010	12/1999	Kobsa	219/121.84	B23K 26/0648
6215094	12/2000	Dausinger	219/121.62	B23K 26/40
6791057	12/2003	Kratzsch	219/121.62	B23K 26/24
7577285	12/2008	Schwarz	348/90	B23K 9/0956
7989730	12/2010	Regaard	219/121.63	B23K 26/04
8822875	12/2013	Webster	219/121.13	G01B 9/0203
9757817	12/2016	Webster	N/A	G01B 9/02091
9802271	12/2016	Stork Genannt Wersborg	N/A	B23K 26/042
10578428	12/2019	Strebel	N/A	G01B 9/02091
10967452	12/2020	Moser	N/A	B23K 15/0013
11511370	12/2021	Sakurai	N/A	G01B 11/02
11964339	12/2023	Sakai	N/A	B23K 26/064
11999008	12/2023	Sakai	N/A	B23K 31/125
12053840	12/2023	Regaard	N/A	B23K 31/125
2004/0007563	12/2003	Hastings	219/121.69	B23K 26/0648
2004/0251243	12/2003	Lizotte	219/121.73	B23K 26/0676

2008/0217312	12/2007	Tokura	219/121.72	B81C 1/00896
2012/0074105	12/2011	Okamoto	219/121.72	B23K 26/146
2012/0285936	12/2011	Urashima	219/121.63	G01B 9/02091
2012/0318775	12/2011	Schwarz	356/606	B23K 26/032
2013/0120740	12/2012	Schonleber	356/72	G01B 9/02063
2013/0175243	12/2012	Wang	219/121.7	B23K 26/382
2014/0144895	12/2013	Stork Genannt Wersborg	219/121.75	B23K 26/042
2014/0153085	12/2013	Dobbie	N/A	N/A
2014/0268145	12/2013	Lane	356/627	G01B 11/04
2015/0014889	12/2014	Goya	219/121.72	B23K 26/0652
2015/0076125	12/2014	Toyosawa	219/121.79	B23K 26/08
2015/0352666	12/2014	Fujita	219/121.61	B23K 26/046
2016/0008920	12/2015	Goya	219/121.61	B23K 26/36
2016/0039045	12/2015	Webster	356/450	G01B 9/02091
2016/0059347	12/2015	Kogel-Hollacher	219/121.73	B23K 26/082
2016/0059350	12/2015	Schoenleber	219/121.81	B23K 26/04
2016/0114434	12/2015	Regaard	219/121.81	B23K 26/046
2016/0193692	12/2015	Regaard	219/121.62	B23K 31/125
2016/0202045	12/2015	Schönleber	356/497	B23K 26/046
2017/0282293	12/2016	Miyata	N/A	B23K 26/048
2017/0326669	12/2016	Moser	N/A	B23K 15/0013
2019/0041196	12/2018	Strebel	N/A	G01B 11/22
2019/0091798	12/2018	Schönleber	N/A	B23K 26/21
2019/0143458	12/2018	Strebel	219/121.64	B23K 26/032
2019/0299331	12/2018	Moser	N/A	B23K 26/064
2020/0023461	12/2019	Galbraith	N/A	B23K 26/032
2020/0033452	12/2019	Takagawa	N/A	G02B 26/0816
2020/0038954	12/2019	Regulin	N/A	B23K 26/147
2020/0041249	12/2019	Strebel	N/A	B23K 26/032
2020/0055141	12/2019	Schürmann	N/A	B23K 26/048
2020/0055142	12/2019	Schürmann	N/A	B23K 26/21
2020/0198049	12/2019	Yokoyama	N/A	B23K 31/003
2020/0198051	12/2019	Sauer	N/A	B23K 26/042
2020/0361038	12/2019	Takechi	N/A	B23K 26/50
2020/0376591	12/2019	Sakai	N/A	G01B 11/22
2021/0031298	12/2020	Sakai	N/A	G01B 9/02
2021/0053149	12/2020	Takechi	N/A	B23K 26/0665
2021/0060695	12/2020	Yokoyama	N/A	B23K 26/21
2021/0323088	12/2020	Yokoyama	N/A	B23K 26/032
2022/0290973	12/2021	Stambke	N/A	B23K 26/082

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2925039	12/2014	CA	N/A
102015012565	12/2015	DE	N/A
7-276069	12/1994	JP	N/A
2002-035981	12/2001	JP	N/A
2002-509032	12/2001	JP	N/A
2006-015373	12/2005	JP	N/A

2013-501964	12/2012	JP	N/A
2016-538134	12/2015	JP	N/A
2019-534788	12/2018	JP	N/A
2011/059536	12/2010	WO	N/A
2012/173008	12/2011	WO	N/A

Primary Examiner: Chou; Jimmy

Attorney, Agent or Firm: Rimon P.C.

Background/Summary

BACKGROUND

1. Technical Field

(1) The present disclosure relates to a laser processing apparatus and a laser processing method.

2. Description of the Related Art

(2) Published Japanese Translation No. 2013-501964 of the PCT International Publication discloses a laser processing apparatus. The laser processing apparatus measures a depth of a keyhole generated during metal processing by laser light by using an optical coherence tomography (OCT) technology that visualizes an internal structure of a sample by using an optical interferometer. The depth of the keyhole can be obtained based on an interference signal according to an optical path difference between measurement light (reflection light) reflected from a bottom surface of the keyhole and light (reference light) on a reference arm side.

SUMMARY

(3) A laser processing apparatus according to one aspect of the present disclosure includes a laser oscillator that oscillates processing laser light to be incident on a processing point on a processing surface of a workpiece, a coupling mirror that deflects or transmits the processing laser light and measurement light to be incident on the processing point toward the processing point, a measurement light deflection unit that changes an incident angle of the measurement light on the coupling mirror, a lens that concentrates the processing laser light and the measurement light on the processing point, a controller that controls the laser oscillator and the measurement light deflection unit, a measurement processor that measures a depth of a keyhole generated at the processing point by the processing laser light by using an optical interference signal based on an interference generated by an optical path difference between the measurement light reflected at the processing point and reference light, and a beam position measurement unit that measures positions of the processing laser light and the measurement light.

(4) A laser processing method according to one aspect of the present disclosure is performed by a laser processing apparatus including a laser light emitting unit that emits laser light to a workpiece and a measurement light emitting unit that emits measurement light for measuring an irradiation position of the laser light on the workpiece, and includes matching the irradiation position of the laser light and an irradiation position of the measurement light on the workpiece each other.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a view schematically illustrating a configuration of a laser processing apparatus according to a first exemplary embodiment of the present disclosure;

(2) FIG. 2 is a view schematically illustrating the laser processing apparatus in a state where a first

mirror is operated from an original position;

(3) FIG. 3 is a view schematically illustrating the laser processing apparatus in a state where deviations in arrival positions of processing laser light and measurement light due to magnification chromatic aberration are corrected;

(4) FIG. 4 is a diagram schematically illustrating tracks of each of the processing laser light and the measurement light on a processing surface when a surface (processing surface) of a workpiece is scanned in a grid shape by operating only the first mirror without operating a measurement light deflection unit;

(5) FIG. 5 is a view illustrating a configuration example of a beam position measurement unit used for calculating a correction amount at a processing light grid point;

(6) FIG. 6 is a flowchart illustrating a method of calculating the correction amount at the processing light grid point;

(7) FIG. 7 is a view illustrating a configuration example of the beam position measurement unit including two position measurement mirrors;

(8) FIG. 8 is a flowchart illustrating a method of generating correction number table data;

(9) FIG. 9 is a diagram illustrating an example of data items included in corrected processing data;

(10) FIG. 10 is a flowchart illustrating a method of generating the corrected processing data;

(11) FIG. 11 is a diagram illustrating a correction number table of a processing point position schematically illustrating a configuration of correction number table data of a processing point position;

(12) FIG. 12 is a flowchart illustrating a method of setting the correction amount;

(13) FIG. 13 is a diagram illustrating a relationship between a scan angle and a correction data point therearound when a scan angle set by a user as processing data does not match a correction number table scan angle of any of data points in the correction number table of the processing point position illustrated in FIG. 11;

(14) FIG. 14 is a flowchart illustrating a laser processing method performed by the laser processing apparatus according to the first exemplary embodiment of the present disclosure;

(15) FIG. 15 is a flowchart illustrating a method of measuring a depth of a keyhole;

(16) FIG. 16 is a diagram illustrating tracks of the processing laser light and the measurement light on the processing surface in a state where an influence of magnification chromatic aberration is corrected by an operation of the measurement light deflection unit;

(17) FIG. 17 is a view schematically illustrating a configuration of a laser processing apparatus according to a first modification example of the present disclosure;

(18) FIG. 18 is a view schematically illustrating a configuration of a laser processing apparatus according to a second modification example of the present disclosure;

(19) FIG. 19 is a schematic view illustrating a laser processing apparatus according to a second exemplary embodiment of the present disclosure;

(20) FIG. 20 is a view illustrating a state when the beam position measurement unit derives a relative position of an optical axis of measurement light with respect to an optical axis of processing light;

(21) FIG. 21 is a flowchart of a program executed by a control device;

(22) FIG. 22 is a diagram illustrating an irradiation position of the processing light and an irradiation position of the measurement light of an imaging element during a first optical adjustment;

(23) FIG. 23 is a diagram illustrating an irradiation position of the processing light and an irradiation position of the measurement light of the imaging element during second and subsequent optical adjustments;

(24) FIG. 24 is a view illustrating a state where the second and subsequent optical adjustments are performed by a laser processing apparatus according to a modification example of the second exemplary embodiment of the present disclosure; and

(25) FIG. 25 is a view illustrating a state where first and subsequent optical adjustments are performed by the laser processing apparatus according to a modification example of the second exemplary embodiment of the present disclosure.

DETAILED DESCRIPTIONS

(26) Preferred exemplary embodiments of the present disclosure will be described in detail below with reference to the accompanying drawings. In the present specification and the drawings, components having substantially the same functions are designated by the same reference numerals, and thus, redundant descriptions thereof are omitted. In FIG. 1 and subsequent figures, an x-axis direction, a y-axis direction, and a z-axis direction respectively represent a direction parallel to an x-axis, a direction parallel to a y-axis, and a direction parallel to a z-axis. The x-axis direction and the y-axis direction are orthogonal to each other. The x-axis direction and the z-axis direction are orthogonal to each other. The y-axis direction and the z-axis direction are orthogonal to each other. An xy plane represents a virtual plane parallel to the x-axis direction and the y-axis direction. An xz plane represents a virtual plane parallel to the x-axis direction and the z-axis direction. A yz plane represents a virtual plane parallel to the y-axis direction and the z-axis direction. Further, in the x-axis direction in FIG. 1 and subsequent figures, a direction indicated by an arrow is assumed to be a positive x-axis direction, and an opposite direction thereof is assumed to be a negative x-axis direction. Further, in the y-axis direction in FIG. 1 and subsequent figures, a direction indicated by an arrow is assumed to be a positive y-axis direction, and an opposite direction thereof is assumed to be a negative y-axis direction. Further, in the z-axis direction in FIG. 1 and subsequent figures, a direction indicated by an arrow is assumed to be a positive z-axis direction, and an opposite direction thereof is assumed to be a negative z-axis direction. The z-axis direction is the same in, for example, a vertical direction or an up-and-down direction, and the x-axis direction and the y-axis direction are the same in, for example, a horizontal direction or a left-to-right direction.

First Exemplary Embodiment

(27) Recently, a laser processing apparatus in which a galvano mirror is combined with an f θ lens has been known. The galvano mirror can finely control a direction in which laser light is reflected. The f θ lens concentrates laser light on a processing point on a surface of a workpiece. However, when the method of measuring a depth of a keyhole disclosed in Japanese Patent Application No. 2013-501964 is applied to a laser processing apparatus in which a galvano mirror is combined with an f θ lens, there are following problems. That is, since wavelengths of processing laser light and measurement light are different from each other and the f θ lens has characteristics of causing chromatic aberration, there are problems that the processing laser light and the measurement light deviate from each other on a surface of a workpiece and a depth of a keyhole cannot be accurately measured.

(28) An object of one aspect of the present disclosure is to provide a laser processing apparatus and a laser processing method capable of accurately measuring a depth of a keyhole.

(29) Non-limiting examples of the present disclosure contribute to a provision of a laser processing apparatus and a laser processing method capable of accurately measuring a depth of a keyhole.

(30) A laser processing apparatus according to one example of the present disclosure includes a laser oscillator that oscillates processing laser light to be incident on a processing point on a processing surface of a workpiece, a coupling mirror that deflects or transmits the processing laser light and measurement light to be incident on the processing point toward the processing point, a measurement light deflection unit that changes an incident angle of the measurement light on the coupling mirror, a lens that concentrates the processing laser light and the measurement light on the processing point, a controller that controls the laser oscillator and the measurement light deflection unit, a measurement processor that measures a depth of a keyhole generated at the processing point by the processing laser light by using an optical interference signal based on an interference generated by an optical path difference between the measurement light reflected at the processing

point and reference light, and a beam position measurement unit that measures positions of the processing laser light and the measurement light.

(31) A laser processing method according to one example of the present disclosure is a laser processing method performed by a laser processing apparatus which includes a first mirror that changes travel directions of processing laser light and measurement light, a measurement light deflection unit that changes an incident angle of the measurement light on the first mirror, a lens that concentrates the processing laser light and the measurement light on a processing point of a processing surface of a workpiece, and measures a depth of a keyhole generated at the processing point by applying the processing laser light thereto, and the method includes setting a target position on the processing surface, setting a first instruction value indicating an operation amount of the first mirror by which the processing laser light reaches the target position, obtaining a second instruction value indicating an operation amount of the measurement light deflection unit based on positions of the processing laser light and the measurement light measured by a beam position measurement unit for measuring the positions of the processing laser light and the measurement light, and controlling the laser oscillator for oscillating the processing laser light, the first mirror, and the measurement light deflection unit based on processing data including the first instruction value and the second instruction value.

(32) According to one example of the present disclosure, a laser processing apparatus and a laser processing method capable of accurately measuring a depth of a keyhole can be constructed.

(33) Further advantages and effects of one example of the present disclosure will be apparent from the specification and drawings. Such advantages and/or effects are respectively provided by some exemplary embodiments and characteristics described in the specification and drawings, but not all need to be provided in order to obtain one or more identical characteristics.

(34) Processing data may include a first instruction value indicating an operation amount of a first mirror and a second instruction value indicating an operation amount of a measurement light deflection unit. A beam position measurement unit may include a position measurement mirror that reflects processing laser light and measurement light passing through a lens, and a two-dimensional imaging element that measures positions of the processing laser light and the measurement light reflected by the position measurement mirror. A controller sets a target position on a processing surface, sets the first instruction value to a target position at which the processing laser light reaches, and calculates the second instruction value based on positions of the processing laser light and the measurement light measured by the two-dimensional imaging element.

(35) The position measurement mirror may be set to a reflectance of a wavelength of the processing laser light that becomes power by which the processing laser light can be incident on the two-dimensional imaging element. The two-dimensional imaging element may be installed at a position where an optical path length of the two-dimensional imaging element from a lens matches an optical path length of a processing point from the lens.

(36) The position measurement mirror may be configured by a plurality of mirrors.

(37) The position measurement mirror may have a reflectance of a wavelength of the processing laser light, which is 0.1% or less.

(38) The controller may set a grid shape pattern on a processing surface and set a grid point of the grid shape pattern at a target position.

(39) Structure of Laser Processing Apparatus 1

(40) A configuration of laser processing apparatus 1 according to a first exemplary embodiment of the present disclosure will be described with reference to FIG. 1. FIG. 1 is a view schematically illustrating the configuration of laser processing apparatus 1 according to the first exemplary embodiment of the present disclosure.

(41) Laser processing apparatus 1 includes processing head 2, optical interferometer 3, measurement processor 4, laser oscillator 5, controller 6, first driver 7, and second driver 8.

(42) Optical interferometer 3 emits measurement light 15 for OCT measurement. Measurement

light **15** emitted from optical interferometer **3** is input to processing head **2** via measurement light inlet **9**. Measurement light inlet **9** is installed on measurement light deflection unit **17**. Measurement light inlet **9** is installed, on processing head **2**, at a position where measurement light **15** can be introduced into measurement light deflection unit **17**.

(43) Laser oscillator **5** oscillates processing laser light **11** for laser processing. Processing laser light **11** oscillated by laser oscillator **5** is input to processing head **2** via processing light inlet **10**.

(44) Processing laser light **11** input to processing head **2** transmits through dichroic mirror **12**, is reflected by first mirror **13**, transmits through lens **14**, and is concentrated on processing surface **19** which is a surface of workpiece **18**.

(45) Thereby, processing point **20** of workpiece **18** is laser-processed. At this time, processing point **20** to which processing laser light **11** is applied melts, and thereby, molten pool **21** is formed in workpiece **18**.

(46) Further, a molten metal evaporates from molten pool **21**, and keyhole **22** is formed in workpiece **18** due to a pressure of steam generated at the time of evaporation.

(47) Measurement light **15** input from measurement light inlet **9** to processing head **2** is converted into parallel light by collimating lens **16** and is reflected by measurement light deflection unit **17**. Thereafter, measurement light **15** is reflected by dichroic mirror **12**, is reflected by first mirror **13**, transmits through lens **14**, and is concentrated on processing point **20** on processing surface **19** of workpiece **18**. Dichroic mirror **12** is a coupling mirror that couples measurement light **15** to processing laser light **11**.

(48) Measurement light **15** is reflected by a bottom surface of keyhole **22** and reaches optical interferometer **3** by traveling back along a propagation path. Optical interferometer **3** generates an optical interference signal due to an optical interference between input measurement light **15** and reference light (not illustrated). The reference light is light applied to a reference mirror (not illustrated) which is a reference surface, in the light emitted from a light source (not illustrated) of optical interferometer **3**.

(49) Measurement processor **4** measures a depth of keyhole **22**, that is, a penetration depth of processing point **20**, based on the optical interference signal. The penetration depth means a distance between the highest point of a melted portion of workpiece **18** and processing surface **19**.

(50) A wavelength (first wavelength) of processing laser light **11** is different from a wavelength (second wavelength) of measurement light **15**. Dichroic mirror **12** has characteristics of transmitting light of the first wavelength therethrough and reflecting light of the second wavelength.

(51) For example, when a YAG laser or a fiber laser is used as processing laser light **11**, a wavelength of processing laser light **11** is 1064 nm. Further, for example, when an OCT light source is used as measurement light **15**, a wavelength of measurement light **15** is 1300 nm.

(52) First mirror **13** and measurement light deflection unit **17** are movable mirrors that can perform a rotational operation in two or more axes. First mirror **13** and measurement light deflection unit **17** are, for example, galvano mirrors.

(53) First mirror **13** is connected to controller **6** via first driver **7**. Measurement light deflection unit **17** is connected to controller **6** via second driver **8**.

(54) First driver **7** operates first mirror **13** based on an instruction from controller **6**. Second driver **8** operates measurement light deflection unit **17** based on an instruction from controller **6**.

(55) Controller **6** includes memory **31**. Memory **31** stores processing data for performing desirable processing for workpiece **18** and correction number table data. Details of the correction number table data will be described below.

(56) FIG. **1** illustrates that each of first mirror **13** and measurement light deflection unit **17** performs only a rotational operation about a rotation axis extending in the y-axis direction as an example. The rotational operation is represented by a dashed rectangle line and both arrow lines in the figure.

(57) Each of first mirror **13** and measurement light deflection unit **17** can be configured to perform a rotational operation in two or more axes. With this configuration, each of first mirror **13** and measurement light deflection unit **17** can also perform, for example, a rotational operation about a rotation axis extending in the x-axis direction.

(58) Hereinafter, for the sake of simple description, a case where each of first mirror **13** and measurement light deflection unit **17** performs a rotational operation about a rotation axis extending in the y-axis direction will be described.

(59) When measurement light deflection unit **17** is in an original position, measurement optical axis **23** of measurement light **15** matches processing optical axis **24** of processing laser light **11** after being reflected by dichroic mirror **12**.

(60) Further, when first mirror **13** is at the original position, processing optical axis **24** of processing laser light **11** matches lens optical axis **25** which is the center of lens **14** when transmitting through lens **14** after being reflected by first mirror **13**.

(61) In the following description, a position (may be referred to as an irradiation position) in which processing laser light **11** and measurement light **15** transmitting through the center of lens **14** reach processing surface **19** of workpiece **18** is referred to as “processing original point **26**” (see FIG. 2).

(62) The original positions of each of first mirror **13** and measurement light deflection unit **17** are the same as positions in which processing laser light **11** and measurement light **15** transmit through the center of lens **14**.

(63) Lens **14** concentrates processing laser light **11** and measurement light **15** on processing point **20**. Lens **14** is, for example, an f θ lens.

(64) First mirror **13** and lens **14** configure a general optical scan system including a galvano mirror and an f θ lens.

(65) Therefore, an arrival position of processing laser light **11** on processing surface **19** can be controlled by rotating first mirror **13** from the original position by a predetermined angle.

(66) Hereinafter, the angle at which first mirror **13** is rotated from the original position is referred to as an “operation amount of first mirror **13**”.

(67) The operation amount of first mirror **13** for applying processing laser light **11** to desirable processing point **20** can be set uniquely when a positional relationship of each optical member configuring processing head **2** and a distance from lens **14** to processing surface **19** are determined.

(68) The distance from lens **14** to processing surface **19** is preferably set to a distance at which a focal position where processing laser light **11** is most concentrated and processing surface **19** match each other such that processing performed by processing laser light **11** is performed most efficiently. However, the distance from lens **14** to processing surface **19** is not limited thereto and may be determined to be any distance according to a processing utility.

(69) By changing the operation amount of first mirror **13** according to a predetermined operation schedule, the position of processing point **20** can be scanned on processing surface **19**.

(70) Further, by performing switching of on and off of laser oscillator **5** under the control of controller **6**, any position on processing surface **19** can be laser-processed in any pattern in a scannable range of processing laser light **11**.

(71) Influence of Chromatic Aberration

(72) Next, an influence of chromatic aberration will be described with reference to FIG. 2. FIG. 2 is a view schematically illustrating laser processing apparatus **1** in a state where first mirror **13** is operated from an original position. In FIG. 2, measurement light deflection unit **17** is assumed to be at the original position.

(73) As illustrated in FIG. 2, processing laser light **11** and measurement light **15** reflected by first mirror **13** travel on the same optical axis until reaching lens **14**. However, after transmitting through lens **14**, a deviation occurs between processing laser light **11** and measurement light **15** in a travel direction.

(74) That is, as illustrated in FIG. 2, a position of processing optical axis **24a** which is an optical

axis of processing laser light **11** is deviated from a position of measurement optical axis **23a** which is an optical axis of measurement light **15**. Therefore, measurement light **15** reaches a position different from a position of processing point **20**.

(75) This is due to a chromatic aberration of lens **14**. The chromatic aberration is an aberration that occurs because a general optical material including lens **14** has a property which is changed in refractive index depending on a wavelength of light.

(76) The chromatic aberration includes two types of aberrations, which are an axial chromatic aberration and a magnification chromatic aberration. The axial chromatic aberration indicates a property that a focal position of the lens is changed depending on a wavelength of light.

(77) Meanwhile, the magnification chromatic aberration indicates a property that an image height on a focal surface is changed depending on the wavelength of light.

(78) A deviation between a travel direction of processing laser light **11** (processing optical axis **24a**) transmitted through lens **14** and a travel direction of measurement light **15** (measurement optical axis **23a**) which is illustrated in FIG. **2** is caused by the above-described magnification chromatic aberration.

(79) In laser processing apparatus **1** according to the present exemplary embodiment, the above-described axial chromatic aberration is also generated at the same time. However, the deviation between the travel direction of processing laser light **11** and the travel direction of measurement light **15** due to the axial chromatic aberration can be reduced as follows. That is, a distance between collimating lens **16** and measurement light inlet **9** may be adjusted, and measurement light **15** immediately after transmitting through collimating lens **16** may be slightly changed to a divergence state or a convergence state from a state of parallel light.

(80) In FIG. **2**, a distance from a position where measurement light **15** reaches processing surface **19** to processing original point **26** is greater than a distance from a position where processing laser light **11** reaches processing surface **19** to processing original point **26**.

(81) However, a distance of the former can be smaller than a distance of the latter due to a lens configuration of lens **14** and a magnitude relationship between wavelengths of processing laser light **11** and measurement light **15**. Generally, light having a long wavelength reaches a position farther from processing original point **26** than light having a short wavelength.

(82) A method of correcting a magnification chromatic aberration includes, for example, a method of adding a property of an achromatic lens to lens **14**. However, when lens **14** is assumed to have both a property of an f θ lens and a property of an achromatic lens, a highly advanced optical design technology is required, and a design of lens **14** requires a great deal of time and cost.

(83) Therefore, in the present exemplary embodiment, the magnification chromatic aberration is corrected at a low cost by operating measurement light deflection unit **17** as described below. In the following description, a deflection unit that changes an angle of measurement optical axis **23** is referred to as a “measurement light deflection unit”. Measurement light deflection unit **17** according to the present exemplary embodiment is an example of the measurement light deflection unit.

(84) Method of Correcting Magnification Chromatic Aberration

(85) Next, a method of correcting a magnification chromatic aberration will be described with reference to FIG. **3**. FIG. **3** is a view schematically illustrating laser processing apparatus **1** in a state where deviations in arrival positions of processing laser light **11** and measurement light **15** due to the magnification chromatic aberration are corrected.

(86) In FIG. **3**, measurement light deflection unit **17** is operated by a predetermined operation amount (may be called an operation angle) from an original position. Thereby, as illustrated in FIG. **3**, processing optical axis **24** of processing laser light **11** and measurement optical axis **23** of measurement light **15** are not disposed on the same axis while reaching lens **14** from dichroic mirror **12**.

(87) However, processing laser light **11** and measurement light **15** each reach the same position on

processing surface **19**, that is, processing point **20** after transmitting through lens **14**.

(88) In FIG. **3**, processing optical axis **24a** of processing laser light **11** passes through the same position as processing optical axis **24a** illustrated in FIG. **2**. Meanwhile, in FIG. **3**, measurement optical axis **23b** of measurement light **15** corrected by an operation of measurement light deflection unit **17** passes through a position different from measurement optical axis **23a** illustrated in FIG. **2**.

(89) The operation amount (that is, an angle by which measurement light deflection unit **17** is rotated from an original position) of measurement light deflection unit **17** is associated one-to-one with the operation amount of first mirror **13**.

(90) Since the operation amount of first mirror **13** is uniquely determined by the position of processing point **20**, the operation amount of measurement light deflection unit **17** is also uniquely determined by the position of processing point **20**.

(91) In the following, an operation amount of measurement light deflection unit **17** will be referred to as a “correction amount”.

(92) Relationship Between Correction Amount and Scan Angle

(93) Next, the relationship between the correction amount and the scan angle will be described.

(94) lens **14** which is an $f\theta$ lens has a relationship of $h=f\theta$ when a focal length of lens **14** is referred to as f , an angle of light incident on lens **14** from lens optical axis **25** is referred to as θ , and a distance (hereinafter referred to as an image height) from an optical axis (lens optical axis **25**) on an image surface (processing surface **19**) of a light beam transmitting through lens **14** is referred to as h .

(95) As described above, first mirror **13** has two axes that perform a rotational operation. It is assumed that the two axes are the x-axis and the y-axis, an angle of an x-axis component from lens optical axis **25** of the light reflected by first mirror **13** is referred to as θ_x , and an angle of a y-axis component from the same lens optical axis **25** is referred to as θ_y .

(96) When image heights in the x and y directions on the image surface of the light beam transmitting through lens **14** are respectively referred to as x and y , a relationship of $x=f\theta_x$ and $y=f\theta_y$ is established.

(97) Thus, when a position where processing laser light **11** reaches processing surface **19** is referred to as (x, y) , $(x, y)=(f\theta_x, f\theta_y)$.

(98) Further, an emission angle of light reflected from mirror **13** when the light is incident on mirror **13** changes by an angle amount twice the operation amount of first mirror **13**.

(99) Therefore, when the operation amount of first mirror **13** is referred to as (ϕ_x, ϕ_y) , a relationship of $(2\phi_x, 2\phi_y)=(\theta_x, \theta_y)$ is established. In the following description, the operation amounts (ϕ_x, ϕ_y) of first mirror **13** are referred to as “scan angles”.

(100) As such, when the scan angles (ϕ_x, ϕ_y) of first mirror **13** are determined, laser processing apparatus **1** according to the present exemplary embodiment also determines an arrival position of processing laser light **11** on processing surface **19**, that is, the position (x, y) of processing point **20**.

(101) As described above, the scan angle is uniquely determined by the position of processing point **20**, and likewise, a correction amount is also uniquely determined by the position of processing point **20**.

(102) Therefore, data (correction number table data) for correcting a deviation of measurement light **15** due to a magnification chromatic aberration is previously calculated, and laser processing apparatus **1** according to the present exemplary embodiment operates measurement light deflection unit **17** by the correction amount corresponding to the position of processing point **20** by using the correction number table data when processing workpiece **18**. The correction number table data represents a corresponding relationship between a scan angle and a correction amount for each processing point **20**.

(103) Details of Correction Number Table Data

(104) Hereinafter, tracks of each of processing laser light **11** and measurement light **15** on processing surface **19**, which are the premise of calculating the correction amount, will be

described with reference to FIG. 4.

(105) FIG. 4 is a diagram schematically illustrating tracks of each of processing laser light **11** and measurement light **15** on processing surface **19** when a surface (processing surface **19**) of workpiece **18** is scanned in a grid shape by operating only first mirror **13** without operating measurement light deflection unit **17**.

(106) FIG. 4 illustrates a state where processing surface **19** is viewed from lens **14** side. An orthogonal grid shape pattern of a solid line in FIG. 4 represents a track (processing light track **28**) of processing laser light **11**. An orthogonal grid shape pattern of a dashed line in FIG. 4 represents a track (measurement light track **27**) of measurement light **15**.

(107) The orthogonal grid shape patterns are tracks when a surface (processing surface **19**) of workpiece **18** is scanned in a grid shape by operating only first mirror **13** without operating measurement light deflection unit **17**.

(108) In the example illustrated in FIG. 4, measurement light deflection unit **17** does not operate, and thereby, a magnification chromatic aberration is not corrected. Thus, in the vicinity of processing original point **26** illustrated in FIGS. 1 to 3, tracks of each of processing laser light **11** and measurement light **15** match each other, but a deviation between both light increases as a distance from processing original point **26** increases.

(109) Thereby, processing light track **28** draws an orthogonal grid shape pattern without distortion, while measurement light track **27** draws a distorted pincushion type track.

(110) A distorted shape of measurement light track **27** illustrated in FIG. 4 can be changed according to optical characteristics of lens **14**.

(111) Further, a deviation amount of a position corresponding to each of processing light track **28** and measurement light track **27** also depends on optical characteristics and an optical design of lens **14** likewise.

(112) In a general example, a commercially available f θ lens having a focal length of 250 mm and a processing surface region of approximately 200 mm in diameter has a deviation of 0.2 mm to 0.4 mm that occurs in the vicinity of an outermost circumference of the processing surface region.

(113) In contrast to this, a diameter of keyhole **22** (for example, see FIG. 1) generated by applying processing laser light **11** to processing point **20** is approximately as small as 0.03 mm to 0.2 mm, although the diameter depends on power and quality of the processing laser light.

(114) Therefore, measurement light **15** does not reach a bottom surface of keyhole **22** due to a positional deviation between processing laser light **11** and measurement light **15** caused by a chromatic aberration of lens **14**, and a correct penetration depth cannot be measured.

(115) FIG. 4 illustrates an orthogonal grid shape pattern of 4×4 squares at equal intervals, but a shape of the grid shape pattern is not limited thereto.

(116) For example, the number of squares of the orthogonal grid shape pattern may be increased, or an interval between grids in a region requiring particularly high accuracy may be reduced in relation to magnification chromatic aberration characteristic of the f θ lens.

(117) Further, a radial grid shape pattern may be set instead of the orthogonal grid shape pattern. However, in the present exemplary embodiment, the correction amount is set on two axes of the x-axis and the y-axis, and thus, the orthogonal grid shape pattern is more preferable.

(118) Comparing processing light track **28** with measurement light track **27** illustrated in FIG. 4, it can be seen that a deviation occurs in respective corresponding grid points in the respective orthogonal grid shape patterns. That is, it can be seen that there is a deviation between processing light grid point **30** at a specific location on processing light track **28** and corresponding measurement light grid point **29** of measurement light track **27**.

(119) In order to generate the correction number table data, the correction amount needs to be calculated (grid point of the grid shape pattern is set to a target position) such that one processing light grid point **30** at the specific location on processing light track **28** and corresponding measurement light grid point **29** of measurement light track **27** match each other.

(120) Method of Calculating Correction Amount

(121) Next, a method of calculating a correction amount at processing light grid point **30** will be described. FIG. **5** is a view illustrating a configuration example of beam position measurement unit **38** used for calculating the correction amount at processing light grid point **30**.

(122) Beam position measurement unit **38** is installed between lens **14** and workpiece **18**. Beam position measurement unit **38** includes position measurement mirror **39**, two-dimensional imaging element **40**, and beam terminator **41**.

(123) Position measurement mirror **39** has a function of attenuating power of processing laser light **11**, divides light having a wavelength of processing laser light **11** into reflection light and transmission light, and has characteristics that reflect light having a wavelength of measurement light **15**.

(124) A reflectance of the wavelength of processing laser light **11** of position measurement mirror **39** is set such that power of reflected processing laser light **11** is approximately the same as power of reflected measurement light **15**.

(125) For example, when a fiber laser having a rated output of 1 kW or more to be used in general processing is selected for processing laser light **11**, minimum power that can be output by processing laser light **11** is approximately 100 W.

(126) In contrast to this, when an OCT light source is used as measurement light **15**, an output is several tens of mW. Therefore, in order to reduce an output of processing laser light **11** of 100 W to the same order (several tens of mW) as measurement light **15** of several tens of mW, the reflectance of wavelength of processing laser light **11** of position measurement mirror **39** is preferably set to 0.1% or less.

(127) Meanwhile, measurement light **15** does not need to be attenuated, and thus, the reflectance of the wavelength of measurement light **15** of position measurement mirror **39** is preferably set to 90% or more.

(128) Two-dimensional imaging element **40** has a function of measuring positions of processing laser light **11** and measurement light **15**. Two-dimensional imaging element **40** may be any sensor as long as the sensor has sensitivity to wavelengths of processing laser light **11** and measurement light **15**, and a commercially available industrial camera including an element such as a charge-coupled device (CCD), a complementary metal oxide-semiconductor (CMOS), or indium gallium arsenide (InGaAs), a two-dimensional beam profiler, or the like can be used therefor.

(129) Beam terminator **41** has a function of terminating processing laser light **11** transmitting through position measurement mirror **39**.

(130) Processing laser light **11** and measurement light **15** transmitting through lens **14** are divided into processing laser light **11a** and measurement light **15a** that are reflected by position measurement mirror **39** and processing laser light **11b** that transmits through position measurement mirror **39**.

(131) Processing laser light **11b** transmitting through position measurement mirror **39** is terminated by beam terminator **41**.

(132) Meanwhile, processing laser light **11a** and measurement light **15a** reflected by position measurement mirror **39** are input to two-dimensional imaging element **40**. Two-dimensional imaging element **40** measures positions of input processing laser light **11a** and input measurement light **15a**.

(133) No optical element for transmitting light therethrough is not disposed in a section from lens **14** to two-dimensional imaging element **40**, and only the light reflected by position measurement mirror **39** is transmitted to the section.

(134) Further, optical path lengths of each of processing laser light **11** and measurement light **15** from lens **14** to two-dimensional imaging element **40** match an optical path length from lens **14** to processing point **20** when beam position measurement unit **38** is not installed.

(135) Therefore, a relative positional relationship of measurement light **15** based on a position of

processing laser light **11** measured by two-dimensional imaging element **40** matches a relationship between positions of processing laser light **11** and measurement light **15** at processing point **20** when beam position measurement unit **38** is not installed.

(136) FIG. **6** is a flowchart illustrating a method of calculating a correction amount at processing light grid point **30**.

(137) In step **S1**, beam position measurement unit **38** is installed at processing light grid point **30** in which the correction amount is obtained. At this time, two-dimensional imaging element **40** is installed in a position where an optical path length from lens **14** to two-dimensional imaging element **40** matches an optical path length from lens **14** to processing point **20** when beam position measurement unit **38** is not installed.

(138) In step **S2**, a scan angle of first mirror **13** is set such that processing laser light **11** reaches processing light grid point **30** in which the correction amount is obtained.

(139) In step **S3**, processing laser light **11** is applied, and an arrival position at which processing laser light **11** reaches two-dimensional imaging element **40** is obtained by using beam position measurement unit **38**.

(140) At this time, an output when applying processing laser light **11** is preferably set to be 10% or more of a rated output of laser oscillator **5**. In particular, when laser oscillator **5** is a fiber laser, a case where the output is set to less than 10% of the rated output is a case where an oscillation state of a laser is unstable, and this is because the arrival position where processing laser light **11** reaches two-dimensional imaging element **40** cannot be measured accurately.

(141) In step **S4**, measurement light **15** is applied, and an arrival position where measurement light **15** reaches two-dimensional imaging element **40** is obtained by using beam position measurement unit **38**.

(142) In step **S5**, a correction amount of measurement light deflection unit **17** is calculated by referring to the measurement result of two-dimensional imaging element **40** of beam position measurement unit **38** such that the arrival position of processing laser light **11** obtained in step **S3** matches the arrival position of measurement light **15**. The correction amount is calculated by, for example, controller **6**.

(143) The correction amount at processing light grid point **30** can be calculated by the method described above. By calculating the correction amount, an output of processing laser light **11** input to two-dimensional imaging element **40** can be approximated to an output of measurement light **15**, and thus, the same two-dimensional imaging element **40** can be used.

(144) Generally, when a position of laser light having a significantly different output is measured by two-dimensional imaging element **40**, different two-dimensional imaging element **40** according to the output needs to be used.

(145) Meanwhile, according to the method of calculating the correction amount described above, there is no need to replace two-dimensional imaging element **40** when measuring arrival positions of processing laser light **11** and measurement light **15**, and an installation error of two-dimensional imaging element **40** can be eliminated. Therefore, the arrival positions of processing laser light **11** and measurement light **15** can be accurately obtained.

(146) Further, an optical path from lens **14** to two-dimensional imaging element **40** includes only an optical path through which reflected light travels without including an optical path through which light transmitting through an optical component travels, thereby being not affected by refraction or a chromatic aberration of a glass material. Therefore, the arrival positions of processing laser light **11** and measurement light **15** can be accurately obtained.

(147) Although one position measurement mirror **39** is used for beam position measurement unit **38** illustrated in FIG. **5**, the number of position measurement mirrors **39** is not limited to one and may be two or more.

(148) FIG. **7** is a view illustrating a configuration example of beam position measurement unit **38** including two position measurement mirrors **39a** and **39b**.

(149) Two position measurement mirrors **39a** and **39b** are separated from each other in the x-axis direction and disposed in parallel with each other.

(150) Processing laser light **11** and measurement light **15** are divided into processing laser light **11a** and measurement light **15a** reflected by position measurement mirror **39a** and processing laser light **11c** transmitting through position measurement mirror **39a**.

(151) Processing laser light **11a** is divided into processing laser light **11b** reflected by position measurement mirror **39b** and processing laser light **11d** transmitting through position measurement mirror **39b**. Processing laser light **11b** is input to two-dimensional imaging element **40**.

(152) Measurement light **15a** is input to two-dimensional imaging element **40** as measurement light **15b** reflected by position measurement mirror **39b**.

(153) At this time, an optical path from position measurement mirror **39a** to two-dimensional imaging element **40** includes only an optical path through which reflected light travels without including an optical path through which light transmitting through an optical component travels.

(154) Further, two-dimensional imaging element **40** is installed in a position where the optical path length from lens **14** to two-dimensional imaging element **40** matches the optical path length from lens **14** to processing point **20** when beam position measurement unit **38** is not installed.

(155) Processing laser light **11c** transmitting through position measurement mirror **39a** is terminated by beam terminator **41a**.

(156) Processing laser light **11d** transmitting through position measurement mirror **39b** is terminated by beam terminator **41b**.

(157) As such, by combining a plurality of position measurement mirrors **39a** and **39b**, power of processing laser light **11** and measurement light **15** reaching two-dimensional imaging element **40** is adjusted to the same extent.

(158) Beam position measurement units **38** illustrated in FIGS. **5** and **7** include position measurement mirrors **39** as optical elements for reflecting processing laser light **11** and measurement light **15**, but position measurement mirrors **39** may each be combined with a total reflection mirror. Even when the total reflection mirror is combined therewith, an optical path from lens **14** to two-dimensional imaging element **40** includes only an optical path through which reflected light travels without including an optical path through which light transmitting through an optical component travels.

(159) Shapes of position measurement mirrors **39** illustrated in FIGS. **5** and **7** are not limited to a flat plate shape, and position measurement mirrors **39** may have flat reflection surfaces by which processing laser light **11** and measurement light **15** are reflected.

(160) Beam position measurement units **38** illustrated in FIGS. **5** and **7** have beam terminators **41**, but beam terminators **41** may not be installed if there is no safety problem.

(161) Although workpiece **18** is illustrated in FIG. **5** for the sake of convenient description, workpiece **18** may be omitted because workpiece **18** is not used when calculating the correction amount described above.

(162) Angles of optical axis of processing laser light **11** and measurement light **15** incident on beam position measurement unit **38** are changed depending on a position of processing light grid point **30**. Therefore, beam position measurement unit **38** may further include a mechanism for adjusting an angle of position measurement mirror **39** and a mechanism for adjusting a position of two-dimensional imaging element **40** in order to input processing laser light **11** and measurement light **15** to two-dimensional imaging element **40**.

(163) Beam position measurement unit **38** may be incorporated into laser processing apparatus **1** as a function of laser processing apparatus **1** or may be incorporated into another unit other than laser processing apparatus **1**.

(164) When beam position measurement unit **38** is incorporated into laser processing apparatus **1**, two-dimensional imaging element **40** may be connected to controller **6**, and controller **6** may control measurement light deflection unit **17** based on a measurement result of two-dimensional

imaging element **40**, and controller **6** may be configured to calculate a correction amount of measurement light deflection unit **17**.

(165) The method of calculating the correction amount described above is suitable when a laser (for example, a single mode fiber laser or the like) having excellent beam quality is used in processing head **2**.

(166) In the single mode fiber laser, a beam diameter of processing laser light **11** at processing point **20** is 50 μm or less, and a high accuracy of the correction amount (10 μm or less) is required, and this is because the correction amount required for a single mode can be calculated in the method of calculating the correction amount.

(167) Method of Generating Correction Number Table Data

(168) Next, a method of generating correction number table data will be described with reference to FIG. **8**. FIG. **8** is a flowchart illustrating the method of generating the correction number table data.

(169) In step **S11**, controller **6** sets a grid shape pattern (for example, processing light track **28** illustrated in FIG. **4**) that is a range in which laser processing is performed on processing surface **19** of temporary workpiece **18** (for example, a flat plate of metal). Temporary workpiece **18** is used for acquiring the correction number table data.

(170) Further, controller **6** selects one processing light grid point from among a plurality of processing light grid points included in the grid shape pattern.

(171) In step **S12**, controller **6** calculates a correction amount by performing a series of processes illustrated in FIG. **6** by using beam position measurement unit **38**.

(172) In step **S13**, controller **6** associates the correction amount calculated in step **S12** with a scan angle when the correction amount is calculated, and stores the associated result in memory **31** as the correction number table data.

(173) Thereafter, controller **6** performs a process of step **S14**. In step **S14**, controller **6** determines whether or not storing the correction number table data is completed for all of the plurality of processing light grid points included in the grid shape pattern set in step **S11**.

(174) In step **S14**, when storing the correction number table data is not completed for all the processing light grid points (step **S14**: NO), controller **6** performs a process of step **S15**.

(175) In step **S15**, controller **6** selects one new processing light grid point (that is, a processing light grid point in which storing the correction number table data is not performed), and then repeats the processes after step **S12**.

(176) In step **S14**, when storing the correction number table data is completed for all the processing light grid points (step **S14**: YES), controller **6** ends a series of processes. The correction number table data is obtained by a series of processes.

(177) When the grid shape pattern set in step **S11** is the 4×4 grid shape pattern illustrated in FIG. **4**, only the correction number table data at 16 processing light grid points is generated. It is preferable to generate more correction number table data by setting a grid shape pattern including 16 or more processing light grid points.

(178) However, even when much correction number table data is generated, a scan angle of first mirror **13** can be set to any value as long as the scan angle is within an operation range of a mechanism, and thus, the scan angle may not match the correction number table data. In this case, the correction amount needs to be obtained by interpolating the correction number table data. A method of interpolating the correction number table data to obtain the correction amount will be described below.

(179) Processing Data

(180) Next, processing data used for processing workpiece **18** will be described.

(181) In the related art, a laser processing apparatus including an f θ lens and a galvano mirror includes a controller that controls a laser oscillator and a galvano mirror by using a plurality of processing data set in time series. Processing is performed in time series in each processing point on a surface of a workpiece. The plurality of processing data is, for example, data in which an

output instruction value to the laser oscillator and data items of a scan angle and a processing speed are set for each processing point.

(182) In the present exemplary embodiment, the output instruction value (also referred to as laser output data) to laser oscillator **5**, a position (also referred to as a processing point position) of processing point **20**, and a scan angle are added to the data items of the processing data used by laser processing apparatus **1**, and the above-described correction amount is added thereto.

(183) In the following description, the processing data to which the correction amount is added as a data item is referred to as “corrected processing data”.

(184) An example of the corrected processing data will be described with reference to FIG. **9**. FIG. **9** is a diagram illustrating an example of data items included in the corrected processing data.

(185) The corrected processing data includes data number k , laser output data $L_{\text{sub}.k}$, processing point position $x_{\text{sub}.k}$, processing point position $y_{\text{sub}.k}$, scan angle $\phi_{x_{\text{sub}.k}}$, scan angle $\phi_{y_{\text{sub}.k}}$, correction amount $\psi_{x_{\text{sub}.k}}$, and correction amount $\psi_{y_{\text{sub}.k}}$ as the data items.

(186) Data number k indicates a sequence of the processing data. k represents an integer of 1 or more. A subscript k attached to each data item other than data number k represents a data item corresponding to a k th data number.

(187) Laser output data $L_{\text{sub}.k}$ indicates an output instruction value to laser oscillator **5**.

(188) Processing point position $x_{\text{sub}.k}$ indicates a position of processing point **20** in the x-axis direction.

(189) Processing point position $y_{\text{sub}.k}$ indicates a position of processing point **20** in the y-axis direction.

(190) Scan angle $\phi_{x_{\text{sub}.k}}$ indicates a scan angle of first mirror **13** that performs scanning in the x-axis direction.

(191) Scan angle $\phi_{y_{\text{sub}.k}}$ indicates a scan angle of first mirror **13** that performs scanning in the y-axis direction.

(192) Correction amount $\psi_{x_{\text{sub}.k}}$ indicates a correction amount of measurement light deflection unit **17** that performs correction of a position of measurement light **15** in the x-axis direction.

(193) Correction amount $\psi_{y_{\text{sub}.k}}$ indicates a correction amount of measurement light deflection unit **17** that performs correction of a position of measurement light **15** in the y-axis direction.

(194) The scan angle of the corrected processing data is an example of a first instruction value. The correction amount of the corrected processing data is an example of a second instruction value.

(195) Next, a method of generating processing data will be described with reference to FIG. **10**. FIG. **10** is a flowchart illustrating the method of generating the processing data.

(196) In step **S21**, controller **6** sets data number k to be referred to to zero. Data number k is assigned to a region storing the processing data in memory **31**.

(197) In step **S22**, controller **6** sets laser output data $L_{\text{sub}.k}$, processing point position $x_{\text{sub}.k}$, and processing point position $y_{\text{sub}.k}$ in the region of data number k in memory **31**.

(198) The values are set by a user of laser processing apparatus **1** using an operator (for example, a keyboard, a mouse, a touch panel, or the like) (not illustrated) in order to implement desirable laser processing.

(199) In step **S23**, controller **6** calculates scan angles $\phi_{x_{\text{sub}.k}}$ and $\phi_{y_{\text{sub}.k}}$ of first mirror **13** based on processing point positions $x_{\text{sub}.k}$ and $y_{\text{sub}.k}$ set in step **S22**, and stores calculated scan angles $\phi_{x_{\text{sub}.k}}$ and $\phi_{y_{\text{sub}.k}}$ in the region of data number k in memory **31**.

(200) When a focal length of lens **14** is f , there is a relationship of $(x_{\text{sub}.k}, y_{\text{sub}.k}) =$

$(2f \cdot \text{Math}.\phi_{x_{\text{sub}.k}}, 2f \cdot \text{Math}.\phi_{y_{\text{sub}.k}})$ between the processing point positions and the scan angles, and thus, the scan angles are automatically determined based on the processing point positions.

(201) A relational equation between the processing point positions and the scan angles, a corresponding number table, and the like may be previously set by a user. In that case, scan angles $\phi_{x_{\text{sub}.k}}$ and $\phi_{y_{\text{sub}.k}}$ of first mirror **13** may be determined by using the relational equation between the processing point positions and the scan angles, the corresponding number table, and

the like.

(202) In step **S24**, controller **6** determines whether or not setting of the processing data is completed for all data numbers k .

(203) In step **S24**, when setting of the processing data for all data numbers k is not completed (step **S24**: NO), controller **6** performs a process of step **S25**.

(204) In step **S25**, controller **6** increases data number k to be referred to by one, and then repeats the processes of step **S22** and subsequent steps.

(205) In step **S24**, when setting of the processing data for all data numbers k is completed (step **S24**: YES), controller **6** ends a series of processes.

(206) By the above-described processes, processing data is set for all data numbers k .

(207) Method of Setting Correction Amount

(208) Next, a method of setting a correction amount for each processing point position for the processing data set by the flow of FIG. **10** will be described.

(209) First, a configuration of correction number table data of a processing point position will be described with reference to FIG. **11**. FIG. **11** is a diagram illustrating correction number table **34** of a processing point position schematically illustrating the configuration of the correction number table data of the processing point position.

(210) In FIG. **11**, corrected processing data set for each processing light grid point on processing surface **19** is schematically illustrated as a plurality of data points **32**.

(211) As described above, data point **32** illustrated in FIG. **11** includes a position (that is, a processing point position) on processing surface **19**, a scan angle, and a correction amount.

(212) Correction data point **33** illustrated in FIG. **11** corresponds to processing original point **26** on processing surface **19**.

(213) In the following description, positions of respective data points **32** of correction number table **34** of the processing point positions are represented by scan angles (ϕx , ϕy) for the sake of convenience.

(214) It is assumed that a data number in a direction corresponding to a scan angle ϕx is i and a data number in a direction corresponding to a scan angle ϕy is j .

(215) Respective data points **32** hold ($\Phi x_{\text{sub},j}$, $\Phi y_{\text{sub},j}$, $\Psi x_{\text{sub},ij}$, $\Psi y_{\text{sub},ij}$) that is a set of correction number table scan angles ($\Phi x_{\text{sub},i}$, $\Phi y_{\text{sub},j}$) and correction number table correction amounts ($\Psi x_{\text{sub},ij}$, $\Psi y_{\text{sub},ij}$).

(216) Correction number table scan angles ($\Phi x_{\text{sub},i}$, $\Phi y_{\text{sub},j}$) include elements of the scan angles (ϕx , ϕy).

(217) Next, a flow of the method of setting the correction amount will be described with reference to FIG. **12**. FIG. **12** is a flowchart illustrating the method of setting the correction amount.

(218) In step **S31**, controller **6** sets data number k to be referred to zero.

(219) In step **S32**, controller **6** compares scan angles ($\phi x_{\text{sub},k}$, $\phi y_{\text{sub},k}$) stored in a region of data number k in memory **31** with all correction number table scan angles ($\Phi x_{\text{sub},i}$, $\Phi y_{\text{sub},j}$) in correction number table **34** of the processing point positions.

(220) Thereby, controller **6** determines whether or not there are data numbers i and j having relationships of $\phi x_{\text{sub},k} = \Phi x_{\text{sub},i}$ and $\phi y_{\text{sub},k} = \Phi y_{\text{sub},j}$.

(221) That is, in step **S32**, it is determined whether or not there is a data item including a scan angle that is exactly the same as a scan angle set by a user in correction number table **34** of the processing point positions.

(222) In step **S32**, when there are data numbers i and j having the relationships of $\phi x_{\text{sub},k} = \Phi x_{\text{sub},i}$ and $\phi y_{\text{sub},k} = \Phi y_{\text{sub},j}$ (step **S32**: YES), controller **6** performs a process of step **S33**.

(223) In step **S32**, when there are no data numbers i and j having relationships of $\phi x_{\text{sub},k} = \Phi x_{\text{sub},i}$ and $\phi y_{\text{sub},k} = \Phi y_{\text{sub},j}$ (step **S32**: NO), controller **6** performs a process of step **S34**.

(224) In step S33, controller 6 sets the correction amount as $(\psi_{x.sub.k}, \psi_{y.sub.k}) = (\Psi_{x.sub.ij}, \Psi_{y.sub.ij})$ by using data numbers i and j having relationships of $\phi_{x.sub.k} = \Phi_{x.sub.i}$ and $\phi_{y.sub.k} = \Phi_{y.sub.j}$.

(225) That is, in present step S33, there is the data item including the scan angle that is exactly the same as the scan angle set by the user, a corresponding correction number table correction amount is set as the correction amount as it is.

(226) In step S34, controller 6 performs an interpolation by using data of the closest four points surrounding scan angles $(\phi_{x.sub.k}, \phi_{y.sub.k})$ set by the user in correction number table 34 of the processing point positions, and sets correction amount $(\psi_{x.sub.k}, \psi_{y.sub.k})$. Details of step S34 will be described below.

(227) In step S35, controller 6 sets (stores) correction amount $(\psi_{x.sub.k}, \psi_{y.sub.k})$ set in step S33 or step S34 in a region of data number k of the processing data in memory 31.

(228) In step S36, controller 6 determines whether or not setting of the correction amount is completed for all the processing data stored in memory 31.

(229) In step S36, when setting of the correction amount for all the processing data is not completed (step S36: NO), controller 6 performs a process of step S37.

(230) In step S37, controller 6 increases data number k to be referred to by one, and then repeats processes step S32 and subsequent steps.

(231) In step S37, when setting of the correction amount for all the processing data is completed (step S36: YES), controller 6 ends a series of processes.

(232) By the above-described processes, correction amounts are set for all data numbers k in the processing data set by the flow of FIG. 10. That is, the corrected processing data is generated.

(233) Details of Interpolation Process

(234) Next, step S34 (interpolation process) illustrated in FIG. 12 will be described in detail. The interpolation process of step S34 is performed when scan angles $(\phi_{x.sub.k}, \phi_{y.sub.k})$ set by a user do not match any of correction number table scan angles $(\Phi_{x.sub.i}, \Phi_{y.sub.j})$ in data points 32.

(235) FIG. 13 is a diagram illustrating a relationship between scan angle X and a correction data point therearound when scan angle X set by a user as processing data does not match a correction number table scan angle of any of data points 32 in correction number table 34 of the processing point positions illustrated in FIG. 11.

(236) Points corresponding to scan angles X $(\phi_{x.sub.k}, \phi_{y.sub.k}, \psi_{x.sub.k}, \psi_{y.sub.k})$ are located in a grid formed by four correction data points A to D.

(237) A value of correction data point A is $(\Phi_{x.sub.i}, \Phi_{y.sub.j}, \Psi_{x.sub.ij}, \Psi_{y.sub.ij})$. A value of correction data point B is $(\Phi_{x.sub.i+1}, \Phi_{y.sub.j}, \Psi_{x.sub.i+1j}, \Psi_{y.sub.i+1j})$. A value of correction data point C is $(\Phi_{x.sub.i}, \Phi_{y.sub.j+1}, \Psi_{x.sub.ij+1}, \Psi_{y.sub.ij+1})$. A value of correction data point D is $(\Phi_{x.sub.i+1}, \Phi_{y.sub.j+1}, \Psi_{x.sub.i+1j+1}, \Psi_{y.sub.i+1j+1})$.

(238) Relationships of $\Phi_{x.sub.i} \leq \phi_{x.sub.k} \leq \Phi_{x.sub.i+1}$ (equal signs are not established at the same time) and $\Phi_{y.sub.j} \leq \phi_{y.sub.k} \leq \Phi_{y.sub.j+1}$ (equal signs are not established at the same time) are established.

(239) Correction amounts $(\psi_{x.sub.k}, \psi_{y.sub.k})$ at this time is calculated by following equations (1) and (2) by using values of scan angles X $(\phi_{x.sub.k}, \phi_{y.sub.k})$ and values of correction data points A, B, C, and D.

$$\psi_{x.sub.k} = (E + \Psi_{x.sub.ij} + F \times \Psi_{x.sub.i+1j} + G \times \Psi_{x.sub.ij+1} + H \times \Psi_{x.sub.i+1j+1}) / J \quad (1)$$

$$\psi_{y.sub.k} = (E \times \Psi_{y.sub.ij} + F \times \Psi_{y.sub.i+1j} + G \times \Psi_{y.sub.ij+1} + H \times \Psi_{y.sub.i+1j+1}) / J \quad (2)$$

(240) E, F, G, H, and J in equations (1) and (2) are calculated by following equations (3) to (7).

$$E = (\phi_{x.sub.k} - \Phi_{x.sub.i}) \times (\phi_{y.sub.k} - \Phi_{y.sub.j}) \quad (3)$$

$$F = (\Phi_{x.sub.i+1} - \phi_{x.sub.k}) \times (\phi_{y.sub.k} - \Phi_{y.sub.j}) \quad (4)$$

$$G = (\phi_{x.sub.k} - \Phi_{x.sub.i}) \times (\Phi_{y.sub.j+1} - \phi_{y.sub.k}) \quad (5)$$

$$H = (\Phi_{x.sub.i+1} - \phi_{x.sub.k}) \times (\Phi_{y.sub.j+1} - \phi_{y.sub.k}) \quad (6)$$

$$J = (\Phi_{x.sub.i+1} - \Phi_{x.sub.i}) \times (\Phi_{y.sub.j+1} - \Phi_{y.sub.j}) \quad (7)$$

(241) Correction amounts can be calculated based on scan angles set by a user through the interpolation process described above. In the above-described interpolation process, a linear interpolation method is used as an example, but other known two-dimensional interpolation methods (spline interpolation, quadratic curved surface approximation, and the like) may be used for the interpolation processing instead of the linear interpolation method.

(242) Further, a high-order approximate curved surface for a correction amount for a scan angle is calculated previously from correction number table correction amounts ($\Psi_{x.sub.ij}$, $\Psi_{y.sub.ij}$) in correction number table **34** of processing point positions, and a correction amount corresponding to a scan angle may be calculated. The “correction number table correction amounts ($\Psi_{x.sub.ij}$, $\Psi_{y.sub.ij}$) in correction number table **34**” represents all data points **32** of correction number table **34** illustrated in FIG. **11**. Fitting by a least square method can be exemplified as a specific example of a method of calculating an approximate curved surface. For example, an equation $z=f(a.sub.j, x, y)$ ($j=0 \dots m-1$) of a curved surface can be obtained as an approximate curved surface for a three-dimensional data set ($x.sub.i, y.sub.i, z.sub.i$) ($i=1 \dots n$). $a.sub.j$ represents a coefficient. By inserting a scan angle into x and y of the “three-dimensional data set ($x.sub.i, y.sub.i, z.sub.i$)” and inserting a correction amount (either x -coordinate or y -coordinate) z , an approximate curved surface of the scan angles ($\Phi_{x.sub.i}, \Phi_{y.sub.j}$) for the correction amount $\Psi_{x.sub.ij}$ and an approximate curved surface of the scan angles ($\Phi_{x.sub.i}, \Phi_{y.sub.j}$) for the correction amount $\Psi_{y.sub.ij}$ can be calculated. As such, relational equations for obtaining correction amounts can be derived based on certain scan angles.

(243) Laser Processing Method

(244) Next, a laser processing method performed by laser processing apparatus **1**, according to an exemplary embodiment of the present disclosure, will be described with reference to FIG. **14**. FIG. **14** is a flowchart illustrating the laser processing method performed by laser processing apparatus **1**, according to the exemplary embodiment of the present disclosure.

(245) In step **S41**, controller **6** sets the data number k to be referred to zero.

(246) In step **S42**, controller **6** reads corrected processing data (laser output data $L.sub.k$, scan angles ($\phi_{x.sub.k}, \phi_{y.sub.k}$) and correction amount ($\psi_{x.sub.k}, \psi_{y.sub.k}$)) corresponding to the data number k from memory **31**.

(247) In step **S43**, controller **6** operates first mirror **13** based on the scan angles ($\phi_{x.sub.k}, \phi_{y.sub.k}$) and operates measurement light deflection unit **17** based on the correction amount ($\psi_{x.sub.k}, \psi_{y.sub.k}$).

(248) Specifically, controller **6** notifies first driver **7** of the scan angles ($\phi_{x.sub.k}, \phi_{y.sub.k}$). Thereby, first driver **7** operates first mirror **13** based on the scan angles ($\phi_{x.sub.k}, \phi_{y.sub.k}$).

(249) Further, controller **6** notifies second driver **8** of the correction amount ($\psi_{x.sub.k}, \psi_{y.sub.k}$). Thereby, second driver **8** operates measurement light deflection unit **17** based on the correction amount ($\psi_{x.sub.k}, \psi_{y.sub.k}$).

(250) In step **S44**, controller **6** oscillates processing laser light **11** from laser oscillator **5** based on the laser output data $L.sub.k$.

(251) Specifically, controller **6** transmits the laser output data $L.sub.k$ indicating a laser output value to laser oscillator **5**. Thereby, laser oscillator **5** oscillates processing laser light **11** based on the laser output data $L.sub.k$.

(252) In step **S45**, controller **6** determines whether or not laser processing corresponding to all the data numbers k stored in memory **31** is completed.

(253) In step **S45**, controller **6** performs a process of step **S46** when the laser processing corresponding to all the data numbers k is not completed (step **S45**: NO).

(254) In step **S46**, controller **6** increases the data number k to be referred to by one, and then repeats processes of step **S42** and subsequent steps.

(255) In step **S45**, when the laser processing corresponding to all the data numbers k is completed (step **S45**: YES), controller **6** ends a series of processes.

(256) By the above-described processing, the laser processing for all the data numbers **k** is performed.

(257) Method of Measuring Depth of Keyhole

(258) Next, a flow of the method of measuring a depth of keyhole **22** when performing the above-described laser processing method will be described with reference to FIG. **15**. FIG. **15** is a flowchart illustrating the method of measuring the depth of keyhole **22**.

(259) In step **S51**, controller **6** acquires position data of processing surface **19** of unprocessed workpiece **18** before starting the laser processing method illustrated in FIG. **14**.

(260) The position data indicates a height of processing surface **19** in an unprocessed state (in other words, a position of processing surface **19** in the z-axis direction illustrated in FIG. **1** and the like). Further, controller **6** outputs a command to measurement processor **4** to start measuring the depth of keyhole **22**.

(261) When a series of processes relating to the laser processing illustrated in FIG. **14** starts, in step **S52**, measurement processor **4** outputs a command for emitting measurement light **15** to optical interferometer **3**.

(262) Optical interferometer **3** generates an optical interference signal according to an optical path difference between measurement light **15** reflected by a bottom surface of keyhole **22** and returned and reference light.

(263) In step **S53**, measurement processor **4** calculates a depth (that is, a penetration depth) of keyhole **22** by using the position data of processing surface **19** of unprocessed workpiece **18** and the optical interference signal generated by optical interferometer **3**. Controller **6** stores the calculated data indicating the depth of keyhole **22** in memory **31**.

(264) In step **S54**, controller **6** determines whether or not to end the measurement of the depth of keyhole **22**.

(265) For example, controller **6** continues to measure the depth of keyhole **22** when a series of processes relating to the laser processing is not completed, and ends the measurement of the depth of keyhole **22** when the series of processes relating to the laser processing is completed.

(266) In step **S54**, when the measurement of the depth of keyhole **22** does not end (step **S54**: NO), controller **6** repeats processes of step **S52** and subsequent steps.

(267) In step **S54**, when the measurement of the depth of keyhole **22** ends (step **S54**: YES), controller **6** performs a process of step **S55**.

(268) In step **S55**, controller **6** outputs a command to measurement processor **4** to end the measurement of the depth of keyhole **22** after the series of processes relating to the laser processing is completed.

(269) The above-described command for starting the measurement of the depth of keyhole **22** and the command for ending the measurement of the depth of keyhole **22** may be output from a command output unit (not illustrated) instead of being output by controller **6**. In that case, the commands are output as a user operates a command output device via an operator such as a keyboard.

(270) Effects

(271) As described above, beam position measurement unit **38** according to the present exemplary embodiment includes position measurement mirror **39** that reflects processing laser light **11** and measurement light **15** transmitting through lens **14**, and two-dimensional imaging element **40** that measures positions of processing laser light **11** and measurement light **15** reflected by position measurement mirror **39**.

(272) Further, position measurement mirror **39** is set to a reflectance of a wavelength of processing laser light **11** that becomes power by which processing laser light **11** can be input to two-dimensional imaging element **40**.

(273) Further, two-dimensional imaging element **40** is installed at a position where an optical path length from lens **14** to two-dimensional imaging element **40** matches an optical path length from

lens **14** to processing point **20**.

(274) Further, laser processing apparatus **1** sets a target position on processing surface **19** and sets a first instruction value (scan angle of measurement light deflection unit **17**) at which processing laser light **11** reaches a target position.

(275) Furthermore, laser processing apparatus **1** is configured to obtain a second instruction value (correction amount of measurement light deflection unit **17**) based on positions of processing laser light **11** and measurement light **15** measured by beam position measurement unit **38**.

(276) With this configuration, deviations of arrival positions of processing laser light **11** and measurement light **15** on processing surface **19** after transmitting through lens **14**, which occurs due to a magnification chromatic aberration of lens **14**, can be corrected.

(277) Thereby, the depth of keyhole **22** can be preferably measured by optical interferometer **3**. That is, the depth of keyhole **22** can be accurately measured.

(278) FIG. **16** is a diagram illustrating tracks of processing laser light **11** and measurement light **15** on processing surface **19** in a state where an influence of a magnification chromatic aberration is corrected by an operation of measurement light deflection unit **17**.

(279) According to FIG. **16**, it can be seen that processing light track **28** which is the track of processing laser light **11** matches measurement light track **27** which is the track of measurement light **15**.

(280) Further, it can be seen that processing light grid point **30** of one of specific locations on processing light track **28** matches corresponding measurement light grid point **29** of measurement light track **27**.

(281) The present disclosure is not limited to the description of the above-described exemplary embodiment, and various modifications can be made without departing from the idea of the present exemplary embodiment. Hereinafter, a modification example of the present exemplary embodiment will be described.

FIRST MODIFICATION EXAMPLE

(282) In the above-described exemplary embodiment, a case where measurement light deflection unit **17** which is a galvano mirror is used as a measurement light deflection unit for changing an optical axis direction of measurement light **15** is described as an example, but the present disclosure is not limited thereto.

(283) The measurement light deflection unit used for laser processing apparatus **1** is installed between, for example, measurement light inlet **9** and dichroic mirror **12** and may have a configuration in which the optical axis direction of measurement light **15** can be changed by a control of controller **6**.

(284) An example of the measurement light deflection unit configured as such is illustrated in FIG. **17**. FIG. **17** is a view schematically illustrating a configuration of laser processing apparatus **1** according to a first modification example of the present disclosure.

(285) Laser processing apparatus **1** illustrated in FIG. **17** includes second mirror **35** instead of measurement light deflection unit **17** illustrated in FIG. **1** and the like, and further includes movement stage **36** and stage driver **37**.

(286) Laser processing apparatus **1** illustrated in FIG. **17** does not include collimating lens **16** illustrated in FIG. **1** and the like.

(287) Second mirror **35** is a parabolic mirror fixed between measurement light inlet **9** and dichroic mirror **12**.

(288) Second mirror **35** may be a micro electro mechanical systems (MEMS) mirror or the like.

(289) Movement stage **36** is provided at measurement light inlet **9**. Stage driver **37** is electrically connected to controller **6** and operates movement stage **36** based on an instruction from controller **6**. Thereby, movement stage **36** moves in the y-axis direction and the z-axis direction in the figure. That is, a movement direction of movement stage **36** is a biaxial direction perpendicular to measurement optical axis **23**.

(290) An emission end of measurement light **15** in measurement light inlet **9** is disposed to match a focal point of second mirror **35**. Thereby, measurement light **15** becomes parallel light after being reflected by second mirror **35** and heads toward dichroic mirror **12**.

(291) An angle of measurement optical axis **23** from second mirror **35** toward dichroic mirror **12** changes due to a movement of movement stage **36**. That is, the measurement light deflection unit is configured with movement stage **36** and second mirror **35**. Thereby, the same effect as when measurement light deflection unit **17** which is a galvano mirror is used can be obtained.

SECOND MODIFICATION EXAMPLE

(292) FIG. **18** is a view schematically illustrating a configuration of laser processing apparatus **1** according to a second modification example of the present disclosure. Laser processing apparatus **1** illustrated in FIG. **18** includes collimating lens **16** illustrated in FIG. **1** and the like instead of second mirror **35** illustrated in FIG. **17**. Further, laser processing apparatus **1** includes movement stage **36** and stage driver **37**. Laser processing apparatus **1** illustrated in FIG. **18** does not include measurement light deflection unit **17** illustrated in FIG. **1** and the like.

(293) Laser processing apparatus **1** according to the first modification example changes an angle of measurement optical axis **23** by using second mirror **35**, whereas laser processing apparatus **1** according to the second modification example changes an angle of measurement optical axis **23** by using collimating lens **16**.

(294) Movement stage **36** is provided at measurement light inlet **9**. Stage driver **37** is electrically connected to controller **6** and operates movement stage **36** based on an instruction from controller **6**. Thereby, movement stage **36** moves in the y-axis direction and the x-axis direction. That is, a movement direction of movement stage **36** is a biaxial direction perpendicular to measurement optical axis **23**.

(295) An emission end of measurement light **15** in measurement light inlet **9** is disposed to match a focal point of collimating lens **16**. Thereby, measurement light **15** becomes parallel light after transmitting through collimating lens **16**, and heads toward dichroic mirror **12**.

(296) An angle of measurement optical axis **23** from collimating lens **16** toward dichroic mirror **12** changes due to a movement of movement stage **36**. That is, a measurement light deflection unit is configured with movement stage **36** and collimating lens **16**. Thereby, the same effect as when measurement light deflection unit **17** which is a galvano mirror is used as measurement light deflection unit can be obtained.

Second Exemplary Embodiment

(297) Published Japanese Translation No. 2016-538134 of the PCT International Publication discloses a method of accurately measuring an entry depth of laser light in a workpiece by using measurement light. This measurement is performed by positioning an irradiation position of the laser light and an irradiation position of the measurement light on the workpiece. A laser processing apparatus to which the method is applied includes an optical member such as a mirror or a lens that guides the emitted laser light and the measurement light to the workpiece.

(298) In the above-described laser processing apparatus, an output of the laser light is relatively high, and thus, a member that fixes the optical member is thermally deformed during a process performed by the laser light. When the irradiation position of laser light and the irradiation position of measurement light on the workpiece are changed under the state, the irradiation position of laser light and the irradiation position of measurement light on the workpiece deviate. As a result, the irradiation position of laser light cannot be measured accurately.

(299) One aspect of the present disclosure is to solve the above-described problems, and an object of the present disclosure is to provide a laser processing apparatus that performs highly accurate positioning of an irradiation position of laser light and an irradiation position of measurement light in a workpiece.

(300) In order to achieve the above object, a laser processing apparatus according to one aspect of the present disclosure includes a laser light emitting unit that emits laser light for processing a

workpiece, a measurement light emitting unit that emits measurement light for measuring an irradiation position of the laser light on the workpiece, a beam position measurement unit that derives a relative position of an optical axis of the measurement light with respect to an optical axis of the laser light, and an optical path changing unit that changes an optical path of at least one of the laser light and the measurement light based on the relative position derived by the beam position measurement unit.

(301) Further, in order to achieve the object, an optical adjustment method of a laser processing apparatus according to one aspect of the present disclosure is an optical adjustment method of a laser processing apparatus including a laser light emitting unit that emits laser light to a workpiece and a measurement light emitting unit that emits measurement light for measuring an irradiation position of laser light on the workpiece, and includes matching the irradiation position of the laser light and an irradiation position of the measurement light on the workpiece with each other, deriving a relative position of an optical axis of the measurement light with respect to an optical axis of the laser light applied to the workpiece, and changing an optical path of at least one of the laser light and the measurement light based on the derived relative position.

(302) According to one aspect of the present disclosure, alignment between an irradiation position of laser light and an irradiation position of measurement light in a workpiece can be made accurately.

(303) A laser processing apparatus may further include a mirror that reflects at least one of the laser light and the measurement light toward the workpiece, and a lens that is disposed between the mirror and the workpiece and converges the laser light and the measurement light on the workpiece. The beam position measurement unit may be disposed between the mirror and the lens.

(304) The beam position measurement unit may include a reflector that reflects the laser light and the measurement light in a direction other than a direction toward the workpiece, and a light receptor that receives the laser light and the measurement light reflected by the reflector. The relative position may be derived based on the irradiation position of the laser light and the irradiation position of the measurement light in the light receptor.

(305) A reflectance of the laser light of the reflector may be set to be less than or equal to a predetermined value.

(306) The beam position measurement unit may include a plurality of reflectors.

(307) The laser processing apparatus may further include a measurement unit that measures a depth of a processing point. The optical path changing unit may change an optical path of at least one of the laser light and the measurement light based on the depth of the processing point measured by the measurement unit so as to align the irradiation position of the laser light and the irradiation position of the measurement light on the workpiece with each other, and may change the optical path of at least one of the laser light and the measurement light based on the relative position derived by the beam position measurement unit when the irradiation position of the laser light and the irradiation position of the measurement light on the workpiece are aligned with each other.

(308) The measurement unit may be an interferometer that measures a length of the optical path of the measurement light based on a waveform generated by an interference between light generated reflecting the measurement light from the workpiece and the measurement light.

(309) Hereinafter, laser processing apparatus **201** according to a second exemplary embodiment of the present disclosure will be described with reference to the drawings. Description will be made by setting an upper side and a lower side in FIG. **19** as an upper portion and a lower portion of laser processing apparatus **201**, respectively, a left side and a right side as a left portion and a right portion of laser processing apparatus **201**, respectively, and a front side and a back side of a drawing sheet as a front portion and a rear portion of laser processing apparatus **201**.

(310) Laser processing apparatus **201** includes processing head **202**, measurement unit **203**, measurement processor **204**, and laser oscillator **205**. Measurement unit **203** is an example of a “measurement light emitting unit”. Measurement processor **204** is an example of the “measurement

unit". Laser oscillator **205** is an example of a "laser light emitting unit".

(311) Processing light LB, which is laser light for processing workpiece W, is input to processing head **202**. Processing head **202** causes input processing light LB to be applied to workpiece W disposed in a lower portion of processing head **202**. Further, measurement light MB for measuring an irradiation position of processing light LB to workpiece W is input to processing head **202**. Processing head **202** applies input measurement light MB to workpiece W.

(312) Measurement unit **203** is, for example, an optical interferometer for optical coherence tomography (OCT) measurement. Measurement unit **203** emits laser light for OCT measurement as measurement light MB. A wavelength of measurement light MB is, for example, 1300 nm. Emitted measurement light MB is input to processing head **202** from measurement light inlet **206** and travels toward a lower portion.

(313) Laser oscillator **205** oscillates processing light LB. Oscillated processing light LB is input to processing head **202** from processing light inlet **207** disposed in a left portion of measurement light inlet **206**, and travels toward the lower portion. Processing light LB is, for example, a YAG laser or a fiber laser. A wavelength of processing light LB is, for example, 1064 nm, which is different from the wavelength of measurement light MB. First mirror **208** and first lens **209** are disposed in a lower portion of processing light inlet **207** in processing head **202**. First lens **209** is an example of a "lens".

(314) Processing light LB input from processing light inlet **207** transmits through first mirror **208**. First mirror **208** is a dichroic mirror. First mirror **208** has characteristics of transmitting light having a wavelength of processing light LB therethrough and reflecting light having a wavelength of measurement light MB.

(315) Further, processing light LB is converged by first lens **209** and collected at processing point WP on processing surface S of workpiece W. Thereby, processing point WP is laser-processed. At this time, workpiece W is melted at processing point WP, and molten pool M is formed thereat. Further, a molten metal evaporates from molten pool M, and keyhole H is formed by a pressure of steam generated by evaporation.

(316) Measurement light MB input from measurement light inlet **206** is converted into parallel light by collimating lens **210** disposed in a lower portion of measurement light inlet **206**. Further, measurement light MB is reflected by second mirror **211** disposed in a lower portion of collimating lens **210** toward first mirror **208** disposed on an optical path of processing light LB. Subsequently, measurement light MB is reflected by first mirror **208** toward processing point WP. First mirror **208** and second mirror **211** correspond to "mirrors".

(317) Further, an angle adjusting mechanism (not illustrated) is disposed in second mirror **211**. The angle adjusting mechanism changes an angle of second mirror **211**. As the angle adjusting mechanism changes the angle of second mirror **211**, second mirror **211** changes an optical path of measurement light MB. Second mirror **211** is an example of an "optical path changing unit".

(318) Further, measurement light MB is converged by first lens **209** and travels toward processing point WP. By adjusting the angle of second mirror **211** as described below, measurement light MB is applied to a lowest point of keyhole H formed at processing point WP.

(319) Subsequently, measurement light MB is reflected by the lowest point of keyhole H and reaches measurement unit **203** by traveling back along an optical path of measurement light MB. Measurement unit **203** generates an optical interference intensity signal based on an interference caused by a difference between an optical path length of reflected measurement light MB and an optical path length of emitted measurement light MB.

(320) Measurement processor **204** measures a depth of keyhole H, that is, a penetration depth of processing point WP, based on the optical interference intensity signal generated by measurement unit **203**. The penetration depth is a distance between a lowest point of keyhole H and processing surface S.

(321) Further, laser processing apparatus **201** further includes beam position measurement unit **220**

and control device **230**.

(322) Beam position measurement unit **220** derives a relative position of an optical axis of measurement light MB with respect to an optical axis of processing light LB. Beam position measurement unit **220** is disposed between first mirror **208** and first lens **209**. Beam position measurement unit **220** includes reflector **221**, beam terminator **222**, second lens **223**, and light receptor **224**.

(323) Reflector **221** and beam terminator **222** are configured to be movable between first position P1 (FIG. **19**) that is out of optical paths of processing light LB and measurement light MB and second position P2 (FIG. **20**) located on the optical paths of processing light LB and measurement light MB. Second lens **223** and light receptor **224** are disposed on a left portion of reflector **221**.

(324) Reflector **221** is a mirror that reflects processing light LB and measurement light MB toward second lens **223** when located at second position P2. Further, reflector **221** has characteristics of dividing light having a wavelength of processing light LB into reflection light and transmission light and of totally reflecting light having a wavelength of measurement light MB. A reflectance of processing light LB of reflector **221** is set to be a predetermined value. The predetermined value is a value at which an intensity of the reflection light of processing light LB applied to light receptor **224** is within a predetermined range. The predetermined range is a range in which a lower limit value is less than an intensity of measurement light MB and an upper limit value is greater than the intensity of measurement light MB, and is a range in which light receptor **224** can receive light.

(325) For example, when a fiber laser having a rated output of 1 kW or more is selected as processing light LB, a minimum output of processing light LB is approximately 100 W. Meanwhile, when an OCT light source is used for measurement light MB, an output of measurement light MB is approximately several tens of mW. Thus, in order to reduce processing light LB of 100 W up to an output of the same order (several tens of mW) as measurement light MB of several tens of mW, a reflectance of processing light LB of reflector **221** is preferably set to 0.1% or less. Since measurement light MB does not need to be attenuated, the reflectance of measurement light MB of reflector **221** is preferably set to 90% or more.

(326) Further, an output of processing light LB when processing light LB is applied to light receptor **224** is preferably set to an output of 10% or more of a rated output of laser oscillator **205**. Particularly, in a case where laser oscillator **205** is a fiber laser, when an output of processing light LB is less than 10% of the rated output, an oscillation state of processing light LB is unstable, and this is because accuracy of an irradiation position LP of processing light LB in light receptor **224** is reduced.

(327) Beam terminator **222** receives transmission light transmitted through reflector **221** and terminates the transmission light at second position P2.

(328) Second lens **223** converges the reflection light and measurement light MB. The converged reflection light and measurement light MB travel toward light receptor **224**.

(329) Light receptor **224** receives the reflection light and measurement light MB. Light receptor **224** is a two-dimensional imaging element with sensitivity with respect to wavelengths of processing light LB and measurement light MB. Light receptor **224** is, for example, a commercially available industrial camera including an element such as a charge-coupled device (CCD), a complementary metal oxide semiconductor (CMOS), or indium gallium arsenide (InGaAs), or a two-dimensional beam profiler.

(330) A shape of second lens **223** and a distance between light receptor **224** and second lens **223** are set such that focal points of the converged reflection light and measurement light MB are located on a light receiving surface that receives the reflection light and measurement light MB in light receptor **224**.

(331) Control device **230** is a computer that performs an overall control of laser processing apparatus **201**. Control device **230** controls an angle adjusting mechanism and adjusts an angle of second mirror **211**.

(332) Next, an operation of laser processing apparatus **201** described above and a program executed by control device **230** will be described with reference to a flowchart of FIG. **21**. The program executes an optical adjustment for aligning an irradiation position of processing light LB and an irradiation position of measurement light MB on workpiece W with each other. This will be described from a state where reflector **221** and beam terminator **222** are located at first position P1 (FIG. **19**).

(333) Control device **230** determines in S100 whether or not the optical adjustment this time is a first optical adjustment. When relative position R, which is irradiation position MP of measurement light MB with respect to irradiation position LP of processing light LB in light receptor **224** to be described below, is not stored in control device **230**, the optical adjustment this time is the first optical adjustment. In this case (YES in S100), control device **230** aligns the irradiation position of processing light LB and the irradiation position of measurement light MB on workpiece W with each other in S102.

(334) Specifically, control device **230** irradiates a processing surface of a workpiece (not illustrated) for adjustment prepared for optical adjustment with processing light LB to form a microhole. Subsequently, control device **230** scans the microhole with measurement light MB while adjusting an angle of second mirror **211** to change an optical path of measurement light MB, and derives a position where a lowest point of the microhole, that is, an optical path length of measurement light MB is the longest from a measurement result of measurement processor **204**. The lowest point of the microhole corresponds to an irradiation position of processing light LB. Control device **230** adjusts an angle of second mirror **211** and aligns an irradiation position of measurement light MB to the lowest point of the microhole, thereby aligning the irradiation position of processing light LB and the irradiation position of measurement light MB in a workpiece for adjustment with each other. Thereby, the irradiation position of processing light LB and the irradiation position of measurement light MB in actual workpiece W are aligned with each other.

(335) Subsequently, control device **230** moves reflector **221** and beam terminator **222** to second position P2 in S104 (FIG. **20**). Transmission light of processing light LB is terminated by beam terminator **222**. Meanwhile, the reflection light of processing light LB and measurement light MB are reflected by reflector **221**, converged by second lens **223**, and applied to light receptor **224**.

(336) At this time, although the irradiation position of processing light LB and the irradiation position of measurement light MB on workpiece W are aligned with each other, irradiation position LP of the reflection light and irradiation position MP of measurement light MB in light receptor **224** are not aligned with each other (FIG. **22**). This is because, even when the irradiation position of processing light LB and the irradiation position of measurement light MB on workpiece W are aligned with each other, wavelengths of processing light LB and measurement light MB are different from each other as described above, and thereby, the optical axis of processing light LB and the optical axis of measurement light MB are not aligned with each other due to an influence of a chromatic aberration of first lens **209**. Further, the reflection light which is processing light LB applied to light receptor **224**, and measurement light MB are converged by second lens **223** having a different chromatic aberration from first lens **209**. For this reason, irradiation position LP of the reflection light in light receptor **224** and irradiation position MP of measurement light MB are not aligned with each other.

(337) However, at this time, relative position R (that is, a deviation between irradiation position LP of the reflection light and irradiation position MP of measurement light MB) which is irradiation position MP of measurement light MB with respect to irradiation position LP of the reflection light of processing light LB in light receptor **224** is relative position R in light receptor **224** when the irradiation position of processing light LB and the irradiation position of measurement light MB on workpiece W are aligned with each other.

(338) Relative position R is measured by light receptor **224**. Relative position R in light receptor

224 has a correlation with a relative position of an optical axis of measurement light MB with respect to an optical axis of processing light LB. That is, light receptor **224** indirectly derives the relative position of the optical axis of measurement light MB with respect to the optical axis of processing light LB. A measurement result of light receptor **224** is output to control device **230**. (339) In **S106**, control device **230** derives relative position R which is irradiation position MP of measurement light MB with respect to irradiation position LP of reflection light in light receptor **224** at this time, from the measurement result of light receptor **224** as relative position R in light receptor **224** when the irradiation position of processing light LB and the irradiation position of measurement light MB on workpiece W are aligned with each other, and stores the derived relative position.

(340) Subsequently, control device **230** ends the program by moving reflector **221** and beam terminator **222** to first position P1 in **S108**. Thereafter, workpiece W is processed. Control device **230** executes the program at a predetermined timing (for example, every predetermined time (10 seconds)) in order to perform the optical adjustment during processing.

(341) When control device **230** starts the program again, control device **230** determines in **S100** whether or not the optical adjustment this time is a first optical adjustment. When above-described relative position R is stored in control device **230**, the optical adjustment this time is second and subsequent optical adjustments. In this case (NO in **S100**), control device **230** moves reflector **221** and beam terminator **222** to second position P2 in **S110** (FIG. 20). Thereby, as described above, processing light LB and measurement light MB are reflected by reflector **221**, converged by second lens **223**, and applied to light receptor **224**.

(342) At this time, irradiation position LP of the reflection light of processing light LB and irradiation position MP (irradiation position MP of unadjusted measurement light MB) of measurement light MB in light receptor **224** are displaced from a time of the first optical adjustment (FIG. 23). That is, relative position R in light receptor **224** is different from relative position R derived by control device **230**.

(343) This is because, since processing light LB has a relatively high output, a temperature of a configuration member of processing head **202** and furthermore a fixing member for fixing the configuration member increases, and thereby, a thermal deformation of the fixing member and furthermore a displacement of the configuration member occurs, and an optical path of processing light LB and an optical path of measurement light MB change. At this time, when reflector **221** and beam terminator **222** are located at first position P1, an incident angle of processing light LB and measurement light MB on first lens **209**, and furthermore, an irradiation position of processing light LB and an irradiation position of measurement light MB on workpiece W are also displaced.

(344) Subsequently, control device **230** adjusts relative position R in light receptor **224** based on the derived relative position R in **S112**. Specifically, control device **230** adjusts an angle of second mirror **211** such that relative position R in light receptor **224** becomes derived relative position R, and changes an optical path of measurement light MB, thereby displacing irradiation position MP of measurement light MB in light receptor **224**. Thereby, adjusted relative position R, which is irradiation position MP of adjusted measurement light MB with respect to irradiation position LP of the reflection light in light receptor **224**, matches derived relative position R (FIG. 23).

(345) Further, control device **230** moves reflector **221** and beam terminator **222** to first position P1 in **S108**. Thereby, workpiece W is irradiated with processing light LB and measurement light MB. At this time, since relative position R in light receptor **224** is adjusted, the irradiation position of processing light LB and the irradiation position of measurement light MB on workpiece W are aligned with each other.

(346) As such, in the second and subsequent optical adjustments, the irradiation position of processing light LB and the irradiation position of measurement light MB on workpiece W can be aligned with each other without scanning a microhole by measurement light MB, control device **230** can easily perform an optical adjustment. Further, as compared with a case where the

irradiation position of measurement light MB corresponding to the lowest point of the microhole is derived by scanning measurement light MB, in a case where irradiation position MP of measurement light MB with respect to irradiation position LP of processing light LB in light receptor **224** is derived, control device **230** can accurately derive the irradiation position of measurement light MB with respect to the irradiation position of processing light LB. Thus, control device **230** can accurately align the irradiation position of processing light LB and the irradiation position of measurement light MB on workpiece W with each other. Further, a workpiece for adjustment need not be prepared in the second optical adjustment.

(347) According to the above-described exemplary embodiment, laser processing apparatus **201** includes laser oscillator **205** that emits processing light LB to workpiece W, measurement unit **203** that emits measurement light MB for measuring an irradiation position of processing light LB on workpiece W, beam position measurement unit **220** that derives a relative position of an optical axis of measurement light MB with respect to an optical axis of processing light LB, and second mirror **211** that changes the optical path of measurement light MB based on relative position R derived by beam position measurement unit **220**.

(348) According to this, an irradiation position of processing light LB and an irradiation position of measurement light MB on workpiece W can be easily and highly accurately aligned with each other.

(349) Further, laser processing apparatus **201** further includes first mirror **208** and second mirror **211** which reflect measurement light MB toward an irradiation position of processing light LB on workpiece W, and first lens **209** which is disposed between workpiece W and first and second mirrors **208** and **211** and converges processing light LB and measurement light MB on workpiece W. Beam position measurement unit **220** is disposed between first and second mirrors **208** and **211** and first lens **209**.

(350) According to this, beam position measurement unit **220** includes an influence of a change in an optical path of measurement light MB caused by displacements of first mirror **208** and second mirror **211**, and a relative position of an optical axis of measurement light MB with respect to an optical axis of processing light LB can be derived.

(351) Further, beam position measurement unit **220** includes reflector **221** that reflects processing light LB and measurement light MB in a direction other than a direction toward workpiece W, and light receptor **224** that receives processing light LB and measurement light MB reflected by reflector **221**. Relative position R is derived based on irradiation position LP of processing light LB and irradiation position MP of measurement light MB in light receptor **224**.

(352) According to this, alignment between an irradiation position of processing light LB and an irradiation position of measurement light MB on workpiece W can be made more easily and more accurately.

(353) Further, a reflectance of processing light LB of reflector **221** is set to be less than or equal to a predetermined value.

(354) According to this, since an intensity of reflection light and an intensity of measurement light MB applied to light receptor **224** can be within a predetermined range, irradiation position MP of measurement light MB with respect to irradiation position LP of reflection light can be easily derived by one light receptor **224** without using a plurality of light receptors **224**. This is because, when one of the intensity of the reflection light and the intensity of measurement light MB is out of the predetermined range, light receptor **224** corresponding to each intensity is required.

(355) Further, laser processing apparatus **201** further includes measurement processor **204** for measuring a depth of processing point WP. Second mirror **211** changes an optical path of measurement light MB based on the depth of processing point WP measured by measurement processor **204** so as to align an irradiation position of processing light LB and an irradiation position of measurement light MB on workpiece W with each other, and changes the optical path of measurement light MB based on relative position R derived by beam position measurement unit

220 when the irradiation position of processing light LB and the irradiation position of measurement light MB on workpiece W are aligned with each other.

(356) According to this, alignment between an irradiation position of processing light LB and an irradiation position of measurement light MB on workpiece W can be made more reliably and more accurately.

(357) Further, measurement processor **204** is an interferometer that measures a length of an optical path of measurement light MB based on a waveform generated by an interference between light generated by reflecting measurement light MB from workpiece W and measurement light MB.

(358) According to this, laser processing apparatus **201** can accurately derive an irradiation position of measurement light MB on workpiece W.

(359) The present disclosure is not limited to the exemplary embodiments described so far. As long as the gist of the present disclosure is not deviated, the present disclosure also includes a form in which various modifications are applied to the present exemplary embodiments and a form constructed by combining components in different exemplary embodiments.

(360) For example, although the flowchart illustrated in FIG. **21** is described as a program executed by control device **230**, a user of laser processing apparatus **201** may perform each step of the flowchart of FIG. **21**. In this case, control device **230** includes a display (not illustrated) that displays relative position R in light receptor **224**, and an operator (not illustrated) for a user to perform switching of positions of reflector **221** and beam terminator **222** and adjustment of an angle of second mirror **211**.

(361) Further, relative position R in light receptor **224** is adjusted by displacing irradiation position MP of measurement light MB in light receptor **224**, but instead, may be adjusted by displacing irradiation position LP of reflection light in light receptor **224**. In this case, for example, an angle adjusting mechanism may be disposed at processing light inlet **207**, and control device **230** may control the angle adjusting mechanism to change an optical path of processing light LB. Angle adjusting mechanisms are disposed in both second mirror **211** and processing light inlet **207**, and control device **230** may controls both angle adjusting mechanisms to change an optical path of processing light LB and an optical path of measurement light MB and to adjust relative position R in light receptor **224**. Further, the angle adjusting mechanism disposed in second mirror **211** may be disposed in measurement light inlet **206**. Further, each angle adjusting mechanism may be controlled by control device **230** or may be a manual type.

(362) Further, in the above-described exemplary embodiments, beam position measurement unit **220** includes one reflector **221** but may include a plurality of reflectors **221**. In this case, as illustrated in FIG. **24**, first reflector **221a** that moves between first position P1 and second position P2, and second reflector **221b** that reflects the reflection light and measurement light MB reflected by first reflector **221a** toward second lens **223** and light receptor **224** may be provided. Further, in this case, a plurality of beam terminators **222** are provided so as to correspond to the number of reflectors **221**. Transmission light transmitted from first reflector **221a** is terminated by first beam terminator **222a**. The transmission light transmitted through second reflector **221b** is terminated by second beam terminator **222b**. As such, by providing the plurality of reflectors **221**, even when an intensity of processing light LB and an intensity of measurement light MB are relatively great, an intensity of reflection light and the intensity of measurement light MB can be adjusted within a predetermined range.

(363) Further, reflector **221** uses a mirror that separates processing light LB into the transmission light and the reflection light, but in addition to this, a mirror that totally reflects processing light LB may be provided. In this case, beam terminator **222** may not be provided.

(364) Further, in the above-described exemplary embodiments, processing light LB and measurement light MB are reflected by reflector **221** and then transmit through second lens **223** to be applied to light receptor **224**. Instead thereof, processing light LB and measurement light MB may transmit through second lens **223** and then reflected by reflector **221** to be applied to light

receptor **224**. In this case, second lens **223** is movably disposed. According to this, even when second lens **223** having a long focal length is selected, optical paths of the reflection light and measurement light MB are bent, and thus, a size of beam position measurement unit **220** can be prevented from increasing.

(365) Further, beam position measurement unit **220** may be configured with two light receptors (not illustrated). In a second optical adjustment, the first light receptor is disposed between processing light inlet **207** and first mirror **208**, and the first light receptor is irradiated with processing light LB. In the second optical adjustment, the second light receptor is disposed between collimating lens **210** and second mirror **211**, and the second light receptor is irradiated with measurement light MB. The center of processing light LB applied to the first light receptor corresponds to an optical axis of the processing light. Further, the center of the measurement light applied to the second light receptor corresponds to an optical axis of measurement light MB. Thus, control device **230** can directly derive a relative position of the optical axis of measurement light MB with respect to an optical axis of processing light LB based on a central position of processing light LB applied to the first light receptor and a central position of measurement light MB applied to the second light receptor. Further, in this case, control device **230** controls an angle adjusting mechanism disposed in measurement light inlet **206** to adjust an angle of measurement light inlet **206** and change an optical path of measurement light MB.

(366) Further, in the above-described exemplary embodiments, reflector **221** is formed in a plate shape but may have a shape other than the plate shape as long as a portion that reflects processing light LB and measurement light MB is flat.

(367) Further, beam position measurement unit **220** includes beam terminator **222** but may include beam terminator **222** when an intensity of transmission light is relatively small instead thereof.

(368) Further, although reflector **221** totally reflects measurement light MB, a reflectance may be set to divide measurement light MB into the reflection light and the transmission light instead thereof. In this case, since relative position R in light receptor **224** can be derived in real time while processing workpiece W, an irradiation position of processing light LB and an irradiation position of measurement light MB on workpiece W can be aligned with each other in real time while processing workpiece W.

(369) When laser light (for example, a single mode fiber laser) having a beam diameter of 50 μm or less at processing point WP is used, accuracy of adjustment of the irradiation position of processing light LB and the irradiation position of measurement light MB is required to be 10 μm or less, but an optical adjustment of laser processing apparatus **201** described above can meet the required accuracy.

(370) Further, a first optical adjustment is performed by scanning a microhole formed at processing point WP with measurement light MB as described above, but instead thereof, as illustrated in FIG. 25, plate member **140** in which slit **141** is formed and power meter **150** that detects an intensity of processing light LB may be used.

(371) In this case, control device **230** changes an optical path of processing light LB so as to scan slit **141** by using processing light LB, and a change in intensity of processing light LB is detected by power meter **150**. Control device **230** adjusts a relative position of the optical path of processing light LB with respect to slit **141** based on the detected change in intensity of processing light LB. Likewise, control device **230** adjusts a relative position of an optical path of measurement light MB with respect to slit **141** to align an irradiation position of processing light LB and an irradiation position of measurement light MB on workpiece W with each other.

(372) Further, there are two mirrors of first mirror **208** and second mirror **211** that reflect measurement light MB toward the irradiation position of processing light LB on workpiece W, but it is needless to say that the number of mirrors is not limited thereto. For example, the number of mirrors may be two or more. Further, disposition of measurement light inlet **206** may be changed, and the number of mirrors is one. In this case, for example, measurement light inlet **206** and

collimating lens **210** may be disposed in a right portion of first mirror **208**, and the mirror may be only first mirror **208**. In this case, an angle adjusting mechanism may be disposed on first mirror **208**.

(373) Further, first mirror **208** has characteristics of transmitting processing light LB therethrough and reflecting measurement light MB but may have characteristics of transmitting measurement light MB therethrough and reflecting processing light LB instead thereof. In this case, for example, processing light LB is incident on first mirror **208** from the right portion, and measurement light MB is incident on first mirror **208** from an upper portion. Further, first mirror **208** may have characteristics of reflecting both processing light LB and measurement light MB. In this case, for example, processing light LB and measurement light MB are incident on first mirror **208** from the right portion. As such, the first mirror reflects at least one of processing light LB and measurement light MB toward workpiece W.

(374) The laser processing apparatus and the laser processing method according to the present disclosure are useful for laser processing of, for example, automobiles and electronic components.

Claims

1. A laser processing apparatus comprising: a laser oscillator configured to oscillate processing laser light to be incident on a processing point on a processing surface of a workpiece; a measurement light inlet configured to introduce measurement light to be incident on the processing point; a coupling mirror configured to deflect or transmit the processing laser light and measurement light toward the processing point; a measurement light deflection unit installed between the measurement light inlet and the coupling mirror and configured to change an incident angle of the measurement light on the coupling mirror by changing an optical axis direction of the measurement light; a lens configured to concentrate the processing laser light and the measurement light on the processing point; a controller configured to control the laser oscillator and the measurement light deflection unit; a measurement processor configured to measure a depth of a keyhole generated at the processing point by the processing laser light by using an optical interference signal based on an interference generated by an optical path difference between the measurement light reflected at the processing point and reference light; and a beam position measurement unit configured to measure positions of the processing laser light and the measurement light, wherein the measurement light deflection unit includes: (i) a parabolic mirror or a micro electro mechanical systems (MEMS) mirror fixed between the measurement light inlet and the coupling mirror and a movement stage configured to move the measurement light inlet, or (ii) a movement stage configured to move the measurement light inlet and a collimating lens.
2. A laser processing apparatus comprising: a laser oscillator configured to oscillate processing laser light to be incident on a processing point on a processing surface of a workpiece; a coupling mirror configured to deflect or transmit the processing laser light and measurement light to be incident on the processing point toward the processing point; a measurement light deflection unit configured to change an incident angle of the measurement light on the coupling mirror; a lens configured to concentrate the processing laser light and the measurement light on the processing point; a controller configured to control the laser oscillator and the measurement light deflection unit; a measurement processor configured to measure a depth of a keyhole generated at the processing point by the processing laser light by using an optical interference signal based on an interference generated by an optical path difference between the measurement light reflected at the processing point and reference light; a beam position measurement unit configured to measure positions of the processing laser light and the measurement light; and a first mirror configured to change a travel direction of the processing laser light and the measurement light, wherein the controller further controls the first mirror based on processing data.
3. The laser processing apparatus of claim 2, wherein the processing data includes a first instruction

value indicating an operation amount of the first mirror and a second instruction value indicating an operation amount of the measurement light deflection unit, the beam position measurement unit includes a position measurement mirror that reflects the processing laser light and the measurement light each passing through the lens, and a two-dimensional imaging element that measures the positions of the processing laser light and the measurement light each reflected by the position measurement mirror, and the controller sets a target position on the processing surface, sets the first instruction value to cause the processing laser light to be incident on the target position, and calculates the second instruction value based on the positions measured by the two-dimensional imaging element.

4. The laser processing apparatus of claim 3, wherein the position measurement mirror is set to have a reflectance at a wavelength of the processing laser light, the reflectance causing power allowing the processing laser light to enter the two-dimensional imaging element, and the two-dimensional imaging element is located at a position where an optical path length from the lens to the two-dimensional imaging element matches an optical path length from the lens to the processing point.

5. The laser processing apparatus of claim 3, wherein the position measurement mirror is composed of a plurality of mirrors.

6. The laser processing apparatus of claim 3, wherein in the position measurement mirror, a reflectance of a wavelength of the processing laser light is 0.1% or less.

7. The laser processing apparatus of claim 3, wherein the controller sets a grid shape pattern on the processing surface and sets a grid point of the grid shape pattern to the target position.

8. A laser processing apparatus comprising: a laser oscillator configured to oscillate processing laser light to be incident on a processing point on a processing surface of a workpiece; a coupling mirror configured to deflect or transmit the processing laser light and measurement light to be incident on the processing point toward the processing point; a measurement light deflection unit configured to change an incident angle of the measurement light on the coupling mirror; a lens configured to concentrate the processing laser light and the measurement light on the processing point; a controller configured to control the laser oscillator and the measurement light deflection unit; a measurement processor configured to measure a depth of a keyhole generated at the processing point by the processing laser light by using an optical interference signal based on an interference generated by an optical path difference between the measurement light reflected at the processing point and reference light; and a beam position measurement unit configured to measure positions of the processing laser light and the measurement light, wherein: the beam position measurement unit derives a relative position of an optical axis of the measurement light with respect to an optical axis of the processing laser light, and the controller controls the coupling mirror having an angle adjusting function or the measurement light deflection unit based on the relative position derived by the beam position measurement unit.

9. The laser processing apparatus of claim 8, wherein the lens is disposed between the coupling mirror and the workpiece, and the beam position measurement unit is disposed between the coupling mirror and the lens.

10. The laser processing apparatus of claim 8, wherein the beam position measurement unit includes a reflector that reflects the processing laser light and the measurement light in a direction other than a direction toward the workpiece, and a light receptor that receives the processing laser light and the measurement light each reflected by the reflector, and the beam position measurement unit derives the relative position based on an irradiation position of the processing laser light and an irradiation position of the measurement light in the light receptor.

11. The laser processing apparatus of claim 10, wherein a reflectance of the processing laser light of the reflector is set to be less than or equal to a predetermined value.

12. The laser processing apparatus of claim 10, wherein the beam position measurement unit includes a plurality of reflectors each being the reflector.

13. The laser processing apparatus of claim 8, wherein the controller controls the coupling mirror or the measurement light deflection unit such that an optical path of at least one of the processing laser light and the measurement light is changed to align an irradiation position of the processing laser light and an irradiation position of the measurement light on the workpiece with each other, and such that an optical path of at least one of the processing laser light and the measurement light is changed based on the relative position derived by the beam position measurement unit when the irradiation position of the processing laser light and the irradiation position of the measurement light on the workpiece are aligned with each other.

14. The laser processing apparatus of claim 13, wherein the measurement processor is an interferometer that measures a length of an optical path of the measurement light based on a waveform generated by the interference.

15. The laser processing apparatus of claim 8, wherein the controller causes the coupling mirror or the measurement light deflection unit to align an irradiation position of the processing laser light and an irradiation position of the measurement light on the workpiece with each other, stores the relative position derived by the beam position measurement unit when the irradiation position of the processing laser light and the irradiation position of the measurement light on the workpiece are aligned with each other, and controls the coupling mirror or the measurement light deflection unit such that a relative position between the irradiation position of the processing laser light and the irradiation position of the measurement light on the beam position measurement unit is aligned with the stored relative position.
