

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250279663

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

Sanchez; Kenneth Jason

SMART RING POWER AND CHARGING

Abstract

A charging system can include an external power source. The external power source can include a first groove. The external power source also can include a second groove. The second groove can be separate from the first groove. The charging system also can include a housing. The housing can include an internal power source configured to be wirelessly charged by the external power source that is removably coupled to the housing. The housing also can include a component configured to draw energy from the internal power source. Other embodiments are disclosed.

Inventors: Sanchez; Kenneth Jason (San Francisco, CA)

Applicant: QUANATA, LLC (SAN FRANCISCO, CA)

Family ID: 88648365

Assignee: QUANATA, LLC (SAN FRANCISCO, CA)

Appl. No.: 19/210878

Filed: May 16, 2025

Related U.S. Application Data

parent US continuation 19189687 20250425 PENDING child US 19210878

parent US continuation 18980230 20241213 PENDING child US 19189687

parent US continuation 18661982 20240513 parent-grant-document US 12191692 child US 18980230

parent US continuation 16926262 20200710 parent-grant-document US 11984742 child US 18661982

us-provisional-application US 62877391 20190723

us-provisional-application US 62992328 20200320

Publication Classification

Int. Cl.: H02J7/00 (20060101); A44C9/00 (20060101); H02J7/02 (20160101); H02J50/00 (20160101); H02J50/10 (20160101)

U.S. Cl.:

CPC H02J7/0045 (20130101); A44C9/0053 (20130101); H02J7/00032 (20200101); H02J7/02 (20130101); H02J50/001 (20200101); H02J50/10 (20160201)

Background/Summary

CROSS-REFERENCES TO RELATED APPLICATIONS [0001] This application is a continuation of U.S. Non-Provisional application Ser. No. 19/189,687, filed on Apr. 25, 2025, which is a continuation of U.S. Non-Provisional application Ser. No. 18/980,230, filed on Dec. 13, 2024, which is a continuation of U.S. Non-Provisional application Ser. No. 18/661,982 filed on May 13, 2024, which is a continuation of U.S. Non-Provisional patent application Ser. No. 16/926,262 filed on Jul. 10, 2020, which claims the benefit of U.S. Provisional Patent Application No. 62/877,391 filed on Jul. 23, 2019, and U.S. Provisional Patent Application No. 62/992,328 filed on Mar. 20, 2020, all of which are incorporated by reference herein in their entirety for all purposes.

FIELD OF THE DISCLOSURE

[0002] The present disclosure generally relates to smart ring wearable devices and, more specifically, to smart ring devices with removable power sources in the environment for enabling charging when a user holds an object with an integrated charger while wearing the smart ring.

BACKGROUND

[0003] To the extent that smart ring technology has been adopted, it has a number of challenges. For example, a number of problems exist with wearable devices generally, including: they often need to be removed for charging; they often have poor fit; they often provide relatively little user interactivity; and they often provide limited functionality.

BRIEF SUMMARY

[0004] A smart ring may be configured with a removable power source and an internal power source. The internal power source may enable continued operation of the smart ring disposed at a finger of a user, while the removable power source may be detached from the smart ring for charging or to be replaced with another charged removable power source. The removable power source may be disposed as a platform at an outer surface of a band-shaped housing of the smart ring. When attached to the smart ring, the removable power source may charge the internal power source. Attaching the removable power source to the band-shaped housing with an adapter may add flexibility to configuring smart rings. Furthermore, the smart ring may operate in a variety of power modes depending on whether the removable power source is attached to the band-shaped housing. In some implementations, the band-shaped housing or the removable power source may include an energy-harvesting component configured to charge, respectively, the internal power source or the removable power source from ambient energy sources.

[0005] In one aspect, a smart ring comprises a band-shaped housing and a removable power source, the removable power source configured to be removably disposed as a platform at an outer surface of the band-shaped housing and to charge the internal power source. The band-shaped housing includes an internal power source and a component configured to draw energy from the internal power source. The component is further configured to perform any one or more of the following operations: i) sense a physical phenomenon external to the band-shaped housing, ii) send communication signals to a communication device external to the band-shaped housing, or iii) implement a user interface.

[0006] In another aspect, a method of operating a smart ring comprises attaching, to a band-shaped housing of the smart ring, a removable power source to be removably disposed as a platform at an outer surface of the band-shaped housing. The method further comprises transferring electrical energy from the removable power source to an internal power source disposed within the band-shaped housing. Still further, the method comprises drawing electrical energy from the internal power source by a component disposed within the band-shaped housing and performing, by the component drawing energy from the internal power source, any one or more of the following operations: i) sensing a physical phenomenon external to the band-shaped housing, ii) sending communication signals to a communication device external to the band-shaped housing, or iii) implementing a user interface.

[0007] In another embodiment, a ring includes a housing. The housing can include an inner surface configured to contact a finger of a user when the housing is worn by the user. The housing also can include a first power source configured to be wirelessly charged by a second power source that is removably coupled to the housing. The housing further can include a component configured to draw energy from the first power source. The component can perform one or more of: sensing an activity of the user wearing the housing or sending data to a communication device.

[0008] In another embodiment, one or more non-transitory computer-readable media can include computing instructions that, when executed on one or more processors, can cause the one or more processors to perform operations. The operations can include wirelessly transferring energy to a first power source disposed within a housing of a ring from a second power source that is removably coupled to the housing. The operations also can include drawing the energy from the first power source by a component of the housing. The operations further can include performing, by the component, one or more of: sensing an activity of a user wearing the housing or sending data to a communication device.

[0009] In another embodiment, a ring can include a housing. The housing can include a first power source configured to be charged by a second power source. The second power source can be removably coupled to an inner surface of the housing to charge the first power source. The inner surface of the housing can be configured to contact a finger of a user wearing the ring. The housing also can include a component configured to draw energy from the first power source. The component can perform one or more of: sensing an activity of the user wearing the housing or sending data to a communication device.

[0010] In another embodiment, a charging system can include a housing. The housing can include an inner surface configured to contact a finger of a user when the housing is worn by the user. The housing also can include an internal power source configured to be wirelessly charged by a removable power source that is removably coupled to the housing. The housing further can include a component configured to draw energy from the internal power source. The charging system also can include a first LED activated in response to a first activity at the removable power source. The charging system further can include a second LED activated in response to a second activity at the removable power source. The second LED can be different from the first LED. The second activity can be different from the first activity.

[0011] In another embodiment, a method of providing a charging system can include providing a housing. Providing the housing can include providing an inner surface configured to contact a finger of a user when the housing is worn by the user. Providing the housing also can include providing an internal power source configured to be wirelessly charged by a removable power source that is removably coupled to the housing. Providing the housing further can include providing a component configured to draw energy from the internal power source. The method of providing a charging system also can include providing a first LED activated in response to a first activity at the removable power source. The method of providing a charging system further can include providing a second LED activated in response to a second activity at the removable power source. The second LED can be different from the first LED. The second activity can be different

from the first activity.

[0012] In another embodiment, a charging system can include a housing. The housing can include an inner surface configured to contact a finger of a user. The housing also can include an internal power source configured to be wirelessly charged by a removable power source that is removably coupled to the housing. The housing further can include a light source configured to draw energy from the internal power source. The charging system also can include a first LED activated in response to a first activity at the removable power source. The charging system further can include a second LED activated in response to a second activity at the removable power source. The second LED can be different from the first LED. The second activity can be different from the first activity.

[0013] In another embodiment, a charging system can include an external power source. The external power source can include a first groove. The external power source also can include a second groove separate from the first groove. The charging system also can include a housing. The housing can include an internal power source configured to be wirelessly charged by the external power source that is removably coupled to the housing. The housing also can include a component configured to draw energy from the internal power source.

[0014] In another embodiment, a charging system can include a charging housing. The charging housing can include a power source. The charging housing also can include a first groove. The charging housing further can include a second groove separate from the first groove. The charging system also can include a ring housing. The ring housing can include an internal power source configured to be wirelessly charged by the power source of the charging housing while the charging housing is removably coupled to the ring housing. The ring housing further can include a component configured to draw energy from the internal power source.

[0015] In another embodiment, a method of providing a charging system can include providing an external power source. Providing an external power source can include providing a first groove. The method of providing a charging system also can include providing a housing. Providing the housing can include providing an internal power source configured to be wirelessly charged by the external power source that is removably coupled to the housing. Providing the housing further can include providing a component configured to draw energy from the internal power source.

[0016] Depending upon the embodiment, one or more benefits may be achieved.

[0017] These benefits and various additional objects, features and advantages of the present disclosure can be fully appreciated with reference to the detailed description and accompanying drawings that follow.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0018] FIG. 1 illustrates a system comprising a smart ring and a block diagram of smart ring components according to some embodiments.

[0019] FIG. 2 illustrates a number of different form factor types of a smart ring according to some embodiments.

[0020] FIG. 3 illustrates examples of different smart ring form factors.

[0021] FIG. 4 illustrates an environment within which a smart ring may operate according to some embodiments.

[0022] FIG. 5A, FIG. 5B, FIG. 5C, and FIG. 5D illustrate assembled configurations (in FIG. 5B and FIG. 5D) and corresponding constituent components (in FIG. 5A and FIG. 5C) of smart rings that include removable power sources according to some embodiments.

DETAILED DESCRIPTION

[0023] Smart ring wearable technology can enable a wide range of applications including security,

safety, health and wellness, and convenient interfacing between a user and a variety of technologies based at least in part upon integrating a variety of sensor, input/output devices, and computing capabilities in a compact form factor. One of the challenges in increasing smart ring capabilities is reliably powering the needed components, particularly considering the limited space for a power source in the compact form factor. An ability to conveniently charge a power source of a smart ring without removing the smart ring from a finger would contribute to the adoption of smart ring technology.

[0024] One way to charge a smart ring without removing the smart ring from the finger may include using a removable power source. The removable power source may be disposed at an outer surface of the band-shaped housing of the smart ring, much as a jewel or another decorative element may be disposed at a band of a ring. We may refer to this as a band and platform configuration. The platform configuration may have some advantages in comparison to attaching a removable power source that has an annular shape in a side-by-side configuration with the band-shaped housing. For example, the band and platform configurations allow a variety of form factors and capacities in the removable power source. Furthermore, the power source need not be sized to the finger of the user. Also, an outer surface of the platform may integrate additional functionality, such as a display or an energy harvesting photovoltaic element.

[0025] Connecting a removable power source to the band-shaped housing via an adapter may confer additional advantages to smart ring configurations with removable power sources. Adapters may be configured to interface a plurality of power source options with a plurality of housing options in a variety of geometries, as described below.

[0026] When attached to the smart ring, the removable power source may charge an internal power source of the smart ring. The internal power source may maintain the state (e.g., by preserving the state of volatile memory) or maintain some other functions of the smart ring (e.g., sensing), while the removable power source is being replaced. In some implementations, adding the removable power source may enable or trigger higher power functionality of the smart ring (e.g., wireless communications, displays, etc.). To that end, a sensor may be configured for detecting whether the removable power source is attached to the band-shaped housing.

[0027] Various techniques, systems, and methods for charging a power source of a smart ring using charging sources integrated into objects in the environment of the smart ring are discussed below with reference to FIG. 1, FIG. 2, FIG. 3, FIG. 4, FIG. 5A, FIG. 5B, FIG. 5C, and FIG. 5D. In section I, a smart ring that may include a removable power source is described with reference to FIG. 1. In section II, example smart ring form factor types and configurations that may accommodate a removable power source are discussed with reference to FIG. 2 and FIG. 3. In section III, an example operating environment in which a smart ring with the removable power source may operate is described with reference to FIG. 4. In section IV, example configurations of assembled smart rings with removable power sources as well as the constituent components are described with reference to FIG. 5A, FIG. 5B, FIG. 5C, and FIG. 5D. In section V, other considerations are described.

Examples of Smart Ring and Smart Ring Components

[0028] FIG. 1 illustrates a system **100** comprising a smart ring **101** that may include a removable power source attached to a band-shaped housing according to one or more of the techniques described herein. FIG. 1 also shows one or more devices or systems that may be electrically, mechanically, or communicatively connected to the smart ring **101**. As shown, the smart ring **101** may include a set of components **102**, which may have various power needs and may impact the rate at which the smart ring **101** consumes electrical energy. Some of the components **102** may be disposed at the band-shaped housing, as described below, and interact with the components disposed at the removable charging source of the smart ring **101** or outside of the smart ring **101** altogether. Furthermore, in implementations where the smart ring **101** uses wireless transfer of electromagnetic energy between the removable power source and the internal power source of the

smart ring, the components **102** may be configured to be compatible with the electromagnetic fields to which the components **102** may be exposed during the wireless power transfer.

[0029] The system **100** may comprise any one or more of: a charger **103** for the smart ring **101**, a user device **104**, a network **105**, a mobile device **106**, or a server **107**. The charger **103** may provide energy to the smart ring **101** via a direct electrical, a wireless, or an optical connection. The smart ring **101** may be in a direct communicative connection with the user device **104**, the mobile device **106**, or the server **107** via the network **105**. Interactions between the smart ring **101** and other components of the system **100** are discussed in more detail in the context of FIG. 4.

[0030] The smart ring **101** may sense a variety of signals indicative of activities of a user wearing the ring **101**, biometric signals, a physiological state of the user, or signals indicative of the user's environment. The smart ring **101** may analyze the sensed signals using built-in computing capabilities or in cooperation with other computing devices (e.g., user device **104**, mobile device **106**, server **107**) and provide feedback to the user or about the user via the smart ring **101** or other devices (e.g., user device **104**, mobile device **106**, server **107**). Additionally or alternatively, the smart ring **101** may provide the user with notifications sent by other devices, enable secure access to locations or information, or a variety of other applications pertaining to health, wellness, productivity, or entertainment.

[0031] The smart ring **101**, which may be referred to herein as the ring **101**, may comprise a variety of mechanical, electrical, optical, or any other suitable subsystems, devices, components, or parts disposed within, at, throughout, or in mechanical connection to a housing **110** (which may be ring shaped and generally configured to be worn on a finger). Additionally, a set of interface components **112a** and **112b** may be disposed at the housing, and, in particular, through the surface of the housing. The interface components **112a** and **112b** may provide a physical access (e.g., electrical, fluidic, mechanical, or optical) to the components disposed within the housing. The interface components **112a** and **112b** may exemplify surface elements disposed at the housing. As discussed below, some of the surface elements of the housing may also be parts of the smart ring components.

[0032] As shown in FIG. 1, the components **102** of the smart ring **101** may be distributed within, throughout, or on the housing **110**. As discussed in the contexts of FIG. 2 and FIG. 3 below, the housing **110** may be configured in a variety of ways and include multiple parts. The smart ring components **102** may, for example, be distributed among the different parts of the housing **110**, as described below, and may include surface elements of the housing **110**. The housing **110** may include mechanical, electrical, optical, or any other suitable subsystems, devices, components, or parts disposed within or in mechanical connection to the housing **110**, including a battery **120**, a charging unit **130**, a controller **140**, a sensor system **150** comprising one or more sensors, a communications unit **160**, a one or more user input devices **170**, or a one or more output devices **190**. Each of the components **120**, **130**, **140**, **150**, **160**, **170**, and/or **190** may include one or more associated circuits, as well as packaging elements. The components **120**, **130**, **140**, **150**, **160**, **170**, and/or **190** may be electrically or communicatively connected with each other (e.g., via one or more busses or links, power lines, etc.), and may cooperate to enable “smart” functionality described within this disclosure.

[0033] The battery **120** may supply energy or power to the controller **140**, the sensors **150**, the communications unit **160**, the user input devices **170**, or the output devices **190**. In some scenarios or implementations, the battery **120** may supply energy or power to the charging unit **130**. The charging unit **130**, may supply energy or power to the battery **120**. In some implementations, the charging unit **130** may supply (e.g., from the charger **103**, or harvested from other sources) energy or power to the controller **140**, the sensors **150**, the communications unit **160**, the user input devices **170**, or the output devices **190**. In a charging mode of operation of the smart ring **101**, the average power supplied by the charging unit **130** to the battery **120** may exceed the average power supplied by the battery **120** to the charging unit **130**, resulting in a net transfer of energy from the

charging unit **130** to the battery **120**. In a non-charging mode of operation, the charging unit **130** may, on average, draw energy from the battery **120**.

[0034] The battery **120** may include one or more cells that convert chemical, thermal, nuclear or another suitable form of energy into electrical energy to power other components or subsystems **140, 150, 160, 170**, and/or **190** of the smart ring **101**. The battery **120** may include one or more alkaline, lithium, lithium-ion and or other suitable cells. The battery **120** may include two terminals that, in operation, maintain a substantially fixed voltage of 1.5, 3, 4.5, 6, 9, 12 V or any other suitable terminal voltage between them. When fully charged, the battery **120** may be capable of delivering to power-sinking components an amount of charge, referred to herein as “full charge,” without recharging. The full charge of the battery may be 1, 2, 5, 10, 20, 50, 100, 200, 500, 1000, 2000, 5000 mAh or any other suitable charge that can be delivered to one or more power-consuming loads as electrical current.

[0035] The battery **120** may include a charge-storage device, such as, for example a capacitor or a super-capacitor. In some implementations discussed below, the battery **120** may be entirely composed of one or more capacitive or charge-storage elements. The charge storage device may be capable of delivering higher currents than the energy-conversion cells included in the battery **120**. Furthermore, the charge storage device may maintain voltage available to the components or subsystems **130, 140, 150, 160, 170**, and/or **190** when one or more cells of the battery **120** are removed to be subsequently replaced by other cells.

[0036] The charging unit **130** may be configured to replenish the charge supplied by the battery **120** to power-sinking components or subsystems (e.g., one or more of subsystems **130, 140, 150, 160, 170**, and/or **190**) or, more specifically, by their associated circuits. To replenish the battery charge, the charging unit **130** may convert one form of electrical energy into another form of electrical energy. More specifically, the charging unit **130** may convert alternating current (AC) to direct current (DC), may perform frequency conversions of current or voltage waveforms, or may convert energy stored in static electric fields or static magnetic fields into direct current. Additionally or alternatively, the charging unit **130** may harvest energy from radiating or evanescent electromagnetic fields (including optical radiation) and convert it into the charge stored in the battery **120**. Furthermore, the charging unit **130** may convert non-electrical energy into electrical energy. For example, the charging unit **130** may harvest energy from motion, or from thermal gradients.

[0037] The controller **140** may include a processor unit **142** and a memory unit **144**. The processor unit **142** may include one or more processors, such as a microprocessor (μ P), a digital signal processor (DSP), a central processing unit (CPU), a graphical processing unit (GPU), a field-programmable gate array (FPGA), an application-specific integrated circuit (ASIC), or any other suitable electronic processing components. Additionally or alternatively, the processor unit **142** may include photonic processing components.

[0038] The memory unit **144** may include one or more computer memory devices or components, such as one or more registers, RAM, ROM, EEPROM, or on-board flash memory. The memory unit **144** may use magnetic, optical, electronic, spintronic, or any other suitable storage technology. In some implementations, at least some of the functionality the memory unit **144** may be integrated in an ASIC or and FPGA. Furthermore, the memory unit **144** may be integrated into the same chip as the processor unit **142** and the chip, in some implementations, may be an ASIC or an FPGA.

[0039] The memory unit **144** may store a smart ring (SR) routine **146** with a set of instructions, that, when executed by the processor **142** may enable the operation and the functionality described in more detail below. Furthermore, the memory unit **144** may store smart ring (SR) data **148**, which may include (i) input data used by one or more of the components **102** (e.g., by the controller when implementing the SR routine **146**) or (ii) output data generated by one or more of the components **102** (e.g., the controller **140**, the sensor unit **150**, the communication unit **160**, or the user input unit **170**). In some implementations, other units, components, or devices may generate data (e.g.,

diagnostic data) for storing in the memory unit **144**.

[0040] The processing unit **142** may draw power from the battery **120** (or directly from the charging unit **130**) to read from the memory unit **144** and to execute instructions contained in the smart ring routine **146**. Likewise, the memory unit **144** may draw power from the battery **120** (or directly from the charging unit **130**) to maintain the stored data or to enable reading or writing data into the memory unit **144**. The processor unit **142**, the memory unit **144**, or the controller **140** as a whole may be capable of operating in one or more low-power mode. One such low power mode may maintain the machine state of the controller **140** when less than a threshold power is available from the battery **120** or during a charging operation in which one or more battery cells are exchanged.

[0041] The controller **140** may receive and process data from the sensors **150**, the communications unit **160**, or the user input devices **170**. The controller **140** may perform computations to generate new data, signals, or information. The controller **140** may send data from the memory unit **144** or the generated data to the communication unit **160** or the output devices **190**. The electrical signals or waveforms generated by the controller **140** may include digital or analog signals or waveforms. The controller **140** may include electrical or electronic circuits for detecting, transforming (e.g., linearly or non-linearly filtering, amplifying, attenuating), or converting (e.g., digital to analog, analog to digital, rectifying, changing frequency) of analog or digital electrical signals or waveforms.

[0042] The sensor unit **150** may include one or more sensors disposed within or throughout the housing **110** of the ring **101**. Each of the one or more sensors may transduce one or more of: light, sound, acceleration, translational or rotational movement, strain, temperature, chemical composition, surface conductivity or other suitable signals into electrical or electronic sensors or signals. A sensor may be acoustic, photonic, micro-electro-mechanical systems (MEMS) sensors, chemical, micro-fluidic (e.g., flow sensor), or any other suitable type of sensor. The sensor unit **150** may include, for example, an inertial motion unit (IMU) for detecting orientation and movement of the ring **101**.

[0043] The communication unit **160** may facilitate wired or wireless communication between the ring **101** and one or more other devices. The communication unit **160** may include, for example, a network adapter to connect to a computer network, and, via the network, to network-connected devices. The computer network may be the Internet or another type of suitable network (e.g., a personal area network (PAN), a local area network (LAN), a metropolitan area network (MAN), a wide area network (WAN), a mobile, a wired or wireless network, a private network, a virtual private network, etc.). The communication unit **160** may use one or more wireless protocols, standards, or technologies for communication, such as Wi-Fi, near field communication (NFC), Bluetooth, or Bluetooth low energy (BLE). Additionally or alternatively, the communication unit **160** may enable free-space optical or acoustic links. In some implementations, the communication unit **160** may include one or more ports for a wired communication connections. The wired connections used by the wireless communication module **160** may include electrical or optical connections (e.g., fiber-optic, twisted-pair, coaxial cable).

[0044] User input unit **170** may collect information from a person wearing the ring **101** or another user, capable of interacting with the ring **101**. In some implementations, one or more of the sensors in the sensor unit **150** may act as user input devices within the user input unit **170**. User input devices may transduce tactile, acoustic, video, gesture, or any other suitable user input into digital or analog electrical signal, and send these electrical signals to the controller **140**.

[0045] The output unit **190** may include one or more devices to output information to a user of the ring **101**. The one or more output devices may include acoustic devices (e.g., speaker, ultrasonic); haptic (thermal, electrical) devices; electronic displays for optical output, such as an organic light emitting device (OLED) display, a laser unit, a high-power light-emitting device (LED), etc.; or any other suitable types of devices. For example, the output unit **190** may include a projector that

projects an image onto a suitable surface. In some implementations, the sensor unit **150**, the user input unit **170**, and the output unit **190** may cooperate to create a user interface with capabilities (e.g., a keyboard) of much larger computer systems, as described in more detail below.

[0046] The components **120**, **130**, **140**, **150**, **160**, **170**, and/or **190** may be interconnected by a bus **195**, which may be implemented using one or more circuit board traces, wires, or other electrical, optoelectronic, or optical connections. The bus **195** may be a collection of electrical power or communicative interconnections. The communicative interconnections may be configured to carry signals that conform to any one or more of a variety of protocols, such as I2C, SPI, or other logic to enable cooperation of the various components.

Example Smart Ring Form Factor Types

[0047] FIG. **2** includes block diagrams of a number of different example form factor types or configurations **205a**, **205b**, **205c**, **205d**, **205e**, and/or **205f** of a smart ring (e.g., the smart ring **101**). The variety of configurations of the ring-shaped housing may influence, or, conversely, depend on the technique for attaching a removable power source. Furthermore, the configurations **205a**, **205b**, **205c**, **205d**, **205e**, and/or **205f** may depend on or determine the types of indicators or communication components disposed at the ring.

[0048] The configurations **205a**, **205b**, **205c**, **205d**, **205e**, and/or **205f** (which may also be referred to as the smart rings **205a**, **205b**, **205c**, **205d**, **205e**, and/or **205f**) may each represent an implementation of the smart ring **101**, and each may include any one or more of the components **102** (or components similar to the components **102**). In some embodiments, one or more of the components **102** may not be included in the configurations **205a**, **205b**, **205c**, **205d**, **205e**, and/or **205f**. The configurations **205a**, **205b**, **205c**, **205d**, **205e**, and/or **205f** include housings **210a-f**, which may be similar to the housing **110** shown in FIG. **1**.

[0049] The configuration **205a** may be referred to as a band-only configuration comprising a housing **210a**. In the configuration **205b**, a band may include two or more removably connected parts, such as the housing parts **210b** and **210c**. The two housing parts **210b** and **210c** may each house at least some of the components **102**, distributed between the housing parts **210b** and **210c** in any suitable manner.

[0050] The configuration **205c** may be referred to as a band-and-platform configuration comprising (i) a housing component **210d** and (ii) a housing component **210e** (sometimes called the “platform **210e**”), which may be in a fixed or removable mechanical connection with the housing **210d**. The platform **210e** may function as a mount for a “jewel” or for any other suitable attachment. The housing component **210d** and the platform **210e** may each house at least one or more of the components **102** (or similar components).

[0051] In some instances, the term “smart ring” may refer to a partial ring that houses one or more components (e.g., components **102**) that enable the smart ring functionality described herein. The configurations **205d** and **205e** may be characterized as “partial” smart rings, and may be configured for attachment to a second ring. The second ring may be a conventional ring without smart functionality, or may be second smart ring, wherein some smart functionality of the first or second rings may be enhanced by the attachment.

[0052] The configuration **205d**, for example, may include a housing **210f** with a groove to enable clipping onto a conventional ring. The grooved clip-on housing **210f** may house the smart ring components described above. The configuration **205e** may clip onto a conventional ring using a substantially flat clip **210g** part of the housing and contain the smart ring components in a platform **210h** part of the housing.

[0053] The configuration **205f**, on the other hand, may be configured to be capable of being mounted onto a finger of a user without additional support (e.g., another ring). To that end, the housing **210i** of the configuration **205f** may be substantially of a partial annular shape subtending between 180 and 360 degrees of a full circumference. When implemented as a partial annular shape, the housing **210i** may be more adaptable to fingers of different sizes than a fully annular

band (360 degrees), and may be elastic. A restorative force produced by a deformation of the housing **210i** may ensure a suitable physical contact with the finger. Additional suitable combinations of configurations (not illustrated) may combine at least some of the housing features discussed above.

[0054] The configuration **205g** may be configured to have two rings, a first ring **205g1** capable of and adapted to be mounted onto a finger of a user, and a second ring **205g2** capable of and adapted to be directly mounted onto the first ring **205g1**, as depicted in FIG. 2. Said another way, the first ring **205g1** and the second ring **205g2** are arranged in a concentric circle arrangement, such that the second ring **205g2** does not contact a user's finger when the smart ring **205g** is worn. Rather, only the first ring **205g1** contacts the user's finger. Additional suitable combinations of configurations (not illustrated) may combine at least some of the housing features discussed above.

[0055] FIG. 3 includes perspective views of example configurations **305a**, **305b**, **305c**, **305d**, **305e**, and/or **305f** of a smart ring (e.g., the smart ring **101**) in which a number of surface elements are included.

[0056] Configuration **305a** is an example band configuration **205a** of a smart ring (e.g., smart ring **101**). Some of the surface elements of the housing may include interfaces **312a**, **312b** that may be electrically connected to, for example, the charging unit **130** or the communications unit **160**. On the outside of the configuration **305a**, the interfaces **312a**, **312b** may be electrically or optically connected with a charger to transfer energy from the charger to a battery (e.g., the battery **120**), or with another device to transfer data to or from the ring **305a**. The outer surface of the configuration **305a** may include a display **390a**, while the inner surface may include a biometric sensor **350a**.

[0057] The configurations **305b** and **305c** are examples of configurations of a smart ring with multiple housing parts (e.g., configuration **205b** in FIG. 2). Two (or more) parts may be separate axially (configuration **305b**), azimuthally (configuration **305c**), or radially (nested rings, not shown). The parts may be connected mechanically, electrically, or optically via, for example, interfaces analogous to interfaces **312a**, **312b** in configuration **305a**. Each part of a smart ring housing may have one or more surface elements, such as, for example, sensors **350b**, **350c** or output elements **390b**, **390c**. The latter may be LEDs (e.g., output element **390b**) or haptic feedback devices (e.g., output element **390c**), among other suitable sensor or output devices. Additionally or alternatively, at least some of the surface elements (e.g., microphones, touch sensors) may belong to the user input unit **170**.

[0058] Configuration **305d** may be an example of a band and platform configuration (e.g., configuration **205c**), while configurations **305e** and **305f** may be examples of the partial ring configurations **205d** and **205e**, respectively. Output devices **390d**, **390e**, and/or **390f** on the corresponding configurations **305d**, **305e**, and/or **305f** may be LCD display, OLED displays, e-ink displays, one or more LED pixels, speakers, or any other suitable output devices that may be a part of a suite of outputs represented by an output unit (e.g., output unit **190**). Other surface elements, such as an interface component **312c** may be disposed within, at, or through the housing. It should be appreciated that a variety of suitable surface elements may be disposed at the illustrated configurations **305a**, **305b**, **305c**, **305d**, **305e**, and/or **305f** at largely interchangeable locations. For example, the output elements **390d**, **390e**, and/or **390f** may be replaced with sensors (e.g., UV sensor, ambient light or noise sensors, etc.), user input devices (e.g., buttons, microphones, etc.), interfaces (e.g., including patch antennas or optoelectronic components communicatively connected to communications units), or other suitable surface elements.

Example Operating Environment for a Smart Ring

[0059] FIG. 4 illustrates an example environment **400** within which a smart ring **405** with a removable power source may be configured to operate. In an embodiment, the smart ring **405** may be the smart ring **101**. In some embodiments, the smart ring **405** may be any suitable smart ring capable of providing at least some of the functionality described herein. Depending on the embodiment, the smart ring **405** may be configured in a manner similar or equivalent to any of the

configurations **205a**, **205b**, **205c**, **205d**, **205e**, and/or **205f** or **305a**, **305b**, **305c**, **305d**, **305e**, and/or **305f** shown in FIG. 2 and FIG. 3.

[0060] The smart ring **405** may interact (e.g., by sensing, sending data, receiving data, receiving energy) with a variety of devices, such as bracelet **420** or another suitable wearable device, a mobile device **422** (e.g., a smart phone, a tablet, etc.) that may be, for example, the user device **104**, another ring **424** (e.g., another smart ring, a charger for the smart ring **405**, etc.), a secure access panel **432**, a golf club **434** (or another recreational accessory), a smart ring **436** worn by another user, or a steering wheel **438** (or another vehicle interface). Additionally or alternatively, the smart ring **405** may be communicatively connected to a network **440** (e.g., WiFi, 5G cellular), and via the network **440** (e.g., network **105** in FIG. 1) to a server **442** (e.g., server **107** in FIG. 1) or a personal computer **444** (e.g., mobile device **106**). Additionally or alternatively, the ring **405** may be configured to sense or harvest energy from natural environment, such as the sun **450**.

[0061] The ring **405** may exchange data with other devices by communicatively connecting to the other devices using, for example, the communication unit **160**. The communicative connection to other device may be initiated by the ring **405** in response to user input via the user input unit **170**, in response to detecting trigger conditions using the sensor unit **150**, or may be initiated by the other devices. The communicative connection may be wireless, wired electrical connection, or optical. In some implementation, establishing a communicative link may include establishing a mechanical connection.

[0062] The ring **405** may connect to other devices (e.g., a device with the charger **103** built in) to charge the battery **120**. The connection to other devices for charging may enable the ring **405** to be recharged without the need for removing the ring **405** from the finger. For example, the bracelet **420** may include an energy source that may transfer the energy from the energy source to battery **120** of the ring **405** via the charging unit **430**. To that end, an electrical (or optical) cable may extend from the bracelet **420** to an interface (e.g., interfaces **112a**, **112b**, **312a**, **312b**) disposed at the housing (e.g., housings **110**, **210a**, **210b**, **210c**, **210d**, **210e**, **210f**, **210g**, **210h**, and/or **210i**) of the ring **405**. The mobile device **422**, the ring **424**, the golf club **434**, the steering wheel **438** may also include energy source configured as chargers (e.g., the charger **103**) for the ring **405**. The chargers for may transfer energy to the ring **405** via a wired or wireless (e.g., inductive coupling) connection with the charging unit **130** of the ring **405**.

Configurations of Smart Rings with Removable Power Sources

[0063] Adding a removable external power source to a smart ring may confer a number of advantages in comparison to a smart ring with only a build-in power source. A rechargeable removable power source may be removed from the smart ring for charging, while the smart ring maintains a level of operation while remaining on a finger of a user. To maintain operation, the smart ring may include a small built-in power source. The energy storage and power capacity of the built-in power source may vary depending on implementation. In some implementations, when the removable power source is removed, it may be replaced by another fully charged removable power source in a few seconds, for example. A removable power source may be larger than an internal power source that can be placed within a band-shaped housing of the smart ring, and, consequently may store significantly more charge than an internal power source. Thus, the larger external power source may enable more applications for the smart ring. Still furthermore, the removable external power sources may be available in a variety of form factors that may be exchanged by a user according to their preference between bulk and capacity. Generally, removable power sources may enable flexible use of the smart ring while offering multiple aesthetic and comfort choices.

[0064] To connect to a housing of the smart ring, a removable power source may connect to an adapter. For the purpose of discussion here, the adapter may be any component that facilitates a removable attachment between the housing and the removable power source. The adapter may be configured to include other functionality, such as facilitating electrical or communicative connections, for example. Generally, the adapter may be fixedly attached to the housing or to the

removable power source. A combination of adapters may be distributed between the housing and the power source. On the other hand, the adapter may be a distinct component, configured to removably attach to the housing and the removable power source.

[0065] The adapter that is removable from the band-shaped housing and from the removable power source may have a number of advantages. For example, removable adapters may be configured to attach a smart ring housing to one of a selection of removable power sources. Conversely, removable adapters may be configured to attach a removable power source to one of a selection of housings. Furthermore, design elements may be included in an adapter, offering aesthetic choices to a user. Still furthermore, repetitive removal of the removable power source may impose a certain amount of wear on the adapter. It may be advantageous to periodically replace the adapter without replacing either the smart ring or the removable power source.

[0066] FIG. 5A, FIG. 5B, FIG. 5C, and FIG. 5D illustrate assembled configurations **505a**, **505b**, and/or **505c** (in FIG. 5B and FIG. 5D) and corresponding constituent components (in FIG. 5A and FIG. 5C) of smart rings that include a band-shaped housing **510** and removable external power sources **520a**, **520b**, and/or **520c** (that may also be referred to, for conciseness, as external power sources or removable power sources). The band-shaped housing **510** may have an outer surface **512**, an inner surface **513**, and two side surfaces **514**. Though the surfaces **512**, **514** may blend into one another, the outer surface **512** may refer to a portion of the housing surface that is substantially opposite to another portion of the housing surface that is configured to be in contact with a finger of a user. In the configurations **505a**, **505b**, and/or **505c**, the removable power sources **520a**, **520b**, and/or **520c** are configured to be disposed at the outer surface **512** of the band-shaped housing **510** with the aid of adapters **580a**, **580b**, and/or **580c**, as described below.

[0067] The band-shaped housing **510** may be the, for example, the housing **110** of the ring **101** in FIG. 1. The housing **510** may include any of the components **102** that enable smart ring functionality as described above. Furthermore, the band-shaped housing **510** may be configured similarly to configurations **205a**, **205b**, **205c**, **205d**, **205e**, **205f**, and/or **205g** in FIG. 2. In so far as the configurations **205d**, **205e**, and/or **205f** do not form a complete band, the band-shaped housing **510** may be formed by a combination of a ring with any of the partial-ring configurations **205d**, **205e**, and/or **205f**. In so far as the configurations **205c** and **205e** already include housing components **210e** and **210h** disposed as platforms at band-shaped housing components, the removable power sources **520a**, **520b**, and/or **520c** may be disposed at the band-shaped housing **510** instead of or in addition to the housing components **210e** and **210h**.

[0068] The housing **510** includes an internal power source. The internal power source may be a battery (e.g., the battery **120**), a capacitor, or a suitable combination of the two. In some implementations, the internal power source may include a generator, configured, for example, to harvest energy from environmental energy sources (e.g., light, movement, temperature gradients). The internal power source may be configured for recharging from the external power sources **520a**, **520b**, and/or **520c**, or from an array of other charging sources or chargers. Some chargers may be wall-plug chargers, some chargers may be environmentally integrated chargers (e.g., built into the steering wheel **438**, the golf club **434** of the environment **400**) or wearable chargers (e.g., the bracelet **420**, a charging glove, etc.). To recharge the internal power source, a charging unit (e.g., the charging unit **130**) may be disposed within the housing **510**. The charging unit may enable wired charging of the internal power source via an electrical connection. Additionally or alternatively, the charging unit may enable wireless charging. The charging unit configured for wireless charging may include an induction coil connected to rectification components to enable charging by electromagnetic induction. The charging unit disposed within the band-shaped housing **510** may facilitate charging the internal power source from the external power source **520a**, **520b**, and/or **520c**.

[0069] Another component disposed within the band-shaped housing **510** may be configured to enable smart-ring functionality (e.g., as described in the discussion of FIG. 1) while drawing power

(equivalently: charge, current, or energy) from the internal power source. For example, the component may be a sensor configured to sense a physical phenomenon external to the band-shaped housing **510**, an electronic communication interface disposed within the band-shaped housing **510** or a user interface disposed in, at, or throughout the band-shaped housing **510**. Furthermore, a controller (e.g., the controller **140**) may be disposed within the band-shaped housing and configured to draw power from the internal power source. In some implementations, any of the components disposed within the band-shaped housing **510** that need power may be configured to draw power from one of the external removable power sources **520a**, **520b**, and/or **520c** that is disposed at the housing **510**.

[0070] One of the components disposed within the band-shaped housing **510** may be a power detection sensor configured to detect a presence of a removable power source (e.g., one of **520a**, **520b**, and/or **520c**). The power detection sensor may be included in the sensors **150** of the smart ring **101**, for example. The power detection sensor may be a current sensor, a voltage sensor, a capacitance sensor, a magnetic sensor, an optical sensor or any other suitable sensor. The smart ring may be configured to operate in one of a plurality of power modes and switch between power modes based at least in part upon detecting the presence (or lack thereof) of the removable power source.

[0071] The band-shaped housing **510** may include an electrical interface **516**, configured to cooperate with any one of the adapters **580a**, **580b**, and/or **580c** in forming an electrical connection with corresponding one or more of the removable power sources **520a**, **520b**, and/or **520c**. Thus formed electrical connections are discussed in more detail below.

[0072] The removable power sources **520a**, **520b**, and/or **520c** may be configured to removably attach to the band-shaped housing **510** (e.g., via the adapters **580a**, **580b**, and/or **580c**) to provide power or energy to the components disposed within or at the band-shaped housing **510**. In some implementations, the removable power sources **520a**, **520b**, and/or **520c** may provide energy only via recharging the internal power source disposed within the band-shaped housing **510**. In other implementations, the removable power sources **520a**, **520b**, and/or **520c** may provide the energy directly to at least some of the components (in addition to the internal power source) disposed within the housing **510**. In either case, the external power sources may provide, on one charge, substantially more energy to the components disposed within the band-shaped housing **510** than what is available in a fully-charged internal power source. For example, a removable power source (e.g., one of the removable power sources **520a**, **520b**, and/or **520c**) may have a capacity to store 10, 100, 1000, 10000 times or more energy than the internal power source.

[0073] Any of the removable power sources **520a**, **520b**, and/or **520c** may include one or more cells that convert chemical, thermal, nuclear or another suitable form of energy into electrical energy. The cells in the power sources **520a**, **520b**, and/or **520c** may include one or more alkaline, nickel-cadmium, nickel-metal-hydride, lithium, lithium-ion, lithium polymer or other suitable cells. The removable power sources **520a**, **520b**, and/or **520c** may each include two terminals that, in operation, maintain a substantially fixed voltage of 1.5, 3, 4.5, 6, 9, 12 V or any other suitable terminal voltage between them. When fully charged, the removable power sources **520a**, **520b**, and/or **520c** may each be capable of delivering an amount of charge, referred to herein as “full charge,” without recharging. The full charge of one of the removable power sources **520a**, **520b**, and/or **520c** may be 10, 20, 50, 100, 200, 500, 1000, 2000, 5000 mAh or any other suitable charge.

[0074] Any one of the removable power sources **520a**, **520b**, and/or **520c** may be configured to transfer energy wirelessly to the internal power source of within the band-shaped housing **510** by way, for example, of the charging unit **130**. To that end any one of the removable power sources **520a**, **520b**, and/or **520c** may include a power transmitter. For example, the power transmitter may include a radio-frequency oscillator connected to a transmitting induction coil for transferring energy to a receiving induction coil disposed within the band-shaped housing **510**. In other implementations, the power transmitter may include a laser diode for transferring energy to a

photovoltaic element disposed within the band-shaped housing **510**.

[0075] In some implementations, any one of the removable power sources **520a**, **520b**, and/or **520c** may include a housing configured to hold one or more battery cells. The housing may include conductive elements to facilitate an electrical connection between the battery cells and the internal power source, e.g. via one of the adapters **580a**, **580b**, and/or **580c**. The removable power sources **520a**, **520b**, and/or **520c** may additionally include (e.g., disposed at a housing) elements for harvesting energy from the environment (e.g., photovoltaic cells, thermoelectric generators, piezoelectric generators, etc.). The harvesting elements may recharge the battery cells within the housing. The housing may additionally include elements for harvesting energy from the environment (e.g., photovoltaic cells, thermoelectric generators, piezoelectric generators, etc.) to recharge the battery cells within the housing. Additionally or alternatively, the housing may include elements for a wireless energy transfer (wireless charging) to the internal power source.

Furthermore, the housing of any one of the removable power sources **520a**, **520b**, and/or **520c** may include fixed or reconfigurable aesthetic elements.

[0076] Generally, external power sources **520a**, **520b**, and/or **520c** may include additional functionality beyond providing energy to the internal power source or other components disposed within the band-shaped housing **510**. One or more sensors, user interface components, memory storage devices, etc., may be disposed within the housing of any of the removable power sources **520a**, **520b**, and/or **520c**. The housing may also include a communication interface (wired or wireless) between the components disposed within the removable power source housing and the components disposed within the band-shaped housing **510**. In some implementations, the communication interface may be configured via a corresponding one of the adapters **580a**, **580b**, and/or **580c**.

[0077] The adapters **580a**, **580b**, and/or **580c** may include mechanical interfaces **582a**, **582b**, and/or **582c** to the housing **510**, mechanical interfaces **584a**, **584b**, and/or **584c** to removable power sources **520a**, **520b**, and/or **520c**, and electrical interfaces **586a**, **586b**, and/or **586c** to facilitate electrical connections between the removable power sources **520a**, **520b**, and/or **520c** and an internal power source disposed within the band-shaped housing **510**. In some implementations, the housing mechanical interfaces **582a**, **582b**, and/or **582c** and the power source mechanical interfaces **584a**, **584b**, and/or **584c** may be made from the same material (e.g., metal, plastic, elastomer, etc.). For example, the adapters **580a**, **580b**, and/or **580c** may be manufactured as substantially monolithic components including the mechanical interfaces **582a**, **582b**, and/or **582c**, **584a**, **584b**, and/or **584c**, with the electrical interfaces **586a**, **586b**, and/or **586c** added in a separate manufacturing step. In other implementations, the housing interface material may be different from the power source interface material.

[0078] The housing mechanical interfaces **582a**, **582b**, and/or **582c** may be configured for a friction fit with the housing **510**. In other implementations, the housing mechanical interfaces **582a**, **582b**, and/or **582c** may include a clipping mechanism, a set screw, a magnet, or any other suitable method for removably attaching to the housing **510**. Still in other implementations, the adapters **580a**, **580b**, and/or **580c** may be fixedly attached to the housing **510** via an adhesive or a solder, for example. To facilitate attachment to the housing **510**, the housing mechanical interfaces **582a**, **582b**, and/or **582c** may include surfaces shaped to conform to the outer surface **512** or side surfaces **514** of the housing **510**.

[0079] The power source mechanical interfaces **584a**, and **584b** may be configured for a friction fit with the external power source **520a** and **520b** or may comprise a clipping mechanism. Additional mechanical features may facilitate connections. For example, the external power source **520b** may include a groove **521** to mate with the interface **584a** or the interface **584b**. In another example, the external power source **520c** may include a groove or a thread **521c** that may be threaded onto a corresponding thread **585** in the interface **584c**. Additionally or alternatively, the power source interfaces **584a**, **584b**, and/or **584c** may include magnets, springs, or other suitable mechanisms to

facilitate secure attachment and convenient removal of the removable power sources **520a**, **520b**, and/or **520c** to the adapters **580a**, **580b**, and/or **580c**.

[0080] The electrical interfaces **586a**, **586b**, and/or **586c** of the adapters **580a**, **580b**, and/or **580c** may include coaxial or two-pin male-male, female-male, or female-female adapters. The interfaces **586a**, **586b**, and/or **586c** may provide two-contact connections between plugs or sockets disposed at the removable power sources **520a**, **520b**, and/or **520c** and a corresponding plug or socket disposed at the interface **516** of the band-shaped housing **510**. In some implementations, mechanical interfaces **582a**, **582b**, and/or **582c** and **584a**, **584b**, and/or **584c** may provide, at least partially, electrical connections between corresponding removable power sources **580a**, **580b**, and/or **580c** and, for example, a charging unit disposed within the band-shaped housing **510**. Such electrical connections may include one or more conductive paths via one or more of the surfaces **512**, **514** of the band-shaped housing **510**. For example, the housing **510** may serve as a ground connection for the electronics disposed within. The electrical interface **516** may then include a single contact, isolated from the ground connection and configured to connect via one of the electrical interfaces **586a**, **586b**, and/or **586c** of the corresponding adapter **580a**, **580b**, and/or **580c** to a corresponding contact at one of the removable power sources **520a**, **520b**, and/or **520c**.

[0081] To add to the discussion on interfaces (e.g., **582a**, **582b**, and/or **582c**, **584a**, **584b**, and/or **584c**, **586a**, **586b**, and/or **586c**), a mechanical interface (e.g., **582a**, **582b**, and/or **582c**) with the band-shaped housing **510** may be different from a mechanical interface (e.g., **584a**, **584b**, and/or **584c**) with a removable power source (e.g., **520a**, **520b**, and/or **520c**). The mechanical interfaces may include snap interfaces and friction fit interfaces with a variety of materials, magnetically-facilitated attachments, threads, set screws, or spring-loaded connectors. As an example of the latter, pogo-pins may be included at an adapter (e.g., **580a**, **580b**, and/or **580c**). The pogo pins may get depressed when pushed against the band-shaped housing **510** until reaching indentations at which the pogo pins may engage with an interface at the band-shaped housing **510**. In this manner, the pogo pins made of a conductive material may facilitate both, mechanical and electrical connections. Additionally or alternatively, elastomeric connectors, made with alternately conductive and electrically insulating elastomer regions, may likewise facilitate both, mechanical and electrical connections. Pogo pins, elastomeric connectors, or other suitable interfaces may likewise be used to connect, mechanically and electrically, with a removable power source (e.g., **520a**, **520b**, and/or **520c**).

[0082] FIG. 5B illustrates two smart ring configurations **505a** and **505b** including the housing **510** and the removable power source **520a**. Adapter **580a** in configuration **505a** leads to a different configuration geometry than adapter **580b** in the configuration **505b**. Using the removable power source **520b** in lieu of the removable power source **520a** may lead to additional configurations. Any removable power source compatible with the adapter **580c** may replace the removable power source **520c** in the configuration **505c** of FIG. 5D. Generally, as discussed above, adapters for removable power sources may increase flexibility and choice of configurations vis-à-vis adapters that are integrated into removable power sources.

[0083] In operation, configurations **505a**, **505b**, and/or **505c** may allow the components disposed within the band-shaped housing **510** to use energy stored within corresponding removable power sources **520a**, and/or **520c**. As discussed above, some components disposed within the band-shaped housing **510** may draw energy from the internal power source, which in turn may draw energy from the corresponding removable power source (one of **520a**, **520b**, and/or **520c**).

[0084] In some implementations, the smart ring may be configured to operate in one of a plurality of power modes. Selecting an operating power mode may be based at least in part upon whether a removable power source (e.g., one of **520a**, **520b**, and/or **520c**) is disposed at the band-shaped housing **510** and charging the internal power source.

[0085] A method of operating a smart ring (e.g., the smart ring **101**, **405** or smart rings in configurations **505a**, **505b**, and/or **505c**) may include detecting that a removable power source

(e.g., one of the removable power sources **520a**, **520b**, and/or **520c**) is disposed at an outer surface of a housing (e.g., the housing **510**). The detection may include detecting that the removable power source is supplying energy to the internal power source of the smart ring. In response to detecting the removable power source at the housing, a controller (e.g., the controller **140**) may switch the smart ring into an operating mode that consumes energy at a higher rate (than when the external power source is not detected) to perform certain functions of the smart ring. The operating mode of the smart ring configuration with a removable power source (e.g., configurations **505a**, **505b**, and/or **505c**) that consumes energy at the higher rate may be referred to as a high-power mode. [0086] For example, the controller of the smart ring may activate a communication unit (e.g., communication unit **160**) or input and output units (e.g., user input unit **170**, output unit **190**) when operating in the high-power mode. In some implementations, the smart ring may sense and log (e.g., in the memory unit **144**) biometric or movement information using one or more sensors (e.g., sensors **150**). Upon detecting (e.g., by the sensor disposed within or at the housing **510**) that the removable power source is connected to the housing **510**, the controller may activate the communication unit that may initiate advertising a connection for the purpose of transferring the logged data. Additionally or alternatively, the controller may activate, in response to the sensor detecting that the removable power source is present at the band-shaped housing **510**, a display or another output device. The output device may then communicate information based at least in part upon the logged data with the user.

[0087] In some implementations, the method may include detecting that the removable power source is not connected to the smart ring and, in response, switching the smart ring into a low-power mode. The low-power mode may include reduced smart ring functionality, for example, to only sensing, as described above. In other implementations, the low power mode may include only maintaining the state (e.g., volatile memory) of the control unit while a user replaces the removable power source. Generally, multiple power modes may be configured depending on the energy resources available to the smart ring. Transitions between some of the power modes may depend on detecting changes to the connection of the removable power source to the smart ring.

[0088] The removable power source (e.g., any of **520a**, **520b**, and/or **520c**) may connect to the housing (e.g., the housing **510**) via an adapter (e.g., the adapters **580a**, **580b**, and/or **580c**) as discussed above. In some implementations, detecting whether the removable power source is connected to the smart ring may be mediated by the adapter. For example, deformation in the adapter or a change in conductivity between two points of the adapter may be sensed to detect the presence of the removable power source.

[0089] Generally, an adapter may facilitate a mechanical connection, an electrical connection, or a communicative connection between the removable power source and the band shaped housing with the internal power source. Furthermore, the adapter may facilitate sensing whether the removable power source is connected.

Examples of Other Considerations

[0090] When implemented in software, any of the applications, services, and engines described herein may be stored in any tangible, non-transitory computer readable memory such as on a magnetic disk, a laser disk, solid state memory device, molecular memory storage device, or other storage medium, in a RAM or ROM of a computer or processor, etc. Although the example systems disclosed herein are disclosed as including, among other components, software or firmware executed on hardware, it should be noted that such systems are merely illustrative and should not be considered as limiting. For example, it is contemplated that any or all of these hardware, software, and firmware components could be embodied exclusively in hardware, exclusively in software, or in any combination of hardware and software. Accordingly, while the example systems described herein are described as being implemented in software executed on a processor of one or more computer devices, persons of ordinary skill in the art will readily appreciate that the examples provided are not the only way to implement such systems.

[0091] The described functions may be implemented, in whole or in part, by the devices, circuits, or routines of the system **100** shown in FIG. **1**. Each of the described methods may be embodied by a set of circuits that are permanently or semi-permanently configured (e.g., an ASIC or FPGA) to perform logical functions of the respective method or that are at least temporarily configured (e.g., one or more processors and a set instructions or routines, representing the logical functions, saved to a memory) to perform the logical functions of the respective method.

[0092] While the present disclosure has been described with reference to specific examples, which are intended to be illustrative only and not to be limiting of the present disclosure, it will be apparent to those of ordinary skill in the art that changes, additions or deletions may be made to the disclosed embodiments without departing from the spirit and scope of the present disclosure.

[0093] Throughout this specification, plural instances may implement components, operations, or structures described as a single instance. Although individual operations of one or more methods are illustrated and described as separate operations, one or more of the individual operations may be performed concurrently in certain embodiments.

[0094] As used herein, any reference to “one embodiment” or “an embodiment” means that a particular element, feature, structure, or characteristic described in connection with the embodiment is included in at least one embodiment. The appearances of the phrase “in one embodiment” in various places in the specification may not be all referring to the same embodiment.

[0095] As used herein, the terms “comprises,” “comprising,” “includes,” “including,” “has,” “having” or any other variation thereof, are intended to cover a non-exclusive inclusion. For example, a process, method, article, or apparatus that comprises a list of elements may not be limited to only those elements but may include other elements not expressly listed or inherent to such process, method, article, or apparatus. Further, unless expressly stated to the contrary, “or” refers to an inclusive “or” and not to an exclusive “or.” For example, a condition A or B is satisfied by any one of the following: A is true (or present) and B is false (or not present), A is false (or not present) and B is true (or present), and both A and B are true (or present).

[0096] In addition, use of the “a” or “an” are employed to describe elements and components of the embodiments herein. Generally speaking, when a system or technique is described as including “a” part or “a” step, the system or technique should be read to include one or at least one part or step. Said another way, for example, a system described as including a blue widget may include multiple blue widgets in some implementations (unless the description makes clear that the system includes only one blue widget).

[0097] Throughout this specification, some of the following terms and phrases are used.

[0098] Communication Interface according to some embodiments: Some of the described devices or systems include a “communication interface” (sometimes referred to as a “network interface”). A communication interface enables the system to send information to other systems and to receive information from other systems, and may include circuitry for wired or wireless communication.

[0099] Each described communication interface or communications unit (e.g., communications unit **160**) may enable the device of which it is a part to connect to components or to other computing systems or servers via any suitable network, such as a personal area network (PAN), a local area network (LAN), or a wide area network (WAN). In particular, the communication unit **160** may include circuitry for wirelessly connecting the smart ring **101** to the user device **104** or the network **105** in accordance with protocols and standards for NFC (operating in the 13.56 MHz band), RFID (operating in frequency bands of 125-134 kHz, 13.56 MHz, or 856 MHz to 960 MHz), Bluetooth (operating in a band of 2.4 to 2.485 GHz), Wi-Fi Direct (operating in a band of 2.4 GHz or 5 GHz), or any other suitable communications protocol or standard that enables wireless communication.

[0100] Communication Link according to some embodiments: A “communication link” or “link” is a pathway or medium connecting two or more nodes. A link between two end-nodes may include one or more sublinks coupled together via one or more intermediary nodes. A link may be a

physical link or a logical link. A physical link is the interface or medium(s) over which information is transferred, and may be wired or wireless in nature. Examples of physical links may include a cable with a conductor for transmission of electrical energy, a fiber optic connection for transmission of light, or a wireless electromagnetic signal that carries information via changes made to one or more properties of an electromagnetic wave(s).

[0101] A logical link between two or more nodes represents an abstraction of the underlying physical links or intermediary nodes connecting the two or more nodes. For example, two or more nodes may be logically coupled via a logical link. The logical link may be established via any combination of physical links and intermediary nodes (e.g., routers, switches, or other networking equipment).

[0102] A link is sometimes referred to as a “communication channel.” In a wireless communication system, the term “communication channel” (or just “channel”) generally refers to a particular frequency or frequency band. A carrier signal (or carrier wave) may be transmitted at the particular frequency or within the particular frequency band of the channel. In some instances, multiple signals may be transmitted over a single band/channel. For example, signals may sometimes be simultaneously transmitted over a single band/channel via different sub-bands or sub-channels. As another example, signals may sometimes be transmitted via the same band by allocating time slots over which respective transmitters and receivers use the band in question.

[0103] Memory and Computer-Readable Media according to some embodiments: Generally speaking, as used herein the phrase “memory” or “memory device” refers to a system or device (e.g., the memory unit **144**) including computer-readable media (“CRM”). “CRM” refers to a medium or media accessible by the relevant computing system for placing, keeping, or retrieving information (e.g., data, computer-readable instructions, program modules, applications, routines, etc.). Note, “CRM” refers to media that is non-transitory in nature, and does not refer to disembodied transitory signals, such as radio waves.

[0104] The CRM may be implemented in any technology, device, or group of devices included in the relevant computing system or in communication with the relevant computing system. The CRM may include volatile or nonvolatile media, and removable or non-removable media. The CRM may include, but is not limited to, RAM, ROM, EEPROM, flash memory, or other memory technology, CD-ROM, digital versatile disks (DVD) or other optical disk storage, magnetic cassettes, magnetic tape, magnetic disk storage or other magnetic storage devices, or any other medium which can be used to store information, and which can be accessed by the computing system. The CRM may be communicatively coupled to a system bus, enabling communication between the CRM and other systems or components coupled to the system bus. In some implementations the CRM may be coupled to the system bus via a memory interface (e.g., a memory controller). A memory interface is circuitry that manages the flow of data between the CRM and the system bus.

[0105] Network according to some embodiments: As used herein and unless otherwise specified, when used in the context of system(s) or device(s) that communicate information or data, the term “network” (e.g., the networks **105** and **440**) refers to a collection of nodes (e.g., devices or systems capable of sending, receiving or forwarding information) and links which are connected to enable telecommunication between the nodes.

[0106] Each of the described networks may include dedicated routers responsible for directing traffic between nodes, and, in certain examples, dedicated devices responsible for configuring and managing the network. Some or all of the nodes may be also adapted to function as routers in order to direct traffic sent between other network devices. Network devices may be inter-connected in a wired or wireless manner, and network devices may have different routing and transfer capabilities. For example, dedicated routers may be capable of high-volume transmissions while some nodes may be capable of sending and receiving relatively little traffic over the same period of time. Additionally, the connections between nodes on a network may have different throughput capabilities and different attenuation characteristics. A fiberoptic cable, for example, may be

capable of providing a bandwidth several orders of magnitude higher than a wireless link because of the difference in the inherent physical limitations of the medium. If desired, each described network may include networks or sub-networks, such as a local area network (LAN) or a wide area network (WAN).

[0107] Node according to some embodiments: Generally speaking, the term “node” refers to a connection point, redistribution point, or a communication endpoint. A node may be any device or system (e.g., a computer system) capable of sending, receiving or forwarding information. For example, end-devices or end-systems that originate or ultimately receive a message are nodes. Intermediary devices that receive and forward the message (e.g., between two end-devices) are also generally considered to be “nodes.”

[0108] Processor according to some embodiments: The various operations of example methods described herein may be performed, at least partially, by one or more processors (e.g., the one or more processors in the processor unit **142**). Generally speaking, the terms “processor” and “microprocessor” are used interchangeably, each referring to a computer processor configured to fetch and execute instructions stored to memory. By executing these instructions, the processor(s) can carry out various operations or functions defined by the instructions. The processor(s) may be temporarily configured (e.g., by instructions or software) or permanently configured to perform the relevant operations or functions (e.g., a processor for an Application Specific Integrated Circuit, or ASIC), depending on the particular embodiment. A processor may be part of a chipset, which may also include, for example, a memory controller or an I/O controller. A chipset is a collection of electronic components in an integrated circuit that is typically configured to provide I/O and memory management functions as well as a plurality of general purpose or special purpose registers, timers, etc. Generally speaking, one or more of the described processors may be communicatively coupled to other components (such as memory devices and I/O devices) via a system bus.

[0109] The performance of certain of the operations may be distributed among the one or more processors, not only residing within a single machine, but deployed across a number of machines. In some example embodiments, the processor or processors may be located in a single location (e.g., within a home environment, an office environment or as a server farm), while in other embodiments the processors may be distributed across a number of locations.

[0110] Words such as “processing,” “computing,” “calculating,” “determining,” “presenting,” “displaying,” or the like may refer to actions or processes of a machine (e.g., a computer) that manipulates or transforms data represented as physical (e.g., electronic, magnetic, or optical) quantities within one or more memories (e.g., volatile memory, non-volatile memory, or a combination thereof), registers, or other machine components that receive, store, transmit, or display information.

[0111] Although specific embodiments of the present disclosure have been described, it will be understood by those of skill in the art that there are other embodiments that are equivalent to the described embodiments. Accordingly, it is to be understood that the present disclosure is not to be limited by the specific illustrated embodiments.

Claims

1. A charging system, comprising: an external power source, wherein the external power source comprises: a first groove; and a second groove separate from the first groove; and a housing, comprising: an internal power source configured to be wirelessly charged by the external power source that is removably coupled to the housing; and a component configured to draw energy from the internal power source.
2. The charging system of claim 1, wherein: the first groove is configured to removably couple the external power source with the housing.

3. The charging system of claim 2, wherein: the second groove is configured to removably couple the external power source with the housing.
 4. The charging system of claim 1, wherein: the housing comprises a ring shape and is configured to be worn by a user of the housing.
 5. The charging system of claim 1, wherein: one or more of the first groove or the second groove is disposed on a portion of an outer perimeter of the external power source.
 6. The charging system of claim 1, wherein: the housing comprises a mechanical interface to facilitate connection with one or more of the first groove or the second groove.
 7. The charging system of claim 6, wherein: the mechanical interface comprises a friction fit interface.
 8. The charging system of claim 6, wherein: the mechanical interface of the housing is disposed at a surface of the housing.
 9. The charging system of claim 1, further comprising: the housing is configured to operate in a first power mode when the external power source is coupled to the housing; and the housing is configured to operate in a second power mode when the external power source is not coupled to the housing, wherein the first power mode is different from the second power mode.
 10. The charging system of claim 1, wherein: the housing comprises a light emitting diode (LED) to output information to a user.
 11. A charging system, comprising: a charging housing, wherein the charging housing comprises: a power source; a first groove; a second groove separate from the first groove; and a ring housing, comprising: an internal power source configured to be wirelessly charged by the power source of the charging housing while the charging housing is removably coupled to the ring housing; and a component configured to draw energy from the internal power source.
 12. A method of providing a charging system, comprising: providing an external power source, comprising: providing a first groove; and providing a housing, comprising: providing an internal power source configured to be wirelessly charged by the external power source that is removably coupled to the housing; and providing a component configured to draw energy from the internal power source.
 13. The method of claim 12, further comprising: threading the first groove onto the housing.
 14. The method of claim 12, further comprising: removably mating the first groove with the housing.
 15. The method of claim 12, further comprising: providing the first groove on a portion of an outer perimeter of the external power source.
 16. The method of claim 12, wherein: providing the housing further comprises: providing a mechanical interface to facilitate connection of the housing with the first groove.
 17. The method of claim 16, wherein: providing the mechanical interface further comprises: disposing the mechanical interface at an inside surface of the housing.
 18. The method of claim 16, wherein: the mechanical interface comprises a friction fit interface.
 19. The method of claim 12, wherein: providing the housing further comprises: configuring the housing to operate in a first power mode when the external power source is attached to the housing; and configuring the housing to operate in a second power mode when the external power source is not attached to the housing, wherein the first power mode is different from the second power mode.
 20. The method of claim 12, further comprising: providing a light emitting diode (LED) on the housing to output information to a user.
-