

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250280062

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

LEE; Sunghyup et al.

ELECTRONIC DEVICE COMPRISING ANTENNA

Abstract

An electronic device includes: a front plate; a rear plate; a side portion including a conductive portion and a non-conductive portion; a support portion; a printed circuit board including: a first surface facing the non-conductive portion; and a second surface facing a direction opposite to the first surface; at least one antenna element disposed on the first surface or disposed inside the printed circuit board closer to the first surface than to the second surface; and a bracket connecting the printed circuit board and the support portion and including: a first portion on which the printed circuit board is disposed; and a second portion extending from the first portion and fixed to the support portion by a screw. The support portion includes a wall protruding toward the rear plate. The printed circuit board is between the non-conductive portion and the wall. The wall supports the first portion.

Inventors: LEE; Sunghyup (Suwon-si, KR), YOO; Sungcheol (Suwon-si, KR), PARK; Jungsik (Suwon-si, KR), SON; Wangik (Suwon-si, KR)

Applicant: SAMSUNG ELECTRONICS CO., LTD. (Suwon-si, KR)

Family ID: 91084957

Assignee: SAMSUNG ELECTRONICS CO., LTD. (Suwon-si, KR)

Appl. No.: 19/210520

Filed: May 16, 2025

Foreign Application Priority Data

KR 10-2022-0153641

Nov. 16, 2022

KR 10-2022-0184884

Dec. 26, 2022

Related U.S. Application Data

parent WO continuation PCT/KR2023/018493 20231116 PENDING child US 19210520

Publication Classification

Int. Cl.: H04M1/02 (20060101); H01Q1/24 (20060101); H01Q1/38 (20060101)

U.S. Cl.:

CPC H04M1/02 (20130101); H01Q1/24 (20130101); H01Q1/38 (20130101);

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This application is a continuation application of International Application No. PCT/KR2023/018493, filed on Nov. 16, 2023, in the Korean Intellectual Property Receiving Office, which claims priority to Korean Patent Application No. 10-2022-0153641, filed on Nov. 16, 2022, in the Korean Intellectual Property Office, and Korean Patent Application No. 10-2022-0184884, filed on Dec. 26, 2022, in the Korean Intellectual Property Office, the disclosures of which are incorporated by reference herein in their entireties.

BACKGROUND

1. Field

[0002] The present disclosure relates to an electronic device including an antenna.

2. Description of Related Art

[0003] With the development of wireless communication technology, electronic devices are commonly used in daily life, and thus use of contents is increasing exponentially. Such electronic devices include a plurality of antennas to support various communication technologies. As the range of available applications expands, the number of antennas included in electronic devices is increasing.

[0004] While electronic devices are becoming slimmer, components for various functions are being added. Therefore, it becomes difficult to position an antenna in a limited space while securing coverage (or communication range) and radiation performance for a desired frequency band, while reducing the electrical effects with various elements within an electronic device.

SUMMARY

[0005] According to an aspect of the present disclosure, an electronic device includes: a front plate being at least a portion of a front surface of the electronic device; a rear plate being at least a portion of a rear surface of the electronic device; a side portion being at least a portion of a side surface of the electronic device and including a conductive portion being a portion of the side surface and a non-conductive portion being another portion of the side surface; a support portion between the front plate and the rear plate and connected to the side portion; a printed circuit board including: a first surface facing the non-conductive portion; and a second surface facing a direction opposite to the first surface; at least one antenna element disposed on the first surface or disposed inside the printed circuit board closer to the first surface than to the second surface; and a bracket connecting the printed circuit board and the support portion and including: a first portion on which the printed circuit board is disposed; and a second portion extending from the first portion and fixed to the support portion by a screw. The support portion includes a wall protruding toward the rear plate. The printed circuit board is between the non-conductive portion and the wall. The wall is configured to support the first portion.

[0006] The electronic device may further include a battery on the support portion and between the support portion and the rear plate. The wall may be between the printed circuit board and the battery, and the wall may be configured to support the battery.

[0007] The electronic device may further include an adhesive member between the support portion

and the rear plate. The support portion may include a third surface at least partially along the side portion. The third surface may face the rear plate and include: a first surface area corresponding to the adhesive member; and a second surface area corresponding to the second portion. The second portion may be fixed to the second surface area by the screw.

[0008] The first surface area may be closer to the rear plate than to the second surface area.

[0009] The support portion may further include a non-conductive wall at least partially between the non-conductive portion and the first surface and connected to the side portion.

[0010] The electronic device may further include a first air gap between the non-conductive wall and the first surface.

[0011] The electronic device may further include a second air gap provided between the non-conductive portion and the non-conductive wall.

[0012] The electronic device may further include a dielectric material of an adhesive material in the second air gap.

[0013] The non-conductive wall may include a recess. The printed circuit board may be inserted into the recess.

[0014] The electronic device may further include a first elastic member between the non-conductive wall and the printed circuit board.

[0015] The support portion may include a fourth surface connecting the wall and the non-conductive wall. The printed circuit board may be inserted into a recess formed by a combination of the wall, the non-conductive wall, and the fourth surface. The support portion may include a groove formed in the fourth surface. The bracket may include an insert inserted into the groove.

[0016] The insert may include a hemming structure.

[0017] The electronic device may further include a second elastic member between the first portion and the wall.

[0018] The electronic device may further include a communication circuit on the second surface. The communication circuit may be configured to transmit and/or receive a mmWave wireless signal through the at least one antenna element.

[0019] The electronic device may further include a heat-conductive material between the bracket and the support portion.

[0020] According to an aspect of the disclosure, provided is an electronic device including an antenna that may secure or improve coverage and/or antenna radiation performance.

[0021] According to an aspect of the disclosure, provided is an electronic device including a printed circuit board with at least one antenna element disposed thereon which may be stably positioned close to a non-conductive portion of the housing exterior. Thus, coverage and/or antenna radiation performance may be ensured or improved.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0022] The above and other aspects, features, and advantages of specific embodiments of the disclosure will become more apparent from the following detailed description taken in conjunction with the accompanying drawings, in which:

[0023] FIG. 1 is a block diagram of an electronic device according to one or more embodiments of the disclosure in a network environment;

[0024] FIG. 2 is a block diagram illustrating an electronic device in a network environment including a plurality of cellular networks, according to one or more embodiments of the disclosure;

[0025] FIG. 3 illustrates an electronic device according to one or more embodiments of the disclosure;

[0026] FIGS. 4 and 5 illustrate an antenna module according to one or more embodiments of the

disclosure;

[0027] FIG. **6** illustrates electronic devices according to various embodiments of the disclosure;

[0028] FIGS. **7** and **8** are exploded perspective views of the electronic device according to one or more embodiments of the disclosure;

[0029] FIG. **9** is a perspective view of an antenna module assembly according to one or more embodiments of the disclosure;

[0030] FIG. **10** is a view illustrating a combination of a frame, a battery, an antenna module assembly, a flexible printed circuit board, and a second adhesive member according to one or more embodiments of the present disclosure;

[0031] FIG. **11** is a perspective view illustrating a combination of a frame, an antenna module assembly, and a battery according to one or more embodiments of the present disclosure;

[0032] FIG. **12** is a cross-sectional view of an electronic device according to one or more embodiments of the disclosure taken along line A-A' in FIG. **10**;

[0033] FIG. **13** is a cross-sectional view of the electronic device according to one or more embodiments of the disclosure taken along line C-C' in FIG. **10**;

[0034] FIG. **14** is a cross-sectional view of the electronic device according to one or more embodiments of the disclosure taken along line D-D' in FIG. **10**;

[0035] FIG. **15** is a cross-sectional view of the electronic device according to one or more embodiments of the disclosure taken along line E-E';

[0036] FIG. **16** is a cross-sectional view of the electronic device according to one or more embodiments of the disclosure taken along line F-F';

[0037] FIGS. **17** and **18** are cross-sectional views each illustrating the assembly of an antenna module assembly and a frame according to one or more embodiments of the present disclosure; and

[0038] FIG. **19** illustrates a cross-sectional view of an electronic device according to one or more embodiments of the present disclosure, a cross-sectional view of an electronic device according to a comparative example, heat maps illustrating electromagnetic wave energy (or wave energy) radiated from the electronic device according to the embodiment, and heat maps illustrating electromagnetic wave energy radiated from the electronic device according to the comparative example.

DETAILED DESCRIPTION

[0039] Hereinafter, various example embodiments of the disclosure disclosed herein will be described in greater detail with reference to the accompanying drawings.

[0040] FIG. **1** is a block diagram of an electronic device **101** in a network environment **100** according to one or more embodiments of the disclosure.

[0041] Referring to FIG. **1**, the electronic device **101** in the network environment **100** may communicate with an external electronic device **102** via a first network **198** (e.g., a short-range wireless communication network), or at least one of an external electronic device **104** or a server **108** via a second network **199** (e.g., a long-range wireless communication network). The electronic device **101** may communicate with the external electronic device **104** via the server **108**. The electronic device **101** may include a processor **120**, memory **130**, an input module **150**, a sound output module **155**, a display module **160**, an audio module **170**, a sensor module **176**, an interface **177**, a connecting terminal **178**, a haptic module **179**, a camera module **180**, a power management module **188**, a battery **189**, a communication module **190**, a subscriber identification module (SIM) **196**, and/or an antenna module **197**. In various embodiments of the disclosure, at least one (e.g., the connection terminal **178**) of the components may be omitted from the electronic device **101**, or one or more other components may be added in the electronic device **101**. In various embodiments of the disclosure, some of the components may be implemented as single integrated circuitry. For example, the sensor module **176**, the camera module **180**, or the antenna module **197** may be implemented as embedded in single component (e.g., the display module **160**).

[0042] The processor **120** may execute, for example, software (e.g., a program **140**) to control at

least one other component (e.g., a hardware or software component) of the electronic device **101** coupled with the processor **120**, and may perform various data processing or computation. As at least part of the data processing or computation, the processor **120** may load a command or data received from another component (e.g., the sensor module **176** or the communication module **190**) in a volatile memory **132**, process the command or the data stored in the volatile memory **132**, and store resulting data in a non-volatile memory **134**. The processor **120** may include a main processor **121** (e.g., a central processing unit (CPU) or an application processor (AP)), or an auxiliary processor **123** (e.g., a graphics processing unit (GPU), a neural processing unit (NPU), an image signal processor (ISP), a sensor hub processor, or a communication processor (CP)) that is operable independently from, or in conjunction with, the main processor **121**. Additionally or alternatively, the auxiliary processor **123** may be adapted to consume less power than the main processor **121**, or to be specific to a specified function. The auxiliary processor **123** may be implemented as separate from, or as part of the main processor **121**.

[0043] The auxiliary processor **123** may control, for example, at least some of functions or states related to at least one component (e.g., the display module **160**, the sensor module **176**, or the communication module **190**) among the components of the electronic device **101**, instead of the main processor **121** while the main processor **121** is in an inactive (e.g., a sleep) state, or together with the main processor **121** while the main processor **121** is in an active state (e.g., executing an application). The auxiliary processor **123** (e.g., an ISP or a CP) may be implemented as part of another component (e.g., the camera module **180** or the communication module **190**) functionally related to the auxiliary processor **123**. According to one or more embodiments of the disclosure, the auxiliary processor **123** (e.g., a neural network processing device) may include a hardware structure specified for processing an artificial intelligence model. The artificial intelligence model may be created through machine learning. Such learning may be performed, for example, in the electronic device **101** itself on which the artificial intelligence model is performed, or may be performed through a separate server (e.g., the server **108**). The learning algorithms may include, for example, supervised learning, unsupervised learning, semi-supervised learning, or reinforcement learning, but is not limited thereto. The artificial intelligence model may include a plurality of artificial neural network layers. The artificial neural network may be any of a deep neural network (DNN), a convolutional neural network (CNN), a recurrent neural network (RNN), a restricted Boltzmann machine (RBM), a deep belief network (DBN), a bidirectional recurrent DNN (BRDNN), a deep Q-network, or a combination of two or more of the above-mentioned networks, but is not limited the above-mentioned examples. In addition to the hardware structure, the artificial intelligence model may additionally or alternatively include a software structure.

[0044] The memory **130** may store various data used by at least one component (e.g., the processor **120** or the sensor module **176**) of the electronic device **101**. The various data may include, for example, software (e.g., the program **140**) and input data or output data for a command related thereto. The memory **130** may include the volatile memory **132** and/or the non-volatile memory **134**.

[0045] The program **140** may be stored in the memory **130** as software, and may include, for example, an operating system (OS) **142**, middleware **144**, and/or an application **146**.

[0046] The input module **150** may receive a command or data to be used by another component (e.g., the processor **120**) of the electronic device **101**, from the outside (e.g., a user) of the electronic device **101**. The input module **150** may include, for example, a microphone, a mouse, a keyboard, a key (e.g., a button), or a digital pen (e.g., a stylus pen).

[0047] The sound output module **155** may output sound signals to the outside of the electronic device **101**. The sound output module **155** may include, for example, a speaker or a receiver. The speaker may be used for general purposes, such as playing multimedia or playing record, and the receiver may be used for incoming calls. The receiver may be implemented as separate from, or as part of the speaker.

[0048] The display module **160** may visually provide information to the outside (e.g., a user) of the electronic device **101**. The display module **160** may include, for example, a display, a hologram device, or a projector and control circuitry to control a corresponding one of the display, hologram device, and projector. The display module **160** may include touch circuitry (e.g., a touch sensor) adapted to detect a touch, or sensor circuitry (e.g., a pressure sensor) adapted to measure the intensity of force incurred by the touch.

[0049] The audio module **170** may convert a sound into an electrical signal and vice versa. The audio module **170** may obtain the sound via the input module **150**, or output the sound via the sound output module **155** or a headphone of an external electronic device (e.g., the external electronic device **102**) directly (e.g., wiredly) or wirelessly coupled with the electronic device **101**.

[0050] The sensor module **176** may detect an operational state (e.g., power or temperature) of the electronic device **101** or an environmental state (e.g., a state of a user) external to the electronic device **101**, and then generate an electrical signal or data value corresponding to the detected state. The sensor module **176** may include, for example, a gesture sensor, a gyro sensor, an atmospheric pressure sensor, a magnetic sensor, an acceleration sensor, a grip sensor, a proximity sensor, a color sensor, an infrared (IR) sensor, a biometric sensor, a temperature sensor, a humidity sensor, or an illuminance sensor.

[0051] The interface **177** may support one or more specified protocols to be used for the electronic device **101** to be coupled with the external electronic device (e.g., the external electronic device **102**) directly (e.g., wiredly) or wirelessly. The interface **177** may include, for example, a high-definition multimedia interface (HDMI), a universal serial bus (USB) interface, a secure digital (SD) card interface, and/or an audio interface.

[0052] The connecting terminal **178** may include a connector via which the electronic device **101** may be physically connected with the external electronic device (e.g., the external electronic device **102**). The connecting terminal **178** may include, for example, an HDMI connector, a USB connector, an SD card connector, and/or an audio connector (e.g., a headphone connector).

[0053] The haptic module **179** may convert an electrical signal into a mechanical stimulus (e.g., a vibration or a movement) or electrical stimulus which may be recognized by a user via his tactile sensation or kinesthetic sensation. The haptic module **179** may include, for example, a motor, a piezoelectric element, or an electric stimulator.

[0054] The camera module **180** may capture a still image or moving images. The camera module **180** may include one or more lenses, image sensors, ISPs, or flashes.

[0055] The power management module **188** may manage power supplied to or consumed by the electronic device **101**. The power management module **188** may be implemented as at least part of, for example, a power management integrated circuit (PMIC).

[0056] The battery **189** may supply power to at least one component of the electronic device **101**. The battery **189** may include, for example, a primary cell which is not rechargeable, a secondary cell which is rechargeable, and/or a fuel cell.

[0057] The communication module **190** may support establishing a direct (e.g., wired) communication channel or a wireless communication channel between the electronic device **101** and the external electronic device (e.g., the external electronic device **102**, the external electronic device **104**, or the server **108**) and performing communication via the established communication channel. The communication module **190** may include one or more CPs that are operable independently from the processor **120** (e.g., the AP) and supports a direct (e.g., wired) communication or a wireless communication. The communication module **190** may include a wireless communication module **192** (e.g., a cellular communication module, a short-range wireless communication module, or a global navigation satellite system (GNSS) communication module) or a wired communication module **194** (e.g., a local area network (LAN) communication module or a power line communication (PLC) module). A corresponding one of these communication modules may communicate with the external electronic device via the first network

198 (e.g., a short-range communication network, such as BLUETOOTH, wireless-fidelity (Wi-Fi) direct, or IR data association (IrDA)) or the second network **199** (e.g., a long-range communication network, such as a legacy cellular network, a 5th generation (5G) network, a next generation communication network, the Internet, or a computer network (e.g., LAN or wide area network (WAN))). These various types of communication modules may be implemented as a single component (e.g., a single chip), or may be implemented as multi components (e.g., multi chips) separate from each other. The wireless communication module **192** may identify and authenticate the electronic device **101** in a communication network, such as the first network **198** or the second network **199**, using subscriber information (e.g., international mobile subscriber identity (IMSI)) stored in the SIM **196**.

[0058] The wireless communication module **192** may support a 5G network, after a 4th generation (4G) network, and next-generation communication technology, e.g., new radio (NR) access technology. The NR access technology may support high-speed transmission of high-capacity data (i.e., enhanced mobile broadband (eMBB)), minimization of terminal power and connection of multiple terminals (massive machine type communications (mMTC)), or high reliability and low latency (ultra-reliable and low-latency communications (URLLC)). The wireless communication module **192** may support a high-frequency band (e.g., a mmWave band) to achieve, for example, a high data transmission rate. The wireless communication module **192** may support various technologies for securing performance in a high-frequency band, such as beamforming, massive multiple-input and multiple-output (MIMO), full-dimensional MIMO (FD-MIMO), array antenna, analog beam-forming, or large-scale antenna. The wireless communication module **192** may support various requirements specified in the electronic device **101**, an external electronic device (e.g., external the electronic device **104**), or a network system (e.g., the second network **199**). According to one or more embodiments of the disclosure, the wireless communication module **192** may support a peak data rate for implementing eMBB (e.g., 20 Gbps or more), loss coverage for implementing mMTC (e.g., 164 dB or less), or U-plane latency for realizing URLLC (e.g., 0.5 ms or less for each of downlink (DL) and uplink (UL) or 1 ms or less for round trip).

[0059] The antenna module **197** may transmit or receive a signal or power to or from the outside (e.g., the external electronic device) of the electronic device **101**. The antenna module **197** may include an antenna including a radiating element including a conductive material or a conductive pattern formed in or on a substrate (e.g., a printed circuit board (PCB)). The antenna module **197** may include a plurality of antennas (e.g., an antenna array). In such a case, at least one antenna appropriate for a communication scheme used in the communication network, such as the first network **198** or the second network **199**, may be selected, for example, by the communication module **190** (e.g., the wireless communication module **192**) from the plurality of antennas. The signal or the power may then be transmitted or received between the communication module **190** and the external electronic device via the selected at least one antenna. Another component (e.g., a radio frequency integrated circuit (RFIC)) other than the radiating element may be additionally formed as part of the antenna module **197**.

[0060] According to various embodiments of the disclosure, the antenna module **197** may form a mmWave antenna module. According to one or more embodiments of the disclosure, the mm Wave antenna module may include a PCB, an RFIC that is disposed on or adjacent to a first surface (e.g., the bottom surface) of the PCB and is capable of supporting a predetermined high-frequency band (e.g., a mmWave band), and a plurality of antennas (e.g., array antennas) that is disposed on or adjacent to a second surface (e.g., the top surface or the side surface) of the PCB and is capable of transmitting or receiving a signal of the predetermined high-frequency band.

[0061] At least some of the above-described components may be coupled mutually and communicate signals (e.g., commands or data) therebetween via an inter-peripheral communication scheme (e.g., a bus, general purpose input and output (GPIO), serial peripheral interface (SPI), or mobile industry processor interface (MIPI)).

[0062] Commands or data may be transmitted or received between the electronic device **101** and the external electronic device **104** via the server **108** coupled with the second network **199**. Each of the external electronic devices **102** or **104** may be a device of a same type as, or a different type, from the electronic device **101**. All or some of operations to be executed at the electronic device **101** may be executed at one or more of the external electronic devices **102**, **104**, or **108**. For example, if the electronic device **101** should perform a function or a service automatically, or in response to a request from a user or another device, the electronic device **101**, instead of, or in addition to, executing the function or the service, may request the one or more external electronic devices to perform at least part of the function or the service. The one or more external electronic devices receiving the request may perform the at least part of the function or the service requested, or an additional function or an additional service related to the request, and transfer an outcome of the performing to the electronic device **101**. The electronic device **101** may provide the outcome, with or without further processing of the outcome, as at least part of a reply to the request. To that end, a cloud computing, distributed computing, mobile edge computing (MEC), or client-server computing technology may be used, for example. The electronic device **101** may provide an ultra-low delay service using, for example, distributed computing or MEC. In another embodiment of the disclosure, the external electronic device **104** may include an internet of things (IoT) device. The server **108** may be an intelligent server using machine learning and/or neural networks. According to one or more embodiments of the disclosure, the external electronic device **104** or the server **108** may be included in the second network **199**. The electronic device **101** may be applied to an intelligent service (e.g., smart home, smart city, smart car, or healthcare) based on 5G communication technology or IoT-related technology.

[0063] An electronic device according to one or more embodiments of the disclosure may be one of various types of electronic devices. The electronic devices may include a portable communication device (e.g., a smartphone), a computer device, a portable multimedia device, a portable medical device, a camera, a wearable device, or a home appliance. However, the electronic device is not limited to any of those described above.

[0064] Various embodiments of the disclosure and the terms used herein are not intended to limit the technological features set forth herein to particular embodiments and include various changes, equivalents, or replacements for a corresponding embodiment. With regard to the description of the drawings, similar reference numerals may be used to refer to similar or related elements. It is to be understood that a singular form of a noun corresponding to an item may include one or more of the things, unless the relevant context clearly indicates otherwise. As used herein, each of such phrases as “A or B,” “at least one of A and B,” “at least one of A or B,” “A, B, or C,” “at least one of A, B, and C,” and “at least one of A, B, or C,” may include any one of, or all possible combinations of the items enumerated together in a corresponding one of the phrases. As used herein, such terms as “1st” and “2nd,” or “first” and “second” may be used to simply distinguish a corresponding component from another, and does not limit the components in other aspect (e.g., importance or order). If an element (e.g., a first element) is referred to, with or without the term “operatively” or “communicatively,” as “coupled with,” “coupled to,” “connected with,” or “connected to” another element (e.g., a second element), the element may be coupled with the other element directly (e.g., wiredly), wirelessly, or via a third element.

[0065] The term “module” may include a unit implemented in hardware, software, or firmware, or any combination thereof, and may interchangeably be used with other terms, for example, “logic,” “logic block,” “part,” or “circuitry”. A module may be a single integral component, or a minimum unit or part thereof, adapted to perform one or more functions. For example, according to one or more embodiments of the disclosure, the module may be implemented in a form of an application-specific integrated circuit (ASIC).

[0066] Various embodiments as set forth herein may be implemented as software (e.g., the program **140**) including one or more instructions that are stored in a storage medium (e.g., an internal

memory **136** or an external memory **138**) that is readable by a machine (e.g., the electronic device **101**). For example, a processor (e.g., the processor **120**) of the machine (e.g., the electronic device **101**) may invoke at least one of the one or more instructions stored in the storage medium, and execute it, with or without using one or more other components under the control of the processor. This allows the machine to be operated to perform at least one function according to the at least one instruction invoked. The one or more instructions may include a code generated by a compiler or a code executable by an interpreter. The machine-readable storage medium may be provided in the form of a non-transitory storage medium. Wherein, the term “non-transitory” simply means that the storage medium is a tangible device, and does not include a signal (e.g., an electromagnetic wave), but this term does not differentiate between where data is semi-permanently stored in the storage medium and where the data is temporarily stored in the storage medium.

[0067] A method according to one or more embodiments of the disclosure may be included and provided in a computer program product. The computer program product may be traded as a product between a seller and a buyer. The computer program product may be distributed in the form of a machine-readable storage medium (e.g., compact disc read only memory (CD-ROM)), or be distributed (e.g., downloaded or uploaded) online via an application store (e.g., PLAYSTORE™), or between two user devices (e.g., smart phones) directly. If distributed online, at least part of the computer program product may be temporarily generated or at least temporarily stored in the machine-readable storage medium, such as memory of the manufacturer's server, a server of the application store, or a relay server.

[0068] Each component (e.g., a module or a program) of the above-described components may include a single entity or multiple entities. One or more of the above-described components may be omitted, or one or more other components may be added. Alternatively or additionally, a plurality of components (e.g., modules or programs) may be integrated into a single component. In such a case, the integrated component may perform one or more functions of each of the plurality of components in the same or similar manner as they are performed by a corresponding one of the plurality of components before the integration. Operations performed by the module, the program, or another component may be carried out sequentially, in parallel, repeatedly, or heuristically, or one or more of the operations may be executed in a different order or omitted, or one or more other operations may be added.

[0069] FIG. 2 is a block diagram **200** illustrating an electronic device **101** in a network environment including a plurality of cellular networks, according to one or more embodiments of the disclosure.

[0070] Referring to FIG. 2, the electronic device **101** may include a first communication processor **212**, a second communication processor **214**, a first radio frequency integrated circuit (RFIC) **222**, a second RFIC **224**, a third RFIC **226**, a fourth RFIC **228**, a first radio frequency front end (RFFE) **232**, a second RFFE **234**, a first antenna module **242**, a second antenna module **244**, and/or an antenna **248**. The electronic device **101** may include a processor **120** and memory **130**. The second network **199** may include a first cellular network **292** and a second cellular network **294**. According to another embodiment, the electronic device **101** may further include at least one of the components illustrated in FIG. 1, and the second network **199** may further include one or more other networks. According to one or more embodiments, the first communication processor **212**, the second communication processor **214**, the first RFIC **222**, the second RFIC **224**, the fourth RFIC **228**, the first RFFE **232**, and the second RFFE **234** may constitute at least a portion of an RF communication module **192**. According to another embodiment, the fourth RFIC **228** may be omitted, or may be included as a portion of the third RFIC **226**.

[0071] The first communication processor **212** may establish a communication channel in a band to be used for RF communication with the first cellular network **292**, and may support legacy network communication via the established communication channel. According to various embodiments, the first cellular network may be a legacy network including a 2nd generation (2G), 3G, 4G, or long-

term evolution (LTE) network. The second communication processor **214** may establish a communication channel corresponding to a predetermined band (e.g., about 6 GHz to about 60 GHz) in a band to be used for RF communication with the second cellular network **294**, and may support 5G network communication via the established communication channel. According to various embodiments, the second cellular network **294** may be a 5G network defined in the 3GPP. In addition, according to one or more embodiments, the first communication processor **212** or the second communication processor **214** may establish a communication channel corresponding to another predetermined band (e.g., about 6 GHz or lower) in the band to be used for RF communication with the second cellular network **294**, and may support 5G network communication through the established communication channel. According to one or more embodiments, the first communication processor **212** and the second communication processor **214** may be implemented in a single chip or in a single package. According to various embodiments, the first communication processor **212** or the second communication processor **214** may be formed in a single chip or a single package with the processor **120**, an auxiliary processor **123**, or a communication module **190**.

[0072] During transmission, the first RFIC **222** may convert a baseband signal generated by the first communication processor **212** into an RF signal of about 700 MHz to about 3 GHz to be used in the first cellular network **292** (e.g., a legacy network). During reception, an RF signal may be acquired from the first cellular network **292** (e.g., the legacy network) through an antenna (e.g., the first antenna module **242**), and may be pre-processed through an RFFE (e.g., the first RFFE **232**). The first RFIC **222** may convert the pre-processed RF signal into a baseband signal to be processed by the first communication processor **212**.

[0073] During transmission, the second RFIC **224** may convert the baseband signal generated by the first communication processor **212** or the second communication processor **214** into an RF signal in a Sub6 band (e.g., about 6 GHz or lower) (hereinafter, referred to as “5G Sub6 RF signal”) to be used in the second cellular network **294** (e.g., a 5G network). During reception, the 5G Sub6 RF signal may be acquired from the second cellular network **294** (e.g., a 5G network) through an antenna (e.g., the second antenna module **244**), and may be pre-processed through an RFFE (e.g., the second RFFE **234**). The second RFIC **224** may convert the pre-processed 5G Sub6 RF signal into a baseband signal so as to be processed by a corresponding one of the first communication processor **212** and the second communication processor **214**.

[0074] The third RFIC **226** may convert the baseband signal generated by the second communication processor **214** into an RF signal in a 5G Above6 band (e.g., about 6 GHz to about 60 GHz) (hereinafter, referred to as a “5G Above6 RF signal”) to be used in the second cellular network **294** (e.g., a 5G network). During reception, the 5G Above6 RF signal may be acquired from the second cellular network **294** (e.g., a 5G network) through an antenna (e.g., the second antenna module **248**), and may be pre-processed through the third RFFE **236**. The third RFIC **226** may convert the pre-processed 5G Above6 RF signal into a baseband signal to be processed by the second communication processor **214**. According to one or more embodiments, the third RFFE **236** may be provided as a portion of the third RFIC **226**.

[0075] According to one or more embodiments, the electronic device **101** may include a fourth RFIC **228** separately from or as at least a portion of the third RFIC **226**. In this case, the fourth RFIC **228** may convert the baseband signal generated by the second communication processor **214** into an RF signal (hereinafter, referred to as an “IF signal”) in an intermediate-frequency band (e.g., about 9 GHz to about 11 GHz), and may then deliver the IF signal to the third RFIC **226**. The third RFIC **226** may convert the IF signal into a 5G Above6 RF signal. During reception, the 5G Above6 RF signal may be acquired from the second cellular network **294** (e.g., a 5G network) via an antenna (e.g., the antenna **248**) and may be converted into an IF signal by the third RFIC **226**. The fourth RFIC **228** may convert the IF signal into a baseband signal to be capable of being processed by the second communication processor **214**.

[0076] According to one or more embodiments, the first RFIC **222** and the second RFIC **224** may be implemented as at least a portion of a single chip or a single package. According to one or more embodiments, the first RFFE **232** and the second RFFE **234** may be implemented as at least a portion of a single chip or a single package. According to one or more embodiments, at least one of the first antenna module **242** and the second antenna module **244** may be omitted, or may be combined with another antenna module to process RF signals of a plurality of corresponding bands. [0077] According to one or more embodiments, the third RFIC **226** and the antenna **248** may be disposed on the same substrate so as to provide a third antenna module **246**. For example, the RF communication module **192** or the processor **120** may be placed on a first substrate (e.g., a main PCB). In such a case, the third RFIC **226** may be disposed on a partial area (e.g., the top surface) of a second substrate (e.g., a sub-PCB) separate from the first substrate, and the antenna **248** may be disposed on another partial area (e.g., the bottom surface), thereby providing the third antenna module **246**. By disposing the third RFIC **226** and the antenna **248** on the same substrate, the length of the transmission line may be reduced therebetween. Through this, it is possible to reduce the loss (e.g., attenuation) of signals in a high-frequency band (e.g., about 6 GHz to about 60 GHz) to be used for, for example, 5G network communication by the transmission line. As a result, the electronic device **101** is able to improve the quality or speed of communication with the second cellular network **294** (e.g., a 5G network).

[0078] According to one or more embodiments, the antenna **248** may be configured as an antenna array that includes a plurality of antenna elements capable of being used for beamforming. In this case, the third RFIC **226** may include a plurality of phase converters **238** corresponding to the plurality of antenna elements, for example, as a portion of the third RFFE **236**. During transmission, each of the plurality of phase shifters **238** may convert the phase of a 5G Above6 RF signal to be transmitted to the outside of the electronic device **101** (e.g., a base station of a 5G network) via a corresponding antenna element. During reception, each of the plurality of phase shifters **238** may convert the phase of the 5G Above6 RF signal received from the outside into the same or substantially the same phase via the corresponding antenna element. This enables transmission or reception through beamforming between the electronic device **101** and the outside.

[0079] The second cellular network **294** (e.g., a 5G network) may be operated independently from the first cellular network **292** (e.g., a legacy network) (e.g., Stand-Alone (SA)), or may be operated in the state of being connected to the first network **592** (e.g., Non-Stand-Alone (NSA)). For example, a 5G network may include only an access network (e.g., a 5G radio access network (RAN) or a next-generation RAN (NG RAN)) but may not include a core network (e.g., a next-generation core (NGC)). In this case, after accessing the access network of the 5G network, the electronic device **101** may access an external network (e.g., the Internet) under the control of the core network (e.g., an evolved packed core (EPC)) of a legacy network. Protocol information for communication with a legacy network (e.g., LTE protocol information) or protocol information for communication with a 5G network (e.g., new radio (NR) protocol information) may be stored in the memory **230**, and may be accessed by another component (e.g., the processor **120**, the first communication processor **212**, or the second communication processor **214**).

[0080] FIG. **3** illustrates an electronic device **3** according to one or more embodiments of the disclosure. FIGS. **4** and **5** illustrate an antenna module **5** according to one or more embodiments of the disclosure.

[0081] In various embodiments of the disclosure, for convenience of description, the direction in which the front surface **30A** of the electronic device **3** is oriented or a display area included in the electronic device **3** is visually exposed is defined as the +z-axis direction, and the direction in which the rear surface **30B** of the electronic device **10B** is oriented is defined as the -z-axis direction.

[0082] Referring to FIG. **3**, an electronic device **3** (e.g., the electronic device **101** of FIG. **1**) may include a housing **30**. The housing **30** may provide, for example, the front surface **30A** of the

electronic device **3**, the rear surface **30B** of the electronic device **3**, and the side surface **30C** of the exemplary electronic device **3**. In various embodiments, the housing **30** may refer to a structure that provides at least a portion of the front surface **30A**, the rear surface **30B**, and the side surface **30C**. [0083] According to one or more embodiments, the housing **30** may include a front plate (or a front cover, a first cover, or a first plate) **31**, a rear plate (or a rear cover, a second cover, or a second plate) **32**, and/or a side portion (or a side surface portion, a side surface member, a side surface bezel structure, or a side wall portion) **33**.

[0084] According to one or more embodiments, the front plate **31** may provide at least a portion of the front surface **30A** of the electronic device **3**. At least a portion of the front plate **31** may be substantially transparent. The front plate **31** may include, for example, a glass plate including various coating layers, or a polymer plate.

[0085] According to one or more embodiments, the rear plate **32** may provide at least a portion of the rear surface **30B** of the electronic device **3**. The rear plate **32** may be substantially opaque. The rear plate **32** may be made of, for example, coated or colored glass, ceramic, polymer, metal (e.g., aluminum, stainless steel (STS), or magnesium), or a combination of two or more of these materials.

[0086] According to one or more embodiments, the side portion **33** may provide at least a portion of the side surface **30B** of the electronic device **3**. The side portion **33** may include a metallic material and/or a non-metallic material (e.g., polymer).

[0087] According to one or more embodiments, the side portion **33** may include a first side portion (or, a first side surface portion, a first side wall, a first side wall portion, a first bezel, or a first bezel portion) **331**, a second side portion (or, a second side surface portion, a second side wall, a second side wall portion, a second bezel, or a second bezel portion) **332**, a third side portion (or a third side surface portion, a third side wall, a third side wall portion, a third bezel, or a third bezel portion) **333**, and/or a fourth side portion (or, a fourth side surface portion, a fourth side wall, a fourth side wall portion, a fourth bezel, or a fourth bezel portion) **334**.

[0088] According to one or more embodiments, when viewed from above the front plate **31** (e.g., in the $-z$ -axis direction), the first side portion **331** may be spaced apart from the second side portion **332** in the $+x$ -axis direction and may be substantially parallel to the second side portion **332**. The first side portion **331** may provide a first side surface corresponding to the x -axis direction in the side surface **30C** of the electronic device **3**. The second side portion **332** may provide a second side surface corresponding to the x -axis direction in the side surface **30C** of the electronic device **3**.

[0089] According to one or more embodiments, the third side portion **333** may interconnect one end portion of the first side portion **331** and one end portion of the second side portion **332**. The fourth side portion **334** may interconnect the other end portion of the first side portion **331** and the other end portion of the second side portion **332**. When viewed from above the front plate **31**, the third side portion **333** may be spaced apart from the fourth side portion **334** in the $+y$ -axis direction and may be substantially parallel to the fourth side portion **334**. The third side portion **333** may provide a third side surface of the electronic device **3** corresponding to the $+y$ -axis direction in the side surface **30C** of the electronic device **3**. The fourth side portion **334** may provide a fourth side surface of the electronic device **3** corresponding to the $-y$ -axis direction in the side surface **30C** of the electronic device **3**.

[0090] According to one or more embodiments, a first corner where the first side portion **331** and the third side portion **333** are connected, a second corner where the first side portion **331** and the fourth side portion **334** are connected, a third corner where the second side portion **332** and the third side portion **333** are connected, and/or a fourth corner where the second side portion **332** and the fourth side portion **334** are connected may be implemented in a smoothly curved shape.

[0091] According to one or more embodiments, the side portion **33** may include a first metal portion **A1**, a second metal portion **A2**, a third metal portion **A3**, a fourth metal portion **A4**, a fifth metal portion **A5**, a sixth metal portion **A6**, a first insulation portion **B1**, a second insulation portion

B2, a third insulation portion B3, a fourth insulation portion B4, a fifth insulation portion B5, and/or a sixth insulation portion B6. The first insulation portion B1 may be disposed in a first segmentation portion between the first metal portion A1 and the second metal portion A2. The first metal portion A1 and the second metal portion A2 may be physically separated with the first insulation portion B1 interposed therebetween. The first insulation portion B1 may be disposed in the first segmentation portion between the first metal portion A1 and the second metal portion A2. The first metal portion A1 and the second metal portion A2 may be physically separated with the first insulation portion B1 interposed therebetween. The second insulation portion B2 may be disposed in a second segmentation portion between the second metal portion A2 and the third metal portion A3. The second metal portion A2 and the third metal portion A3 may be physically separated with the second insulation portion B2 interposed therebetween. The third insulation portion B3 may be disposed in a third segmentation portion between the third metal portion A3 and the fourth metal portion A4. The third metal portion A3 and the fourth metal portion A4 may be physically separated with the third insulation portion B3 interposed therebetween. The fourth insulation portion B4 may be disposed in a fourth segmentation portion between the fourth metal portion A4 and the fifth metal portion A5. The fourth metal portion A4 and the fifth metal portion A5 may be physically separated with the fourth insulation portion B4 interposed therebetween. The fifth insulation portion B5 may be disposed in a fifth segmentation portion between the fifth metal portion A5 and the sixth metal portion A6. The fifth metal portion A5 and the sixth metal portion A6 may be physically separated with the fifth insulation portion B5 interposed therebetween. The sixth insulation portion B6 may be disposed in a sixth segmentation portion between the first metal portion A1 and the sixth metal portion A6. The first metal portion A1 and the sixth metal portion A6 may be physically separated with the sixth insulation portion B6 interposed therebetween.

[0092] According to one or more embodiments, the side surface 30C of the electronic device 3 may include surface areas provided by the plurality of metal portions A1, A2, A3, A4, A5, and A6 and surface areas provided by the plurality of insulation portions B1, B2, B3, B4, B5, and B6. The surface areas provided by the plurality of metal portions A1, A2, A3, A4, A5, and A6 and the surface areas provided by the plurality of insulation portions B1, B2, B3, B4, B5, and B6 may be smoothly connected without a substantial height difference.

[0093] According to one or more embodiments, a combination of the plurality of metal portions A1, A2, A3, A4, A5, and A6 may be defined or interpreted as a side surface metal A (or a side surface metal body, a side surface metal structure, an outer metal body, an outer metal structure, a side surface conductor, a side surface conductive structure, an outer conductor, or an outer conductive structure).

[0094] According to various embodiments, the positions, shapes, or number of the plurality of metal portions included in the side portion 33 and the positions or number of the plurality of insulation portions provided to correspond to the plurality of metal portions may vary and are not limited to the illustrated examples.

[0095] According to one or more embodiments, the rear plate 32 may include a first rear plate 321 and a second rear plate 322 connected to the first rear plate 321. The first rear plate 321 may provide a partial surface area of the rear surface 30B of the electronic device 3, and the second rear plate 322 may provide another partial surface area of the rear surface 30B of the electronic device 3.

[0096] According to one or more embodiments, a periphery of the second rear plate 322 may include a first periphery connected to the first rear plate 321 and a second periphery connected to the side portion 33.

[0097] According to one or more embodiments, a partial surface area of the rear surface 30B of the electronic device 3 provided by the second rear plate 322 may be positioned higher in the direction in which the rear surface 30B of the electronic device 3 is oriented (e.g., the -z-axis direction) than another partial surface area of the rear surface 30B of the electronic device 3 provided by the first

rear plate **321**.

[0098] According to one or more embodiments, the second periphery of the second rear plate **322** connected to the side portion **33** may extend to correspond to the third corner where the first side portion **331** and the third side portion **333** are connected, a portion of the first side portion **331** extending from the third corner, and a portion of the third side portion **333** extending from the third corner. The third corner, the portion of the first side portion **331** extending from the third corner, and the portion of the third side portion **333** extending from the third corner may be positioned higher in the direction in which the rear surface **30B** of the electronic device **3** is oriented (e.g., the -z-axis direction) than other portions of the side portion **33** to correspond to the second periphery of the second rear plate **322**.

[0099] According to various embodiments, an integrated structure or member including the second rear plate **322** and the side portion **33** may be provided. For example, the second rear plate **322** may be connected to a metal portion (e.g., the first metal portion **A1**) included in the side portion **33** and may include the same metallic material as the metal portion.

[0100] According to various embodiments, a partial surface area of the rear surface **30B** of the electronic device **3** provided by the first rear plate **321** and another partial surface area of the rear surface **30B** of the electronic device **3** provided by the second rear plate **322** may be implemented such that there is substantially no height difference therebetween (not separately illustrated).

[0101] According to various embodiments, an integrated rear plate (not separately illustrated) replacing the first rear plate **321** and the second rear plate **322** may be provided.

[0102] According to one or more embodiments, the electronic device **3** may include a display module **401**, a first camera module **402**, a second camera module **403**, a third camera module **404**, a fourth camera module **405**, a first light-emitting module **406**, a second light-emitting module (not separately illustrated), a first sensor module **407**, a second sensor module (not separately illustrated), a first audio input module (not separately illustrated), a second audio input module (not separately illustrated), a first audio output module (not separately illustrated), a second audio output module (not separately illustrated), a first key input module **412**, a second key input module **413**, a first connection terminal **414**, a second connection terminal (not separately illustrated), and/or an antenna module **5**. The electronic device **3** may omit at least one of the above-mentioned components or may additionally include other components.

[0103] According to one or more embodiments, the display area (or active area) of the display module **401** may be visible through the front plate **31**.

[0104] According to one or more embodiments, the electronic device **3** may be implemented so that the display area, which is visible through the front plate **31**, as large as possible (e.g., a large screen or full screen). For example, the display module **401** may be implemented to have a periphery having substantially the same shape as the periphery of the front plate **31**.

[0105] According to one or more embodiments, the first camera module **402**, the second camera module **403**, the third camera module **404**, or the fourth camera module **405** may include one or more lenses, one or more image sensors, and/or an image signal processor (ISP).

[0106] According to one or more embodiments, the first camera module **402**, the second camera module **403**, and the third camera module **404** may be provided to correspond to the rear surface **30B** of the electronic device **3**. The first camera module **402**, the second camera module **403**, or the third camera module **404** may be defined or interpreted as a “rear camera module.”

[0107] According to one or more embodiments, the first camera module **402** is positioned to correspond to a first camera hole provided in the second rear plate **322** and is visible from the exterior of the electronic device **1** through the first camera hole. The second camera module **403** is positioned to correspond to a second camera hole provided in the second rear plate **322** and is visible from the outside of the electronic device **3** through the second camera hole. The third camera module **403** is positioned to correspond to a third camera hole provided in the second rear plate **322** and is visible from the outside of the electronic device **3** through the third camera hole. In

various embodiments, the second rear plate **322** may be implemented to provide a first light-transmitting area replacing the first camera hole, a second light-transmitting area replacing the second camera hole, and/or a third light-transmitting area replacing the third camera hole. In various embodiments, the second rear plate **322** may be referred to as a “camera deco portion.”

[0108] According to one or more embodiments, when viewed from above of the rear surface **30B** of the electronic device **3** (e.g., when viewed in the +z-axis direction), the first camera module **402**, the second camera module **403**, and the third camera module **404** may be aligned in a direction from the third side portion **333** toward the fourth side portion **334** (e.g., the -y-axis direction). When viewed from above the rear surface **30B** of the electronic device **3**, the first camera module **402** may be positioned to correspond to the first corner where the first side portion **331** and the third side portion **333** are connected, and the second camera module **403** may be positioned between the first camera module **402** and the third camera module **404**.

[0109] According to various embodiments, the relative positions among the first camera module **402**, the second camera module **403**, and the third camera module **404**, and the shape of the second rear plate **322** corresponding to the relative positions may vary (not separately illustrated) without being limited to the illustrated example. The number of camera modules corresponding to the second rear plate **322** may vary (not separately illustrated) without being limited to the illustrated example.

[0110] According to various embodiments, the first camera module **402**, the second camera module **403**, or the third camera module **404** may include a wide-angle camera module, a telephoto camera module, a color camera module, a monochrome camera, or an IR camera (e.g., a time-of-flight (TOF) camera or a structured light camera module).

[0111] According to one or more embodiments, the first camera module **402**, the second camera module **403**, and the third camera module **404** may have different properties (e.g., angles of view) or functions.

[0112] According to various embodiments, the first camera module **402**, the second camera module **403**, or the third camera module **404** may provide different angles of view (or lenses with different angles of view). The electronic device **3** may selectively use the angle of view of the first camera module **402**, the second camera module **403**, or the third camera module **404** based on a user's selection regarding the angle of view.

[0113] According to one or more embodiments, the fourth camera module **405** may be positioned inside the electronic device **3** to correspond to the front surface **30A** of the electronic device **3**. External light may pass through the front plate **31** and may reach the fourth camera module **405**. The fourth camera module **405** may be defined or interpreted as a “front camera module.”

[0114] According to one or more embodiments, the fourth camera module **405** may be positioned closer to the third side portion **333** than to the fourth side portion **334** when viewed from above the front surface **30A** of the electronic device **3** (e.g., when viewed in the -z axis direction). When viewed from above the front **30A** of the electronic device **3**, the separation distance of the fourth camera module **405** from the first side portion **331** and the separation distance of the fourth camera module **405** from the second side portion **332** may be substantially the same.

[0115] According to one or more embodiments, the fourth camera module **405** may be positioned to be aligned with an opening provided in the display area of the display module **401** or may be at least partially inserted into the opening. External light may reach the fourth camera module **405** through the front plate **31** and the opening in the display area. The opening of the display area aligned with or overlapping the fourth camera module **405** may be provided in the form of a hole. In various embodiments, when viewed from above on the front surface **30A** of the electronic device **3**, the opening of the display area aligned with or overlapping the fourth camera module **405** may be provided as a notch (not separately illustrated).

[0116] According to various embodiments, the fourth camera module **405** may overlap the display area of the display module **401** when viewed from above on the front surface **30A** of the electronic

device **3**. The fourth camera module **405** may be positioned on the rear surface of the display area or below or beneath the display area. When viewed from the outside of the electronic device **3**, the fourth camera module **405** or the position of the fourth camera module **405** may not be substantially visually distinguished (or exposed). The fourth camera module **405** may include, for example, a hidden behind-display camera (e.g., an under-display camera (UDC)). External light may pass through the front plate **31** and the display area to reach the fourth camera module **405**. [0117] According to various embodiments, the fourth camera module **405** may be positioned to be aligned with a recess (not separately illustrated) provided in the rear surface of the display area or may be at least partially inserted into the recess. When viewed from the outside of the electronic device **3**, the fourth camera module **405** or the position of the fourth camera module **405** may not be substantially visually distinguished (or exposed).

[0118] According to various embodiments, although not separately illustrated, the portion of the display area that at least partially overlaps the fourth camera module **405** may include a pixel structure and/or a wiring structure that is different from other areas. The pixel structure and/or the wiring structure provided in the portion of the display area that at least partially overlaps the fourth camera module **405** may be implemented to reduce light loss between the outside of the electronic device **3** and the fourth camera module **405**. The portion of the display area that at least partially overlaps the first sensor module **405** may have, for example, a different pixel density (e.g., the number of pixels per unit area) from other partial areas. For example, the portion of the display area that at least partially overlaps the fourth camera module **405** may not substantially include a plurality of pixels.

[0119] According to one or more embodiments, the first light-emitting module **406** may be provided to correspond to the rear surface **30B** of the electronic device **1**. The first light-emitting module **406** may include a light source for the first camera module **402**, the second camera module **403**, and/or the third camera module **404**. The first light-emitting module **406** may include, but is not limited to, an LED, an IR LED, or a xenon lamp.

[0120] According to one or more embodiments, the first light-emitting module **406** may be positioned to correspond to the flash hole (or light transmission area) provided in the first rear plate **321**.

[0121] According to various embodiment, the first light-emitting module **406** may be positioned to correspond to the flash hole (or light transmission area) provided in the first rear plate **322**.

[0122] According to one or more embodiments, a second light-emitting module (e.g., an LED, an IR LED, or a xenon lamp) (not separately illustrated) may be provided to correspond to the front surface **30A** of the electronic device **3**. The second light-emitting module may provide status information of the electronic device **3** in the form of light. In various embodiments, the second light-emitting module may provide a light source that operates in conjunction with the operation of the fourth camera module **405**.

[0123] According to one or more embodiments, the first sensor module **407** may be positioned inside the electronic device **3** to correspond to the front surface **30A** of the electronic device **3**. The first sensor module **407** may include, for example, an optical sensor (e.g., a proximity sensor or an illuminance sensor). The position of first terminal units **407** may vary without being limited to the illustrated example.

[0124] According to one or more embodiments, the first sensor module **407** may overlap the display area of the display module **401** when viewed from above the front surface **30A** of the electronic device **3**. The first sensor module **407** may be positioned on the rear surface of the display area or below or beneath the display area. When viewed from the outside of the electronic device **3**, the first sensor module **407** or the position of the first sensor module **407** may not be substantially visually distinguished (or exposed). External light may pass through the front plate **31** and the display area to reach the first sensor module **407**.

[0125] According to various embodiments, the first sensor module **407** may be positioned to be

aligned with a recess (not separately illustrated) provided in the rear surface of the display area or may be at least partially inserted into the recess. When viewed from the outside of the electronic device **3**, the first sensor module **407** or the position of the first sensor module **407** may not be substantially visually distinguished (or exposed).

[0126] According to various embodiments, although not separately illustrated, the portion of the display area of the display module **401** that at least partially overlaps the first sensor module **407** may include a pixel structure and/or a wiring structure that is different from other areas. The pixel structure and/or the wiring structure provided in the portion of the display area that at least partially overlaps the first sensor module **407** may be implemented to reduce light loss between the outside of the electronic device **3** and the first sensor module **407**. For example, the portion of the display area that at least partially overlaps the first sensor module **407** may have a pixel density (e.g., the number of pixels per unit area) that is different from other partial areas. For example, the portion of the display area that at least partially overlaps the first sensor module **407** may not substantially include a plurality of pixels.

[0127] According to various embodiments, the first sensor module **407** may be positioned to be aligned with an opening provided in the display area of the display module **401** or may be at least partially inserted into the opening. External light may pass through the front plate **31** and the opening in the display area to reach the first sensor module **407**. The opening in the display area aligned with or overlapping the first sensor module **407** may be provided in the form of a hole. In various embodiments, when viewed from above on the front surface **30A** of the electronic device **3**, the opening of the display area aligned with or overlapping the first sensor module **407** may be provided as a notch (not separately illustrated).

[0128] According to various embodiments, the second sensor module (not separately illustrated) may include an optical, electrostatic, or ultrasonic biometric sensor (e.g., a fingerprint sensor). The second sensor module may be disposed in the electronic device **3** in at least partially the same as or similar to the first sensor module **407**. The electronic device **3** may further include one or more third sensor modules (not separately illustrated) provided at various other positions.

[0129] According to one or more embodiments, the first sound input module (not separately illustrated) may include a first microphone. The second sound input module (not separately illustrated) may include a second microphone. The first microphone may be positioned inside the electronic device **3** to correspond to the first microphone hole **408** provided in the fourth side portion **334**. The second microphone may be positioned inside the electronic device **3** to correspond to the second microphone hole **409** provided in the third side portion **333**. The positions or number of microphones and microphone holes **408** or **409** corresponding to the microphones may vary (not separately illustrated) without being limited to the illustrated example.

[0130] According to one or more embodiments, the first sound output module (not separately illustrated) may include a first speaker (not separately illustrated) used to reproduce data related to multimedia or recording. The first speaker may be positioned inside the electronic device **3** to correspond to the first speaker hole **410** provided in the fourth side portion **334**. The positions or number of first sound output modules including the first speaker may vary (not separately illustrated).

[0131] According to one or more embodiments, the second sound output module (not separately illustrated) may include a second speaker (e.g., a receiver for a call) (not separately used) used for a call. The second speaker may be positioned inside the electronic device **3** to correspond to the second speaker hole **411** (e.g., an opening in the form of a through hole or a notch) provided in the front plate **31** or the third side portion **333** between the front plate **31** and the third side portion **333**. The positions or number of second sound output modules including the second speaker may vary (not separately illustrated).

[0132] According to various embodiments, the first speaker may include a piezo speaker, in which case the first speaker hole **410** may be omitted.

[0133] According to various embodiments, the second speaker may include a piezo speaker, in which case the second speaker hole **411** may be omitted.

[0134] According to various embodiments, a first single hole (not separately illustrated) may be provided to replace the first microphone hole **408** and the first speaker hole **410**.

[0135] According to various embodiments, a second single hole (not separately illustrated) may be provided to replace the second microphone hole **409** and the second speaker hole **411**.

[0136] According to one or more embodiments, the first key input module **412** or the second key input module **413** may include a key positioned in an opening in the first side portion **331** and a key signal generator (not separately illustrated) configured to generate a key signal in response to a press or touch on the key. The positions or number of key input modules **412** or **413** may vary (not separately illustrated) without being limited to the illustrated example.

[0137] According to one or more embodiments, the first connection terminal **414** may be positioned inside the electronic device **3** to correspond to the first connection terminal hole provided in the fourth side portion **334**. An external electronic device may be electrically connected to the electronic device **3** via the first connection terminal **414**. The electronic device **3** may receive or transmit power and/or data from or to an external electronic device via the first connection terminal **414**. The first connection terminal **414** may include, for example, a USB connector or an HDMI connector. The positions or number of first connection terminals **414** may vary (not separately illustrated) without being limited to the illustrated example.

[0138] According to one or more embodiments, the second connection terminal (not separately illustrated) may be positioned inside the electronic device **3** to correspond to a second connector hole provided in the fourth side portion **334**. A cover member **415** may be positioned in the second connector hole to cover the second connection terminal. An external storage medium such as a SIM card (or a universal SIM (USIM) card) or a memory card (e.g., a secure digital (SD) memory card) may be connected to the second connector. The positions or number of second connection terminals may vary without being limited to the illustrated example.

[0139] According to one or more embodiments, the antenna module **5** may be positioned inside the electronic device **3** to correspond to the first side portion **331**. The antenna module **5** may be positioned closer to the first side portion **331** than to the second side portion **332**. Electromagnetic waves (or radio waves) transmitted (or radiated) from the antenna module **5** may pass through the first side portion **331** to propagate to the exterior of the electronic device **3**. Electromagnetic waves transmitted from the exterior of the electronic device **3** may pass through the first side portion **331** to be received (or detected) by the antenna module **5**.

[0140] According to various embodiments, the antenna module **5** may be the third antenna module **246** of FIG. **2**.

[0141] According to one or more embodiments, the antenna module **5** may include an antenna structure **51**, a communication circuit (or wireless communication circuit) **54**, and/or a power management circuit **55**.

[0142] According to one or more embodiments, the antenna structure **51** may include a printed circuit board **510**. The printed circuit board **510** may include a first surface **511** and a second surface **512** facing a direction opposite to the first surface **511**. The first surface **511** and the second surface **512** may, for example, be substantially parallel.

[0143] According to one or more embodiments, the first surface **511** of the printed circuit board **510** may face the first side portion **331**.

[0144] According to one or more embodiments, a first direction **501** in which the first surface **511** of the printed circuit board **510** is oriented may be substantially parallel to a direction from the second side portion **332** toward the first side portion **331** (e.g., the +x-axis direction) when viewed from above the front surface **30A** of the electronic device **3** (e.g., in the -z-axis direction).

[0145] According to one or more embodiments, the printed circuit board **510** may include a plurality of pattern layers (not separately illustrated) including conductive patterns and a plurality

of non-conductive layers (e.g., insulating layers) (not separately illustrated) alternately laminated with the plurality of pattern layers.

[0146] According to one or more embodiments, the printed circuit board **510** may include a plurality of conductive vias (not separately illustrated). The conductive vias may be conductive holes provided to allow connection wires to be disposed for electrically connecting conductive patterns of different pattern layers. The conductive vias may include, for example, a plated through hole (PTH), a laser via hole (LVH), a buried via hole (BVH), or a stacked via. At least one conductive via may, for example, electrically connect signal line patterns included in different pattern layers (e.g., patterns of conductive lines utilized as electrical paths) as portions of a signal line. At least one conductive via may, for example, electrically connect ground planes (or ground areas or ground patterns) included in different pattern layers.

[0147] According to one or more embodiments, the printed circuit board **510** may include an antenna array **52**. The antenna array **52** may, for example, be implemented as some conductive patterns among the plurality of pattern layers included in the printed circuit board **510**. The antenna array **52** may be disposed on the first surface **511** or disposed inside the printed circuit board **510** closer to the first surface **511** than to the second surface **512**. The antenna array **52** may include a plurality of antenna elements **521**, **522**, **523**, **524**, and **525**. The plurality of antenna elements **521**, **522**, **523**, **524**, and **525** may be, for example, the antenna **248** of FIG. 2.

[0148] According to one or more embodiments, the plurality of antenna elements **521**, **522**, **523**, **524**, and **525** may have substantially the same shape and may be disposed at regular intervals. The plurality of antenna elements **521**, **522**, **523**, **524**, and **525** may be disposed in a second direction **502** (e.g., the y-axis direction) when viewed from above the first surface **511** (e.g., in the +x-axis direction). The second direction **502** may be substantially parallel to a direction from the fourth side portion **334** toward the third side portion **333** (e.g., the +y-axis direction) or a direction from the third side portion **333** toward the fourth side portion **334** (e.g., the -y-axis direction) when viewed from above the front surface **30A** of the electronic device **3**.

[0149] According to one or more embodiments, when viewed from above the first surface **511** of the printed circuit board **510**, the plurality of antenna elements **521**, **522**, **523**, **524**, and **525** may be substantially square-shaped. For example, when viewed from above the first surface **511**, the first antenna element **521** may include a first edge **E1**, a second edge **E2**, a third edge **E3**, and a fourth edge **E4**. When viewed from above the first surface **511**, the first edge **E1** and the second edge **E2** may be spaced apart from each other in the second direction **502** and may be substantially parallel to each other. When viewed from above the first surface **511**, the third edge **E3** and the fourth edge **E4** may be spaced apart from each other in a third direction **503** perpendicular to the second direction **502** and may be substantially parallel to each other. The third direction **503** may be substantially parallel to a direction in which the front surface **30A** of the electronic device **3** is oriented or a direction in which the rear surface **30B** of the electronic device **3** is oriented. The remaining antenna elements **522**, **523**, **524**, and **525** may have substantially the same shape as the first antenna element **521**. The shape of the plurality of antenna elements **521**, **522**, **523**, **524**, and **525** is not limited thereto and may vary. The plurality of antenna elements **521**, **522**, **523**, **524**, and **525** may, for example, be provided in various polygonal shapes such as circular, elliptical, or triangular (not separately illustrated).

[0150] According to various embodiments, the number or positions of antenna elements included in the antenna array **52** are not limited to the illustrated embodiment and may vary (not separately illustrated).

[0151] According to various embodiments, the number or positions of antenna arrays **52** are not limited to the illustrated embodiment and may vary (not separately illustrated).

[0152] According to one or more embodiments, the printed circuit board **510** may include a ground plane **53** that functions as an antenna ground. The ground plane **53** may contribute to securing antenna radiation performance (or radio wave transmission/reception performance or

communication performance) and/or coverage with respect to the plurality of antenna elements **521, 522, 523, 524, and 525**. The ground plane **53** may reduce electromagnetic interference (EMI) (or signal loss) with respect to the plurality of antenna elements **521, 522, 523, 524, and 525**.

[0153] According to one or more embodiments, the ground plane **53** may be positioned closer to the second surface **512** of the printed circuit board **510** than to the antenna array **52**. When viewed from above the first surface **511** of the printed circuit board **510**, the antenna array **52** may at least partially overlap the ground plane **53**. For example, the antenna array **52** may be included in a first pattern layer (not separately illustrated) of the printed circuit board **510**, and the ground plane **53** may be included in a second pattern layer (not separately illustrated) closer to the second surface **512** than to the first pattern layer.

[0154] According to one or more embodiments, the antenna structure **51** may function as a patch antenna. When the communication circuit **54** provides (or feeds) electromagnetic signals (or wireless signals, RF signals, or radiation currents) to the plurality of antenna elements **521, 522, 523, 524, and 525**, the antenna structure **51** may function as a resonator (e.g., a patch antenna) since the plurality of antenna elements **521, 522, 523, 524, and 525** resonate with the ground plane **53** and act as radiating elements. The plurality of antenna elements **521, 522, 523, 524, and 525** may be interpreted as a plurality of patches.

[0155] According to one or more embodiments, the plurality of antenna elements **521, 522, 523, 524, and 525** may be included in a single pattern layer (not separately illustrated) among the plurality of pattern layers included in the printed circuit board **510** (e.g., a single-layer patch structure). For example, the plurality of antenna elements **521, 522, 523, 524, and 525** may be directly fed from the communication circuit **54**.

[0156] According to various embodiments, the printed circuit board **510** may further include a plurality of dummy antenna elements (e.g., dummy patches) (not separately illustrated) (e.g., a stacked patch structure). When viewed from above the first surface **511** of the printed circuit board **510**, the plurality of dummy antenna elements may be positioned to overlap one-to-one with the plurality of antenna elements **521, 522, 523, 524, and 525** and may be in an electrically floating state. A pattern layer including the plurality of dummy antenna elements may be positioned closer to the first surface **511** than to another pattern layer including the plurality of antenna elements **521, 522, 523, 524, and 525**. The communication circuit **54** provides (or feeds) electromagnetic signals (or wireless signals, RF signals, or radiation currents) to the plurality of antenna elements **521, 522, 523, 524, and 525**, and the dummy antenna elements may be indirectly fed from the plurality of antenna elements **521, 522, 523, 524, and 525**. The plurality of antenna elements **521, 522, 523, 524, and 525** may be defined or interpreted as a plurality of feeding antenna elements. The plurality of dummy antenna elements may be electromagnetically coupled with the plurality of antenna elements **521, 522, 523, 524, and 525**, may operate as a part of a radiator, and may adjust radiation characteristics. The plurality of dummy antenna elements may, for example, shift the resonant frequency of the antenna module **5** to a predetermined frequency or by a predetermined amount. The plurality of dummy antenna elements may, for example, expand the bandwidth in which electromagnetic waves can be transmitted or received via the antenna module **5**, or may form different frequency bands (e.g., multiple bands). The plurality of dummy antenna elements may, for example, reduce electromagnetic noise and improve antenna performance.

[0157] According to various embodiments, the printed circuit board **510** may further include a plurality of feeding antenna elements (not separately illustrated) that at least partially overlap the plurality of antenna elements **521, 522, 523, 524, and 525** and are physically separated from the plurality of antenna elements **521, 522, 523, 524, and 525** when viewed from above the first surface **511** (e.g., a stacked patch structure). A pattern layer including the plurality of antenna elements **521, 522, 523, 524, and 525** may be positioned closer to the first surface **511** than to a pattern layer including the plurality of feeding antenna elements. The communication circuit **54** provides (or feeds) electromagnetic signals (or wireless signals, RF signals, or radiation currents) to

the plurality of feeding antenna elements, and the plurality of antenna elements **521**, **522**, **523**, **524**, and **525** may be indirectly fed from the plurality of feeding antenna elements. The plurality of antenna elements **521**, **522**, **523**, **524**, and **525** may be interpreted as a plurality of dummy antenna elements.

[0158] According to one or more embodiments, the communication circuit **54** may be positioned on the second surface **512** of the printed circuit board **510** via a conductive adhesive material (or conductive bonding material) such as solder. The communication circuit **54** may be electrically connected to the plurality of antenna elements **521**, **522**, **523**, **524**, and **525** via wirings (or electrical paths) included in the printed circuit board **510**.

[0159] According to one or more embodiments, the communication circuit **54** may include a radio frequency integrated circuit (RFIC). The communication circuit **54** may correspond to, for example, the third RFIC **226** of FIG. **2**.

[0160] According to various embodiments, the communication circuit **54** may be disposed on a printed circuit board different from the printed circuit board **510**. The different printed circuit board may correspond to, for example, the first printed circuit board **74** of FIGS. **7** and **8**, on which components such as the processor **120**, the memory **130**, or the communication module **190** of FIG. **1** are disposed. For example, the communication circuit **54** may be omitted from the antenna module **5**.

[0161] According to one or more embodiments, the communication circuit **54** may perform up-converting or down-converting of a frequency of a transmitted or received signal. For example, the communication circuit **54** may receive an intermediate frequency (IF) signal from a wireless communication circuit (e.g., the wireless communication module **192** of FIG. **1**) disposed on a different printed circuit board (e.g., the first printed circuit board **74** of FIGS. **7** and **8**), and may up-convert the received IF signal into a radio frequency (RF) signal (e.g., a mmWave signal). As another example, the communication circuit **54** may down-convert an RF signal received via the antenna array **52** into an intermediate frequency (IF) signal, and the IF signal may be provided to a wireless communication circuit (e.g., the wireless communication module **192** of FIG. **1**) disposed on a different printed circuit board (e.g., the first printed circuit board **74** of FIGS. **7** and **8**).

[0162] According to one or more embodiments, the communication circuit **54** may transmit and/or receive signals in substantially the same frequency band (or frequency) via the plurality of antenna elements **521**, **522**, **523**, **524**, and **525**.

[0163] According to one or more embodiments, the communication circuit **54** may transmit and/or receive signals in at least a portion of a frequency band ranging from about 3 GHz to about 100 GHz via the plurality of antenna elements **521**, **522**, **523**, **524**, and **525**.

[0164] According to one or more embodiments, the power management circuit **55** may be disposed on the second surface **512** of the printed circuit board **510** via a conductive adhesive material (or conductive bonding material) such as solder. The power management circuit **55** may be electrically connected to the communication circuit **54** or various other components (e.g., passive elements) disposed on the printed circuit board **510** via wires (or electrical paths) included in the printed circuit board **510**.

[0165] According to one or more embodiments, the power management circuit **55** may include a power management integrated circuit (PMIC).

[0166] According to various embodiments, the power management circuit **55** may be disposed on a printed circuit board (e.g., the first printed circuit board **74** of FIGS. **7** and **8**) different from the printed circuit board **510**. For example, the power management circuit **55** may be omitted from the antenna module **5**.

[0167] According to one or more embodiments, the antenna module **5** may be electrically connected to a different printed circuit board (e.g., the first printed circuit board **74** of FIGS. **7** and **8**) via an electrical connection member (not separately illustrated), such as a flexible printed circuit board (FPCB) (e.g., the flexible printed circuit board **1000** of FIG. **10**). For example, one end

portion of the electrical connection member (not separately illustrated) may be electrically connected to a connector (e.g., an FPCB connector) (not separately illustrated) disposed on the second surface **512** of the printed circuit board **510**, and the other end of the electrical connection member may be electrically connected to a connector disposed on a different printed circuit board (e.g., the first printed circuit board **74** of FIGS. **7** and **8**). As another example, one end of the electrical connection member (not separately illustrated) may be electrically connected to conductive terminals (e.g., lands or copper pads) provided on the second surface **512** via a conductive adhesive material (or conductive bonding material) such as solder.

[0168] According to various embodiments, the antenna module **5** may further include a shielding member (or an electromagnetic shielding member) (not separately illustrated) that encloses at least one of the communication circuit **54** and/or the power management circuit **55**. The shielding member may reduce electromagnetic interference (e.g., electromagnetic noise) related to the communication circuit **54** and/or the power management circuit **55**. The shielding member may, for example, include a conductive member such as a shield can. As another example, the shielding member may include a protective member such as urethane resin and a conductive coating such as an electromagnetic interference (EMI) paint applied to the outer surface of the protective member. In various embodiments, the shielding member may be provided as various shielding sheets.

[0169] According to various embodiments, the antenna module **5** may further include a frequency tuning circuit (or matching circuit) (not separately illustrated) disposed on the printed circuit board **510**. The frequency tuning circuit may include, for example, a tuner or a passive element. The frequency tuning circuit may perform impedance matching, may shift a resonant frequency to a designated frequency, or may shift the resonant frequency by a predetermined amount.

[0170] According to one or more embodiments, the printed circuit board **510** may include a first electrical path (not separately illustrated) that transmits an electromagnetic signal (or wireless signal, RF signal, or radiation current) to the first antenna element **521**. The first electrical path may electrically connect the first antenna element **521** and the communication circuit **54**. The first electrical path may be defined or interpreted as a “first transmission line” or a “first feeding line” via which the electromagnetic signal is transmitted.

[0171] According to one or more embodiments, a portion of the first antenna element **521** to which an electromagnetic signal (or wireless signal, RF signal, or radiation current) is transmitted from the first electrical path may be defined or interpreted as a first feeding portion **FP1**. According to various embodiments, the first electrical path or a portion of the first electrical path connected to the first antenna element **521** may be defined or interpreted as a “first feeding portion,” and a portion of the first antenna element **521** to which the electromagnetic signal is transmitted from the first electrical path may be defined or interpreted as a “first feeding point.” Providing an electromagnetic signal to the first feeding portion **FP1** (or the first electrical path or the first feeding point) by the communication circuit **54** may be defined or interpreted as “first feeding.”

[0172] According to one or more embodiments, when viewed from above the first surface **511** of the printed circuit board **510**, the first feeding portion **FP1** may be positioned between the center **C** of the first antenna element **521** and the first edge **E1**. When viewed from above the first surface **511**, the distance of the center **C** of the first antenna element **521** from the first edge **E1** in the second direction **502** and the distance of the center **C** of the first antenna element **521** from the second edge **E2** may be substantially the same. When viewed from above the first surface **511**, the distance of the center **C** of the first antenna element **521** from the third edge **E3** in the third direction **503** and the distance of the center **C** of the first antenna element **521** from the fourth edge **E4** may be substantially the same.

[0173] According to one or more embodiments, when viewed from above the first surface

[0174] **511** of the printed circuit board **510**, the first feeding portion **FP1** may be positioned closer to the first edge **E1** than to the center **C** of the first antenna element **521**.

[0175] According to various embodiments, the first feeding portion **FP1** may be substantially

positioned at the first edge **E1** (not separately illustrated).

[0176] According to one or more embodiments, the printed circuit board **510** may include a second electrical path (not separately illustrated) that transmits an electromagnetic signal (or wireless signal, RF signal, or radiation current) to the first antenna element **521**. The second electrical path may electrically connect the first antenna element **521** and the communication circuit **54**. The second electrical path may be defined or interpreted as a “second transmission line” or a “second feeding line” via which the electromagnetic signal is transmitted.

[0177] According to one or more embodiments, a portion of the first antenna element **521** to which an electromagnetic signal (or wireless signal, RF signal, or radiation current) is transmitted from the second electrical path may be defined or interpreted as a second feeding portion **FP2**. According to various embodiments, the second electrical path or a portion of the second electrical path connected to the second antenna element **521** may be defined or interpreted as a “second feeding portion,” and a portion of the first antenna element **521** to which the electromagnetic signal is transmitted from the second electrical path may be defined or interpreted as a “second feeding point.” Providing an electromagnetic signal to the second feeding portion **FP2** (or the second electrical path or the second feeding point) by the communication circuit **54** may be defined or interpreted as “second feeding.”

[0178] According to one or more embodiments, when viewed from above the first surface **511** of the printed circuit board **510**, the second feeding portion **FP2** may be positioned between the center **C** of the first antenna element **521** and the third edge **E3**.

[0179] According to one or more embodiments, when viewed from above the first surface **511** of the printed circuit board **510**, the second feeding portion **FP2** may be positioned closer to the third edge **E3** than to the center **C** of the first antenna element **521**.

[0180] According to various embodiments, the second feeding portion **FP2** may be substantially positioned at the third edge **E3** (not separately illustrated).

[0181] According to one or more embodiments, when viewed from above the first surface **511** of the printed circuit board **510**, the first feeding portion **FP1** and the second feeding portion **FP2** may form a substantially 90-degree angle with respect to the center **C** of the first antenna element **521**.

[0182] According to one or more embodiments, when viewed from above the first surface **511** of the printed circuit board **510**, the distance by which the first feeding portion **FP1** is spaced apart from the center **C** of the first antenna element **521** in the second direction **502** may be substantially the same as the distance by which the second feeding portion **FP2** is spaced apart from the center **C** of the first antenna element **521** in the third direction **503**.

[0183] According to one or more embodiments, when viewed from above the first surface **511** of the printed circuit board **510**, the distance by which the first feeding portion **FP1** is spaced apart from the first edge **E1** in the second direction **502** may be substantially the same as the distance by which the second feeding portion **FP2** is spaced apart from the third edge **E3** in the third direction **503**.

[0184] According to one or more embodiments, when the communication circuit **54** provides (or feeds) an electromagnetic signal (or wireless signal, RF signal, or radiation current) to the first feeding portion **FP1** via the first electrical path, an electromagnetic wave of a first linear polarization may be radiated from the first antenna element **521**. When the communication circuit **54** provides an electromagnetic signal to the first feeding portion **FP1**, an electromagnetic wave of the first linear polarization having a first polarization direction may be radiated due to the current path (or the surface current distribution) on the first antenna element **521**. The first linear polarization may be an electromagnetic wave that oscillates in the first polarization direction. The first linear polarization may be interpreted as the polarity direction of the electric field with respect to the propagation direction (or transmission direction) of the electromagnetic wave radiated (or transmitted) from the first antenna element **521**. The first polarization direction may be the direction in which the electric field oscillates (or a direction parallel to the vector of the electric

field) and may be perpendicular to the propagation direction of the electromagnetic wave. The propagation direction of the electromagnetic wave may correspond to the direction in which the plane of the first antenna element **521**, having a flat plate (or planar) shape, is oriented (e.g., the first direction **501** in which the first surface **511** of the printed circuit board **510** is oriented).

[0185] According to one or more embodiments, during the first feeding, the first polarization direction of the first linear polarization radiated from the first antenna element **521** may be substantially the second direction **502**.

[0186] According to one or more embodiments, when the communication circuit **54** provides (or feeds) an electromagnetic signal (or wireless signal, RF signal, or radiation current) to the second feeding portion **FP2** via the second electrical path, an electromagnetic wave of a second linear polarization may be radiated from the first antenna element **521**. When the communication circuit **54** provides an electromagnetic signal to the second feeding portion **FP2**, an electromagnetic wave of the second linear polarization having a second polarization direction (or oscillating in the second polarization direction) may be radiated due to the current path (or the surface current distribution) on the first antenna element **521**. The second polarization direction may be perpendicular to the propagation direction of the electromagnetic wave (e.g., the $-z$ -axis direction).

[0187] According to one or more embodiments, during the second feeding, the second polarization direction of the second linear polarization radiated from the first antenna element **521** may be substantially the third direction **503**.

[0188] According to various embodiments, the first feeding portion **FP1** may be positioned between the center **C** of the first antenna element **521** and the second edge **E2** (not separately illustrated). When viewed from above the first surface **511** of the printed circuit board **510**, the first feeding portion **FP1** and the second feeding portion **FP2** may form a substantially 90-degree angle with respect to the center **C** of the first antenna element **521**. When viewed from above the first surface **511**, the distance by which the first feeding portion **FP1** is spaced apart from the center **C** of the first antenna element **521** in the second direction **502** may be substantially the same as the distance by which the second feeding portion **FP2** is spaced apart from the center **C** of the first antenna element **521** in the third direction **503**. When viewed from above the first surface **511**, the distance by which the first feeding portion **FP1** is spaced apart from the second edge **E2** in the second direction **502** may be substantially the same as the distance by which the second feeding portion **FP2** is spaced apart from the third edge **E3** in the third direction **503**.

[0189] According to various embodiments, the second feeding portion **FP2** may be positioned between the center **C** of the first antenna element **521** and the fourth edge **E4** (not separately illustrated). When viewed from above the first surface **511** of the printed circuit board **510**, the first feeding portion **FP1** and the second feeding portion **FP2** may form a substantially 90-degree angle with respect to the center **C** of the first antenna element **521**. When viewed from above the first surface **511**, the distance by which the first feeding portion **FP1** is spaced apart from the center **C** of the first antenna element **521** in the second direction **502** may be substantially the same as the distance by which the second feeding portion **FP2** is spaced apart from the center **C** of the first antenna element **521** in the third direction **503**. When viewed from above the first surface **511**, the distance by which the first feeding portion **FP1** is spaced apart from the first edge **E1** in the second direction **502** may be substantially the same as the distance by which the second feeding portion **FP2** is spaced apart from the fourth edge **E4** in the third direction **503**.

[0190] According to various embodiments, a single feeding portion replacing the first feeding portion **FP1** and the second feeding portion **FP2** may be provided. The single feeding portion may be substantially positioned, for example, at a first corner (e.g., a first vertex) where the first edge **E1** and the third edge **E3** meet, a second corner (e.g., a second vertex) where the second edge **E2** and the third edge **E3** meet, a third corner (e.g., a third vertex) where the second edge **E2** and the fourth edge **E4** meet, or a fourth corner (e.g., a fourth vertex) where the first edge **E1** and the fourth edge **E4** meet when viewed from above the first surface **511** of the printed circuit board **510**. As

another example, when viewed from above the first surface **511**, the single feeding portion may be positioned between the center C of the first antenna element **521** and the first corner, between the center C of the first antenna element **521** and the second corner, between the center C of the first antenna element **521** and the third corner, or between the center C of the first antenna element **521** and the fourth corner. When the communication circuit **54** provides (or feeds) an electromagnetic signal (or wireless signal, RF signal, or radiation current) to the feeding portion, the linear polarization radiated from the first antenna element **521** may have a polarization direction that is substantially parallel to a diagonal direction forming a substantially 45-degree angle with the second direction **502** or the third direction **503** when viewed from above the first surface **511**. The linear polarization having a diagonal polarization direction may be interpreted as a combination of a first polarization component parallel to the second direction **502** and a second polarization component parallel to the third direction **503**.

[0191] According to various embodiments, although not separately illustrated, the first antenna element **521** may be provided in a form that includes a first notch provided at the first edge E1, a second notch provided at the second edge E2, a third notch provided at the third edge E3, and/or a fourth notch provided at the fourth edge E4. When viewed from above the first surface **511** of the printed circuit board **510**, the center C of the first antenna element **521** may be positioned between the first notch and the second notch, and the first notch and the second notch may be provided substantially symmetrically with respect to the center C of the first antenna element **521**. When viewed from above the first surface **511**, the center C of the first antenna element **521** may be positioned between the third notch and the fourth notch, and the third notch and the fourth notch may be provided substantially symmetrically with respect to the center C of the first antenna element **521**.

[0192] According to various embodiments, although not separately illustrated, the first antenna element **521** may be provided in a form that includes a fifth notch provided at a first corner where the first edge E1 and the third edge E3 meet, a sixth notch provided at a second corner where the second edge E2 and the third edge E3 meet, a seventh notch provided at a third corner where the second edge E2 and the fourth edge E4 meet, and/or an eighth notch provided at a fourth corner where the first edge E1 and the fourth edge E4 meet. When viewed from above the first surface **511** of the printed circuit board **510**, the center C of the first antenna element **521** may be positioned between the fifth notch and the seventh notch, and the fifth notch and the seventh notch may be provided substantially symmetrically with respect to the center C of the first antenna element **521**. When viewed from above the first surface **511**, the center C of the first antenna element **521** may be positioned between the sixth notch and the eighth notch, and the sixth notch and the eighth notch may be provided substantially symmetrically with respect to the center C of the first antenna element **521**.

[0193] According to various embodiments, although not separately illustrated, the shape of the first antenna element **521** and the position of the feeding portion may be variously provided to radiate a linear polarization corresponding to at least one selected or predetermined frequency band. The linear polarization may be interpreted as a combination of a first polarization component and a second polarization component, which respectively have polarization directions perpendicular to the other.

[0194] According to various embodiments, although not separately illustrated, the shape of the first antenna element **521** and the position of the feeding portion may be variously provided to radiate a circular polarization corresponding to at least one selected or predetermined frequency band. The circular polarization may be interpreted as a combination of a first polarization component and a second polarization component, which have polarization directions perpendicular to each other. When the phase difference between the first polarization component and the second polarization component is substantially 90 degrees, the combination of the first polarization component and the second polarization component may provide a synthesized wave having characteristics of circular

polarization with an axial ratio that is substantially close to 1.

[0195] According to one or more embodiments, in substantially the same manner as the first resonator (e.g., a first patch resonator or a first patch resonating portion) (or a first radiating portion) including the first antenna element **521**, the antenna module **5** may provide a second resonator (e.g., a second patch resonator or a second patch resonating portion) (or a second radiating portion) including the second antenna element **522**. In substantially the same manner as the first resonator including the first antenna element **521**, the antenna module **5** may provide a third resonator (e.g., a third patch resonator or a third patch resonating portion) (or a third radiating portion) including the third antenna element **523**. In substantially the same manner as the first resonator including the first antenna element **521**, the antenna module **5** may provide a fourth resonator (e.g., a fourth patch resonator or a fourth patch resonating portion) (or a fourth radiating portion) including the fourth antenna element **524**. In substantially the same manner as the first resonator including the first antenna element **521**, the antenna module **5** may provide a fifth resonator (e.g., a fifth patch resonator or a fifth patch resonating portion) (or a fifth radiating portion) including the fifth antenna element **525**.

[0196] According to one or more embodiments, the electronic device **3** may include a beamforming system (or beamforming circuit) for the antenna module **5**. The beamforming system may allow a stronger signal to be received in a desired direction, a signal to be transmitted in a desired direction, or a signal to be prevented from being received from an undesired direction. The beamforming system included in the communication circuit **54** may adjust the beam pattern (e.g., the shape and direction of a beam) by controlling the phase or amplitude of an electromagnetic signal (or wireless signal, RF signal, or radiation current).

[0197] According to one or more embodiments, a processor (e.g., the processor **120** of FIG. **1**) may determine the phase of electromagnetic signals (or wireless signals, RF signals, or radiation currents) provided (or fed) to the plurality of antenna elements **521**, **522**, **523**, **524**, and **525** based on codebook information related to beamforming stored in memory (e.g., the memory **130** of FIG. **1**) and according to the frequency (or frequency band) used by an application (or program). The communication circuit **54** of the antenna module **5** may adjust the phases of the electromagnetic signals provided (or fed) to the plurality of antenna elements **521**, **522**, **523**, **524**, and **525** under the control of the processor. The communication circuit **54** of the antenna module **5** may efficiently control (e.g., allocate or arrange) a plurality of beams via a plurality of resonators (or radiating portions) (e.g., the first resonator, the second resonator, the third resonator, the fourth resonator, and the fifth resonator) included in the antenna module **5** under the control of the processor.

[0198] According to one or more embodiments, during feeding to the first resonator, which includes the first antenna element **521**, a radiation field (or electromagnetic field) may be generated from the first resonator. The radiation field generated from the first resonator may include, for example, a first radiation field generated from the first resonator during first feeding and/or a second radiation field generated from the first resonator during second feeding. The first radiation field and the first beam pattern provided by the first radiation field may correspond to a first linear polarization having a first polarization direction (e.g., substantially the second direction **502**). The second radiation field and the second beam pattern provided by the second radiation field may correspond to a second linear polarization having a second polarization direction (e.g., substantially the third direction **503**). The second resonator including the second antenna element **522** may provide a radiation field in substantially the same or a similar manner as the first resonator including the first antenna element **521**. The third resonator including the third antenna element **523** may provide a radiation field in substantially the same or a similar manner as the first resonator including the first antenna element **521**. The fourth resonator including the fourth antenna element **524** may provide a radiation field in substantially the same or a similar manner as the first resonator including the first antenna element **521**. The fifth resonator including the fifth antenna element **525** may provide a radiation field in substantially the same or a similar manner as the first resonator

including the first antenna element **521**.

[0199] According to one or more embodiments, the radiation field from the first resonator including the first antenna element **521**, the radiation field from the second resonator including the second antenna element **522**, the radiation field from the third resonator including the third antenna element **523**, the radiation field from the fourth resonator including the fourth antenna element **524**, or the radiation field from the fifth resonator including the fifth antenna element **525** may provide a beam pattern that radiates or concentrates relatively more electromagnetic wave energy (or wave energy) in the first direction **501** in which the first surface **511** of the printed circuit board **510** is oriented.

[0200] According to one or more embodiments, interference (e.g., constructive interference and/or destructive interference) among the radiation field (or beam pattern) from the first resonator, the radiation field (or beam pattern) from the second resonator, the radiation field (or beam pattern) from the third resonator, the radiation field (or beam pattern) from the fourth resonator, and the radiation field (or beam pattern) from the fifth resonator may allow relatively more electromagnetic wave energy (or wave energy) to be radiated or concentrated in the first direction **501** in which the first surface **511** of the printed circuit board **510** is oriented.

[0201] According to one or more embodiments, during the first feeding to the first resonator including the first antenna element **521**, a beam pattern of the first linear polarization having the first polarization direction (e.g., the second direction **502**) (or oscillating in the first polarization direction) may be radiated from the first resonator. During the first feeding to the second resonator including the second antenna element **522**, a beam pattern of the first linear polarization having the first polarization direction (or oscillating in the first polarization direction) may be radiated from the second resonator. During the first feeding to the third resonator including the third antenna element **523**, a beam pattern of the first linear polarization having the first polarization direction (or oscillating in the first polarization direction) may be radiated from the third resonator. During the first feeding to the fourth resonator including the fourth antenna element **524**, a beam pattern of the first linear polarization having the first polarization direction (or oscillating in the first polarization direction) may be radiated from the fourth resonator. During the first feeding to the fifth resonator including the fifth antenna element **525**, a beam pattern of the first linear polarization having the first polarization direction (or oscillating in the first polarization direction) may be radiated from the fifth resonator. According to one or more embodiments, during the first feeding, interference (e.g., constructive interference and/or destructive interference) among the beam pattern from the first resonator, the beam pattern from the second resonator, the beam pattern from the third resonator, the beam pattern from the fourth resonator, and the beam pattern from the fifth resonator may provide a synthesized beam pattern (or radiation pattern) of the first polarization direction, in which relatively more wave energy may be radiated or concentrated within the coverage range corresponding to the first direction **501** in which the first surface **511** of the printed circuit board **510** is oriented.

[0202] According to one or more embodiments, during the second feeding to the first resonator including the first antenna element **521**, a beam pattern of the second linear polarization having the second polarization direction (e.g., the third direction **503**) (or oscillating in the second polarization direction) may be radiated from the first resonator. During the second feeding to the second resonator including the second antenna element **522**, a beam pattern of the second linear polarization having the second polarization direction (or oscillating in the second polarization direction) may be radiated from the second resonator. During the second feeding to the third resonator including the third antenna element **523**, a beam pattern of the second linear polarization having the second polarization direction (or oscillating in the second polarization direction) may be radiated from the third resonator. During the second feeding to the fourth resonator including the fourth antenna element **524**, a beam pattern of the second linear polarization having the second polarization direction (or oscillating in the second polarization direction) may be radiated from the

fourth resonator. During the second feeding to the fifth resonator including the fifth antenna element **525**, a beam pattern of the second linear polarization having the second polarization direction (or oscillating in the second polarization direction) may be radiated from the fifth resonator. According to one or more embodiments, during the second feeding, interference (e.g., constructive interference and/or destructive interference) among the beam pattern from the first resonator, the beam pattern from the second resonator, the beam pattern from the third resonator, the beam pattern from the fourth resonator, and the beam pattern from the fifth resonator may provide a synthesized beam pattern (or radiation pattern) of the second polarization direction, in which relatively more wave energy may be radiated or concentrated within the coverage range corresponding to the first direction **501** in which the first surface **511** of the printed circuit board **510** is oriented.

[0203] According to one or more embodiments, the electronic device **3** may include a radio frequency (RF) window area (or an electromagnetic wave transmission area) (not separately illustrated) corresponding to the antenna module **5**. Electromagnetic waves transmitted (or radiated) from the antenna module **5** may pass through the RF window area to propagate to the exterior of the electronic device **3**. Electromagnetic waves transmitted from the exterior of the electronic device **3** may pass through the RF window area to be received (or detected) by the antenna module **5**. The RF window area may be positioned to at least partially correspond to the coverage (or beam coverage) (e.g., communication range) of the antenna module **5**.

[0204] According to one or more embodiments, when viewed from above the first surface **511** of the printed circuit board **510**, the RF window area may at least partially overlap the first surface **511**.

[0205] According to one or more embodiments, when viewed from above the first surface **511** of the printed circuit board **510**, the RF window area may include a portion of the first side portion **331** that at least partially overlaps the first surface **511**.

[0206] According to one or more embodiments, the RF window area may include a dielectric material of a non-conductive material, an air gap, or a combination thereof. The air gap may be defined or interpreted as a dielectric material having the permittivity of air.

[0207] According to one or more embodiments, the RF window area may be implemented to reduce the influence on the antenna radiation performance (or electromagnetic wave transmission/reception performance) or the coverage (or beam coverage) of the antenna module **5**. The RF window area may have a permittivity that is capable of reducing the electromagnetic influence on the antenna module **5**. The RF window area may have a permittivity that is capable of reducing the degradation of the antenna radiation performance of the antenna module **5** or a permittivity that does not degrade the antenna radiation performance to a threshold level or lower. The RF window area may have a permittivity that has an effect within a range that does not exceed the coverage area intended to be secured by the antenna module **5** or a permittivity that substantially does not affect the coverage of the antenna module **5**.

[0208] According to one or more embodiments, the permittivity of the RF window area may be a value that is capable of reduce the difference from the permittivity of air (e.g., a low permittivity).

[0209] According to various embodiments, the RF window area may include a dielectric lens (or an electromagnetic lens) or may be implemented to operate as a dielectric lens. A dielectric lens may focus or diffuse electromagnetic waves, similar to how an optical lens refracts light waves. A dielectric lens may secure or enhance the antenna radiation performance and/or coverage of the antenna module **5**.

[0210] According to one or more embodiments, the first metal portion **A1** included in the side surface metal **A** of the side portion **33** may include an opening **34** provided to correspond to the antenna module **5**. Electromagnetic waves transmitted (or radiated) from the antenna module **5** may pass through the opening **34** to propagate to the exterior of the electronic device **3**. Electromagnetic waves transmitted from the exterior of the electronic device **3** may pass through the opening **34** to

be received (or detected) by the antenna module **5**.

[0211] According to one or more embodiments, the opening **34** of the first metal portion **A1** may reduce the influence of the first metal portion **A1** on the electromagnetic waves radiated from the antenna module **5**, thereby reducing beam pattern deformation (e.g., distortion), compared to a comparative example in which the opening **34** is omitted.

[0212] Hereinafter, the term “comparative example” is used merely for comparison with the embodiment of the disclosure and does not have a prior art status over the various embodiments of the disclosure.

[0213] According to one or more embodiments, the first side portion **333** may include a non-conductive portion **35** of a non-conductive material (e.g., a polymer) disposed in the opening **34** of the first metal portion **A1**.

[0214] According to one or more embodiments, when viewed from above the first surface **511** of the printed circuit board **510**, the non-conductive portion **35** may overlap the antenna array **52**. The non-conductive portion **35** may be included in the RF window area corresponding to the antenna module **5**.

[0215] According to one or more embodiments, electromagnetic waves transmitted (or radiated) from the antenna module **5** may pass through the non-conductive portion **35** to propagate to the exterior of the electronic device **3**. Electromagnetic waves transmitted from the exterior of the electronic device **3** may pass through the non-conductive portion **35** to be received (or detected) by the antenna module **5**.

[0216] According to one or more embodiments, the opening **34** provided in the first metal portion **A1** corresponding to the antenna module **5** may be a through-hole. When viewed from above the first surface **511** of the printed circuit board **510**, the first metal portion **A1** may include a surrounding conductive area that entirely surrounds the opening **34**. When viewed from above the first surface **511**, the opening **34** entirely surrounded by the surrounding conductive area may be interpreted as a through-hole. The shape of the opening **3037** is not limited to the illustrated example and may vary (not separately illustrated).

[0217] According to one or more embodiments, the non-conductive portion **35** may have a permittivity capable of reducing the electromagnetic influence on the antenna radiation performance (or electromagnetic wave transmission/reception performance) or the coverage (or beam coverage) of the antenna module **5**.

[0218] According to one or more embodiments, the permittivity of the non-conductive portion **35** may be a value capable of reducing the difference from the permittivity of air (e.g., a low permittivity).

[0219] According to one or more embodiments, the non-conductive portion **35** may provide a portion of the side surface **30C** of the electronic device **3**. A partial surface area of the side surface **30C** of the electronic device **3** provided by the non-conductive portion **35** may be smoothly connected to a partial surface area of the side surface **30C** of the electronic device **3** provided by the first metal portion **A1** without a substantial height difference.

[0220] According to various embodiments, the side portion **33** may further include a coating layer (not separately illustrated) of various colors or textures that substantially provides the side surface **30C**. The coating layer may suppress or prevent the non-conductive portion **35** and the first metal portion **A1** from appearing distinguishable.

[0221] According to various embodiments, the non-conductive portion **35** and the first metal portion **A1** may have substantially the same color to suppress or prevent them from appearing distinguishable.

[0222] According to various embodiments, although not separately illustrated, the antenna module **5** may be positioned to correspond to the second side portion **332**, the third side portion **333**, or the fourth side portion **334**.

[0223] The electronic device **3** may further include various components depending on its provision

form. Although all of these components cannot be listed since the components are modified diversely depending on the convergence trend of electronic devices **3**, components equivalent to the above-mentioned components may be further included in the electronic device **3**. In various embodiments, certain components may be excluded from the above-described components or replaced with other components depending on the provided form of the electronic device.

[0224] FIG. **6** illustrates electronic devices **3** according to various embodiments of the disclosure.

[0225] Referring to FIG. **6**, the opening **34** provided in the first metal portion **A1** and the non-conductive portion **35** corresponding to the opening **34** are not limited to the exemplary embodiment of FIG. **3** and may be modified into various other forms.

[0226] According to a first exemplary embodiment **610**, the first metal portion **A1** may include a first conductive portion **611**, a second conductive portion **612**, and a segmentation portion **613** between the first conductive portion **611** and the second conductive portion **612**.

[0227] The segmentation portion **613** may be interpreted as another form of opening that replaces the through-hole-shaped opening **34** described with reference to FIG. **3**. A non-conductive portion **614** may be disposed in the segmentation portion **613**. The non-conductive portion **614** may be included in the RF window area corresponding to the antenna module **5** (see FIG. **3**).

[0228] According to a second exemplary embodiment **620**, the first metal portion **A1** may include a first notch **623**. When viewed from above the first surface **511** (see FIG. **5**) of the antenna module **5**, the first notch **623** may be recessed in the direction in which the front surface **30A** (see FIG. **3**) of the electronic device **3** is oriented (e.g., the +z-axis direction). The first notch **623** may be interpreted as another form of opening that replaces the through-hole-shaped opening **34** described with reference to FIG. **3**. A non-conductive portion **624** may be disposed in the first notch **623**. The non-conductive portion **624** may be included in the RF window area corresponding to the antenna module **5** (see FIG. **3**).

[0229] According to a third exemplary embodiment **630**, the first metal portion **A1** may include a second notch **633**. When viewed from above the first surface **511** (see FIG. **5**) of the antenna module **5**, the second notch **633** may be recessed in the direction in which the rear surface **30B** (see FIG. **3**) of the electronic device **3** is oriented (e.g., the -z-axis direction). The second notch **633** may be interpreted as another form of opening that replaces the through-hole-shaped opening **34** described with reference to FIG. **3**. A non-conductive portion **634** may be disposed in the second notch **633**. The non-conductive portion **634** may be included in the RF window area corresponding to the antenna module **5** (see FIG. **3**).

[0230] According to various embodiments, the opening provided in the first metal portion **A1** and the non-conductive portion corresponding to the opening may be provided in various other forms corresponding to the coverage of the antenna module **5**.

[0231] FIGS. **7** and **8** are exploded perspective views of an electronic device **3** according to one or more embodiments of the disclosure. FIG. **9** is a perspective view of an antenna module assembly **9** according to one or more embodiments of the disclosure. FIG. **10** is a view illustrating a combination of a frame **701**, a battery **76**, an antenna module assembly **9**, a flexible printed circuit board **1000**, and a second adhesive member (or a second bonding member) **1202** according to one or more embodiments of the disclosure. FIG. **10** may illustrate at least a portion indicated by "I" in FIG. **8**. FIG. **11** is a perspective view illustrating a combination of the frame **701**, the antenna module assembly **9**, and the battery **76** according to one or more embodiments of the disclosure.

[0232] Referring to FIGS. **7** to **11**, the electronic device **3** may include a front plate **31**, a rear plate **32**, a side portion **33**, a first support portion **71**, a second support portion **72**, a third support portion **73**, a display module **401**, a first printed circuit board **74**, a second printed circuit board **75**, a battery **76**, an antenna module assembly **9**, a first screw **S1**, a second screw **S2**, a flexible printed circuit board **1000**, and/or a second adhesive member (or bonding member) **1202**. In various embodiments, the electronic device **3** may omit some of the above components or additionally include other components.

[0233] According to one or more embodiments, the first support portion **71** may be at least partially positioned between the front plate **31** and the rear plate **32**. The first support portion **71** may be connected to the side portion **33**. The first support portion **71** may include a metallic material and/or a non-metallic material (e.g., a polymer).

[0234] According to one or more embodiments, the first support portion **71** may include a first support surface **71A** corresponding to the front plate **31**, and a second support surface **71B** corresponding to the rear plate **32** and provided opposite to the first support surface **71A**. The electronic device **3** may include a first space (not separately illustrated) between the first support surface **71A** and the front plate **31** and a second space (e.g., the second space **1502** of FIGS. **12** to **16**) between the second support surface **71B** and the rear plate **32**. A component such as the display module **401** may be disposed on the first support surface **71A** within the first space. Components such as the first camera **402**, the second camera **403**, the third camera **404**, the second support portion **72**, the third support portion **73**, the first printed circuit board **74**, the second printed circuit board **75**, the battery **76**, or the antenna module assembly **9** may be disposed on the second support surface **71B** within the second space.

[0235] According to one or more embodiments, the first support surface **71A** of the first support portion **71** may provide a front seating portion on which one or more components are stably disposed or supported. The front seating portion may be provided by a combination of surface areas having different heights.

[0236] According to one or more embodiments, the second support surface **71B** of the first support portion **71** may provide a rear seating portion on which one or more components are stably disposed or supported. The rear seating portion may be provided with a combination of surface areas having different heights.

[0237] According to one or more embodiments, a combination of the first support portion **71** and the side portion **33** may provide a frame (or a frame structure or a framework) **701** of the electronic device **3**. An integrated frame **701** that provides the first support portion **71** and the side portion **33** may be provided.

[0238] According to one or more embodiments, the first support portion **71** may include a non-conductor (e.g., the non-conductor **1401** of FIG. **12**) that includes one or more non-conductive portions and a conductor (e.g., the conductor **1402** of FIGS. **12** and **13**) that is connected to the non-conductor and includes one or more conductive portions.

[0239] According to one or more embodiments, the conductor (e.g., the conductor **1402** of FIG. **13**) of the first support portion **71** may be connected to the side surface metal A of the side portion **33**.

[0240] According to one or more embodiments, an integrated metal structure including the conductor (e.g., the conductor **1402** of FIG. **13**) of the first support portion **71** and the side surface metal A of the side portion **33** may be provided. The conductor of the first support portion **71** and the side surface metal A of the side portion **33** may include the same metal material.

[0241] According to one or more embodiments, the non-conductor (e.g., the non-conductor **1401** of FIG. **12**) of the first support portion **71** may be connected to the plurality of insulation portions **B1**, **B2**, **B3**, **B4**, **B5**, and **B6** of the side portion **33**.

[0242] According to one or more embodiments, an integrated non-metallic structure including the non-conductor (e.g., the non-conductor **1401** of FIG. **12**) of the first support portion **71** and the plurality of insulation portions **B1**, **B2**, **B3**, **B4**, **B5**, and **B6** of the side portion **33** may be provided. The non-conductor of the first support portion **71** and the plurality of insulation portions **B1**, **B2**, **B3**, **B4**, **B5**, and **B6** of the side portion **33** may include the same non-metallic material.

[0243] According to one or more embodiments, various electronic components such as the display **401**, the first printed circuit board **74**, the second printed circuit board **75**, or the battery **76**, or various members related to the electronic components may be disposed on or supported by the frame **701** or the first support portion **71**.

[0244] According to various embodiments, the first support portion **71** may be referred to by

various other terms such as “bracket,” “first support element,” “first support member,” or “first support structure.”

[0245] According to various embodiments, the first support portion **71** may be interpreted as a portion of the housing **30** (see FIG. 3).

[0246] According to one or more embodiments, the display module **401** may be positioned between the first support portion **71** and the front plate **31**. The display module **401** may be disposed on (or coupled to) the front plate **31** and/or the first support portion **71**.

[0247] According to one or more embodiments, the display module **401** may be coupled to the front plate **31** via an optically transparent adhesive member (or optically transparent adhesive material) such as optical clear adhesive (OCA), optical clear resin (OCR), or super view resin (SVR) (not separately illustrated).

[0248] According to one or more embodiments, the first printed circuit board **74** and the second printed circuit board **75** may be disposed on (or coupled to) the first support portion **71** between the first support portion **71** and the rear plate **32**.

[0249] According to one or more embodiments, the battery **76** may be disposed on the first support portion **71** between the first support portion **71** and the rear plate **32**.

[0250] According to one or more embodiments, a plurality of electronic components may be electrically connected to the first printed circuit board **74**. Some of the plurality of electronic components may be disposed on the first printed circuit board **74**. The others of the plurality of electronic components may be electrically connected to the first printed circuit board **74** via an electrical path such as a flexible printed circuit board or a cable. The plurality of electronic components may include, for example, the display module **401**, a second microphone (not separately illustrated) corresponding to the second microphone hole **409** (see FIG. 3), the first camera module **402**, the second camera module **403**, the third camera module **404**, the fourth camera module **405**, the first light-emitting module **406** (see FIG. 3), the first sensor module **407** (see FIG. 3), the first key input module **412**, or the second key input module **413**.

[0251] According to one or more embodiments, the second printed circuit board **75** may be electrically connected to the first printed circuit board **74** via an electrical path such as a flexible printed circuit board.

[0252] According to one or more embodiments, a plurality of electronic components may be electrically connected to the second printed circuit board **75**. Some of the plurality of electronic components may be disposed on the second printed circuit board **75**. The others of the plurality of electronic components may be electrically connected to the second printed circuit board **75** via an electrical path such as a flexible printed circuit board or a cable. The plurality of electronic components may include, for example, a first microphone (not separately illustrated) corresponding to the first microphone hole **408**, a first speaker (not separately illustrated) corresponding to the first speaker hole **410**, a first connection terminal **414**, or a second connection terminal (not separately illustrated) corresponding to the cover member **415**.

[0253] According to one or more embodiments, the first printed circuit board **74** and the second printed circuit board **75** may be spaced apart from each other with the battery **76** interposed therebetween when viewed from above the rear plate **32** (e.g., in the +z-axis direction).

[0254] According to one or more embodiments, when viewed from above the rear plate **32**, the first printed circuit board **74** may be at least partially positioned between the third side portion **333** (see FIG. 3) and the battery **76**. When viewed from above the rear plate **32**, the second printed circuit board **75** may be at least partially positioned between the fourth side portion **334** (see FIG. 4) and the battery **76**.

[0255] According to various embodiments, when viewed from above the rear plate **32**, the first printed circuit board **74** may further include a protrusion (not separately illustrated) extending between the first side portion **331** and the battery **76** or between the second side portion **332** and the battery **76**. The protrusion may be electrically connected to the second printed circuit board **75**

via an electrical path such as a flexible printed circuit board.

[0256] According to various embodiments, an integrated printed circuit board (not separately illustrated) that replaces the first printed circuit board **74** and the second printed circuit board **75** may be provided. The integrated printed circuit board may include, for example, a first board portion positioned between the third side portion **333** (see FIG. **3**) and the battery **76** and a second board portion positioned between the fourth side portion **334** (see FIG. **3**) and the battery **76** when viewed from above the rear plate **32**, and may include a third board portion interconnecting the first board portion and the second board portion. The third board portion may be positioned between the first side portion **331** and the battery **76**, or between the second side portion **332** (see FIG. **3**) and the battery **76** when viewed from above the rear plate **32**. The third portion may be implemented substantially rigid or flexible.

[0257] According to various embodiments, although not separately illustrated, the first printed circuit board **74** or the second printed circuit board **75** may include a primary PCB (or a main PCB), a secondary PCB (or a sub-PCB), and/or an interposer substrate. When viewed from above the rear plate **32**, the primary PCB and the secondary PCB may overlap. The interposer substrate may be disposed between the primary PCB and the secondary PCB and may electrically connect the primary PCB and the secondary PCB.

[0258] According to one or more embodiments, the battery **76** is a device that supplies power to at least one component of the electronic device **3**, and may include, for example, a non-rechargeable primary battery, a rechargeable secondary battery, or a fuel cell.

[0259] According to one or more embodiments, a conductor (not separately illustrated) included in the first support portion **71** may provide electromagnetic shielding. The conductor included in the first support portion **71** may reduce or prevent electromagnetic influence (e.g., electromagnetic interference (EMI)) on the display module **401**, the first printed circuit board **74**, the second printed circuit board **75**, the battery **76**, or various other electrical components. The conductor included in the first support portion **71** may reduce or prevent electromagnetic influence between any two components.

[0260] According to one or more embodiments, the conductor (not separately illustrated) included in the first support portion **71** may be electrically connected to a first ground plane (or first ground area) (not separately illustrated) included in the first printed circuit board **74** via a flexible conductive member (or flexible conductive portion or flexible conductive component) positioned between the first support portion **71** and the first printed circuit board **74**. The flexible conductive member may include, for example, a conductive clip (e.g., a conductive structure including an elastic structure), a pogo pin, a spring, a conductive foam, a conductive rubber, a conductive tape, or a conductive connector.

[0261] According to one or more embodiments, the conductor (not separately illustrated) included in the first support portion **71** may be electrically connected to a second ground plane (or second ground area) (not separately illustrated) included in the second printed circuit board **75** via a flexible conductive member (or flexible conductive portion or flexible conductive component) positioned between the first support portion **71** and the second printed circuit board **75**.

[0262] According to one or more embodiments, the first ground plane of the first printed circuit board **74** and the second ground plane of the second printed circuit board **75** may be electrically connected via an electrical connection member (e.g., a flexible printed circuit board) (not separately illustrated) that electrically connects the first printed circuit board **74** and the second printed circuit board **75**.

[0263] According to one or more embodiments, a combination of the conductor (not separately illustrated) included in the first support portion **71**, the first ground plane (not separately illustrated) of the first printed circuit board **74**, and the second ground plane (not separately illustrated) of the second printed circuit board **75** may be defined or interpreted as a ground (or ground structure) of the electronic device **3**.

[0264] According to one or more embodiments, the second support portion (or a second support element, a second support member, or a second support structure) **72** may be positioned between the first support portion **71** and the rear plate **32**. At least a portion of the first printed circuit board **74** may be positioned between the first support portion **71** and the second support portion **72**, and the second support portion **72** may protect the first printed circuit board **74**. The second support portion **72** may be coupled to the first support portion **71** and/or the first printed circuit board **74** through screw fastening or various other methods.

[0265] According to one or more embodiments, the third support portion (or a third support element, a third support member, or a third support structure) **73** may be positioned between the first support portion **71** and the rear plate **32**. At least a portion of the second printed circuit board **75** may be positioned between the first support portion **71** and the third support portion **73**, and the third support portion **73** may protect the second printed circuit board **75**. The third support portion **73** may be coupled to the first support portion **71** and/or the second printed circuit board **75** through screw fastening or various other methods.

[0266] According to one or more embodiments, the third support portion **73** may be at least partially positioned to be spaced apart from the second support portion **72** with the battery **76** therebetween when viewed from above the rear plate **32**.

[0267] According to various embodiments, the frame **701** may be defined or interpreted as the “front case” of the electronic device **3**, and the second support portion **72** and/or the third support portion **73** may be defined or interpreted as the “rear case” of the electronic device **3**.

[0268] According to various embodiments, the second support portion **72** and/or the third support portion **73** may be interpreted as a portion of the housing **30** (see FIG. 3).

[0269] According to various embodiments, an integrated support portion (not separately illustrated) that replaces the second support portion **72** and the third support portion **73** may be provided.

[0270] According to one or more embodiments, the second support portion **72** or the third support portion **73** may include a metallic material and/or a non-metallic material (e.g., a polymer).

[0271] According to one or more embodiments, at least one conductive portion (e.g., the first conductive portion **A1**, the second conductive portion **A2**, the third conductive portion **A3**, the fourth conductive portion **A4**, or the fifth conductive portion **A5**) included in the side portion **33** may be configured to operate as an antenna radiator. The at least one conductive portion included in the side portion **33** may be electrically connected to a wireless communication circuit (e.g., the wireless communication module **192** of FIG. 1) disposed on the first printed circuit board **74**.

[0272] According to various embodiments, the second support portion **72** or the third support portion **73** may include a non-conductor (not separately illustrated) made of a non-metallic material, and at least one conductive pattern (not separately illustrated) disposed on the non-conductor. The at least one conductive pattern may be disposed on the non-conductor through, for example, laser direct structuring (LDS). The LDS may be a method of drawing a pattern on a non-conductor by using a laser and plating a conductive material such as copper or nickel on the pattern to form a conductive pattern. At least one conductive pattern included in the second support portion **72** or the third support portion **73** may be configured to operate as an antenna radiator. The at least one conductive pattern included in the third support portion **73** may be electrically connected to a wireless communication circuit (e.g., the wireless communication module **192** in FIG. 3) disposed on the first printed circuit board **74**.

[0273] According to one or more embodiments, the wireless communication circuit (e.g., the wireless communication module **192** of FIG. 1) may process a transmission signal or a reception signal in at least one selected or predetermined frequency band via at least one antenna radiator (e.g., at least one conductive portion included in the side portion **33**, or at least one conductive pattern included in the second support portion **72** or the third support portion **73**). The selected or predetermined frequency band may include, for example, at least one of a low band (LB) (about 600 MHz to about 1 GHz), a middle band (MB) (about 1 GHz to about 2.3 GHz), a high band

(HB) (about 2.3 GHz to about 2.7 GHz), or an ultra-high band (UHB) (about 2.7 GHz to about 6 GHz). The predetermined frequency band may include various other frequency bands.

[0274] According to one or more embodiments, the antenna module assembly **9** may include an antenna module **5** and an antenna module bracket **8**.

[0275] According to one or more embodiments, the antenna module **5** may be disposed on or coupled to the antenna module bracket **8**.

[0276] According to one or more embodiments, the antenna module **5** may be disposed on or coupled to the antenna module bracket **8** via an adhesive material (or bonding material) (not separately illustrated). For example, a heat-responsive adhesive material (or heat-responsive bonding material), a photo-responsive adhesive material (or photo-responsive bonding material), a general adhesive or general bonding material, or a double-sided tape may be disposed between the antenna module **5** and the antenna module bracket **8**.

[0277] According to various embodiments, the antenna module **5** may be disposed on or coupled to the antenna module bracket **8** via a screw (not separately illustrated).

[0278] According to various embodiments, the antenna module **5** may be disposed on or coupled to the antenna module bracket **8** via snap-fits. The antenna module bracket **8** may include, for example, one or more hooks (not separately illustrated). The one or more hooks may be fastened to the antenna module **5** to prevent the antenna module **5** from being separated from the antenna module bracket **8**.

[0279] According to one or more embodiments, the antenna module bracket **8** may be a support element (or support member) or a connecting element (or connecting member) that connects the antenna module **5** and the first support portion **71**. The antenna module **5** may be stably and securely connected to the first support portion **71** via the antenna module bracket **8**.

[0280] According to one or more embodiments, for external impacts such as the dropping of the electronic device **3**, the antenna module bracket **8** may suppress or prevent the influence of the external impacts on the antenna module **5**.

[0281] According to various embodiments, the antenna module assembly **9** may include a flexible member of a flexible material (or an elastic member of an elastic material) (not separately illustrated) or a buffering member of a buffering material (not separately illustrated) disposed between the antenna module **5** and the antenna module bracket **8**. The flexible member (or elastic member) or the buffering member may reduce or prevent the influence of external impacts, such as the dropping of the electronic device **3**, on the antenna module **5**. The flexible member (or elastic member) or the buffering member may suppress or prevent the separation of the antenna module **5** and the antenna module bracket **8** due to external impacts such as the dropping of the electronic device **3**.

[0282] According to one or more embodiments, an adhesive material (or bonding material) disposed between the antenna module **5** and the antenna module bracket **8** (not separately illustrated) may not only couple the antenna module **5** and the antenna module bracket **8** but also suppress or prevent the influence of external impacts on the antenna module **5**. The adhesive material (or bonding material) disposed between the antenna module **5** and the antenna module bracket **8** may include a buffering material.

[0283] According to various embodiments, the electronic device **3** may include a flexible member of a flexible material (or an elastic member of an elastic material) (not separately illustrated) or a buffering member of a buffering material (not separately illustrated) between the antenna module assembly **9** and the first support portion **71**. The flexible member (or elastic member) or the buffering member may reduce or prevent the influence of external impacts, such as the dropping of the electronic device **3**, on the antenna module **5**. The flexible member (or elastic member) or the buffering member may suppress or prevent the separation of the antenna module **5** and the antenna module bracket **8** due to external impacts such as the dropping of the electronic device **3**.

[0284] According to one or more embodiments, the antenna module assembly **9** may be positioned

between the first support portion **71** and the rear plate **32**.

[0285] According to one or more embodiments, the antenna module bracket **8** may be provided as an integral metallic body (or metal structure) including one or more bended portions.

[0286] According to one or more embodiments, the antenna module bracket **8** may be implemented through a processing method such as computer numerical control (CNC), die casting, or pressing.

[0287] According to one or more embodiments, the antenna module bracket **8** may include titanium, amorphous alloy, metal-ceramic composite material (e.g., cermet), or stainless steel.

[0288] According to various embodiments, the antenna module bracket **8** may include magnesium, magnesium alloy, aluminum, aluminum alloy, zinc alloy, or copper alloy. The antenna module bracket **8** may include various other metallic materials.

[0289] According to one or more embodiments, the antenna module bracket **8** may be coupled to the first support portion **71** through screw fastening.

[0290] According to one or more embodiments, the antenna module bracket **8** may include a first screw hole **H1** corresponding to a first screw **S1** and/or a second screw hole **H2** corresponding to a second screw **S2**.

[0291] According to one or more embodiments, the first support portion **71** may include a first screw fastening portion (or first boss) **SF1** corresponding to the first screw hole **H1** of the antenna module bracket **8** and/or a second screw fastening portion (or second boss) **SF2** corresponding to the second screw hole **H2** of the antenna module bracket **8**. The screw fastening portion may include a female thread capable of being fastened with the male thread of a screw.

[0292] According to one or more embodiments, the antenna module bracket **8** may include a first portion **81**, a second portion **82**, a third portion **83**, a first insert **801**, and/or a second insert **802**.

[0293] According to one or more embodiments, the antenna module **5** may be disposed on or coupled to the first portion **81**.

[0294] According to various embodiments, the first portion **81** of the antenna module bracket **8** may include an opening (not separately illustrated) or a recess (not separately illustrated) in which a component disposed on the second surface **512** of the antenna module **5** (e.g., the communication circuit **54** or the power management circuit **55**) may be positioned.

[0295] According to one or more embodiments, the second portion **82** of the antenna module bracket **8** may extend from the first portion **81**. The second portion **82** may include the first screw hole **H1**.

[0296] According to one or more embodiments, the third portion **83** of the antenna module bracket **8** may extend from the first portion **81**. The third portion **83** may include the second screw hole **H2**.

[0297] According to one or more embodiments, when the second portion **82** is coupled to the first screw fastening portion **SF1** of the first support portion **71** by the first screw **S1**, and the third portion **83** is coupled to the second screw fastening portion **SF2** of the first support portion **71** by the second screw **S2**, the relative position between the first support portion **71** and the first portion **81** may be provided such that the first surface **511** of the antenna module **5** faces the non-conductive portion **35** of the side portion **33**.

[0298] According to one or more embodiments, the relative position where the second portion **82** including the first screw hole **H1** extends from the first portion **81**, and the relative position where the third portion **83** including the second screw hole **H2** extends from the first portion **81** may be provided to stably maintain the first portion **81**, in which the antenna module **5** is disposed, against external impacts such as the dropping of the electronic device **3**.

[0299] According to one or more embodiments, when viewed from above the rear plate **32** or from above the first surface **511** of the antenna module **5**, the second portion **82** and the third portion **83** may be positioned on opposite sides of the antenna module **5**.

[0300] According to one or more embodiments, to reduce the impact on the antenna radiation performance or coverage of the antenna module **5**, the antenna module bracket **8** (or the first portion **81**) may be implemented such that, when viewed from above the first surface **511** of the

antenna module **5**, it extends forward of the first surface **511** and does not overlap the first surface **511** or the antenna array **52**.

[0301] According to various embodiments, the antenna module bracket **8** may further include a fourth portion (not separately illustrated) extending from the first portion **81**. The fourth portion may protrude in the first direction (the +x-axis direction), in which the first surface **511** is oriented, with respect to the first surface **511** of the antenna module **5**. The fourth portion may form an acute angle or a right angle with the first surface **511**. When the fourth portion forms an acute angle or an obtuse angle with the first surface **511**, the fourth portion may overlap the first surface **511** or the antenna array **52** when viewed from above the first surface **511**. The fourth portion may affect the electromagnetic waves (or electromagnetic wave energy) radiated from the antenna module **5** and may change the coverage (or beam coverage). For example, the electromagnetic waves radiated from the antenna module **5** may be reflected by the fourth portion, causing a change in the propagation direction, and coverage based on this may be provided. The fourth portion may be interpreted as a “reflector.”

[0302] According to various embodiments, the fourth portion of the antenna module bracket **8** may further include a plurality of openings. The plurality of openings may be positioned to allow some of the electromagnetic waves (or electromagnetic wave energy) radiated from the antenna module **5** to pass therethrough. In various embodiments, the plurality of openings may be positioned in a one-to-one correspondence with the plurality of antenna elements **521**, **522**, **523**, **524**, and **525**. In various embodiments, the antenna module bracket **8** may further include a non-conductive dielectric material disposed in the plurality of openings included in the fourth portion. The non-conductive dielectric material may have a permittivity that is capable of reducing the impact on the antenna radiation performance or coverage. The non-conductive dielectric material may include, for example, a low-permittivity material.

[0303] According to various embodiments, the opening provided in the first metal portion **A1** and the non-conductive portion corresponding to the opening may be provided in various other forms (e.g., refer to the exemplary embodiments **610**, **620**, or **630** of FIG. **6**) that are capable of reducing the impact on the coverage, corresponding to the coverage provided by the combination of the antenna module **5** and the fourth portion of the antenna module bracket **8**.

[0304] According to one or more embodiments, the flexible printed circuit board **1000** may electrically connect the antenna module **5** and the first printed circuit board **74**.

[0305] According to one or more embodiments, the antenna module **5** may include a connector **56** disposed on the antenna module bracket **8**. The connector **56** may be electrically connected to the antenna structure **51**. The flexible printed circuit board **1000** may be electrically connected to the connector **56**.

[0306] According to one or more embodiments, the first support portion **71** may include a recess **R** corresponding to the antenna module assembly **9**. The antenna module assembly **9** may be inserted into the recess **R**.

[0307] According to one or more embodiments, the first support portion **71** may include a first wall **W1** and a second wall **W2**. The first wall **W1** and the second wall **W2** may be provided in the form of protrusions extending in a direction toward the rear plate **32**. The first wall **W1** may be spaced apart from the second wall **W2** in the direction in which the first surface **511** of the antenna module **5** is oriented. The recess **R** of the first support portion **71** may include a spacing between the first wall **W1** and the second wall **W2**. The antenna module **5** may be inserted between the first wall **W1** and the second wall **W2**. The first portion **81** of the antenna module bracket **8**, where the antenna module **5** is disposed, may be inserted between the first wall **W1** and the second wall **W2**.

[0308] According to one or more embodiments, when viewed from above the first surface **511** of the antenna module **5**, the first wall **W1** may overlap the first surface **511**.

[0309] According to one or more embodiments, the first wall **W1** may be coupled to the first side portion **331**.

[0310] According to one or more embodiments, when viewed from above the first surface **511** of the antenna module **5**, the non-conductive portion **35** may overlap the first wall **W1**.

[0311] According to one or more embodiments, the first wall **W1** may be included in the RF window area of the antenna module **5**. The first wall **W1** may include a non-conductive material. Electromagnetic waves transmitted (or radiated) from the antenna module **5** may pass through the first wall **W1** and the non-conductive portion **35** to propagate to the exterior of the electronic device **3**. Electromagnetic waves transmitted from the exterior of the electronic device **3** may pass through the non-conductive portion **35** and the first wall **W1** to be received (or detected) by the antenna module **5**.

[0312] According to one or more embodiments, the first wall **W1** may have a permittivity capable of reducing the impact on the antenna radiation performance (or electromagnetic wave transmission/reception performance) or the coverage (or beam coverage) of the antenna module **5**.

[0313] According to various embodiments, the first wall **W1** may be interpreted as a separate element from the first support portion **71** and as a portion of the first side portion **331**.

[0314] According to one or more embodiments, when viewed from above the second surface **512** of the antenna module **5** (see FIG. 5), the second wall **W2** may overlap the second surface **512**.

[0315] According to one or more embodiments, the second wall **W2** may support the antenna module **5**.

[0316] According to one or more embodiments, a portion of the first portion **81** included in the antenna module bracket **8** may be positioned between the antenna module **5** and the second wall **W2**.

[0317] According to one or more embodiments, the second wall **W2** may support the first portion **81** of the antenna module bracket **8**.

[0318] According to one or more embodiments, when viewed from above the rear plate **32**, the antenna module assembly **9** may be at least partially positioned between the first side portion **331** and the battery **76**.

[0319] According to one or more embodiments, the second support surface **71B** of the first support portion **71** may include a battery seating portion (not separately illustrated). The battery seating portion may provide a recess in which the battery **76** is fitted and accommodated. The battery **76** may include a battery front surface (not separately illustrated) facing the front plate **31**, a battery rear surface **76B** facing the rear plate **32**, and a battery side surface (not separately illustrated) connecting the battery front surface and the battery rear surface **76B**. According to one or more embodiments, the battery seating portion may include a battery support wall **BW** (see FIG. 10) that at least partially surrounds the battery side surface when viewed from above the rear plate **32**. The battery seating portion may include a recess surrounded by the battery support wall **BW** in the second support surface **71B** of the first support portion **71**.

[0320] According to one or more embodiments, the second wall **W2** may be a portion of the battery support wall **BW**.

[0321] According to one or more embodiments, the first support portion **71** may include a third surface **710**. The third surface **710** may be at least partially positioned along the side portion **33**. The third surface **710** may be positioned adjacent to the side portion **33**. The third surface **710** may extend from the boundary between the surface provided by the side portion **33** and the surface provided by the first support portion **71**.

[0322] According to one or more embodiments, the third surface **710** of the first support portion **71** may include a first surface area **711**, a second surface area **712**, and/or a third surface area **713**.

[0323] According to one or more embodiments, the first surface area **711** of the third surface **710** may be connected to the boundary between the surface provided by the side portion **33** and the surface provided by the first support portion **71**.

[0324] According to one or more embodiments, the first surface area **711** of the third surface **710** may include a plane substantially facing the rear plate **32** or the rear surface **30B** of the electronic

device **3** illustrated in FIG. **3**.

[0325] According to one or more embodiments, the first surface area **711** of the third surface **710** may include a plane substantially perpendicular to the first surface **511** of the antenna module **5**.

[0326] According to one or more embodiments, a second adhesive member **1202** (or a second bonding member **1202**) of an adhesive material that bonds the first support portion **71** and the rear plate **32** may be at least partially disposed on the first surface area **711** of the third surface **710**.

[0327] According to one or more embodiments, the first screw fastening portion SF**1** may be provided to correspond to the second surface area **712** of the third surface **710**.

[0328] According to one or more embodiments, the second surface area **712** of the third surface **710** may include a plane substantially facing the rear plate **32** or the rear surface **30B** of the electronic device **3** illustrated in FIG. **3**. The second surface area **712** may include a plane substantially parallel to the first surface area **711**.

[0329] According to one or more embodiments, the second surface area **712** of the third surface **710** may include a plane substantially perpendicular to the first surface **511** of the antenna module **5**.

[0330] According to one or more embodiments, the second portion **82** of the antenna module bracket **8** including the first screw hole H**1** may overlap the second surface area **712** of the third surface **710** when viewed from above the rear plate **32**.

[0331] According to one or more embodiments, the second portion **82** of the antenna module bracket **8** including the first screw hole H**1** may have a substantially flat plate shape. The second portion **82** may be substantially parallel to the second surface area **712** of the third surface **710**.

[0332] According to one or more embodiments, the second portion **82** of the antenna module bracket **8** including the first screw hole H**1** may be bent toward the first portion **81** of the antenna module bracket **8**, in which the antenna module **5** is disposed.

[0333] According to one or more embodiments, in a direction in which the rear surface **30B** of the electronic device **3** (see FIG. **3**) is oriented (e.g., the $-z$ -axis direction), the first surface area **711** of the third surface **710** may be provided higher than the second surface area **712** of the third surface **710**. The first surface area **711** may be closer to the rear plate **32** than to the second surface area **712**. In various embodiments, the second surface area **712** may provide a recess in which the second portion **82** of the antenna module bracket **8**, including the first screw hole H**1**, may be fitted.

[0334] According to one or more embodiments, providing the second surface area **712** lower than the first surface area **711** in a direction in which the rear surface **30B** of the electronic device **3** (see FIG. **3**) (e.g., the $-z$ axis direction) is oriented may allow the head S**11** of the first screw S**1** to be spaced apart from the rear plate **32** so as not to press against the rear plate **32**.

[0335] According to one or more embodiments, the second screw fastening portion SF**2** may be provided to correspond to the third surface area **713** of the third surface **710**.

[0336] According to one or more embodiments, the third surface area **713** of the third surface **710** may include a plane substantially facing the rear plate **32** or the rear surface **30B** of the electronic device **3** illustrated in FIG. **3**. The third surface area **713** may include a plane substantially parallel to the first surface area **711**.

[0337] According to one or more embodiments, the third surface area **713** of the third surface **710** may include a plane substantially perpendicular to the first surface **511** of the antenna module **5**.

[0338] According to one or more embodiments, the third portion **83** of the antenna module bracket **8** including the second screw hole H**2** may overlap the third surface area **713** of the third surface **710** when viewed from above the rear plate **32**.

[0339] According to one or more embodiments, the third portion **83** of the antenna module bracket **8** including the second screw hole H**2** may have a substantially flat plate shape. The third portion **83** may be substantially parallel to the third surface area **713** of the third surface **710**.

[0340] According to one or more embodiments, the third portion **83** of the antenna module bracket

8 including the second screw hole **H2** may be bent toward the first portion **81** of the antenna module bracket **8**, in which the antenna module **5** is disposed.

[0341] According to one or more embodiments, in a direction in which the rear surface **30B** of the electronic device **3** (see FIG. **3**) is oriented (e.g., the $-z$ -axis direction), the first surface area **711** of the third surface **710** may be provided higher than the third surface area **713** of the third surface **710**. The first surface area **711** may be closer to the rear plate **32** than to the third surface area **713**. In various embodiments, the third surface area **713** may provide a recess in which the third portion **83** of the antenna module bracket **8**, including the second screw hole **H2**, may be fitted.

[0342] According to one or more embodiments, providing the third surface area **713** lower than the first surface area **711** in a direction in which the rear surface **30B** of the electronic device **3** (see FIG. **3**) (e.g., the $-z$ axis direction) is oriented may allow the head **S21** of the second screw **S2** to be spaced apart from the rear plate **32** so as not to press against the rear plate **32**.

[0343] According to one or more embodiments, the first screw hole **H1** and the second screw hole **H2** of the antenna module bracket **8** may be aligned in the second direction **502** (e.g., the y -axis direction) when viewed from above the rear plate **32**.

[0344] According to various embodiments, a coupling structure (not separately illustrated) in which the first screw fastening portion **SF1** of the first support **71** is fitted into the first screw hole **H1** of the antenna module bracket **8** may be provided.

[0345] According to various embodiments, a coupling structure (not separately illustrated) in which the second screw fastening portion **SF2** of the first support **71** is fitted into the second screw hole **H2** of the antenna module bracket **8** may be provided.

[0346] According to various embodiments, the second surface area **712** of the third surface **710** may be provided as a first inclined surface (not separately illustrated) forming an obtuse angle with the first surface area **711** of the third surface **710** or forming an acute angle with the first surface **511** of the antenna module **5**. The first screw fastening portion **SF1** may be positioned on the first inclined surface. The second portion **82** of the antenna module bracket **8**, which includes the first screw hole **H1**, may extend from the first portion **81** of the antenna module bracket **8** to correspond to the first inclined surface. For example, the bent angle of the second portion **82** relative to the first portion **81** may be implemented with an angle (e.g., an obtuse angle) larger than the illustrated example angle (e.g., about 90 degrees).

[0347] According to various embodiments, the third surface area **713** of the third surface **710** may be provided as a second inclined surface (not separately illustrated) forming an obtuse angle with the first surface area **711** of the third surface **710** or forming an acute angle with the first surface **511** of the antenna module **5**. The first screw fastening portion **SF1** may be positioned on the second inclined surface. The third portion **83** of the antenna module bracket **8**, which includes the second screw hole **H2**, may extend from the first portion **81** of the antenna module bracket **8** to correspond to the second inclined surface. For example, the bent angle of the third portion **83** relative to the first portion **81** may be implemented with an angle (e.g., an obtuse angle) larger than the illustrated example angle (e.g., about 90 degrees).

[0348] According to various embodiments, although not separately illustrated, the screw fastening structure between the antenna module bracket **8** and the first support **71** is not limited to the illustrated example and may be variously modified.

[0349] According to one or more embodiments, the first insert **801** of the antenna module bracket **8** may extend from the first portion **81** of the antenna module bracket **8**. The second insert **802** of the antenna module bracket **8** may extend from the first portion **81** of the antenna module bracket **8**.

[0350] According to one or more embodiments, when viewed from above the first surface **511** of the antenna module **5** or from above the rear plate **32**, the first insert **801** and the second insert **802** may be positioned on opposite sides of the antenna module **5**.

[0351] According to one or more embodiments, the first insert **801** may be positioned to correspond to the second portion **82** including the first screw hole **H1**.

[0352] According to one or more embodiments, the first insert **801** may extend from one side of the first portion **81** that is closer to the front plate **31** than to the rear plate **32**, and the second portion **82** including the first screw hole **H1** may extend from the other side of the first portion **81** that is closer to the rear plate **32** than to the front plate **31**.

[0353] According to one or more embodiments, the second insert **802** may be positioned to correspond to the third portion **83** including the second screw hole **H2**.

[0354] According to one or more embodiments, the second insert **802** may extend from one side of the first portion **81** that is closer to the front plate **31** than to the rear plate **32**, and the third portion **83** including the second screw hole **H2** may extend from the other side of the first portion **81** that is closer to the rear plate **32** than to the front plate **31**.

[0355] According to one or more embodiments, the first insert **801** and/or the second insert **802** may be provided to include a hemming structure (or hemming joint).

[0356] According to one or more embodiments, the first insert **801** and the second insert **802** may be spaced apart from each other and aligned in the second direction **502** (e.g., the y-axis direction).

[0357] According to one or more embodiments, the first support portion **71** may include a first groove (or first guide groove) **1101** corresponding to the first insert **801** of the antenna module bracket **8**.

[0358] According to one or more embodiments, the first support portion **71** may include a second groove (or second guide groove) **1102** corresponding to the second insert **802** of the antenna module bracket **8**. The first insert **801** may be inserted into the first groove **1101**. The second insert **802** may be inserted into the second groove **1102**.

[0359] According to one or more embodiments, the second support surface **71B** of the first support portion **71** may include a fourth surface **720** (see FIGS. **15** and **16**) connecting the first wall **W1** and the second wall **W2**. The third surface **710** may be provided higher than the fourth surface **720** (see FIGS. **15** and **16**) in a direction in which the rear surface **30B** (see FIG. **3**) of the electronic device **3** is oriented (e.g., the -z-axis direction). The recess **R** may be provided by a combination of the first wall **W1**, the second wall **W2**, and the fourth surface **720** (see FIGS. **15** and **16**). The first groove **1101** and the second groove **1102** may be provided on the fourth surface **720** (see FIGS. **15** and **16**).

[0360] According to one or more embodiments, the first groove **1101** and the second groove **1102** may be spaced apart from each other and aligned in the second direction **502** (e.g., the y-axis direction).

[0361] According to one or more embodiments, the combination of the first insert **801** and the first groove **1101** and the combination of the second insert **802** and the second groove **1102** may guide the placement of the antenna module assembly **9** in the assembly process of placing the antenna module assembly **9** in the frame **701**. The combination of the first insert **801** and the first groove **1101** may be defined or interpreted as a “first guide **G1**,” and the combination of the second insert **802** and the second groove **1102** may be defined or interpreted as a “second guide **G2**.”

[0362] According to one or more embodiments, the first guide **G1** and the second guide **G2** may be spaced apart from each other and aligned in the second direction **502** (e.g., the y-axis direction).

[0363] According to one or more embodiments, a method of placing the antenna module assembly **9** in the frame **701** may include a first operation, a second operation, and a third operation. In the first operation, the antenna module assembly **9** may be inserted into the recess **R** of the frame **701**. In the second operation, the antenna module assembly **9** may be rotated about the guide **G**. In the third operation, the antenna module bracket **8** may be coupled to the frame **701** through screw fastening.

[0364] According to one or more embodiments, in the first operation, the antenna module assembly **9** may be inserted into the recess **R** of the frame **701**. In the first operation, the first insert **801** of the antenna module bracket **8** may be inserted into the first groove **1101**, and the second insert **802** of the antenna module bracket **8** may be inserted into the second groove **1102**.

[0365] According to one or more embodiments, in the second operation, the antenna module assembly **9** inserted into the recess **R** may be rotated about the guide **G**. Through the second operation, the first surface **511** of the antenna module **5** may substantially face the non-conductive portion **35** of the first side portion **331**. Through the second operation, the second portion **82** of the antenna module bracket **8** may be positioned to correspond to the second surface area **712** of the first support portion **71**, and the third portion **83** of the antenna module bracket **8** may be positioned to correspond to the third surface area **713** of the first support portion **71**.

[0366] According to one or more embodiments, the clearance between the first insert **801** and the first groove **1101** of the first guide **G1** and the clearance between the second insert **802** and the second groove **1102** of the second guide **G2** may be provided to allow the antenna module assembly **9** to rotate in a balanced and stable manner when the second operation is performed.

[0367] According to one or more embodiments, in the third operation, the second portion **82** of the antenna module bracket **8** may be coupled to the first screw fastening portion **SF1** of the first support portion **71** by the first screw **S1**, and the third portion **83** of the antenna module bracket **8** may be coupled to the second screw fastening portion **SF2** of the first support portion **71** by the second screw **S2**.

[0368] According to various embodiments, a first opening (not separately illustrated) may be provided to replace the first groove **1101**. A second opening (not separately illustrated) may be provided to replace the second groove **1102**. The first opening may be a first through-hole penetrating between the first support surface **71A** and the second support surface **71B** of the first support portion **71**. The second opening may be a second through-hole penetrating between the first support surface **71A** and the second support surface **71B** of the first support portion **71**.

[0369] According to various embodiments, although not separately illustrated, the positions or number of guides are not limited to the illustrated example and may vary. The first guide **G1** and the second guide **G2** may be provided, for example, between the second portion **82** and the third portion **83** when viewed from above the first surface **511** of the antenna module **5** or from above the rear plate **32**. As another example, a single guide may be provided to replace the first guide **G1** and the second guide **G2**. To allow the antenna module assembly **9** to move in a balanced and stable manner when the second operation is performed, a clearance between the insert and the groove of the single guide and/or a width of the single guide extending in the second direction **502** may be provided.

[0370] According to one or more embodiments, heat emitted from the antenna module **5** may be transferred to the first support portion **71** (or the frame **701**) via the antenna module bracket **8** by conduction, in which heat flows from a high-temperature portion to a low-temperature portion. Heat may be emitted from components such as the antenna structure **51** (see FIG. 4), the communication circuit **54**, or the power management circuit **55**. The first support portion **71** or the frame **701** may be included in a heat spreader of the electronic device **3**. The antenna module bracket **8** may serve as a heat transfer path between the antenna module **5** and the first support portion **71**. According to various embodiments, the heat spreader of the electronic device **3** may be interpreted as further including the antenna module bracket **8**. The dissipation or distribution of heat, emitted from the antenna module **5**, to the antenna module bracket **8** and the first support portion **71** (or the frame **701**) may prevent overheating of the antenna module **5**, thereby suppressing or preventing performance degradation or damage to the antenna module **5**.

[0371] According to one or more embodiments, at least a portion of the antenna module **5** may be in physical contact with the antenna module bracket **8**. Heat emitted from the antenna module **5** may be transferred to the antenna module bracket **8** through the physical contact portion between the antenna module **5** and the antenna module bracket **8**.

[0372] According to one or more embodiments, a heat-conductive material (not separately illustrated), such as a thermal interface material (TIM), may be disposed between the antenna module **5** and the antenna module bracket **8**. The heat-conductive material may enhance the

performance of transferring heat (e.g., heat transfer performance) from the antenna module 5 to the antenna module bracket 8. In various embodiments, an adhesive material (or bonding material) that couples the antenna module 5 and the antenna module bracket 8 may include a heat-conductive material.

[0373] According to one or more embodiments, at least a portion of the antenna module bracket 8 may be in physical contact with the first support portion 71. Heat may be transferred from the antenna module bracket 8 to the first support portion 71 via the physical contact portion between the antenna module bracket 8 and the first support portion 71.

[0374] In various embodiments, a heat-conductive material (not separately illustrated), such as a TIM, may be disposed between the antenna module bracket 8 and the first support portion 71. The heat-conductive material may enhance the performance of heat transfer from the antenna module bracket 8 to the first support portion 71.

[0375] According to one or more embodiments, convective heat transfer, which is a mode of energy transfer between a solid surface and a gas, may act between the antenna module bracket 8 and the internal air of the electronic device 3, and between the first support portion 71 and the internal air of the electronic device 3.

[0376] FIG. 12 is a cross-sectional view of an electronic device 3 according to one or more embodiments of the disclosure taken along line A-A' in FIG. 10. FIG. 13 is a cross-sectional view of the electronic device 3 according to one or more embodiments taken along line C-C' in FIG. 10. FIG. 13 is a cross-sectional view of the electronic device 3 according to one or more embodiments of the disclosure taken along line C-C' in FIG. 10. FIG. 14 is a cross-sectional view of an electronic device 3 according to one or more embodiments of the disclosure taken along line D-D' in FIG. 10. FIG. 15 is a cross-sectional view of the electronic device 3 according to one or more embodiments of the disclosure taken along line E-E'. FIG. 16 is a cross-sectional view of the electronic device 3 according to one or more embodiments of the disclosure taken along line F-F'. FIGS. 17 and 18 are cross-sectional views each illustrating the assembly of an antenna module assembly 9 and a frame 701 according to one or more embodiments of the present disclosure.

[0377] Referring to FIGS. 12 to 18, the electronic device 3 may include a front plate 31, a rear plate 32, a first side portion 331, a first support portion 71, a display module 401, a first adhesive member (or first bonding member) 1201, a second adhesive member (or second bonding member) 1202, an antenna module 5, an antenna module bracket 8, a first screw S1, a second screw S2, a first elastic member (or first elastic element) 1301, and/or a second elastic member (or second elastic element) 1302.

[0378] According to one or more embodiments, the front plate 31 may provide the front surface 30A of the electronic device 3. The rear plate 32 may provide the rear surface 30B of the electronic device 3. The front surface 30A and the rear surface 30B of the electronic device 3 may be oriented in substantially opposite directions.

[0379] According to one or more embodiments, the first side portion 331 may be provided as a first side surface of the side surface 30C (see FIG. 3) of the electronic device 3. The first side portion 331 may be provided by a combination of a first metal portion A1 and a non-conductive portion 35. The first metal portion A1 may include an opening 34 corresponding to the antenna module 5. The non-conductive portion 35 may be disposed in the opening 34 of the first metal portion A1.

[0380] According to one or more embodiments, the first support portion 71 may be positioned between the front plate 31 and the rear plate 32. The first support portion 71 may be connected to a side portion 33 (see FIG. 7). The first support portion 71 may include a non-conductor 1401 that includes at least one non-conductive portion and a conductor 1402 that is connected to the non-conductor 1401 and includes at least one conductive portion.

[0381] According to one or more embodiments, the display module 401 may be positioned between the first support portion 71 and the front plate 31. The display area (or active area) of the display module 401 may be visible through the front plate 31.

[0382] According to one or more embodiments, the first adhesive member (or first bonding member) **1201** may be disposed between the first support portion **71** and the display module **401**. The display module **401** may be disposed on the first support portion **71** via the first adhesive member (or first bonding member) **1201**.

[0383] According to one or more embodiments, the second adhesive member (or second bonding member) **1202** may be disposed between the first support portion **71** and the rear plate **32**. The rear plate **32** may be disposed on the first support portion **71** via the second adhesive member (or second bonding member) **1202**.

[0384] According to one or more embodiments, the second adhesive member (or second bonding member) **1202** may be disposed between the rear plate **32** and the first surface area **711** of the first support portion **71**.

[0385] According to one or more embodiments, the first surface area **711** may include a plane that is substantially oriented in a direction in which the rear surface **30B** of the electronic device **3** is oriented (e.g., the $-z$ axis direction).

[0386] According to one or more embodiments, the antenna module **5** may be connected to the first support portion **71** via the antenna module bracket **8**. The antenna module **5** may be disposed on or coupled to the first portion **81** of the antenna module bracket **8**. The antenna module **5** and the antenna module bracket **8** may be positioned in a space between the first support portion **71** and the rear plate **32** (e.g., the second space **1502**).

[0387] According to one or more embodiments, the second portion **82** of the antenna module bracket **8** extending from the first portion **81** may be fixed to the second surface area **712** of the first support portion **71**. The second portion **82** may include the first screw hole **H1**. The first screw fastening portion **SF1** may be provided to correspond to the second surface area **712**. Through fastening (e.g., screw fastening) between the first screw **S1** and the first screw fastening portion **SF1**, the second portion **82** may be fixed to the second surface area **712**.

[0388] According to one or more embodiments, the third portion **83** of the antenna module bracket **8** extending from the first portion **81** may be fixed to the third surface area **713** of the first support portion **71**. The third portion **83** may include the second screw hole **H2**. The first screw fastening portion **SF2** may be provided to correspond to the third surface area **713**. Through fastening (e.g., screw fastening) between the second screw **S2** and the second screw fastening portion **SF2**, the third portion **83** may be fixed to the third surface area **713**.

[0389] According to one or more embodiments, the second surface area **712** and/or the third surface area **713** may include a plane that is substantially oriented in a direction in which the rear surface **30B** of the electronic device **3** is oriented (e.g., the $-z$ axis direction).

[0390] According to one or more embodiments, the second surface area **712** and/or the third surface area **713** may be substantially parallel to the first surface area **711**.

[0391] According to one or more embodiments, the second surface area **712** and/or the third surface area **713** may include a plane that is substantially perpendicular to the first surface **511** of the antenna module **5**.

[0392] According to one or more embodiments, the second surface area **712** and the third surface area **713** may be provided lower than the first surface area **711** in a direction in which the rear surface **30B** of the electronic device **3** is oriented (e.g., the $-z$ axis direction). Providing the second surface area **712** lower than the first surface area **711** in the direction in which the rear surface **30B** of the electronic device **3** is oriented may allow the head **S11** of the first screw **S1** to be spaced apart from the rear plate **32** so as not to press against the rear plate **32**. Providing the third surface area **713** lower than the first surface area **711** in the direction in which the rear surface **30B** of the electronic device **3** is oriented may allow the head **S21** of the second screw **S2** to be spaced apart from the rear plate **32** so as not to press against the rear plate **32**.

[0393] According to one or more embodiments, the first support portion **71** may include a first wall **W1**, a second wall **W2**, and a fourth surface **720**. A recess **R** corresponding to the antenna module

assembly **9** in the first support portion **71** may be provided by a combination of the first wall **W1**, the second wall **W2**, and the fourth surface **720**. The antenna module assembly **9** may be inserted into the recess **R**.

[0394] According to one or more embodiments, the first wall **W1** may be at least partially positioned between the first side portion **331** and the first surface **511** of the antenna module **5**. The first wall **W1** may be connected to the first side portion **331**. When viewed from above the first surface **511** of the antenna module **5**, the non-conductive portion **35** of the first side portion **331** may overlap the first wall **W1**. When viewed from above the first surface **511** of the antenna module **5**, the non-conductive portion **35** and the first wall **W1** may overlap the first surface **511** of the antenna module **5** or the antenna array **52** of the antenna module **5** (see FIG. **9**).

[0395] According to one or more embodiments, the second wall **W2** may be positioned to correspond to the second surface **512** of the antenna module **5**. When viewed from above the second surface **512** of the antenna module **5**, the second wall **W2** may overlap the second surface **512**.

[0396] According to one or more embodiments, the second wall **W2** may support the antenna module **5**.

[0397] According to one or more embodiments, a portion of the first portion **81** included in the antenna module bracket **8** may be positioned between the antenna module **5** and the second wall **W2**.

[0398] According to one or more embodiments, the second wall **W2** may support the first portion **81** of the antenna module bracket **8**.

[0399] According to one or more embodiments, when viewed from above the rear plate **32**, the antenna module assembly **9** may be at least partially positioned between the first side portion **331** and the battery **76**.

[0400] According to one or more embodiments, the second wall **W2** may be a portion of the battery support wall **BW** (see FIG. **10**).

[0401] According to one or more embodiments, the non-conductive portion **35** and the first wall **W1** may be included in the RF window area of the antenna module **5**. The non-conductive portion **35** and the first wall **W1** may include a non-conductive material. Electromagnetic waves transmitted (or radiated) from the antenna module **5** may pass through the first wall **W1** and the non-conductive portion **35** to propagate to the exterior of the electronic device **3**. Electromagnetic waves transmitted from the exterior of the electronic device **3** may pass through the non-conductive portion **35** and the first wall **W1** to be received (or detected) by the antenna module **5**.

[0402] According to one or more embodiments, the non-conductive portion **35** and the first wall **W1** may have a permittivity capable of reducing the impact on the antenna radiation performance (or electromagnetic wave transmission/reception performance) or the coverage (or beam coverage) of the antenna module **5**.

[0403] According to one or more embodiments, a first air gap **AG1** may be provided between the first wall **W1** and the first surface **511** of the antenna module **5**. Compared to a comparative example in which substantially no spacing (e.g., the first air gap **AG1**) is present between the first wall **W1** and the first surface **511** of the antenna module **5**, the first air gap **AG1** may reduce the electromagnetic influence of the first wall **W1** on the antenna radiation performance (or electromagnetic wave transmission/reception performance) or the coverage (or beam coverage) of the antenna module **5**.

[0404] According to one or more embodiments, a surface of the first wall **W1** facing the first surface **511** of the antenna module **5** may include a recess (not separately illustrated). The recess of the first wall **W1** may contribute to the provision of the first air gap **AG1**.

[0405] According to various embodiments, a first dielectric material (not separately illustrated) disposed (e.g., filled) in the first air gap **AG1** may be provided. The first dielectric material may be included in the RF window area. The first dielectric material may have a permittivity that is

capable of reducing the degradation of the antenna radiation performance of the antenna module **5** or a permittivity that does not degrade the antenna radiation performance to a threshold level or lower. The first dielectric material may have a permittivity that has an effect within a range that does not exceed the coverage area intended to be secured by the antenna module **5** or a permittivity that substantially does not affect the coverage of the antenna module **5**. The permittivity of the first dielectric material may be, for example, a value that reduces the difference from the permittivity of air (e.g., a low permittivity). In various embodiments, the first dielectric material may include an adhesive material or a bonding material.

[0406] According to one or more embodiments, a second air gap **AG2** may be provided between the non-conductive portion **35** and the first wall **W1**. Compared to a comparative example in which substantially no spacing (e.g., the second air gap **AG2**) is present between the non-conductive portion **35** and the first wall **W1**, the second air gap **AG2** may reduce the electromagnetic influence of the non-conductive portion **35** or the first wall **W1** on the antenna radiation performance (or electromagnetic wave transmission/reception performance) or the coverage (or beam coverage) of the antenna module **5**.

[0407] According to various embodiments, a second dielectric material (not separately illustrated) disposed (e.g., filled) in the first air gap **AG2** may be provided. The second dielectric material may be included in the RF window area. The second dielectric material may have a permittivity that is capable of reducing the degradation of the antenna radiation performance of the antenna module **5** or a permittivity that does not degrade the antenna radiation performance to a threshold level or lower. The second dielectric material may have a permittivity that has an effect within a range that does not exceed the coverage area intended to be secured by the antenna module **5** or a permittivity that substantially does not affect the coverage of the antenna module **5**. The permittivity of the second dielectric material may be, for example, a value that reduces the difference from the permittivity of air (e.g., a low permittivity). In various embodiments, the second dielectric material may include an adhesive material or a bonding material.

[0408] According to various embodiments, the first wall **W1** may include at least one opening (not separately illustrated) that overlaps the first surface **511** of the antenna module **5** or the antenna array **52** (see FIG. **9**) when viewed from above the first surface **511**. The at least one opening of the first wall **W1** may reduce the electromagnetic influence of the first wall **W1** on the antenna radiation performance (or electromagnetic wave transmission/reception performance) or the coverage (or beam coverage) of the antenna module **5**.

[0409] According to various embodiments, the non-conductive portion **35** or the first wall **35** may be implemented as a dielectric lens. A dielectric lens may secure or enhance the antenna radiation performance and/or coverage of the antenna module **5**.

[0410] According to various embodiments, the non-conductive portion **35** and the first wall **35** may be implemented as a dielectric lens. A dielectric lens may secure or enhance the antenna radiation performance and/or coverage of the antenna module **5**.

[0411] According to one or more embodiments, the first elastic member **1301** may be at least partially disposed between the first wall **W1** and the antenna module **5**. The first elastic member **1301** may be disposed or coupled to the first wall **W1** or the antenna module **5**. For example, the first elastic member **1301** may be at least partially disposed between the first surface **511** of the antenna module **5** and the first wall **W1**. The first elastic member **1301** may suppress or prevent the antenna module **5** from colliding with the first wall **W1**. The first elastic member **1301** may include a buffering material. For external impacts such as the dropping of the electronic device **3**, the first elastic member **1301** may suppress or prevent the influence of external impacts on the antenna module **5**. During the assembly of placing the antenna module assembly **9** in the frame **701** (see FIGS. **7** and **8**), the first elastic member **1301** may suppress or prevent the antenna module **5** from colliding with the first wall **W1**.

[0412] According to one or more embodiments, the first elastic member **1301** may contribute to

providing a spacing (e.g., the first air gap AG1) between the first wall W1 and the antenna module 5.

[0413] According to one or more embodiments, the first elastic member 1301 may be disposed at a position that does not substantially affect the antenna radiation performance or the coverage of the antenna module 5.

[0414] According to one or more embodiments, the first elastic member 1301 may be interpreted as at least a portion of the first dielectric material disposed in the first air gap AG1.

[0415] According to one or more embodiments, the second elastic member 1302 may be disposed between the second wall W2 and the first portion 81 of the antenna module bracket 8. The second elastic member 1302 may be disposed on or coupled to the second wall W2 or the antenna module bracket 8. The second wall W2 may support the first portion 81 of the antenna module bracket 8 via the second elastic member 1302.

[0416] According to various embodiments, the second elastic member 1302 may include a heat-conductive material (not separately illustrated). The second elastic member 1302 may enhance the performance of transferring heat (e.g., heat transfer performance) from the antenna module bracket 8 to the first support portion 71.

[0417] According to one or more embodiments, the electronic device 3 may include a first guide G1 provided by a combination of the first insert 801 of the antenna module bracket 8 and the first groove 1101 of the first support portion 71. The electronic device 3 may include a second guide G2 provided by a combination of the second insert 802 of the antenna module bracket 8 and the second groove 1102 of the first support portion 71. During the assembly of the antenna module assembly 9 into the frame 701 (see FIGS. 7 and 8), the first guide G1 and the second guide G2 may guide the placement of the antenna module assembly (see FIGS. 7 and 8).

[0418] According to one or more embodiments, a method of placing the antenna module assembly 9 in the frame 701 may include a first operation, a second operation, and a third operation. In the first operation, the antenna module assembly 9 may be inserted into the recess R of the frame 701. In the second operation, the antenna module assembly 9 may be rotated about the first guide G1 and the second guide G2. In the third operation, the antenna module bracket 8 may be coupled to the frame 701 by the first screw S1 (see FIG. 13) and the second screw S2 (see FIG. 14).

[0419] “1701” in FIG. 17 is a cross-sectional view illustrating the antenna module assembly 9 and the frame 701 corresponding to the first guide G1 according to the first operation. “1801” in FIG. 18 is a cross-sectional view illustrating the antenna module assembly 9 and the frame 701 corresponding to the second guide G2 according to the first operation. “1702” in FIG. 17 is a cross-sectional view illustrating the antenna module assembly 9 and the frame 701 corresponding to the first guide G1 according to the second operation. “1802” in FIG. 18 is a cross-sectional view illustrating the antenna module assembly 9 and the frame 701 corresponding to the second guide G2 according to the second operation.

[0420] According to one or more embodiments, in the first operation, the antenna module assembly 9 may be inserted into the recess R of the frame 701. Through the first operation, the first insert 801 of the antenna module bracket 8 may be inserted into the first groove 1101, and the second insert 802 of the antenna module bracket 8 may be inserted into the second groove 1102.

[0421] According to one or more embodiments, in the second operation, the antenna module assembly 9 inserted into the recess R may be rotated about the first guide G1 and the second guide G2. Through the second operation, the second portion 82 of the antenna module bracket 8 may be positioned to correspond to the second surface area 712 of the first support portion 71, and the third portion 83 of the antenna module bracket 8 may be positioned to correspond to the third surface area 713 of the first support portion 71.

[0422] According to one or more embodiments, in the third operation, the second portion 82 of the antenna module bracket 8 may be coupled to the first screw fastening portion SF1 of the first support portion 71 by the first screw S1, and the third portion 83 of the antenna module bracket 8

may be coupled to the second screw fastening portion SF2 of the first support portion 71 by the second screw S2.

[0423] FIG. 19 illustrates a cross-sectional view of an electronic device 3 of one or more embodiments of the present disclosure (1900), a cross-sectional view of an electronic device of a comparative example (2000), heat maps illustrating electromagnetic wave energy (or wave energy) radiated from the electronic device 3 of the embodiment, and heat maps illustrating electromagnetic wave energy radiated from the electronic device of the comparative example.

[0424] Referring to FIG. 19, an electronic device 3 of one or more embodiments may include a frame 701 and an antenna module assembly 9. The antenna module assembly 9 may include an antenna module 5 and an antenna module bracket 8. A method of placing the antenna module assembly 9 in the frame 701 may include insertion (1901), rotation (1902), and fixation (not separately illustrated). Insertion (1901) may refer to inserting the antenna module assembly 9 into the recess R of the frame 701 so that a guide G (e.g., the first guide G1 of FIG. 17 and the second guide G2 of FIG. 18) is provided. Rotation (1902) may refer to rotating the antenna module assembly 9 about the guide G. Fixation may refer to fixing the antenna module bracket 8 to the frame 701 through screw fastening.

[0425] An electronic device according to a comparative example may include a frame 20701 and an antenna module assembly 2009. The antenna module assembly 2009 may include an antenna module 5 and an antenna module bracket 2008. A method of placing the antenna module assembly 2009 in the frame 20701 may include insertion (2001) and fixation (not separately illustrated). Insertion (2001) may refer to inserting the antenna module assembly 2009 into a recess R1 of the frame 20701. Fixation may refer to fixing the antenna module bracket 2008 to the frame 20701 through screw fastening.

[0426] Since the method of placing the antenna module assembly 9 in the frame 701 of the electronic device 3 of the embodiment includes the combination of insertion (1901) and rotation (1902), the first wall W1 may more easily provide a recess 1904 in which the antenna module 5 may be inserted closer to the non-conductive portion 35 compared to the first wall W11 of the electronic device of the comparative example.

[0427] In the electronic device 3 of the embodiment, the method of placing the antenna module assembly 9 in the frame 701 includes a combination of insertion (1901) and rotation (1902). Accordingly, compared to the electronic device of the comparative example, the distance by which the first surface 511 of the antenna module 5 is spaced apart from the non-conductive portion 35 (or the opening 34 of the first metal portion A1) may be reduced (see “L1” and “L2”). Since the electronic device 3 of the embodiment is capable of reducing the distance between the first surface 511 of the antenna module 5 and the non-conductive portion 35 (or the opening 34 of the first metal portion A1) compared to the electronic device of the comparative example, the electromagnetic influence of the first metal portion A1 on the antenna module 5 may be reduced. In the electronic device 3 of the embodiment, the coverage 1903 of the antenna module 5 may be improved compared to the coverage 2003 of the antenna module 5 in the electronic device of the comparative example.

[0428] “1910” represents a heat map indicating wave energy when electromagnetic waves of an operating frequency (or usage frequency) of about 28 GHz are radiated from the antenna module 5 in the electronic device 3 of the embodiment. “2010” represents a heat map indicating wave energy when electromagnetic waves of an operating frequency of about 28 GHz are radiated from the antenna module 5 in the electronic device of the comparative example. By comparing the heat map of “1910” and the heat map of “2010,” the electronic device 3 of the embodiment may provide a beam pattern that ensures transmission/reception performance for electromagnetic waves in a more expanded coverage area compared to the electronic device of the comparative example.

[0429] “1920” represents a heat map indicating wave energy when electromagnetic waves of an operating frequency (or usage frequency) of about 39 GHz are radiated from the antenna module 5

in the electronic device **3** of the embodiment. “**2020**” represents a heat map indicating wave energy when electromagnetic waves of an operating frequency of about 39 GHz are radiated from the antenna module **5** in the electronic device of the comparative example. By comparing the heat map of “**1920**” and the heat map of “**2020**,” the electronic device **3** of the embodiment may provide a beam pattern that ensures transmission/reception performance for electromagnetic waves in a more expanded coverage area compared to the electronic device of the comparative example.

[0430] Table 1 illustrates the gain of the antenna module **5** for electromagnetic waves in a first polarization direction at a use frequency (or operating frequency) of about 28 GHz.

TABLE-US-00001

TABLE 1 CDF-EIFP [dBm]	Category	CDF 50%	CDF 100%
Electronic device 3	0.45	9.63	embodiment
Electronic device of comparative example	-0.17	8.93	

[0431] Referring to FIG. **19** and Table 1, the electronic device **3** of the embodiment may expand coverage compared to the electronic device of the comparative example. For example, based on a cumulative distribution function (CDF) of 50% or 100%, the electronic device **3** of the embodiment may have improved transmission/reception performance for electromagnetic waves in the first polarization direction compared to the electronic device of the comparative example.

[0432] Table 2 illustrates the gain of the antenna module **5** for electromagnetic waves in a second polarization direction different from (e.g., perpendicular to) the first polarization direction at a use frequency (or operating frequency) of about 39 GHz.

TABLE-US-00002

TABLE 2 CDF-EIFP [dBm]	Category	CDF 50%	CDF 100%
Electronic device 3	0.55	11.1	embodiment
Electronic device of comparative example	0.89	10.36	

[0433] Referring to FIG. **19** and Table 2, the electronic device **3** of the embodiment may expand coverage compared to the electronic device of the comparative example. For example, based on a CDF of 50% or 100%, the electronic device **3** of the embodiment may have improved transmission/reception performance for electromagnetic waves in the second polarization direction compared to the electronic device of the comparative example.

[0434] In the electronic device **3** of the embodiment, the placement of the antenna module assembly **9** in the recess **R** of the frame **701** through a combination of insertion (**1901**) and rotation (**1902**) may contribute to maintaining the relative position of the antenna module assembly **9** with respect to the frame **701**, even if loosening or relaxation of screw fastening occurs due to external impacts such as the dropping of the electronic device **3** (e.g., the loosening of the first screw **S1** or the second screw **S2** of FIG. **10**). As the relative position between the frame **701** and the antenna module assembly **9** is maintained, the antenna radiation performance or coverage of the antenna module **5** may also be maintained.

[0435] According to an exemplary embodiment of the disclosure, an electronic device **3** includes a front plate **31**, a rear plate **32**, a side portion (e.g., the side portion **33**), a support portion (e.g., the first support portion **71**), a printed circuit board **510**, at least one antenna element (e.g., the plurality of antenna elements **521**, **522**, **523**, **524**, and **525**), and a bracket (e.g., the antenna module bracket **8**). The front plate **31** provides at least a portion of the front surface **30A** of the electronic device **3**. The rear plate **32** provides at least a portion of the rear surface **30B** of the electronic device **3**. The side portion (e.g., the side portion **33**) provides at least a portion of a side surface **30C** of the electronic device **3**. The side portion (e.g., the side portion **33**) includes a conductive portion (e.g., the first metal portion **A1**) providing a portion of the side surface **30C** and a non-conductive portion **35** providing another portion of the side surface **30C**. The support portion (e.g., the first support portion **71**) is positioned between the front plate **31** and the rear plate **32**. The support portion (e.g., the first support portion **71**) is connected to the side portion (e.g., side portion **33**). The printed circuit board **510** includes a first surface **511** facing the non-conductive portion **35** and a second surface **512** facing a direction opposite to the first surface **511**. At least one antenna element (e.g., the plurality of antenna elements **521**, **522**, **523**, **524**, and **525**) is disposed on the first surface **511** or disposed inside the printed circuit board **510** positioned the first surface **511** than to the second surface **512**. A bracket **8** connects the printed circuit board **510** and the support portion (e.g., the

first support portion **71**). The bracket **8** includes a first portion **81** on which the printed circuit board **510** is disposed, and a second portion **82** extending from the first portion **81** and fixed to the support portion (e.g., first support portion **71**) by a screw (e.g., the first screw **S1**). The support portion (e.g., the first support portion **71**) includes a wall (e.g., the second wall **W2**) protruding toward the rear plate **32**. The printed circuit board **510** is positioned between the non-conductive portion **35** and the wall (e.g., the second wall **W2**). The wall (e.g., the second wall **W2**) supports the first portion **81**.

[0436] According to an exemplary embodiment of the disclosure, the electronic device **3** may further include a battery **76** disposed on the support portion (e.g., the first support portion **71**) between the support portion (e.g., the first support portion **71**) and the rear plate **32**. The wall (e.g., the second wall **W2**) may be positioned between the printed circuit board **510** and the battery **76**. The wall (e.g., the second wall **W2**) may support the battery **76**.

[0437] According to an exemplary embodiment of the disclosure, the electronic device **3** may further include an adhesive member (e.g., the second adhesive member **1202**) disposed between the support portion (e.g., first support portion **71**) and the rear plate **32**. The support portion (e.g., the first support portion **71**) may include a third surface **710** at least partially positioned along the side portion (e.g., the side portion **33**). The third surface **710** may face the rear plate **32**. The third surface **710** may include a first surface area **711** corresponding to an adhesive member (e.g., the second adhesive member **1202**) and a second surface area **712** corresponding to the second portion **82**. The second portion **82** may be fixed to the second surface area **712** by a screw (e.g., the first screw **S1**).

[0438] According to an exemplary embodiment of the disclosure, the first surface area **711** may be positioned closer to the rear plate **32** than to the second surface area **712**.

[0439] According to an exemplary embodiment of the disclosure, the support portion (e.g., the first support portion **71**) may further include a non-conductive wall (e.g., the first wall **W1**) at least partially positioned between the non-conductive portion **35** and the first surface **511** and connected to the side portion (e.g., the side portion **33**).

[0440] According to an exemplary embodiment of the disclosure, the electronic device **3** may further include a first air gap **AG1** provided between the non-conductive wall (e.g., the first wall **W1**) and the first surface **511**.

[0441] According to an exemplary embodiment of the disclosure, the electronic device **3** may further include a second air gap **AG2** provided between the non-conductive portion **35** and the non-conductive wall (e.g., the first wall **W1**).

[0442] According to an exemplary embodiment of the disclosure, the electronic device **3** may further include a dielectric material of an adhesive material disposed in the second air gap **AG2**.

[0443] According to an exemplary embodiment of the disclosure, the non-conductive wall (e.g., the first wall **W1**) may include a recess into which the printed circuit board **510** is inserted.

[0444] According to an exemplary embodiment of the disclosure, the electronic device **3** may further include a first elastic member **1301** positioned between the non-conductive wall (e.g., the first wall **W1**) and the printed circuit board **510**.

[0445] According to an exemplary embodiment of the disclosure, the support portion **71** may include a fourth surface **720** connecting the wall (e.g., the second wall **W2**) and the non-conductive wall (e.g., the first wall **W1**). The printed circuit board **510** may be inserted into a recess **R** provided by a combination of the wall (e.g., the second wall **W2**), the non-conductive wall (e.g., the first wall **W1**), and the fourth surface **720**. The support portion (e.g., the first support portion **71**) may include a groove (e.g., the first groove **1101**) provided in the fourth surface **720**. The bracket **8** may include an insert (e.g., the first insert **801**) inserted into the groove (e.g., the first groove **1101**).

[0446] According to an exemplary embodiment of the disclosure, the insert (e.g., the first insert **801**) may include a hemming structure.

[0447] According to an exemplary embodiment of the disclosure, the electronic device **3** may further include a second elastic member **1302** positioned between the first portion **81** and the wall (e.g., the second wall **W2**).

[0448] According to an exemplary embodiment of the disclosure, the electronic device **3** may further include a communication circuit **54** disposed on the second surface **512**. The communication circuit **54** may be configured to transmit and/or receive a mmWave wireless signal via at least one antenna element (e.g., the plurality of antenna elements **521**, **522**, **523**, **524**, and **525**).

[0449] According to an exemplary embodiment of the disclosure, the electronic device **3** may further include a heat-conductive material disposed between the bracket (e.g., the antenna module bracket **8**) and the support portion (e.g., the first support portion **71**).

[0450] According to an exemplary embodiment of the disclosure, an electronic device **3** includes a front plate **31**, a rear plate **32**, a side portion (e.g., the side portion **33**), a support portion (e.g., the first support portion **71**), a printed circuit board **510**, at least one antenna element (e.g., the plurality of antenna elements **521**, **522**, **523**, **524**, and **525**), a communication circuit **54**, and a bracket (e.g., the antenna module bracket **8**). The front plate **31** provides at least a portion of the front surface **30A** of the electronic device **3**. The rear plate **32** provides at least a portion of the rear surface **30B** of the electronic device **3**. The side portion (e.g., the side portion **33**) provides at least a portion of a side surface **30C** of the electronic device **3**. The side portion (e.g., the side portion **33**) includes a conductive portion (e.g., the first metal portion **A1**) providing a portion of the side surface **30C** and a non-conductive portion **35** providing another portion of the side surface **30C**. The support portion (e.g., the first support portion **71**) is positioned between the front plate **31** and the rear plate **32**. The support portion (e.g., the first support portion **71**) is connected to the side portion (e.g., side portion **33**). The printed circuit board **510** includes a first surface **511** facing the non-conductive portion **35** and a second surface **512** facing a direction opposite from the first surface **511**. At least one antenna element (e.g., the plurality of antenna elements **521**, **522**, **523**, **524**, and **525**) is disposed on the first surface **511** or disposed inside the printed circuit board **510** positioned the first surface **511** than to the second surface **512**. The communication circuit **54** is disposed on the second surface **512**. The communication circuit **54** is configured to transmit and/or receive a mmWave wireless signal via at least one antenna element (e.g., the plurality of antenna elements **521**, **522**, **523**, **524**, and **525**). A bracket (e.g., the bracket **8**) connects the printed circuit board **510** and the support portion (e.g., the first support portion **71**). The bracket (e.g., the antenna module bracket **8**) includes a first portion **81** on which the printed circuit board **510** is disposed, and a second portion **82** extending from the first portion **81** and fixed to the support portion (e.g., first support portion **71**) by a screw (e.g., the first screw **S1**). The support portion (e.g., the first support portion **71**) includes a wall (e.g., the second wall **W2**) protruding toward the rear plate **32**. The printed circuit board **510** is positioned between the non-conductive portion **35** and the wall (e.g., the second wall **W2**). The wall (e.g., the second wall **W2**) supports the first portion **81**.

[0451] According to an exemplary embodiment of the disclosure, the electronic device **3** may further include a battery **76** disposed on the support portion (e.g., the first support portion **71**) between the support portion (e.g., the first support portion **71**) and the rear plate **32**. The wall (e.g., the second wall **W2**) may be positioned between the printed circuit board **510** and the battery **76**. The wall (e.g., the second wall **W2**) may support the battery **76**.

[0452] According to an exemplary embodiment of the disclosure, the support portion (e.g., the first support portion **71**) may further include a non-conductive wall (e.g., the first wall **W1**) at least partially positioned between the non-conductive portion **35** and the first surface **511**.

[0453] According to an exemplary embodiment of the disclosure, the electronic device **3** may further include a dielectric material of an adhesive material disposed between the non-conductive portion **35** and the non-conductive wall (e.g., the first wall **W1**).

[0454] According to an exemplary embodiment of the disclosure, the support portion (e.g., the first

support portion **71**) may include a fourth surface **720** connecting the wall (e.g., the second wall **W2**) and the non-conductive wall (e.g., the first wall **W1**). The printed circuit board **510** may be inserted into a recess **R** provided by a combination of the wall (e.g., the second wall **W2**), the non-conductive wall (e.g., the first wall **W1**), and the fourth surface **720**. The support portion (the first support portion **71**) may include a groove (e.g., the first groove **1101**) provided in the fourth surface **720**. The bracket (e.g., the antenna module bracket **8**) may include an insert (e.g., the first insert **801**) inserted into the groove (e.g., the first groove **1101**).

[0455] While various embodiments have been described above with reference to the drawings, the present disclosure is not limited thereto, and any combination or substitution of components as appropriate is included within the scope of the present disclosure. In some embodiments, modifications such as combinations, changes in the order of processes, and various changes in design may be made on the basis of knowledge of a person skilled in the art, and such modified embodiments are within the scope of the present disclosure and the appended claims.

Claims

1. An electronic device comprising: a front plate being at least a portion of a front surface of the electronic device; a rear plate being at least a portion of a rear surface of the electronic device; a side portion being at least a portion of a side surface of the electronic device and comprising a conductive portion being a portion of the side surface and a non-conductive portion being another portion of the side surface; a support portion between the front plate and the rear plate and connected to the side portion; a printed circuit board comprising: a first surface facing the non-conductive portion; and a second surface facing a direction opposite to the first surface; at least one antenna element disposed on the first surface or disposed inside the printed circuit board closer to the first surface than to the second surface; and a bracket connecting the printed circuit board and the support portion and comprising: a first portion on which the printed circuit board is disposed; and a second portion extending from the first portion and fixed to the support portion by a screw, wherein the support portion comprises a wall protruding toward the rear plate, wherein the printed circuit board is between the non-conductive portion and the wall, and wherein the wall is configured to support the first portion.
2. The electronic device of claim 1, further comprising: a battery on the support portion and between the support portion and the rear plate, wherein the wall is between the printed circuit board and the battery, and wherein the wall is configured to support the battery.
3. The electronic device of claim 1, further comprising: an adhesive member between the support portion and the rear plate, wherein the support portion comprises a third surface at least partially along the side portion, wherein the third surface faces the rear plate and comprises: a first surface area corresponding to the adhesive member; and a second surface area corresponding to the second portion, and wherein the second portion is fixed to the second surface area by the screw.
4. The electronic device of claim 3, wherein the first surface area is closer to the rear plate than to the second surface area.
5. The electronic device of claim 1, wherein the support portion further comprises a non-conductive wall at least partially between the non-conductive portion and the first surface and connected to the side portion.
6. The electronic device of claim 5, further comprising: a first air gap between the non-conductive wall and the first surface.
7. The electronic device of claim 5, further comprising: a second air gap between the non-conductive portion and the non-conductive wall.
8. The electronic device of claim 7, further comprising: a dielectric material of an adhesive material in the second air gap.
9. The electronic device of claim 5, wherein the non-conductive wall comprises a recess, and

wherein the printed circuit board is inserted into the recess.

10. The electronic device of claim 5, further comprising: a first elastic member between the non-conductive wall and the printed circuit board.

11. The electronic device of claim 5, wherein the support portion comprises a fourth surface connecting the wall and the non-conductive wall, wherein the printed circuit board is inserted into a recess formed by a combination of the wall, the non-conductive wall, and the fourth surface, wherein the support portion comprises a groove formed in the fourth surface, and wherein the bracket comprises an insert inserted into the groove.

12. The electronic device of claim 11, wherein the insert comprises a hemming structure.

13. The electronic device of claim 1, further comprising: a second elastic member between the first portion and the wall.

14. The electronic device of claim 1, further comprising: a communication circuit on the second surface, wherein the communication circuit is configured to transmit and/or receive a mm Wave wireless signal through the at least one antenna element.

15. The electronic device of claim 1, further comprising: a heat-conductive material between the bracket and the support portion.
