

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12406651
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Hewett; Adam

Noninvasive neural stimulation through audio

Abstract

First data comprising a first range of audio frequencies is received. The first range of audio frequencies corresponds to a predetermined cochlear region of a listener. Second data comprising a second range of audio frequencies is also received. Third data comprising a first modulated range of audio frequencies is acquired. The third data is acquired by modulating the first range of audio frequencies according to a stimulation protocol that is configured to provide neural stimulation of a brain of the listener. The second data and the third data are arranged to generate an audio composition from the second data and the third data.

Inventors:	Hewett; Adam (Chicago, IL)
Applicant:	BrainFM, Inc. (Brooklyn, NY)
Family ID:	72042318
Assignee:	BrainFM, Inc. (Brooklyn, NY)
Appl. No.:	18/067921
Filed:	December 19, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230282199 A1	Sep. 07, 2023

Related U.S. Application Data

continuation parent-doc US 17556623 20211220 US 11532298 child-doc US 18067921
continuation parent-doc US 16276961 20190215 US 11205414 20211221 child-doc US 17556623

Publication Classification

Int. Cl.: G10K11/18 (20060101); **A61N7/00** (20060101)

U.S. Cl.:

CPC **G10K11/18** (20130101); A61N2007/0026 (20130101); A61N2007/0073 (20130101)

Field of Classification Search

CPC: G10K (11/18); G10K (15/02); A61N (2007/0026); A61N (2007/0073); A61N (7/00);
A61M (21/02); A61M (2021/0027); A61M (2205/502); A61M (2230/10); A61M (21/00);
A61M (2021/0022); A61B (5/291); A61B (5/38); A61B (5/4848); A61B (5/4064)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
4883067	12/1988	Knispel	984/301	A61B 5/375
5267942	12/1992	Saperston	600/28	A63B 71/0686
2003/0089218	12/2002	Gang	N/A	N/A
2005/0201574	12/2004	Lenhardt	381/151	A61H 23/0245
2008/0097633	12/2007	Jochelson	N/A	N/A
2008/0101621	12/2007	Zimmerman	381/61	A61B 7/00
2011/0169603	12/2010	Fithian	N/A	N/A
2014/0330848	12/2013	Chen	N/A	N/A
2015/0356876	12/2014	Wang	N/A	N/A
2017/0043236	12/2016	Li	N/A	N/A
2017/0124074	12/2016	Cama	N/A	N/A
2020/0213790	12/2019	Osborne	N/A	N/A

OTHER PUBLICATIONS

Non-Final Office Action issued in U.S. Appl. No. 17/505,453 mailed on May 4, 2023 (32 pages).
cited by applicant

Primary Examiner: Nguyen; Hien N

Attorney, Agent or Firm: Akerman LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. application Ser. No. 17/556,623, titled “Noninvasive Neural Stimulation Through Audio,” filed Dec. 20, 2021, and currently pending; U.S. application Ser. No. 17/556,623 is a continuation of U.S. application Ser. No. 16/276,961, titled “Noninvasive Neural Stimulation Through Audio,” filed on Feb. 15, 2019, and issued on Dec. 21, 2021, as U.S. Pat. No. 11,205,414. The entire contents of U.S. application Ser. Nos. 17/556,623 and 16/276,961 are incorporated herein by reference.

TECHNICAL FIELD

(1) The present disclosure relates to neural stimulation, and in particular, noninvasive neural

stimulation using audio.

BACKGROUND

(2) For decades, neuroscientists have observed wave-like activity in the brain called neural oscillations. Various aspects of these oscillations have been related to attentional states. The ability to influence attentional states, via noninvasive brain stimulation, would be greatly desirable.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIGS. 1A and 1B are visual representations of entrainment, according example embodiments.
- (2) FIG. 2 is a process flow for providing noninvasive neural stimulation using audio, according to example embodiments.
- (3) FIG. 3 is a visual representation of audio filtering used in providing noninvasive neural stimulation using audio, according to example embodiments.
- (4) FIG. 4 is an illustration of a software user interface configured to generate a cochlear profile for use in noninvasive neural stimulation using audio, according to example embodiments.
- (5) FIG. 5 is a visual representation of audio fidelity for use in noninvasive neural stimulation using audio, according to example embodiments.
- (6) FIG. 6 is an illustration of a software user interface configured to generate a stimulation profile for use in noninvasive neural stimulation using audio, according to example embodiments.
- (7) FIGS. 7A-C are visual representations of the alignment of a modulation signal with the rhythmic elements of an audio element being modulated according to phase and rate to provide noninvasive neural stimulation using audio, according to example embodiments.
- (8) FIGS. 8A-C are visual representations of modulation depth for use in noninvasive neural stimulation using audio, according to example embodiments.
- (9) FIG. 9 is a graph comparing the Phase-Locking Value between a modulated acoustic element and the output of an Electroencephalogram to the Phase-Locking Value between an unmodulated acoustic element and the output of an Electroencephalogram, according to example embodiments.
- (10) FIGS. 10A and 10B are illustrations of modulation waveforms used to target specific areas of the brain for use in noninvasive neural stimulation using audio, according to example embodiments.
- (11) FIG. 11 is an illustration of a software user interface used to generate stimulation waveforms that target specific areas of a brain for noninvasive neural stimulation using audio, according to example embodiments.
- (12) FIG. 12 is functional diagram of an audio arranger used in noninvasive neural stimulation using audio, according to example embodiments.
- (13) FIG. 13 is a flowchart illustrating a process flow for providing the noninvasive neural stimulation using audio techniques, according to example embodiments.
- (14) FIG. 14 is a functional diagram of an apparatus configured to provide the noninvasive neural stimulation using audio of the present disclosure, according to example embodiments.

DESCRIPTION OF EXAMPLE EMBODIMENTS

Overview

- (15) The present disclosure is directed to methods of neural stimulation with any audio. Example embodiments provide a neuroscience-informed way to select for audio components which, when combined with modulated audio components, create an audio arrangement which will stimulate the brain in a noninvasive way.
- (16) According to example embodiments of the present application, first data comprising a first range of audio frequencies is received. The first range of audio frequencies corresponds to a predetermined cochlear region of a listener. Second data comprising a second range of audio

frequencies is also received. Third data comprising a first modulated range of audio frequencies is acquired. The third data is acquired by modulating the first range of audio frequencies according to a stimulation protocol that is configured to provide neural stimulation of a brain of the listener. The second data and the third data are arranged to generate an audio composition from the second data and the third data.

Example Embodiments

(17) Described herein are techniques that provide for non-invasive neural stimulation of the brain. For example, the techniques of the present application utilize modulation of audio elements (e.g., amplitude modulation or volume modulation) to provide stimulus to stimulate the brain. The concept behind this stimulation may be analogized to the way in which unsynchronized metronomes arranged on a table will synchronize due to constructive and destructive interference of the energy transferred between the metronomes via the platform on which they are arranged.

(18) As illustrated in FIG. 1A, several metronomes **101a-e** begin unsynchronized at a time **T1**. Energy is transferred between metronomes **102a-e** via table **102**. The metronomes **101a-e** will reach a minimum energy state, as illustrated in time **T2**, characterized in the synchronization of the motion of metronomes **102a-e**. This synchronization is analogous to how periodic and temporally structured sounds can synchronize and entrain the communication between neurons of the brain. External traveling waves (e.g., acoustic or audio waves) are converted to neuro-electric signals (e.g., via the ear), which entrain desired neural excitations within the brain. In other words, periodic audio may be used to entrain the attentional oscillatory cycles of the brain. Such neural stimulation may be used to improve a user's focus, memory, meditation and sleep, among others.

(19) FIG. 1B depicts a simplified illustration of synchronization of external signals and neural oscillations. External modulated sound **110** is presented to the listener. The listener's existing neural oscillations **111** become synchronized, or entrained to match the external signals as illustrated in entrained neural oscillations **112**. Specifically, the phase of neural oscillations **111** has shifted to match that of external signal **110**, as illustrated in entrained neural oscillations **112**.

(20) The present disclosure provides methods, apparatuses and computer executable media configured to provide such neural stimulation via audio elements. As used herein, "audio element" refers to a single audio input, usually a single digital file, but also could be an audio feed from a live recording. As further explained below, the techniques may be particularly effective when the audio stimulation is provided by predetermined frequencies that are associated with known portions of the cochlea of the human ear. Furthermore, the techniques of the present application provide for the selection of the waveforms configured to target specific areas of the brain.

(21) With reference now made to FIG. 2, depicted therein is a process flow **200** according to the techniques described herein. The process flow **200** is exemplary, and elements may be added or removed from process flow **200** without deviating from the inventive concepts of the present application. Process flow **200** is configured to generate a stimulation protocol **260**. As used herein, a "stimulation protocol" (such as stimulation protocol **260**) is one or more values that determine how a modulator (such as modulator **250**) modulates audio frequency data to induce neural stimulation or entrainment. According to specific example embodiments, a stimulation protocol (such as stimulation protocol **260**) may provide one or more of a modulation rate, phase, depth and/or waveform for the modulation to be applied to audio frequency data that is used to induce neural stimulation or entrainment. Modulation rate, phase, depth and waveform refer to four non-exclusive parameters used to control any low frequency oscillator. Rate is the speed of the oscillation, often defined in hertz. Phase is the particular point in the full cycle of modulation, often measured as an angle in degrees. Depth is the how large or small the modulation cycle is, in comparison to what it is modulating. In amplitude modulation, it would be expressed as a linear percent of the whole volume available. Waveform expresses the shape of the modulation cycle, such as a sine wave, a triangle wave or some other custom wave. Neural stimulation via such a stimulation protocol may be used on conjunction with a cochlear profile to induce effective

stimulations in a user's brain.

(22) The process flow **200** of FIG. 2 also provides for the generation of a cochlear profile for use in noninvasive neural stimulation. A cochlear profile refers to a list of frequency bands to be modulated generated based upon the portion of the human cochlea associated with the indicated frequency ranges. In other words, the cochlear profile refers a list of frequency bands to be modulated that correspond to one or more frequencies within the human auditory range. Frequencies not specified will be excluded from modulation. The process flow of FIG. 2 also illustrates the application of the stimulation protocol and the cochlear profile to provide neural stimulation.

(23) The process flow **200** begins with an audio element or elements **202**. An audio element **202** may be embodied as a live recording, pre-composed music files, audio with no music at all, or a combination of elements from all three. To achieve better brain stimulation, a wide spectrum of sound may be used, as opposed to just a single tone or a several tones. Accordingly, audio elements **202** may be selected such that the combination of audio elements have a large spectral audio profile—in other words, audio elements **202** are selected such that the combination of the audio elements has many frequency components. For example, one or more of audio elements **202** may be selected from music composed from many instruments with timbre that produces overtones all across the spectral profile.

(24) Furthermore, the audio elements **202** may be selected to ensure both a large number of frequencies are being modulated, and also ensuring that unmodulated frequency regions are also included so that a listener is not disturbed by the modulations giving rise to the brain stimulations. For example, according to the techniques described herein, a band pass filter may be used to extract a frequency region, such as 400 Hz to 900 Hz, from an audio element, while a band stop filter may be used to generate a signal with all but the 400 Hz to 900 Hz frequency range. This extraction would result in one audio element file with only this frequency region and one audio element file without it. A “band pass filter” is a device or process that passes frequencies within a certain range and rejects frequencies outside that range, while a “band stop filter,” also called a notch filter, t-notch filter, band-elimination filter, and band-rejection filter, is a conventional audio process that passes most frequencies unaltered, but attenuates those in a range to very low levels.

(25) Illustrated in FIG. 3 is a simplified example of such a filter processing. Audio element **310** comprises two frequency components, a first frequency component at a frequency of “X,” and a second frequency component of “2X.” After passing through a band pass filter that filters frequency “X,” filtered audio element **315** is generated, comprising the “X” frequency component. After passing through a band notch filter configured to attenuate frequency “X,” filtered audio element **320** is generated, which comprises the “2X” frequency component. Audio element **315** may be modulated to provide brain stimulation or entrainment, while audio element **320** would remain unmodulated. The two audio elements could be combined to create a cohesive experience not unlike the original save for the additional modulations. Such an audio element may then be used to provide neural stimulation and entrainment in such a way that a listener is not disturbed by the modulations giving rise to the brain stimulations. Real world audio elements may comprise a wide range of frequencies, and the band pass filter may extract a range of frequency values, while the band stop filter would attenuate a range of frequency values. The simplified audio elements of FIG. 3 were chosen to illustrate the effect of a filtering process as used in the present example embodiment with an easily visualized audio element. In fact, to achieve the best possible brain stimulation, a wide spectrum of sound may be used, as opposed to just a single tone or a several tones. Furthermore, the stimulation may come from audio that has a large spectral audio profile—in other words, audio that has many frequency components, like music with its many instruments and timbre that produces overtones all across the spectral profile, as will be described in greater detail below.

(26) Returning to FIG. 2, audio element **202** is provided to spectral analyzer **210**. Spectral analyzer

210 analyzes the frequency components of audio elements **202**. “Spectral analysis” refers to sonographic representations and mathematical analysis of sound spectra, or by mathematically generated spectra. “Spectral range” or “spectral region” refers to specific bands of frequencies within the spectra. As will be described in greater detail below, spectral analyzer **210** may be used to determine how the frequency components of audio element **202** are to be utilized to implement the non-invasive neural stimulation techniques of the present disclosure.

(27) Specifically, spectral analyzer **210** analyzes the frequency components of each audio element **202**. If it is determined that one or more of audio elements **202** are composed of a large variety of frequency components across the spectrum, the one or more audio elements **202** are sent to the filter queue **211**. As its name implies, the filter queue **211** is a queue for audio filter **230**. Because the stimulation protocol **260** may be applied to a specific frequency or a relatively narrow range of frequencies, audio elements **202** that contain a large variety of frequency components undergo filtering in operation **230** to separate these large varieties of frequency components. For example, audio elements that contain audio from a plurality of instruments may contain audio data with frequency components that cross the audible frequency spectrum. Because the stimulation protocol **260** will only be applied to a subset of these frequencies, such audio elements are sent to audio filter **230**. In other words, the filtering of operation **230** selects a frequency range from an audio element for modulation.

(28) If it is determined that one or more of audio elements **202** has a single frequency component, or multiple frequency components but centered around a narrow band, the one or more audio elements **202** are sent to unfiltered queue **212**. In other words, if the audio element **260** covers a sufficiently narrow frequency range, the stimulation protocol **260** may be applied to the entire audio element, and therefore, no further filtering would be required. Accordingly, such audio elements are sent to audio separator **232**. Audio separator **232** looks at the spectral data of an audio input and pairs it with a cochlear profile to determine if the audio input should be modulated or not.

(29) Additionally, spectral data may be sent from spectral analyzer to one or more of audio filter **230** and audio separator **232**. This spectral data may be used, for example, in conjunction with cochlear profile **231**, to determine which portions of the audio elements **202** are to be modulated according to stimulation protocol **260**.

(30) Both audio filter **230** and audio separator **232** are configured to filter audio elements for modulation (in the case of filter **230**) or select audio elements for modulation (in the case of selector **232**) based upon one or more cochlear profiles **231**. Cochlear profile **231** provides instructions to one or more of filters **230** and/or selector **232** based upon the frequency sensitivity of the cochlear of the human ear. According to the present example embodiment, “cochlear profile” refers to a list of frequency bands to be modulated. Frequencies not specified will be excluded from modulation.

(31) With reference now made to FIG. **4**, depicted therein is a visual representation of the cochlea **400** of the human ear. The cochlea **400** is the spiral cavity of the inner ear containing the organ of Corti, which produces nerve impulses in response to sound vibrations. Different portions of cochlea **400** sense sounds at different frequencies due to the shape and rigidity of the cochlea **400** in the different regions. The base of the cochlea **400**, closest to the outer ear, is stiff and where higher frequency sounds are transduced. The apex, or top, of the cochlea is more flexible and transduces lower frequency sounds.

(32) The cochlea, in addition to sensing different frequencies in different regions, also has sensitivity that varies with the region of the cochlea. Each region has a number of cochlear filters that help the brain decide what to pay attention to. Sensitive cochlear regions draw attention more than insensitive regions. For example, sound in the frequency range of a human scream will draw our attention where the same sound, reduced in pitch to bass level, may be completely overlooked. The difference in reaction is largely due to the sensitivity of different areas in the cochlea. Knowing how the cochlea and larger auditory system draw our attention enables neural stimulation to be

incorporated into audio without disturbing the listener. Specifically, it has been determined that modulation targeting frequencies associated with the insensitive regions of the cochlea will stimulate the brain without disturbing the listener.

(33) For example, by providing stimulation through the modulation of frequencies between 0 Hz-1500 Hz, the modulation may be less noticeable to the listener but the modulation may have a substantial stimulation effect on the brain. Providing modulation at frequencies higher than the 0 Hz-1500 Hz range may be avoided because the sensitivity of the cochlear regions increases dramatically for high frequencies. Similarly, the stimulation could be provided through modulation at frequencies between 8 kHz and 20 kHz, as the sensitivity of the cochlea decrease at such higher frequencies.

(34) As a counter example, sensitive areas of the cochlea may be targeted specifically if the audio being modulated supports it without being obtrusive. For example, there are relatively insensitive regions of the cochlea between 5 kHz and 6.5 kHz, and these frequencies may be modulated in audio elements that lack significant audio components in this range. For example, audio elements created using instruments that do not make great use of that range may provide stimulation through modulation of this range.

(35) According to other examples, audio elements created with instruments that make heavy use of a region within a usually insensitive band, such as 900-1200 Hz, may be used for brain stimulation. These special cases may be taken into account using spectral profiling, but generally avoiding highly sensitive regions is a safe, effective way to highly stimulate the brain without disturbing the listener.

(36) As illustrated in FIG. 4, region **410**, a region sensitive to particularly high frequency sounds, and region **440**, a region sensitive to particularly low frequency sounds, are generally less sensitive than region **440**, a region sensitive to intermediate frequency sounds.

(37) It has been determined that neural stimulation targeting insensitive regions (i.e., stimulation protocols that modulate high and low frequency sounds) will stimulate the brain without disturbing the listener. For example, stimulation protocols associated with these relatively low sensitivity regions will achieve the entrainment described above with reference to FIG. 1. Yet, because the stimulation is implemented through frequencies to which the human ear is less sensitive, the stimulation may not affect the listener's enjoyment of, for example, music that contains audio elements substantially within the sensitive region **430**.

(38) Further, it has been determined that modulation of both low and high frequencies has a special effect on the brain. If both regions have identical modulation, the brain fuses the two regions into a single virtual source, increasing the fidelity of the stimulation waveform. Therefore, by avoiding sensitive cochlear regions while targeting both high and low regions, the fidelity of the stimulation waveform may be increased without disturbing the listener. For example, a piece of audio could be modulated using frequencies between 0-1500 Hz and frequencies between 8 kHz-20 kHz. The modulation of the two frequency regions may be substantially identical in waveform, phase and rate. Such modulation may create increased waveform fidelity for both ranges of stimulation.

(39) Fidelity of the waveform is analogous to the difference in resolution of digital images: a low resolution image has less pixels, and thus will not be able to capture as much detail as a high resolution image with more pixels. In the same way, high frequency carriers are able to increase the fidelity of a modulation waveform. Depicted in FIG. 5 is an audio analysis of amplitude modulation applied to a carrier of 100 Hz (**210**) where the waveform shape of the modulation is not clearly recreated when compared to a modulated carrier of 10,000 Hz (**210**), which looks smooth due to its higher fidelity.

(40) The fidelity of the stimulation waveform may have a significant impact on the effectiveness of the neural stimulation provided by the modulation. Just as in audio synthesis, neural oscillations will react differently depending on the waveform of the modulation.

(41) Returning to FIG. 4, the visual representation of the cochlea **400** is implemented through a

software interface that may be used to select cochlear regions to target for stimulation, in which cochlear regions represent frequency bands across the spectrum of human hearing. The software interface of FIG. 4 would be used to create a cochlear profile to be used in filters and audio separators. For example, a user input device 420 may be used to select portions of the cochlea 400 associated with the frequency ranges that the user determines should be stimulated via the stimulation protocol. According to the example of FIG. 4, the user input device 420 has been used to select cochlear region 415 associated with 7,000 Hz-8,500 Hz. Accordingly, the cochlear profile 231 of FIG. 2, may instruct both the audio filter 230 and the audio separator 332 to select 7,000 Hz-8,500 Hz as a frequency range to receive modulation per the stimulation protocol. 260. The software interface of FIG. 4 may also be used to add audio elements 406 to the project, and assign audio elements 405 to the cochlear profile 407.

(42) Returning to FIG. 2, each audio element in filter queue 211 may be filtered via audio filter 230, and based upon the frequency range filtered by audio filter 230, the frequency data may be sent to modulator 250 for modulation according to stimulation protocol 260, or sent to mixer 251 for recombination with the modulated components for inclusion in a final audio element.

(43) For example, audio filter 230 may receive instructions from the cochlear profile 231 for each audio element being filtered. These instructions may indicate which frequency range within the audio element are to be modulated, for example the frequencies corresponding to the less sensitive portions of the human cochlea. In carrying out this operation, audio filter 230 may use one or more band passes to extract the chosen frequency components for modulation 240. Accordingly to other example embodiments, band stop filters, equalizers, or other audio processing elements known to the skilled artisan may be used in conjunction with or as an alternative to the band pass filter to separate the contents of filter queue 211 into frequency components for modulation 240 and frequency components that will not receive modulation 242.

(44) The frequency components for modulation 240 are passed to modulator 250 in accordance with the frequencies indicated in cochlear profiles 231. The remainder of the frequency components 242 are passed directly to the mixer 251 where modulated and unmodulated frequency components are recombined to form a single audio element 252. This process is done for each audio element in the filter queue 211.

(45) Similarly, audio separator 232 may receive instructions from the cochlear profile 231 selected for each audio element. Based upon the instructions provided by cochlear profile 231, audio separator 232 may separate the audio elements contained in unfiltered queue 212 into audio elements to be modulated 243 and audio elements not to be modulated 244. By placing an audio element into audio elements to modulate 243, audio separator 232 selects a frequency range comprising the entirety of the audio element for modulation. Accordingly, the audio elements to be modulated 243 are sent to modulator 250, while the audio elements not to be modulated are sent to audio arranger 253, where these audio elements will be arranged with audio elements that contain modulation to form a final combined audio element.

(46) As illustrated in FIG. 2, modulator 250 applies stimulation protocol 260 to the frequency components for modulation 240 and the audio elements to be modulated 243. The stimulation protocol 260 specifies the duration of the auditory stimulation, as well as the desired stimulation across that timeframe. To control the stimulation, it continually instructs modulator 250 as to the rate, depth, waveform and phase of the modulations.

(47) Turning to FIG. 6, illustrated therein is an example of a stimulation protocol according to the techniques described herein. In particular, FIG. 6 illustrates a software interface 600 that may be utilized to create a stimulation protocol to provide neural stimulation. Specifically, the stimulation protocol illustrated in FIG. 6 includes controls for the rate of the stimulation 620, and the depth of the stimulation 640. According to the example of FIG. 6, these features of the stimulation protocol are defined as a function of time.

(48) The rate of the stimulation 620 may be established such that the modulation provided by the

stimulation protocol synchronizes amplitude modulation of the audio elements being modulated to rhythms in the underlying audio elements. The stimulation protocol may adjust the modulation phase to align with rhythmic acoustic events in the audio. By aligning the modulation with the acoustic events in the audio elements being modulated, the stimulation protocol may be generated to ensure that the stimulation provided by the modulator is not interfered with by the underlying audio elements being modulated, and vice versa, keeps the stimulating modulation from interfering with the underlying music. Rhythmic acoustic events such as drum beats in music, or waves in a beach recording, are perceived in the brain as a form of amplitude modulation. If the modulation provided by the stimulation protocol is not aligned with these rhythmic acoustic events of the audio elements being modulated, the rhythmic acoustic events could interfere with the stimulation modulation. This misalignment would create interference between the rhythmic elements of the audio elements and the amplitude modulations meant to stimulate the brain. Accordingly, it may be beneficial to synchronize the stimulation protocol modulation with the rhythmic elements of the audio element being modulated.

(49) Furthermore, synchronizing the stimulation protocol modulation with the rhythmic elements of the audio element being modulated prevents distortion of the audio by allowing the modulation cycle crest to align with the crest of notes or beats in music. For example, music at 120 beats per minute equates to 2 beats a second, equivalent to 2 Hz modulation. Quarter notes would align with 2 Hz modulation if the phase is correct. 8th notes would align at 4 Hz, 32nd notes would align with 16 Hz. If a stimulation protocol is being applied to music in an MP3 which plays at 120 beats per minute (BPM), the stimulation protocol would want to modulate the audio elements of the music file at 2 Hz. Specifically, “hertz” refers to a number of cycles per second, so 2 Hz corresponds to 120 BPM, as a 120 BPM piece of music will have two beats every second. Similarly, the rate of modulation may be set as a multiple of BPM for the audio element.

(50) Illustrated in FIGS. 7A-C are visual representations of modulations that are not aligned with the beats of an audio element (FIG. 7A), modulations whose rate, but not phase, is aligned with the beats of an audio element (FIG. 7B), and modulations whose rate and phase are aligned with the beats of an audio element (FIG. 7C).

(51) The frequency of modulation signal **710** of FIG. 7A is not a multiple of the frequency of beats **715a-d**, and therefore, the maxima of signal **710** cannot be aligned with beats **715a-d**. In other words, signal **710** has a different rate than the rhythmic components illustrated through beats **715a-d**. Similarly, because modulation signal **710** begins at time **T0** and the rhythmic components of the audio element do not start until time **T1**, modulation signal **710** would be out of phase with beats **715a-d** even if its rates were the same. The frequency of modulation signal **720** of FIG. 7B is a multiple of the frequency of beats **725a-d**, but because the modulation signal **720** begins at time **T0** and the rhythmic components of the audio element do not start until time **T1**, modulation signal **720** is out of phase with beats **725a-d**. The frequency of modulation signal **730** of FIG. 7B is aligned with the frequency of beats **735a-d**, and this alignment is accomplished by phase shifting the modulation signal **720** such that modulation signal **730** begins at **T1**, instead of at time **T0**.

(52) In order to ensure that the stimulation protocol aligns with the rhythmic elements of the audio elements being modulated, the phases of the stimulation modulation and the rhythmic elements of the audio element may be aligned. Returning to the example of the 120 BPM MP3 file, applying 2 Hz modulation to the MP3 file may not align with the rhythmic elements of the MP3 file if the phase of the stimulation modulation is not aligned with MP3 file. For example, if the maxima of the stimulation modulation is not aligned with the drum beats in the MP3 file, the drum beats would interfere with the stimulation modulation, and the stimulation protocol may cause audio distortion even through the stimulation modulation is being applied with a frequency that matches the rate of a 2 BPM audio element.

(53) Such distortion may be introduced because, for example, MP3 encoding often adds silence to the beginning of the encoded audio file. Accordingly, the encoded music would start later than

beginning of the audio file. If the encoded music begins 250 milliseconds after the beginning of the encoded MP3 file, stimulation modulation that is applied at 2 Hz starting at the very beginning of the MP3 file will be 180° out of phase with the rhythmic components of the MP3 file. In order to synchronize the modulations to the beats in the file, the phase of the modulation would have to be shifted by 180°. If the phase of the modulation is adjusted by 180°, the modulation cycle will synchronize with the first beat of the encoded music.

(54) In order to ensure that the stimulation modulation aligns with the rhythmic elements of the audio elements being modulated, the audio elements are provided to a beat detector, an example of which is illustrated as beat detector **220** of FIG. 2. “Beat Detection” refers to a process of analyzing audio to determine the presence of rhythms and their parameters, such that one can align the rhythms of one piece of audio with the rhythms of another. Accordingly, beat detector **220** detects rhythms in music or rhythmic auditory events in non-music audio. Beat detector **220** detects the phase and rate of the rhythms. Rhythmic information may already be known about audio element **202** through, for example, metadata included in audio element **202**. This rhythmic information may indicate the phase where the rhythm of the audio element begins (e.g., at a particular phase) or that the rhythmic element has a defined rhythm rate (e.g., defined in BPM of the audio element). Beat detector **220** may be configured to read or interpret this data included in audio element **202**.

(55) According to other example embodiments, rhythm detector **220** may be configured to analyze the content of audio elements to determine information such as the phase and BPM of audio element **202**. For example, according to one specific example embodiment, five musical pieces would be selected, and each musical piece would be a WAV file, six minutes long. Beat detector **220** may determine that each of the musical pieces has a BPM of 120. Beat detector **220** may further determine that each musical piece starts immediately, and therefore, each musical piece has a starting phase of 0. According to other examples, beat detector **220** may determine that each musical piece has a silent portion prior to the start of the musical piece, such as the 250 millisecond delay provided by some MP3 encoding. Beat detector **220** may detect this delay, and convert the time delay into a phase shift of the rhythmic elements of the music based upon the BPM of the musical piece. As illustrated in FIG. 2, the data determined by beat detector **220** is provided to stimulation protocol **260**. This data may be used to ensure that the modulation provided by the stimulation protocol aligns with the rhythmic elements of the audio elements being modulated.

(56) Returning to FIG. 6, the modulation rate **620** may be set to 16 Hz (corresponding to 32nd notes of a 120 BPM audio element) for the first 8 minutes of the audio element, 8 Hz (corresponding to 16th notes of a 120 BPM audio element) for the next 8 minutes, 4 Hz (corresponding to 8th notes of a 120 BPM audio element) for the next 8 minutes and once again to 16 Hz for the final 6 minutes of the audio element. As illustrated in element **630**, the rate of the stimulation protocol may be dynamically adjusted to mate the rhythmic elements of the audio elements being modulated by the stimulation protocol based upon the data provided by, for example, beat detector **220** of FIG. 2. Similarly, the phase of the modulation may be dynamically mated to the rhythms in the audio via checkbox **630**. The rate **620** may also be specified across the duration of the stimulation by moving points **610a-d** via user input.

(57) As also illustrated in FIG. 6, the depth of the stimulation **640** may also be controlled. Modulation depth refers to the intensity of the modulation applied to the audio element. In other words, depth is the how large or small the modulation cycle is in comparison to what it is modulating. In amplitude modulation, depth would be expressed as a linear percent of the whole volume available.

(58) The concept of modulation depth is illustrated in FIGS. 8A-C. Illustrated in FIG. 8A is an amplitude modulated signal **800**. Value **810** is the unmodulated peak to peak carrier amplitude, while value **820** is the peak-to-peak audio amplitude after modulation. The percentage of modulation depth is the ratio of the peak-to-peak audio amplitude after modulation **820** to the peak to peak audio amplitude of the unmodulated signal. FIG. 8B illustrates a signal **830** with 50%

modulation depth. According to this specific example embodiment, a modulation depth of 50% means that the modulation is causing 50% of the volume of the audio element to rise and fall periodically throughout the audio element. FIG. 8C illustrates a signal **840** with 100% modulation depth. According to this specific example embodiment, a modulation depth of 100% means that the modulation is causing 100% of the volume of the audio element to rise and fall periodically throughout the audio element.

(59) Returning to FIG. 6, it has been demonstrated that high depth modulation produces greater neural stimulation. High intensity neural stimulation of this type has the advantage of producing better behavioral results in a short period, such as 15 minutes, but can have disadvantages past that time. In the same way that too much coffee can make one jittery, high intensity neural stimulation for too long can actually decrease performance. Therefore, it may be beneficial to moderate the depth of modulation across the stimulation timeline. For example, in a 30 minute stimulation session, one might modulate at a high depth of 70% for a first portion of the audio element. However, at the 15 minute mark, the modulation depth may be gradually reduced such that the modulation depth is down to 50% by the end of the audio element. This would effectively have the advantage of both high intensity stimulation and a “cool down” period where the user would be less stimulated and so maintain peak performance. Such a stimulation session is illustrated in depth of stimulation **640**. As illustrated, the depth of modulation period **645** increases from 25% to 75% to allow the listener some time to adjust to the modulation. After this “ramp up” period, there is an extended period with 75% modulation depth to ensure a high level of neural stimulation. This period of high depth modulation may comprise a majority of the audio piece to which modulation has been applied. Period **645** may increase the depth of the modulation over a period with a minimum length 15 seconds. Additionally, modulation depth gradually decreases from 75% to 50% over the last 15 minutes of the audio element to prevent overstimulation. Accordingly to other example embodiment, this decrease in depth takes place of over a minimum length of time of one minute. Accordingly to still other example embodiments, the modulation depth may continually change from high to low and back again, with a minimum of 15 seconds between high and low phases.

(60) The depth **640** may also specified across the duration of the stimulation by moving points **612a-d** via user input. Finally, a save button **690** is provided to save the protocol to an electronic medium.

(61) Returning again to FIG. 2, as illustrated therein, stimulation protocol **260** is based upon data provided by beat detector **220**, and also waveform protocol **259**. Waveform protocol **259** may be used to effect neural oscillatory overtones and/or to target specific brain regions by specifying the waveform of the modulation pattern applied to the audio elements being modulated. Neural oscillations may react differently depending on the waveform of the modulation. Sine waveform modulation may be used if stimulation is intended to target a single frequency of neural oscillations. As a sine waveform has no overtones included in the waveform, sine wave modulation waveforms may produce few overtones in the brain. More complex waveforms may be used to produce neural oscillatory overtones. “Overtones” or “harmonics” refer to resonant frequencies above the fundamental frequency that are produced when the waveform of an oscillator is anything other than a sine wave. An example of a waveform that contains overtones is illustrated in FIG. 3. Waveform **310** includes a fundamental frequency “X” and an overtone or harmonic “2X.” Each of waveforms **315** and **320** contains just a sine waveform, and therefore, just contains its respective fundamental frequency.

(62) In music, overtones contribute to timbre—the way a piano and a guitar, playing the same fundamental frequency, will sound completely different from one another. Brain imaging data has also shown that complex waveforms delivered with waveforms that contain overtones result in broader stimulation of neural oscillatory overtones far past the range of stimulation. Accordingly, “neural oscillatory overtones” refer to resonant frequencies above the fundamental frequency of

stimulation. Like audio, or any data with a time-series, neural oscillations show harmonic and overtone frequencies when analyzing the spectrum and the fundamental frequency of stimulation. (63) With reference now made to FIG. 9, depicted therein are overtones of neural stimulation modulated signal. Specifically, the phase synchronization between an acoustic signal and the output of an Electroencephalogram (EEG) is illustrated. Phase-Locking Value (PLV) is a statistic that looks at the relationship between two signals, while an EEG measures brain activity. Accordingly, the PLV may be used to investigate task-induced changes in long range synchronization of neural activity. Specifically, the PLV statistic may be used as a proxy for connectivity. If the two signals rise and fall together more than a baseline value, then there is more synchronization or loosely speaking, enhanced connectivity between these two signals. Accordingly, spikes in the PLV **910** between EEG values and acoustic signals may be considered an indication of entrainment of the neural signals by the acoustic signal at the frequency where the spike arises. The analysis of FIG. 9 graphs the PLV of an acoustic signal with an EEG signal. The solid line **910** graphs the PLV for a modulated acoustic signal versus the EEG of the listener, while the dashed line **920** graphs the PLV for an unmodulated acoustic signal versus the EEG of the listener. There are peaks **925** at the modulation rates used in the stimulation session **930**: 8 Hz, 12 Hz, 14 Hz and 16 Hz. Overtones, such as overtones **940a-c**, start to show up immediately after region **930** and may continue throughout to much higher frequency ranges.

(64) Brain imaging data has shown that neural stimulation based upon complex waveforms results in broader stimulation of neural oscillatory overtones far past the range of stimulation due to the presence of overtones, such as the spikes **940a-c** of FIG. 9. Accordingly, waveform protocol **259** of FIG. 2 may be configured to provide waveforms to stimulation protocol **260** that are configured to provide stimulation past the range of stimulation via overtones.

(65) Waveform protocol **259** of FIG. 2 may also be configured to provide waveforms that target specific areas of the brain. Since the waveform is enhanced using the present invention, there is a unique opportunity to target actual regions of the brain. Neural oscillatory waveforms differ dramatically depending on the region of the brain being measured. Different regions of the brain exhibit different waveform shapes in their neural oscillations. Even if two brain regions are firing at the exact same rate, the purpose of the oscillation may be very different, and the different purpose may be expressed through different waveforms. Matching the waveform of the stimulation to the brain region being targeted may enhance the effectiveness of neural stimulation and may enhance the targeting of specific brain regions.

(66) With reference now made to FIGS. **10A** and **10B**, depicted therein are example embodiments of waveforms generated by waveform protocol **259** of FIG. 2 configured to target and enhance neural stimulation for specific areas of the brain. Illustrated in FIG. **10A** are the EEG output measured from different regions on the brain. Alpha neural oscillations (which range from 8-12 Hz) are prevalent all through the brain, but serve different purposes in different areas. Even if two brain regions are firing at the exact same rate, the purpose of the oscillation could be very different. This difference in purpose of effect is often expressed through specific waveforms. 10 Hz oscillations measured from the frontal cortex **1010** look very different from the same oscillations rate taken from the motor cortex **1020**. The motor cortex oscillations **1020** have an “M”-like shape to them among other features quite different from the frontal cortex oscillations **1010** which are relatively smoother. By using modulation waveforms that generally mimic the shape of specific areas of the brain, neural stimulation of such specific areas of the brain may be enhanced. FIG. **10B** illustrates examples of such modulation waveforms configured to target the frontal cortex **1030** and the motor cortex **1040**.

(67) Specifically, waveform **1030** is configured to enhance neural stimulation of the frontal cortex, and therefore, is shaped to mimic the shape of frontal cortex oscillations **1010**. Accordingly, waveform **1030** is provided with a relatively smooth shape, in this case, a shape similar to that of a sine wave. Waveform **1040** is configured to enhance neural stimulation of the motor cortex, and

therefore, is shaped to mimic the “M”-like shape of motor cortex oscillations **1020**.

(68) If a user decides to generate a stimulation protocol to help ease anxiety by stimulating 10 Hz in the frontal regions of the brain, a stimulation protocol may be generated to use the frontal waveform **1030** at a rate of 10 Hz. The modulation could be applied to one or more audio files, and played for the user. This process would be much more effective than using a single modulation waveform for all purposes.

(69) Waveform protocol **259** of FIG. **2** may be implemented through a software interface like that illustrated in FIG. **11**. FIG. **11** depicts an example software interface **1100** that may be used to generate or create a waveform protocol, which controls the waveform or waveforms used in the stimulation protocol **260** of FIG. **2**. In the example of FIG. **11**, a waveform is associated with a modulation rate. This means that when a certain modulation rate is being used it will automatically be used in conjunction with the associated modulation waveform. A user may enter the desired modulation rate to be associated with the waveform protocol in the Modulation Rate textbox field **1110**. Next, a depiction of the head and a typical EEG sensor array **1120** is presented to the user. Array **1120** allows the user to select a sensor **1125** and retrieve a list of typical neural oscillatory waveforms for that modulation rate (entered in text box **1110**) and brain region **1130**. If the user selects the frontal cortex, included in list **1130** would be the relative smooth waveform **1030** of FIG. **10**. Similarly, if the user selects the motor cortex, included in list **1130** would be the “M”-like shaped waveform **1040** of FIG. **10**. The user may then select the desired waveform **1140**, and save the protocol via selection button **1190**. This waveform protocol may then be provided to stimulation protocol **260** of FIG. **2**.

(70) Returning to FIG. **2**, once stimulation protocol **260** has been generated, a protocol that may take into account the output of one or more of beat detector **202** and waveform protocol **259**, the protocol is provided to modulator **250**.

(71) The stimulation protocol **260** specifies the duration of the auditory stimulation, as well as the desired stimulation across that timeframe. To control the stimulation, it continually instructs the modulator **250** as to the rate, depth, waveform and phase of the modulations. As described above, the stimulation protocol **260** may instruct modulator **250** based upon the output of beat detector **220** to ensure the rates are multiples or factors of the BPM measured by rhythmic content in the audio elements **202**. As also described above, a modulation waveform may be specified in the waveform protocol **259**, and is used to effect neural oscillatory overtones and/or to target specific brain regions, which is provided to modulator **250** via stimulation protocol **260**. Finally, modulation phase control of modulator **250** may be provided by stimulation protocol **260** based upon beat detector **220** to ensure the phase of modulation matches the phase of rhythmic content in the audio elements **202**. Modulation depth control is used to manipulate the intensity of the stimulation.

(72) The modulator **250** may use a low-frequency oscillator according to the stimulation protocol **260**, which contains ongoing rate, phase, depth, and waveform instruction. Low frequency oscillation (LFO) is a technique where an additional oscillator, that operates at a lower frequency than the signal being modulated, modulates the audio signal, thus causing a difference to be heard in the signal without the actual introduction of another sound source. LFO is commonly used by electronic musicians to add vibrato or various effects to a melody. In this case it is used to modulate the amplitude, frequency, stereo panning or filters according to the stimulation protocol **260**.

(73) The modulator **250** is used to modulate frequency components **240** and unfiltered audio elements **243**. Frequency components **240** are modulated and then mixed with their counterpart unmodulated components **242** in mixer **251** to produce final filtered, modulated audio elements **252**, which are then sent to the audio arranger **253**. Audio elements **243**, on the other hand, are modulated in full, so they need not be remixed, and are therefore sent directly to the audio arranger **253**.

(74) An “audio arranger” is a device or process that allows a user to define a number of audio components to fill an audio composition with music wherever the score has no implicit notes.

Accordingly, audio arranger **253** arranges all audio content across the timeline of the stimulation protocol **260**. As illustrated in FIG. 2, stimulation protocol **260** sends its timeframe to the audio arranger **253**. In essence, audio arranger **253** creates the final audio arrangement. Most importantly, audio arranger **253** ensures that modulated content is always present, and is always coupled with unmodulated content. Filtered, modulated audio elements **252** automatically contain modulated and unmodulated content, but audio arranger **253** must still arrange them for maximum coverage across the timeline. Modulated audio elements **254** and unmodulated audio elements **244** must be arranged such that a modulated element is always paired with an unmodulated element, and that there are always at least two elements present throughout the timeline.

(75) Illustrated in FIG. 12 is a logical flow chart of the computer functions to be performed by audio arranger **253**. As noted above, the job of the audio arranger **253** is to ensure that modulated audio is always paired with unmodulated audio, as well as ensuring an even distribution of available audio content. Audio elements, both modulated **254** and unmodulated **244**, will be sent to the audio arranger **253**, along with filtered and modulated elements **252**. Audio arranger **253** then distributes the audio elements evenly across the span of the arrangement **1230**. Audio arranger **253** also ensures that modulated elements **254** are always paired with unmodulated audio **254**. For filtered, modulated audio elements **252**, audio arranger **253** doesn't need to worry about pairing modulated and unmodulated content, since the filter already separated frequency components such that each element already contains modulated and unmodulated components, so audio arranger **253** need only distribute the elements evenly **252**. For example, audio arranger **253** may distribute the elements such that at least 50% of the stimulation timeline of the arranged audio file contains modulated frequency components.

(76) Returning to FIG. 12, once arrangement is complete, the arranged audio element is sent to the final mixdown **270** which provides a final mixdown and encodes the full audio onto an electronic medium. "Final mixdown" refers to the final output of a multi-track audio arrangement. A multitrack recording is anything with more than one individual track, or more than one piece of audio layered on top of another, to be played simultaneously. The final output of multitrack audio is also known as the mixdown.

(77) With reference now made to FIG. 13, depicted therein is a flowchart **1300** illustrating an exemplary process flow according to the techniques described herein. The process begins in operation **1305** where first data comprising a first range of audio frequencies is received. The first range of frequencies corresponds to a predetermined cochlear region of the listener. In operation **1310**, second data, comprising a second range of frequencies, is received. Examples of operations **1305** and **1310** may include any combinations of operations corresponding to one or more of operations of **240**, **242**, **243** and **244** of FIG. 2. For example, the first data of operation **1305** may comprise frequency components to modulate **240** of FIG. 2 that have been filtered out of an audio element by filter **230**. According to other example embodiments, the first data of operation **1305** may comprise audio elements to modulate **243** that have been separated audio separator **232** of FIG. 2. According to still other example embodiments, the first data in operation **1305** may comprises a combination of frequency components to modulate **240** and audio elements to modulate **243** of FIG. 2. Example embodiments of the second data of operation **1310** may comprises frequency components not to modulate **242** of FIG. 2, audio elements not to modulate **244** also of FIG. 2, or a combination thereof.

(78) In operation **1310**, third data is acquired that corresponds to a first modulated range of audio frequencies. The third data is acquired by modulating the first range of audio frequencies according to a stimulation protocol configured to provide neural stimulation of a brain of a listener. For example, operation **1310** may include the modulation by modulator **250** of frequency components to modulate **240** and/or audio elements to modulate **243** according to stimulation protocol **260**, as illustrated in FIG. 2.

(79) In operation **1320**, the second data and third data are arranged to generate an audio

composition from the second data and the third data. For example, operation **1320** may include the operations carried out by mixer **251** and/or audio arranger **253** of FIG. **2**.

(80) FIG. **14** illustrates a hardware block diagram of a computing device **1400** that may perform the functions of any of the computing or control entities referred to herein in connection with noninvasive neural stimulation through audio. It should be appreciated that FIG. **14** provides only an illustration of one embodiment and does not imply any limitations with regard to the environments in which different embodiments may be implemented. Many modifications to the depicted environment may be made.

(81) As depicted, the device **1400** includes a bus **1412**, which provides communications between computer processor(s) **1414**, memory **1416**, persistent storage **1418**, communications unit **1420**, and input/output (I/O) interface(s) **1422**. Bus **1412** can be implemented with any architecture designed for passing data and/or control information between processors (such as microprocessors, communications and network processors, etc.), system memory, peripheral devices, and any other hardware components within a system. For example, bus **1412** can be implemented with one or more buses.

(82) Memory **1416** and persistent storage **1418** are computer readable storage media. In the depicted embodiment, memory **1416** includes random access memory (RAM) **1424** and cache memory **1426**. In general, memory **1416** can include any suitable volatile or non-volatile computer readable storage media. Instructions for the “Neural Stimulation Control Logic” may be stored in memory **1416** or memory **1418** for execution by processor(s) **1414**. The Neural Stimulation Control Logic stored in memory **1416** or memory **1418** may implement the noninvasive neural stimulation through audio techniques of the present application.

(83) One or more programs may be stored in persistent storage **1418** for execution by one or more of the respective computer processors **1414** via one or more memories of memory **1416**. The persistent storage **1418** may be a magnetic hard disk drive, a solid state hard drive, a semiconductor storage device, read-only memory (ROM), erasable programmable read-only memory (EPROM), flash memory, or any other computer readable storage media that is capable of storing program instructions or digital information.

(84) The media used by persistent storage **1418** may also be removable. For example, a removable hard drive may be used for persistent storage **1418**. Other examples include optical and magnetic disks, thumb drives, and smart cards that are inserted into a drive for transfer onto another computer readable storage medium that is also part of persistent storage **1418**.

(85) Communications unit **1420**, in these examples, provides for communications with other data processing systems or devices. In these examples, communications unit **1420** includes one or more network interface cards. Communications unit **1420** may provide communications through the use of either or both physical and wireless communications links.

(86) The above description is intended by way of example only. Although the techniques are illustrated and described herein as embodied in one or more specific examples, it is nevertheless not intended to be limited to the details shown, since various modifications and structural changes may be made within the scope and range of equivalents of the claims.

Claims

1. A method performed by a computing system, the method comprising: obtaining an input audio signal comprising one or more input audio elements, wherein the one or more input audio elements comprise one or more rhythmic components; generating one or more modulated audio elements by modulating at least a portion of at least one of the one or more input audio elements of the input audio signal with a modulation signal, wherein the modulation signal comprises both (i) a fundamental modulation rate less than 40 Hz and (ii) a modulation waveform arranged to cause one or more neural oscillations at rates different than the fundamental modulation rate of the

modulation signal in a brain of a listener above the fundamental modulation rate of the modulation signal; creating an audio output signal by mixing the one or more modulated audio elements of the input audio signal with one or more unmodulated portions of the one or more input audio elements of the input audio signal; and wherein generating the one or more modulated audio elements of the input audio signal comprises causing both of a modulation phase and the modulation rate of the modulation signal to align with the one or more rhythmic components of the one or more input audio elements of the input audio signal.

2. The method of claim 1, further comprising: causing playback of the audio output signal to the listener.

3. The method of claim 1, further comprising: analyzing at least one of the one or more input audio elements of the input audio signal; detecting at least one of a phase or a tempo based on the analyzing; and wherein adjusting one or both of a modulation phase or a modulation rate of the modulation signal so that both the modulation phase and the modulation rate of the modulation signal align with the one or more rhythmic components of the one or more input audio elements of the input audio signal comprises adjusting one or both of a modulation phase or a modulation rate based on at least one of the phase or the tempo.

4. The method of claim 1, wherein the modulation signal further comprises a modulation depth corresponding to an intensity of modulation applied to the one or more input audio elements of the input audio signal.

5. The method of claim 1, wherein the modulation waveform comprises a complex waveform.

6. The method of claim 1, wherein modulating the at least a portion of at least one of the one or more input audio elements of the input audio signal with a modulation signal comprises applying the modulation signal to audio information within the one or more input audio elements of the input audio signal that is at least one of (i) between about 0 Hz and 1500 Hz or (ii) between about 8 kHz and 20 kHz.

7. The method of claim 1, wherein the fundamental modulation rate of the modulation signal is between about 2 Hz to about 16 Hz.

8. The method of claim 1, wherein the one or more neural oscillations above the fundamental modulation rate of the modulation signal are between about 4 Hz to about 40 Hz.

9. The method of claim 1, further comprising: causing a graphical user interface to display one or more options, wherein each option is associated with a particular modulation signal; and after receiving an indication of a selected option via the graphical user interface, the step of modulating the at least a portion of at least one of the one or more input audio elements of the input audio signal with a modulation signal comprises modulating the at least a portion of at least one of the one or more input audio elements of the input audio signal with the particular modulation signal corresponding to the selected option.

10. Tangible, non-transitory computer-readable media comprising program instructions, wherein the program instructions, when executed by one or more processors, cause a computing system to perform functions comprising: obtaining an input audio signal comprising one or more input audio elements, wherein the one or more input audio elements comprise one or more rhythmic components; generating one or more modulated audio elements by modulating at least a portion of at least one of the one or more input audio elements of the input audio signal with a modulation signal, wherein the modulation signal comprises both (i) a fundamental modulation rate less than 40Hz and (ii) a modulation waveform arranged to cause one or more neural oscillations at rates different than the fundamental modulation rate of the modulation signal in a brain of a listener above the fundamental modulation rate of the modulation signal; creating an audio output signal by mixing the one or more modulated audio elements of the input audio signal with one or more unmodulated portions of the one or more input audio elements of the input audio signal; and wherein generating the one or more modulated audio elements of the input audio signal comprises causing both of a modulation phase and the modulation rate of the modulation signal to align with

the one or more rhythmic components of the one or more input audio elements of the input audio signal.

11. The tangible, non-transitory computer-readable media of claim 10, wherein the functions further comprise: causing playback of the audio output signal to the listener.

12. The tangible, non-transitory computer-readable media of claim 10, wherein the functions further comprise: analyzing at least one of the one or more input audio elements of the input audio signal; detecting at least one of a phase or a tempo based on the analyzing; and wherein adjusting one or both of a modulation phase or a modulation rate of the modulation signal so that both the modulation phase and the modulation rate of the modulation signal align with the one or more rhythmic components of the one or more input audio elements of the input audio signal comprises adjusting one or both of a modulation phase or a modulation rate based on at least one of the phase or the tempo.

13. The tangible, non-transitory computer-readable media of claim 10, wherein the modulation signal further comprises a modulation depth corresponding to an intensity of modulation applied to the one or more input audio elements of the input audio signal.

14. The tangible, non-transitory computer-readable media of claim 10, wherein the modulation waveform comprises a complex waveform.

15. The tangible, non-transitory computer-readable media of claim 10, wherein modulating the at least a portion of at least one of the one or more input audio elements of the input audio signal with a modulation signal comprises applying the modulation signal to audio information within the one or more input audio elements of the input audio signal that is at least one of (i) between about 0 Hz and 1500 Hz or (ii) between about 8 kHz and 20 kHz.

16. The tangible, non-transitory computer-readable media of claim 10, wherein the fundamental modulation rate of the modulation signal is between about 2 Hz to about 16 Hz.

17. The tangible, non-transitory computer-readable media of claim 10, wherein the one or more neural oscillations above the fundamental modulation rate of the modulation signal are between about 4 Hz to about 40 Hz.

18. The tangible, non-transitory computer-readable media of claim 10, wherein the functions further comprise: causing a graphical user interface to display one or more options, wherein each option is associated with a particular modulation signal; and after receiving an indication of a selected option via the graphical user interface, the step of modulating the at least a portion of at least one of the one or more input audio elements of the input audio signal with a modulation signal comprises modulating the at least a portion of at least one of the one or more input audio elements of the input audio signal with the particular modulation signal corresponding to the selected option.
