

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent
Kind Code
Date of Patent
Inventor(s)

12408512
B2
September 02, 2025
Shinokawa; Yasuharu et al.

Organic EL display panel and method for manufacturing organic EL display panel

Abstract

An organic electro luminescence display panel includes pixel electrodes, a plurality of elongated column banks, a missing portion at which part of the elongated column banks does not exist, a pair of repair banks formed, above the pixel electrodes, in each of two gaps between a column bank that has the missing portion and column banks adjacent on opposite sides in a row direction of the column bank, a light emitting layer and a common electrode provided above the light emitting layer. The repair banks include a pair of repair row banks formed at positions spaced by a predetermined distance or more in a column direction above the pixel electrodes that exist in the two gaps and whose positions in the column direction are same, at least at part thereof, as that of the missing portion.

Inventors:	Shinokawa; Yasuharu (Tokyo, JP), Umezu; Kazuhiro (Tokyo, JP), Ishikawa; Daisuke (Tokyo, JP), Kawakatsu; Yasuhiro (Tokyo, JP)
Applicant:	JOLED INC. (Tokyo, JP)
Family ID:	71947764
Assignee:	JOLED INC. (Tokyo, JP)
Appl. No.:	17/310514
Filed (or PCT Filed):	February 06, 2020
PCT No.:	PCT/JP2020/004675
PCT Pub. No.:	WO2020/162571
PCT Pub. Date:	August 13, 2020

Prior Publication Data

Document Identifier	Publication Date
----------------------------	-------------------------

Foreign Application Priority Data

JP 2019-021506 Feb. 08, 2019

Publication Classification

Int. Cl.: H10K59/122 (20230101); H10K59/12 (20230101); H10K71/00 (20230101);
H10K71/40 (20230101)

U.S. Cl.:

CPC H10K59/122 (20230201); H10K71/00 (20230201); H10K59/1201 (20230201);
H10K71/441 (20230201); H10K71/861 (20230201)

Field of Classification Search

CPC: H10K (71/861); H10K (59/10); H10K (59/12); H10K (59/122); H10K (59/173); H10K
(59/171); H10K (59/121); H10K (59/80); H10K (59/87); H10K (59/1201); H10K (71/70);
H10H (29/37); H10H (29/80); H01L (22/10); H01L (22/12); H01L (22/20); H01L (22/22)

References Cited**U.S. PATENT DOCUMENTS**

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2017/0012246	12/2016	Onimaru et al.	N/A	N/A
2017/0040393	12/2016	Onimaru	N/A	H10K 50/11
2017/0077460	12/2016	Hayashida et al.	N/A	N/A
2017/0170244	12/2016	Kobayashi et al.	N/A	N/A
2017/0301889	12/2016	Hayashida et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2007264186	12/2006	JP	N/A
2009104030	12/2008	JP	N/A
2010267576	12/2009	JP	N/A
2016071992	12/2015	JP	N/A
2017033813	12/2016	JP	N/A
2018101558	12/2017	JP	N/A
2015118882	12/2014	WO	N/A
2015118883	12/2014	WO	N/A
2015133090	12/2014	WO	N/A
2016047021	12/2015	WO	N/A

OTHER PUBLICATIONS

International Search Report in PCT/JP2020/004675 dated Apr. 7, 2020. cited by applicant

Background/Summary

CROSS REFERENCE TO RELATED APPLICATIONS

(1) This application is a U.S. National Phase of International Patent Application No. PCT/JP2020/004675 filed on Feb. 6, 2020, which claims priority benefit of Japanese Patent Application No. JP 2019-021506 filed in the Japan Patent Office on Feb. 8, 2019. Each of the above-referenced applications is hereby incorporated herein by reference in its entirety.

TECHNICAL FIELD

(2) The present disclosure relates a method for manufacturing an organic electro luminescence (EL) display panel in which organic EL elements utilizing an electroluminescence phenomenon of an organic material are arranged in an array, and particularly to a step of forming a bank.

BACKGROUND ART

(3) In recent years, an organic EL display panel has been placed into practical use as a display apparatus of the light emitting type. In an organic EL display panel, each organic EL element is a light emitting element of the current driven type that has a basic structure in which a light emitting layer containing an organic light emitting material is arranged between paired electrodes, that is, an anode and a cathode. When the light emitting element is to be driven, a voltage is applied between the paired electrodes such that light is emitted by recombination of holes injected from the anode into the light emitting layer and electrons injected from the cathode into the light emitting layer. In an organic EL display panel for color display, organic EL elements form subpixels of RGB colors and RGB subpixels adjacent to each other cooperatively form one pixel.

(4) In manufacture of an organic EL display panel, a substrate is partitioned into regions with banks, and a light emitting layer is formed in each region. The banks are formed by patterning a photosensitive thermosetting resin into bank shapes by a photolithography method and then heating and baking them.

(5) For formation of the light emitting layer, a wet method is often used by which an ink, for forming a light emitting layer, containing a polymer material or a low molecular weight material having a good thin film formation property is applied to recessed spaces partitioned with the banks, by an ink jet method or another method. According to this wet method, also in a large size panel, organic functional layers including the light emitting layer can be formed comparatively easily.

(6) If a bank suffers from partial collapse therein in the manufacturing process of such an organic EL display panel as described above, then when a light emitting layer is to be formed at a subsequent step, inks of different colors applied across the bank having the defective portion are sometimes mixed to cause color mixture. In this case, the emission color within the area within which such color mixture occurs sometimes becomes different from the original emission color or is recognized as a dark point in error, resulting in deterioration of the display quality. Especially, in a configuration in which banks extending in a column direction are provided, there is the possibility that the color mixture may expand to a plurality of pixels along the bank and cause significant deterioration of the display quality.

(7) Therefore, for example, PTL 1 and PTL 2 disclose a technology of applying a thermosetting repair material in the form of a paste to a position spaced by a predetermined distance from a defective portion existing in a bank and then heating and baking the repair material to form a dam, to thereby suppress expansion of color mixture.

CITATION LIST

SUMMARY

Technical Problem

(10) However, it may be sometimes difficult for the method disclosed in PTL 1 to suppress, in a manufacturing process, expansion of color mixture that is caused by a defect of a form in which part of an elongated bank is missing.

(11) Taking the problem described above into consideration, it is an object of the present disclosure to provide a method for manufacturing an organic EL display panel and an organic EL display panel by which, when part of an elongated bank is missing in the manufacturing process of an organic EL display panel, the range of subpixels within which the display quality is deteriorated by the missing can be restricted.

Solution to Problem

(12) A method for manufacturing an organic EL display panel according to one aspect of the present disclosure include a step of preparing a substrate, a step of forming a plurality of pixel electrodes arranged in a matrix on an upper face of the substrate, a step of forming, between the pixel electrodes adjacent to each other at least in a row direction on the substrate, a plurality of elongated banks extending in a column direction and formed in parallel to each other, a step of detecting a missing portion at which part of the elongated banks does not exist, a step of forming, above the pixel electrodes, a pair of repair banks in each of two gaps between a bank in which the missing portion has been detected and banks adjacent on opposite sides in the row direction of the column bank, a step of forming a light emitting layer by applying an ink that contains an organic light emitting material to each of gaps between the plurality of banks, and a step of forming a common electrode above the light emitting layer. The step of forming the pair of repair banks includes a first step of forming a pair of repair row banks at positions spaced by a predetermined distance or more in the column direction above the pixel electrodes that exist in the two gaps and whose positions in the column direction are same, at least at part thereof, as that of the missing portion, and a second step of forming repair column banks that connect, in the column direction, an end portion of each of the repair row banks that are not connected in the row direction to the bank that has the missing portion to a closest portion of the column bank.

(13) Further, an organic EL display panel according to one aspect of the present disclosure includes a substrate, a plurality of pixel electrodes arranged in a matrix on an upper face of the substrate, a plurality of elongated column banks that are extending in a column direction and are formed in parallel to each other between the pixel electrodes adjacent to each other at least in a row direction on the substrate, a missing portion at which part of the elongated column banks does not exist, a pair of repair banks formed, above the pixel electrodes, in each of two gaps between a column bank that has the missing portion and column banks adjacent on opposite sides in the row direction of the column bank, a light emitting layer composed of an application film formed in each of gaps between the plurality of column banks, and a common electrode provided above the light emitting layer. The repair banks include a pair of repair row banks formed at positions spaced by a predetermined distance or more in the column direction above the pixel electrodes that exist in the two gaps and whose positions in the column direction are same, at least at part thereof, as that of the missing portion, and repair column banks that connect, in the column direction, an end portion of each of the repair row banks that are not connected in the row direction to the column bank that has the missing portion to a closest portion of the column bank.

Advantageous Effect of the Invention

(14) With the display panel and the method for manufacturing a display panel according to the one aspect of the present disclosure, when part of an elongated bank is missing in the manufacturing

process, the range of subpixels in which the display quality is deteriorated by the missing in a completed organic EL display panel can be restricted to subpixels that include pixel electrodes whose positions in the column direction are same, at least at part thereof, as that of the missing portion.

Description

BRIEF DESCRIPTION OF DRAWINGS

- (1) FIG. 1 is a schematic block diagram depicting an example of a configuration of an organic EL display apparatus according to an embodiment.
- (2) FIG. 2 is a partial plan view schematically depicting a display panel according to the embodiment.
- (3) FIG. 3 is a partially enlarged sectional view of the display panel according to the embodiment, taken along line A-A' of FIG. 2.
- (4) FIG. 4A is a schematic perspective view depicting an example of a missing portion 3a that occurs in a column bank 14a, and FIG. 4B is a schematic perspective view depicting a state in which a pair of repair banks 52X1 and a pair of banks 52X2 and 52Y2 are formed so as to sandwich the missing portion 3a therebetween in a Y direction.
- (5) FIG. 5A is a schematic perspective view depicting an example of a missing portion 3b that occurs in a column bank 14a and is longer than the missing portion 3a, and FIG. 5B is a schematic perspective view depicting a state in which pairs of repair banks 52X1 and 52Y1 and pairs of repair banks 52X2 and 52Y2 are formed so as to sandwich the missing portion 3b therebetween in the Y direction.
- (6) FIG. 6 is a schematic flow chart depicting a manufacturing process of the display panel according to the embodiment.
- (7) FIGS. 7A, 7B, 7C, 7D, and 7E are schematic sectional views depicting parts of manufacturing steps of the display panel according to the embodiment.
- (8) FIG. 8 is a view schematically depicting a method for applying an ink to an inside of a gap by an ink jet method.
- (9) FIG. 9 is a schematic configuration diagram depicting an example of a repair apparatus used for detection of a missing portion and repair of a bank.
- (10) FIG. 10A is a schematic plan view depicting application positions of a repair material by a needle dispenser, set around the missing portion of FIG. 7A, and FIG. 10B is a schematic plan view depicting a state in which dam portions are formed.
- (11) FIG. 11A is a schematic plan view depicting application positions of a repair material by the needle dispenser, set around the missing portion of FIG. 8A, and FIG. 11B is a schematic plan view depicting a state in which dam portions are formed.
- (12) FIGS. 12A, 12B, 12C, 12D, 12E, 12F, and 12G are schematic sectional views depicting a manner in which a dam portion is formed by applying a repair material by the needle dispenser. FIG. 12A is a schematic sectional view depicting a state of a tank and a needle in a state before the repair material is applied. FIG. 12B is a schematic sectional view depicting a state in which the repair material attached to the needle is applied to an application point P1. FIG. 12C is a schematic sectional view depicting a state while the needle is being moved upward. FIG. 12D is a schematic sectional view depicting a state in which the needle has been moved upward. FIG. 12E is a schematic sectional view depicting a state in which the needle and the tank are moved and the repair material is applied to an application point P2. FIG. 12F is a schematic sectional view depicting a state in which the repair material applied to the application point P1 and the repair material applied to the application point P2 are connected. FIG. 12G is a schematic sectional view depicting a state in which the needle has been moved upward.

- (13) FIGS. **13A**, **13B**, and **13C** are partially enlarged sectional views of the display panel according to the embodiment, taken along line B-B, line C-C, and line D-D of FIG. **11B**, respectively.
- (14) FIGS. **14A** and **14B** are schematic plan views depicting states of a display panel on which dam portions are formed, which is supposed as a comparative example.
- (15) FIG. **15** is a schematic plan view depicting a state in which an ink layer is formed on a display panel **100**.
- (16) FIG. **16** is a schematic plan view depicting a state in which an ink layer is formed on the display panel according to the comparative example.
- (17) FIG. **17A** is a schematic perspective view depicting an example of a missing portion occurring in a bank, and FIG. **17B** is a schematic perspective view depicting a state in which dam portions conceived by the present inventors are formed around the missing portion.
- (18) FIG. **18A** is a schematic perspective view depicting another example of a missing portion occurring in a bank, and FIG. **18B** is a schematic perspective view depicting a state in which dam portions conceived by the inventors are formed around the missing portion.
- (19) FIG. **19A** is a schematic plan view depicting a state in which the dam portions of FIG. **17B** are formed, and FIG. **19B** is a schematic plan view depicting a state in which the dam portions of FIG. **18B** are formed.

DESCRIPTION OF EMBODIMENTS

(20) <Circumstances Leading to Mode for Carrying Out the Present Invention>

(21) In a method for manufacturing an organic EL display panel of the line bank structure, a light emitting layer is formed by forming a plurality of elongated banks extending in a column direction and formed in parallel to each other on a substrate and applying inks containing organic light emitting materials to gaps between the plurality of banks. According to the organic EL display panel of the line bank structure, since each ink is movable in the gaps along the banks, the dispersion in film thickness at the point of time of application of the ink is uniformized by flow of the ink, and a light emitting layer of a uniform film thickness can thus be formed. As a result, an organic EL display panel having little luminance unevenness can be manufactured. However, if a defect exists in a bank, then there is the possibility that the ink applied in a gap may advance into an adjacent gap through the defect, resulting in production of a color mixture region in which inks of different emission colors are mixed. Especially, in the organic EL display panel of the line bank structure, since mixed inks flow along the banks, there is the possibility that deterioration of the display quality may occur over a plurality of pixels.

(22) As a method for repairing a defect of a line bank, for example, a technology is disclosed in PTL 1 and PTL 2 bp which dams are formed at positions of a predetermined distance in a column direction from a defect in gaps on opposite sides in a row direction of the defect to thereby restrict occurrence of deterioration of the display quality caused by color mixture to subpixels on the opposite sides in the row direction of the defect.

(23) However, in regard to a defect in the form of missing part of an elongated bank in a manufacturing process, in a case where the missing portion has a predetermined length in a longitudinal direction, the method described in PTL 1 is sometimes difficult to suppress expansion of color mixture.

(24) FIG. **17A** is a schematic perspective view depicting an example of a missing portion occurring in a bank of a display panel that includes elongated banks.

(25) As depicted in FIGS. **17A** and **17B**, the display panel includes, as main components thereof, a base substrate **11**, pixel electrodes **12** arranged in a matrix in X and Y directions, a hole injection layer **13**, column banks **14a** extending in the Y direction (column direction) and row banks **24** of lower height extending in the X direction (row direction), both the column banks **14a** and the row banks **24** being arranged between the pixel electrodes **12**, an organic light emitting layer, an electron transport layer, a common electrode, and a sealing layer. Further, light emitting elements having organic light emitting layers each corresponding to one of emission colors of red (R), green

(G), and blue (B) are arranged as subpixels in a matrix corresponding to the pixel electrodes **12**. It is to be noted that FIG. **17A** depicts a state before baking of the column banks **14a** before the electron transport layer, the common electrode, and the sealing layer are formed in the manufacturing process.

(26) As depicted in FIG. **17A**, the display panel has a missing portion **3c** at which part of a column bank **14a** is missing from a surface of the base substrate **11** and part of the elongated column bank **14a** does not exist. Opposite ends **3c1** and **3c2** of the missing portion **3c** are positioned on pixel electrodes **12c1** and **12c2**, respectively, and the missing portion **3c** has such a positional relation that the position thereof in the Y direction is same, at least at part thereof, as those of the two pixel electrodes **12c1** and **12c2**. Therefore, according to the method for forming dams at positions spaced by a predetermined distance in the Y direction from a defective portion as disclosed in PTL 1, it is difficult to suppress expansion of color mixture.

(27) In contrast, FIG. **17B** is a schematic perspective view depicting a form of a display panel in which dam portions conceived by the inventors are formed for the missing portion **3c**. FIG. **19A** is a schematic plan view depicting a state in which the dam portions of FIG. **17B** are formed. It is to be noted that FIG. **17B** depicts a state after baking of the column banks **14a** before the electron transport layer, the common electrode, and the sealing layer are formed in the manufacturing process.

(28) In the form of the display panel depicted in FIG. **17B**, paired repair row banks **52X1** and **52X2** are formed at positions **A1** and **A2** spaced by a predetermined distance $2 \times a$ in the column direction above the pixel electrodes **12c1** and **12c2**, respectively, in each of two gaps **20** between a column bank **14** in which a missing portion **3c** exists and adjacent column banks **14** on the opposite sides in the row direction of the column bank **14**. Here, the positions **A1** and **A2** may be positions at which the distance in the Y direction is in the maximum, above the pixel electrodes **12c1** and **12c2**, respectively. In this case, the repair row banks **52X1** and **52X2** are individually formed to configure dams **501** and **502** such that the dams **501** and **502** partition the gaps **20** into a first space **SA** formed from a space portion adjacent to the missing portion **3c** and two second spaces **SB** each formed from a space portions that is not adjacent to the missing portion **3c**. Consequently, color mixture can be restricted to the inside of the first space **SA**, and mixed ink can be suppressed from flowing into the second spaces **SB**.

(29) On the other hand, a method depicted in FIG. **18B** in which the missing portion **3c** is further expanded in the Y direction until the opposite ends **3d1** and **3d2** of the missing portion **3d** are positioned on the row banks **24** fails to suppress expansion of color mixture. FIG. **18A** is a schematic perspective view depicting another example of a missing portion that occurs in a bank, and FIG. **18B** is a schematic perspective view depicting a state in which dam portions conceived by the inventors are formed around a missing portion. FIG. **19B** is a schematic plan view depicting a state in which the dam portions of FIG. **18B** are formed.

(30) As depicted in FIG. **18A**, the missing portion **3d** has a position in the Y direction same as those of the two pixel electrodes **12d1** and **12d2** and has a position overlapping in the Y direction part of the row banks **24** between which the pixel electrodes **12d1** and **12d2** are sandwiched in the Y direction.

(31) Therefore, such a method as depicted in FIG. **17B** by which pairs of repair row banks **52X1** and **52X2** are formed at the positions **A1** and **A2** spaced by the predetermined distance $2 \times a$ in the column direction above pixel electrodes **12d1** and **12d2**, respectively, fails to dam up the gaps **20** positioned on the opposite sides in the X direction of the missing portion **3d** and fails to partition the gaps **20** into the first space **SA** adjacent to the missing portion **3d** and the second spaces **SB** that are not adjacent to the missing portion **3d**. Therefore, the mixed color ink flows out from within the first space **SA** into the second spaces **SB** to thereby expand color mixture.

(32) Therefore, the inventors have intensively studied a structure for damming up, in a case in which a missing portion has a position overlapping in the Y direction part of a row bank in addition

to pixel electrodes, the gaps **20** located on the opposite sides in the X direction of a column bank having the missing portion and a method for manufacturing the structure, and have come up with the method for manufacturing an organic EL display panel and the organic EL display panel according to the present disclosure.

(33) <<Overview of Modes for Carrying Out the Invention>

(34) An organic EL display panel according to an embodiment of the present disclosure includes a substrate, a plurality of pixel electrodes arranged in a matrix on an upper face of the substrate, a plurality of elongated column banks that are extending in a column direction and are formed in parallel to each other between the pixel electrodes adjacent to each other at least in a row direction on the substrate, a missing portion at which part of the elongated column banks does not exist, a pair of repair banks formed, above the pixel electrodes, in each of two gaps between a column bank that has the missing portion and column banks adjacent on opposite sides in the row direction of the column bank, a light emitting layer composed of an application film formed in each of gaps between the plurality of column banks, and a common electrode provided above the light emitting layer. The repair banks include a pair of repair row banks formed at positions spaced by a predetermined distance or more in the column direction above the pixel electrodes that exist in the two gaps and whose positions in the column direction are same, at least at part thereof, as that of the missing portion, and repair column banks that connect, in the column direction, an end portion of each of the repair row banks that are not connected in the row direction to the column bank that has the missing portion to a closest portion of the column bank.

(35) With such a configuration as just described, when part of an elongated bank is missing in a manufacturing process, the range of subpixels in which the display quality is deteriorated by the missing in a completed organic EL display panel can be restricted to subpixels including pixel electrodes whose positions in the column direction are same, at least at part thereof, as that of the missing portion.

(36) Further, in another aspect, the organic EL display panel according to the aspect described above may be configured such that the pair of repair row banks are formed at positions at which the distance in the column direction is in the maximum.

(37) With such a configuration as just described, the repair banks can be formed in a maximum range in which the color mixture region is included in subpixels whose positions in the Y direction are same, at least at part thereof, as that of the missing portion.

(38) Further, in a further aspect, the organic EL display panel according to any one of the aspects described above may be configured such that, of the light emitting layer formed in one of the two gaps, a portion that is formed in a range sandwiched by the pair of repair row banks contains an organic light emitting material that is contained in the light emitting layer formed in the other gap opposing in the row direction across the missing portion, and a portion that is formed outside the range sandwiched by the pair of repair row banks does not contain the organic light emitting material that is contained in the light emitting layer formed in the opposing gap.

(39) With such a configuration as just described, the color mixture region is restricted to a range of subpixels whose positions in the Y direction are same, at least at part thereof, as that of the missing portion, and the deterioration of the display quality caused by the color mixture can be restricted to within the subpixels that overlap, at least at part thereof, the missing portion in the Y direction.

(40) Further, in a still further aspect, the organic EL display panel according to any one of the aspects described above may be configured such that it further includes a plurality of elongated row banks that are extending in the row direction and are formed in parallel to each other between the pixel electrodes adjacent to each other at least in the column direction on the substrate, and opposite ends of the missing portion in the column bank that has the missing portion are each positioned on an upper face of one of the row banks.

(41) With such a configuration as just described, in a case where part of an elongated bank is missing in the manufacturing process and an end portion of the missing portion **3** in the Y direction

is positioned on an upper face of a row bank, the range of subpixels whose display quality is deteriorated by the missing in a completed display panel can be restricted.

(42) Further, in a yet further aspect, the organic EL display panel according to any one of the aspects described above may be configured such that, at portions of the pixel electrodes positioned below the row banks, a contact hole at which part of a surface of the pixel electrode is recessed is provided, and the repair column banks are formed at positions at which the repair column banks do not overlap the contact holes as viewed in plan.

(43) With such a configuration as just described, it can be suppressed that the height of the repair column banks formed above the contact holes becomes insufficient by an amount of a height corresponding to the thickness of the flattening layer.

(44) Meanwhile, a method for manufacturing an organic EL display panel according to an embodiment of the present disclosure includes a step of preparing a substrate, a step of forming a plurality of pixel electrodes arranged in a matrix on an upper face of the substrate, a step of forming, between the pixel electrodes adjacent to each other at least in a row direction on the substrate, a plurality of elongated column banks extending in a column direction and formed in parallel to each other, a step of detecting a missing portion at which part of the elongated column banks does not exist, a step of forming, above the pixel electrodes, a pair of repair banks in each of two gaps between a column bank in which the missing portion has been detected and column banks adjacent on opposite sides in the row direction of the column bank, a step of forming a light emitting layer by applying an ink that contains an organic light emitting material to each of gaps between the plurality of column banks, and a step of forming a common electrode above the light emitting layer. The step of forming the pair of repair banks includes a first step of forming a pair of repair row banks at positions spaced by a predetermined distance or more in the column direction above the pixel electrodes that exist in the two gaps and whose positions in the column direction are same, at least at part thereof, as that of the missing portion, and a second step of forming repair column banks that connect, in the column direction, an end portion of each of the repair row banks that are not connected in the row direction to the column bank that has the missing portion to a closest portion of the column bank.

(45) With such a configuration as just described, an organic EL display panel can be manufactured in which, when part of an elongated bank is missing in a manufacturing process, the range of subpixels in which the display quality is deteriorated by the missing can be restricted to subpixels including pixel electrodes whose positions in the column direction are same, at least at part thereof, as that of the missing portion.

(46) Further, in another aspect, the method for manufacturing an organic EL display panel according to the aspect described above may be configured such that, at the first step, the pair of repair row banks are formed at positions at which the distance in the column direction is in the maximum.

(47) With such a configuration as just described, by forming repair row banks above the pixel electrodes at the formation step of repair banks, such a disadvantage that the height of the repair row banks formed on the upper face of the flattening layer becomes insufficient by an amount of a height corresponding to the thickness of the pixel electrodes and such a disadvantage that the material of the repair row banks gets wet and spreads onto the flattening layer or the row banks and flows before it is hardened can be suppressed.

(48) Further, in a further aspect, the method for manufacturing an organic EL display panel according to any one of the aspects described above may be configured such that, at the step of forming the light emitting layer, of inks applied into one of the two gaps, an ink applied to a range sandwiched by the pair of repair row banks flows out through the missing portion into the other gap opposing in the row direction across the missing portion but is blocked within the range in the column direction by the pair of repair row banks.

(49) With such a configuration as just described, a display panel can be manufactured in which the

color mixture region is restricted to a range of subpixels whose positions in the Y direction are same, at least at part thereof, as that of the missing portion **3**, and the deterioration of the display quality caused by the color mixture can be restricted to within the subpixels that overlap, at least at part thereof, the missing portion in the Y direction.

(50) Further, in a still further aspect, the method for manufacturing an organic EL display panel according to any one of the aspects described above may be configured such that it further includes a step of forming, between the pixel electrodes that are adjacent to each other at least in the column direction on the substrate, a plurality of elongated row banks extending in the row direction and formed in parallel to each other, and opposite ends of the missing portion in the column bank that has the missing portion are each positioned on an upper face of one of the row banks.

(51) With such a configuration as just described, a display panel can be manufactured in which, in a case where part of an elongated bank is missing in the manufacturing process and an end portion of the missing portion **3** in the Y direction is positioned on an upper face of a row bank, the range of subpixels whose display quality is deteriorated by the missing is restricted.

(52) Further, in a yet further aspect, the method for manufacturing an organic EL display panel according to any one of the aspects described above may be configured such that it further includes a step of forming, at portions of the pixel electrodes positioned below the row banks, a contact hole at which part of a surface of the pixel electrode is recessed, and the repair column banks are formed at positions at which the repair column banks do not overlap the contact holes as viewed in plan.

(53) With such a configuration as just described, a display panel can be manufactured in which it can be suppressed that the height of the repair column banks formed above the contact holes becomes insufficient by an amount of a height corresponding to the thickness of the flattening layer.

Embodiments

(54) <General Configuration of Organic EL Display Apparatus>

(55) FIG. **1** is a schematic block diagram depicting a configuration of an organic EL display apparatus **1** having a display panel **100** according to an embodiment.

(56) As depicted in FIG. **1**, the organic EL display apparatus **1** includes the display panel **100** and a drive controlling unit **101** connected to the display panel **100**. The display panel **100** is a panel that utilizes an electroluminescence phenomenon of an organic material, and a plurality of light emitting elements (organic EL elements) **10** are arrayed in a matrix on a substrate as depicted in FIG. **2**. The drive controlling unit **101** is configured from four drive circuits **102** to **105** and a control circuit **106**.

(57) It is to be noted that the arrangement of the drive controlling unit **101** with respect to the display panel **100** is not restricted to this.

(58) <Configuration of Organic EL Display Panel>

(59) FIG. **2** is a plan view schematically depicting a general configuration of the display panel **100** as viewed from a display face side. FIG. **3** is a partially enlarged sectional view of the display panel **100**, taken along line A-A of FIG. **2**. The display panel **100** is of what is generally called the top emission type and has the display face on a Z direction side thereof.

(60) The configuration of the display panel **100** is described with reference to FIGS. **2** and **3**.

(61) As depicted in FIG. **3**, the display panel **100** includes, as main components thereof, a base substrate **11**, pixel electrodes **12**, a hole injection layer **13**, column banks **14**, an organic light emitting layer **15**, an electron transport layer **16**, a common electrode **17**, and a sealing layer **18**.

(62) The hole injection layer **13** and the electron transport layer **16** correspond to a functional layer, and the functional layer is structured so as to be sandwiched by the pixel electrodes **12** and the common electrode **17**.

(63) Thus, light emitting elements **10R**, **10G**, and **10B** each having the organic light emitting layer **15** corresponding to an emission color of one of red (R), green (G), and blue (B) form subpixels, and such subpixels are arranged in a matrix as depicted in FIG. **2**.

(64) It is to be noted that FIG. 2 depicts a state in which the electron transport layer **16**, the common electrode **17**, and the sealing layer **18** are removed.

(65) [Base Substrate]

(66) The base substrate **11** has a substrate main body portion **11a**, a thin film transistor (TFT) layer **11b**, and a flattening layer **11c**.

(67) The substrate main body portion **11a** is a portion that serves as a base of the display panel **100** and can be formed from any of insulating materials such as alkaline-free glass, soda glass, polycarbonate resin, polyester resin, and alumina. Further, the substrate main body portion **11a** may otherwise be formed using a polyimide material.

(68) The TFT layer **11b** is provided for each of the subpixels on a surface of the substrate main body portion **11a**, and a pixel circuit including a thin film transistor element is formed in each of the TFT layers **11b**.

(69) The flattening layer **11c** is formed on the TFT layers **11b**. The flattening layer **11c** is made of an organic insulating material such as a polyimide resin, an acrylic resin, and a novolac type phenolic resin or an inorganic insulating material such as silicon oxide (SiO) or silicon nitride (SiN), and has a function of ensuring electric insulation between the TFT layers **11b** and the pixel electrodes **12** and flattening, even if a step exists on an upper face of a TFT layer **11b**, the step to suppress an influence of the step on the base face configuring the pixel electrodes **12**.

(70) [Pixel Electrode]

(71) The pixel electrodes **12** are each a pixel electrode provided individually for each subpixel on the base substrate **11** and is made of a light-reflecting conductive material such as silver (Ag), aluminum (Al), an aluminum alloy, molybdenum (Mo), or an alloy of silver, palladium, and copper (APC). In the present embodiment, the pixel electrode **12** serves as an anode.

(72) It is to be noted that a known transparent conductive film may be provided further on surfaces of the pixel electrodes **12**. As a material for the transparent conductive film, for example, indium tin oxide (ITO) or indium zinc oxide (IZO) can be used. The transparent conductive film is interposed between the pixel electrodes **12** and the hole injection layer **13** and has a function of improving bondability between the layers.

(73) [Hole Injection Layer]

(74) The hole injection layer **13** is a layer made of an oxide of, for example, silver (Ag), molybdenum (Mo), chromium (Cr), vanadium (V), tungsten (W), nickel (Ni), or iridium (Ir) or a conductive polymer material such as PEDOT (mixture of polythiophene and polystyrene sulfonic acid). Of the above, the hole injection layer **13** made of a metal oxide has a function of stably assisting holes, or assisting generation of holes, to inject and transport holes into and to the organic light emitting layer **15**.

(75) [Bank]

(76) On a surface of the hole injection layer **13**, a plurality of column banks **14** each having a strip shape as viewed in plan are provided in parallel such that they extend along the Y direction (column direction). Such column banks **14** are made of an insulating organic material (for example, an acrylic resin, a polyimide resin, a novolac type phenol resin, or other resins).

(77) A cross section of each column bank **14** has a trapezoidal shape as depicted in FIG. 3, and between the column banks **14**, gaps **20** (**20R**, **20G**, and **20B**) partitioned by the column banks **14** are formed. On a bottom of each gap **20**, a plurality of pixel electrodes **12** are provided in a line in the Y direction, and a hole injection layer **13**, an organic light emitting layer **15**, and an electron transport layer **16** are formed as the functional layer on each pixel electrode **12**.

(78) The column bank **14** partitions light emitting elements **10** adjacent to each other in the X direction from each other and has a function also as a structure for suppressing applied inks from overflowing when the organic light emitting layer **15** is formed by a wet method.

(79) A row bank **24** has a height smaller than that of the column bank **14** (refer to FIG. 7), and is formed between a pixel electrode **12** and another pixel electrode **12** adjacent to each other in the Y

direction in each gap **20** and partitions light emitting elements **10** adjacent to each other in the Y direction from each other. In other words, the display panel **100** is an organic EL display panel having what is generally called a line bank.

(80) In the plurality of gaps **20**, the positions in the Y direction of the plurality of row banks **24** formed therein are same as each other. Each row bank **24** extends in the X direction (row direction) and passes under a column bank **14** to be connected to an adjacent row bank **24** such that it has a shape of a strip extending in the X direction. Accordingly, on the base substrate **11**, the column banks **14** and the row banks **24** are formed in a lattice as a whole (refer to FIG. 2).

(81) [Missing Portion of Column Bank]

(82) A missing portion **3** existing in a column bank **14a** is described.

(83) In the display panel **100**, the missing portion **3** is a region in which part of the column bank **14a** is missing from the surface of the flattening layer **11c** such that part of the elongated column bank **14a** does not exist. Such missing of the column bank **14a** occurs incidentally in manufacture of the column banks **14a**. For example, such missing occurs where sufficient polymerization is not made because of insufficient light exposure at a step of exposure for a bank material layer and the material there is washed away at a subsequent development step. In a case where the missing portion **3** is produced in this manner, color mixture occurs between ink layers **15a** formed in gaps adjacent to each other through the missing portion **3**. Therefore, since the location of the column bank **14a** at which the missing portion **3** is produced makes a cause of emission color failure by color mixture of inks of different emission colors, the location is determined as a defect.

(84) FIG. 4A is a schematic perspective view depicting an example of a missing portion **3a** produced in a column bank **14a**. In FIG. 4A, one end **3a1** in the Y direction of the missing portion **3a** is positioned between row banks **24** adjacent to each other in the Y direction, and the other end **3a2** of the missing portion **3a** is positioned on a row bank **24**.

(85) Meanwhile, FIG. 5A is a schematic perspective view depicting an example of a missing portion **3b** that is produced in a column bank **14a** and is longer than the missing portion **3a**. In FIG. 5A, one end **3b1** in the Y direction of the missing portion **3b** is positioned on a row bank **24**, and also the other end **3b2** of the missing portion **3b** is positioned on a different row bank **24**. It is to be noted that, in the present specification, where the missing portions **3a** and **3b** are not distinguished from each other, each of them is referred to as a missing portion **3**.

(86) It is to be noted that a defect that occurs in a column bank **14a** is not limited to such missing portions **3** as described above. In a case where a foreign article enters one column bank **14a** and penetrates a wall face of the column bank **14** to an adjacent gap **20**, it can be said that a defect occurs. For example, in a case where a foreign article sticks to a column bank **14a** and makes a defect, or in a case where a foreign article exists in or under a column bank **14a**, if the close contact between the foreign article and the bank material is low, a gap is generated and forms a flow path for the ink, resulting in production of a defect. Accordingly, this makes a cause of color mixture that occurs between ink layers **15a** formed in gaps adjacent to each other with the foreign article interposed therebetween. The present disclosure makes it an object to repair the missing portions **3** among various defects.

(87) [Repair Bank]

(88) In the case where there is a missing portion **3** in which part of an elongated column bank **14** is missing, a configuration is adopted in which a pair of repair banks **52** are formed in each of two gaps **20** between the column bank **14** in which the missing portion **3** exists and adjacent column banks **14** on the opposite sides of the column bank **14** in the row direction.

(89) In the following, a configuration of the repair banks **52** is described.

(90) FIG. 4B is a schematic perspective view depicting a state where a pair of repair banks **52X1** and a pair of banks **52X2** and **52Y2** are formed such that a missing portion **3a** is interposed therebetween in the Y direction. As depicted in FIG. 4B, pairs of repair row banks **52X1** and **52X2** (where they are not distinguished from each other, each of them is referred to as a repair row bank

52X) are formed at positions **A1** and **A2** spaced by a predetermined distance or more in the column direction above pixel electrodes **12a1** and **12a2** (where they are not distinguished from each other, each of them is referred to as a pixel electrode **12a**) that have a same position in the Y direction, at least at part thereof, as that of the missing portion **3a**. Here, the positions **A1** and **A2** are positions at which the distance in the Y direction is in the maximum, above the pixel electrodes **12a1** and **12a2**.

(91) At this time, by forming the pairs of repair row banks **52X1** and **52X2** above the pixel electrodes **12a1** and **12a2**, the number of subpixels that become dark spots can be minimized.

(92) Further, in a case where a repair row bank **52X** is formed, for example, on a row bank **24**, since both of them are made of an organic material, they are high in affinity, and therefore, the material of the repair row bank **52X** is liable to get wet and spread on the row bank **24** and cannot be formed with a sufficient height as a dam of the repair row bank **52X** in some cases. In contrast, if a repair row bank **52X** is formed above a pixel electrode **12** as depicted in FIG. **4B**, a necessary height can be secured for the repair row bank **52X**.

(93) By such a configuration as described above, in the example depicted in FIG. **4B**, the repair row banks **52X1** formed above the pixel electrode **12a1** in the two gaps **20** between a column bank **14** having the missing portion **3a** and column banks **14** on the opposite sides in the X direction of the column bank **14** are structured such that end portions thereof on the opposite sides in the X direction are connected to the column banks **14** adjacent in the X direction. Consequently, the dam **501** that connects the column banks **14** to each other can be constructed.

(94) However, the repair row banks **52X2** formed on the pixel electrode **12a2** are structured such that end portions thereof on the missing portion **3a** side in the X direction are not connected in the X direction to adjacent column banks **14**, and a dam that connects the column banks **14** to each other cannot be constructed. Therefore, such a configuration is adopted that each of the repair row banks **52X2** is additionally provided with a repair column bank **52Y2** that connects the end portion of the repair row bank **52X2**, which is not connected in the X direction to the column bank **14**, and a portion of the column bank **14**, which is closest to the end portion, to each other in the Y direction. In particular, each of the repair banks **52** formed on the pixel electrode **12a2** have an L-shaped configuration as viewed in plan including the repair row bank **52X2** and the repair column bank **52Y2**.

(95) By such a configuration as described above, the repair banks **52** formed above the pixel electrode **12a2** in the two gaps **20** between the column bank **14** having the missing portion **3a** and the column banks **14** on the opposite sides in the X direction of the column bank **14** are each structured such that the end portions on the opposite sides thereof are connected to the column banks **14** that are individually adjacent in the X direction.

(96) From the foregoing, as depicted in FIG. **4B**, the repair banks **52** formed from the repair row banks **52X1** are formed in the gaps **20** provided on the opposite sides of the column bank **14** having the missing portion **3a** to configure the dam **501**, and the repair banks **52** formed from the repair row banks **52X2** and the repair column banks **52Y2** are formed in the gaps **20** to configure the dam **502**. Further, by the pair of dams **501** and **502**, the gaps **20** are partitioned into the first space **SA** composed of a space portion adjacent to the missing portion **3a** and the two second spaces **SB** composed of space portions that are not adjacent to the missing portion **3a**.

(97) On the other hand, FIG. **5B** is a schematic perspective view depicting a state where pairs of repair banks **52X1** and **52Y1** and pairs of repair banks **52X2** and **52Y2** are formed such that they sandwich the missing portion **3b** therebetween in the Y direction. As depicted in FIG. **5B**, a pair of repair row banks **52X1** and **52X2** (where they are not distinguished from each other, each of them is referred to as a repair row bank **52X**) are formed at positions **A1** and **A2** spaced by a predetermined distance or more in the column direction above pixel electrodes **12b1** and **12b2** (where they are not distinguished from each other, each of them is referred to as a pixel electrode **12b**) whose positions in the Y direction are same, at least at part thereof, with that of the missing

portion **3b**. Here, the positions **A1** and **A2** may be positions at which the distance in the Y direction is in the maximum, above the pixel electrodes **12b1** and **12b2**.

(98) However, in the example depicted in FIG. 5B, the repair row banks **52X1** and **52X2** formed on the pixel electrodes **12b1** and **12b2** are structured such that end portions thereof on the missing portion **3b** side in the X direction are not connected in the X direction to the adjacent column bank **14**, and a dam that connects the column banks **14** to each other cannot be constructed. Therefore, such a structure is adopted that repair column banks **52Y1** and **52Y2** are additionally provided by which the end portions of the repair row banks **52X1** and **52X2**, which are not connected to the column bank **14** in the X direction, and portions of the column bank **14**, which are closest to the respective end portions, are connected to each other in the Y direction. In particular, the repair banks **52** formed on the pixel electrode **12b1** are formed from the repair row banks **52X1** and the repair column banks **52Y1** while the repair banks **52** formed on the pixel electrode **12b2** are formed from the repair row banks **52X2** and the repair column banks **52Y2** such that they have an L-shaped configuration as viewed in plan.

(99) By such a configuration as just described, in each of the two gaps **20** between the column bank **14** having the missing portion **3b** and the column banks **14** on the opposite sides in the X direction of the column bank **14**, the two pairs of repair banks **52** formed above the pixel electrodes **12b1** and **12b2** are structured such that end portions on the opposite sides thereof are individually connected to the column banks **14** adjacent in the X direction.

(100) From the foregoing, as depicted in FIG. 5B, in the gaps **20** on the opposite sides in the X direction of the column bank **14** having the missing portion **3b**, the repair banks **52** formed from the repair row banks **52X1** and the repair column banks **52Y1** are formed to configure the dam **501**, and the repair banks **52** formed from the repair row banks **52X2** and the repair column banks **52Y2** are formed to configure the dam **502**. Further, the pair of dams **501** and **502** partition the gaps **20** into the first space SA configured from a space portion adjacent to the missing portion **3b** and the two second spaces SB configured from space portions that are not adjacent to the missing portion **3b**.

(101) It is to be noted that a width of each of the repair banks (thickness as viewed in plan) is, for example, 5 to 50 μm .

(102) As described above, in the present embodiment, it is possible, in the gaps **20** on the opposite sides of the column bank **14** in which the missing portion **3** exists, to block the mixture color ink by the pair of dams **501** and **502** to thereby prevent spreading of the mixture color region.

(103) [Organic Light Emitting Layer]

(104) The organic light emitting layer **15** is a portion in which carriers (holes and electrons) recombine to emit light and includes organic materials each corresponding to one of the colors of R, G, and B.

(105) The organic light emitting layers **15** are formed in grooved gaps (refer to the gaps **20R**, **20G**, and **20B** of FIG. 3) defined by the column banks **14** and extending in the Y direction.

(106) It is to be noted that the gap **20R** depicted in FIG. 3 is a gap in which a red light emitting layer is formed to form the red light emitting element **10R**, and the gap **20G** and the gap **20B** are gaps in which green and blue light emitting layers are formed to form the green and blue light emitting elements **10G** and **10B**, respectively.

(107) Accordingly, the organic light emitting layers **15** of colors different from each other are arranged across the column banks **14**.

(108) Examples of a material for the organic light emitting layers **15** include fluorescent materials such as polyparaphenylene vinylene (PPV), polyfluorene, oxynoid compounds, perylene compounds, coumarin compounds, azacoumarin compounds, oxazole compounds, oxadiazole compounds, perinone compounds, pyrrolopyrrole compounds, naphthalene compounds, anthracene compounds, fluorene compounds, fluoranthene compounds, tetracene compounds, pyrene compounds, coronene compounds, quinolone compounds, azaquinolone compounds, pyrazoline

derivatives, pyrazolone derivatives, rhodamine compounds, chrysene compounds, phenanthrene compounds, cyclopentadiene compounds, stilbene compounds, diphenylquinone compounds, styryl compounds, butadiene compounds, dicyanomethylene pyran compounds, dicyanomethylene thiopyran compounds, fluorescein compounds, pyrylium compounds, thiopyrylium compounds, selenapyrylium compounds, telluropirylium compounds, aromatic aldadiene compounds, oligophenylene compounds, thioxanthene compounds, cyanine compounds, acridine compounds, metal complex of 8-hydroxyquinoline compound, metal complex of 2-bipyridine compound, complex of Schiff salt and group III metal, oxin metal complex, and rare earth complex.

(109) In the display panel **100**, a pair of repair banks **52** are formed in each of gaps **20** on the opposite sides of a column bank **14** having a missing portion **3** such that the opposite ends of each of the repair banks **52** are connected to the column banks **14** on the opposite sides in the X direction to form dams **501** and **502**. Therefore, by the pair of dams **501** and **502** opposing to each other in the Y direction, the gaps **20** are partitioned into a first space SA adjacent to the missing portion **3** and two second spaces SB that are not adjacent to the missing portion **3**. Consequently, even if a color mixture region is formed in the first space SA, the color mixture region does not spread to the second spaces SB beyond the repair banks **52**.

(110) As a result, a configuration can be implemented in which, in the organic light emitting layers **15** formed in one of the two gaps **20** opposing to each other in the row direction across the missing portion **3**, a portion of the organic light emitting layer **15**, which is formed in the range sandwiched by the pair of repair row banks **52X1** and **52X2**, contains an organic light emitting material that is contained in the organic light emitting layer **15** formed in the other gap **20** opposing in the row direction across the missing portion **3** while portions of the organic light emitting layer **15** formed outside the range sandwiched between the pair of repair row banks **52X1** and **52X2** do not contain the organic light emitting material contained in the organic light emitting layer **15** formed in the other gap **20**.

(111) [Electron Transport Layer]

(112) The electron transport layer **16** has a function of transporting electrons injected from the common electrode **17** to the organic light emitting layer **15** and is formed, for example, from oxadiazole derivatives (OXD), triazole derivatives (TAZ), phenanthroline derivatives (BCP, Bphen), or other derivatives.

(113) [Common Electrode]

(114) The common electrode **17** is formed from a light transmissive material having electric conductivity such as ITO or IZO and is provided over all subpixels.

(115) In the present embodiment, the common electrode **17** serves as a cathode.

(116) [Sealing Layer **18**]

(117) The sealing layer **18** is provided in order to protect the hole injection layer **13**, the organic light emitting layer **15**, the electron transport layer **16**, and the common electrode **17** against moisture and oxygen.

(118) It is to be noted that, though not depicted, a black matrix or a color filter, for example, may be formed on the sealing layer **18**.

(119) <Method for Manufacturing Display Panel>

(120) FIG. **6** is a schematic flow chart depicting a manufacturing process of the display panel **100**.

(121) FIGS. **7A** and **7B** are sectional views schematically depicting part of the manufacturing process of the display panel **100**.

(122) The method for manufacturing the display panel **100** is described with reference to FIGS. **3**, **5A**, and **5B** on the basis of the flow chart of FIG. **6**.

(123) First, a TFT layer **11b** is formed on a substrate main body portion **11a** (step S1).

(124) Then, a flattening layer **11c** is formed on the TFT layer **11b** by a photoresist method using an organic material having superior insulation to produce a base substrate **11** (step S2). The thickness of the flattening layer **11c** is, for example, approximately 4 μm . It is to be noted that, though not

depicted in the sectional view of FIG. 3 and the flow chart of FIG. 6, when the flattening layer **11c** is formed, contact holes **2** (refer to FIG. 2) are formed.

(125) Then, a pixel electrode made of a metal material and having a thickness of approximately 200 [nm] is formed on the base substrate **11** by a vacuum deposition method or a sputtering method (step S3).

(126) Then, a hole injection layer made of tungsten oxide is formed uniformly on the base substrate **11** and the pixel electrode by a sputtering method or another method (step S4).

(127) Then, pixel electrodes **12** and a hole injection layer **13** are formed by patterning for each subpixel by a photolithography method (step S5).

(128) Then, row banks **24** and column banks **14** are formed in the following manner by a photolithography method.

(129) First, a bank material for forming the row banks **24** (for example, a photoresist material having photosensitivity) is applied uniformly on the hole injection layer **13** (step S6).

(130) Thereafter, a photo mask having openings conforming to the pattern of the row banks **24** is overlaid on the applied bank material layer, and ultraviolet (UV) rays are irradiated to perform light exposure. Then, a surplus bank material that is not hardened is removed with a developer to form unbaked row banks **24a**. Thereafter, the unbaked row banks **24** are heated and baked to form row banks **24** (step S7).

(131) Then, a bank material for forming column banks **14** (for example, a negative-type photosensitive resin composition) is applied uniformly on the substrate on which the row banks **24** have been formed.

(132) A mask having openings conforming to the pattern of the column banks **14** to be formed is overlaid on the bank material layer, and exposure is performed from above the mask. Thereafter, a surplus bank material is removed with an alkaline developer to pattern the bank material to form the pattern for column banks (step S6). Thereafter, the unbaked column banks **14** are heated and baked to form column banks **14** (step S7). This baking is performed by heating the unbaked column banks **14** for 60 minutes at a temperature of 200° C. to 240° C.

(133) As depicted in FIG. 7A, the row banks **24** and the column banks **14** are formed in pattern. Between adjacent ones of the column banks **14**, gaps **20** are formed.

(134) Then, occurrence of a missing portion in the column banks **14** formed in pattern is checked (step S8), and if a missing portion is present, then repair of it is performed.

(135) Although the bank repair is hereinafter described in detail, this is performed by applying a repair material to gaps **20** between the column banks **14** and drying the repair material to form a dam portion in the vicinity of the detected missing portion. In FIG. 7B, a state is depicted in which an unbaked repair bank **52a** is formed by applying a repair material to a gap **20** between the column banks **14** (step S9).

(136) Thereafter, the unbaked repair bank **52a** is heated and baked to complete the repair bank **52** in addition to the column banks **14** and the row banks **24**, thereby completing the repair of the missing portion **3** (step S10). This baking is performed by heating the unbaked repair bank **52a** for 60 minutes at a temperature of 200° C. to 240° C.

(137) FIG. 7C depicts a state in which the column banks **14** are formed and the repair bank **52** is formed by the baking, namely, a state in which the missing portion **3** on the column bank **14** is repaired.

(138) For the column banks **14** formed in this manner, a process for adjusting a contact angle of the column banks **14** to an ink to be applied at a next step may further be carried out. Alternatively, in order to provide liquid repellency to surfaces of the column banks **14**, a surface treatment with a predetermined alkaline solution, water, or an organic solvent, and a plasma process may be carried out, for example. It is to be noted that, in order to provide liquid repellency to the column banks, a material having liquid repellency may be used as the bank material for the column banks.

(139) It is to be noted here that, although the column banks and the dam portions are baked

separately from each other, otherwise they may be baked simultaneously. In particular, although processing here is performed in the order of formation of column banks, baking of the column banks, detection of a missing portion, formation of dam portions, and baking of the dam portions, the processing may be performed otherwise in the order of formation of column banks, detection of a missing portion, formation of dam portions, and baking of the column banks and the dam portions.

(140) Then, as depicted in FIG. 7D, inks for forming the organic light emitting layers **15** are applied to the gaps **20** between adjacent ones of the column banks **14**. The inks are each a mixture of an organic material for configuring the organic light emitting layer **15** and a solvent and is applied to the inside of the gaps **20** by an ink jet method. The method for applying inks to the inside of the gaps **20** by an ink jet method is hereinafter described in detail.

(141) Then, the solvent contained in the applied ink layers **15a** is evaporated to be dried, and then heated and baked as occasion demands to form organic light emitting layers **15** in the gaps **20** as depicted in FIG. 7E (step **S11**).

(142) Then, the solvent contained in the applied ink layers **15a** is evaporated to be dried, and then heated and baked as occasion demands to form organic light emitting layers **15** in the gaps **20** as depicted in FIG. 7 (step **S11**).

(143) Then, on the organic light emitting layer **15** and the column banks **14**, a material for configuring the electron transport layer **16** is deposited by a vacuum evaporation method to form an electron transport layer **16** (step **S12**).

(144) Then, a material such as ITO or IZO is deposited by a sputtering method or another method to form a common electrode (step **S13**).

(145) Then, on a surface of the common electrode **17**, a light transmissive material such as SiN or silicon oxynitride (SiON) is deposited by a sputtering method, a chemical vapor deposition (CVD) method, or another method to form a sealing layer **18** (step **S14**).

(146) The display panel **100** is completed through the steps described above.

(147) [Method for Applying Inks to Inside of Gaps **20** by Ink Jet Method]

(148) Details of a method for applying inks for the organic light emitting layer **15** to the inside of the gaps **20** using an ink jet method are described.

(149) At the time of formation of the organic light emitting layer **15**, inks **15a** that are solutions for forming organic light emitting layer **15** are used to form an organic light emitting layer **15R** in the gap **20R** for a red subpixel, form an organic light emitting layer **15G** in the gap **20G** for a green subpixel, and form an organic light emitting layer **15B** in the gap **20B** for a blue subpixel, in each of regions between a plurality of line banks. It is to be noted that the organic light emitting layer **15R** and the organic light emitting layer **15G** or the organic light emitting layer **15B** may be different in thickness from each other. For example, by making the amount of ink to be applied to the inside of the gap **20R** greater than the amount of ink to be applied to the inside of the gap **20B** and the gap **20G**, the thickness of the organic light emitting layer **15R** can be formed greater than that of the organic light emitting layer **15B** and the organic light emitting layer **15G**.

(150) In order to simplify the description, the inks are sequentially applied to gaps for all three colors by a method for applying an ink to a plurality of gaps **20** for the first color on the substrate setting the amount of the ink to be discharged from a nozzle to a first condition, applying an ink to a plurality of gaps **20** for the second color on the substrate setting the amount of the ink to be discharged from the nozzle to a second condition, and then applying an ink to a plurality of gaps **20** for the third color on the substrate setting the amount of the ink to be discharged from the nozzle to a third condition. After the application of an ink to the gaps **20** for the first color on the substrate ends, an ink is applied to the gaps **20** for the second color on the substrate, whereafter an ink is applied to the gaps **20** for the third color on the substrate. Thus, such application steps as just described are performed repeatedly to sequentially apply the inks for the gaps **20** for the three colors. It is to be noted that, as the nozzle for delivering an ink, nozzles different from one another,

namely, a nozzle for delivering the ink of the first color, a nozzle for delivering the ink of the second color, and a nozzle for delivering the ink of the third color, may be used.

(151) (Method for Uniformly Applying Ink to Gap **20** Between Column Banks **14**)

(152) Now, a method for applying an ink (for example, an ink for red gaps) to gaps of one color is described. FIG. **8** is a view depicting a step of applying an ink for light emitting layer formation to a substrate and is a schematic view in a case where the ink is applied uniformly to gaps **20** between column banks **14**.

(153) The organic light emitting layer **15** extends not only in light emitting regions (regions surrounded by column banks **14** and row banks **24** in FIG. **2**) but also to adjacent non-self-luminous regions (regions on row banks **24** in FIG. **2**). By this, at the time of formation of the organic light emitting layer **15**, the ink applied to the light emitting regions can flow in a column direction through the ink applied to the non-self-luminous regions, and consequently, the film thickness can be leveled between pixels in the column direction. Therefore, large film thickness unevenness is less likely to occur in the column direction, and improvement in terms of luminance unevenness among pixels and lifespan reduction of individual pixels can be anticipated.

(154) In the present application method, the substrate is placed on a work table of a droplet delivering device while it is in a state in which the column banks **14** extend in the Y direction, and while scanning is performed in the X direction with an ink jet head **301** in which a plurality of discharge ports **3031** are arranged on a line along the Y direction, the ink is landed from each discharge port **3031** aiming at a landing target set in a gap **20** between column banks **14**.

(155) It is to be noted that the region to which the ink for the organic light emitting layer **15** is applied with a same application amount is one of three regions lined up in an adjacent relation to each other in the X direction.

(156) The method for forming the organic light emitting layer **15** is not limited to this, and inks may be dropped and applied not by such a method as an ink jet method or a gravure printing method but by a known method such as a dispenser method, a nozzle coating method, a spin coating method, intaglio printing, or relief printing.

(157) [Detection of Missing Portion **3** and Formation of Repair Banks **52**]

(158) As described in the foregoing description of the manufacturing method, accurately, after unbaked column banks **14a** and unbaked repair banks **52a** are formed, the unbaked column banks **14a** and the unbaked repair banks **52a** are heated, baked, and hardened to form final column banks **14** and repair banks **52**. However, since the unbaked column banks **14a** and the unbaked repair banks **52a** are solidified to some degree and have a stable bank shape and dam shape, respectively, in the present specification, also the unbaked column banks **14a** and the unbaked repair banks **52a** are represented merely as column banks **14a** and repair banks **52a**, respectively.

(159) Detection of a missing portion **3** in a column bank **14a** is performed, for example, by pattern inspection of a photographed surface image of the column banks **14a** formed on the base substrate **11**.

(160) FIG. **9** is a schematic configuration diagram depicting an example of a repair apparatus that is used for detection of a bank missing portion and for repair of the bank missing portion.

(161) The repair apparatus **200** includes a table **202** on which the base substrate **11** described hereinabove is to be placed, an imaging element **211**, and a head unit **210** to which a needle dispenser **213** is attached, all provided on a base **201**. The table **202** can move in the Y direction on the basis of an instruction of a central processing unit (CPU) **231** of a controller **230**, and the head unit **210** can move in the X direction and the Z direction in accordance with an instruction of the CPU **231**.

(162) Accordingly, the needle dispenser **213** attached to the head unit **210** can move in the X direction, the Y direction, and the Z direction relative to the base substrate **11** placed on the table **202** above the base substrate **11** in accordance with an instruction of the CPU **231**.

(163) It is to be noted here that the base substrate **11** on which the pixel electrodes **12**, the hole

injection layer **13**, the column banks **14a**, and the row banks **24** are formed is represented as the base substrate **11**.

(164) Formation of a repair bank **52** is performed by applying a repair material from the needle dispenser **213** to a plurality of positions set along a line on which the repair bank **52** is to be formed (repair bank formation line) in a gap **20**.

(165) (Setting of Repair Bank Formation Line)

(166) First, a case is described in which one end **3a1** in the Y direction of the missing portion **3a** depicted in FIG. **4A** is positioned between row banks **24** adjacent to each other in the Y direction, and the other end **3a2** is positioned on a row bank **24**. FIG. **10A** is a schematic plan view depicting application positions of the repair material by the needle dispenser, which are set in the vicinity of the missing portion **3a** of FIG. **4A**.

(167) As depicted in FIG. **10A**, in a case where a missing portion **3a** exists in a column bank **14a**, coordinate positions of the opposite ends **3a1** and **3a2** in the Y direction of the missing portion **3a** are acquired, and pixel electrodes **12a1** and **12a2** whose position in the Y direction is same, at least at part thereof, as that of the missing portion **3a** are specified on the basis of the acquired coordinate positions. Then, repair row bank formation lines LX1 and LX2 (hereinafter referred to as lines LX1 and LX2) in the X direction are set to positions A1 and A2 that are spaced by a predetermined distance $2 \times a$ or more in the column direction above the pixel electrodes **12a1** and **12a2**. Points P1 to P4 depicted in FIG. **10** represent application positions by the needle dispenser set along the lines LX1 and LX2. Here, the lines LX1 and LX2 may be set to positions at which the distance in the Y direction between the lines LX1 and LX2 is in the maximum above the pixel electrodes **12a1** and **12a2**.

(168) Then, the coordinate positions of the opposite ends **3a1** and **3a2** in the Y direction of the missing portion **3a** and the positions in the Y direction of the lines LX1 and LX2 are compared with each other.

(169) In the example of FIG. **10A**, the one end **3a1** in the Y direction of the missing portion **3a** is positioned between row banks **24** adjacent to each other in the Y direction. Therefore, in the pixel electrodes **12a1**, there is a relation that the position in the Y direction of the line LX1 is positioned on the upper side, in the figure, of the coordinate of the end **3a1** in the Y direction of the missing portion **3a**. Accordingly, it is determined that the end portions of the repair row banks **52X1** formed on the line LX1 are connected to the column bank **14a**.

(170) In contrast, the other end **3a2** of the missing portion **3a** is positioned on a row bank **24**. Therefore, in the pixel electrodes **12a2**, there is a relation that the position in the Y direction of the line LX2 is positioned on the upper side, in the figure, of the coordinate of the other end **3a2** in the Y direction of the missing portion **3a**. Accordingly, it is determined that the end portions of the repair row banks **52X2** formed on the line LX2 are not connected to the column bank **14a**.

(171) In this case, repair column bank formation lines LY2 (hereinafter referred to as lines LY2) are set in the Y direction from the points P4 closest to the missing portion **3a** among the points P1 to P4 to at least the other end **3a2** in the Y direction of the missing portion **3a**. Points P5 to P7 depicted in FIG. **10A** represent application positions by the needle dispenser set along the lines LY2. At this time, it is necessary for the points P7 to be set to positions on the row bank **24** as viewed in top plan.

(172) Now, a case in which both of the opposite ends **3b1** and **3b2** in the Y direction of the missing portion **3b** depicted in FIG. **5A** are positioned between row banks **24** adjacent to each other in the Y direction is described. FIG. **11A** is a schematic plan view depicting application positions of the repair material by the needle dispenser, which are set in the vicinity of the missing portion **3b**.

(173) Also in the example depicted in FIG. **11A**, pixel electrodes **12b1** and **12b2** whose positions in the Y direction are same, at least at part thereof, as that of the missing portion **3b** are specified on the basis of coordinate positions of the opposite ends **3b1** and **3b2** in the Y direction of the missing portion **3b**. Then, lines LX1 and LX2 in the X direction are set to positions A1 and A2 above the

pixel electrodes **12b1** and **12b2**, respectively. Application points **P1** to **P4** by the needle dispenser are set along the lines **LX1** and **LX2**.

(174) Now, coordinate positions of the opposite ends **3b1** and **3b2** in the Y direction of the missing portion **3b** and the positions in the Y direction of the lines **LX1** and **LX2** are compared with each other.

(175) In the example of FIG. **11A**, both of the opposite ends **3b1** and **3b2** in the Y direction of the missing portion **3b** are positioned on upper faces of row banks **24** that are adjacent each other in the Y direction. Therefore, the position in the Y direction of the line **LX1** is positioned on the lower side, in the figure, of the coordinate of the end **3b1** in the Y direction of the missing portion **3b** and the position in the Y direction of the line **LX2** is positioned on the upper side, in the figure, of the coordinate of the end **3b2** in the Y direction of the missing portion **3b**. Accordingly, it is determined that the end portions of the repair row banks **52X1** and **52X2** formed on the lines **LX1** and **LX2** are not connected to the column bank **14a** on both of the pixel electrodes **12b1** and **12b2**.

(176) In this case, lines **LY1** and **LY2** are set in the Y direction from the points **P4** that are closest to the missing portion **3a** among the points **P1** to **P4** to at least the opposite ends **3b1** and **3b2** in the Y direction of the missing portion **3a**. The points **P5** to **P7** depicted in FIG. **10A** represent application positions by the needle dispenser set along the lines **LY1** and **LY2**. At this time, it is necessary for the points **P7** to be set to positions on the row banks **24** as viewed in plan.

(177) (Application and Baking of Repair Material)

(178) FIGS. **12A**, **12B**, **12C**, **12D**, **12E**, **12F**, and **12G** are views schematically depicting a manner in which a repair bank **52** is formed by sequentially applying the repair material to application points **P1**, **P2**,

(179) The repair apparatus **200** forms a repair bank **52** by sequentially applying the repair material to the application points **P1**, **P2**, **P3**, and **P4** or **P1**, **P2**, **P3**, **P4**, **P5**, **P6**, and **P7** set in this manner by using a needle **213a**. The needle dispenser **213** has a tank **213b**, which accommodates the repair material therein, mounted to a tip end portion thereof and can apply the repair material adhering to the needle **213a** in a unit of microliter by moving the needle **213a** upward and downward so as to penetrate the tank **213b**.

(180) First, as depicted in FIGS. **12A** and **12B**, the needle **213a** and the tank **213b** are positioned above the application point **P1**, and the needle **213a** is moved downward to cause the repair material to adhere to the needle **213a**, whereafter the needle **213a** is moved toward the application point **P1** to apply the repair material to the application point **P1**.

(181) Although the repair material has fluidity until it is applied, after the application, it is kept in a mountain shape, and a mountain of the repair material is formed at the application point **P1** as depicted in FIG. **12C**.

(182) Then, the needle **213a** is pulled up into the tank **213b** and the needle **213a** and the tank **213b** are moved to the application point **P2** as depicted in FIG. **12D**. Then, as depicted in FIG. **12E**, the needle **213a** is moved downward and is moved, after the repair material adheres thereto, toward the application point **P2** to apply the repair material to the application point **P2**.

(183) By this, a mountain of the repair material formed at the application point **P2** connects to the mountain of the repair material formed at the application point **P1** as depicted in FIG. **12F**.

(184) Thereafter, the needle **213a** is pulled up and moved to the application point **P3** as depicted in FIG. **12G**.

(185) Similarly, a mountain of the repair material is formed at the application points **P3** and **P4** or **P3**, **P4**, **P5**, **P6**, and **P7** so as to connect to the mountain of the repair material at the application point **P2**.

(186) In this manner, the mountains of the repair material connect to each other in a shape in which they extend from the point **A1** on the column bank **14a** having the missing portion **3** to the adjacent column banks **14a**. Then, the mountains of the applied repair material are dried and are, as occasion demands, subjected to exposure to form a repair bank **52**.

(187) Further, since, at a subsequent simultaneous baking step, the applied repair material is hardened, the repair bank **52** having more stabilized physical properties is formed.

(188) (Formation of Repair Bank **52**)

(189) FIG. **10B** is a schematic plan view depicting a state in which repair banks **52** are formed in the vicinity of the missing portion **3a** of FIG. **4A**. As depicted in FIG. **10B**, application of the repair material by the needle dispenser **213** and baking using, for example, a laser beam are performed at points **P1** to **P4**, points **P1** to **P4**, and points **P5** to **P7** respectively along lines **LX1**, **LX2**, and **LY2** depicted in FIG. **10A** in each of the two gaps **20** between the column bank **14** having the missing portion **3a** and the column banks **14** on the opposite sides in the X direction of the column bank **14**.

(190) Consequently, as depicted in FIG. **10B**, repair banks **52** each including a repair row bank **52X1** are formed in the gaps **20** on the opposite sides in the X direction of the column bank **14** having the missing portion **3a** to form a dam **501** connected at opposite end portions thereof to the column banks **14** adjacent in the X direction. Further, repair banks **52** each including a repair row bank **52X2** and a repair column bank **52Y2** are formed in the gaps **20** to form a dam **502** connected at opposite end portions thereof to the column banks **14** adjacent in the X direction.

(191) Further, by the pair of dams **501** and **502** opposing to each other in the Y direction, the gaps **20** are partitioned into a first space **SA** formed from a space portion adjacent to the missing portion **3a** and two second spaces **SB** formed from space portions that are not adjacent to the missing portion **3a**.

(192) Further, FIG. **11B** is a schematic plan view depicting a state in which repair banks **52** are formed in the vicinity of the missing portion **3b** of FIG. **5A**. In the example depicted in FIG. **11B**, in each of the two gaps **20** between the column bank **14** having the missing portion **3b** and the column banks **14** on the opposite sides in the X direction of the column bank **14**, application of the repair material by the needle dispenser **213** and baking using, for example, a laser beam are performed at positions of the points **P1** to **P4**, the points **P1** to **P4**, points **P5** to **P7**, points **P5** to **P7** respectively along the lines **LX1**, **LX2**, **LY1**, and **LY2** depicted in FIG. **11A**.

(193) Consequently, as depicted in FIG. **5B**, in the gaps **20** on the opposite sides of the column bank **14** having the missing portion **3b**, repair banks **52** each including a repair row bank **52X1** and a repair column bank **52Y1** are formed to form a dam **501** connected at opposite end portions thereof to the column banks **14** adjacent in the X direction. Further, repair banks **52** each including a repair row bank **52X2** and a repair column bank **52Y2** are formed in the gaps **20** to form a dam **502** connected at opposite end portions thereof to the column banks **14** adjacent in the X direction. Further, by the pair of dams **501** and **502** opposing to each other in the Y direction, the gaps **20** are partitioned into a first space **SA** formed from a space portion adjacent to the missing portion **3b** and two second spaces **SB** formed from space portions that are not adjacent to the missing portion **3b**.

(194) By performing the light emitting layer formation step at the next step **S9** (refer to FIG. **6**) after the missing portion **3** of any column bank **14** is repaired in such a manner as described above, an ink color mixture region is restricted as hereinafter described, and the ink is applied to the first space **SA** and the second spaces **SB** to form the organic light emitting layer **15**.

(195) By providing the pair of dams **501** and **502** in the light emitting regions of the pixels on the inner side of the row banks **24** in this manner, normal light emission can be expected outside the pair of dams **501** and **502**, and therefore, the area of subpixels whose display quality is deteriorated can be reduced.

(196) It is to be noted that, as the repair material, a composition of a resin that is hardened by application of light or heat can be used.

(197) Examples of the resin include curable resins having an ethylene double bond such as a (meth)acryloyl group, an allyl group, a vinyl group, or a vinyl oxy group.

(198) Further, a crosslinking agent that crosslinks to a resin, for example, an epoxy compound or a polyisocyanate compound, may be added.

(199) Further, in this resin structure, fluorinated polymer with fluorine introduced therein may be

used. Since fluorine is introduced in the resin of the repair material, liquid repellency can be provided to the repair banks **52** to be formed. Otherwise, various liquid repellent agents may be added to the resin. The addition amount of the liquid repellent agent is 0.01 to 10 wt %. By adding the liquid repellent agent by an amount within this range, storage stability of the resin composition becomes good and also the liquid repellency of the repair banks **52** to be formed becomes good. (200) It is to be noted that, as the repair material, a material same as the bank material from which the column banks **14a** are formed may be used.

(201) To the resin composition included in the repair material, a solvent and a photopolymerization initiator may be suitably added as occasion demands.

(202) For the solvent, one or more solvents having solubility into resin and having a boiling point of approximately 150° C. to 250° C. may be used.

(203) As the photopolymerization initiator, various commercially available photopolymerization initiators can be used.

(204) At the time of application of the repair material, the solid content of the repair material is adjusted, for example, to 20 to 90 wt %, and the viscosity is adjusted, for example, to 10 to 50 cP (centipoise).

(205) The addition amount of the photopolymerization initiator is adjusted according to the exposure amount upon baking, and it is, for example, 0.1 to 50 wt % to the total solid content, preferably 5 to 30 wt %.

(206) (Advantageous Effects in Manufacture of Repair Banks **52**)

(207) Now, details of the method for manufacturing the repair banks **52** are described.

(208) FIGS. **13A**, **13B**, and **13C** are partially enlarged sectional views of the display panel **100** according to the embodiment, taken along line B-B, line C-C, and line D-D of FIG. **11B**, respectively.

(209) Referring to FIG. **13A**, the thickness of the flattening layer **11c** is approximately 4 μm, the height of the column bank **14** is approximately 1 μm, and the thickness of the pixel electrode **12** is approximately 0.2 μm. At the formation step of the organic light emitting layer **15**, a height **521** of a dam necessary to prevent flowing out of the ink **15a** is approximately 0.7 to 0.8 μm, and it is preferable to form a repair row bank **52X** of the height **521** or more above the pixel electrode **12** (in a case where a hole injection layer **13** is stacked, above an upper face of the hole injection layer **13**) as depicted in FIG. **13A**. In a case where a repair bank (**52**) is formed on an upper face of the flattening layer **11c** between a pixel electrode **12** and another pixel electrode **12**, the height of the repair row bank **52X** becomes short by an amount of a height corresponding to the thickness of the pixel electrode **12** and the ink **15a** sometimes flows out.

(210) Further, in the case where the repair bank (**52**) is formed on the upper face of the flattening layer **11c** between a pixel electrode **12** and another pixel electrode **12**, since both of them are made of organic materials, they are high in affinity, and the material of the repair bank (**52**) is liable to get wet and spread. For example, the material may flow before it is hardened by a laser beam, resulting in failure to form the repair bank (**52**) with a sufficient height as a dam. In contrast, in the display panel **100**, since the repair row bank **52X** is formed above the pixel electrode **12**, a necessary height can be secured for the repair row bank **52X**.

(211) Further, referring to FIG. **13B**, the height of the row bank **24** is approximately 0.5 μm. As depicted in FIG. **13A**, on an upper face of the row bank **24** positioned above a gap between a pixel electrode **12** and another pixel electrode **12**, a recessed portion of a depth corresponding to the thickness of approximately 0.2 μm of the pixel electrode exists. In a case where the repair column bank **52Y** is formed across the recessed portion, a recessed portion of an equivalent depth is formed at the same position also on an upper face of the repair column bank **52Y**.

(212) When the repair column bank **52Y** is formed with a height **524** necessary for a dam, a portion of the repair column bank **52Y** formed on the upper face of the row bank **24** is raised by the thickness of approximately 0.5 μm of the row bank **24**. Therefore, even if a recessed portion of a

depth corresponding to the thickness of approximately $0.2\text{ }\mu\text{m}$ of the pixel electrode in the maximum exists on the upper face of the repair column bank **52Y**, the height of the repair column bank **52Y** at the recessed portion does not become lower than the height **524** (approximately 0.7 to $0.8\text{ }\mu\text{m}$) necessary for the dam.

(213) On the other hand, the depth of the contact hole **2** formed in the flattening layer **11c** is approximately $4\text{ }\mu\text{m}$ equal to the thickness of the flattening layer **11c**. Accordingly, in a case where the repair column bank **52Y** is formed on the upper face of the repair column bank **52Y** above the contact hole **2**, a recessed portion of a depth corresponding to the thickness of approximately $4\text{ }\mu\text{m}$ of the flattening layer **11c** is formed on the upper face of the repair column bank **52Y**, and therefore, the repair column bank **52Y** thus formed cannot secure the height **524** necessary for the dam. Therefore, it is necessary to form the repair column bank **52Y** avoiding the position above the contact hole **2**. Since, in the display panel **100**, the repair column bank **52Y** is formed avoiding the position above the contact hole **2**, the repair column bank **52Y** can secure a height necessary for the dam and can suppress flowing out of ink.

(214) FIG. **13C** is a schematic view when it is supposed that a repair column bank (**52**) is formed so as to compensate for a missing portion of a column bank **14** at a position same as that of the missing portion **3**. In this case, since the repair column bank (**52**) is formed on the upper face of the flattening layer **11c** between a pixel electrode **12** and another pixel electrode **12**, from a reason similar to that in the example depicted in FIGS. **13A** and **13B**, the height **524** (approximately 0.7 to $0.8\text{ }\mu\text{m}$) necessary for the dam cannot be secured.

(215) FIGS. **14A** and **14B** are schematic plan views each depicting a state of a display panel on which dam portions are formed, which is supposed as a comparative example.

(216) First, FIG. **14A** is a schematic plan view when it is supposed that, in two gaps **20** between a column bank **14** on which a missing portion **3** exists and column banks **14** adjacent on the opposite sides in the row direction of the column bank **14**, a pair of repair row banks **52I** are formed at positions **A1** and **A2** spaced by a predetermined distance $2\times a$ in the column direction such that each of the repair row banks **52I** cross the two gaps **20**.

(217) In this case, in the vicinity of each of the positions **A1** and **A2** at which the repair row banks **52I** and the missing portion **3** intersect with each other, the repair row bank **52I** is formed on the upper face of the flattening layer **11c** between a pixel electrode **12** and another pixel electrode **12**. Accordingly, as described hereinabove, the height of the repair bank **52I** becomes short by an amount of a height corresponding to the thickness of the pixel electrode **12**. Further, the material of the repair bank (**52**) is liable to get wet and spread to the flattening layer **11c** and flows before it is hardened. Therefore, the repair row banks **52I** cannot sometimes be formed to a height sufficient for the dam.

(218) Further, since the repair banks **52** are made of a repair material having translucency, where the repair banks **52** are formed on the flattening layer **11c** similarly having translucency, the visibility when they are viewed in plan is not good, and the workability when the repair material is applied at the bank repair step deteriorates significantly. Therefore, the repair banks **52** are each preferably formed above a region in which the pixel electrode **12** having a light shielding property is formed.

(219) FIG. **14B** is a schematic plan view when it is assumed that, in a case where end portions in the Y direction of a missing portion **3** are positioned on upper faces of row banks **24**, two repair row banks **52J** for connecting the end portion in the Y direction of the missing portion **3** and column banks **14** on the opposite sides in the X direction of the column bank **14** having the missing portion **3** to each other are formed on each of the upper faces of the row banks **24**.

(220) In this case, since both the repair row banks **52J** and the row banks **24** are made of organic materials, they are high in affinity as described above, and the material of the repair row banks (**52**) is liable to get wet and spread on the row banks **24**. Therefore, the repair row banks **52X** cannot sometimes be formed to a height sufficient for the dam.

(221) Further, since contact holes **2** are formed within the range of the row banks **24** as viewed in plan, the repair row banks **52J** are formed such that they pass above the contact holes **2**. Therefore, a recessed portion of a depth corresponding to the thickness of approximately 4 μm of the flattening layer **11c** is formed on the upper face of each of the repair row banks **52J** as described hereinabove, and it is difficult to secure a height necessary for the dam.

(222) In contrast, by forming the repair row banks **52X** above the pixel electrodes **12** as depicted in FIG. **4B**, the height of the repair row banks **52X** necessary for the dam can be secured.

(223) The display panel **100** is configured such that part of each of the repair column banks **52Y** is formed on the upper face of a row bank **24**. However, in the display panel **100**, since the repair column banks **52Y** are formed avoiding positions above the contact holes **2**, there is no decrease of the height arising from the contact holes **2**. Further, since the repair column banks **52Y** are individually connected, for example, at an end portion thereof in the Y direction, to the repair row banks **52X** formed above the column banks **14** and the pixel electrodes **12** as depicted in FIG. **10B** and FIG. **11B**, even where the affinity of the material with the upper faces of the row banks **24** is high, it can be suppressed that the material of the repair column banks **52Y** gets wet and spreads on the row banks **24**. Therefore, in the display panel **100**, even where the repair column banks **52Y** are formed on the upper faces of row banks **24**, a height necessary for the dam can be secured, and flowing out of ink can be suppressed.

(224) <Advantageous Effects of Display Panel **100**>

(225) Now, spreading of an ink color mixture region is described through comparison between the display panel **100** according to the embodiment and a display panel of a comparative example.

(226) FIG. **15** is a schematic plan view depicting a state in which an ink layer is formed on the display panel **100**. FIG. **15** is a plan view depicting a state in which, after pairs of repair banks **52** are formed in the vicinity of a column bank **14** having a missing portion **3** in the display panel **100** according to the present embodiment, an ink layer **15a** (R) is formed by applying an ink of an emission color of red to one gap **20** (R) adjacent to the column bank **14** and an ink layer **15a** (G) is formed by applying an ink of an emission color of green to the other gap **20** (G). FIG. **16** is a plan view depicting a state in which, in the display panel according to the comparative example depicted in FIG. **14B**, an ink layer **15a** (R) is formed in a gap **20** (R) and an ink layer **15a** (G) is formed in another gap **20** (G) similarly, the gaps being adjacent each other across the column bank **14**.

(227) In the comparative example, as depicted in FIG. **16**, the repair banks **52** and the column bank **14** are not connected to each other owing to the missing portion **3**, and a dam by the repair banks **52** is not formed. Therefore, a color mixture region formed by mixture of a red ink applied to the gap **20** (R) and a green ink applied to the gap **20** (G) through the missing portion **3** flows out passing through gaps between the repair banks **52** and the column bank **14** (FL1, FL2), and in the gap **20** (R) and the gap (G), the red ink and the green ink mix with each other and spread in the Y direction. This color mixture region extends long in the Y direction along the gaps **20**, and the length thereof sometimes becomes approximately several centimeters. Then, in the display panel **100** manufactured in this manner, in such a color mixture region, light is emitted in an emission color different from the original emission color. It is to be noted that, where a color filter is installed, since a surplus color is cut, an original emission color is observed. However, the luminance of the light after passing through the color filter sometimes drops. Further, in the color mixture region, the film thickness of the light emitting layer after manufacture sometimes becomes different from a desired one, and a light emission efficiency and a voltage sometimes change from desired ones.

(228) In contrast, in the display panel **100**, as depicted in FIG. **15**, in the gap **20** (R) to which a red ink is applied, of the gaps **20** on the opposite sides of a column bank **14** having a missing portion **3**, a pair of repair banks **52** are formed, and the opposite ends of the repair banks **52** are connected to the column banks **14** on the opposite sides in the X direction to form a pair of dams **501** and **502** opposing to each other in the Y direction. Meanwhile, a pair of repair banks **52** are formed in the

gap **20** (G) to which a green ink is applied, and the opposite ends of the repair banks **52** are connected to the column banks **14** on the opposite sides in the X direction to form dams **501** and **502** similarly. By the pair of dams **501** and **502** opposing to each other in the Y direction, the gaps **20** are partitioned into a first space SA formed from a space portion adjacent to the missing portion **3** and two second spaces SB formed from space portions that are not adjacent to the missing portion **3**. Therefore, as depicted in FIG. **15**, even if a color mixture region is formed in the first space SA, the color mixture region does not spread to the second spaces SB beyond the repair banks **52**. In other words, the color mixture region is restricted to a range of subpixels whose position in the Y direction is same, at least at part thereof, as that of the missing portion **3**, and deterioration of the display quality or occurrence of a phenomenon caused by color mixture such as emission of light of an emission color different from the original emission color, drop in luminance after passing through a color filter, or change of a light emission efficiency or a voltage from a desired one can be restricted to the range of subpixels that overlap, at least at part thereof, the missing portion **3** in the Y direction.

(229) As described above, with the display panel **100** and the method for manufacturing the display panel **100** according to the embodiment, when part of an elongated bank is missing in a manufacturing process, the range of subpixels whose display quality is deteriorated by such missing in a completed organic EL display panel can be restricted to subpixels including pixel electrodes whose position in the column direction is same, at least at part thereof, as that of the missing portion. Further, in a case where part of a bank is missing and an end portion in the Y direction of the missing portion **3** is positioned on the upper face of a row bank **24**, the range of subpixels whose display quality is deteriorated by the missing can be restricted.

(230) <Modifications>

(231) While the display panel **100** according to the embodiment has been described, the present disclosure is not at all restricted to the embodiment described above except essential characteristic components of the same. For example, also modes obtained by applying various modifications conceivable by those skilled in the art to the embodiment and modes implemented by combining the components and the functions in embodiments in a desired manner without departing from the subject matter of the present invention are included in the present disclosure. In the following, as examples of such modes as just described, modifications of the display panel **100** are described.

(232) <Modification 1>

(233) While, in the embodiment described above, the position at which a repair bank **52** is formed is a position above the pixel electrode **12**, such a configuration may be adopted that, in addition to the repair column banks **52Y** in the display panel **100** according to the embodiment, repair row banks **52** are formed on the upper face of the flattening layer **11c** between a pixel electrode **12** and another pixel electrode **12** in the vicinity of the positions A1 and A2 at which the repair row banks **521** and the missing portion **3** intersect with each other as depicted in FIG. **14**. Such a disadvantage that the height of the repair row banks **521** formed on the upper face of the flattening layer **11c** is insufficient by an amount of a height corresponding to the thickness of the pixel electrodes **12** or that the material of the repair row banks **521** is liable to get wet and spread on the flattening layer **11c** and flows before they are hardened is suppressed by the connection to the repair banks **52** formed above the pixel electrodes **12** existing nearby, and the length in the Y direction of the missing portion **3** can be reduced. As a result, in comparison with the repair banks **52** in the display panel **100**, the area of the color mixture region in subpixels can be reduced.

(234) <Other Modifications>

(235) While, in the display panel **100** according to the embodiment, three types of pixels are used including red pixels, green pixels, and blue pixels, the present invention is not restricted to this. For example, only one type of a light emitting layer may be used, or four types of light emitting layers for light emission of red, green, blue, and yellow may be used.

(236) Further, while the embodiment described above is configured such that the hole injection

layer **13**, the organic light emitting layer **15**, and the electron transport layer **16** exist between the pixel electrodes **12** and the common electrode **17**, the present invention is not limited to this. For example, such a configuration may be used that only the organic light emitting layer **15** exists between the pixel electrodes **12** and the common electrode **17**. Also such a configuration that a hole injection layer, a hole transport layer, an electron transport layer, an electron injection layer, and the like are provided in addition to the light emitting layers or a configuration including a plurality of ones of or all of them simultaneously may be adopted. Further, the layers mentioned need not all be configured from organic compounds but may be configured from inorganic materials.

(237) While, in the description of the embodiment and modifications, bank repair methods and bank forms are described taking an organic EL panel of the top emission type as an example, the bank repair methods and the bank forms can be applied also to an organic EL panel of the bottom emission type.

(238) While, in the description of the embodiment and the modifications, bank repair methods and bank forms are described taking an organic EL display panel as an example, the display panel is not limited to an organic EL display panel as long as it is of the type in which a self-luminous layer is formed by a wet method in a line bank structure. For example, the present disclosure can be applied also to a case in which the display panel is formed by a wet method in a line bank structure using a solvent in which electroluminescence quantum dot is dispersed, and similar advantageous effects are achieved.

(239) <<Supplement>>

(240) Any of the embodiments described above indicates a preferred particular example of the present invention. Numerical values, shapes, materials, components, locations, and connection forms of the components, steps, orders of the steps, and so forth indicated by the embodiments are exemplary and are not intended to limit the present invention. Further, steps that are included in the embodiments but not described in independent claims that indicate top concepts of the present invention are described as optional components that constitute more preferable modes.

(241) Further, the order in which the steps are executed is exemplary for particular description of the present invention, and an order different from the described order may be applicable. Further, part of the steps may be executed simultaneously with (in parallel to) a different step.

(242) Further, in order to facilitate understandings of the invention, the scale of components in the figures to which the embodiments refer is sometimes different from an actual one. Further, the present invention shall not be restricted by the foregoing description of the embodiments and can be altered suitably without departing from the subject matter of the present invention.

(243) Further, at least part of the functions of the embodiments and the modifications may be combined.

(244) Furthermore, also various modifications in which a change within a range conceived by those skilled in the art is applied to the present embodiments are included in the present invention.

INDUSTRIAL APPLICABILITY

(245) The present disclosure can be utilized, for example, in organic EL display panels and organic EL display apparatuses that are used as various display apparatuses for home use, for use in public facilities, or for business use, television apparatuses, displays for portable electronic equipment, and so forth.

REFERENCE SIGNS LIST

(246) **1**: Organic EL display apparatus **3**: Missing portion **10**: Organic EL element **11**: Base substrate **14**, **14a**: Column bank **15**: Organic light emitting layer **20**: Gap **24**, **24a**: Row bank **52**: Repair bank **52X**: Repair row bank **52Y**: Repair column bank **501**, **502**: Dam **100**: Display panel **200**: Repair apparatus **213**: Needle dispenser

Claims

1. A method for manufacturing an organic electro luminescence display panel, comprising: a step of preparing a substrate; a step of arranging a plurality of pixel electrodes in a matrix on an upper face of the substrate; a step of forming, between the plurality of pixel electrodes adjacent to each other at least in a row direction on the substrate, a plurality of elongated column banks extending in a column direction and formed in parallel to each other; a step of detecting a missing portion at which part of a column bank of the plurality of elongated column banks does not exist; a step of forming, above the plurality of pixel electrodes, a pair of repair banks in each of two gaps between the column bank of the plurality of elongated column banks in which the missing portion has been detected and column banks adjacent on opposite sides in the row direction of the column bank, wherein the pair of repair banks are not connected with the column bank, the pair of repair banks are connected with row banks of a plurality of elongated row banks, each repair bank of the pair of repair banks is L-shaped, and a first side of the L-shaped repair bank is parallel to the plurality of elongated column banks and a second side of the L-shaped repair bank is parallel to the plurality of elongated row banks; a step of forming a light emitting layer by applying a first ink that contains an organic light emitting material to each of the gaps between the plurality of elongated column banks; and a step of forming a common electrode above the light emitting layer, wherein the step of forming the pair of repair banks includes a first step of forming the pair of repair row banks at positions spaced by at least a predetermined distance in the column direction above the plurality of pixel electrodes that exist in the two gaps and whose positions in the column direction are same, at least at part thereof, as that of the missing portion, and a second step of forming repair column banks that connect, in the column direction, an end portion of each of the pair of repair row banks that are not connected in the row direction to the column bank that has the missing portion to a closest portion of the column bank.
2. The method for manufacturing the organic electro luminescence display panel according to claim 1, wherein, at the first step, the pair of repair row banks are formed at positions at which the predetermined distance in the column direction is maximum.
3. The method for manufacturing the organic electro luminescence display panel according to claim 1, wherein, at the step of forming the light emitting layer, of the first ink applied into a first gap of the two gaps, a second ink applied to a range sandwiched by the pair of repair row banks flows out through the missing portion into a second gap of the two gaps opposing in the row direction across the missing portion but is blocked within the range in the column direction by the pair of repair row banks.
4. The method for manufacturing the organic electro luminescence display panel according to claim 1, further comprising: a step of forming, between the plurality of pixel electrodes that are adjacent to each other at least in the column direction on the substrate, the plurality of elongated row banks extending in the row direction and formed in parallel to each other, wherein opposite ends of the missing portion in the column bank that has the missing portion are each positioned on an upper face of one row bank of the plurality of elongated row banks.
5. The method for manufacturing the organic electro luminescence display panel according to claim 4, further comprising: a step of forming, at portions of the plurality of pixel electrodes positioned below the plurality of elongated row banks, a contact hole at which part of a surface of at least one pixel electrode of the plurality of pixel electrodes is recessed, wherein the repair column banks are formed at positions at which the repair column banks do not overlap the contact holes as viewed in plan.
6. An organic electro luminescence display panel, comprising: a substrate; a plurality of pixel electrodes arranged in a matrix on an upper face of the substrate; a plurality of elongated column banks that extends in a column direction and are formed in parallel to each other between the plurality of pixel electrodes adjacent to each other at least in a row direction on the substrate; a missing portion at which part of a column bank of the plurality of elongated column banks does not

exist; a pair of repair banks formed, above the plurality of pixel electrodes, in each of two gaps between the column bank of the plurality of elongated column banks that has the missing portion and column banks adjacent on opposite sides in the row direction of the column bank, wherein the pair of repair banks are not connected with the column bank, the pair of repair banks are connected with row banks of a plurality of elongated row banks, each repair bank of the pair of repair banks is L-shaped, and a first side of the L-shaped repair bank is parallel to the plurality of elongated column banks and a second side of the L-shaped repair bank is parallel to the plurality of elongated row banks; a light emitting layer composed of an application film formed in each of the gaps between the plurality of elongated column banks; and a common electrode provided above the light emitting layer, wherein the repair banks include a pair of repair row banks formed at positions spaced by at least a predetermined distance in the column direction above the plurality of pixel electrodes that exist in the two gaps and whose positions in the column direction are same, at least at part thereof, as that of the missing portion, and repair column banks that connect, in the column direction, an end portion of each of the pair of repair row banks that are not connected in the row direction to the column bank that has the missing portion to a closest portion of the column bank.

7. The organic electro luminescence display panel according to claim 6, wherein the pair of repair row banks are formed at positions at which the predetermined distance in the column direction is maximum.

8. The organic electro luminescence display panel according to claim 6, wherein, of the light emitting layer formed in a first gap of the two gaps, a portion that is formed in a range sandwiched by the pair of repair row banks contains an organic light emitting material that is contained in the light emitting layer formed in a second gap of the two gaps which opposes the row direction across the missing portion, and a portion that is formed outside the range sandwiched by the pair of repair row banks does not contain the organic light emitting material that is contained in the light emitting layer formed in the second gap.

9. The organic electro luminescence display panel according to claim 6, further comprising: a plurality of elongated row banks that extends in the row direction and are formed in parallel to each other between the plurality of pixel electrodes adjacent to each other at least in the column direction on the substrate, wherein opposite ends of the missing portion in the column bank that has the missing portion are each positioned on an upper face of one row bank of the plurality of elongated row banks.

10. The organic electro luminescence display panel according to claim 9, wherein at portions of the plurality of pixel electrodes positioned below the plurality of elongated row banks, a contact hole at which part of a surface of at least one pixel electrode of the plurality of pixel electrodes is recessed is provided, and the repair column banks are formed at positions at which the repair column banks do not overlap the contact holes as viewed in plan.
