

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12411197
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Liu; I-Ru et al.

Direction finding antenna

Abstract

A direction finding antenna includes a substrate, a reflecting ring, and a plurality of radiating elements, wherein the substrate has a surface. The reflecting ring is disposed on the surface of the substrate and is formed by connecting a plurality of side wires and is a closed polygon. Each of the side wires forms a reflector. The radiating elements are disposed on the surface of the substrate and are respectively located on an outside of the side wires, and each of the radiating elements corresponds to one of the side wires. Each of the side wires and each of the corresponding radiating elements form an antenna structure, and the antenna structures face different directions, thereby providing the needed accuracy of direction finding in different directions.

Inventors:	Liu; I-Ru (Hsinchu, TW), Kuo; Chun-Yi (Hsinchu, TW)
Applicant:	ACCTON TECHNOLOGY CORPORATION (Hsinchu, TW)
Family ID:	84282902
Assignee:	ACCTON TECHNOLOGY CORPORATION (Hsinchu, TW)
Appl. No.:	18/096152
Filed:	January 12, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240036144 A1	Feb. 01, 2024

Foreign Application Priority Data

CN	202221933678.1	Jul. 26, 2022
----	----------------	---------------

Publication Classification

Int. Cl.: G01S3/02 (20060101); G01S3/04 (20060101); G01S3/12 (20060101); G01S3/72 (20060101); H01Q19/10 (20060101)

U.S. Cl.:

CPC G01S3/043 (20130101); G01S3/12 (20130101); G01S3/72 (20130101); H01Q19/10 (20130101)

Field of Classification Search

CPC: G01S (3/043); G01S (3/12); G01S (3/00); G01S (3/72); H01Q (9/06); H01Q (9/285); H01Q (19/10)

USPC: 342/417; 342/419

References Cited

U.S. PATENT DOCUMENTS				
Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9082307	12/2014	Sharawi	N/A	H01Q 9/16
10938105	12/2020	Snyder	N/A	H01Q 19/193
11271319	12/2021	Celik	N/A	H01Q 1/38
2016/0164182	12/2015	Lai	216/13	H01Q 21/0006
2024/0377494	12/2023	Vale	N/A	H01Q 21/20
2024/0380108	12/2023	Chen	N/A	H01Q 21/205
FOREIGN PATENT DOCUMENTS				
Patent No.	Application Date	Country	CPC	
102055072	12/2013	CN	H01Q 1/36	
110854505	12/2019	CN	H01Q 19/06	
213753050	12/2020	CN	H01Q 1/38	
2331185	12/1998	GB	H01Q 19/062	
WO-2020041858	12/2019	WO	H01Q 21/29	

Primary Examiner: Nguyen; Chuong P

Attorney, Agent or Firm: Birch, Stewart, Kolasch & Birch, LLP

Background/Summary

BACKGROUND OF THE INVENTION

Technical Field

(1) The present disclosure relates generally to an antenna, and more particularly to a direction finding antenna.

Description of Related Art

(2) With the advance of the wireless communication, the use of mobile electronic devices increases gradually. In order to position a mobile device in a space as the mobile electronic devices are moving, there are many technologies have been developed, for example, to estimate a distance between the mobile device and a positioning device by using the Received Signal Strength

Indicator (RSSI).

(3) However, only acknowledging the distance between the mobile device and the positioning device is still not accurate for some positioning uses. For example, in property management, typically a Bluetooth device, such as a smart tag, is disposed on an object. The positioning device could only estimate the distance between the mobile device and the positioning device. In view of a user, the user could only acknowledge a distance between the user and the object, but not a direction of the object relative to the user.

(4) Therefore, Direction Finding technology has been developed. For example, a plurality of antennas receives a wireless signal of a targeted mobile device, and a direction of the targeted mobile device relative to each of the antennas could be determined through the wireless signal received by each of the antennas. Alternatively, a plurality of antennas sends a wireless signal to the mobile device, and a position of the mobile device relative to each of the antennas could be determined by the mobile device. However, as direction finding technology requires a plurality of antennas, a directivity of each of the antennas is needed to be large and the structure of each of the antennas is complex, thereby occupying a large space.

BRIEF SUMMARY OF THE INVENTION

(5) In view of the above, the primary objective of the present disclosure is to provide a direction finding antenna having a good accuracy of direction finding.

(6) Another primary objective of the present disclosure is to provide a direction finding antenna conducive to miniaturization.

(7) The present disclosure provides a direction finding antenna, including a substrate, a reflecting ring, and a plurality of radiating elements, wherein the substrate has a surface. The reflecting ring is disposed on the surface of the substrate, wherein the reflecting ring is formed by connecting a plurality of side wires and is a closed polygon. The radiating elements are disposed on the surface of the substrate and located on an outside of the side wires respectively and correspondingly. Each of the radiating elements corresponds to one of the side wires.

(8) The present disclosure further provides a direction finding antenna including a substrate and a plurality of antenna structures, wherein the substrate has a surface. The antenna structures are disposed on the surface of the substrate and respectively face to different directions, wherein each of the antenna structures includes a reflector and a radiating element. The reflectors are connected together to form a closed polygon, and the radiating elements are respectively and correspondingly located on an outside of one of the reflectors.

(9) With the aforementioned design, the reflecting ring has the structure of the continuous and closed polygon, and each of the side wires serves as a reflector to reflect a signal sent by each of the radiating elements, increasing a directivity of each of the antennas and improving the accuracy of direction finding. Besides, the structure of the direction finding antenna of the present disclosure is simple and conducive to miniaturization.

Description

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWINGS

(1) The present disclosure will be best understood by referring to the following detailed description of some illustrative embodiments in conjunction with the accompanying drawings, in which

(2) FIG. 1 is a perspective view of the direction finding antenna according to a first embodiment of the present disclosure;

(3) FIG. 2 is a top view of the direction finding antenna according to the first embodiment of the present disclosure;

(4) FIG. 3A is a schematic view of the antenna structure ANT1 according to the first embodiment of the present disclosure;

- (5) FIG. 3B is similar to FIG. 3A, showing the distances D1 to D3, the lengths L1 to L5, and the widths W1 to W5 of the antenna structure ANT1 according to the first embodiment of the present disclosure;
- (6) FIG. 4A is a schematic view showing a return loss of each of the antenna structures ANT1 to ANT4 of the direction finding antenna according to the first embodiment of the present disclosure;
- (7) FIG. 4B is a schematic view showing a return loss of each of the antenna structures ANT5 to ANT8 of the direction finding antenna according to the first embodiment of the present disclosure;
- (8) FIG. 5 is a schematic view showing a radiation pattern of the antenna structure ANT1 operating at 2.45 GHz according to the first embodiment of the present disclosure;
- (9) FIG. 6 is a schematic view showing a radiation pattern of the antenna structure ANT2 operating at 2.45 GHz according to the first embodiment of the present disclosure;
- (10) FIG. 7 is a schematic view showing a radiation pattern of the antenna structure ANT3 operating at 2.45 GHz according to the first embodiment of the present disclosure;
- (11) FIG. 8 is a schematic view showing a radiation pattern of the antenna structure ANT4 operating at 2.45 GHz according to the first embodiment of the present disclosure;
- (12) FIG. 9 is a schematic view showing a radiation pattern of the antenna structure ANT5 operating at 2.45 GHz according to the first embodiment of the present disclosure;
- (13) FIG. 10 is a schematic view showing a radiation pattern of the antenna structure ANT6 operating at 2.45 GHz according to the first embodiment of the present disclosure;
- (14) FIG. 11 is a schematic view showing a radiation pattern of the antenna structure ANT7 operating at 2.45 GHz according to the first embodiment of the present disclosure;
- (15) FIG. 12 is a schematic view showing a radiation pattern of the antenna structure ANT8 operating at 2.45 GHz according to the first embodiment of the present disclosure;
- (16) FIG. 13 is a schematic view showing a current distribution of each of the antenna structures ANT1 to ANT8 according to the first embodiment of the present disclosure;
- (17) FIG. 14 is a top view of the direction finding antenna according to a first comparative example of the present disclosure;
- (18) FIG. 15 is a schematic view showing a radiation pattern of the antenna structure ANT1' operating at 2.45 GHz according to the first comparative example of the present disclosure;
- (19) FIG. 16 is a schematic view showing a current distribution of the antenna structure ANT8 according to the first embodiment of the present disclosure and a current distribution of the antenna structure ANT8' according to the first comparative example of the present disclosure;
- (20) FIG. 17 is a top view of the direction finding antenna according to a second embodiment of the present disclosure;
- (21) FIG. 18 is a top view of the direction finding antenna according to a second comparative example of the present disclosure;
- (22) FIG. 19 is a schematic view showing a radiation pattern of the antenna structure ANT1 operating at 2.45 GHz according to the second embodiment of the present disclosure and the antenna structure ANT1' operating at 2.45 GHz according to the second comparative example of the present disclosure;
- (23) FIG. 20 is a schematic view showing a current distribution of the antenna structure ANT6 according to the second embodiment of the present disclosure and a current distribution of the antenna structure ANT6' according to the second comparative example of the present disclosure;
- and
- (24) FIG. 21 is a top view of the direction finding antenna according to a third embodiment of the present disclosure.

DETAILED DESCRIPTION OF THE INVENTION

(25) A direction finding antenna 1 according to a first embodiment of the present disclosure is illustrated in FIG. 1 to FIG. 3B and is a printed microstrip antenna including a substrate 10, a reflecting ring 20, and a plurality of radiating elements 30.

(26) The substrate **10** has a surface **12**. In the current embodiment, the substrate **10** is a square substrate, wherein a length of the substrate **10** is, but not limited to, 180 mm and a width of the substrate **10** is, but not limited to, 180 mm. The substrate **10** could be made of, but not limited to, a glass fiber filled EPOXY sheet, a ceramic filled PTFE sheet, a hydrocarbon/ceramic sheet, a Bakelite, or glass fibers.

(27) The reflecting ring **20** is disposed on the surface **12** of the substrate **10** and is a metal lead wire disposed on the surface **12** of the substrate **10**. The reflecting ring **20** is formed by connecting a plurality of side wires **22** and is a closed polygon. In other words, the side wires **22** are connected to form the reflecting ring **20** which is a closed polygon. A length of each of the side wires **22** is identical, and two opposite ends of each of the side wires **22** in an extending direction of each of the side wires **22** are respectively connected to other two of the side wires **22**. Each of the side wires **22** forms a reflector adapted to reflect a wireless signal, thereby a length of the side wire **22** in the longitudinal direction of the side wire **22** could be increased as large as possible in a limited space and the reflection effect could be enhanced. In the current embodiment, the reflecting ring **20** is, but not limited to, an octagon. In other embodiments, the reflecting ring **20** could be a triangle, a quadrilateral, a pentagon, or a polygon with more than five sides. Preferably, the reflecting ring **20** is a closed regular polygon.

(28) Referring to FIG. 3B, in the current embodiment, a width W1 of each of the side wires **22** is 3 mm as an example, and a length L1 of an outer edge of each of the side wires **22** is 61 mm as an example.

(29) The radiating elements **30** are disposed on the surface **12** of the substrate **10**, wherein each of the radiating elements **30** is correspondingly located on an outside of one of the side wires **22**. For example, each of the radiating elements **30** could be a metal lead wire disposed on the surface **12** of the substrate **10**. Each of the radiating elements **30** corresponds to one of the side wires **22** and is adapted to transmit or receive a wireless signal in an orientation correspondingly. Each of the radiating elements **30** could be also called a driver. In the current embodiment, each of the radiating elements **30** makes use of a dipole antenna structure.

(30) In the current embodiment, each of the side wires **22** and each of the radiating elements **30** of the direction finding antenna **1** jointly form a plurality of antenna structures ANT1 to ANT8 facing different directions. In order to illustrate easily, the description below would only describe the radiating element **30** and the side wire **22** of the antenna structure ANT1 as an example, for the antenna structures ANT1 to ANT8 have substantially the same configurations.

(31) As shown in FIG. 3A and FIG. 3B, the radiating element **30** includes a first radiator **32** and a second radiator **34** that are spaced, wherein the first radiator **32** has a first main section **322** and a first side section **324**, and the second radiator **34** has a second main section **342** and a second side section **344**. The first main section **322** and the second main section **342** are respectively a rectangular shape, wherein both a width W2 of the first main section **322** and a width W2 of the second main section **342** are 2 mm as an example, and both a length L2 of the first main section **322** and a length L2 of the second main section **342** are 18.5 mm as an example. Both a longitudinal direction of the first main section **322** and a longitudinal direction of the second main section **342** are located on an axis i that is parallel to the extending direction of the corresponding side wire **22** of the reflecting ring **20**. The first main section **322** has a first end **322a** and a second end **322b** in the longitudinal direction of the first main section **322**. The second main section **342** has a first end **342a** and a second end **342b** in the longitudinal direction of the second main section **342**. The first end **322a** of the first main section **322** and the first end **342a** of the second main section **342** are adjacent and spaced by a distance D1 without contact. In the current embodiment, the distance D1 is 1 mm as an example. The first side section **324** is connected to the second end **322b** of the first main section **322**, and the second side section **344** is connected to the second end **342b** of the second main section **342**. The first side section **324** and the second side section **344** bend and extend along a direction deviating from the axis i, thereby fulfilling an equivalent antenna

length through bending. In the current embodiment the extending direction of the first side section **324** and the extending direction of the second side section **344** are perpendicular or substantially perpendicular to the axis *i*, and the first side section **324** and the second side section **344** extend towards the corresponding side wire **22**. In other words, an outer end of the first radiator **32** and an outer end of the second radiator **34** bend towards the corresponding side wire **22** (i.e., bend inwards), thereby to fulfill the purpose of the miniaturization of the direction finding antenna **1**. In the current embodiment, both a width **W3** of the first side section **324** and a width **W3** of the second side section **344** are 1.5 mm as an example, and both a length **L3** of the first side section **324** and a length **L3** of the second side section **344** are 3.25 mm as an example. The first side section **324** and the second side section **344** are adapted to increase a total length of the first radiator **32** and the second radiator **34**, thereby increasing a length of a current path.

(32) In the current embodiment, the first radiator **32** further includes a third side section **326** that is connected to the first end **322a** of the first radiator **32** and extends towards the side wire **22**. A width **W4** of the third side section **326** is 1.5 mm as an example (i.e., equal to the width **W3** of the first side section **324** and the width **W3** of the second side section **344**), and a length **L4** of the third side section **326** is 4 mm as an example. Moreover, the first radiator **32** could further include an extending section **328** that is connected to the third side section **326** and extends to a position between the corresponding first end **342a** of the second main section **342** and the side wire **22**. A width **W5** of the extending section **328** is 2 mm as an example (i.e., equal to the width **W2** of the first main section **322** and the width **W2** of the second main section **342**), and a length **L5** of the extending section **328** is 4 mm as an example. A part of a projection area of the extending section **328** projecting along a direction perpendicular to the axis *i* overlaps with a part of the first main section **322**, wherein an overlapping length in the direction parallel to the axis *i* is about 3 mm, and a distance **D2** in the direction perpendicular to the axis *i* spaced between the part of the extending section **328** overlapping with the first main section **322** and the first main section **322** is 2 mm.

(33) In the current embodiment, both a distance **D3** between an outer edge of the side wire **22** and an inner edge of the first main section **322** and a distance **D3** of the outer edge of the side wire **22** and an inner edge of the second main section **342** are about 13 mm.

(34) The surface **12** of the substrate **10** on a side of the radiating element **30** away from the side wire **22**, i.e., a space between an outer edge of the first main section **322** and a side edge **14** of the substrate **10** and a space between an outer edge of the second main section **342** and the side edge **14** of the substrate **10**, does not have other functional antenna elements, such as a director of a Yagi antenna. Conventional Yagi antennas are constructed of a reflector, a driven member, and a plurality of directors, but the direction finding antenna **1** in the current embodiment does not have a director in each of the directions, thereby the direction finding antenna **1** in the current embodiment could be more compact than the conventional Yagi antennas, and hence conducive to miniaturization. Moreover, as the outer end of the first radiator **32** and the outer end of the second radiator **34** correspondingly bend towards the side wire **22**, each of the antenna structures **ANT1** to **ANT8** could be even more compact. In other embodiments, other functional antenna elements could be disposed in the space between the outer edge of the first main section **322** and the side edge **14** of the substrate **10** and the space between the outer edge of the second main section **342** and the side edge **14** of the substrate **10**, further increasing a directivity of each of the antenna structures **ANT1** to **ANT8**.

(35) An end of the extending section **328** of the first radiator **32** away from the third side section **326** and the first end **342a** of the second radiator **34** could be connected to a wireless signal control device (not shown), wherein the wireless signal control device respectively drives the plurality of radiating elements **30** to transmit a wireless signal. More specifically, signals could be fed jointly through the end of the extending section **328** of the first radiator **32** and the first end **342a** of the second radiator **34**, and could be sent jointly through the first main section **322** and the first side section **324**, and the second main section **342** and the second side section **344**. The reflecting ring

20 is connected to a ground. A part of the wireless signal transmitted by the radiating element **30** is transmitted in a corresponding direction by the reflectors formed by each of the side wires **22**. Moreover, the radiating elements **30** could receive a wireless signal come from an external electronic device (not shown) and transmit the wireless signal to the wireless signal control device, so as to determine a direction and a distance of the external electronic device relative to the direction finding antenna **1**.

(36) In an embodiment, the first radiator **32** and the second radiator **34** could be a symmetric structure (i.e., the third side section **326** and the extending section **328** are omitted), and the first end **322a** of the first radiator **32** and the first end **342a** of the second radiator **34** are connected to the wireless signal control device (i.e., the first end **322a** of the first radiator **32** and the first end **342a** of the second radiator **34** directly feed a signal).

(37) In an embodiment, the outer end of the first radiator **32** (i.e., the first side section **324**) and the outer end of the second radiator **34** (i.e., the second side section **344**) could be designed to bend in a direction away from the side wire **22**, which could fulfill the equivalent antenna length as well.

(38) Referring to FIGS. **4A** and **4B**, in two schematic views showing a return loss of each of the antenna structures **ANT1** to **ANT8** of the direction finding antenna **1** in the current embodiment, the return loss of each of the antenna structures **ANT1** to **ANT8** is less than -13 dB at 2.4 GHz frequency.

(39) Moreover, when the direction finding antenna **1** in the current embodiment operates between 2 GHz and 6 GHz frequency, the isolation among the antenna structures **ANT1** to **ANT8** is less than -20 dB.

(40) FIG. **5** to FIG. **12** respectively show a radiation pattern of the antenna structures **ANT1** to **ANT8** operating at 2.45 GHz. Table 1 is an analysis table according to the aforementioned radiation patterns and shows that a main lobe magnitude of each of the antenna structures **ANT1** to **ANT8** ranges between 5.54 dBi and 5.68 dBi, and a 3 dB-beamwidth of each of the antenna structures **ANT1** to **ANT8** ranges between 51.7 degrees and 54.6 degrees. As the 3 dB-beamwidth of each of the antenna structures **ANT1** to **ANT8** is less than 54.6 degrees, a better accuracy of direction finding could be provided, so that the direction finding antenna **1** could have a better field of view and a better angle of arrival.

(41) TABLE-US-00001 TABLE 1 the analysis table according to the radiation pattern of each of the antenna structures **ANT1** to **ANT8**

Antenna structure	ANT1	ANT2	ANT3	ANT4	ANT5	ANT6	ANT7	ANT8
Main lobe magnitude (dBi)	5.61	5.68	5.62	5.63	5.55	5.54	5.68	5.67
Main lobe direction (deg)	71	114	161	204	252	293	341	25
3 dB-beamwidth (deg)	51.7	53.7	52.9	53.3	55.6	54.6	52.6	53.8
Side lobe level (dBi)	-3.6	-4.1	-3.6	-3.9	-4.2	-4.1	-4.0	-4.2

(42) FIG. **13** is a schematic view showing a current distribution of each of the antenna structures **ANT1** to **ANT8** and clearly shows that a current distribution of the reflecting ring **20** is continuous, even the side wire **22** that is the farthest from one of the antenna structures **ANT1** to **ANT8** shows a clear current distribution.

(43) A direction finding antenna **100** according to a first comparative example of the present disclosure is shown in FIG. **14**. Compared with the direction finding antenna **1** in the current embodiment, the direction finding antenna **100** in the first comparative example does not have a closed reflecting ring **20**, but a plurality of discrete or discontinuous side wires **101**, wherein each of the side wires **101** forms a reflector of one of a plurality of antenna structures **ANT1'** to **ANT8'**.

(44) FIG. **15** is a schematic view showing a radiation pattern of the antenna structure **ANT1'** in the first comparative example and indicates that the 3 dB-beamwidth of the antenna structure **ANT1'** in the first comparative example is 93 degrees. Compared with the antenna structure **ANT1** in the current embodiment as shown in FIG. **5** in which the 3 dB-beamwidth is 51.7 degrees, the direction finding antenna **1** in the current embodiment could provide a better accuracy of direction finding than the direction finding antenna **100** in the first comparative example.

(45) FIG. **16** is a comparison of a current distribution of the antenna structure **ANT8** in the current

embodiment and a current distribution of the antenna structure ANT8' in the first comparative example and shows that the side wires 22 of the reflecting ring 20 in the current embodiment have the clear and continuous current distribution, but a current distribution of the side wires 101 in the first comparative example is not continuous, wherein the further from the antenna structure ANT8' that transmits a wireless signal the side wire 101 is, the less clear the current distribution on the side wire 101 is.

(46) As shown in the aforementioned comparison, the direction finding antenna 1 in the current embodiment could be conducive to increasing the accuracy of direction finding of each of the antenna structures ANT1 to ANT8 through the continuous current distribution formed by the closed reflecting ring 20. In other words, the direction finding antenna 1 in the current embodiment could have a better accuracy of direction finding even without using a director.

(47) A direction finding antenna 2 according to a second embodiment of the present disclosure is shown in FIG. 17, which has almost the same structure as that of the first embodiment, except that the number of the antenna structures ANT1 to ANT6 is six, and a reflecting ring 20a is a regular hexagon having six side wires 22a, wherein a length of an outer edge of each of the side wires 22a could be slightly larger or equal to the length L1 of the outer edge of the side wire 22 in the first embodiment.

(48) A direction finding antenna 200 according to a second comparative example of the present disclosure is shown in FIG. 18. Compared with the direction finding antenna 2 in the current embodiment, the direction finding antenna 200 of the second comparative example does not have a closed reflecting ring 20a, but a plurality of discrete or discontinuous side wires 201, wherein each of the side wires 201 forms a reflector of one of a plurality of antenna structures ANT1' to ANT6'.

(49) FIG. 19 is a schematic view showing a radiation pattern of the antenna structure ANT1 in the current embodiment and the antenna structure ANT1' in the second comparative example, wherein a 3 dB-beamwidth of the antenna structure ANT1 in the current embodiment is 48 degrees, and a 3 dB-beamwidth of the antenna structure ANT1' in the second comparative example is 67 degrees, thereby the direction finding antenna 2 in the current embodiment could provide a better accuracy of direction finding than the direction finding antenna 200 in the second comparative example.

(50) FIG. 20 is a comparison of a current distribution of the antenna structure ANT6 in the current embodiment and a current distribution in the antenna structure ANT6' in the second comparative example and shows that the side wires 22a of the reflecting ring 20a in the current embodiment have a clear and continuous current distribution, but a current distribution of the side wires 201 in the second comparative example is not continuous, wherein the further from the antenna structure ANT6' that transmits a wireless signal the side wire 201 is, the less clear the current distribution on the side wire 101 is.

(51) The direction finding antenna 2 in the current embodiment could similarly be conducive to increase the accuracy of direction finding of each of the antenna structures ANT1 to ANT6 through the current distribution formed by the closed reflecting ring 20a.

(52) A direction finding antenna 3 according to a third embodiment of the present disclosure is shown in FIG. 21, which has almost the same structure as that of the first embodiment, except that the number of the antenna structures ANT1 to ANT4 is four, and a reflecting ring 20b is a regular quadrilateral having four side wires 22b, wherein each of the antenna structures ANT1 to ANT4 faces different directions. The direction finding antenna 3 in the current embodiment has the advantages as the same as that of the aforementioned embodiments, thereby the advantages are not stated again.

(53) With the aforementioned design, the direction finding antenna of the present disclosure could effectively increase the accuracy of direction finding through the closed reflecting ring, and could be conducive to miniaturization of the direction finding antenna through the simple structure of the direction finding antenna of the present disclosure.

(54) It must be pointed out that the embodiments described above are only some preferred

embodiments of the present disclosure. All equivalent structures which employ the concepts disclosed in this specification and the appended claims should fall within the scope of the present disclosure.

Claims

1. A direction finding antenna, comprising: a substrate having a surface; a reflecting ring disposed on the surface of the substrate, wherein the reflecting ring is formed by connecting a plurality of side wires and is a closed polygon; and a plurality of radiating elements disposed on the surface of the substrate and located on an outside of the side wires respectively and correspondingly, wherein the substrate is made of a glass fiber filled EPOXY sheet, a ceramic filled PTFE sheet, a hydrocarbon/ceramic sheet, a Bakelite, or glass fibers, wherein the reflecting ring is a metal lead wire disposed on the surface of the substrate; a length of each of the side wires of the reflecting ring is identical and the reflecting ring forms a closed regular polygon, and wherein the radiating elements have the same configurations; each of the radiating elements is a metal lead wire disposed on the surface of the substrate.
2. The direction finding antenna as claimed in claim 1, wherein a number of the side wires is four or more.
3. The direction finding antenna as claimed in claim 1, wherein each of the radiating elements is a dipole antenna and comprises a first radiator and a second radiator that are spaced; the first radiator has a first main section and a first side section, and the second radiator has a second main section and a second side section; the first main section and the second main section are respectively a rectangular shape extending along an axis and being correspondingly parallel to one of the side wire; the first main section has a first end and a second end in a longitudinal direction of the first main section, and the second main section has a first end and a second end in a longitudinal direction of the second main section, wherein the first end of the first main section and the first end of the second main section are adjacent and spaced by a distance; the first side section is connected to the second end of the first main section, and the second side section is connected to the second end of the second main section; each of the first side sections and each of the second side sections of each of the radiating elements extend correspondingly towards one of the side wires.
4. The direction finding antenna as claimed in claim 3, wherein each of the first radiators further comprises a third side section and an extending section, and the third side section is correspondingly connected to the first end of the first main section and correspondingly extends towards one of the side wires; the extending section is connected to the third side section and extends correspondingly to a position between the first end of the second main section and one of the side wires.
5. A direction finding antenna, comprising: a substrate having a surface; a plurality of antenna structures disposed on the surface of the substrate and respectively facing to different directions, wherein each of the antenna structures comprises a reflector and a radiating element; the reflectors are connected to form a closed polygon, and the radiating elements are respectively and correspondingly located on an outside of the reflectors, wherein the substrate is made of a glass fiber filled EPOXY sheet, a ceramic filled PTFE sheet, a hydrocarbon/ceramic sheet, a Bakelite, or glass fibers, wherein the reflectors form a closed regular polygon; each of the reflectors is a metallic side wire disposed on the surface of the substrate; a length of each of the side wires is identical, and two opposite ends of each of the side wires in an extending direction of each of the side wires are respectively connected to other two of the side wires, and wherein the radiating elements have the same configurations; each of the radiating elements is a metal lead wire disposed on the surface of the substrate.
6. The direction finding antenna as claimed in claim 5, wherein a number of the reflectors is four or more.

7. The direction finding antenna as claimed in claim 5, wherein each of the radiating elements is a dipole antenna and comprises a first radiator and a second radiator that are spaced; the first radiator has a first main section and a first side section, and the second radiator has a second main section and a second side section; the first main section and the second main section are respectively a rectangular shape and extend along an axis and are correspondingly parallel to one of the reflector; the first main section has a first end and a second end in a longitudinal direction of the first main section, and the second main section has a first end and a second end in a longitudinal direction of the second main section, wherein the first end of the first main section and the first end of the second main section are adjacent and are spaced by a distance; the first side section is connected to the second end of the first main section, and the second side section is connected to the second end of the second main section; each of the first side sections and each of the second side sections of each of the radiating elements extend correspondingly towards one of the side wires.

8. The direction finding antenna as claimed in claim 7, wherein each of the first radiators further comprises a third side section and an extending section, and the third side section is correspondingly connected to the first end of the first main section and extends correspondingly towards one of the side wires; the extending section is connected to the third side section and extends correspondingly to a position between the first end of the second main section and the reflector.
