

# US Patent & Trademark Office

## Patent Public Search | Text View

---

United States Patent

12414329

Kind Code

B2

Date of Patent

September 09, 2025

Inventor(s)

Chen; Chia-Wei et al.

---

### Forming low-resistance capping layer over metal gate electrode

---

#### Abstract

A semiconductor device includes stacks of nano-structures that each extend in a first horizontal direction. The stacks each extend in a vertical direction and are separated from one another in a second horizontal direction. A first gate is disposed over a first subset of the stacks. A second gate is disposed over a second subset of the stacks. A first conductive capping layer is disposed over a substantial entirety of an upper surface of the first gate. A second conductive capping layer is disposed over a substantial entirety of an upper surface of the second gate. A dielectric structure is disposed between the first gate and the second gate in the second horizontal direction. The dielectric structure physically and electrically separates the first gate and the second gate. An upper surface of the dielectric structure is substantially free of having the first or second conductive capping layers disposed thereon.

---

**Inventors:** Chen; Chia-Wei (Hsinchu, TW), Hsu; Wei Cheng (Hsinchu, TW), Chen; Hui-Chi (Hsinchu County, TW), Chen; Jian-Hao (Hsinchu, TW), Yu; Kuo-Feng (Hsinchu County, TW), Chiu; Shih-Hang (Taichung, TW), Wang; Wei-Cheng (Hsinchu, TW), Chen; Yen-Ju (Hsinchu, TW), Cheng; Chun-Chih (Changhua County, TW)

**Applicant:** Taiwan Semiconductor Manufacturing Company, Ltd. (Hsin-Chu, TW)

**Family ID:** 84314754

**Assignee:** TAIWAN SEMICONDUCTOR MANUFACTURING COMPANY, LTD.  
(Hsinchu, TW)

**Appl. No.:** 17/737851

**Filed:** May 05, 2022

#### Prior Publication Data

**Document Identifier**

US 20230010952 A1

**Publication Date**

Jan. 12, 2023

Related U.S. Application Data

us-provisional-application US 63220164 20210709

Publication Classification

Int. Cl.: H01L23/00 (20060101); H10D30/01 (20250101); H10D30/67 (20250101); H10D62/10 (20250101); H10D64/01 (20250101)

U.S. Cl.:

CPC H10D30/6735 (20250101); H10D30/031 (20250101); H10D30/6729 (20250101); H10D30/6739 (20250101); H10D30/6757 (20250101); H10D62/118 (20250101); H10D64/01 (20250101);

Field of Classification Search

CPC: H10D (30/6735); H10D (30/031); H10D (30/6729); H10D (30/6739); H10D (30/6757); H10D (62/118); H10D (64/01); H10D (62/121)

References Cited

U.S. PATENT DOCUMENTS

| Patent No.   | Issued Date | Patentee Name | U.S. Cl. | CPC          |
|--------------|-------------|---------------|----------|--------------|
| 8487378      | 12/2012     | Goto et al.   | N/A      | N/A          |
| 8729634      | 12/2013     | Shen et al.   | N/A      | N/A          |
| 8826213      | 12/2013     | Ho et al.     | N/A      | N/A          |
| 8887106      | 12/2013     | Ho et al.     | N/A      | N/A          |
| 9991352      | 12/2017     | Frougier      | N/A      | H10D 30/6757 |
| 2013/0334606 | 12/2012     | Shen          | N/A      | N/A          |
| 2014/0282326 | 12/2013     | Hsin et al.   | N/A      | N/A          |
| 2015/0041909 | 12/2014     | Bouche        | N/A      | N/A          |
| 2016/0204221 | 12/2015     | He            | N/A      | N/A          |
| 2019/0259619 | 12/2018     | Zang          | N/A      | N/A          |
| 2020/0135476 | 12/2019     | Huang         | N/A      | N/A          |
| 2020/0152736 | 12/2019     | Yu            | N/A      | N/A          |
| 2022/0208790 | 12/2021     | Yoon          | N/A      | H10D 62/116  |
| 2022/0293730 | 12/2021     | Kim           | N/A      | H10D 64/015  |

FOREIGN PATENT DOCUMENTS

| Patent No. | Application Date | Country | CPC |
|------------|------------------|---------|-----|
| 201937609  | 12/2018          | TW      | N/A |

Primary Examiner: Park; Samuel

Attorney, Agent or Firm: HAYNES AND BOONE, LLP

## Background/Summary

### PRIORITY DATA

(1) The present application is a utility application of provisional U.S. patent application Ser. No. 63/220,164, filed on Jul. 9, 2021, entitled “Forming Low-Resistance Capping Layer Over Metal Gate Electrode”, the disclosure of which is hereby incorporated by reference in its entirety.

### BACKGROUND

(2) The semiconductor integrated circuit (IC) industry has experienced exponential growth. Technological advances in IC materials and design have produced generations of ICs where each generation has smaller and more complex circuits than the previous generation. In the course of IC evolution, functional density (i.e., the number of interconnected devices per chip area) has generally increased while geometry size (i.e., the smallest component (or line) that can be created using a fabrication process) has decreased. This scaling down process generally provides benefits by increasing production efficiency and lowering associated costs. Such scaling down has also increased the complexity of processing and manufacturing ICs.

(3) For example, as the sizes of the transistor components continue to get smaller, gate resistance may increase undesirably, particularly for devices located far away from the gate vias. The increase in gate resistance may adversely impact device performance such as a speed.

(4) Therefore, although existing semiconductor devices have been generally adequate for their intended purposes, they have not been entirely satisfactory in every aspect.

---

## Description

### BRIEF DESCRIPTION OF THE DRAWINGS

(1) Aspects of the present disclosure are best understood from the following detailed description when read with the accompanying figures. It is emphasized that, in accordance with the standard practice in the industry, various features are not drawn to scale. In fact, the dimensions of the various features may be arbitrarily increased or reduced for clarity of discussion. It is also emphasized that the drawings appended illustrate only typical embodiments of this invention and are therefore not to be considered limiting in scope, for the invention may apply equally well to other embodiments.

(2) FIG. 1A illustrates a three-dimensional perspective view of a FinFET device.

(3) FIG. 1B illustrates a top view of a FinFET device.

(4) FIG. 1C illustrates a three-dimensional perspective view of a multi-channel gate-all-around (GAA) device.

(5) FIGS. 2-15 illustrate a series of cross-sectional views of a semiconductor device at various stages of fabrication according to embodiments of the present disclosure.

(6) FIG. 16 illustrates a simplified diagrammatic fragmentary top view of a portion of a semiconductor device according to an embodiment of the present disclosure.

(7) FIG. 17 illustrates a cross-sectional view of a semiconductor device at a stage of fabrication according to embodiments of the present disclosure.

(8) FIG. 18 illustrates a three-dimensional perspective view of a semiconductor device at a stage of fabrication according to embodiments of the present disclosure.

(9) FIG. 19 illustrates a cross-sectional view of a semiconductor device at a stage of fabrication according to embodiments of the present disclosure.

(10) FIG. 20 illustrates a Static Random Access Memory (SRAM) cell according to an embodiment of the present disclosure.

(11) FIG. 21 illustrates an integrated circuit fabrication system according to an embodiment of the

present disclosure.

(12) FIGS. 22-23 is a flowchart illustrating a method of fabricating a semiconductor device according to various aspects of the present disclosure.

#### DETAILED DESCRIPTION

(13) The following disclosure provides many different embodiments, or examples, for implementing different features of the provided subject matter. Specific examples of components and arrangements are described below to simplify the present disclosure. These are, of course, merely examples and are not intended to be limiting. For example, the formation of a first feature over or on a second feature in the description that follows may include embodiments in which the first and second features are formed in direct contact, and may also include embodiments in which additional features may be formed between the first and second features, such that the first and second features may not be in direct contact. In addition, the present disclosure may repeat reference numerals and/or letters in the various examples. This repetition is for the purpose of simplicity and clarity and does not in itself dictate a relationship between the various embodiments and/or configurations discussed.

(14) Further, spatially relative terms, such as “beneath,” “below,” “lower,” “above,” “upper” and the like, may be used herein for ease of description to describe one element or feature's relationship to another element(s) or feature(s) as illustrated in the figures. The spatially relative terms are intended to encompass different orientations of the device in use or operation in addition to the orientation depicted in the figures. The apparatus may be otherwise oriented (rotated 90 degrees or at other orientations) and the spatially relative descriptors used herein may likewise be interpreted accordingly.

(15) Still further, when a number or a range of numbers is described with “about,” “approximate,” and the like, the term is intended to encompass numbers that are within a reasonable range including the number described, such as within  $\pm 10\%$  of the number described or other values as understood by person skilled in the art. For example, the term “about 5 nm” encompasses the dimension range from 4.5 nm to 5.5 nm.

(16) The present disclosure is generally related to semiconductor devices, which may be fabricated using field-effect transistors (FETs) such as three-dimensional fin-line FETs (FinFETs) or multi-channel gate-all-around (GAA) devices. FinFET devices have semiconductor fin structures that protrude vertically out of a substrate. The fin structures are active regions, from which source/drain regions and/or channel regions are formed. The gate structures partially wrap around the fin structures. GAA devices have multiple elongated nano-structure channels that may be implemented as nano-tubes, nano-sheets, or nanowires. In recent years, FinFET devices and GAA devices have gained popularity due to their enhanced performance compared to conventional planar transistors. However, as semiconductor device sizes continue to get scaled down, the imperfections within FinFET or GAA devices may lead to potential problems.

(17) In more detail, modern FinFET and/or GAA device fabrication may involve forming a high-k metal gate (HKMG) structure, which contains a high-k gate dielectric (with a dielectric constant greater than that of silicon oxide) and a metal gate electrode. As device sizes continue to get scaled down, however, gate resistance may become a greater concern, since an increase in gate resistance may result in a slower device speed. For example, recent semiconductor technology nodes may involve forming a HKMG structure that wraps around a plurality of vertically protruding active regions structures (e.g., vertical stacks of nano-structures in the case of a GAA device, or fin structures in the case of a FinFET device), and then forming a gate via over the HKMG structure to provide electrical connectivity to the HKMG structure and the active regions structures below. As the semiconductor device scaling down continues, the HKMG structure may be wrapping over an even greater number of active region structures. Compared to the active region structures located close to the gate via, the active region structures that are located farther away from the gate via (e.g., active region structures at or near the end of a row of active region structures) may experience

a substantially longer signal path for electrical signals traveling to and from the gate via. The longer signal path may lead to an increase in resistance, which is referred to as gate resistance herein. As gate resistance increases, a time constant (which is a product of resistance and capacitance) also increases, which results in a slower speed for the semiconductor device, particularly for the devices corresponding to the active region structures at or near the end of the row of the active region structures.

(18) To address the problem discussed above, the present disclosure introduces a low-resistance layer (e.g., a tungsten-containing layer) over the gate electrode of the GAA and/or GAA FinFET devices. In some embodiments, the low-resistance layer may be implemented as a capping layer at the top of the metal gate electrode. The low-resistance capping layer has a substantially lower resistivity compared to the gate via and the various metal layers of the gate electrode. As such, gate resistance may be substantially reduced even for devices at or near the end of the row of active region structures. The reduction in gate resistance results in a slower delay and/or faster device speed.

(19) The various aspects of the present disclosure are now discussed below with reference to FIGS. **1A-1C** and **2-19**. In more detail, FIGS. **1A-B** illustrate an example FinFET device, and FIG. **1C** illustrates an example GAA device. FIGS. **2-19** illustrate cross-sectional side, top, or three-dimensional perspective views, of an IC device at various stages of fabrication according to embodiments of the present disclosure. FIG. **20** illustrates a memory circuit as an example IC application implemented using IC devices fabricated according to the various aspects of the present disclosure. FIG. **21** illustrates a semiconductor fabrication system. FIGS. **22-23** each illustrate a flowchart of a method of fabricating an IC device according to various aspects of the present disclosure.

(20) Referring now to FIGS. **1A** and **1B**, a three-dimensional perspective view and a top view of a portion of an Integrated Circuit (IC) device **90** are illustrated, respectively. The IC device **90** is implemented using FinFETs. As shown in FIG. **1A**, the IC device **90** includes a substrate **110**. The substrate **110** may comprise an elementary (single element) semiconductor, such as silicon, germanium, and/or other suitable materials; a compound semiconductor, such as silicon carbide, gallium arsenic, gallium phosphide, indium phosphide, indium arsenide, indium antimonide, and/or other suitable materials; an alloy semiconductor such as SiGe, GaAsP, AlInAs, AlGaAs, GaInAs, GaInP, GaInAsP, and/or other suitable materials. The substrate **110** may be a single-layer material having a uniform composition. Alternatively, the substrate **110** may include multiple material layers having similar or different compositions suitable for IC device manufacturing. In one example, the substrate **110** may be a silicon-on-insulator (SOI) substrate having a semiconductor silicon layer formed on a silicon oxide layer. In another example, the substrate **110** may include a conductive layer, a semiconductor layer, a dielectric layer, other layers, or combinations thereof. Various doped regions, such as source/drain regions, may be formed in or on the substrate **110**. The doped regions may be doped with n-type dopants, such as phosphorus or arsenic, and/or p-type dopants, such as boron, depending on design requirements. The doped regions may be formed directly on the substrate **110**, in a p-well structure, in an n-well structure, in a dual-well structure, or using a raised structure. Doped regions may be formed by implantation of dopant atoms, in-situ doped epitaxial growth, and/or other suitable techniques.

(21) Three-dimensional active regions **120** are formed on the substrate **110**. The active regions **120** may include elongated fin-like structures that protrude upwardly out of the substrate **110**. As such, the active regions **120** may be interchangeably referred to as fin structures **120** or fins **120** hereinafter. The fin structures **120** may be fabricated using suitable processes including photolithography and etch processes. The photolithography process may include forming a photoresist layer overlying the substrate **110**, exposing the photoresist to a pattern, performing post-exposure bake processes, and developing the photoresist to form a masking element (not shown) including the resist. The masking element is then used for etching recesses into the substrate **110**,

leaving the fin structures **120** on the substrate **110**. The etching process may include dry etching, wet etching, reactive ion etching (RIE), and/or other suitable processes. In some embodiments, the fin structure **120** may be formed by double-patterning or multi-patterning processes. Generally, double-patterning or multi-patterning processes combine photolithography and self-aligned processes, allowing patterns to be created that have, for example, pitches smaller than what is otherwise obtainable using a single, direct photolithography process. As an example, a layer may be formed over a substrate and patterned using a photolithography process. Spacers are formed alongside the patterned layer using a self-aligned process. The layer is then removed, and the remaining spacers, or mandrels, may then be used to pattern the fin structures **120**.

(22) The IC device **90** also includes source/drain features **122** formed over the fin structures **120**. The source/drain features **122** may include epi-layers that are epitaxially grown on the fin structures **120**. The IC device **90** further includes isolation structures **130** formed over the substrate **110**. The isolation structures **130** electrically separate various components of the IC device **90**. The isolation structures **130** may include silicon oxide, silicon nitride, silicon oxynitride, fluoride-doped silicate glass (FSG), a low-k dielectric material, and/or other suitable materials. In some embodiments, the isolation structures **130** may include shallow trench isolation (STI) features. In one embodiment, the isolation structures **130** are formed by etching trenches in the substrate **110** during the formation of the fin structures **120**. The trenches may then be filled with an isolating material described above, followed by a chemical mechanical planarization (CMP) process. Other isolation structure such as field oxide, local oxidation of silicon (LOCOS), and/or other suitable structures may also be implemented as the isolation structures **130**. Alternatively, the isolation structures **130** may include a multi-layer structure, for example, having one or more thermal oxide liner layers.

(23) The IC device **90** also includes gate structures **140** formed over and engaging the fin structures **120** on three sides in a channel region of each fin **120**. In other words, the gate structures **140** each wrap around a plurality of fin structures **120**. The gate structures **140** may be dummy gate structures (e.g., containing an oxide gate dielectric and a polysilicon gate electrode), or they may be HKMG structures that contain a high-k gate dielectric and a metal gate electrode, where the HKMG structures are formed by replacing the dummy gate structures. Though not depicted herein, the gate structure **140** may include additional material layers, such as an interfacial layer over the fin structures **120**, a capping layer, other suitable layers, or combinations thereof.

(24) Referring to FIGS. **1A-1B**, multiple fin structures **120** are each oriented lengthwise along the X-direction, and multiple gate structure **140** are each oriented lengthwise along the Y-direction, i.e., generally perpendicular to the fin structures **120**. In many embodiments, the IC device **90** includes additional features such as gate spacers disposed along sidewalls of the gate structures **140**, hard mask layer(s) disposed over the gate structures **140**, and numerous other features.

(25) FIG. **1C** illustrates a three-dimensional perspective view of an example GAA device **150**. For reasons of consistency and clarity, similar components in FIG. **1C** and FIGS. **1A-1B** will be labeled the same. For example, active regions such as fin structures **120** rise vertically upwards out of the substrate **110** in the Z-direction. The isolation structures **130** provide electrical separation between the fin structures **120**. The gate structure **140** is located over the fin structures **120** and over the isolation structures **130**. A mask **155** is located over the gate structure **140**, and gate spacers **160** are located on sidewalls of the gate structure **140**. A capping layer **165** is formed over the fin structures **120** to protect the fin structures **120** from oxidation during the forming of the isolation structures **130**.

(26) A plurality of nano-structures **170** are disposed over each of the fin structures **120**. The nano-structures **170** may include nano-sheets, nano-tubes, or nano-wires, or some other type of nano-structure that extends horizontally in the X-direction. Portions of the nano-structures **170** under the gate structure **140** may serve as the channels of the GAA device **150**. Dielectric inner spacers **175** may be disposed between the nano-structures **170**. In addition, although not illustrated for reasons

of simplicity, each stack of the nano-structures **170** may be wrapped around circumferentially by a gate dielectric as well as a gate electrode. In the illustrated embodiment, the portions of the nano-structures **170** outside the gate structure **140** may serve as the source/drain features of the GAA device **150**. However, in some embodiments, continuous source/drain features may be epitaxially grown over portions of the fin structures **120** outside of the gate structure **140**. Regardless, conductive source/drain contacts **180** may be formed over the source/drain features to provide electrical connectivity thereto. An interlayer dielectric (ILD) **185** is formed over the isolation structures **130** and around the gate structure **140** and the source/drain contacts **180**.

(27) Additional details pertaining to the fabrication of GAA devices are disclosed in U.S. Pat. No. 10,164,012, titled "Semiconductor Device and Manufacturing Method Thereof" and issued on Dec. 25, 2018, as well as in U.S. Pat. No. 10,361,278, titled "Method of Manufacturing a Semiconductor Device and a Semiconductor Device" and issued on Jul. 23, 2019, and also in U.S. Pat. No. 9,887,269, titled "Multi-Gate Device and Method of Fabrication Thereof" and issued on Feb. 6, 2018, the disclosures of each which are hereby incorporated by reference in their respective entireties. To the extent that the present disclosure refers to a fin structure or FinFET devices, such discussions may apply equally to the GAA devices.

(28) FIG. 2 is a diagrammatic fragmentary cross-sectional side view of a portion of an IC device **200** at a given stage of fabrication according to embodiments of the present disclosure. The IC device **200** may be implemented as a FinFET or a GAA device, though it is illustrated as a GAA device herein for reasons of simplicity.

(29) The cross-sectional side view of FIG. 2 is taken across a plane defined by the Y-direction and Z-direction (e.g., across a Y-Z plane). As such, the cross-sectional side view of FIG. 2 may also be referred to as a Y-cut. In some embodiments, the cross-sectional side view of the IC device **200** in FIG. 2 may be obtained by taking a cross-sectional cut along the cutline A-A'. It is also understood that although the discussions below primarily use a GAA device (e.g., the GAA device of FIG. 1C) to illustrate the inventive concepts of the present disclosure, the same concepts may apply to the FinFET device (e.g., the FinFET device of FIGS. 1A-1B) as well, unless otherwise noted.

(30) As shown in FIG. 2, the IC device **200** includes the substrate **110** discussed above with reference to FIGS. 1A-1C, for example a silicon substrate. A plurality of active regions may be formed by patterning the substrate **110**. For example, the active regions may include the stacks of nano-structures **170** discussed above with reference to FIG. 1C. The stacks of nano-structures shown in FIG. 2 are labeled with separate reference numerals **170A**, **170B**, **170C**, and **170D** for ease of reference in the discussions below. Nevertheless, it is understood that the nano-structures **170A-170D** each protrude vertically upwards (in the Z-direction) out of the substrate **110** and each extend laterally in the X-direction, just like the nano-structures **170** of FIG. 1C. It is understood that although four example nano-structures **170A-170D** are illustrated herein, the IC device **200** may include a substantially greater number of nano-structures, for example over twenty or thirty of fin structures similar to the nano-structures **170A-170D**. The fin structures disposed between the nano-structures **170A-170C** are not specifically illustrated herein but instead are represented by a plurality of dots **210**, and the fin structures disposed between the fin structures nano-structures **170B-170D** are not specifically illustrated herein but instead are represented by a plurality of dots **211**.

(31) The bottom portions of the nano-structures **170** may include fin structures **120**, which are separated from one another in the Y-direction by the isolation structures **130**, which may include a suitable dielectric material such as silicon oxide, silicon nitride, silicon oxynitride, fluoride-doped silicate glass (FSG), as discussed above with reference to FIGS. 1A-1B. In the illustrated embodiment, the isolation structures **130** include shallow trench isolation (STI) structures.

(32) Still referring to FIG. 2, the IC device **200** includes a high-k metal gate (HKMG) structure **140**. The HKMG structure **140** may include a high-k gate dielectric and a metal-containing gate electrode. The high-k gate dielectric contains a high-k dielectric material, which refers to a

dielectric material having a dielectric constant that is greater than a dielectric constant of silicon oxide (e.g., about 3.9). Example materials of the high-gate k dielectric include hafnium oxide, zirconium oxide, aluminum oxide, hafnium dioxide-alumina alloy, hafnium silicon oxide, hafnium silicon oxynitride, hafnium tantalum oxide, hafnium titanium oxide, hafnium zirconium oxide, or combinations thereof. The metal-containing gate electrode is formed over the high-k gate dielectric. The metal-containing gate electrode may include one or more work function (WF) metal layers and a fill metal layer. The work function metal layers may be configured to tune a work function of the respective transistor. Example materials for the work function metal layers may include titanium nitride (TiN), Titanium aluminide (TiAl), tantalum nitride (Ta<sub>2</sub>N), titanium carbide (TiC), tantalum carbide (TaC), tungsten carbide (WC), aluminum titanium nitride (TiAlN), zirconium aluminide (ZrAl), tungsten aluminide (WAl), tantalum aluminide (TaAl), hafnium aluminide (HfAl), or combinations thereof. The fill metal layer may serve as the main conductive portion of the metal-containing gate electrode. In some embodiments, the fill metal layer may include cobalt, tungsten, copper, aluminum, or alloys or combinations thereof. It is understood that the HKMG structure may include additional layers, such as interfacial layers, capping layers, diffusion/barrier layers, or other applicable layers.

(33) According an aspect of the present disclosure, the IC device **200** includes a conductive capping layer **300** that is formed over an upper surface of the HKMG structure **140**. A gate via **320** is then formed over the conductive capping layer **300**. The conductive capping layer **300** may be formed over a substantial majority (e.g., greater than 90%) of an upper surface of the HKMG structure **140**, at least in the Y-direction. In other words, in the cross-sectional Y-cut side view, a substantial entirety (e.g., at least 90%) of the upper surface of the HKMG structure **140** has the conductive capping layer **300** formed thereon. In some embodiments, the conductive capping layer **300** is formed over an entirety of an upper surface of the HKMG structure **140** in at least the Y-direction. Accordingly, a dimension of the conductive capping layer **300** in the Y-direction is substantially greater (e.g., at least several times greater) than a maximum dimension of the gate via **320** in the Y-direction. Note that the HKMG structure **140** may be physically and electrically separated from other adjacent HKMG structures (not illustrated herein) based on requirements of the circuit design, and in such cases, the conductive capping layer **300** is also broken up to ensure that these HKMG structures are not inadvertently shorted electrically, which will be discussed in greater detail below.

(34) Still referring to FIG. 2, the conductive capping layer **300** has a lower resistivity than the metal-containing electrode of the HKMG, as well as a lower resistivity than the gate via **320**. In that regard, resistivity of a specific type of material measures the electrical resistance of that specific type of material to electrical conduction on a per unit (e.g., length, or volume) basis. As such, a material with a lower resistivity is a better electrical conductor than a material with a higher resistivity, assuming that the two materials have the same size and operate within the same environment.

(35) One of the reasons for the implementation of the conductive capping layer **300** is to reduce the gate resistance. In more detail, the gate via **320** is formed to provide electrical connectivity to the HKMG structure **140** and the nano-structures **170A-170D** disposed underneath the HKMG structure **140**. However, after propagating vertically through the gate via **320**, electrical signals have to travel horizontally in the Y-direction to reach the various nano-structures. As discussed above, there may be many nanostructures disposed between the nano-structures **170A** and **170C**, as well as between the nano-structures **170B** and **170D**. Thus, the electrical signal propagating through the gate via **320** may only need to travel a distance **220** to reach the nano-structure **170A** but may have to travel a much longer distance **221** to reach the nano-structure **170C**. Likewise, the electrical signal propagating through the gate via **320** may only need to travel a small distance **220** to reach the nano-structure **170B** but may have to travel the much longer distance **221** to reach the nano-structure **170D**.



(36) In conventional embodiments where the conductive capping layer **300** is not implemented, the propagation of the electrical signal would take place mostly within the metal-containing gate electrode of the HKMG structure **140**. Although the metal-containing gate electrode is electrically conductive, such a horizontal propagation path (along the Y-direction) of the electrical signal may still result in signal loss due to the inherent electrical resistance of the metal-containing gate electrode. Alternatively stated, the horizontal propagation of the electrical signal between the gate via **320** and the nano-structures corresponds to gate resistance experienced by the respective nano-structures. The signal loss or gate resistance may be even worse for the nano-structures at or near the end of the row of nano-structures, such as the nano-structure **170C** that is disposed at the end of the row. In other words, even if the signal loss or gate resistance experienced by the nano-structure **170A** is tolerable (since it is disposed relatively close to the gate via **320**), the signal loss or gate resistance experienced by the nano-structure **170C** may be too significant to overlook. As a result, the nano-structures herein, and especially the nano-structures that are far away from the gate via **320** (such as the nano-structures **170C** and **170D**), could experience degraded device performance such as slower device speed, etc, since resistance is inversely correlated with device speed.

(37) To overcome the problems discussed above, the present disclosure implements the conductive capping layer **300** to reduce the gate resistance experienced by the nano-structures. As discussed above, the conductive capping layer **300** has a lower resistivity than the gate via **320**, as well as a lower resistivity than the metal layers of the HKMG structure **140**. As such, the conductive capping layer **300** can conductive electricity better than the HKMG structure **140** with reduced signal loss. Note that the conductive capping layer **300** is also formed over a substantial entirety of the HKMG structure **140**. As such, to reach even the farthest nano-structures **170C** or **170D**, the horizontal propagation of the electrical signals may take place mostly within the conductive capping layer **300**, rather than through the more resistive metal layers of the HKMG structure **140**. Therefore, even the most remotely located nano-structures **170C** and **170D** (from the gate via **320**) may experience a substantial reduction in gate resistance and signal loss. In this manner, the device performance (particularly for the devices corresponding to the nano-structures **170C** and **170D**) may be improved.

(38) FIGS. **3-15** illustrate diagrammatic fragmentary cross-sectional views of a portion of the IC device **200** at various stages of fabrication according to various embodiments of the present disclosure. Whereas FIG. **2** illustrates its cross-sectional view along a Y-Z plane, FIGS. **3-15** illustrate the cross-sectional views along a X-Z plane, and as such, FIGS. **3-15** may be referred to as X-cuts. For example, the cross-sectional side views of the IC device in FIGS. **3-15** may be obtained by taking a cross-sectional cut along the cutline B-B' shown in FIG. **1B**.

(39) Referring to FIG. **3**, the IC device **200** includes an active region, which may be in the form of the nano-structure **170** discussed above in some embodiments, or may be the fin structures **120** in some other embodiments. The dielectric structure **190** surrounds the nano-structure **170** laterally in the X-direction. In some embodiments, the dielectric structure **190** may include different dielectric components, for example, the ILD **185** and the gate spacers **160** discussed above. The HKMG structure **140** is formed over the nano-structure **170**. In some embodiments, the HKMG structure **140** is formed as a part of a gate replacement process, in which a dummy gate structure is formed first and subsequently replaced by the HKMG structure. In that regard, the initially-formed dummy gate structure may include a dummy gate dielectric (e.g., a silicon oxide gate dielectric) and a dummy polysilicon gate electrode. After the formation of source/drain regions, the dummy gate structure is removed (e.g., via one or more etching processes), thereby forming an opening or recess within the dielectric structure **190**. The opening or recess also exposes an upper surface of the nano-structure **170**. The HKMG structure **140** is then formed in the opening to replace the removed dummy gate structure.

(40) In the embodiment shown in FIG. **3**, the HKMG structure **140** includes a high-k gate dielectric layer **400** formed over the nano-structure **170**, a work function (WF) metal layer **410** formed over

the high-k gate dielectric layer **400**, a conductive layer **420** formed over the WF metal layer **410**, a protection layer **430** formed over the conductive layer **420**, and a glue layer **440** formed over the protection layer **430**. In some embodiments, an interfacial layer may also be formed between the nano-structure **170** and the high-k gate dielectric layer **410**.

(41) The high-k gate dielectric layer **400** includes a high-k dielectric material having a dielectric constant greater than that of silicon oxide. The high-k gate dielectric layer **400** may be formed by one or more suitable deposition processes, such as an atomic layer deposition (ALD) process, a plasma enhanced atomic layer deposition (PEALD) process, a chemical vapor deposition (CVD) process, or a physical vapor deposition (PVD) process, or combinations thereof.

(42) The WF metal layer **410** may include a metal or metal compound configured to tune a work function of a transistor. Non-limiting example materials for the WF metal layer **410** may include titanium nitride (TiN), Titanium aluminide (TiAl), tantalum nitride (TaN), titanium carbide (TiC), tantalum carbide (TaC), tungsten carbide (WC), aluminum titanium nitride (TiAlN), zirconium aluminide (ZrAl), tungsten aluminide (WAl), tantalum aluminide (TaAl), hafnium aluminide (HfAl), or combinations thereof. The WF metal layer **410** may also be formed using one or more suitable deposition processes such as ALD, CVD, PVD, or combinations thereof.

(43) The conductive layer **420** includes an electrically conductive material that also has good gap-filling performance. In some embodiments, the conductive layer **420** includes titanium nitride (TiN). In some embodiments, the conductive layer **420** may also be formed using the same processing chamber (e.g., an ALD chamber, a PVD chamber, a CVD chamber, etc.) that was used to form the WF metal layer **410**. As such, the conductive layer **420** may also be referred to as an in-situ layer. The conductive layer **420** may be considered a portion of the fill metal discussed above, which serves as a main conductive portion of the metal gate electrode of the HKMG structure **140**.

(44) The protection layer **430** includes a dielectric material. In some embodiments, the protection layer **430** may include silicon oxide (SiO<sub>2</sub>). The protection layer **430** provides protection for the layers below, for example to the conductive layer **420** and the WF metal layer **410**. The protection layer **430** may also be formed using one or more suitable deposition processes such as ALD, CVD, PVD, or combinations thereof.

(45) The glue layer **440** also includes a conductive material. In some embodiments, the glue layer **440** includes titanium nitride. The material composition of the glue layer **440** is configured to enhance adhesion with the conductive capping layer **300** (see FIG. 2) that will be formed over the glue layer **440** in a subsequent process. Without the glue layer **440**, the conductive capping layer **300** may not have sufficient adhesion with the metal gate electrode of the HKMG structure **140**. In other words, had the glue layer **440** not been formed, the conductive capping layer **300** may peel off from the metal gate electrode of the HKMG structure **140** too easily. The glue layer **440** may also be considered a portion of the fill metal of the metal gate electrode. The glue layer **440** may be formed using one or more suitable deposition processes such as ALD, CVD, PVD, or combinations thereof.

(46) In the illustrated embodiment, a narrow gap **450** (or a seam) may also exist within the HKMG structure **140**, for example, within the glue layer **440**. In some embodiments, such a gap **450** may be formed due to the gap-filling capabilities of the glue layer **440**. In some embodiments, the gap **450** may be eliminated altogether.

(47) Referring now to FIG. 4, an etching-back process **500** is performed to the IC device **200**. The etching-back process **500** partially etches away the HKMG structure **140** to reduce the height of the HKMG structure **140** in the Z-direction. The etching-back process **500** may have substantially similar etching rates for the layers **400**, **410**, **420**, **430**, and **440**, so that the reduction in height due to the etching-back process **500** may be substantially similar for all the layers **400-440**.

(48) The partial removal of the layers **400-440** forms an opening **510**, where the side surfaces of the opening **510** are defined by the dielectric structure **190**, and the bottom surface of the opening **510** is defined by the upper surfaces of the layers **400-440**. The opening **510** has a depth **520** measured

in the Z-direction. The depth **520** is carefully configured to be not too deep nor too shallow. This is because the opening **510** is formed so that it can be filled by the conductive capping layer **300** in a subsequent process. As such, the depth **520** of the opening **510** translates into the thickness of the conductive capping layer **300**. If the depth **520** is too high, the conductive capping layer **300** will be too thick and the HKMG structure **140** will be too thin, which may adversely affect the performance or operation of the HKMG structure **140**. On the other hand, if the depth **520** is too low, the conductive capping layer **300** will be too thin, and it may not adequately serve its purpose of reducing the gate resistance. In some embodiments, the depth **520** is in a range between about 20 nm and about 70 nm, for example, between about 30 nm and about 60 nm. The depth **520** may also be defined relative to a height **530** of a remaining portion of the HKMG structure **140**. In some embodiments, a ratio between the depth **520** and the height **530** is in a range between about 5 nm and about 25 nm. As discussed above, these ranges involving the depth **520** are not randomly chosen but specifically configured herein to ensure that the soon-to-be-formed conductive capping layer **300** is sufficiently thick to reduce the gate resistance, while preserving a sufficient amount of HKMG structure **140** so that the intended operations involving the gate or device performance is not compromised.

(49) Referring now to FIG. 5, a selective growth process **550** is performed to the IC device **200** to form the conductive capping layer **300** over the HKMG structure **140**. In some embodiments, the selective growth process **550** is performed in an atomic layer deposition (ALD) tool, with the precursors selected from the group consisting of: WC's, H.sub.2, WF.sub.6, and SiH.sub.4. The selective growth process **550** is also performed at a process temperature in a range between about 400 degrees Celsius and about 500 degrees Celsius, for a process duration between about 2 minutes and about 30 minutes, at a process pressure in a range between about 2 Torr and about 500 Torr.

(50) The selective growth process **550** is configured to grow the materials of the conductive capping layer **300** directly on upper surfaces of the WF metal layer **410**, the conductive layer **420**, and the glue layer **440**, but not directly on the upper surfaces of the high-k gate dielectric layer **400** or the protection layer **430**. In some embodiments, the selective growth process **550** is configured to grow fluorine-free-tungsten (FFW) as the material of the conductive capping layer **300**. In other embodiments, the selective growth process **550** may be configured to grow another tungsten-containing material or another suitable material as the conductive capping layer **300**. Regardless of the specific type of material grown as the conductive capping layer **300**, it is understood that the conductive capping layer **300** has a lower resistivity than the metal gate electrode of the HKMG structure **140**, for example, a lower resistivity than each of the layers **400**, **410**, **420**, **430**, and **440**.

(51) Due to the fact that the conductive capping layer **300** is selectively grown directly on the layers **410**, **420**, and **440**, but not directly on the layers **400** or **430**, the conductive capping layer **300** may exhibit certain unique physical characteristics. For example, a bottom surface **570** of the conductive capping layer **300** may have concave recesses **580-581** that are each recessed in the Z-direction. The locations of the recesses **580-581** correspond to (or are aligned with) the locations of the protection layer **430**. This is because while the conductive capping layer **300** is not grown directly on the upper surfaces of the protection layer **430** (since the protection layer **430** is not conductive), the portions of the conductive layer capping **300** grown directly on the upper surfaces of the layers **420** and **440** may extend laterally (in the X-direction), such that they eventually merge into one another. As such, portions of the conductive capping layer **300** are still disposed over the protection layer **430**, but these portions are formed at a more elevated location vertically, thereby resulting in the recesses **580-581**. In some embodiments, the bottom surface **570** of the conductive capping layer **300** may further include a protrusion **590** that protrude downward vertically in the Z-direction. In other words, the protrusion **590** may protrude into the gap **450**.

(52) Note that no planarization process is needed to planarize an upper surface **600** of the conductive capping layer **300**, since the selective growth process **550** may be able to tune a thickness (measured vertically in the Z-direction) of the conductive capping layer **300** with relative

precision. As such, the selective growth process **550** may stop once the upper surface **600** is substantially co-planar with the upper surfaces of the dielectric structure **190**. Having said that, it is understood that the upper surface **600** of the conductive capping layer **300** may or may not be perfectly flat, and it may include a curvature in certain embodiments. For example, the upper surface **600** may be downwardly curved (in the Z-direction) in some embodiments, such that it has a lower vertical elevation at the middle than at the edges.

(53) Also note that a thickness of the conductive capping layer **300** may substantially correspond to the depth **520** of the opening **510** discussed above with reference to FIG. 4. As such, the reference numeral **520** may also be referred to as a thickness **520** of the conductive capping layer **300**. As such, the thickness **520** of the conductive capping layer **300** is in a range between about 2 nm and about 8 nm, and a ratio between the thickness **520** and the height **530** of the remaining portion of the HKMG structure **140** is in a range between about 50% and about 100%. Again, these ranges are not randomly chosen but specifically configured to ensure that the conductive capping layer **300** may achieve sufficient gate resistance reduction without interfering with the desired operations of the transistors herein.

(54) Referring now to FIG. 6, the gate via **320** discussed above is formed over the upper surface **600** of the conductive capping layer **300**. As discussed above, the gate via **320** provides electrical connectivity to the HKMG structure **140** and the nano-structure **170** below. Due to the formation of the low-resistance conductive capping layer **300**, signals propagating through the gate via **320** may travel to each of the nano-structures **170** through the conductive capping layer **300**. Since the resistivity of the conductive capping layer **300** is very low, even the farthest nano-structure **170** (e.g., nano-structures **170C** or **170D** in FIG. 2) from the gate via **320** would not experience much signal loss, and therefore the gate resistance is substantially reduced, and device speed is improved.

(55) The embodiments discussed above in association with FIGS. 3-6 correspond to a semiconductor device having a relatively low threshold voltage. As such, the embodiments shown in FIGS. 3-6 may be referred to as a low-threshold-voltage embodiment. FIG. 7 illustrates another embodiment of the IC device **200** having a medium threshold voltage (i.e., greater than the low threshold voltage of the embodiments of FIGS. 3-6). As such, the embodiment of FIG. 7 may be referred to as a medium-threshold-voltage embodiment. For reasons of consistency and clarity, similar components appearing in FIGS. 3-7 will be labeled the same.

(56) Referring to FIG. 7, which is the X-cut view of the IC device **200**, the HKMG structure **140** of the IC device **200** includes the high-k gate dielectric layer **400**, the WF metal layer **410**, the conductive layer **420**, the protection layer **430**, and the glue layer **440**. Unlike the low-threshold-voltage embodiment of FIG. 6, however, the medium-threshold-voltage embodiment of FIG. 7 further includes a conductive layer **620** that is formed between the high-k gate dielectric layer **400** and the WF metal layer **410**. The addition of the conductive layer **620** helps tune the threshold voltage of the embodiment of FIG. 7 to be a greater voltage than the embodiment of FIG. 6 (e.g., a larger positive value for NFETs or a larger magnitude of a negative value for PFETs).

(57) At the stage of FIG. 7, the IC device **200** has undergone the same fabrication processes discussed above with reference to FIGS. 4-6, such as the etching-back process **500**, the selective growth process **550**, and the formation of the gate via **320**. The selective growth process **550** forms the conductive capping layer **300** over the HKMG structure **140**. Note that the bottom surface **570** of the conductive capping layer **300** may still have concave recesses **580-581** that correspond to the locations of the protection layer **430**, since the conductive capping layer **300** is not grown directly on the upper surfaces of the protection layer **430**. The bottom surface **570** of the conductive capping layer **300** also includes the downward protrusion **590** into the gap **450**.

(58) FIG. 8 further illustrates another embodiment of the IC device **200**, where the HKMG structure **140** is configured to have a relatively high threshold voltage compared to the embodiments of FIG. 6 and FIG. 7. As such, the embodiment shown in FIG. 8 may be referred to as a high-threshold-voltage embodiment. For reasons of consistency and clarity, similar

components appearing in FIGS. 5-8 will be labeled the same.

(59) Referring to FIG. 8, which is the X-cut view of the IC device **200**, the HKMG structure **140** of the IC device **200** includes the high-k gate dielectric layer **400**, the conductive layer **620**, the WF metal layer **410**, the conductive layer **420**, and the protection layer **430**. Unlike the low-threshold-voltage embodiment of FIG. 6 and the medium-threshold-voltage embodiment of FIG. 7, however, the high-threshold-voltage embodiment of FIG. 8 does not include the glue layer **440**. In addition, the conductive layer **620** of FIG. 8 is substantially thicker than the conductive layer **620** in the embodiment of FIG. 7. Such a configuration of the HKMG structure **140** helps tune the threshold voltage of the embodiment of FIG. 8 to be a greater voltage than the embodiments of FIGS. 6-7 (e.g., a larger positive value for NFETs or a larger magnitude of a negative value for PFETs).

(60) At the stage of FIG. 8, the IC device **200** has undergone the same fabrication processes discussed above with reference to FIGS. 4-6, such as the etching-back process **500**, the selective growth process **550**, and the formation of the gate via **320**. The selective growth process **550** forms the conductive capping layer **300** over the HKMG structure **140**. Due at least in part to the elimination of the glue layer **440**, the bottom surface **570** of the conductive capping layer **300** now has a concave recess **630** (recessed upwardly in the Z-direction). The recess **630** generally corresponds to the location of the protection layer **430**, and a center of the recess **630** corresponds to the location of the gap **450**. Again, the formation of the recess **630** is attributed to the fact that the conductive capping layer **300** is not grown directly on the upper surfaces of the protection layer **430** by the selective growth process **550**.

(61) The embodiments discussed above with reference to FIGS. 3-8 pertain to a first process flow to form the conductive capping layer **300**. FIGS. 9-15 pertain to a second process flow to form the conductive capping layer **300**. Again, for reasons of consistency and clarity, similar components appearing in both the first process flow discussed above and the second process flow discussed below will be labeled the same.

(62) Referring now to FIG. 9, which also illustrates the X-cut view of the IC device **200**, the HKMG structure **140** of the IC device **200** also undergoes the etching-back process **500**. As a result, the opening **510** is formed by the partial removal of the HKMG structure **140**.

(63) Referring now to FIG. 10, a glue layer deposition process **650** is performed to the IC device **200** to deposit a glue layer **660** in the opening **510**. The glue layer deposition process **650** may include an ALD process, a CVD process, a PVD process, or combinations thereof. In some embodiments, the glue layer **660** has a material composition that is similar to (or the same as) the glue layer **440**. For example, the glue layer **660** may also have a titanium nitride material composition. The glue layer **660** partially fills the opening **510**. For example, the glue layer **660** is formed on side surfaces and upper surfaces of the dielectric structure **190** and on upper surfaces of the etched-back HKMG structure **140**. Since the deposition process **650** is not a selective deposition process, portions of the glue layer **660** are formed on all of the layers **400-440** of the HKMG structure **140**.

(64) The glue layer deposition process **650** is configured to form the glue layer **660** to have a thickness **670**, where the thickness **670** is in a range between about 1 nm and about 10 nm. Such a thickness range is not randomly chosen but specifically configured to maximize device performance. In more detail, as will be discussed below, the remaining portion of the opening **510** will be filled by the conductive capping layer **300**. The glue layer **660** is formed herein to increase the adhesion with the conductive capping layer **300**, so that it does not peel off. Had the thickness **670** been too small (i.e., the glue layer **660** being formed too thin), then the glue layer **660** may not offer enough adhesion with the conductive capping layer **300**, and the conductive capping layer **300** could still suffer from undesirable peeling or detachment problems. On the other hand, had the thickness **670** been too great (i.e., the glue layer **660** being formed too thick), then there may not be a sufficient amount or volume of the conductive capping layer **300** to adequately reduce the gate resistance. Here, the specifically configured thickness range of the glue layer **660** allows for the

optimization of both conductive capping layer adhesion and gate resistance reduction.

(65) Referring now to FIG. 11, a conductive capping layer deposition process **680** is performed to the IC device **200** to deposit the conductive capping layer **300** in the opening **510**. The conductive capping layer **300** is deposited on the upper surfaces and side surfaces of the glue layer **660** and completely fills the opening **510**. In some embodiments, the conductive capping layer deposition process **680** may include an ALD process, a CVD process, a PVD process, or combinations thereof.

(66) Referring now to FIG. 12, a planarization process **690** is performed to the IC device **200**. In some embodiments, the planarization process **690** includes a CMP process. The planarization process **690** removes excess portions of the conductive capping layer **300** and excess portions of the glue layer **660** that are disposed over the dielectric structure **190**, such that the upper surfaces of the remaining portions of the conductive capping layer **300** and the glue layer **660** are substantially co-planar with the upper surfaces of the dielectric structure **190**. At this stage of fabrication, the conductive capping layer **300** has a thickness **695**. In some embodiments, the thickness **695** is in a range between about 20 nm and about 60 nm. In some embodiments, a ratio of the thickness **695** of the capping layer **300** and the thickness **670** of the glue layer **660** is in a range between about 2:1 and about 60:1. Such a ratio range is not randomly chosen but specifically configured to maximize device performance, because as discussed above, the glue layer **660** should not be too thin compared to the conductive capping layer **300**, as that may lead to peeling issues of the conductive capping layer **300**. Nor should the glue layer **660** be too thick compared to the conductive capping layer **300**, as that may lead to insufficient gate resistance reduction.

(67) Referring now to FIG. 13, the gate via **320** discussed above is formed over the upper surface **600** of the conductive capping layer **300**. As discussed above, the gate via **320** provides electrical connectivity to the HKMG structure **140** and the nano-structure **170** below. Due to the formation of the low-resistance conductive capping layer **300**, the gate resistance is substantially reduced.

(68) It is also understood that FIGS. 9-13 correspond to a low-threshold-voltage embodiment of the second process flow, where the HKMG structure **140** is substantially similar to the HKMG structure **140** of FIG. 6 (formed by the first process flow). FIG. 14 corresponds to a medium-threshold-voltage embodiment of the second process flow, where the HKMG structure **140** is substantially similar to the HKMG structure **140** of FIG. 7 (formed by the first process flow). Again, similar components appearing in the low-threshold-voltage embodiment of FIG. 13 and the medium-threshold-voltage embodiment of FIG. 14 are labeled the same.

(69) As shown in the X-cut cross-sectional side view of FIG. 14, the IC device **200** of the medium-threshold-voltage embodiment has an HKMG structure **140** that includes the layers **400-440** and the layer **620** discussed above. The HKMG structure **140** is etched back, and the glue layer **660** is formed over the etched-back HKMG structure **140**, and thereafter the conductive capping layer **300** is formed over the glue layer **660**. A planarization process is then performed to planarize the upper surfaces of the conductive capping layer **300** and the glue layer **660** until they are substantially co-planar with the upper surfaces of the dielectric structure **190**. The gate via **320** is then formed on the upper surface of the conductive capping layer **300**.

(70) FIG. 15 is an X-cut cross-sectional side view of a high-threshold-voltage embodiment of the second process flow, where the HKMG structure **140** is substantially similar to the HKMG structure **140** of FIG. 8 (formed by the first process flow). Again, similar components appearing in the low-threshold-voltage and medium-threshold-voltage embodiments of FIG. 13-14 and the high-threshold-voltage embodiment of FIG. 15 are labeled the same. As shown in FIG. 15, the IC device **200** of the high-threshold-voltage embodiment has an HKMG structure **140** that includes the layers **400-430** and the layer **620** discussed above. The HKMG structure **140** is etched back, and the glue layer **660** is formed over the etched-back HKMG structure **140**, and thereafter the conductive capping layer **300** is formed over the glue layer **660**. A planarization process is then performed to planarize the upper surfaces of the conductive capping layer **300** and the glue layer **660** until they are substantially co-planar with the upper surfaces of the dielectric structure **190**. The gate via **320**

is then formed on the upper surface of the conductive capping layer **300**.

(71) Regardless of the process flow performed to form the conductive capping layer **300**, and regardless of the IC device **200** being a low-threshold-voltage device, a medium-threshold-voltage device, or a high-threshold-voltage device, the implementation of the conductive capping layer **300** herein along a substantial entirety of the upper surface of the HKMG structure **140** in the Y-direction reduces gate resistance, especially for the active region structures located far away from the gate via. Such a gate resistance reduction leads to faster device speed, lower signal loss, etc.

(72) FIG. **16** illustrates a simplified diagrammatic fragmentary top view of a portion of the IC device **200** according to an embodiment of the present disclosure. For reasons of simplicity, certain layers and/or additional details about certain layers are not specifically illustrated herein. As shown in FIG. **16**, a plurality of active region structures, such as the nano-structures **170A-170D** discussed above, extend in the X-direction. Of course, these active region structures may be implemented as stacks of nano-structures (e.g., nano-sheets, nano-tubes, nano-wires, etc.) in embodiments where the IC device **200** is a GAA device. A plurality of HKMG structures **140** each extend in the Y-direction and overlap with the nano-structures **170A-170D** in the top view. The conductive capping layer **300** is formed over each of the HKMG structures **140**, and the gate via **320** is formed over the conductive capping layer **300**. The conductive capping layer **300** extends in the Y-direction, and its dimension **700** in the Y-direction is substantially similar to a dimension **710** of the HKMG structure **140** in the Y-direction. In some embodiments, the dimension **700** is greater than about 90% of the dimension **710**. In some embodiments, the dimension **700** is about equal to the dimension **710**. As discussed above, the fact that the conductive capping layer **300** is formed over a substantial entirety of an upper surface of the HKMG structure **140** allows the electrical signals traveling through the gate via **320** to reach the active region structures that are located far away (e.g., the nano-structures **170C** and **170D**) with minimal loss, since the conductive capping layer **300** has a low resistivity and spans through a substantial entirety of the HKMG structure **140** (and therefore all the active region structures located below the HKMG structure **140**). As such, the formation of the conductive capping layer herein reduces gate resistance and improves speed.

(73) In a typical IC device that contains many microelectronic components (e.g., gate structures), circuit designs may require that adjacent microelectronic components need to be kept electrically separate (or isolated) from one another. In other words, for some circuits to operate correctly, some of the microelectronic components located close to one another should still be electrically isolated from one another, which may be governed by or checked by a set of design rules. As such, the formation of the conductive capping layer **300** needs to follow such design rules to avoid causing inadvertent or otherwise unintentional electrical shorting between adjacent microelectronic components.

(74) One example of the formation of the conductive capping layer **300** that complies with the design rules according to an embodiment of the present disclosure is illustrated in FIG. **17**, which is a Y-cut cross-sectional view (i.e., taken across a Y-Z plane) of a portion of the IC device **200**. For reasons of consistency and clarity, similar components in FIG. **17** and FIGS. **1A-1C** and FIGS. **2-16** will be labeled the same. The portion of the IC device **200** shown in FIG. **17** includes a plurality of vertical stacks (such as stacks **170E**, **170F**, and **170G**) of nano-structures, that are wrapped around or surrounded by a plurality of HKMG structures **140E**, **140F**, and **140G**, respectively. As discussed above, the nano-structures in the stacks **170E-170G** each include a semiconductor material (e.g., silicon) and extend in the X-direction, and they are stacked over one another in the vertical Z-direction. The nano-structures may serve as channels of a transistor. In some embodiments, the nano-structures of the stack **170E** and the HKMG **140E** are components of an NFET, and the nano-structures of the stack **170F** and the HKMG **140F** are components of a PFET, where the NFET and the PFET form an interface **730** that extends in the Z-direction. For the purposes of facilitating the ensuing discussions, the HKMG **140E** and **140F** may be viewed as a single (or merged) gate structure, since they need not be electrically isolated from one another.

(75) However, design rules may specify that the merged gate structure made up of the HKMGs **140E** and **140F** need to be kept electrically separate from the HKMG **140G**, even though the HKMG **140G** is disposed adjacent to the HKMG **140F**. In other words, the HKMG **140G** constitutes a separate and different gate structure than the gate structure made up of the HKMGs **140E** and **140F**. To ensure the electrical separation between the HKMG **140G** and HKMG **140F**, a dielectric structure **740** (also referred to as a cut-metal-gate (or CMG) structure) is formed between the HKMG **140F** and **140G**. In some embodiments, following the formation of the HKMGs **140F-140G**, one or more etching processes may be performed to etch a trench or opening that extends vertically (in the Z-direction) into the boundary between the HKMG **140F** and **140G**. The trench or opening will then be filled by one or more dielectric materials in a subsequent deposition process to form the dielectric structure **740**. In some embodiments, the dielectric structure **740** contains silicon nitride, which is a good candidate material for preventing the conduction of electricity. In other embodiments, the dielectric structure **740** may include another electrically insulating material, for example, SiO.sub.x, SiCN, SiON, SiOCN, AlO.sub.X, HfO.sub.X, LaO.sub.X, ZrO.sub.X, or combinations thereof. In this manner, the dielectric structure **740** effectively serves as an electrical barrier to prevent the undesirable electrical shorting between the HKMG **140F** and **140G**.

(76) The conductive capping layers **300E** and **300G** are formed over the upper surfaces of the HKMG structures **140E-140F** and **140G**, respectively, through a selective growth or selective deposition process, where the materials of the conductive capping layers **300E** and **300G** are selectively grown on a metal-containing material (e.g., the metal-containing gate electrode of the HKMGs **140E-140G**), but not on non-metal materials such as dielectric materials. As such, the upper surface of the dielectric structure **740** is substantially free of having the conductive capping layers **300E** or **300G** formed thereon. In some embodiments, the selective growth process may be an embodiment of the selective growth process **550** discussed above with reference to FIG. 5. In any case, the selective growth of the conductive capping layers **300E** and **300G** herein ensures the electrical separation between the HKMG structures **140F** and **140G**. Had a continuous conductive capping layer been formed across the upper surfaces of the HKMGs **140F** and **140G**, undesirable electrical shorting between the HKMGs **140F** and **140G** would have occurred, which would violate design rules and/or lead to IC defects or performance degradations.

(77) Still referring to FIG. 17, the gate via **320** may be formed on the conductive capping layer **300E** to provide electrical connectivity to the HKMGs **140E** and **140F** below. Again, the conductive capping layer **300E** is substantially wider than the gate via **320** and has a substantially lower resistivity than either the gate via **320** or the metal gate electrode of the HKMGs **140E-140F**. Accordingly, the conductive capping layer **300E** helps to reduce parasitic resistance as discussed above. It is noted that although one gate via **320** is illustrated herein for reasons of simplicity, another similar gate via may also be formed on the conductive capping layer **300G** to provide electrical connectivity to the HKMG **140G**, and the conductive capping layer **300G** may also help to reduce the parasitic gate resistance.

(78) FIG. 17 illustrates how the conductive capping layer may be arranged to ensure the electrical separation of gate structures in an embodiment where the IC device **200** includes a CMG structure. FIG. 18 illustrates how the conductive capping layer may be arranged to ensure the electrical separation of gate structures in another embodiment where the IC device **200** includes dielectric fin structures instead of a CMG structure. In more detail, FIG. 18 illustrates a three-dimensional perspective view of the embodiment of the IC device **200**. The IC device **200** includes three example vertical stacks **170L**, **170M**, **170N**, of nano-structures. The nano-structures contain a semiconductor material (e.g., silicon) and each extend in the X-direction. Within each of the stacks **170L-170N**, the nano-structures are disposed over one another vertically in the Z-direction. The stacks **170L-170N** are separated from one another horizontally in the Y-direction, and they are each surrounded by a respective HKMG **140L**, **140M**, and **140N**.

(79) As shown in FIG. 18, the IC device **200** includes dielectric fin structures **750A** and **750B** (also



referred to as hybrid fin structures). Unlike the fin structures **120L-120N**, the dielectric fin structures **750A-750B** are not meant to serve as the active regions of transistors. Rather, the dielectric fin structures **750A-750B** are configured to prevent the merging of adjacently disposed epitaxially-grown source/drain components of the IC device **200**, so as to prevent the unintentional electrical shorting between these epitaxially-grown source/drain components. As such, the dielectric fin structures **750A-750B** each include a plurality of electrically insulating materials. For example, the dielectric fin structure **750A** includes dielectric layers **751A**, **752A**, and **753A**. The dielectric layer **751A** may include a low-k dielectric material or silicon oxide. The dielectric layer **752A** may include silicon carbon nitride and may surround the side and bottom surfaces of the dielectric layer **751A**. The dielectric layer **753A** may include a high-k dielectric material and may be located over the upper surfaces of the dielectric layers **751A** and **752A**. Similarly, the dielectric fin structure **750B** includes dielectric layers **751B**, **752B**, and **753B**, which are arranged the same as, and have material compositions substantially similar to, the dielectric layers **751A**, **752A**, and **753A**.

(80) In the embodiment shown in FIG. **18**, the dielectric fin structure **750A** is also disposed between the HKMGs **140L-140M**, and the dielectric fin structure **750B** is also disposed between the HKMGs **140M-140N**. Design rules may allow the HKMGs **140M** and **140N** to be electrically connected to each other, and therefore a conductive capping layer **300M** is formed over a substantial entirety of the upper surfaces of both the HKMGs **140M** and **140N**, as well as over the upper surface of the dielectric fin structure **750B**. In other words, the conductive capping layer **300M** may electrically connect the HKMG **140M** and HKMG **140N** together. However, the design rules may also specify that HKMG **140L** need to be electrically isolated from the HKMGs **140M-140N**. Therefore, a conductive capping layer **300L** is formed over a substantial entirety of an upper surface of the HKMG **140L**, but it is separated from the conductive capping layer **300M**, since no portions of the conductive capping layers **300L** or **300M** are formed over the dielectric fin structure **750A** (specifically, over the dielectric layer **753A**).

(81) In some embodiments, a continuous conductive capping layer is initially formed over the upper surfaces of the HKMGs **140L-140N** and the dielectric layers **753A-753B** (of the dielectric fin structures **750A-750B**). Thereafter, one or more etching processes may be performed to etch away portions of such a conductive capping layer over the dielectric layer **753A**. In this manner, the continuous conductive capping layer is broken up into the conductive capping layers **300L** and **300M**. The disconnection between the conductive capping layers **300L** and **300M** prevents the unintentional electrical shorting between the HKMGs **140L** and **140M-140N**.

(82) It is understood that a gate via (similar to the gate via **320** discussed above, but not specifically illustrated herein for reasons of simplicity) may be formed over the conductive capping layer **300L**, or over the conductive capping layer **300M**. Again, the conductive capping layer may have a substantially greater dimension in the Y-direction, as well as a lower resistivity, than such a gate via. As such, the implementation of the conductive capping layers **300L** or **300M** helps to reduce parasitic gate resistance in the manner discussed above.

(83) In addition to not shorting adjacent gate structures, the implementation of the conductive capping layers herein is also carefully configured to avoid shorting source/drain contacts that are adjacent to one another, which may be achieved using gate spacers. For example, referring now to FIG. **19**, a cross-sectional side view of an embodiment of the IC device **200** is taken along the X-direction and the Z-direction (e.g., an X-cut). The nano-structures in FIG. **19** are arranged into vertical stacks of **170P**, **170Q**, and **170R**. HKMGs **140P**, **140Q**, and **140R** are formed over the stacks **170P**, **170Q**, and **170R**, respectively. Conductive capping layers **300P**, **300Q**, and **300R** are formed over the HKMGs **140P**, **140Q**, and **140R**, respectively. As discussed above, the conductive capping layers **300P-300R** have lower resistivity than the metal gate electrodes of the HKMGs **140P-140R** and the gate vias, and therefore help reduce gate resistance.

(84) The stacks **170P** and **170Q** are separated in the X-direction by a source/drain component

**760A**, and the stacks **170Q** and **170R** are separated in the X-direction by a source/drain component **760B**. A source/drain contact **770A** is formed over the source/drain component **760A**, and a source/drain contact **770B** is formed over the source/drain component **760B**, to provide electrical connectivity to the source/drain components **760A** and **760B**, respectively. Design rules may specify that the source/drain contact **770A** be kept electrically isolated from the source/drain contact **770B**. Therefore, gate spacer structures **160A-160D** are implemented to ensure that the conductive capping layers do not inadvertently connect these source/drain contacts **770A-770B** together electrically. Specifically, a gate spacer structure **160A** is formed between the conductive capping layer **300P** and the source/drain contact **770A**, a gate spacer structure **160B** is formed between the conductive capping layer **300Q** and the source/drain contact **770A**, a gate spacer structure **160C** is formed between the conductive capping layer **300Q** and the source/drain contact **770B**, and a gate spacer structure **160D** is formed between the conductive capping layer **300R** and the source/drain contact **770B**.

(85) It is understood that in some embodiments, each of the gate spacer structures **160A-160D** may include multiple gate spacers (e.g., two or three different gate spacers). In some embodiments, the multiple gate spacers may have different material compositions. For example, one gate spacer may include silicon oxide, while another gate spacer may include silicon nitride, etc. In other embodiments, the different gate spacers may include different types of silicon oxide. Since the gate spacer structures **160A-160D** are electrically insulating, inadvertent electrical shorting between the conductive capping layers **300P-300R** and their respective nearby source/drain contacts **770A-770B** is prevented.

(86) It is understood that the IC device discussed above with the low-resistance conductive capping layer may be implemented in a variety of IC applications, including memory devices such as Static Random-Access Memory (SRAM) devices. In that regard, FIG. 20 illustrates an example circuit schematic for a single-port SRAM cell (e.g., 1-bit SRAM cell) **800**. The single-port SRAM cell **800** includes pull-up transistors **PU1**, **PU2**; pull-down transistors **PD1**, **PD2**; and pass-gate transistors **PG1**, **PG2**. As show in the circuit diagram, transistors **PU1** and **PU2** are p-type transistors, and transistors **PG1**, **PG2**, **PD1**, and **PD2** are n-type transistors. According to the various aspects of the present disclosure, the **PG1**, **PG2**, **PD1**, and **PD2** transistors are implemented with thinner spacers than the **PU1** and **PU2** transistors. Since the SRAM cell **800** includes six transistors in the illustrated embodiment, it may also be referred to as a 6T SRAM cell.

(87) The drains of pull-up transistor **PU1** and pull-down transistor **PD1** are coupled together, and the drains of pull-up transistor **PU2** and pull-down transistor **PD2** are coupled together. Transistors **PU1** and **PD1** are cross-coupled with transistors **PU2** and **PD2** to form a first data latch. The gates of transistors **PU2** and **PD2** are coupled together and to the drains of transistors **PU1** and **PD1** to form a first storage node **SN1**, and the gates of transistors **PU1** and **PD1** are coupled together and to the drains of transistors **PU2** and **PD2** to form a complementary first storage node **SNB1**. Sources of the pull-up transistors **PU1** and **PU2** are coupled to power voltage **Vcc** (also referred to as **Vdd**), and the sources of the pull-down transistors **PD1** and **PD2** are coupled to a voltage **Vss**, which may be an electrical ground in some embodiments.

(88) The first storage node **SN1** of the first data latch is coupled to bit line **BL** through pass-gate transistor **PG1**, and the complementary first storage node **SNB1** is coupled to complementary bit line **BLB** through pass-gate transistor **PG2**. The first storage node **N1** and the complementary first storage node **SNB1** are complementary nodes that are often at opposite logic levels (logic high or logic low). Gates of pass-gate transistors **PG1** and **PG2** are coupled to a word line **WL**. SRAM devices such as the SRAM cell **800** may be implemented using “planar” transistor devices, with FinFET devices, and/or with GAA devices.

(89) FIG. 21 illustrates an integrated circuit fabrication system **900** according to embodiments of the present disclosure. The fabrication system **900** includes a plurality of entities **902**, **904**, **906**, **908**, **910**, **912**, **914**, **916** . . . , **N** that are connected by a communications network **918**. The network

**918** may be a single network or may be a variety of different networks, such as an intranet and the Internet, and may include both wire line and wireless communication channels.

(90) In an embodiment, the entity **902** represents a service system for manufacturing collaboration; the entity **904** represents an user, such as product engineer monitoring the interested products; the entity **906** represents an engineer, such as a processing engineer to control process and the relevant recipes, or an equipment engineer to monitor or tune the conditions and setting of the processing tools; the entity **908** represents a metrology tool for IC testing and measurement; the entity **910** represents a semiconductor processing tool, such the processing tools to perform the selective growth process **550** discussed above; the entity **912** represents a virtual metrology module associated with the processing tool **910**; the entity **914** represents an advanced processing control module associated with the processing tool **910** and additionally other processing tools; and the entity **916** represents a sampling module associated with the processing tool **910**.

(91) Each entity may interact with other entities and may provide integrated circuit fabrication, processing control, and/or calculating capability to and/or receive such capabilities from the other entities. Each entity may also include one or more computer systems for performing calculations and carrying out automations. For example, the advanced processing control module of the entity **914** may include a plurality of computer hardware having software instructions encoded therein. The computer hardware may include hard drives, flash drives, CD-ROMs, RAM memory, display devices (e.g., monitors), input/output device (e.g., mouse and keyboard). The software instructions may be written in any suitable programming language and may be designed to carry out specific tasks.

(92) The integrated circuit fabrication system **900** enables interaction among the entities for the purpose of integrated circuit (IC) manufacturing, as well as the advanced processing control of the IC manufacturing. In an embodiment, the advanced processing control includes adjusting the processing conditions, settings, and/or recipes of one processing tool applicable to the relevant wafers according to the metrology results.

(93) In another embodiment, the metrology results are measured from a subset of processed wafers according to an optimal sampling rate determined based on the process quality and/or product quality. In yet another embodiment, the metrology results are measured from chosen fields and points of the subset of processed wafers according to an optimal sampling field/point determined based on various characteristics of the process quality and/or product quality.

(94) One of the capabilities provided by the IC fabrication system **900** may enable collaboration and information access in such areas as design, engineering, and processing, metrology, and advanced processing control. Another capability provided by the IC fabrication system **900** may integrate systems between facilities, such as between the metrology tool and the processing tool. Such integration enables facilities to coordinate their activities. For example, integrating the metrology tool and the processing tool may enable manufacturing information to be incorporated more efficiently into the fabrication process or the APC module, and may enable wafer data from the online or in site measurement with the metrology tool integrated in the associated processing tool.

(95) FIG. **22** is a flowchart illustrating a method **1000** of fabricating a semiconductor device. The method **1000** includes a step **1010** to form a gate structure over a plurality of stacks of nano-structures. The nano-structures are disposed over one another in a vertically direction and each extend in a first horizontal direction. The gate structure extends in a second horizontal direction different from the first horizontal direction. The gate structure contains metal.

(96) The method **1000** includes a step **1020** to etch back a portion of the gate structure.

(97) The method **1000** includes a step **1030** to grow a conductive capping layer on the gate structure after the gate structure has been etched back. The conductive capping layer has a lower resistivity than the metal of the gate structure. The conductive capping layer spans a substantial entirety of tan upper surface of the gate structure in the second horizontal direction.

(98) The method **1000** includes a step **1040** to form a gate via over the conductive capping layer. The conductive capping layer is substantially wider than the gate via.

(99) In some embodiments, the step **1010** includes forming a high-k gate dielectric and a metal-containing gate electrode. The metal-containing gate electrode includes a plurality of conductive layers and a non-conductive layer. In some embodiments, the step **1030** includes selectively growing the conductive capping layer directly on upper surfaces of the conductive layers, but not directly on an upper surface of the non-conductive layer.

(100) In some embodiments, the step **1010** includes forming a first gate structure and forming a second gate structure. In some embodiments, the method further includes a step to form a dielectric structure that separates the first gate structure and the second gate structure in the second horizontal direction.

(101) In some embodiments, the step **1030** includes selectively growing the conductive capping layer on upper surfaces of the first gate structure and the second gate structure, but not on upper surfaces of the dielectric structure.

(102) It is understood that additional steps may be performed before, during, or after the steps **1010-1040**. For example, the method **1000** may include a step of forming the stacks of nano-structures before the gate structure is formed. The method **1000** may also include the formation of other conductive contacts and vias, interconnect lines, packaging, and testing processes. For reasons of simplicity, these additional steps are not discussed in detail herein.

(103) FIG. **23** is a flowchart illustrating a method **1100** of fabricating a semiconductor device. The method **1100** includes a step **1110** to form a gate structure that contains a metal gate electrode over a plurality of stacks of nano-structures. The nano-structures are disposed over one another in a vertically direction and each extend in a first horizontal direction. The gate structure extends in a second horizontal direction different from the first horizontal direction.

(104) The method **1100** includes a step **1120** to etch back a portion of the gate structure.

(105) The method **1100** includes a step **1130** to deposit a glue layer over the gate structure after the gate structure has been etched back.

(106) The method **1100** includes a step **1140** to form a conductive capping layer on the glue layer. The conductive capping layer and the glue layer are formed with different material compositions.

(107) The method **1100** includes a step **1150** to form a gate via over a portion of an upper surface of the conductive capping layer. The gate via and the metal gate electrode each have a greater resistivity than the conductive capping layer.

(108) In some embodiments, the metal gate electrode includes a plurality of conductive layers and a non-conductive layer. In some embodiments the step **1130** comprises depositing the glue layer directly on upper surfaces of the conductive layers and the non-conductive layer, the glue layer defining a recess. In some embodiments, the conductive capping layer is formed in the recess and spans over a substantial entirety of an upper surface of the gate structure in the second horizontal direction.

(109) In some embodiments, the step **1130** comprises depositing a titanium nitride layer as the glue layer. In some embodiments, the step **1140** comprises forming a tungsten-containing layer as the conductive layer.

(110) In some embodiments, the step **1110** includes forming a first gate structure and forming a second gate structure. In some embodiments, the method **1100** further comprises: forming a dielectric fin structure that separates the first gate structure and the second gate structure in the second horizontal direction, wherein the conductive capping layer is formed over upper surfaces of the first gate structure, the second gate structure, and the dielectric fin structure; and removing, through one or more etching processes, a portion of the conductive capping layer covering the dielectric fin structure.

(111) It is understood that additional steps may be performed before, during, or after the steps **1110-1150**. For example, the method **1100** may include a step of forming the nano-structures before the

gate structure is formed on the fin structures or on the nano-structures. The method 1100 may also include the formation of other conductive contacts and vias, interconnect lines, packaging, and testing processes. For reasons of simplicity, these additional steps are not discussed in detail herein. (112) In summary, the present disclosure involves forming a conductive capping layer over a gate structure of an IC device. The conductive capping layer has a lower resistivity than the metal-containing gate electrode of the gate structure, as well as having a lower resistivity than a gate via that is then formed on the conductive capping layer. The conductive capping layer also extends along a substantial entirety of the upper surface of the gate structure in at least a Y-direction, which is the same direction in which the gate structure extends. As such, the conductive capping layer is formed over a gate structure that surrounds a plurality of stacks of nano-structures. In a first process flow, the conductive capping layer is formed by etching back a portion of the gate structure, and then selectively growing a low-resistivity material on the various metal-containing layers of the etched-back gate structure. In a second process flow, the conductive capping layer is formed by etching back a portion of the gate structure, depositing a glue layer on the etched-back gate structure, and then depositing a low-resistivity material on the glue layer.

(113) The unique fabrication process flow and the resulting IC device structure of the present disclosure offers advantages over conventional devices. It is understood, however, that no particular advantage is required, other embodiments may offer different advantages, and that not all advantages are necessarily disclosed herein. One advantage is the improved performance of IC devices. For example, as device sizes are scaled down in newer technology generations, gate resistance may become a greater concern than in prior technology generations. This is even more pronounced for active regions that are located far away from the gate via. The increase in gate resistance (especially for these far away devices) may result in a greater time constant, which corresponds to a longer delay and/or slower device speed, a larger signal loss, etc. Here, by implementing the low-resistivity conductive capping layer along a substantial entirety of the upper surface of the gate structure in at least the Y-direction, the gate resistance may be substantially reduced, such that even the devices located far away from the gate via may experience a much smaller gate resistance. Consequently, the IC devices herein may exhibit improved performance, such as faster speed, reduced signal loss, etc. Another advantage is that the conductive capping layers can be selectively deposited, or etched, in a manner such that they do not present electrical shorting risks. Therefore, the conductive capping layers herein are fully compatible with existing fabrication processes/devices, for example, with IC devices that utilize CMG structures or dielectric fin structures.

(114) The advanced lithography process, method, and materials described above can be used in many applications, including multi-channel devices such as Gate-All-Around (GAA) devices, or fin-type field effect transistors (FinFETs). In the case of FinFETs, the fins may be patterned to produce a relatively close spacing between features, for which the above disclosure is well suited. In addition, spacers used in forming fins of FinFETs, also referred to as mandrels, can be processed according to the above disclosure. To the extent that the present disclosure refers to a fin structure or FinFET devices, such discussions may apply equally to the GAA devices, or vice versa.

(115) One aspect of the present disclosure pertains to a semiconductor device. The semiconductor device includes a plurality of stacks of nano-structures. The nano-structures each extend in a first horizontal direction. The stacks each extend in a vertical direction and are separated from one another in a second horizontal direction different from the first horizontal direction. A first gate structure is disposed over a first subset of the stacks of nano-structures. The first gate structure surrounds each of the nano-structures in the first subset. A second gate structure is disposed over a second subset of the stacks of nano-structures. The second gate structure surrounds each of the nano-structures in the second subset. A first conductive capping layer is disposed over a substantial entirety of an upper surface of the first gate structure. A second conductive capping layer is disposed over a substantial entirety of an upper surface of the second gate structure. A dielectric

structure is disposed between the first gate structure and the second gate structure in the second horizontal direction. The dielectric structure physically and electrically separates the first gate structure and the second gate structure. An upper surface of the dielectric structure is substantially free of having the first conductive capping layer or the second conductive capping layer disposed thereon.

(116) Another aspect of the present disclosure pertains to a method of fabricating a semiconductor device. A gate structure is formed over a plurality of stacks of nano-structures. The nano-structures are disposed over one another in a vertically direction and each extend in a first horizontal direction. The gate structure extends in a second horizontal direction different from the first horizontal direction. The gate structure contains metal. A portion of the gate structure is etched back. A conductive capping layer is grown on the gate structure after the gate structure has been etched back. The conductive capping layer has a lower resistivity than the metal of the gate structure. The conductive capping layer spans a substantial entirety of an upper surface of the gate structure in the second horizontal direction. A gate via is formed over the conductive capping layer. The conductive capping layer is substantially wider than the gate via.

(117) Another aspect of the present disclosure pertains to a method of fabricating a semiconductor device. A gate structure is formed that contains a metal gate electrode over a plurality of stacks of nano-structures. The nano-structures are disposed over one another in a vertically direction and each extend in a first horizontal direction. The gate structure extends in a second horizontal direction different from the first horizontal direction. A portion of the gate structure is etched back. A glue layer is deposited over the gate structure after the gate structure has been etched back. A conductive capping is formed layer on the glue layer. The conductive capping layer and the glue layer are formed with different material compositions. A gate via is formed over a portion of an upper surface of the conductive capping layer. The gate via and the metal gate electrode each have a greater resistivity than the conductive capping layer.

(118) The foregoing has outlined features of several embodiments so that those skilled in the art may better understand the detailed description that follows. Those skilled in the art should appreciate that they may readily use the present disclosure as a basis for designing or modifying other processes and structures for carrying out the same purposes and/or achieving the same advantages of the embodiments introduced herein. Those skilled in the art should also realize that such equivalent constructions do not depart from the spirit and scope of the present disclosure, and that they may make various changes, substitutions and alterations herein without departing from the spirit and scope of the present disclosure. For example, by implementing different thicknesses for the bit line conductor and word line conductor, one can achieve different resistances for the conductors. However, other techniques to vary the resistances of the metal conductors may also be utilized as well.

## Claims

1. A device, comprising: a plurality of stacks of nano-structures, wherein the nano-structures each extend in a first horizontal direction, wherein the stacks each extend in a vertical direction and are separated from one another in a second horizontal direction different from the first horizontal direction; a first gate structure disposed over a first subset of the stacks of nano-structures, wherein the first gate structure surrounds each of the nano-structures in the first subset; a second gate structure disposed over a second subset of the stacks of nano-structures, wherein the second gate structure surrounds each of the nano-structures in the second subset; a first conductive capping layer disposed over a substantial entirety of an upper surface of the first gate structure; a second conductive capping layer disposed over a substantial entirety of an upper surface of the second gate structure; and a dielectric structure disposed between the first gate structure and the second gate structure in the second horizontal direction, wherein the dielectric structure physically and

electrically separates the first gate structure and the second gate structure, and wherein an upper surface of the dielectric structure is substantially free of having the first conductive capping layer or the second conductive capping layer disposed thereon.

2. The device of claim 1, wherein the dielectric structure includes a cut-metal-gate (CMG) structure that contains a single type of dielectric material.
3. The device of claim 1, wherein the dielectric structure includes a dielectric fin structure that contains multiple types of dielectric materials.
4. The device of claim 1, a gate via disposed over the first conductive capping layer or over the second conductive capping layer, wherein a dimension of the gate via measured in the second horizontal direction is substantially less than a dimension of the first conductive capping layer or the second conductive capping layer measured in the second horizontal direction.
5. The device of claim 4, wherein the dimension of the first conductive capping layer or the second conductive capping layer is at least multiple times greater than the dimension of the gate via.
6. The device of claim 4, wherein the first conductive capping layer and the second conductive capping layer each have a lower resistivity than the gate via, the first gate structure, and the second gate structure.
7. The device of claim 1, further comprising a source/drain contact and a gate spacer structure, wherein the gate spacer structure physically and electrically separates the source/drain contact from the first conductive capping layer or from the second conductive capping layer in the first horizontal direction.
8. The device of claim 1, wherein the first conductive capping layer and the second conductive capping layer each contain tungsten.
9. The device of claim 1, wherein: the first gate structure and the second gate structure each include a respective metal-containing gate electrode; and the first conductive capping layer or the second conductive capping layer has a lower resistivity than the metal-containing gate electrode.
10. The device of claim 1, wherein in a cross-sectional view defined by the first horizontal direction and the vertical direction, a bottom surface of the first conductive capping layer or the second conductive capping layer includes one or more recesses.
11. The device of claim 10, wherein: the first gate structure or the second gate structure includes one or more non-conductive layers; and the one or more recesses are located directly over the one or more non-conductive layers.
12. The device of claim 1, further comprising a glue layer disposed between the first conductive capping layer and the first gate structure or between the second conductive capping layer and the second gate structure, wherein the glue layer defines a recess in a cross-sectional view defined by the first horizontal direction and the vertical direction, and wherein the conductive capping layer is disposed within the recess in the cross-sectional view.
13. A device, comprising: a first stack of semiconductive nano-structures, wherein the semiconductive nano-structures in the first stack are disposed over one another in a vertical direction in a cross-sectional side view; a second stack of semiconductive nano-structures, wherein the semiconductive nano-structures in the second stack are disposed over one another in the vertical direction in the cross-sectional side view; a first gate that circumferentially surrounds the first stack of semiconductive nano-structures in the cross-sectional side view; a second gate that circumferentially surrounds the second stack of semiconductive nano-structures in the cross-sectional side view; a first conductive layer disposed over a substantial entirety of an upper surface of the first gate in the cross-sectional side view; a second conductive layer disposed over a substantial entirety of an upper surface of the second gate in the cross-sectional side view; and an electrically insulating structure disposed between the first gate and the second gate, and between the first conductive layer and the second conductive layer, in the cross-sectional side view.
14. The device of claim 13, wherein no portion of the first conductive layer or the second conductive layer is disposed on an uppermost surface of the electrically insulating structure in the

cross-sectional side view.

15. The device of claim 13, wherein an uppermost surface of the electrically insulating structure is wider than a bottommost surface of the electrically insulating structure in the cross-sectional side view.

16. The device of claim 13, further comprising a gate via disposed over the first conductive layer; wherein: the first conductive layer has a lower resistivity than the gate via; or the first conductive layer is at least multiple times wider than the gate via in the cross-sectional side view.

17. The device of claim 16, wherein the first conductive layer has a lower resistivity than the gate via.

18. The device of claim 16, wherein the first conductive layer is at least multiple times wider than the gate via in the cross-sectional side view.

19. The device of claim 13, wherein: the first gate has a gate electrode component; and the first conductive layer or the second conductive layer has a lower resistivity than the gate electrode component.

20. The device of claim 13, wherein the electrically insulating structure has a different depth than the first gate or the second gate in the cross-sectional side view.

21. A device, comprising: a plurality of stacks of nano-structures, wherein the nano-structures each extend in a first horizontal direction, wherein the stacks each extend in a vertical direction and are separated from one another in a second horizontal direction different from the first horizontal direction; a first gate structure disposed over a first subset of the stacks of nano-structures, wherein the first gate structure circumferentially surrounds each of the nano-structures in the first subset in a cross-sectional side view defined by the vertical direction and the second horizontal direction; a second gate structure disposed over a second subset of the stacks of nano-structures, wherein the second gate structure circumferentially surrounds each of the nano-structures in the second subset in the cross-sectional side view; a first conductive layer disposed over a substantial entirety of an upper surface of the first gate structure in the cross-sectional side view; a second conductive layer disposed over a substantial entirety of an upper surface of the second gate structure in the cross-sectional side view; and a dielectric structure disposed between the first gate structure and the second gate structure in the second horizontal direction in the cross-sectional side view, wherein the dielectric structure separates the first conductive layer from the second conductive layer.

22. The device of claim 21, wherein the dielectric structure has slanted side surfaces in the cross-sectional side view.

23. The device of claim 21, wherein no portion of the first conductive layer or the second conductive layer is disposed directly on an upper surface of the dielectric structure.

---