

# US Patent & Trademark Office

## Patent Public Search | Text View

United States Patent Application Publication

20250286604

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

CHA; Jaemoon et al.

### ELECTRONIC DEVICE CHANGING TRANSMISSION ANTENNA AND METHOD FOR OPERATING THE SAME

#### Abstract

According to an example embodiment, an electronic device includes a communication processor including processing circuitry, RF circuitry connected to the at least one communication processor, and a plurality of antennas connected to the RF circuitry. The communication processor is configured to control the RF circuitry to provide a first RF signal corresponding to a specified frequency band to the first antenna based at least in part on the portable communication device being fully unfolded. The communication processor is configured to control the RF circuitry to provide a second RF signal corresponding to the specified frequency band to the second antenna instead of the first antenna based at least in part on the portable communication device being fully folded.

**Inventors:** CHA; Jaemoon (Suwon-si, KR), JEON; Minhwan (Suwon-si, KR), PARK; Jaewoo (Suwon-si, KR), LEE; Yeonjoo (Suwon-si, KR)

**Applicant:** Samsung Electronics Co., Ltd. (Suwon-si, KR)

**Family ID:** 1000008626805

**Appl. No.:** 19/218290

**Filed:** May 25, 2025

#### Foreign Application Priority Data

KR 10-2022-0099524

Aug. 09, 2022

KR 10-2022-0127055

Oct. 05, 2022

#### Related U.S. Application Data

parent US continuation 18446814 20230809 PENDING child US 19218290

parent WO continuation PCT/KR2023/011790 20230809 PENDING child US 18446814

## Publication Classification

**Int. Cl.:** H04B7/08 (20060101); H04B7/06 (20060101)

**U.S. Cl.:**

**CPC** H04B7/0814 (20130101); H04B7/0608 (20130101);

---

## Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This application is a continuation of U.S. application Ser. No. 18/446,814, filed Aug. 9, 2023, which is a continuation of International Application No. PCT/KR2023/011790 designating the United States, filed on Aug. 9, 2023, in the Korean Intellectual Property Receiving Office and claiming priority to Korean Patent Application Nos. 10-2022-0099524, filed on Aug. 9, 2022, and 10-2022-0127055, filed on Oct. 5, 2022, in the Korean Intellectual Property Office, the disclosures of all of which are incorporated by reference herein in their entireties.

### BACKGROUND

#### Field

[0002] The disclosure relates to an electronic device changing a transmission antenna and a method for operating the same.

#### Description of Related Art

[0003] To transmit a signal from an electronic device to a communication network (e.g., a base station), data generated from a processor or a communication processor in the electronic device may be signal-processed through a radio frequency integrated circuit (RFIC) and radio frequency front-end (hereinafter, 'RFFE' for convenience of description) circuit and then transmitted to the outside of the electronic device through an antenna.

[0004] According to an embodiment, an electronic device supporting a plurality of communication networks may provide a plurality of transmission (Tx) paths for signal transmission for each communication network. The plurality of transmission paths provided to support the plurality of communication networks by the electronic device may include an RFIC and/or RFFE circuit for each path. Further, each RFFE circuit may be connected with one or more antennas and, accordingly, the plurality of transmission paths may be divided into a plurality of antenna transmission paths (antenna Tx paths) corresponding to the plurality of antennas.

[0005] Different path loss may occur in the plurality of antenna transmission paths because the lengths of the transmission paths and components disposed on the transmission paths are different from each other. Further, as the antennas respectively corresponding to the antenna transmission paths are disposed in different positions on the electronic device, different antenna losses may occur.

### SUMMARY

[0006] Embodiments of the disclosure provide an electronic device capable of configuring an optimal antenna transmission path considering the path loss and/or channel environment corresponding to each antenna when an electronic device including a plurality of antenna transmission paths transmits a transmission signal and a method for configuring an antenna path of a transmission signal by the electronic device.

[0007] According to an example embodiment, an electronic device may comprise: at least one communication processor, an RF circuitry connected to the at least one communication processor, and a plurality of antennas connected to the RF circuitry. The at least one communication processor

may be configured to, based on identifying a folding state of the electronic device being an open state, control the RF circuitry to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas. The at least one communication processor may be configured to, based on identifying the folding state of the electronic device being a closed state, identify whether the electronic device is gripped. The at least one communication processor may be configured to control the RF circuitry to provide a second RF signal corresponding to the first frequency band to a second antenna different from the first antenna among the plurality of antennas, based on identifying that the electronic device is gripped.

[0008] According to an example embodiment, a method of operating an electronic device including an RF circuitry and a plurality of antennas connected to the RF circuitry may comprise controlling the RF circuitry to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas based on identifying that a folding state of the electronic device is an open state. The method of operating the electronic device may comprise, based on identifying the folding state of the electronic device being a closed state, identifying whether the electronic device is gripped. The method of operating the electronic device may comprise controlling the RF circuitry to provide a second RF signal corresponding to the first frequency band to a second antenna different from the first antenna among the plurality of antennas, based on identifying that the electronic device is gripped.

[0009] According to an example embodiment, a non-transitory computer-readable storage medium may store instructions that, when executed by at least one processor, cause an electronic device to perform at least one operation. The at least one operation may comprise controlling the RF circuitry to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas based on identifying that a folding state of the electronic device is an open state. The at least one operation may comprise, based on identifying the folding state of the electronic device being a closed state, identifying whether the electronic device is gripped. The at least one operation may comprise controlling the RF circuitry to provide a second RF signal corresponding to the first frequency band to a second antenna different from the first antenna among the plurality of antennas, based on identifying that the electronic device is gripped.

[0010] According to an example embodiment, an electronic device may comprise at least one communication processor, a camera, an RF circuitry connected to the at least one communication processor, and a plurality of antennas connected to the RF circuitry. The at least one communication processor may be configured to, based on identifying that the camera is in an off state, control the RF circuitry to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas. The at least one communication processor may be configured to control the RF circuitry to provide a second RF signal corresponding to the first frequency band to a second antenna different from the first antenna among the plurality of antennas, based on identifying that the camera is changed from the off state to an on state.

[0011] According to an example embodiment, a method of operating an electronic device including a camera, an RF circuitry, and a plurality of antennas connected to the RF circuitry may comprise controlling the RF circuitry to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas based on identifying that the camera is in an off state. The method of operating the electronic device may comprise controlling the RF circuitry to provide a second RF signal corresponding to the first frequency band to a second antenna different from the first antenna among the plurality of antennas, based on identifying that the camera is changed from the off state to an on state.

[0012] According to an example embodiment, a non-transitory computer-readable storage medium may store instructions that, when executed by at least one processor, cause an electronic device to perform at least one operation. The at least one operation may comprise controlling the RF circuitry of the electronic device to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas based on identifying that the camera is in an off state. The

at least one operation may comprise controlling the RF circuitry to provide a second RF signal corresponding to the first frequency band to a second antenna different from the first antenna among the plurality of antennas, based on identifying that the camera is changed from the off state to an on state.

[0013] According to an example embodiment, an electronic device may comprise at least one communication processor, an RF circuitry connected to the at least one communication processor, and a plurality of antennas connected to the RF circuitry. The at least one communication processor may be configured to control the RF circuitry to provide a first RF signal corresponding to a first sub frequency of a first frequency band to a first antenna among the plurality of antennas. The at least one communication processor may be configured to identify whether at least one first parameter associated with the first antenna and at least one second parameter associated with the second antenna meet an antenna change condition, wherein the condition may be set corresponding to the first sub frequency of the first frequency band. The at least one communication processor may be configured to control the RF circuitry to provide a second RF signal corresponding to the first sub frequency of the first frequency band to a second antenna different from the first antenna among the plurality of antennas, based on the at least one first parameter and the at least one second parameter meeting the condition.

[0014] According to an example embodiment, a method of operating an electronic device including an RF circuitry and a plurality of antennas connected to the RF circuitry may comprise controlling the RF circuitry to provide a first RF signal corresponding to a first sub frequency of a first frequency band to a first antenna among the plurality of antennas. The method of operating the electronic device may include identifying whether at least one first parameter associated with the first antenna and at least one second parameter associated with the second antenna meet an antenna change condition, wherein the condition may be set corresponding to the first sub frequency of the first frequency band. The method of operating the electronic device may comprise controlling the RF circuitry to provide a second RF signal corresponding to the first sub frequency of the first frequency band to a second antenna different from the first antenna among the plurality of antennas, based on the at least one first parameter and the at least one second parameter meeting the condition.

[0015] According to an example embodiment, a non-transitory computer-readable storage medium may store instructions that, when executed by at least one processor, cause an electronic device to perform at least one operation. The at least one operation may comprise controlling the RF circuitry of the electronic device to provide a first RF signal corresponding to a first sub frequency of a first frequency band to a first antenna among the plurality of antennas of the electronic device. The at least one operation may comprise identifying whether at least one first parameter associated with the first antenna and at least one second parameter associated with the second antenna meet an antenna change condition, wherein the condition may be set corresponding to the first sub frequency of the first frequency band. The at least one operation may comprise controlling the RF circuitry to provide a second RF signal corresponding to the first sub frequency of the first frequency band to a second antenna different from the first antenna among the plurality of antennas, based on the at least one first parameter and the at least one second parameter meeting the condition.

---

## **Description**

### **BRIEF DESCRIPTION OF THE DRAWINGS**

[0016] The above and other aspects, features and advantages of certain embodiments of the present disclosure will be more apparent from the following detailed description, taken in conjunction with the accompanying drawings, in which:

[0017] FIG. 1 is a block diagram illustrating an example electronic device in a network environment according to various embodiments;

[0018] FIG. 2A is a block diagram illustrating an example configuration of an electronic device for supporting legacy network communication and 5G network communication according to various embodiments;

[0019] FIG. 2B is a block diagram illustrating an example configuration of an electronic device for supporting legacy network communication and 5G network communication according to various embodiments;

[0020] FIG. 3A is a diagram illustrating an example change of transmission antennas according to various embodiments;

[0021] FIG. 3B is a diagram illustrating an example change of transmission antennas according to various embodiments;

[0022] FIG. 4A is a flowchart illustrating an example method of operating an electronic device according to various embodiments;

[0023] FIG. 4B is a diagram illustrating a housing of an electronic device according to various embodiments;

[0024] FIG. 4C is a diagram illustrating antennas in an open state of an electronic device according to various embodiments;

[0025] FIG. 4D is a diagram illustrating antennas in a closed state of an electronic device according to various embodiments;

[0026] FIG. 4E is a diagram illustrating human body contact in a closed state according to various embodiments;

[0027] FIG. 4F is a diagram illustrating various folding states of an electronic device according to various embodiments;

[0028] FIG. 5A is a flowchart illustrating an example method of operating an electronic device according to various embodiments;

[0029] FIG. 5B is a flowchart illustrating an example method of operating an electronic device according to various embodiments;

[0030] FIG. 6 is a flowchart illustrating an example method of operating an electronic device according to various embodiments;

[0031] FIG. 7A is a flowchart illustrating an example method of operating an electronic device according to various embodiments;

[0032] FIG. 7B is a diagram illustrating an arrangement of an antenna and a camera according to various embodiments;

[0033] FIG. 7C is a flowchart illustrating an example method of operating an electronic device according to various embodiments;

[0034] FIG. 7D is a flowchart illustrating an example method of operating an electronic device according to various embodiments; and

[0035] FIG. 8 is a flowchart illustrating an example method of operating an electronic device according to various embodiments.

#### DETAILED DESCRIPTION

[0036] FIG. 1 is a block diagram illustrating an example electronic device **101** in a network environment **100** according to an embodiment. Referring to FIG. 1, the electronic device **101** in the network environment **100** may communicate with an electronic device **102** via a first network **198** (e.g., a short-range wireless communication network), or an electronic device **104** or a server **108** via a second network **199** (e.g., a long-range wireless communication network). According to an embodiment, the electronic device **101** may communicate with the electronic device **104** via the server **108**. According to an embodiment, the electronic device **101** may include a processor **120**, memory **130**, an input module **150**, a sound output module **155**, a display module **160**, an audio module **170**, a sensor module **176**, an interface **177**, a connecting terminal **178**, a haptic module

**179**, a camera module **180**, a power management module **188**, a battery **189**, a communication module **190**, a subscriber identification module (SIM) **196**, or an antenna module **197**. In an embodiment, at least one (e.g., the connecting terminal **178**) of the components may be omitted from the electronic device **101**, or one or more other components may be added in the electronic device **101**. According to an embodiment, some (e.g., the sensor module **176**, the camera module **180**, or the antenna module **197**) of the components may be integrated into a single component (e.g., the display module **160**).

[0037] The processor **120** may execute, for example, software (e.g., a program **140**) to control at least one other component (e.g., a hardware or software component) of the electronic device **101** coupled with the processor **120**, and may perform various data processing or computation. According to an embodiment, as at least part of the data processing or computation, the processor **120** may store a command or data received from another component (e.g., the sensor module **176** or the communication module **190**) in volatile memory **132**, process the command or the data stored in the volatile memory **132**, and store resulting data in non-volatile memory **134**. According to an embodiment, the processor **120** may include a main processor **121** (e.g., a central processing unit (CPU) or an application processor (AP)), or an auxiliary processor **123** (e.g., a graphics processing unit (GPU), a neural processing unit (NPU), an image signal processor (ISP), a sensor hub processor, or a communication processor (CP)) that is operable independently from, or in conjunction with, the main processor **121**. For example, when the electronic device **101** includes the main processor **121** and the auxiliary processor **123**, the auxiliary processor **123** may be configured to use lower power than the main processor **121** or to be specified for a designated function. The auxiliary processor **123** may be implemented as separate from, or as part of the main processor **121**.

[0038] The auxiliary processor **123** may control at least some of functions or states related to at least one component (e.g., the display module **160**, the sensor module **176**, or the communication module **190**) among the components of the electronic device **101**, instead of the main processor **121** while the main processor **121** is in an inactive (e.g., sleep) state, or together with the main processor **121** while the main processor **121** is in an active state (e.g., executing an application). According to an embodiment, the auxiliary processor **123** (e.g., an image signal processor or a communication processor) may be implemented as part of another component (e.g., the camera module **180** or the communication module **190**) functionally related to the auxiliary processor **123**. According to an embodiment, the auxiliary processor **123** (e.g., the neural processing unit) may include a hardware structure specified for artificial intelligence model processing. The artificial intelligence model may be generated via machine learning. Such learning may be performed, e.g., by the electronic device **101** where the artificial intelligence is performed or via a separate server (e.g., the server **108**). Learning algorithms may include, but are not limited to, e.g., supervised learning, unsupervised learning, semi-supervised learning, or reinforcement learning. The artificial intelligence model may include a plurality of artificial neural network layers. The artificial neural network may be a deep neural network (DNN), a convolutional neural network (CNN), a recurrent neural network (RNN), a restricted Boltzmann machine (RBM), a deep belief network (DBN), a bidirectional recurrent deep neural network (BRDNN), deep Q-network or a combination of two or more thereof but is not limited thereto. The artificial intelligence model may, additionally or alternatively, include a software structure other than the hardware structure.

[0039] The memory **130** may store various data used by at least one component (e.g., the processor **120** or the sensor module **176**) of the electronic device **101**. The various data may include, for example, software (e.g., the program **140**) and input data or output data for a command related thereto. The memory **130** may include the volatile memory **132** or the non-volatile memory **134**.

[0040] The program **140** may be stored in the memory **130** as software, and may include, for example, an operating system (OS) **142**, middleware **144**, or an application **146**.

[0041] The input module **150** may receive a command or data to be used by other component (e.g.,

the processor **120**) of the electronic device **101**, from the outside (e.g., a user) of the electronic device **101**. The input module **150** may include, for example, a microphone, a mouse, a keyboard, keys (e.g., buttons), or a digital pen (e.g., a stylus pen).

[0042] The sound output module **155** may output sound signals to the outside of the electronic device **101**. The sound output module **155** may include, for example, a speaker or a receiver. The speaker may be used for general purposes, such as playing multimedia or playing record. The receiver may be used for receiving incoming calls. According to an embodiment, the receiver may be implemented as separate from, or as part of the speaker.

[0043] The display module **160** may visually provide information to the outside (e.g., a user) of the electronic device **101**. The display **160** may include, for example, a display, a hologram device, or a projector and control circuitry to control a corresponding one of the display, hologram device, and projector. According to an embodiment, the display **160** may include a touch sensor configured to detect a touch, or a pressure sensor configured to measure the intensity of a force generated by the touch.

[0044] The audio module **170** may convert a sound into an electrical signal and vice versa. According to an embodiment, the audio module **170** may obtain the sound via the input module **150**, or output the sound via the sound output module **155** or a headphone of an external electronic device (e.g., an electronic device **102**) directly (e.g., wiredly) or wirelessly coupled with the electronic device **101**.

[0045] The sensor module **176** may detect an operational state (e.g., power or temperature) of the electronic device **101** or an environmental state (e.g., a state of a user) external to the electronic device **101**, and then generate an electrical signal or data value corresponding to the detected state. According to an embodiment, the sensor module **176** may include, for example, a gesture sensor, a gyro sensor, an atmospheric pressure sensor, a magnetic sensor, an accelerometer, a grip sensor, a proximity sensor, a color sensor, an infrared (IR) sensor, a biometric sensor, a temperature sensor, a humidity sensor, or an illuminance sensor.

[0046] The interface **177** may support one or more specified protocols to be used for the electronic device **101** to be coupled with the external electronic device (e.g., the electronic device **102**) directly (e.g., wiredly) or wirelessly. According to an embodiment, the interface **177** may include, for example, a high definition multimedia interface (HDMI), a universal serial bus (USB) interface, a secure digital (SD) card interface, or an audio interface.

[0047] A connecting terminal **178** may include a connector via which the electronic device **101** may be physically connected with the external electronic device (e.g., the electronic device **102**). According to an embodiment, the connecting terminal **178** may include, for example, a HDMI connector, a USB connector, a SD card connector, or an audio connector (e.g., a headphone connector).

[0048] The haptic module **179** may convert an electrical signal into a mechanical stimulus (e.g., a vibration or motion) or electrical stimulus which may be recognized by a user via his tactile sensation or kinesthetic sensation. According to an embodiment, the haptic module **179** may include, for example, a motor, a piezoelectric element, or an electric stimulator.

[0049] The camera module **180** may capture a still image or moving images. According to an embodiment, the camera module **180** may include one or more lenses, image sensors, image signal processors, or flashes.

[0050] The power management module **188** may manage power supplied to the electronic device **101**. According to an embodiment, the power management module **188** may be implemented as at least part of, for example, a power management integrated circuit (PMIC).

[0051] The battery **189** may supply power to at least one component of the electronic device **101**. According to an embodiment, the battery **189** may include, for example, a primary cell which is not rechargeable, a secondary cell which is rechargeable, or a fuel cell.

[0052] The communication module **190** may support establishing a direct (e.g., wired)

communication channel or a wireless communication channel between the electronic device **101** and the external electronic device (e.g., the electronic device **102**, the electronic device **104**, or the server **108**) and performing communication via the established communication channel. The communication module **190** may include one or more communication processors that are operable independently from the processor **120** (e.g., the application processor (AP)) and supports a direct (e.g., wired) communication or a wireless communication. According to an embodiment, the communication module **190** may include a wireless communication module **192** (e.g., a cellular communication module, a short-range wireless communication module, or a global navigation satellite system (GNSS) communication module) or a wired communication module **194** (e.g., a local area network (LAN) communication module or a power line communication (PLC) module). A corresponding one of these communication modules may communicate with the external electronic device **104** via a first network **198** (e.g., a short-range communication network, such as Bluetooth™, wireless-fidelity (Wi-Fi) direct, or infrared data association (IrDA)) or a second network **199** (e.g., a long-range communication network, such as a legacy cellular network, a 5G network, a next-generation communication network, the Internet, or a computer network (e.g., local area network (LAN) or wide area network (WAN))). These various types of communication modules may be implemented as a single component (e.g., a single chip), or may be implemented as multi components (e.g., multi chips) separate from each other. The wireless communication module **192** may identify or authenticate the electronic device **101** in a communication network, such as the first network **198** or the second network **199**, using subscriber information (e.g., international mobile subscriber identity (IMSI)) stored in the subscriber identification module **196**.

[0053] The wireless communication module **192** may support a 5G network, after a 4G network, and next-generation communication technology, e.g., new radio (NR) access technology. The NR access technology may support enhanced mobile broadband (eMBB), massive machine type communications (mMTC), or ultra-reliable and low-latency communications (URLLC). The wireless communication module **192** may support a high-frequency band (e.g., the mm Wave band) to achieve, e.g., a high data transmission rate. The wireless communication module **192** may support various technologies for securing performance on a high-frequency band, such as, e.g., beamforming, massive multiple-input and multiple-output (massive MIMO), full dimensional MIMO (FD-MIMO), array antenna, analog beam-forming, or large scale antenna. The wireless communication module **192** may support various requirements specified in the electronic device **101**, an external electronic device (e.g., the electronic device **104**), or a network system (e.g., the second network **199**). According to an embodiment, the wireless communication module **192** may support a peak data rate (e.g., 20 Gbps or more) for implementing eMBB, loss coverage (e.g., 164 dB or less) for implementing mMTC, or U-plane latency (e.g., 0.5 ms or less for each of downlink (DL) and uplink (UL), or a round trip of 1 ms or less) for implementing URLLC.

[0054] The antenna module **197** may transmit or receive a signal or power to or from the outside (e.g., the external electronic device). According to an embodiment, the antenna module **197** may include one antenna including a radiator formed of a conductive body or conductive pattern formed on a substrate (e.g., a printed circuit board (PCB)). According to an embodiment, the antenna module **197** may include a plurality of antennas (e.g., an antenna array). In this case, at least one antenna appropriate for a communication scheme used in a communication network, such as the first network **198** or the second network **199**, may be selected from the plurality of antennas by, e.g., the communication module **190**. The signal or the power may then be transmitted or received between the communication module **190** and the external electronic device via the selected at least one antenna. According to an embodiment, other parts (e.g., radio frequency integrated circuit (RFIC)) than the radiator may be further formed as part of the antenna module **197**.

[0055] According to an embodiment, the antenna module **197** may form a mmWave antenna module. According to an embodiment, the mmWave antenna module may include a printed circuit board, a RFIC disposed on a first surface (e.g., the bottom surface) of the printed circuit board, or

adjacent to the first surface and capable of supporting a designated high-frequency band (e.g., the mmWave band), and a plurality of antennas (e.g., array antennas) disposed on a second surface (e.g., the top or a side surface) of the printed circuit board, or adjacent to the second surface and capable of transmitting or receiving signals of the designated high-frequency band.

[0056] At least some of the above-described components may be coupled mutually and communicate signals (e.g., commands or data) therebetween via an inter-peripheral communication scheme (e.g., a bus, general purpose input and output (GPIO), serial peripheral interface (SPI), or mobile industry processor interface (MIPI)).

[0057] According to an embodiment, commands or data may be transmitted or received between the electronic device **101** and the external electronic device **104** via the server **108** coupled with the second network **199**. The external electronic devices **102** or **104** each may be a device of the same or a different type from the electronic device **101**. According to an embodiment, all or some of operations to be executed at the electronic device **101** may be executed at one or more of the external electronic devices **102**, **104**, or **108**. For example, if the electronic device **101** should perform a function or a service automatically, or in response to a request from a user or another device, the electronic device **101**, instead of, or in addition to, executing the function or the service, may request the one or more external electronic devices to perform at least part of the function or the service. The one or more external electronic devices receiving the request may perform the at least part of the function or the service requested, or an additional function or an additional service related to the request, and transfer an outcome of the performing to the electronic device **101**. The electronic device **101** may provide the outcome, with or without further processing of the outcome, as at least part of a reply to the request. To that end, a cloud computing, distributed computing, mobile edge computing (MEC), or client-server computing technology may be used, for example. The electronic device **101** may provide ultra low-latency services using, e.g., distributed computing or mobile edge computing. In an embodiment, the external electronic device **104** may include an Internet-of-things (IoT) device. The server **108** may be an intelligent server using machine learning and/or a neural network. According to an embodiment, the external electronic device **104** or the server **108** may be included in the second network **199**. The electronic device **101** may be applied to intelligent services (e.g., smart home, smart city, smart car, or health-care) based on 5G communication technology or IoT-related technology.

[0058] FIG. 2A is a block diagram **200** illustrating an example configuration of an electronic device **101** for supporting legacy network communication and 5G network communication according to various embodiments. Referring to FIG. 2A, the electronic device **101** may include a first communication processor (e.g., including processing circuitry) **212**, a second communication processor (e.g., including processing circuitry) **214**, a first radio frequency integrated circuit (RFIC) **222**, a second RFIC **224**, a third RFIC **226**, a fourth RFIC **228**, a first radio frequency front end (RFFE) **232**, a second RFFE **234**, a first antenna module **242**, a second antenna module **244**, a third antenna module **246** (each of the antenna modules including at least one antenna), and antennas **248**. The electronic device **101** may further include a processor (e.g., including processing circuitry) **120** and a memory **130**. The second network **199** may include a first cellular network **292** and a second cellular network **294**. According to an embodiment, the electronic device **101** may further include at least one component among the components of FIG. 1, and the second network **199** may further include at least one other network. According to an embodiment, the first communication processor **212**, the second communication processor **214**, the first RFIC **222**, the second RFIC **224**, the fourth RFIC **228**, the first RFFE **232**, and the second RFFE **234** may form at least part of the wireless communication module **192**. According to an embodiment, the fourth RFIC **228** may be omitted or be included as part of the third RFIC **226**.

[0059] The first communication processor **212** may include various processing circuitry and establish a communication channel of a band that is to be used for wireless communication with the first cellular network **292** or may support legacy network communication via the established

communication channel. According to an embodiment, the first cellular network may be a legacy network that includes second generation (2G), third generation (3G), fourth generation (4G), or long-term evolution (LTE) networks. The second CP **214** may include various processing circuitry and establish a communication channel corresponding to a designated band (e.g., from about 6 GHz to about 60 GHz) among bands that are to be used for wireless communication with the second cellular network **294** or may support fifth generation (5G) network communication via the established communication channel. According to an embodiment, the second cellular network **294** may be a 5G network defined by the 3rd generation partnership project (3GPP). Additionally, according to an embodiment, the first CP **212** or the second CP **214** may establish a communication channel corresponding to another designated band (e.g., about 6 GHz or less) among the bands that are to be used for wireless communication with the second cellular network **294** or may support fifth generation (5G) network communication via the established communication channel.

[0060] The first communication processor **212** may perform data transmission/reception with the second communication processor **214**. For example, data classified as transmitted via the second cellular network **294** may be changed to be transmitted via the first cellular network **292**. In this case, the first communication processor **212** may receive transmission data from the second communication processor **214**. For example, the first communication processor **212** may transmit/receive data to/from the second communication processor **214** via an inter-processor interface **213**. The inter-processor interface **213** may be implemented as, e.g., universal asynchronous receiver/transmitter (UART) (e.g., high speed-UART (HS-UART)) or peripheral component interconnect bus express (PCIe) interface, but is not limited to a specific kind. The first communication processor **212** and the second communication processor **214** may exchange packet data information and control information using, e.g., a shared memory. The first communication processor **212** may transmit/receive various pieces of information, such as sensing information, output strength information, or resource block (RB) allocation information, to/from the second communication processor **214**.

[0061] According to implementation, the first communication processor **212** may not be directly connected with the second communication processor **214**. In this case, the first communication processor **212** may transmit/receive data to/from the second communication processor **214** via a processor **120** (e.g., an application processor). For example, the first communication processor **212** and the second communication processor **214** may transmit/receive data to/from the processor **120** (e.g., an application processor) via an HS-UART interface or PCIe interface, but the kind of the interface is not limited thereto. The first communication processor **212** and the second communication processor **214** may exchange control information and packet data information with the processor **120** (e.g., an application processor) using a shared memory.

[0062] According to an embodiment, the first communication processor **212** and the second communication processor **214** may be implemented in a single chip or a single package. According to an embodiment, the first CP **212** or the second CP **214**, along with the processor **120**, an assistance processor **123**, or communication module **190**, may be formed in a single chip or single package. For example, as shown in FIG. 2B, an integrated communication processor **260** may support all of the functions for communication with the first cellular network **292** and the second cellular network **294**.

[0063] As described above, at least one of the processor **120**, the first communication processor **212**, the second communication processor **214**, or the integrated communication processor **260** may be implemented as a single chip or a single package. In this case, the single chip or single package may include a memory (or storage means) storing instructions that cause at least some of operations performed according to an embodiment and a processing circuit (or operation circuit, but the term is not limited) for executing instructions.

[0064] Upon transmission, the first RFIC **222** may convert a baseband signal generated by the first communication processor **212** into a radio frequency (RF) signal with a frequency ranging from

about 700 MHz to about 3 GHz which is used by the first cellular network **292** (e.g., a legacy network). Upon receipt, the RF signal may be obtained from the first network **292** (e.g., a legacy network) through an antenna (e.g., the first antenna module **242**) and be pre-processed via an RFFE (e.g., the first RFFE **232**). The first RFIC **222** may convert the pre-processed RF signal into a baseband signal that may be processed by the first communication processor **212**.

[0065] Upon transmission, the second RFIC **224** may convert the baseband signal generated by the first communication processor **212** or the second communication processor **214** into a Sub6-band (e.g., about 6 GHz or less) RF signal (hereinafter, “5G Sub6 RF signal”) that is used by the second cellular network **294** (e.g., a 5G network). Upon receipt, the 5G Sub6 RF signal may be obtained from the second cellular network **294** (e.g., a 5G network) through an antenna (e.g., the second antenna module **244**) and be pre-processed via an RFFE (e.g., the second RFFE **234**). The second RFIC **224** may convert the pre-processed 5G Sub6 RF signal into a baseband signal that may be processed by a corresponding processor of the first communication processor **212** and the second communication processor **214**.

[0066] The third RFIC **226** may convert the baseband signal generated by the second communication processor **214** into a 5G Above6 band (e.g., about 6 GHz to about 60 GHz) RF signal (hereinafter, “5G Above6 RF signal”) that is to be used by the second cellular network **294** (e.g., a 5G network). Upon receipt, the 5G Above6 RF signal may be obtained from the second cellular network **294** (e.g., a 5G network) through an antenna (e.g., the antenna **248**) and be pre-processed via the third RFFE **236**. The third RFIC **226** may convert the pre-processed 5G Above6 RF signal into a baseband signal that may be processed by the second communication processor **214**. According to an embodiment, the third RFFE **236** may be formed as part of the third RFIC **226**.

[0067] According to an embodiment, the electronic device **101** may include the fourth RFIC **228** separately from, or as at least part of, the third RFIC **226**. In this case, the fourth RFIC **228** may convert the baseband signal generated by the second communication processor **214** into an intermediate frequency band (e.g., from about 9 GHz to about 11 GHz) RF signal (hereinafter, “IF signal”) and transfer the IF signal to the third RFIC **226**. The third RFIC **226** may convert the IF signal into a 5G Above6 RF signal. Upon receipt, the 5G Above6 RF signal may be received from the second cellular network **294** (e.g., a 5G network) through an antenna (e.g., the antenna **248**) and be converted into an IF signal by the third RFIC **226**. The fourth RFIC **228** may convert the IF signal into a baseband signal that may be processed by the second communication processor **214**.

[0068] According to an embodiment, the first RFIC **222** and the second RFIC **224** may be implemented as at least part of a single chip or single package. According to an embodiment, when the first RFIC **222** and the second RFIC **224** in FIG. 2A or 2B are implemented as a single chip or a single package, they may be implemented as an integrated RFIC. In this case, the integrated RFIC is connected to the first RFFE **232** and the second RFFE **234** to convert a baseband signal into a signal of a band supported by the first RFFE **232** and/or the second RFFE **234**, and may transmit the converted signal to one of the first RFFE **232** and the second RFFE **234**. According to an embodiment, the first RFFE **232** and the second RFFE **234** may be implemented as at least part of a single chip or single package. According to an embodiment, at least one of the first antenna module **242** or the second antenna module **244** may be omitted or be combined with another antenna module to process multi-band RF signals.

[0069] According to an embodiment, the third RFIC **226** and the antenna **248** may be disposed on the same substrate to form the third antenna module **246**. For example, the wireless communication module **192** or the processor **120** may be disposed on a first substrate (e.g., a main printed circuit board (PCB)). In this case, the third RFIC **226** and the antenna **248**, respectively, may be disposed on one area (e.g., the bottom) and another (e.g., the top) of a second substrate (e.g., a sub PCB) which is provided separately from the first substrate, forming the third antenna module **246**.

Placing the third RFIC **226** and the antenna **248** on the same substrate may shorten the length of the

transmission line therebetween. This may reduce a loss (e.g., attenuation) of high-frequency band (e.g., from about 6 GHz to about 60 GHz) signal used for 5G network communication due to the transmission line. Thus, the electronic device **101** may enhance the communication quality with the second network **294** (e.g., a 5G network).

[0070] According to an embodiment, the antenna **248** may be formed as an antenna array which includes a plurality of antenna elements available for beamforming. In this case, the third RFIC **226** may include a plurality of phase shifters **238** corresponding to the plurality of antenna elements, as part of the third RFFE **236**. Upon transmission, the plurality of phase shifters **238** may change the phase of the 5G Above6 RF signal which is to be transmitted to the outside (e.g., a 5G network base station) of the electronic device **101** via their respective corresponding antenna elements. Upon receipt, the plurality of phase shifters **238** may change the phase of the 5G Above6 RF signal received from the outside to the same or substantially the same phase via their respective corresponding antenna elements. This enables transmission or reception via beamforming between the electronic device **101** and the outside.

[0071] The second cellular network **294** (e.g., a 5G network) may be operated independently (e.g., as standalone (SA)) from, or in connection (e.g., as non-standalone (NSA)) with the first cellular network **292** (e.g., a legacy network). For example, the 5G network may include access networks (e.g., 5G access networks (RANs)) but lack any core network (e.g., a next-generation core (NGC)). In this case, the electronic device **101**, after accessing a 5G network access network, may access an external network (e.g., the Internet) under the control of the core network (e.g., the evolved packet core (EPC)) of the legacy network. Protocol information (e.g., LTE protocol information) for communication with the legacy network or protocol information (e.g., New Radio (NR) protocol information) for communication with the 5G network may be stored in the memory **230** and be accessed by other components (e.g., the processor **120**, the first communication processor **212**, or the second communication processor **214**).

[0072] FIG. **3A** is a diagram illustrating an example change of transmission antennas according to various embodiments.

[0073] According to an embodiment, an RF circuitry **300** of an electronic device **101** may include an RFIC **301** (e.g., the first RFIC **222**, the second RFIC **224**, the third RFIC **226**, and/or the fourth RFIC **228**) and/or a plurality of PAs **303** and **313**. It will be appreciated by one of ordinary skill in the art that the plurality of PAs **303** and **313** may be included in at least one RFFE (e.g., the first RFFE **232**, the second RFFE **234**, and/or the third RFFE **236**). A first antenna **305** may be connected to the first PA **303**, and a second antenna **315** may be connected to the second PA **313**. For example, an RF signal may be provided to the first antenna **305** through the first PA **303**. An RF path to the first antenna **305** through the first PA **303** may be referred to as a first RF path. For example, an RF signal may be provided to the second antenna **315** through the second PA **313**. An RF path to the second antenna **315** through the second PA **313** may be referred to as a second RF path. An RF path may refer, for example, to a path to which an RF signal is applied and may refer, for example, to at least some of a plurality of pieces of hardware associated with the path.

[0074] According to an embodiment, the electronic device **101** (e.g., the first communication processor **212** of FIG. **2A**, the second communication processor **214** of FIG. **2A**, and/or the integrated communication processor **260** of FIG. **2B**) may support the function of changing transmission antennas. The electronic device **101** may determine to provide the RF signal through the first RF path, for example. In this case, the electronic device **101** may provide the RF signal to the first PA **303**. Thus, the RF signal amplified by the PA **303** may be provided to the first antenna **305**. For example, the electronic device **101** may identify that a condition for changing an RF path is met. For example, when a first indicator indicating at least one performance corresponding to a first RF path is worse than a second indicator indicating at least one performance corresponding to a second RF path (or when the first indicator and the second indicator meet a preset condition), the electronic device **101** may change the RF path from the first RF path to the second RF path. There

are no limitations on the preset condition associated with the first indicator and the second indicator. The electronic device **101** (e.g., a communication processor (e.g., the first communication processor **212**, the second communication processor **214**, or the integrated communication processor **260**)) may change the RF path from the first RF path to the second RF path by controlling at least part of the RF circuitry **300**. Accordingly, the RF signal may be provided to the second PA **313**. The RF signal amplified by the second PA **313** may be provided to the second antenna **315**. As described above, the transmission antenna for the RF signal may be changed from the first antenna **305** to the second antenna **315**. This may be referred to as transmission antenna hopping. For example, when dual connectivity (e.g., EN-DC but not limited) is supported, the electronic device **101** may include PAs (e.g., the PAs **303** and **313**) supporting the same frequency band. In this case, the electronic device **101** may perform transmission antenna hopping using the plurality of PAs **303** and **313**. For example, the PAs **303** and **313** may support a middle band (MB)/high band (HB). In this case, the electronic device **101** may perform transmission antenna hopping for the RF signal of MB/HB.

[0075] FIG. 3B is a diagram illustrating an example change of transmission antennas according to various embodiments.

[0076] According to an embodiment, the RF circuitry **310** of the electronic device **101** may include an RFIC **301** (e.g., the first RFIC **222**, the second RFIC **224**, the third RFIC **226**, and/or the fourth RFIC **228**), a PA **321**, and/or a switch **323**. The switch **323** may selectively connect either the first antenna **325** or the second antenna **327** to the PA **321**. For example, the switch **323** may operate based on the control of the communication processors **212**, **214**, and/or **260** and/or the RFIC **301**, but is not limited thereto. It will be appreciated by one of ordinary skill in the art that the switch **323** may be implemented as SPnT, but the type is not limited. For example, in the embodiment of FIG. 3B, the switch **323** may be controlled so that the RF signal is provided to the first antenna **325** through the PA **321**. This may be referred to as a first RF path. For example, the switch **323** may be controlled so that the RF signal is provided to the second antenna **327** through the PA **321**. This may be referred to as a second RF path.

[0077] According to an embodiment, the electronic device **101** (e.g., the communication processor **212**, **214**, and/or **260**) may support a function of changing a transmission antenna. The electronic device **101** may determine to provide the RF signal through the first RF path, for example. In this case, the electronic device **101** may control the switch **323** to provide an RF signal to the first PA **321**. Accordingly, the RF signal amplified by the first PA **321** may be provided to the first antenna **325**. For example, the electronic device **101** may identify that a condition for changing an RF path is met. For example, when a first indicator indicating at least one performance corresponding to a first RF path is worse than a second indicator indicating at least one performance corresponding to a second RF path (or when the first indicator and the second indicator meet a preset condition), the electronic device **101** may change the RF path from the first RF path to the second RF path.

[0078] In an example, the conditions associated with the first indicator and the second indicator may be conditions associated with the first received strength (which may be, RSRP, but is not limited) corresponding to the first antenna **325** and the second received strength corresponding to the second antenna **327**. The electronic device **101** may be configured to measure received strengths corresponding to the antennas **325** and **327** in a designated period (e.g., 640 ms, but is not limited). The electronic device **101** may identify the received strength difference (e.g., RSRP diff current) which is a difference between the first received strength and the second received strength at the current time. Further, the electronic device **101** may identify MTPL diff which is a difference between a first maximum transmission power level (MTPL) corresponding to the first RF path and a second MTPL corresponding to the second RF path. In an example condition, the electronic device **101** may identify that the antenna change condition is met when the sum of the received strength difference (RSRP diff current) at the current time and the MTPL diff is a first threshold (referred to as high threshold for convenience of description) or more. In an example condition,

when the change degree of received strength is larger than a threshold change degree (e.g., when an abrupt received strength change is detected), the electronic device **101** may identify that the antenna change condition is met.

[0079] In an example, the electronic device **101** may identify the average received strength difference (which is referred to as RSRP average). The average may be calculated, e.g., for two or more times, and the number of the times is not limited. In an example condition, the electronic device **101** may identify that the antenna change condition is met when the sum of the average received strength difference (RSRP average) and the MTPL is a second threshold (referred to as low threshold for convenience of description) or more. The second threshold may be smaller than the first threshold, but is not limited. In an example condition, the electronic device **101** may also identify that the antenna change condition is met when a continuous received strength difference occurs. It will be appreciated by one of ordinary skill in the art that the above-described antenna change conditions are merely examples, and whether the antenna change condition is met may be determined based on the respective received strengths of the antennas, average of the differences, MTPLs, and/or MTPL difference, and whether the antenna change conditions are met may also be determined based on at least one parameter that replaces the above-described parameters or is added.

[0080] For example, upon identifying that the antenna change condition is met, the electronic device **101** (e.g., a communication processor (e.g., the first communication processor **212**, the second communication processor **214**, or the integrated communication processor **260**)) may change the RF path from the first RF path to the second RF path by controlling the switch **323**. Accordingly, the RF signal amplified by the PA **321**, which used to be provided to the first antenna **325**, may be provided to the second antenna **327**. As described above, the transmission antenna for the RF signal may be changed from the first antenna **325** to the second antenna **327**. This may be referred to as transmission antenna switching.

[0081] According to various embodiments, the electronic device **101** may change the transmission antenna by the transmission antenna hopping described in connection with FIG. 3A or the transmission antenna switching described in connection with FIG. 3B. In the disclosure, the operation of changing the transmission antenna may be performed, e.g., by transmission antenna hopping or by transmission antenna switching.

[0082] FIG. 4A is a flowchart illustrating an example method of operating an electronic device according to various embodiments. FIG. 4A is described with reference to FIG. 4B. FIG. 4B is a diagram illustrating a housing of an electronic device according to various embodiments.

[0083] Referring to FIG. 4A, the electronic device **101** (e.g., the first communication processor **212** of FIG. 2A, the second communication processor **214** of FIG. 2A, and/or the integrated communication processor **260** of FIG. 2B) may identify that the folding state of the electronic device **101** is an open state in operation **401**. For example, the communication processor **212**, **214**, and/or **260** may receive information associated with the folding state of the processor **120** (e.g., application processor). For example, referring to FIG. 4B, the electronic device **101** may include a first housing **431** and a second housing **432**. The first housing **431** and the second housing **432** may be rotated by a hinge structure (e.g., the hinge structure **458** of FIG. 4C). For example, when one surface of the first housing **431** and one surface of the second housing **432** face in substantially the same direction, the folding state of the electronic device **101** may be referred to as an open state. For example, when one surface of the first housing **431** and one surface of the second housing **432** substantially face each other, the folding state of the electronic device **101** may be referred to as a closed state. The electronic device **101** may identify whether the folding state of the electronic device **101** is the open state, closed state, or half-closed state. For example, the processor **120** may identify the folding state based on sensing data from at least one sensor (e.g., hall sensor) for determining whether it folds. The processor **120** may transfer the identified folding state information to the communication processor **212**, **214**, and/or **260**, and the communication

processor **212**, **214**, and/or **260** may identify the folding state of the electronic device **101** based on the received information.

[0084] Referring back to FIG. **4A**, in operation **403**, the electronic device **101** may control the RF circuitry (e.g., the RF circuitry **300** of FIG. **3A** or the RF circuitry **310** of FIG. **3B**) to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas based on the folding state being the open state. For example, the antenna available for each folding state may be set among the antennas available corresponding to the first frequency band. For example, the antenna corresponding to the folding state being the open state among the antennas available corresponding to the first frequency band may be the first antenna. For example, the antenna corresponding to the folding state being the closed state among the antennas available corresponding to the first frequency band may be the second antenna. The antenna corresponding to the open state and the antenna corresponding to the closed state are described below.

[0085] According to an embodiment, in operation **405**, the electronic device **101** may identify that the folding state of the electronic device **101** changes from the open state to the closed state. the electronic device **101** may identify that the folding state of the electronic device **101** being the closed state. For example, as described above, the processor **120** may identify that the folding state changes from the open state to the closed state based on information from at least one sensor. The processor **120** may provide information indicating that the folding state is the closed state to the communication processor **212**, **214**, and/or **260**. The communication processor **212**, **214**, and/or **260** may identify that the folding state of the electronic device **101** changes from the open state to the closed state based on information from the processor **120**.

[0086] According to an embodiment, in operation **407**, the electronic device **101** may identify that the electronic device **101** is gripped by the user. For example, referring to FIG. **4B**, the electronic device **101** may include at least one grip sensor **441** and **442**. For example, the processor **120** may identify whether the electronic device **101** is gripped based on information sensed by at least one grip sensor **441** and **442**. In an example, upon identifying that a grip is identified by all of the grip sensors **441** and **442**, it may be determined that the electronic device **101** is gripped, but this is an example and is not limited. The processor **120** may provide information for identifying whether it is gripped to the communication processor **212**, **214**, and/or **260**. The communication processor **212**, **214**, and/or **260** may identify whether the electronic device **101** is gripped based on information from the processor **120**. Meanwhile, this is an example, and the communication processor **212**, **214**, and/or **260** may identify whether it is gripped based on an indicator associated with the strength of the reflected wave, such as voltage standing wave ratio (VSWR), without information from the application processor. For example, it will be appreciated by one of ordinary skill in the art that whether it is a free space environment, whether an object is detected, and/or the type of the object may be identified based on the VSWR, and the identifying method is not limited.

[0087] Referring back to FIG. **4A**, according to an embodiment, the electronic device **101** may control the RF circuitry to provide the second RF signal corresponding to the first frequency band to the second antenna different from the first antenna among the plurality of antennas, based on the electronic device **101** being gripped, in operation **409**. The second RF signal may refer, for example, to an RF signal subsequent to the first RF signal in time series, and the first RF signal and the second RF signal may be based on the first frequency band. Here, control of the RF circuitry may be, e.g., control corresponding to transmission antenna hopping or control corresponding to transmission antenna switching. As described above, for example, the second antenna may be an antenna corresponding to the closed state among the antennas available corresponding to the first frequency band. As described above, the electronic device **101** may change the transmission antenna from the first antenna corresponding to the open state to the antenna corresponding to the closed state based on transmission antenna hopping or transmission antenna switching. Meanwhile, changing the transmission antenna from the first antenna to the second antenna based on the electronic device **101** being gripped is merely an example, and a change of transmission antennas

may also be performed without determining whether it is gripped. For example, the electronic device **101** may change the transmission antenna from the first antenna corresponding to the open state to the second antenna corresponding to the closed state based on a change of the folding state from the open state to the closed state. As described above, in the open state, the first antenna which has relatively high performance may be used and, in the closed state, the second antenna which has relatively high performance may be used as the transmission antenna. Hereinafter, a transmission antenna in a foldable electronic device is described.

[0088] FIG. **4C** is a diagram illustrating antennas in an open state of an electronic device according to various embodiments. FIG. **4D** is a diagram illustrating antennas in a closed state of an electronic device according to various embodiments. FIG. **4E** is a diagram illustrating human body contact in a closed state according to various embodiments.

[0089] Referring to FIG. **4C**, antennas **451**, **452**, **453**, **454**, **455**, **456**, and **457** may be disposed on the first housing **431** of the electronic device **101**. Antennas **461**, **462**, **463**, **464**, **465**, **466**, and **467** may be disposed on the second housing **432** of the electronic device **101**. The antennas **451**, **452**, **453**, **454**, **455**, **456**, and **457** and/or the antennas **461**, **462**, **463**, **464**, **465**, **466**, and **467** may be segmented antennas, but their types are not limited. The first housing **431** and the second housing **432** may be connected to the hinge structure **458**. The hinge structure **458** may include, e.g., a rotatable structure. Accordingly, at least one housing may be rotated about the hinge structure **458** as an axis so that the electronic device **101** may be folded as shown in FIG. **4D**. The folding state of the electronic device **101** in FIG. **4D** may be referred to as a closed state.

[0090] Referring back to FIG. **4C**, the electronic device **101** may determine to transmit an RF signal of a first frequency band, for example. The electronic device **101** may determine an antenna **455** among antennas corresponding to the first frequency band, as the transmission antenna. The antenna **455** may be, e.g., a basic (or default) transmission antenna corresponding to the first frequency band. For example, when the folding state is the open state, the antenna **455** may have better performance than the other antennas in the first frequency band. Accordingly, the antenna **455** may be the basic transmission antenna. Meanwhile, it will be appreciated by one of ordinary skill in the art that even in the open state, the electronic device **101** may identify whether the antenna change condition is met, and that the transmission antenna may be changed based on the satisfaction of the antenna change condition.

[0091] According to an embodiment, the folding state of the electronic device **101** may be changed from the open state to the closed state. Referring to FIG. **4D**, in the closed state, the antennas **451**, **452**, and **453** disposed on an upper side of the first housing **431** may approach the antennas **461**, **462**, and **463** disposed on an upper side of the second housing **432**. In the closed state, the antennas **455**, **456**, and **457** disposed on a lower side of the first housing **431** may approach the antennas **465**, **466**, and **467** disposed on a lower side of the second housing **432**. The close disposition of antennas may affect antenna performance. In particular, the distance between the antennas **455** and **465** may be smaller than the distance between other antennas. Accordingly, performance degradation may occur. Accordingly, if the antenna **455** used in the open state is continuously used, communication performance may deteriorate. Accordingly, it may be desirable to change the transmission antenna. For example, the electronic device **101** may use an antenna (e.g., **451** or **461**) corresponding to the closed state as the transmission antenna. In the closed state, the distance between the antennas **451** and **461** may be larger than the distance between the other antennas. Accordingly, the antenna **451** having a relatively large distance between the antennas **451** and **461** may be determined as the transmission antenna, but this is an example and the transmission antenna corresponding to the closed state is not limited. Since there is a possibility that the human body may come into contact with the lower antennas **455**, **456**, and **457** by the grip, the antenna **451** disposed on the upper side may be determined as the transmission antenna, but is not limited thereto. For example, it may be required that the distance between the antennas be equal to or larger than a predetermined distance (e.g., 0.4 mm) to ensure good antenna performance.

Accordingly, any antenna for which the distance from the adjacent antenna in the closed state is the predetermined distance (e.g., 0.4 mm) or more may be used as the transmission antenna in the closed state, the manner of setting and/or selecting the transmission antenna is not limited. For example, the antenna **453** and the antenna **451** may be used in MB/HB. Accordingly, in the closed state, the antenna **453** may be used as the transmission antenna corresponding to MB/HB. In the open state, the antenna **451** may be used as the transmission antenna corresponding to MB/HB. Although not shown, the folding state of the electronic device **101** may be a half-closed state. The half-closed state may refer, for example, to a state in which the angle between the first housing **431** and the second housing **432** has a certain value between the open state and the closed state, but is not limited. In the half-closed state, the electronic device **101** may determine a transmission antenna based on the distance between the antennas. For example, in the half-closed state, the electronic device **101** may identify the transmission antenna corresponding to the corresponding angle. For example, the transmission antenna corresponding to the angle between the housings **431** and **432** may be set, and the electronic device **101** may identify the transmission antenna corresponding to a specific angle. Or, the electronic device **101** may also calculate the distance between antennas at a specific angle in the half-closed state and determine the transmission antenna based on the calculation result. For example, the electronic device **101** may determine the antenna having the largest distance to the most adjacent antenna among the available antennas in a specific band, as the transmission antenna. Meanwhile, it will be appreciated by one of ordinary skill in the art that when the distance to the most adjacent antenna from the transmission antenna being used is a predetermined distance (e.g., 0.4 mm) or more in the half-closed state, the transmission antenna may be maintained.

[0092] Meanwhile, as in FIG. **4E**, a human body **459** (e.g., face) may be placed close to the antenna. For example, the user may bring her body **459** close to the electronic device **101** for a call while the folding state of the electronic device **101** is the closed state. As illustrated in FIG. **4A**, the electronic device **101** may change the transmission antenna when a grip on the electronic device **101** is identified. For example, in an example, the electronic device **101** may change the transmission antenna based on a change of the folding state to the closed state and identifying a grip. However, this is merely an example, and the electronic device **101** may also be configured to change the transmission antenna without identifying whether it is gripped if the folding state is changed to the closed state. Meanwhile, folding the electronic device so that the distance between the antennas **451** and **461** is larger than the distance between the antennas **453** and **463** as shown in FIG. **4D** is merely an example. The electronic device **101** may also be implemented to be folded to have substantially the same distance between antennas. It will be appreciated by one of ordinary skill in the art that even in this case, the electronic device **101** may change the transmission antenna based on a change of the folding state. For example, a change of the transmission antenna to an antenna having relatively good performance may be performed when the folding state is the closed state.

[0093] FIG. **4F** is a diagram illustrating various states and views of an electronic device according to various embodiments.

[0094] In contrast to the electronic device **101** being folded in the left/right direction with respect to the direction shown in the drawings in FIGS. **4C** and **4D**, the electronic device **101** according to the embodiment of FIG. **4F** may be implemented to be folded in the upper/lower direction. The electronic device **101** may include a first housing **471** and a second housing **472**. Antennas **481**, **482**, **483**, **484**, and **485** may be disposed on the first housing **471**. Antennas **491**, **492**, **493**, and **494** may be disposed on the second housing **472**. The first housing **471** and the second housing **472** may be connected to the hinge structure **473**. The hinge structure **473** may include a rotatable structure. Accordingly, the housing may rotate about the hinge structure **473** as an axis.

Accordingly, as shown in FIG. **4F**, the first housing **471** and the second housing **472** may rotate to face each other (e.g., in the upper/lower direction).

[0095] According to an embodiment, when the folding state is the open state, the electronic device **101** may use, e.g., an antenna **482** disposed on the first housing **471** as the transmission antenna. According to an embodiment, when the folding state is the closed state, the antennas **481** and **491** may substantially contact each other, antennas **482** and **492** may substantially contact each other, and the antennas **483** and **493** may substantially contact each other. For example, the distance between the antennas **482** and **492** may be less than a predetermined distance (e.g., 0.4 mm), and the performance of the antenna **482** may be degraded. Meanwhile, when the folding state is the open state, the distance between the antennas **485** and **494** may be the predetermined distance (e.g., 0.4 mm). When the folding state is the closed state, the antenna **485** may be used as the transmission antenna. For example, the antennas **483** and **493** may be antennas configured for the B41 band and/or the N41 band, but are not limited thereto. As described above, the electronic device **101** may change the transmission antenna according to the change from the open state to the closed state. Alternatively, the electronic device **101** may change the transmission antenna based on the change to the closed state and identified of a grip. Meanwhile, as in FIG. 4F, the folding of the electronic device such that the distance between the antennas **485** and **494** is relatively large is merely an example. The electronic device **101** may also be implemented to be folded to have substantially the same distance between antennas. It will be appreciated by one of ordinary skill in the art that even in this case, the electronic device **101** may change the transmission antenna based on a change of the folding state. For example, a change of the transmission antenna to an antenna having relatively good performance may be performed when the folding state is the closed state. [0096] FIG. 5A is a flowchart illustrating an example method of operating an electronic device according to various embodiments.

[0097] According to an embodiment, the electronic device **101** (e.g., the first communication processor **212** of FIG. 2A, the second communication processor **214** of FIG. 2A, and/or the integrated communication processor **260** of FIG. 2B) may identify that the folding state of the electronic device **101** is an open state in operation **501**. For example, the communication processor **212**, **214**, and/or **260** may receive information about the folding state (e.g., information indicating the open state) of the electronic device **101** from the application processor (e.g., the processor **120**), but this is merely an example, and the manner in which the communication processor **212**, **214**, and/or **260** identifies the folding state is not limited. In another example, the communication processor **212**, **214**, and/or **260** may directly receive sensing data from the sensor.

[0098] In operation **503**, the electronic device **101** may control the RF circuitry (e.g., the RF circuitry **300** of FIG. 3A or the RF circuitry **310** of FIG. 3B) to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas. Here, the first antenna may be, e.g., a transmission antenna corresponding to the open state, but is not limited thereto.

[0099] In operation **505**, the electronic device **101** may identify that the folding state of the electronic device **101** changes from the open state to the closed state. The electronic device **101** may identify that the folding state of the electronic device **101** being the closed state. For example, the communication processor **212**, **214**, and/or **260** may receive information about the folding state (e.g., information indicating the closed state) of the electronic device **101** from the application processor (e.g., the processor **120**), but this is an example, and the manner in which the communication processor **212**, **214**, and/or **260** identifies the folding state is not limited.

[0100] According to an embodiment, in operation **507**, the electronic device **101** may identify whether the electronic device **101** is gripped by the user. The electronic device **101** may control the RF circuitry to provide the second RF signal corresponding to the first frequency band to the second antenna different from the first antenna among the plurality of antennas, based on the electronic device **101** being identified to be gripped (yes in **507**), in operation **509**. For example, operation **509** may be a forced transmission antenna change. The second antenna may be, e.g., a transmission antenna corresponding to the closed state, but is not limited thereto. Upon identifying

that the electronic device **101** is gripped, the electronic device **101** may perform a transmission antenna change (e.g., transmission antenna hopping or transmission antenna switching) without determining whether the measured parameter meets the antenna change condition, and this may be referred to as a forced antenna change. Based on being identified otherwise (no in **507**), the electronic device **101** may identify whether the measured parameter meets the antenna change condition in operation **511**. For example, operation **511** may be a transmission antenna change algorithm on state. When the measured parameter meets the antenna change condition (yes in **511**), the electronic device **101** may control the RF circuitry to provide the second RF signal corresponding to the first frequency band to the second antenna different from the first antenna among the plurality of antennas, in operation **509**. If the measured parameter does not meet the antenna change condition (no in **511**), the electronic device **101** may maintain the transmission antenna. When identified otherwise, whether to change the transmission antenna may be determined based on whether the measured parameter meets the antenna change condition, and this may be referred to as a transmission antenna change algorithm on state. Meanwhile, the state of maintaining the transmission antenna regardless of the measured parameter may be referred to as a transmission antenna change algorithm off state.

[0101] FIG. 5B is a flowchart illustrating an example method of operating an electronic device according to various embodiments.

[0102] According to an embodiment, the electronic device **101** (e.g., the first communication processor **212** of FIG. 2A, the second communication processor **214** of FIG. 2A, and/or the integrated communication processor **260** of FIG. 2B) may identify that the folding state of the electronic device **101** is an open state in operation **521**. In operation **523**, the electronic device **101** may control the RF circuitry (e.g., the RF circuitry **300** of FIG. 3A or the RF circuitry **310** of FIG. 3B) to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas. Here, the first antenna may be, e.g., a transmission antenna corresponding to the open state, but is not limited thereto. In operation **525**, the electronic device **101** may identify that the folding state of the electronic device **101** changes from the open state to the closed state. The electronic device **101** may identify that the folding state of the electronic device **101** being the closed state. For example, the communication processor **212**, **214**, and/or **260** may receive information about the folding state (e.g., information indicating the closed state) of the electronic device **101** from the application processor (e.g., the processor **120**), but this is an example, and the manner in which the communication processor **212**, **214**, and/or **260** identifies the folding state is not limited.

[0103] According to an embodiment, in operation **527**, the electronic device **101** may identify whether the electronic device **101** is gripped by the user. The electronic device **101** may control the RF circuitry to provide the second RF signal corresponding to the first frequency band to the second antenna different from the first antenna among the plurality of antennas, based on the electronic device **101** being identified to be gripped (yes in **527**), in operation **529**. Based on being identified as not gripped (no in **527**), the electronic device **101** may maintain the antenna in operation **531**. For example, operation **531** may be a transmission antenna change algorithm off state. While whether to change the transmission antenna is determined depending on whether the measured parameter meets the antenna change condition when not gripped in FIG. 5A, it may be implemented that the antenna is maintained regardless of the measured parameter when not gripped in FIG. 5B.

[0104] FIG. 6 is a flowchart illustrating an example method of operating an electronic device according to various embodiments.

[0105] According to an embodiment, the electronic device **101** (e.g., the first communication processor **212** of FIG. 2A, the second communication processor **214** of FIG. 2A, and/or the integrated communication processor **260** of FIG. 2B) may control the RF circuitry (e.g., the RF circuitry **300** of FIG. 3A or the RF circuitry **310** of FIG. 3B) to provide a first RF signal

corresponding to a first frequency band to a first antenna among a plurality of antennas in operation **601**. Here, the first antenna may be, e.g., a transmission antenna corresponding to the open state, but is not limited thereto. In operation **603**, the electronic device **101** may identify whether the folding state of the electronic device **101** is the closed state. Upon identifying that the folding state is the closed state (yes in **603**), the electronic device **101** may determine whether to change the antenna based on whether the measured parameter meets the antenna change condition in operation **605**. For example, operation **605** may be a transmission antenna change algorithm on state. In the embodiment of FIG. 6, the electronic device **101** may perform an antenna change when the measured parameter (e.g., the received strength for each antenna, but is not limited) meets the antenna change condition without performing an antenna change immediately as the folding state of the electronic device **101** is identified as the closed state. The electronic device **101** may maintain the antenna when the measured parameter (e.g., the received strength for each antenna, but is not limited) does not meet the antenna change condition although the folding state is the closed state. Upon identifying that the folding state is not the closed state (no in **603**), the electronic device **101** may maintain the antenna in operation **607**. Meanwhile, according to an embodiment, when the folding state is identified as the closed state, and a grip on the electronic device **101** is identified, the electronic device **101** may be configured to determine whether to change the antenna based on whether the measured parameter meets the antenna change condition in operation **605**. For example, operation **607** may be a transmission antenna change algorithm off state.

[0106] FIG. 7A is a flowchart illustrating an example method of operating an electronic device according to various embodiments. The embodiment of FIG. 7A is described with reference to FIG. 7B. FIG. 7B is a diagram illustrating an arrangement of an antenna and a camera according to various embodiments.

[0107] Referring to FIG. 7A, according to an embodiment, the electronic device **101** (e.g., the first communication processor **212** of FIG. 2A, the second communication processor **214** of FIG. 2A, and/or the integrated communication processor **260** of FIG. 2B) may control the RF circuitry (e.g., the RF circuitry **300** of FIG. 3A or the RF circuitry **310** of FIG. 3B) to provide a first RF signal corresponding to a first frequency band to a first antenna among a plurality of antennas in operation **701**. In operation **701**, the first antenna may be, e.g., a transmission antenna configured corresponding to the first frequency band while the camera is turned off. For example, referring to FIG. 7B, a first camera **723** and a second camera **721** may be disposed on the PCB **722** of the electronic device **101**. For example, the second camera **721** may be a front camera, and the first camera **723** may be a rear camera, but is not limited thereto. The electronic device **101** may include the first antenna **713**, the second antenna **711**, and a third antenna **712**. For example, the first antenna **713** may be, e.g., a basic (or default) transmission antenna corresponding to the first frequency band. Accordingly, while the first camera **723** is turned off, the electronic device **101** may control the RF circuitry to provide the RF signal of the first frequency band to the first antenna **713**.

[0108] Referring back to FIG. 7A, according to an embodiment, in operation **703**, the electronic device **101** may identify whether the camera is turned on. When the camera is turned on (yes in **703**), the electronic device **101** may control the RF circuitry to provide the second RF signal corresponding to the first frequency band to the second antenna different from the first antenna among the plurality of antennas in operation **705**. When the camera is not turned on (no in **703**), the electronic device **101** may maintain the antenna in operation **707**. For example, referring to FIG. 7B, the electronic device **101** may control the RF circuitry to provide the second RF signal to the second antenna **711** different from the first antenna **713**. In FIG. 7B, the distance between the first antenna **713** and the first camera **723** may be relatively small. As the RF signal is provided from the first antenna **713**, electromagnetic waves generated from the first antenna **713** may affect the first camera **723**. If the use of the first antenna **713** is maintained while the first camera **723** is turned on, the quality of the image obtained by the first camera **723** may deteriorate. To maintain image

quality, the transmission power of the RF signal should be reduced (e.g., reduce by 7 dB), but this may deteriorate communication quality. Accordingly, in a state in which the first camera **723** is turned on, the electronic device **101** may change the transmission antenna from the first antenna **713**, which is the basic transmission antenna, to the second antenna **711**. The electronic device **101** may control the RF circuitry so that the second RF signal of the first frequency band is provided to the second antenna **711**. Since the distance between the second antenna **711** and the first camera **723** is relatively large, the influence of electromagnetic waves generated from the second antenna **711** on the first camera **723** may be relatively small. Accordingly, the electronic device **101** may not reduce, or may reduce by a relatively small degree, the transmission power of the RF signal provided to the second antenna **711**, thereby preventing (or mitigating) communication quality degradation and/or degradation of quality of the image obtained by the first camera **723**.

[0109] According to an embodiment, the electronic device **101** may change the transmission antenna from the first antenna **713** to the third antenna **712** based on the turn-on of the first camera **723**. Meanwhile, the second camera **721** may be turned on while performing communication based on the third antenna **712**. The distance between the third antenna **712** and the second camera **721** may be relatively small, and electromagnetic waves generated from the third antenna **712** may affect the second camera **721**. The electronic device **101** may change the transmission antenna based on the turn-on of the second camera **721**. For example, when the first camera **723** is turned off while the second camera **721** is turned on, the electronic device **101** may change the transmission antenna to the first antenna **713** which is the basic transmission antenna. For example, when both the cameras **721** and **723** are turned on, the electronic device **101** may determine that the second antenna **711** having the least influence on both the cameras **721** and **722**) (or having the largest spacing) is the transmission antenna.

[0110] FIG. 7C is a flowchart illustrating an example method of operating an electronic device according to various embodiments.

[0111] According to an embodiment, the electronic device **101** (e.g., the first communication processor **212** of FIG. 2A, the second communication processor **214** of FIG. 2A, and/or the integrated communication processor **260** of FIG. 2B) may control the RF circuitry (e.g., the RF circuitry **300** of FIG. 3A or the RF circuitry **310** of FIG. 3B) to provide a first RF signal corresponding to a first frequency band to a first antenna among a plurality of antennas in operation **731**. In operation **731**, the first antenna may be, e.g., a transmission antenna configured corresponding to the first frequency band while the camera is turned off. In operation **733**, the electronic device **101** may identify whether the camera is turned on. When the camera is not turned on (no in **733**), the electronic device **101** may maintain the antenna in operation **739**. When the camera is turned on (yes in **733**), the electronic device **101** may identify whether the MTPL for the second RF signal exceeds a threshold in operation **735**. When the MTPL exceeds the threshold (yes in **735**), the electronic device **101** may control the RF circuitry to provide the second RF signal corresponding to the first frequency band to the second antenna different from the first antenna among the plurality of antennas in operation **737**. When the MTPL is the threshold or less (no in **735**), the electronic device **101** may maintain the antenna in operation **739**. For example, since the distance between the first antenna **713** and the first camera **723** is relatively small in FIG. 7B, the electromagnetic waves generated from the first antenna **713** may affect the first camera **723**. Meanwhile, when the transmission power of the RF signal applied to the first antenna **713** is relatively small, the influence of the electromagnetic waves generated from the first antenna **713** on the first camera **723** may be reduced as well. Accordingly, when electromagnetic waves with a relatively small magnitude are generated, it may be preferable to maintain use of the basic transmission antenna rather than performing an antenna change. Accordingly, as shown in FIG. 7C, the electronic device **101** may be configured to perform a transmission antenna change when the MTPL exceeds the threshold and maintain the transmission antenna when the MTPL is the threshold or less. The threshold (e.g., 16 dBm) may be determined to be a value at which a

relatively good quality of image may be measured by the camera, but is not limited. For example, when 5G SA is used, 3 dB transmission power back-off relative to the average transmission power may be performed and, when EN-DC is used, 10 dB transmission power back-off relative to the average transmission power may be performed. Thus a context where the MTPL is the threshold (e.g., 16 dBm) or less may occur and, in this case, the transmission antenna may be maintained. [0112] FIG. 7D is a flowchart illustrating an example method of operating an electronic device according to various embodiments.

[0113] According to an embodiment, the electronic device **101** (e.g., the first communication processor **212** of FIG. 2A, the second communication processor **214** of FIG. 2A, and/or the integrated communication processor **260** of FIG. 2B) may control the RF circuitry (e.g., the RF circuitry **300** of FIG. 3A or the RF circuitry **310** of FIG. 3B) to provide a first RF signal corresponding to a first frequency band to a first antenna among a plurality of antennas in operation **741**. In operation **741**, the first antenna may be, e.g., a transmission antenna configured corresponding to the first frequency band while the camera is turned off. In operation **743**, the electronic device **101** may identify whether the camera is turned on. When the camera is not turned on (no in **743**), the electronic device **101** may maintain the antenna in operation **749**. When the camera is turned on (yes in **743**), the electronic device **101** may identify whether the transmission power for the second RF signal exceeds a threshold in operation **745**. When the transmission power exceeds the threshold (yes in **745**), the electronic device **101** may control the RF circuitry to provide the second RF signal corresponding to the first frequency band to the second antenna different from the first antenna among the plurality of antennas in operation **747**. When the transmission power is the threshold or less (no in **745**), the electronic device **101** may maintain the antenna in operation **749**. As described in connection with FIG. 7C, when electromagnetic waves with a relatively small magnitude are generated, it may be preferable to maintain use of the basic transmission antenna rather than performing an antenna change. Accordingly, as shown in FIG. 7D, the electronic device **101** may be configured to perform a transmission antenna change when the transmission power exceeds the threshold and maintain the transmission antenna when the transmission power is the threshold or less. The threshold may be determined to be a value at which a relatively good quality of image may be measured by the camera, but is not limited.

[0114] FIG. 8 is a flowchart illustrating an example method of operating an electronic device according to various embodiments.

[0115] According to an embodiment, in operation **801**, the electronic device **101** (e.g., the communication processor **212**, **214**, and/or **260**) may control the RF circuitry (e.g., the RF circuitry **300** of FIG. 3A or the RF circuitry **310** of FIG. 3B) to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas. In operation **803**, the electronic device **101** may identify one of the sub frequencies in the frequency band. In operation **805**, the electronic device **101** may identify whether the measured parameter meets the antenna change condition corresponding to the identified sub frequency. Meanwhile, the electronic device **101** may be configured to identify the antenna change condition corresponding to the identified sub frequency, but is not limited. For example, the antenna change condition may be set to differ for each sub frequency. For example, the high threshold and/or low threshold may be set to differ for each sub frequency. For example, the imbalance between antennas (e.g., PPx antenna and DRx antenna) may be set to differ for each sub frequency. For example, Table 1 is an example of the threshold (e.g., high threshold) for each sub frequency in the N78 band.

TABLE-US-00001  
TABLE 1 Sub frequency Low Mid High (3750 Mhz) (3840 Mhz) (3930 Mhz)  
Threshold Threshold 1 Threshold 2 Threshold 3 (high threshold)

[0116] As described above, the electronic device **101** may perform a transmission antenna change when the sum of the received strength difference (RSRP diff current) at the current time and the MTPL diff is the high threshold or more. Here, the high threshold may be set to differ for each for the low band (3750 MHZ), mid band (3840 MHZ), and high band (3903 MHZ) of the N78 band,

for example. The electronic device **101** may identify whether the antenna change condition set for each sub band is met in the N78 band. When the antenna change condition is met (yes in **805**), the electronic device **101** may control the RF circuitry to provide the second RF signal corresponding to the first frequency band to the second antenna different from the first antenna among the plurality of antennas in operation **807**. When the antenna change condition is met (no in **805**), the electronic device **101** may maintain the antenna in operation **809**. For example, it is assumed that the electronic device **101** uses the mid band in the N78 band. The sum of the received strength difference (RSRP diff current) and MTPL diff measured by the electronic device **101** may be larger than or equal to Threshold **1**, but may be less than Threshold **2**. Although the antenna change condition corresponding to the low band is met, the antenna change condition corresponding to the mid band is not met, so that the electronic device **101** may maintain the transmission antenna. [0117] For example, Table 2 is an example of the threshold (e.g., high threshold) for each sub frequency in the N78 band.

TABLE-US-00002 TABLE 2 Sub frequency 3750 Mhz 3800 Mhz 3840 Mhz 3880 Mhz 3930 Mhz  
Threshold Threshold Threshold Threshold Threshold Threshold (high 1 2 3 4 5 threshold)

[0118] While different thresholds are set for three sub frequencies for the N78 band in Table 1, different thresholds may be set for five sub frequencies for the N78 band in Table 2, but the number of divisions is not limited. Since the N78 band is relatively wide, sub thresholds as in Table 2 may be set. As described above, as the RSRP diff of the RSRP where the performance is not good at a specific sub frequency is relatively large, the transmission antenna may not be changed, or the case where a transmission antenna change is not performed although needed at a specific sub frequency may be prevented and/or reduced. For example, when the total radiated power (TRP) worsens, it may refer, for example, to the Rx performance in the TDD band worsening as well. Accordingly, in a case where a specific antenna is used for the N78 band, when the RSRP is PRx −91 dBm, and DRx −90 dBm, the RSRP Diff may increase to PRx −93.4 dBm, DRx −90 dBm even in the context of the same electric field. If the high threshold is 5 dB, and imbalance setting is 3750 MHz reference 1 dB, then RSRP Diff+MTPL Diff is 6 dB as a result. Thus, a transmission antenna change may be performed to 5 dB, which is the high threshold, or more. If the imbalance is 1 dB, PRx becomes −91 dBm when the DRx electric field is −90 dBm, and if the PRx electric field deteriorates by 5 dB when the MTPL is the same, a transmission antenna change may be performed. However, in a case where the imbalance is likewise set to 1 dB for 3930 MHz, when the DRx electric field is −90 dBm, the PRx is −93.4 dBm, so that a transmission antenna change may be performed even when the PRx electric field deteriorates by only 2.6 dB. As described above, to prevent and/or reduce a transmission antenna change from being performed according to a relatively small level of degradation of 2.6 dB, for 3930 Mhz, the high threshold and/or imbalance may be set to differ. For example, when the imbalance is set to 3.4 dB, transmission antenna change may not be performed until it deteriorates to 6 dB. Meanwhile, if the imbalance is set to 3.4 dB for the entire N78 band, transmission antenna change may be performed only when degradation occurs to 7.4 dB at 3750 MHz. Accordingly, even in one band, the threshold and/or imbalance of the antenna change condition may be set to differ for each sub frequency.

[0119] According to an example embodiment, an electronic device may comprise at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B), an RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) connected to the at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B), and a plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B) connected to the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B). The at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B) may be configured to control the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B) based on identifying that a folding state of the electronic device is an open state. The at least one communication processor (e.g., **212** or

**214** of FIG. 2A or **260** of FIG. 2B) may be configured to, based on identifying the folding state of the electronic device being a closed state, identify whether the electronic device is gripped. The at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B) may be configured to control the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide a second RF signal corresponding to the first frequency band to a second antenna different from the first antenna among the plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B), based on identifying that the electronic device is gripped.

[0120] According to an example embodiment, the at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B) may be configured, as at least part of controlling the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide the second RF signal to the second antenna based on identifying that the electronic device is gripped, control the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide the second RF signal to the second antenna, based on identifying that the electronic device is gripped, independently from at least one first parameter associated with the first antenna and at least one second parameter associated with the second antenna.

[0121] According to an example embodiment, the at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B) may be configured to, as at least part of controlling the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) provide the second RF signal to the second antenna based on identifying that the electronic device is gripped, control the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide the second RF signal to the second antenna, based on at least one first parameter associated with the first antenna and at least one second parameter associated with the second antenna meeting an antenna change condition.

[0122] According to an example embodiment, the at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B) may be further configured to, based on identifying that the electronic device is not gripped, identify whether at least one first parameter associated with the first antenna and at least one second parameter associated with the second antenna meets an antenna change condition. The at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B) may be further configured to control the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide a third RF signal corresponding to the first frequency band to the second antenna, based on the at least one first parameter and the at least one second parameter meeting the antenna change condition.

[0123] According to an example embodiment, the at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B) may be further configured to control the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide the third RF signal to the first antenna, based on the at least one first parameter and the at least one second parameter not meeting the antenna change condition.

[0124] According to an example embodiment, the at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B) may be further configured to control the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide the third RF signal corresponding to the first frequency band to the first antenna, based on identifying that the electronic device is not gripped.

[0125] According to an example embodiment, in the folding state of the closed state, a first distance to a third antenna most adjacent from the first antenna may be less than a second distance to a fourth antenna most adjacent from the second antenna.

[0126] According to an example embodiment, the at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B) may be further configured to control the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide a fourth RF signal corresponding to the first frequency band to the first antenna among the plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B), based on the folding state being the open state.

[0127] According to an example embodiment, a method of operating an electronic device including an RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) and a plurality of antennas (e.g., **305** and

315 of FIG. 3A or 325 and 327 of FIG. 3B) connected to the RF circuitry (e.g., 300 of FIG. 3A or 310 of FIG. 3B) may comprise controlling the RF circuitry (e.g., 300 of FIG. 3A or 310 of FIG. 3B) to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas (e.g., 305 and 315 of FIG. 3A or 325 and 327 of FIG. 3B) based on identifying that a folding state of the electronic device is an open state. The method of operating the electronic device may comprise, based on identifying the folding state of the electronic device being a closed state, identifying whether the electronic device is gripped. The method of operating the electronic device may comprise controlling the RF circuitry (e.g., 300 of FIG. 3A or 310 of FIG. 3B) to provide a second RF signal corresponding to the first frequency band to a second antenna different from the first antenna among the plurality of antennas (e.g., 305 and 315 of FIG. 3A or 325 and 327 of FIG. 3B), based on identifying that the electronic device is gripped.

[0128] According to an example embodiment, a non-transitory computer-readable storage medium may store instructions that, when executed by at least one processor, cause an electronic device to perform at least one operation. The at least one operation may comprise controlling the RF circuitry (e.g., 300 of FIG. 3A or 310 of FIG. 3B) of the electronic device to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas (e.g., 305 and 315 of FIG. 3A or 325 and 327 of FIG. 3B) based on identifying that a folding state of the electronic device is an open state. The at least one operation may comprise, based on identifying the folding state of the electronic device being a closed state, identifying whether the electronic device is gripped. The at least one operation may comprise controlling the RF circuitry (e.g., 300 of FIG. 3A or 310 of FIG. 3B) to provide a second RF signal corresponding to the first frequency band to a second antenna different from the first antenna among the plurality of antennas (e.g., 305 and 315 of FIG. 3A or 325 and 327 of FIG. 3B), based on identifying that the electronic device is gripped.

[0129] According to an example embodiment, an electronic device may comprise: at least one communication processor (e.g., 212 or 214 of FIG. 2A or 260 of FIG. 2B), a camera, an RF circuitry (e.g., 300 of FIG. 3A or 310 of FIG. 3B) connected to the at least one communication processor (e.g., 212 or 214 of FIG. 2A or 260 of FIG. 2B), and a plurality of antennas (e.g., 305 and 315 of FIG. 3A or 325 and 327 of FIG. 3B) connected to the RF circuitry (e.g., 300 of FIG. 3A or 310 of FIG. 3B). The at least one communication processor (e.g., 212 or 214 of FIG. 2A or 260 of FIG. 2B) may be configured to control the RF circuitry (e.g., 300 of FIG. 3A or 310 of FIG. 3B) to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas (e.g., 305 and 315 of FIG. 3A or 325 and 327 of FIG. 3B), based on identifying that the camera is in an off state. The at least one communication processor (e.g., 212 or 214 of FIG. 2A or 260 of FIG. 2B) may be configured to control the RF circuitry (e.g., 300 of FIG. 3A or 310 of FIG. 3B) to provide a second RF signal corresponding to the first frequency band to a second antenna different from the first antenna among the plurality of antennas (e.g., 305 and 315 of FIG. 3A or 325 and 327 of FIG. 3B), based on identifying that the camera is changed from the off state to an on state.

[0130] According to an example embodiment, controlling the RF circuitry (e.g., 300 of FIG. 3A or 310 of FIG. 3B) to provide the second RF signal to the second antenna based on identifying that the electronic device is gripped may control the RF circuitry (e.g., 300 of FIG. 3A or 310 of FIG. 3B) to provide the second RF signal to the second antenna based on identifying that the electronic device is gripped, independently from at least one first parameter associated with the first antenna and at least one second parameter associated with the second antenna.

[0131] According to an example embodiment, controlling the RF circuitry (e.g., 300 of FIG. 3A or 310 of FIG. 3B) to provide the second RF signal to the second antenna, based on identifying that the electronic device is gripped may control the RF circuitry (e.g., 300 of FIG. 3A or 310 of FIG. 3B) to provide the second RF signal to the second antenna, based on at least one first parameter associated with the first antenna and at least one second parameter associated with the second

antenna meeting an antenna change condition.

[0132] According to an example embodiment, the method of operating the electronic device may further comprise, based on identifying that the electronic device is not gripped, identifying whether at least one first parameter associated with the first antenna and at least one second parameter associated with the second antenna meets an antenna change condition. The method of operating the electronic device may further comprise controlling the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide a third RF signal corresponding to the first frequency band to the second antenna, based on the at least one first parameter and the at least one second parameter meeting the antenna change condition.

[0133] According to an example embodiment, the method of operating the electronic device may further comprise controlling the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide the third RF signal to the first antenna, based on the at least one first parameter and the at least one second parameter not meeting the antenna change condition.

[0134] According to an example embodiment, the method of operating the electronic device may further comprise controlling the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide the third RF signal corresponding to the first frequency band to the first antenna, based on identifying that the electronic device is not gripped.

[0135] According to an example embodiment, in the folding state of the closed state, a first distance to a third antenna most adjacent from the first antenna may be less than a second distance to a fourth antenna most adjacent from the second antenna.

[0136] According to an example embodiment, the method of operating the electronic device may further comprise controlling the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide a fourth RF signal corresponding to the first frequency band to the first antenna among the plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B), based on the folding state being the open state.

[0137] According to an example embodiment, a method of operating an electronic device including a camera, an RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B), and a plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B) connected to the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) may comprise controlling the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B), based on identifying that the camera is in an off state. The method of operating the electronic device may comprise controlling the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide a second RF signal corresponding to the first frequency band to a second antenna different from the first antenna among the plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B), based on identifying that the camera is changed from the off state to an on state.

[0138] According to an example embodiment, a non-transitory computer-readable storage medium may store instructions that, when executed by at least one processor, cause an electronic device to perform at least one operation. The at least one operation may comprise controlling the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide a first RF signal corresponding to a first frequency band to a first antenna among the plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B) of the electronic device, based on identifying that the camera of the electronic device is in an off state. The at least one operation may comprise controlling the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide a second RF signal corresponding to the first frequency band to a second antenna different from the first antenna among the plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B), based on identifying that the camera is changed from the off state to an on state.

[0139] According to an example embodiment, a first distance between the first antenna and the camera may be less than a second distance between the second antenna and the camera.

[0140] According to an example embodiment, the at least one communication processor (e.g., **212**

or **214** of FIG. 2A or **260** of FIG. 2B) may be configured to, as at least part of controlling the RF circuitry (**300** of FIG. 3A or **310** of FIG. 3B) provide the second RF signal to the second antenna based on identifying that the camera is changed from the off state to the on state, control the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide the second RF signal to the second antenna, based on identifying that a maximum transmission power level (MTPL) corresponding to the second antenna is a threshold or less.

[0141] According to an example embodiment, an electronic device may comprise at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B), an RF circuitry (**300** of FIG. 3A or **310** of FIG. 3B) connected to the at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B), and a plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B) connected to the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B). The at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B) may be configured to control the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide a first RF signal corresponding to a first sub frequency of a first frequency band to a first antenna among the plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B). The at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B) may be configured to identify whether at least one first parameter associated with the first antenna and at least one second parameter associated with the second antenna meet an antenna change condition, wherein the condition may be set corresponding to the first sub frequency of the first frequency band. The at least one communication processor (e.g., **212** or **214** of FIG. 2A or **260** of FIG. 2B) may be configured to control the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide a second RF signal corresponding to the first sub frequency of the first frequency band to a second antenna different from the first antenna among the plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B), based on the at least one first parameter and the at least one second parameter meeting the antenna change condition.

[0142] According to an example embodiment, a method of operating an electronic device including an RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) and a plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B) connected to the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) may comprise controlling the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide a first RF signal corresponding to a first sub frequency of a first frequency band to a first antenna among the plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B). The method of operating the electronic device may include identifying whether at least one first parameter associated with the first antenna and at least one second parameter associated with the second antenna meet an antenna change condition, wherein the condition may be set corresponding to the first sub frequency of the first frequency band. The method of operating the electronic device may comprise controlling the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) to provide a second RF signal corresponding to the first sub frequency of the first frequency band to a second antenna different from the first antenna among the plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B), based on the at least one first parameter and the at least one second parameter meeting the condition.

[0143] According to an example embodiment, a non-transitory computer-readable storage medium may store instructions that, when executed by at least one processor, cause an electronic device to perform at least one operation. The at least one operation may comprise controlling the RF circuitry (e.g., **300** of FIG. 3A or **310** of FIG. 3B) of the electronic device to provide a first RF signal corresponding to a first sub frequency of a first frequency band to a first antenna among the plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B). The at least one operation may comprise identifying whether at least one first parameter associated with the first antenna and at least one second parameter associated with the second antenna meet an antenna change condition, wherein the condition may be set corresponding to the first sub frequency of the first frequency band. The at least one operation may comprise controlling the RF circuitry (e.g.,

**300** of FIG. 3A or **310** of FIG. 3B) to provide a second RF signal corresponding to the first sub frequency of the first frequency band to a second antenna different from the first antenna among the plurality of antennas (e.g., **305** and **315** of FIG. 3A or **325** and **327** of FIG. 3B), based on the at least one first parameter and the at least one second parameter meeting the condition.

[0144] The electronic device according to an embodiment of the disclosure may be one of various types of electronic devices. The electronic devices may include, for example, a portable communication device (e.g., a smartphone), a computer device, a portable multimedia device, a portable medical device, a camera, a wearable device, a home appliance, or the like. According to an embodiment of the disclosure, the electronic devices are not limited to those described above.

[0145] It should be appreciated that various embodiments of the present disclosure and the terms used therein are not intended to limit the technological features set forth herein to particular embodiments and include various changes, equivalents, or replacements for a corresponding embodiment. With regard to the description of the drawings, similar reference numerals may be used to refer to similar or related elements. It is to be understood that a singular form of a noun corresponding to an item may include one or more of the things, unless the relevant context clearly indicates otherwise. As used herein, each of such phrases as “A or B,” “at least one of A and B,” “at least one of A or B,” “A, B, or C,” “at least one of A, B, and C,” and “at least one of A, B, or C,” may include all possible combinations of the items enumerated together in a corresponding one of the phrases. As used herein, such terms as “1st” and “2nd,” or “first” and “second” may be used to simply distinguish a corresponding component from another, and does not limit the components in other aspect (e.g., importance or order). It is to be understood that if an element (e.g., a first element) is referred to, with or without the term “operatively” or “communicatively”, as “coupled with,” “coupled to,” “connected with,” or “connected to” another element (e.g., a second element), the element may be coupled with the other element directly (e.g., wiredly), wirelessly, or via a third element.

[0146] As used herein, the term “module” may include a unit implemented in hardware, software, or firmware, or any combination thereof, and may interchangeably be used with other terms, for example, “logic,” “logic block,” “part,” or “circuitry”. A module may be a single integral component, or a minimum unit or part thereof, adapted to perform one or more functions. For example, according to an embodiment, the module may be implemented in a form of an application-specific integrated circuit (ASIC).

[0147] An embodiment of the disclosure may be implemented as software (e.g., the program **140**) including one or more instructions that are stored in a storage medium (e.g., internal memory **136** or external memory **138**) that is readable by a machine (e.g., the electronic device **101**). For example, a processor (e.g., the processor **120**) of the machine (e.g., the electronic device **101**) may invoke at least one of the one or more instructions stored in the storage medium, and execute it, with or without using one or more other components under the control of the processor. This allows the machine to be operated to perform at least one function according to the at least one instruction invoked. The one or more instructions may include a code generated by a compiler or a code executable by an interpreter. The machine-readable storage medium may be provided in the form of a non-transitory storage medium. Wherein, the “non-transitory” storage medium is a tangible device, and may not include a signal (e.g., an electromagnetic wave), but this term does not differentiate between where data is semi-permanently stored in the storage medium and where the data is temporarily stored in the storage medium.

[0148] According to an embodiment, a method according to various embodiments of the disclosure may be included and provided in a computer program product. The computer program products may be traded as commodities between sellers and buyers. The computer program product may be distributed in the form of a machine-readable storage medium (e.g., compact disc read only memory (CD-ROM)), or be distributed (e.g., downloaded or uploaded) online via an application store (e.g., Play Store™), or between two user devices (e.g., smart phones) directly. If distributed

online, at least part of the computer program product may be temporarily generated or at least temporarily stored in the machine-readable storage medium, such as memory of the manufacturer's server, a server of the application store, or a relay server.

[0149] According to an embodiment, each component (e.g., a module or a program) of the above-described components may include a single entity or multiple entities. Some of the plurality of entities may be separately disposed in different components. According to various embodiments, one or more of the above-described components may be omitted, or one or more other components may be added. Alternatively or additionally, a plurality of components (e.g., modules or programs) may be integrated into a single component. In such a case, according to various embodiments, the integrated component may still perform one or more functions of each of the plurality of components in the same or similar manner as they are performed by a corresponding one of the plurality of components before the integration. According to various embodiments, operations performed by the module, the program, or another component may be carried out sequentially, in parallel, repeatedly, or heuristically, or one or more of the operations may be executed in a different order or omitted, or one or more other operations may be added.

[0150] While the disclosure has been illustrated and described with reference to various example embodiments, it will be understood that the various example embodiments are intended to be illustrative, not limiting. It will be further understood by those skilled in the art that various changes in form and detail may be made without departing from the true spirit and full scope of the disclosure, including the appended claims and their equivalents. It will also be understood that any of the embodiment(s) described herein may be used in conjunction with any other embodiment(s) described herein.

## Claims

1. A portable communication device comprising: a plurality of antennas including a first antenna and a second antenna; radio frequency (RF) circuitry electrically connected with the first antenna and the second antenna; and a communication processor including processing circuitry and electrically connected with the RF circuitry, the communication processor configured to: control the RF circuitry to provide a first RF signal corresponding to a specified frequency band to the first antenna based at least in part on the portable communication device being fully unfolded; and control the RF circuitry to provide a second RF signal corresponding to the specified frequency band to the second antenna instead of the first antenna based at least in part on the portable communication device being fully folded.
2. The portable communication device of claim 1, wherein the communication processor is configured to: control the RF circuitry to provide the second RF signal to the second antenna instead of the first antenna further based on the portable communication device being gripped by a user.
3. The portable communication device of claim 1, wherein the communication processor is configured to: control the RF circuitry to provide the second RF signal to the second antenna instead of the first antenna further based on a specified condition being satisfied with respect to at least one of a first reference signal received power (RSRP) associated with the first antenna or a second RSRP associated with the second antenna.
4. The portable communication device of claim 1, wherein the communication processor is configured to: control the RF circuitry to provide the second RF signal to the second antenna instead of the first antenna further based on a specified condition being satisfied with respect to at least one of a first maximum transmission power level (MTPL) associated with the first antenna or a second MTPL associated with the second antenna.
5. The portable communication device of claim 1, further comprising a camera, wherein the communication processor is configured to control the RF circuitry to provide the second RF signal

to the second antenna instead of the first antenna based further on the camera being turned on.

**6.** A method performed by a portable communication device comprising radio frequency (RF) circuitry and a plurality of antennas including a first antenna and a second antenna, the method comprising: based at least in part on the portable communication device being fully unfolded, providing, through the RF circuitry, a first RF signal corresponding to a specified frequency band to the first antenna; and based at least in part the portable communication device being fully folded, providing, through the RF circuitry, a second RF signal corresponding to the specified frequency band to the second antenna instead of the first antenna.

**7.** The method of claim 6, further comprising: based on identifying that a status of the portable communication device is changed from an unfolded status to a folded status and the portable communication device is gripped by a user, performing, through the RF circuitry, a transmission of the second RF signal corresponding to the specified frequency band via the second antenna changed from the first antenna.

**8.** The method of claim 6, wherein the second RF signal is provided to the second antenna instead of the first antenna further based on a specified condition being satisfied with respect to at least one of a first reference signal received power (RSRP) associated with the first antenna or a second RSRP associated with the second antenna.

**9.** The method of claim 6, wherein the second RF signal is provided to the second antenna instead of the first antenna further based on a specified condition being satisfied with respect to at least one of a first maximum transmission power level (MTPL) associated with the first antenna or a second MTPL associated with the second antenna.

**10.** The method of claim 6, wherein the portable communication device further comprises a camera; and wherein the second RF signal is provided to the second antenna instead of the first antenna further based on the camera being turned on.

**11.** A foldable communication device comprising: a plurality of antennas including a first antenna and a second antenna; radio frequency (RF) circuitry electrically connected with the first antenna and the second antenna; at least one processor including processing circuitry and electrically connected with the RF circuitry; and memory including instructions, which when executed by the at least one processor individually or collectively, cause the foldable communication device to: transmit, using the RF circuitry, a first RF signal corresponding to a specified frequency band via the first antenna based on identifying that a status of the foldable communication device corresponds to a unfolded status; determine that the status of the foldable communication device is changed from the unfolded status to a folded status, and transmit, using the RF circuitry, a second RF signal corresponding to the specified frequency band via the second antenna changed from the first antenna based on the determination that the status of the foldable communication device is changed from the unfolded status to a folded status.

**12.** The foldable communication device of claim 11, further comprising a foldable housing including a first housing and a second housing foldable with respect to the first housing, wherein the first antenna and the second antenna are included in the first housing.

**13.** The foldable communication device of claim 12, wherein the first antenna is positioned at a top portion of the first housing, and the second antenna is positioned at a bottom portion of the first housing.

**14.** The foldable communication device of claim 11, wherein the instructions, when executed by the at least one processor individually or collectively, cause the foldable communication device to: transmit, using the RF circuitry, the second RF signal corresponding to the specified frequency band via the second antenna changed from the first antenna based on identifying that a status of the foldable communication device is changed from an unfolded status to a folded status and the foldable communication device is gripped by a user.

**15.** The foldable communication device of claim 11, wherein the instructions, when executed by the at least one processor individually or collectively, cause the foldable communication device to:

transmit, using the RF circuitry, the second RF signal corresponding to the specified frequency band via the second antenna changed from the first antenna based on identifying that the camera is turned on.

**16.** A method performed by a foldable communication device comprising radio frequency (RF) circuitry and a plurality of antennas including a first antenna and a second antenna, the method comprising: based on identifying that a status of the foldable communication device corresponds to a unfolded status, transmitting, using the RF circuitry, a first RF signal corresponding to a specified frequency band via the first antenna; determining that the status of the foldable communication device is changed from the unfolded status to a folded status; and based on the determination, transmitting, using the RF circuitry, a second RF signal corresponding to the specified frequency band via a second antenna changed from the first antenna.

**17.** The method of claim 16, wherein the foldable communication device further comprises a foldable housing including a first housing and a second housing foldable with respect to the first housing, and wherein the first antenna and the second antenna are included in the first housing.

**18.** The method of claim 17, wherein the first antenna is positioned at a top portion of the first housing, and the second antenna is positioned at a bottom portion of the first housing.

**19.** The method of claim 16, further comprising: transmitting, using the RF circuitry, the second RF signal corresponding to the specified frequency band via the second antenna changed from the first antenna based on identifying that a status of the foldable communication device is changed from an unfolded status to a folded status and the foldable communication device is gripped by a user; and/or transmitting, using the RF circuitry, the second RF signal corresponding to the specified frequency band via the second antenna changed from the first antenna based on identifying that the camera is turned on.

**20.** A non-transitory computer readable storage medium storing one or more programs, the one or more programs comprising instructions configured to, when executed by at least one processor of a foldable electronic device, cause the foldable electronic device to: transmit, using a RF circuitry, a first RF signal corresponding to a specified frequency band via a first antenna based on identifying that a status of the foldable communication device corresponds to a unfolded status; determine that the status of the foldable communication device is changed from the unfolded status to a folded status; and transmit, using the RF circuitry, a second RF signal corresponding to the specified frequency band via a second antenna changed from the first antenna based on the determination that the status of the foldable communication device is changed from the unfolded status to a folded status.

---