

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12416664
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Chaji; Gholamreza et al.

Micro device arrangement in donor substrate

Abstract

This disclosure is related to arranging micro devices in the donor substrate by either patterning or population so that there is no interfering with non-receiving pads and the non-interfering area in the donor substrate is maximized. This enables the transfer of micro devices to a receiver substrate with fewer steps.

Inventors:	Chaji; Gholamreza (Kitchener, CA), Fathi; Ehsanollah (Waterloo, CA)
Applicant:	VueReal Inc. (Waterloo, CA)
Family ID:	1000008818246
Assignee:	VueReal Inc. (Waterloo, CA)
Appl. No.:	18/398124
Filed:	December 27, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240133940 A1	Apr. 25, 2024

Related U.S. Application Data

continuation parent-doc US 18179894 20230307 US 11892497 child-doc US 18398124
continuation parent-doc US 16542022 20190815 US 11624770 20230411 child-doc US 18179894
division parent-doc US 15724320 20171004 US 10488455 20191126 child-doc US 16542022
us-provisional-application US 62515185 20170605
us-provisional-application US 62482899 20170407
us-provisional-application US 62473671 20170320
us-provisional-application US 62426353 20161125
us-provisional-application US 62403741 20161004

Publication Classification

Int. Cl.: **G01R31/26** (20200101); **B41M5/26** (20060101); **H01L21/683** (20060101); **H01L23/00** (20060101); **H01L23/544** (20060101); **H05K1/11** (20060101); **H05K13/00** (20060101); **H10K71/18** (20230101)

U.S. Cl.:

CPC **G01R31/2635** (20130101); **B41M5/265** (20130101); **H01L21/6835** (20130101); **H01L23/544** (20130101); **H01L24/27** (20130101); **H01L24/29** (20130101); **H01L24/32** (20130101); **H01L24/83** (20130101); **H05K1/111** (20130101); **H05K13/0015** (20130101); **H10K71/18** (20230201); H01L2221/68368 (20130101); H01L2223/54426 (20130101); H01L2224/95001 (20130101); H01L2224/97 (20130101); H01L2924/1304 (20130101); H01L2924/1304 (20130101); H01L2924/00012 (20130101)

Field of Classification Search

CPC: G01R (31/2635); H01L (2224/97); H01L (21/6835); H01L (24/27); H01L (24/32); H01L (24/29); H01L (24/83); H01L (23/544); H05K (1/111); H05K (13/0015)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
6132909	12/1999	Phillips	N/A	N/A
8349116	12/2012	Bibl et al.	N/A	N/A
8668835	12/2013	Indrakanti et al.	N/A	N/A
9893041	12/2017	Pokhriyal et al.	N/A	N/A
10177123	12/2018	Gardner et al.	N/A	N/A
11624770	12/2022	Chaji	438/141	B41M 5/265
11892497	12/2023	Chaji	N/A	H01L 24/32
2002/0035435	12/2001	Ninomiya et al.	N/A	N/A
2010/0127242	12/2009	Zhou et al.	N/A	N/A
2011/0151153	12/2010	Felder et al.	N/A	N/A
2012/0241919	12/2011	Mitani	N/A	N/A
2013/0316529	12/2012	Golda et al.	N/A	N/A
2014/0290867	12/2013	Bibl et al.	N/A	N/A
2015/0262856	12/2014	Thompson et al.	N/A	N/A
2016/0141196	12/2015	Chang	N/A	N/A
2016/0144608	12/2015	Chang	N/A	N/A
2016/0259250	12/2015	Hendriks et al.	N/A	N/A
2016/0336304	12/2015	Wu et al.	N/A	N/A
2017/0373046	12/2016	Gardner et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
101632156	12/2009	CN	N/A
102137590	12/2010	CN	N/A
103646893	12/2013	CN	N/A

104716043	12/2014	CN	N/A
104952851	12/2014	CN	N/A
105129259	12/2014	CN	N/A
105609455	12/2015	CN	N/A
105632985	12/2015	CN	N/A
115116925	12/2021	CN	N/A
H0583022	12/1992	JP	N/A
20150119149	12/2014	KR	N/A
201327910	12/2012	TW	N/A
201448024	12/2013	TW	N/A
9736194	12/1996	WO	N/A
0222374	12/2001	WO	N/A
2016010062	12/2015	WO	N/A
2016100657	12/2015	WO	N/A
2016116889	12/2015	WO	N/A

OTHER PUBLICATIONS

International Search Report and Written Opinion in International Application No. PCT/IB2017/056082, mailed Jan. 30, 2018 (7 pages). cited by applicant

Primary Examiner: Zarneke; David A

Attorney, Agent or Firm: Nixon Peabody LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION(S) (1) This application is a continuation of U.S. application Ser. No. 18/179,894, filed Mar. 7, 2023, now allowed, which is a continuation of U.S. application Ser. No. 16/542,022, filed Aug. 15, 2019, now U.S. Pat. No. 11,624,770, issued Apr. 11, 2023, which is a division of U.S. application Ser. No. 15/724,320, filed Oct. 4, 2017, now U.S. Pat. No. 10,488,455, issued Nov. 26, 2019, which claims priority to and the benefit of U.S. Provisional Patent Application No. 62/403,741, filed Oct. 4, 2016, U.S. Provisional Patent Application No. 62/426,353, filed Nov. 25, 2016, U.S. Provisional Patent Application No. 62/473,671, filed Mar. 20, 2017, U.S. Provisional Patent Application No. 62/482,899, filed Apr. 7, 2017, and U.S. Provisional Patent Application No. 62/515,185 filed Jun. 5, 2017, each of which is hereby incorporated by reference herein in its entirety.

TECHNICAL FIELD

(1) The present disclosure relates to a system for transferring micro devices onto a receiver substrate, and in particular to the patterning of micro devices on a donor substrate, and the landing area on a receiver substrate to increase the efficiency of transfer process.

BACKGROUND

(2) Several different selective transfer processes have already been developed for micro devices. However, if the receiver substrate requires different micro devices that are part of different donor substrates, the extra devices on the other donor substrates may interfere with the locations (pads) assigned to other types of micro devices on the receiver substrate.

(3) An object of the present invention is to overcome the shortcomings of the prior art by providing a particular patterning of devices on the donor substrate to avoid interference with pads on the receiver substrate destined for other micro devices. Other inventions comprise pre-processing the

devices on a donor substrate (cartridge substrate), preparing the landing area (or pads) on a receiver substrate, transferring the micro devices from the donor substrate to the receiver substrate, and post processing to enable device functionality. The pre-processing step may include patterning and adding bonding elements. The transfer process may involve bonding of a pre-selected array of micro devices to the receiver substrate followed by removing the donor substrate.

SUMMARY OF THE INVENTION

(4) Accordingly, the present invention relates to a method of populating a receiver substrate, comprising: a) providing a receiver substrate including a plurality of pixels, each pixel including first pads for receiving a first type of micro device and second pads for receiving a second type of micro device; b) providing a first donor substrate including a plurality of the first type of micro devices arranged in arrays separated by first interfering areas void of the first type of micro devices; c) aligning a first group of the first type of micro devices on the first donor substrate with a first group of the first pads on the receiver substrate, whereby the first interfering areas of the first donor substrate overlap the second pads to prevent interference with the second pads by the first type of micro devices; d) transferring the first group of the first type of micro devices from the first donor substrate to the first group of the first pads of the receiver substrate; e) adjusting a relative position of the first donor substrate and the receiver substrate to align a second group of the first type of micro devices with a second group of the first pads on the receiver substrate, whereby the first interfering areas of the first donor substrate overlap the second pads to prevent interference with the second pads by the first type of micro devices; and f) transferring the second group of the first type of micro devices from the first donor substrate to the second group of the first pads of the receiver substrate.

(5) Another aspect of the present invention relates to a donor substrate comprising: non-interfering areas including arrays of micro devices for transfer to receiver pads on a receiver substrate; and interfering areas comprising rows or columns of void areas for overlapping non-receiving pads on the receiver substrate to prevent micro devices on the donor substrate from interfering with non-receiving pads during transfer of microdevices to the receiving pads.

(6) Another feature of the present invention provides a method of arranging micro devices on a donor substrate to avoid interference with non-receiving pads on a receiver substrate during transfer of micro devices from the donor substrate to receiving pads on the receiver substrate, comprising: a) determining interfering areas on the donor substrate by i) determining areas on the donor substrate that overlap non-receiving pads on the receiver substrate during transfer of a first micro device to a first receiving pad on the receiver substrate; and ii) determining areas on the donor substrate that will not overlap non-receiving pads after offsetting at least one of the donor or the receiver substrate relative to the other to align at least a second micro device with a second receiving pad on the receiver substrate or another receiver substrate after the first micro device has been transferred to the receiver substrate; and b) arranging micro devices on the donor substrate in non-interfering areas other than the interfering areas.

(7) Another aspect of the present invention relates to a method of populating a receiver substrate, comprising: a) providing a receiver substrate including a plurality of pixels, each pixel including first pads for receiving a first type of micro device and second pads for receiving a second type of micro device; b) providing a first donor cartridge substrate including a plurality of the first type of micro devices arranged in arrays, and a plurality of the second type of micro devices arranged in arrays, interleaved with the arrays of the first types of micro device separated by a first interfering area void of the first or second types of micro devices; c) aligning a first group of the first types of micro devices and a first group of the second type of micro devices on the first donor cartridge substrate with a first group of the first pads and a second group of second pads, respectively, on the receiver substrate, whereby the first interfering area of the first donor cartridge substrate overlap an area caused by a difference in pitch between the pads and the pixels; d) transferring the first group of the first and second types of micro devices from the first donor cartridge substrate to the first

group of the first and second pads of the receiver substrate; e) adjusting a relative position of the first donor cartridge substrate and the receiver substrate to align a second group of the first and second types of micro devices with a second group of the first and second pads on the receiver substrate, whereby the first interfering areas of the first donor substrate overlap an area caused by a difference in pitch between the pads and the pixels; and f) transferring the second group of the first and second types of micro devices from the first donor substrate to the second group of the first and second pads of the receiver substrate.

(8) According to one embodiment, a method of populating a receiver substrate may be provided. The method may comprising the steps of: preparing a plurality of microdevices on one or more donor substrates, transferring the plurality of microdevices from the one or more donor substrates to a first cartridge substrate, the plurality of microdevices are arranged in arrays, separated by an interfering area in between, on the first cartridge substrate, selecting one or more transferable sets of micro devices in the first cartridge substrate, identifying a number of defective microdevices in each transferable set of micro devices and correcting the defective microdevices prior to transfer, aligning and transferring the selected micro devices on the first cartridge substrate to corresponding contact pads on a first receiver substrate; and determining if the first receiver substrate is fully populated with microdevices; i) in response to determining that the first receiver substrate is fully populated, proceeding to a second receiver substrate and repeating steps c) to e), ii) in response to determining that the first receiver substrate is not fully populated, determining whether the first cartridge substrate 1) has enough microdevices to continue transferring microdevices to the first receiver substrate or 2) has not enough microdevices to continue transferring microdevices to the first receiver substrate; iii) in response to determining that the first cartridge substrate has enough microdevices, selecting another transferable set of micro devices in the first cartridge substrate and repeating steps d) to e); else in response to determining that the first cartridge substrate has not enough microdevices, selecting a second cartridge substrate and repeating steps b) to f).

(9) According to another embodiment, a method of transferring a plurality of microdevices into a system substrate may be provided. The method comprising: arranging the plurality of microdevices in arrays separated by an interfering area in between a cartridge substrate, selecting one or more transferable sets of microdevices in the cartridge substrate, identifying a number of defective micro devices in each transferable set of micro devices, correcting the defective microdevices if a sum of a number of the identified defective microdevices is more than a threshold value; and aligning and transferring the selected micro devices on the cartridge substrate to corresponding contact pads on the receiver substrate.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) The invention will be described in greater detail with reference to the accompanying drawings which represent preferred embodiments thereof, wherein:
- (2) FIG. 1 illustrates an example of a micro device arrangement in a donor substrate.
- (3) FIG. 2 illustrates an example of a receiver substrate pixel with three different sub pixels.
- (4) FIG. 3A illustrates an embodiment of a donor substrate arranged into interference and non-interference areas based on the receiver substrate.
- (5) FIG. 3B illustrates another embodiment of a donor substrate arranged into interference and non-interference areas based on the receiver substrate.
- (6) FIG. 4 illustrates an embodiment using a taller pad associated with one of the microdevices to improve the non-interfering area.
- (7) FIG. 5 illustrates a cluster pad embodiment to improve the non-interfering area.
- (8) FIG. 6A illustrates an embodiment of a donor substrate with a non-interfering area associated

with the pads at the edge of cluster pads.

(9) FIG. 6B illustrates a donor substrate embodiment with a non-interfering area associated with the inside pads of the cluster.

(10) FIG. 7A illustrates an example of a donor substrate and a receiver substrate with cluster pads.

(11) FIG. 7B illustrates another example of a donor substrate and a receiver substrate with cluster pads.

(12) FIG. 8 illustrates an example of a receiver substrate with pads in the pixel arranged in two directions.

(13) FIG. 9A illustrates an embodiment of a donor substrate with a non-interfering area associated with the one of the pads in the pixel.

(14) FIG. 9B illustrates another embodiment of a donor substrate with a non-interfering area associated with the one of the pads in the pixel.

(15) FIG. 9C illustrates another embodiment of a donor substrate with a non-interfering area associated with the one of the pads in the pixel.

(16) FIG. 9D illustrates another embodiment of a donor substrate with non-interfering area associated with the one of the pads in the pixel.

(17) FIG. 10 illustrates an embodiment with cluster pads to improve the non-interfering area for the pixel pads arranged in two directions.

(18) FIG. 11A illustrates an embodiment of a donor substrate with a non-interfering area associated with the one of the pads in the cluster.

(19) FIG. 11B illustrates another embodiment of a donor substrate with a non-interfering area associated with the one of the pads in the cluster.

(20) FIG. 11C illustrates another embodiment of a donor substrate with a non-interfering area associated with the one of the pads in the cluster.

(21) FIG. 12A illustrates an example of a donor substrate and a receiver substrate with cluster pads arranged in two directions.

(22) FIG. 12B illustrates an example of a donor substrate and a receiver substrate with cluster pads arranged in two directions.

(23) FIG. 12C illustrates an example of a donor substrate and a receiver substrate with cluster pads arranged in two directions.

(24) FIG. 12D illustrates an example of a donor substrate and a receiver substrate with cluster pads arranged in two directions.

(25) FIG. 13A illustrates an embodiment of a pad cluster in a receiver substrate and a donor substrate with a non-interfering area associated with reference to the one of the pads in the cluster.

(26) FIG. 13B illustrates another embodiment of a donor substrate with a non-interfering area associated with the one of the pads in the cluster.

(27) FIG. 14A illustrates an example of a donor substrate and a receiver substrate with cluster pads arranged in two directions.

(28) FIG. 14B illustrates an example of a donor substrate and a receiver substrate with cluster pads arranged in two directions.

(29) FIG. 15A illustrates an example of a donor (cartridge) substrate with different types of micro devices.

(30) FIG. 15B is a flow chart of the process of the present invention.

(31) FIG. 15C is a flow chart of the micro device mounting process of the present invention.

(32) FIG. 16 illustrates an example of a donor (cartridge) substrate with different types of micro devices.

(33) FIG. 17 illustrates an example of a donor substrate for the same type of micro devices, but a different pitch between sets of micro devices.

(34) FIG. 18 illustrates an example of a donor substrate with non-uniformity of output across a block of micro devices.

- (35) FIG. 19 illustrates an example of a receiver substrate with non-uniformity of output across a plurality of block of micro devices.
- (36) FIG. 20 illustrates an example of a receiver substrate with skewed blocks of micro devices.
- (37) FIG. 21 illustrates an example of a receiver substrate with flipped blocks of micro devices.
- (38) FIG. 22 illustrates an example of a receiver substrate with flipped and alternating blocks of micro devices.
- (39) FIG. 23 illustrates an example of a donor substrate with two different blocks of micro devices.
- (40) FIG. 24 illustrates an example of a receiver substrate with skewed blocks of different micro devices.
- (41) FIG. 25A illustrates an example of a donor substrate with three different types of blocks of micro devices.
- (42) FIG. 25B illustrates an example of populating a cartridge from different blocks to eliminate the non-uniformity found in any one block.
- (43) FIG. 26 illustrates an example of a cartridge substrate with a plurality of different types of blocks of micro devices.
- (44) FIG. 27 illustrates an example of a cartridge substrate with a plurality of different types of offset blocks of micro devices.

DETAILED DESCRIPTION

- (45) While the present teachings are described in conjunction with various embodiments and examples, it is not intended that the present teachings be limited to such embodiments. On the contrary, the present teachings encompass various alternatives and equivalents, as will be appreciated by those of skill in the art.
- (46) In this disclosure, a pad on a receiver substrate refers to a designated area on the receiver substrate where a micro device has been or will be transferred from a donor substrate. The pads could be conductive to provide a connection between the micro device and a pixel circuit or the connections to the pixel circuits may be underneath the pad or on the side of the pad. The pad may have some form of bonding materials to hold the micro device permanently. The pad may be a multi-layer stack to offer a more mechanically stable structure, and also to provide better functionality, such as bonding and conductivity capability.
- (47) The pads in this description may provide at least one of an electrical connection, a mechanical connection, and a defined area for transferring micro devices. The shapes of the pads used in the illustrated embodiments are for the purpose of illustration only, and the pads may have any arbitrary shape. The position of the pads with respect to the pixels may be changed without any effect on the embodiments. The orientation of the group of pads in the pixel may be changed. For example, they may be rotated, shifted or moved to different positions. The pads may have a complex structure comprising different conductive, semiconductor and dielectric layers. The pads may be positioned on top of other structures, such as transistors, in the receiver substrate. Also, the pads may be beside other structures on the receiver substrates.
- (48) The shape of the micro devices used in the embodiments are for purpose of illustration, and the micro devices may have different shapes. The micro devices may have one or more pads on the side that will contact the receiver substrate. The pads may provide mechanical or electrical connection or a combination of both.
- (49) In one embodiment, a method of arranging micro devices in the donor substrate is described that is used to transfer micro devices to the receiver substrate. In the donor substrate, micro devices are arranged in relation to the pixel area, and within the area associated with the pixel the micro devices may have a pitch that is smaller than the pixel pitch.
- (50) In this arrangement, the pitch between the micro devices at the boundary of two pixels may be different from the pitch of micro devices within the pixel.
- (51) In this case, there are more micro devices on the donor substrate than intended/wanted pads in the receiver substrate associated with the donor substrate area. Therefore, the micro devices may

interfere with other unwanted/unintended pads in the receiver substrate. Several embodiments in this document are described to define interfering areas of the donor substrate to either remove or not populate micro devices in those areas. This embodiment may be used for different micro device arrangements in the donor substrate.

(52) In another embodiment, a method of arranging micro devices described in a donor substrate to avoid interference with unwanted pads, includes a) defining interfering areas or non-interfering areas where: 1) the non-interfering areas are spaces in the donor substrate that are not covered by other unwanted pads during micro device transfer to receiver substrate, i.e. the interfering areas are covered by unwanted pads, OR 2) will not be covered by pads after offsetting the donor or receiver substrate in a certain direction to align at least one micro device with a wanted pad in the receiver substrate after at least one micro device different from said micro device is transferred to a pad different from the said pad in the receiver substrate, i.e. the interfering areas will be covered by pads in subsequent steps; and b) arranging micro devices in the non-interfering areas of the donor substrate.

(53) In the receiver substrate described above, one pad on the receiver substrate may have a taller structure, and the micro device associated with the pad may have a shorter structure. Thus, there will be no interfering area for this pad.

(54) To increase the non-interfering area, one embodiment comprises a method of arranging the pads associated with the micro device transfer position in the receiver substrate into clusters, wherein within said clusters the pad pitch is smaller than the sub-pixel pitch.

(55) In case of cluster pads, a donor substrate for a pad at the edge of a cluster may be arranged in such way that interfering and non-interfering areas are similar to the pixel area where the width of the interfering area is the same as the distance of the other pads from the pad.

(56) In case of a cluster, a donor substrate for a pad inside of the cluster may be arranged, whereby interfering and non-interfering areas are similar to the pixel area, and the interfering areas are defined by: a) Finding the distance between the pad and the edge of the cluster; b) Picking one micro device as a reference device on the donor substrate; c) Defining the interfering area from the micro device on both sides similar to the distance of the associated pads to the edge of the cluster.

(57) The pattern of interfering and non-interfering areas, defined by an area associated with a pixel on the donor substrate, may be repeated on the donor substrate similar to the pixel pitch.

(58) In the remaining area of the donor substrate, patterned (arranged) for the middle pad, associated with each pixel, a column (or row) of micro devices is between interfering areas whose width is larger than the minimum distance of the middle micro device from the edge of said cluster.

(59) In one embodiment to maximize the non-interfering area, the pad pitch within the cluster may be the same as the micro device pitch in the donor substrate.

(60) In another embodiment to maximize the non-interfering area, the pads may be arranged in a two-dimensional cluster. The pads in the cluster may be aligned with at least another pad.

(61) In one embodiment, a donor substrate for the pads may be aligned with other pads in two directions, creating diagonal interfering areas with reference to the pad cluster orientations. The area may contain other pads and the remaining area associated with a pixel is non-interfering, in which micro device may exist.

(62) In another embodiment, a donor substrate for the pads may be aligned with pads in only one direction, which has the interfering area as:

(63) One row including other pads if the said pad is aligned vertically with the other pads, OR

(64) One column if the said pad is aligned horizontally with another pad.

(65) Whereby, the remaining area associated with a pixel is non-interfering in which a micro device can exist.

(66) In this embodiment, donor substrate, and/or cartridge substrate are used interchangeably. The characteristics of the donor substrate can be applied to the cartridge and vice versa.

(67) FIG. 1 illustrates a donor substrate **150**, in which there are more micro devices **160** than

associated pads in a receiver substrate, e.g. see FIGS. 2 and 3. In this case, the micro devices **160** may have a pitch **170** smaller than a pixel pitch of the receiver substrate in an area or block **130** of the donor substrate associated with the pixels. Also, as the pixel pitch may not be a multiple of the micro device pitch **170**, the micro device pitch **180** between two adjacent (vertically and horizontally) pixel areas **130** and **140** may have a different pitch, e.g. a void or interference area, to accommodate the difference between the pixel and micro device pitches.

(68) In traditional pick and place, the micro devices **160** on the transfer head, e.g. donor substrate **150**, are transferred one at a time or one row at a time to a position on the receiver substrate. To populate the rest of the receiver substrate or another receiver substrate, the transfer head needs to be repopulated or a new donor substrate **150** must be used. This process requires fast and accurate movement and precision alignment every time to avoid the interference of the micro devices **160** on the donor substrate **150** with other micro devices **160** already on the receiver substrate or other pads on the receiver substrate not destined to receive that particular micro device **160**. However, the present invention enables more micro devices **160** to be disposed on the donor substrate **150** than what is required to populate an equivalent area on the receiver substrate, thereby minimizing repopulation steps. Accordingly, empty or void areas on the donor substrate **150** enable the donor substrate **150** (or receiver substrate) to be offset during the transfer process to align the remaining set of micro devices **160** with corresponding locations in the receiver substrate. The offset can be done independently, or it can be part of moving the donor substrate **150** to the new location on the receiver substrate or a new receiver substrate.

(69) FIG. 2 illustrates a pixel structure in a receiver substrate **200**. An array of pixels on the receiver substrate **200** may be made of different orientations and combinations of this pixel structure. The pixel structure comprises different micro devices and each micro device may have a different pixel circuit or pixel connections. The pads **204**, **214**, **224** for each micro-device type are put in each designated subpixel area **202**, **212**, **222**, with a width of **208**, **218** and **228**, respectively, and repeated in both x and y directions forming an array of pixels. In the illustrated embodiment, the receiver substrate **200** includes three different pads **204**, **214**, **224** for three different micro devices at a distance of **216** and **226** apart. However, one can use any number of different micro devices. In one pixel array structure, the micro device types (or subpixel type) only vary in one direction (one-directional array structure). In another array type, the micro devices can vary in two or more directions (two-directional array). If the donor substrate **150** for each device type has micro devices **160** in all areas, i.e. a completely filled 2×2 array, the micro devices **160**, in corresponding areas to the pads **204**, **214** and **224** of the other micro device types, may interfere with the pads **204**, **214** and **224** during the transfer process. In one case, only the micro devices **160** in the area related to the corresponding pads, e.g. **204**, on the receiver substrate **200**, remain on the donor substrate **150**. However, in this case the donor substrate **150** needs to be replaced or refilled after each transfer, which can increase the processing steps. Moreover, the micro device utilization may be affected, if the reset of micro devices **160** cannot be used. In one aspect of the invention, the donor substrate **150** for each micro device **160** is divided into interfering and non-interfering areas. The micro devices **160** from the interfering areas of the donor substrate **150** are removed or not populated. In one aspect of this invention, the micro devices **160** are arranged in a donor substrate **150** to avoid interfering with unwanted pads, e.g. **214** and **224**, where the method includes: a) defining non-interfering areas as: i) spaces in the donor substrate **150** that do not correspond with, overlap or interfere with other unwanted pads **204**, **214**, **224** on the receiver substrate **200** during transfer of a first set of the micro devices **160** to a first set of the pads **204** on the receiver substrate **200**; and ii) spaces in the donor substrate **150** that do not correspond with, overlap or interfere with the pads **204**, **214** and **224** after offsetting the donor or the receiver substrates **150** or **200**, respectively, in a certain direction to align a second set of the micro device **160** with a second set of the wanted pad **204**, **214** and **224** in the receiver substrate **200** after at least the first set of the micro devices **160** different from the second set of the micro devices **160** is transferred to the second set

of pads **214** or **224** different from the first set of pads **204** in the receiver substrate **200**; and b) arrange the micro devices **160** only in the non-interfering areas of the donor substrate **150**.

(70) Alternatively, the method may include: a) defining interfering areas as: i) spaces in the donor substrate **150** that correspond with, overlap or interfere with other unwanted pads **204**, **214**, **224** on the receiver substrate **200** during transfer of a first set of the micro devices **160** to a first set of the pads **204** on the receiver substrate **200**; and ii) spaces in the donor substrate **150** that correspond with, overlap or interfere with the pads **204**, **214** and **224** after offsetting the donor or the receiver substrates **150** or **200**, respectively, in a certain direction to align a second set of the micro device **160** with a second set of the wanted pad **204**, **214** and **224** in the receiver substrate **200** or a different receiver substrate after at least the first set of the micro devices **160** different from the second set of the micro devices **160** is transferred to the second set of pads **214** or **224** different from the first set of pads **204** in the receiver substrate **200**; and b) arrange the micro devices **160** only in the non-interfering areas of the donor substrate **150**, but not the interfering areas.

(71) In one way to define the non-interfering areas, the directions of an offsetting donor substrate **150** (or the receiver substrate **200**) in relation to the receiver substrate **200** (or the donor substrate **150**) are defined. For example, after a first set of the micro devices **160** are transferred from the donor substrate **150** to the first set of pads **204**, the donor substrate **150** is offset horizontally and vertically. After transferring the first set of micro devices **160** from the donor substrate **150** to the receiver substrate **200**, the donor substrate **150** is either offset horizontally or vertically. The other set of micro devices **160** may be aligned with other related pads **214** or **224**, and transferred to these pads on the receiver substrate **200** that can be the original receiver substrate **200** or a different one. The following procedure is an exemplary process that can be used to identify the interfering and non-interfering area. a) A first set of micro devices for transferring to the receiver substrate is used as a reference. b) From the reference micro devices, draw lines in parallel with the offsetting direction. c) Draw lines in the direction of offsets from the corresponding pads for other type of micro devices in reference to the reference pads on the donor substrate. d) Identify the closest lines from the other types of micro devices to the lines of the micro device on the donor substrate. e) Draw a line between the selected lines and the micro device line. This line has a similar distance from each of the micro device line and selected lines. f) The areas defined by the new lines and encompassing the micro device are the non-interfering areas. The other areas are defined as interfering areas.

(72) FIG. 3A shows one example of defining non-interfering area **304-1** and interfering area **304-2**. The pixel area **330** includes both non-interfering and interfering areas **304-1** and **304-2**, respectively. In this case, the micro devices are offset horizontally and vertically. As a result, the width $w_{sub.ni}$ of the non-interfering area **304-1** for each micro device is half of the sum of the distances $w_{sub.1}$ and $w_{sub.2}$ between the pad **304 314** for that micro device and the other adjacent pads **314304**, **324**, respectively. In FIG. 3B, the devices are offset horizontally and diagonally. As a result, the non-interfering area **304-1** has a slope similar to the slope of a diagonal offset process. As can be seen in both cases, the non-interfering area **304-1** is small compared to the interfering area **304-2**.

(73) One solution to address this issue is to have one of the pads **414** taller than at least one of the other pads **404**, **424**. The micro device **414-D** with the taller pad **414** may be the more expensive device or more used on the receiver substrate **400**. However, it can be any other device as well. In the illustrated embodiment, the other micro devices **404-D** and **424-D** may have a taller structure compared to the micro devices **414-D** associated with the taller pads **414**, whereby the resulting combination of pad **414** and device **414-D** heights are substantially the same as those of pad **404** and device **404-D**. One method to achieve a taller device is to have taller connection pads. The taller pad may be on either side of the device. FIG. 4 shows an exemplary receiver substrate **400** in which one or more pads **414** are taller than the other pads **404**, **424**. In the illustrated embodiment, three different micro devices **404-D**, **414-D**, **424-D** are being transferred to the receiver substrate

400 from donor substrates **450-04**, **450-14**, **450-24**, respectively. The micro devices **404-D** and **424-D**, associated with the shorter pad structures **404** and **424**, have taller structures compared to the other micro device **414-D**. The same technique can be applied to other combination of micro devices (more or less than three micro devices). Accordingly, the shorter micro devices **414-D** will not interfere with the shorter pads **404** and **424**, and the interfering area on the donor substrate **450-14** is minimal.

(74) In another solution, the pads **504**, **514** and **524** for different micro devices may be set in a cluster **540** close to each other, leaving a large area or pitch between clusters. In one embodiment, the circuit or other connections associated with the pads **504**, **514** and **524** may be defined by sub-pixel structures #1, #2 and #3 with widths **508**, **518** and **528**, respectively, for ease of implementation. In another embodiment, the circuits and connections may have any other structure. The closer the pads **504**, **514** and **524** are together, the larger the non-interfering area **506** will be. In one case, the distance between two pads, e.g. **216** or **226**, can be equal to or smaller than $\frac{1}{3}$ of the pixel pitch **530** for three different micro devices (three different sub-pixels) on the donor substrate. For more or fewer sub-pixels (micro device types) similarly the pads **504**, **514** and **524** may be put closer together. In one embodiment, the distances **216** and **226** between the pads **504**, **514** and **524** in the cluster **540** is similar to the micro device pitch on the donor or cartridge substrate. If the different micro devices have the same pitch on the donor substrates, the cluster pads **504**, **514** and **524** will have the same pitch. In another case, the distance between the pads **504**, **514** and **524** in the cluster **540** is a multiple (for example twice that) of the pitch of micro devices on the donor substrate. In another embodiment, the distance between the pads can be smaller than the pitch of micro devices on the donor substrate. FIG. 5 shows a receiver substrate with an example of pad clusters **540**. These pads **504**, **514**, **524** may be from the sub-pixels **502**, **512**, **526** in one pixel **530** or from different pixels. The pads **504**, **514**, **524** may be in any position with reference to the pixel **530**. It is possible that the order and position of the pads **504**, **514**, **524** are different for different pixels.

(75) FIG. 6A shows the interfering area **604-1**, and the non-interfering **604-2** area for the pad **604** at the edge of the cluster **640**. The same structure can be used for the other pad **624** at the other side of the cluster **640**. As can be seen the non-interfering areas **604-2** for the pads **604** and **624** at the edge of the cluster **640** are larger compared to previous cases. For the pad **614** in the middle, the non-interfering area **614-1** and interfering area **614-2** can be a stripe pattern as demonstrated in FIG. 6B. Here, the width of the stripe is the same as the distance between the middle pad **614** and the other pads **604** and **624**. To define the non-interfering areas, following steps can be used: a) Find the distance between the pad **604** and the edge of the cluster pad b) Pick one micro device as a reference device in the donor substrate c) Interfering area is defined from the micro device to both sides similar to the distance of the associated pads to the edge of cluster.

(76) The pattern of interfering and non-interfering areas defined by an area associated with a pixel in the donor substrate can be repeated in the donor substrate similar to the pixel pitch. In the remaining areas of the donor substrate, patterned (arranged) for the middle pad, associated with each pixel, a column (or row) of micro devices is between interfering areas whose width is larger than the minimum distance of the middle micro device from the edge of said cluster. If the distance between the middle pad and the other pads is the same, the ratio of interfering area **614-2** to non-interfering area **614-1** may be the same. Similar to FIG. 3B, the interfering and non-interfering areas **614-2** and **614-1** may have different shapes depending on the offsetting direction. Also, similar to FIG. 4, the middle pad can be taller and so in this case the non-interfering area for the middle micro device can be the entire donor substrate.

(77) If the micro devices do not have a similar pitch, the distance between pads **604**, **614** and **624** in the cluster **640** can be similar to any of the pitch of the micro devices or each pad **604**, **614** and **624** may have different distance from the other pads. To improve the non-interfering area, the middle device may be the one with the larger pitch, whereby using taller pads can help to improve the

interfering area.

(78) FIG. 7A illustrates an embodiment in which pads **704**, **714** and **724** in a receiver substrate **700** have the same pitch as micro devices **752** and **754** in a donor substrate **750**. The position of a pad cluster **740** may be different with reference to the pixels **730** on the receiver substrate **700**. The size of the pads **704**, **714** and **724** may be smaller than, similar to, or larger than the micro devices **752** and **754**. The shape of the micro devices **752** and **754** and the pads **704**, **714** and **724** may be any suitable shape and size. In this case, the micro devices **752** and **754** may be removed (or nonpopulated) from the interfering area on the donor substrate **750** creating void areas on the donor substrate **750** corresponding to current or future populated or unpopulated pads on the receiver substrate **700** and any subsequent receive substrate, which are not designated to receive one of the micro-devices from the current donor substrate **750**.

(79) FIG. 7A illustrates an embodiment for the edge pad **704** (similar structure can be used for **724**). In the illustrated embodiment, the donor substrate **750** includes arrays of micro-devices **752** separated by void areas, each with at least a width substantially equal to the sum of the pitches of the adjacent pads, e.g. pad **704** to **714** and pad **714** to **724**, of the pitch $\times$ N (the number of adjacent pads) for equally spaced pads. The minimum distance for the void areas, i.e. the distance between arrays of micro devices **752** on the donor substrate **750**, is the distance from one side of the pad closest to the pad being filled, e.g. pad **714**, to the opposite side of pad farthest from the pad being filled, e.g. pad **724**. In other words, the area to cover the other pads **714** and **724** without interfering therewith during a current or any future transfer steps. The donor substrate **750** may be comprised of columns and rows of micro devices **752** and **754**, and include void areas defined by a number of missing columns or rows equal to the number of pads, e.g. **714** and **724**, adjacent to the receiver pad, e.g. **704**, on each side thereof. The number of columns in each array is dependent upon the spacing between the pads **704** and **724** in adjacent pixels **730**. For example, the donor substrate **750** for the pad **704**, which includes two adjacent pads **714** and **724** to the right and none to the left, may include a void area with two missing columns of micro devices, if the pitch of the micro devices **752** and **754** is the same as the pads **714** and **724**. Alternatively, if the pitches are different, then the void area may be at least the distance from the pad, e.g. pad **704**, mounted to the far edge of the farthest pad, e.g. pad **724**.

(80) Some of the micro devices **754** may have already been transferred to the receiver substrate **700**, and the donor substrate **750** (or the receiver substrate **700**) is offset vertically and/or horizontally with reference to the next receiver substrate **700** (or donor substrate **750**), so that another micro device **754** is aligned with one of the bare pads **704** (pads to which no micro device is transferred). In this case, the empty space created by transferring the micro device **754** will be a new empty area which will be on top of the pad **714**, and the empty space that was on top of the pad **714** will be on top of the pad **724**, when the receiver substrate **700** (or donor substrate **750**) is subsequently offset again. As such there will be no interference caused by the micro devices **752** and **754** for the unwanted pads **714** and **724**. One can finish all the micro devices in one column by offsetting vertically first and then moving to the next column (for example after finishing column 2, it moving to column 1). However other combinations of vertical and horizontal offsetting can be used. The pixels **730** or the pad clusters **740** may be at an angle either vertically or horizontally. In this case, the rows or columns of micro devices will be tilted as well. In addition, the micro devices can be at an angle without the pads or pixels being at angles. In this case, the offsetting direction will be toward the angle of the column or the row.

(81) FIG. 7B shows a similar structure for a donor substrate **751**, as above, but for the middle pad **714**, which would be aligned with the receiver substrate **700** before or after the donor substrate **750**. In the illustrated embodiment, the arrays, e.g. $1\times N$ array, of micro devices **753** and **755** are separated by void areas each with a width substantially equal to the sum of the pitches of the adjacent pads, e.g. **704** and **724**, e.g. the pitch $\times$ N (N=the number of adjacent pads) for equally spaced pads. The minimum distance for the void areas, i.e. the distance between arrays of micro

devices **753** on the donor substrate **751**, is the distance from one side of the pad closest to the pad being filled, e.g. pad **704** or **724**, to the opposite side of the pad farthest from the pad being filled, e.g. the same pad **704** or **724**. In other words, the void areas have enough space, i.e. distance between arrays of micro devices **753** to cover the other pads **704** and **724** without interfering therewith during current or future transfer steps. Typically, the length of the void areas is the full length of the donor substrate **751**. For pad clusters **740** of three pads **704**, **714** and **724**, the donor substrate **751** for the middle pads **714** may include arrays of micro devices **753** laterally separated by twice the pitch of the pads, and vertically separated by the pitch of the pads. The donor substrate **751** may be comprised of columns and rows of micro devices **753** and **755**, and include void areas defined by a number of missing columns or rows equal to the number of pads, e.g. **704** and **724**, adjacent to the receiver pad, e.g. **714**, on each side thereof. The number of columns in each array is dependent upon the spacing between the pads **704** and **724** in adjacent pixels **730**. For example, the donor substrate **751** for the receiver pad **714**, which includes one adjacent pad **704** to the left, and one pad **724** to the right, may include a void area with one missing column of micro devices on each side, if the pitch of the micro devices **753** and **755** is the same as the pads **714** and **724**. Alternatively, if the pitches are different, then the void area may be at least the distance from the pad, e.g. pad **714**, mounted to the far edge of the farthest pad, e.g. pad **704** or **724**.

(82) FIG. **8** illustrates another pixel orientation embodiment **850**, in which the sub-pixels **802**, **812** and **822** are distributed in two dimensions, e.g. horizontally and vertically. The pads **804**, **814** and **824** are shown in each corresponding sub-pixel **802**, **812** and **822** area. A horizontal distance **806** is between the pads **804** and **824**, a horizontal distance **816** is between pads **804** and **814**, a horizontal distance **826** is between pads **824** and **814**, and a vertical distance **836** is between pad **824** and pads **804** and **814**. The distances **806**, **816**, **826**, and **836** are used to define the interfering and non-interfering areas. The sub-pixels **802**, **812** and **822** may be aligned in vertical and horizontal orientations (or diagonally). For example, pads **814** and **824** may be aligned vertically and so horizontal distance **826** may be zero.

(83) FIGS. **9A-9D** illustrate some examples for the interfering areas and the non-interfering areas for different pads **904**, **914** and **924**. FIG. **9A** is for pad **904** based on horizontal and vertical offsetting of micro devices. In this case, the non-interfering areas **904-1** and interfering area **904-2** may be a combination of boxes around or offset from the pads **904**, **914**, **924**. FIG. **9B** shows another example of the non-interfering area **904-1** and the interfering area **904-2** for pad **904**. Here, the denominator of the two non-interfering areas between pad **904** and **914** and pads **904** and **924** is used as the non-interfering area for pad **904**. FIG. **9C** shows horizontal non-interfering area **924-1** and interfering area **924-2**. For pad **914**, the most optimized case is based on diagonal offsetting. FIG. **9D** shows the diagonal strips for the non-interfering area **914-1** and the interfering area **914-2**. Other patterns also may be used with different offsetting direction. In this embodiment different pad heights, as described in FIG. **4**, may be used to improve the device utilization for some of the pads.

(84) FIG. **10** illustrates another embodiment of a cluster pad **1040**, in which the pads **1004**, **1014** and **1024** are in two dimensions. Similar to FIG. **5**, the pads **1004**, **1014** and **1024** may have a different pitch depending on the different pitches of the micro devices on the donor substrate.

(85) FIG. **11A** illustrates a non-interfering area **1104-1**, and an interfering area **1104-2** for a pad **1104** at the edge of a cluster **1140**. The non-interfering areas for the pads at the edge are larger than previous cases. FIG. **11B** shows a non-interfering area **1124-1** and an interfering area **1124-2** for a pad **1124**. For the pad **1114** in the middle, a non-interfering area **1114-1** and an interfering area **1114-2** may be a diagonally striped pattern, as demonstrated in FIG. **11C**. Here, the width of the strip is the same as the distance, e.g. center to center or the diagonal pitch, between the middle pad **1114** and the other pads **1104** and **1124**. If the distance between the middle pad **1114** and the other pads **1104** and **1124** is the same, the ratio of the interfering area **1114-2** to the non-interfering area **1114-1** may be the same. Similar to FIG. **3B**, here the two areas can have different shapes

depending on the offsetting direction. Also, similar to FIG. 4, the middle pad **1114** can be taller and so in this case the non-interfering area **1114-1** for the middle micro device **1114** may be the entire donor substrate.

(86) FIGS. **12A** to **12D** illustrates an embodiment in which the pads **1204**, **1214** and **1224** in a receiver substrate **1200** have the same pitch as micro devices **1252** and **1254** in a donor substrate **1250**. The position of a pad cluster **1240** on the receiver substrate **1200** may be different in reference to the pixels **1230** on the donor substrate **1250**. The size of the pads **1204**, **1214** and **1224** may be smaller or similar or larger than the micro devices **1252** and **1254**. The shape of the micro devices **1252** and **1254**, and the pads **1204**, **1214** and **1224** may be any suitable shape and size. In this embodiment, the micro devices **1252** and **1254** are removed (or nonpopulated) from the interfering area on the donor substrate **1250**.

(87) FIG. **12A** illustrates an embodiment of a donor substrate **1250** for the edge pad **1204**. Some of the micro devices **1254** may have already been transferred to the receiver substrate **1200**, and the donor substrate **1250** (or receiver substrate **1200**) is offset vertically and/or horizontally with reference to the next receiver substrate **1200** (or the donor substrate **1250**) so that another micro device **1254** is aligned with the bare pads **1204** on a subsequent receiver substrate **1200** (pads to which no micro device has yet been transferred). In the illustrated embodiment, a plurality of arrays or blocks of micro devices **1252** and **1254** are provided on the donor substrate **1250**. Within each array of micro devices, the spacing or pitch of the micro devices may be consistent, e.g. a first predetermined pitch, and is ideally the same pitch or spacing as the pads **1204** and **1214**. Each array of micro devices is separated by a void, i.e. an interfering area defined by a distance across of at least N times the pitch or spacing between the pads or from one side of the closest pad to the far side of the farthest pad, e.g. **1204** or **1214**, where N is the number of adjacent pads, e.g. **1204** or **1214**. Typically, the length of the void areas is the full length of the donor substrate **1250**. In this case, the empty spaces on the donor substrate **1250** created by transferring the micro device **1254** may be a new empty area, which could be on top of other pads **1214**, **1224** in subsequent receiver substrates **1200**. As such there will be no interference caused by the micro devices for the unwanted pads **1214**, **1224**. One can finish all the micro devices **1254** in one column by offsetting vertically first and then moving to the next column (for example, after finishing column **2**, moving it to column **1**). However, other combinations of vertical and horizontal offsetting can be used. The pixels **1230** or the pad clusters **1240** can be at an angle be either vertically or horizontally. In this case, the rows or columns of the micro devices will be tilted as well. In addition, the micro devices **1252** and **1254** may be at an angle without the pads or pixels being at angles. In this case, the offsetting direction will be toward the angle of the column or the row.

(88) The donor substrate **1250** may be comprised of columns and rows of micro devices **1252** and **1254**, and includes void areas defined by a number of missing columns or rows equal to the number of pads, e.g. **1214**, adjacent to the receiver pad, e.g. **1204**, on each side thereof. The number of columns in each array is dependent upon the spacing between the pads **1204** and **1214** in adjacent pixels **1230**. For example, the donor substrate **1250** for the pad **1204**, which includes one adjacent pad **1214** (pad **1224** is the same lateral distance) to the right and none to the left, may include a void area with one missing column of micro devices, if the pitch of the micro devices **1252** and **1254** is the same as the pads **1204** and **1214**. Alternatively, if the pitches are different, then the void area may be at least the distance from the pad, e.g. pad **1204**, being mounted to the far edge of the farthest pad, e.g. pad **1214**.

(89) FIG. **12B** shows a similar structure for the donor substrate **1260**, as in FIG. **12A**, for the middle pad **1224** on the receiver substrate **1200**. However, the interfering area with no micro device extends horizontally across the donor substrate **1260** to avoid interfering with pads **1204** and **1214**. As above, each donor substrate **1260** includes a plurality of arrays or blocks of micro devices **1253** and **1255**. Within each array of micro devices, the spacing or pitch of the micro devices may be the same, e.g. a first predetermined pitch, ideally the same pitch or spacing as the pads **1204** and **1214**,

but may have a larger or smaller pitch. Each array of micro devices **1253** is separated by a void, i.e. an interfering area, of N times the pitch or spacing between the pads from one side of the closest pad to the far side of the farthest pad, e.g. **1204** or **1214**, where N is the number of adjacent pads, e.g. **1204** and **1214**. Typically, the length of the void areas is the full length or width of the donor substrate **1260**. The donor substrate **1260** for the middle pad **1224** is moved laterally, i.e. perpendicular to the donor substrate **1250** for the pad **1204**, for subsequent receiver substrates **1200**.

(90) FIG. 12C shows the donor substrate **1270** for the middle pad **1214**. Here, the interfering area is diagonal, e.g. at an acute angle, relative to the sides of the donor substrate **1270**, and offsetting of the donor substrate **1270** (or receiver substrate **1200**) for subsequent receiver substrates **1200** (or donor substrates **1270**) is done diagonally or vertically and horizontally. The donor substrate **1270** may be comprised of columns and rows of micro devices **1257** and **1259**, and include void areas defined by a number of missing columns or rows equal to the number of pads, e.g. **1204** and **1224**, adjacent to the receiver pad, e.g. **1214**, on each side thereof. The number of columns in each array is dependent upon the spacing between the pads **1214** and **1204** in adjacent pixels **1230**. For example, the donor substrate **1270** for the pad **1214**, which includes one adjacent pad **1204** to the left, and one pad **1224** below (both are the same lateral distance diagonally) and none to the right, may include a void area with one missing diagonal column of micro devices, if the pitch of the micro devices **1257** and **1259** is the same as the pads **1214** and **1224**. Alternatively, if the pitches are different, then the void area may be at least the distance from the pad, e.g. pad **1214**, mounted to the far edge of the farthest pad, e.g. pad **1224**.

(91) FIG. 12D illustrates a donor substrate **1280**, which has a similar structure to the donor substrate **1260** for transferring to the pad **1214**, but with a slightly different arrangement for the micro devices **1257** and **1259** to maximize the transfer. The voids in the donor substrate **1270** are parallel (or perpendicular) to the sides of the donor substrate **1270**, but the donor substrate **1270** is rotated, e.g. 45°, relative to the receiver substrate **1200**.

(92) FIG. 13A shows a non-interfering area **1304-1**, and an interfering area **1304-2** for the pad **1304** at the edge of the cluster **1340** for a pixel width **1350** corresponding to a void area on a donor substrate. As seen, the non-interfering areas **1304-1** for the pads at the edge are larger than previous cases. The same pattern may be used for the pad **1314**. For the pad **1324** in the middle, the non-interfering area **1324-2** and interfering area **1324-1** can be vertical stripe pattern as demonstrated in FIG. 13B. Here, the width of the non-interfering area **1324-2** is the same as the distance between the middle pad **1314** and the other pads **1304**, **1324** in the other pixel. If the distance between the middle pad and the other pads is the same, the ratio of interfering area **1324-12** to non-interfering area **1324-21** may be the same. Similar to FIG. 3B, here the interfering and non-interfering areas **1324-12** and **1324-21** may have different shapes depending on the offsetting direction. Also, similar to FIG. 4, one of the pads may be taller and so in this case the non-interfering area for the middle micro device may be the entire donor substrate.

(93) FIGS. 14A and 14B illustrate an embodiment in which pads **1404**, **1414** and **1424** in a receiver substrate **1400** have the same pitch as micro devices in donor substrates **1450** and **1460**. The position of a pad cluster **1440** may be different with reference to the pixels **1430**. The size of pads **1404**, **1414** and **1424** may be smaller or similar or larger than the micro devices **1452**, **1454**, **1455** and **1457**. The shape of the micro devices **1452**, **1454**, **1455** and **1457** and the pads **1404**, **1414** and **1424** may be any suitable size or shape. In this case, the micro devices **1452**, **1454**, **1455** and **1457** may be removed (or nonpopulated) from the interfering area on the donor substrates **1450** and **1460**.

(94) FIG. 14A illustrates an embodiment of a donor substrate **1450** for the edge pad **1404**. Some of the micro devices **1454** may already have been transferred to the receiver substrate **1400**, and the donor substrate **1450** (or receiver substrate **1400**) is offset vertically and/or horizontally with reference to the next receiver substrate **1400** (or the donor substrate **1450**) so that another micro

device **1452** is aligned with one of the bare pads **1404** (pads to which no micro device has been yet transferred). In the illustrated embodiment, a plurality of arrays of micro devices **1452** and **1454** are provided on the donor substrate **1450**. Within each array of micro devices, the spacing or pitch of the micro devices laterally and vertically may be the same, e.g. a first predetermined pitch, ideally the same pitch or spacing as the pads **1404** and **1414**. Each array of micro devices is separated by a void, i.e. an interfering area, of N times the pitch of the pads or a spacing between the pads or the lateral or vertical distance from one side of the closest pad to the far side of the farthest pad, e.g. **1414** and **1424**, where N is the number of laterally or vertically adjacent pads, e.g. two in this case **1414** and **1424**. Typically, the length of the void areas is the full length of the donor substrate **1450**. (95) In this case, the empty spaces created by transferring the micro device **1454** will be a new empty area which will be on top of other pads **1414** and **1424**. As such there will be no interference caused by the micro devices for the unwanted pads **1414** and **1424**. One can finish all the micro devices in one column by offsetting vertically first and then moving to the next column (for example, after finishing column 2, moving to column 1). However other combinations of vertical and horizontal offsetting may be used. The pixels **1430** or the pad clusters **1440** may be at an angle to each other, either vertically or horizontally. In this case, the rows or columns of the micro device may be tilted as well. In addition, the micro devices may be at an angle without the pads or pixels being at angles. In this case, the offsetting direction will be toward the angle of the column or the row.

(96) The donor substrate **1450** may be comprised of columns and rows of micro devices **1452** and **1454**, and includes void areas defined by a number of missing columns or rows equal to the number of pads, e.g. **1414** and **1424**, adjacent to the receiver pad, e.g. **1404**, on each side thereof. The number of columns in each array is dependent upon the spacing between the pads **1424** and **1404** in adjacent pixels **1430**. For example, the donor substrate **1450** for the receiver pad **1404**, which includes two laterally spaced adjacent pads **1414** and **1424** to the right (pad **1414** is equally spaced from pads **1404** and **1424**), and none to the left, may include a void area with two missing columns of micro devices, if the pitch of the micro devices **1452** and **1454** is the same as the pads **1414** and **1424**. Alternatively, if the pitches are different, then the void area may be at least the distance from the pad, e.g. pad **1404**, being mounted to the far edge of the farthest pad, e.g. pad **1424**.

(97) FIG. 14B illustrates a donor substrate **1460**, similar to the structure in FIG. 14A, but for the middle pad **1414**. However, the interfering area with no micro devices **1455** and **1457** is a horizontal void, e.g. row, with a single column of micro devices missing, e.g. pads **1404** and **1424** vertically spaced by one pitch distance from the receiver pad **1414**.

(98) FIG. 15A illustrates one example of a multi-type micro-device cartridge **1800**. The cartridge **1800** includes three different types, e.g. colors, of micro devices **1801**, **1802**, **1803**, e.g. blue, green and red. However, any number and variety of different types of devices may be possible. The distances between the micro devices **1801**, **1802** and **1803**, i.e. x_1 , x_2 , x_3 , respectively, are related to the pitch of the landing areas in the receiver substrate, e.g. receiver substrate **700** from FIGS. 7A and 7B. After an array or first set of micro devices **1805**, which may be related to the pixel pitch in the receiver substrate, there may be a different pitch x_4 , y_2 , i.e. a void area or interfering area, between adjacent sets **1805** and **1815** of micro devices **1801**, **1802** and **1803**. The separation or pitch is to compensate for a mismatch between the pixel pitch and the micro device pitch (landing area pitch), and to ensure that micro devices on the donor or cartridge substrate **1800** do not interfere with pads, e.g. the horizontally and vertically adjacent cluster **740**, or existing micro devices on the receiver substrate, e.g. receiver substrate **700**. For example, the void area may be an area defined by at least the distance from one side of an outer pad of the pixel to a far side of the outer pad at the opposite side of the pixel or at least the distance of N times the pitch of the pads, where N is the number of adjacent pads in the pixel. The length may be the entire length of the cartridge **1800**. In this case, if pick and place is used to develop the cartridge **1800**, the force

elements may be in the form of columns that corresponds to the column of each micro device type or it can be a separate element for each micro device.

(99) With reference to FIG. 15B, during assembly, a first step **1821** includes preparing micro devices on the original donor substrates, e.g. donor substrates **750** or **1450**. Then, in step **1822**, the micro devices are prepared for separation from the donor substrates **750** or **1450**. In step **1823** the micro devices from one or more donor substrates, e.g. **750** and **1450**, are transferred onto the cartridge **1800**, and arranged according to the pixel arrangement on the receiver substrate, e.g. **700** or **1400**. The next step **1824**, which is optional, involves identifying micro devices with defects, and either correcting them in place, or removing them and replacing them with an operating micro device in step **1825**. The identification of defects may be conducted in the cartridge **1800** before transfer or on the receiver substrate **700** or **1400** after transfer, or both. Subsequently, or prior, to the identification and correction step **1824**, a plurality of groups of micro devices **1801**, **1802** and **1803**, which may form a pixel, from each array or set of micro devices **1805**, **1810** and **1815**, may be mounted on the receiver substrate, e.g. receiver substrate **700**, simultaneously from the cartridge **1800**, in step **1826**.

(100) With reference to FIG. 15C, the transfer step **1826** may be broken down into a logical loop, in which the first step **18261** comprises loading or selecting a first cartridge **1800**. The next step **18262** comprises selecting a set of micro devices on the cartridge **1800** for transfer, preferably ones already tested for defects, and that comprise a number of defects below a desired threshold value, e.g. less than 10%. Step **18263** comprises aligning the selected micro devices on the cartridge **1800**, e.g. by moving or offsetting the cartridge **1800** or the receiver substrate, e.g. receiver substrate **700**, or both, relative to the other into alignment with a subsequent plurality of clusters of pads, e.g. cluster **740**. The next step **18264** includes transferring the aligned micro devices on the cartridge **1800** to the pads on the receiver substrate, e.g. **700** or **1400**. Step **18264** may be broken down into substeps including **18264a**, in which the selected micro devices from the cartridge **1800** are connected to the receiver substrate, e.g. **700** or **1400**. Substep **18264b** comprises turning on the micro devices to test their connection to the receiver substrate, e.g. **700** or **1400**. The test may be conducted by biasing the micro devices through the cartridge **1800** and/or the receiver substrate, e.g. **700** or **1400**. If some of the micro devices are found to be defective, step **18264c** includes adjusting one or more of the bonding parameters of the micro devices to correct the cause of the defect. Step **18265** determines whether the receiver substrate, e.g. **700** or **1400**, is fully populated. If yes, in step **18266**, the process proceeds to a new receiver substrate and the mounting process is repeated. If no, step **18267** determines if the cartridge **1800** includes enough micro devices to continue with further transfers. If yes, the process returns to step **18262** for the selection of the next set of micro devices to be transferred. If no, the process returns to step **18261** for selection of another cartridge **1800**.

(101) FIG. 16 illustrates another example of a multi-type micro-device cartridge **1900**. The cartridge **1900** includes three different types, e.g. colors, of micro devices **1901**, **1902**, **1903**. The other area **1904** may be spare micro devices or a void area (interfering area). However, any number and variety of different types of device may be possible. The distances between micro devices x_1 , x_2 , x_3 are related to the pitch of the landing areas in the receiver substrate, e.g. receiver substrate **1200**, in FIGS. 12A-12D. After an array or a first set of micro devices, which may be related to the pixel pitch in the receiver substrate, there may be a different lateral and vertical pitch x_4 , y_2 , i.e. a void area or interfering area, between laterally and vertically adjacent sets of pixels. This pitch compensates for any mismatch between the pixel pitch and the micro device pitch (landing area pitch), and ensures that micro devices on the donor or cartridge substrate **1900** do not interfere with pads, e.g. the horizontally and vertically adjacent cluster **1240**, or existing micro devices on the receiver substrate, e.g. receiver substrate **1200**. For example, the void area may be an area defined by at least the distance from one side of an outer pad of the pixel to a far side of the outer pad at the opposite side of the pixel or at least the distance of N times the pitch of the pads, where N is the

number of adjacent (horizontally or vertically) pads in the pixel. The length may be the entire length of the cartridge **1900**. During assembly, a plurality of groups of micro devices **1901**, **1902** and **1903**, which may form a pixel, from each array or set of micro devices, may be mounted on the receiver substrate, e.g. receiver substrate **1200**, simultaneously. Then the cartridge **1900** or the receiver substrate, e.g. receiver substrate **1200**, or both are moved relative to the other into alignment with a subsequent plurality of clusters of pads, e.g. cluster **1240**, and the mounting process is repeated, until the cartridge **1900** is empty or the receiver substrate is filled. Another cartridge **1900** or receiver substrate is introduced.

(102) FIG. **17** illustrates one example of micro devices, e.g. **1801** or **1902**, prepared on a donor substrate **1850** before transferring to multi-type micro-device cartridge, e.g. **1800** or **1900**. Here, one can use supporting layers **1860**, **1870** for individual device or for a group of devices. Here, the micro device pitch $x1$ can match the pitch in the cartridge **1800** or **1900** or it can be multiple of cartridge pitch. As above the vertical and horizontal array pitch $y2$ and $x4$ provide voids or interference areas to prevent interaction of the micro devices **1801** with pads on the receiver substrate or undesired areas on the cartridge **1800** or **1900**.

(103) In all the structures above, it is possible to move the micro devices from the first cartridge to a second one prior to using them in populating a substrate. Extra processing step can be done after transfer. or some of the processing steps can be divided between first and secondary cartridge structure.

(104) FIG. **18** illustrates an example of a block of microdevices **1482** on a donor substrate **1480**, which may be any one of the aforementioned donor substrates described herein. As a result of manufacturing and material flaws, the microdevices may have a gradual decrease or increase in output power, i.e. non-uniformity, across the donor substrate, as illustrated with darker to lighter coloring. Since the micro devices may be transferred together in the block **1482** or one or more at a time in sequence into the receiver substrate, the adjacent devices in the receiver substrate gradually degrade in uniformity. However, a worse problem may occur where a series of the blocks **1482** ends and the next series of blocks starts, e.g. along an intersection line **1484**, which may result in an abrupt change as demonstrated in FIG. **19**. The abrupt change may result in visual artifact for optoelectronic devices, such as displays.

(105) In order to solve the problem of non-uniformity, one embodiment, illustrated in FIG. **20**, includes skewing or staggering the individual blocks **1482** with the ones below and above them in the display, so that the edge of the blocks are not sharp lines, i.e. eliminating the intersection **1484**, and whereby the blocks of devices **1482** form a skewed pattern on the display. Therefore, the average impact of the sharp transition is reduced significantly. The skew may be random and may have different profiles.

(106) FIG. **21** illustrates another embodiment, in which the microdevices in adjacent blocks are flipped so that the devices with similar performance are adjacent one another, e.g. the performance in a first block decrease from a first outer side to a first inner side, while the performance of a second adjacent block increases from a second inner side, adjacent to the first inner side to a second outer side, which may keep the changes very smooth and eliminate the abrupt intersection **1484**.

(107) FIG. **22** illustrates an exemplary combination of flipping the devices, alternating the high and low performing devices at the inner sides, and skewing the edges to improve the average uniformity furthermore. In the illustrated example, the device performance alternates between high and low in both directions, i.e. in adjacent horizontal blocks and in adjacent vertical blocks.

(108) In one case, the performance of micro devices at the edges of the blocks are matched for adjacent transferred blocks (array) prior to the transfer to the receiver substrate.

(109) FIG. **23** illustrates using two or more blocks **1580** and **1582**, to populate a block in the cartridge or receiver substrate **1590**. Here also the method of skewing or flipping can be used for further improving the average uniformity as demonstrated in FIG. **24**. Also, a random or predefined pattern may be used to populate the cartridge or receiver substrate **1590** with micro devices from

more than one block.

(110) FIG. 25A illustrates samples with more than one blocks **1680**, **1682** and **1684**, which may be from the same donor substrate or different donor substrates. FIG. 25B illustrates an example of populating a cartridge **1690** from different blocks to eliminate the non-uniformity found in any one block.

(111) FIGS. 26 and 27 illustrate structures with multiple cartridges **1790**. The position of the cartridges **1790** are chosen in a way to eliminate overlapping the same area in the receiver substrate with cartridges with the same micro-devices during different transfer cycles. In one case, the cartridge may be independent of the other cartridges, which means separate arms or controller is handling each cartridge independently. In another case, the alignment may be done independently, but the other actions can be synchronized. In this case, the substrate may move to facilitate the transfer after the alignment. In another case, the cartridges may move together to facilitate the transfer after the alignment. In another case, both may move to facilitate the transfer. In another case, the cartridges may be assembled in advanced. In this case, a frame or substrate can hold the assembled cartridges. The distance X3, Y3 between cartridges **1790** can be a multiple of the width X1, X2 or length Y1, Y2 of the cartridge **1790**. It can be a function of moving steps to different direction. For example, $X3 = KX1 + HX2$, where K is the movement step to left (directly or indirectly) and H is the movement steps to the right (directly or indirectly) for populating a substrate. The same can be used for distance between cartridges Y3 and the length of Y1 and Y2. As shown in FIG. 26, the cartridges may be aligned in one or two direction. In another case, shown in FIG. 27, the cartridges may not be aligned in at least one direction. Each cartridge **1790** may have independent control for applying pressure and temperature toward the substrate. Other arrangements are also possible depending on the direction of movement between substrate and cartridges.

(112) In another case, the cartridges **1790** may have different devices and therefore populating different areas in the receiver substrate with different devices. In this case, the relative position of the cartridges **1790** and the receiver substrate changes after each transfer cycle to populate a different area with all the required micro devices from the different cartridges.

(113) In another case, several arrays of cartridges **1790** are prepared. Here, after devices are transferred to the receiver substrate from a first array of cartridges, the receiver substrate is moved to the next array of micro devices to fill the remaining areas in the receiver substrate or receive different devices.

(114) In another case, the cartridges **1790** may be on a curve surface and therefore circular movement provides contact for transferring the micro devices into the substrate.

(115) According to one embodiment, a method of populating a receiver substrate may be provided. The method may comprising the steps of: preparing a plurality of microdevices on one or more donor substrates, transferring the plurality of microdevices from the one or more donor substrates to a first cartridge substrate, the plurality of microdevices are arranged in arrays, separated by an interfering area in between, on the first cartridge substrate, selecting at least one set of microdevices in the first cartridge substrate associated with a set of contact pads in the receiver substrate, identifying a number of defective microdevices in the at least one set of microdevices, correcting the defective microdevices if the number of defective microdevices in the set is more than a set threshold value; and aligning and transferring the selected set of microdevices on the first cartridge substrate to corresponding contact pads on the receiver substrate.

(116) According to another embodiment, wherein after transferring the selected set of microdevices to the receiver substrate, if the receiver substrate is not fully populated, the method further comprising the steps of: determining whether the first cartridge substrate 1) has enough microdevices to continue transferring microdevices to the receiver substrate or 2) has not enough microdevices to continue transferring microdevices to the receiver substrate, in response to determining that the first cartridge substrate has enough microdevices, selecting another set of

microdevices in the first cartridge substrate for transferring to the receiver substrate; else in response to determining that the first cartridge substrate has not enough microdevices, selecting a second cartridge substrate.

(117) According to one embodiment, the defective microdevices are removed if the number of the defective microdevices is more than the set threshold value, the defective microdevices are repaired if the number of the defective microdevices is less than the set threshold value and the defective microdevices are replaced with spare microdevices on each cartridge substrate if the number of the defective microdevices is less than the set threshold value.

(118) According to some embodiments, the step of selecting one or more sets of microdevices on the first cartridge substrate and the second cartridge substrate comprising: selecting one or more sets of microdevices, wherein number a defected microservices in one or more sets of microdevices is less than a threshold value; and transferring the selected set of microdevices to populate the system substrate.

(119) According to another embodiment, the first cartridge substrate and the second cartridge substrate includes different types of the plurality of microdevices. The different types of microdevices comprises one of: red color microdevices, blue color microdevices or green color microdevices. The plurality of microdevices of different types are arranged in arrays on each cartridge according to a type of microdevice.

(120) According to yet another embodiment, the interfering area comprises one of: spare microdevices or void areas.

(121) According to some embodiments, the method may further comprising biasing the microdevices through the receiver substrate to test a connection between the transferred microdevices and the receiver substrate and adjusting one or more of the bonding parameters of the microdevices to correct the cause of the defective microdevices, wherein a distance between the plurality of microdevices on each cartridge substrate depends on a pitch of corresponding contact pads on the receiver substrate.

(122) According to another embodiment, rows of the micro devices from each cartridge substrate are placed in a skewed arrangement on the receiver substrate to reduce the effect of abrupt transitions caused by non-uniformity of microdevices across each cartridge substrate.

(123) According to one embodiment, laterally adjacent rows of the micro devices from different cartridge substrates are placed in a flipped arrangement on the receiver substrate with the high or low side of a row from one of the donor substrates adjacent to a high side or low side, respectively, of an adjacent row of another donor substrate to reduce abrupt transitions caused by non-uniformity of micro devices across each cartridge substrate.

(124) According to further embodiments, vertically adjacent rows of micro devices from different cartridge substrates are placed in an alternating arrangement with high sides vertically adjacent to low sides to reduce abrupt transitions caused by non-uniformity of micro devices across each cartridge substrate.

(125) According to another embodiment, a method of populating a receiver substrate, the method comprising the steps of: preparing a plurality of microdevices on one or more donor substrates, transferring the plurality of microdevices from the one or more donor substrates to a cartridge substrate, the plurality of microdevices are arranged in arrays, selecting one or more sets of microdevices in the cartridge substrate for transferring to the receiver substrate, wherein a number of defective microdevices in the selected one or more sets of microdevices is less than a set threshold value; and aligning and transferring the selected set of microdevices on the cartridge substrate to corresponding contact pads on the receiver substrate.

(126) According to one embodiment, the number defective microdevices are identified and corrected before or after transferring to the receiver substrate, the defective microdevices are corrected by one of: repairing, replacing or removing the defective microdevices in the cartridge substrate the defective microdevices are replaced with the spare microdevices on the cartridge

substrate.

(127) According to further embodiment, the cartridge substrate includes different types of the plurality of microdevices, the different types of microdevices comprises red color microdevices, blue color microdevices or green color microdevices.

(128) The foregoing description of one or more embodiments of the invention has been presented for the purposes of illustration and description. It is not intended to be exhaustive or to limit the invention to the precise form disclosed. Many modifications and variations are possible in light of the above teaching. It is intended that the scope of the invention be limited not by this detailed description, but rather by the claims appended hereto.

Claims

1. A method of populating a receiver substrate, the method comprising the steps of: preparing a plurality of microdevices on one or more donor substrates; transferring the plurality of microdevices from the one or more donor substrates to a cartridge substrate, the plurality of microdevices being arranged in arrays, separated by an interfering area in between, on the cartridge substrate; selecting one or more transferable sets of microdevices in the cartridge substrate; identifying a number of defective microdevices in each transferable set of microdevices; correcting the defective microdevices if a sum of the number of the identified defective microdevices is more than a threshold value; and aligning and transferring the selected one or more transferable sets of microdevices on the cartridge substrate to corresponding contact pads on the receiver substrate.
 2. The method of claim 1, wherein the number of defective microdevices are identified and corrected before or after transferring to the receiver substrate.
 3. The method of claim 2, wherein the defective microdevices are corrected by one of: repairing, replacing, or removing the defective microdevices in the cartridge substrate.
 4. The method of claim 3, wherein the defective microdevices are replaced with spare microdevices on the cartridge substrate.
 5. The method of claim 1, wherein the cartridge substrate includes different types of the plurality of microdevices, the different types of the plurality of microdevices being red color microdevices, blue color microdevices, or green color microdevices.
-