

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250287600

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

Lee; Taegon et al.

SEMICONDUCTOR DEVICES HAVING CAPACITOR STRUCTURES

Abstract

An example semiconductor device includes a first semiconductor structure and a second semiconductor structure. The first semiconductor structure includes a substrate, an active region within the substrate, circuit elements on the substrate, an element isolation region defining the active region, impurity regions disposed within the active region on both sides of the circuit elements, an interconnection structure electrically connected with the circuit elements, and a capacitor structure spaced apart from the interconnection structure in a first direction. The second semiconductor structure includes a plate layer disposed on the first semiconductor structure, gate electrodes sequentially stacked and spaced apart from each other in a direction, perpendicular to an upper surface of the plate layer, on the plate layer, and channel structures extending through the gate electrodes in the perpendicular direction.

Inventors: Lee; Taegon (Suwon-si, KR), Lee; Kangin (Suwon-si, KR), Ha; Jieun (Suwon-si, KR), Kang; Minkyu (Suwon-si, KR)

Applicant: SAMSUNG ELECTRONICS CO., LTD. (Suwon-si, KR)

Family ID: 1000008130320

Appl. No.: 18/885142

Filed: September 13, 2024

Foreign Application Priority Data

KR 10-2024-0033310

Mar. 08, 2024

Publication Classification

Int. Cl.: H10B43/40 (20230101); G11C16/30 (20060101); H10B41/27 (20230101); H10B41/41 (20230101); H10B43/27 (20230101)

U.S. Cl.:

CPC **H10B43/40** (20230201); **G11C16/30** (20130101); **H10B41/27** (20230201); **H10B41/41** (20230201); **H10B43/27** (20230201);

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION

[0001] This application claims benefit of priority to Korean Patent Application No. 10-2024-0033310 filed on Mar. 8, 2024, in the Korean Intellectual Property Office, the disclosure of which is incorporated herein by reference in its entirety.

BACKGROUND

[0002] In a data storage system requiring data storage, a semiconductor device capable of storing high-capacitance data is required. Accordingly, a manner to increase the data storage capacitance of semiconductor devices has been researched. Additionally, highly integrated semiconductor devices are in demand. For example, as one of the methods to increase the degree of integration of a semiconductor device, a semiconductor device, in which memory cells and a peripheral circuit region are arranged vertically, has been proposed.

SUMMARY

[0003] The present disclosure relates to a semiconductor device including a capacitor structure with improved integration and electrical characteristics.

[0004] The object of the present application is not limited to the foregoing content and may be variously extended without departing from the spirit and domain of the present disclosure.

[0005] In some implementations, a semiconductor device includes a first semiconductor structure including a substrate, an active region within the substrate, circuit elements on the substrate, an element isolation region defining the active region, impurity regions disposed within the active region on both sides of the circuit elements, an interconnection structure electrically connected to the circuit elements, and a capacitor structure spaced apart from the interconnection structure in a first direction, and a second semiconductor structure including a plate layer disposed on the first semiconductor structure, gate electrodes sequentially stacked and spaced apart from each other in a direction, perpendicular to an upper surface of the plate layer, on the plate layer, and channel structures penetrating through the gate electrodes and extending in the perpendicular direction, wherein the capacitor structure may include: a first electrode structure including a first strap portion disposed on the substrate and extending in the first direction, and first electrodes extending from the first strap portion in a second direction, intersecting the first direction; and a second electrode structure including a second strap portion extending on the substrate in the first direction and spaced apart from the first strap portion in the second direction, and second electrodes extending from the second strap portion in the second direction and arranged alternately with the first electrodes, and the first electrodes may have a plate shape extending from an upper surface of the first strap portion in a vertical direction, intersecting the first direction and the second direction, and the second electrodes may have a plate shape extending from an upper surface of the second strap portion in the vertical direction.

[0006] In some implementations, a semiconductor device includes a substrate including an active region; circuit elements on the active region; an element isolation region defining the active region; impurity regions disposed inside the active region on both sides of the circuit elements; a capacitor structure spaced apart from the circuit elements; and a first finger trench spaced apart from the circuit elements and extending inside the substrate in a first direction, and a second finger trench extending in the first direction and arranged alternately with the first finger trench, wherein the

capacitor structure may include: first lower electrodes disposed on the first finger trench; and second lower electrodes disposed on the second finger trench and arranged alternately with the first lower electrodes, wherein the first lower electrodes and the second lower electrodes may have a plate shape extending in the first direction and a vertical direction, intersecting the first direction, and an upper surface of the first finger trench and an upper surface of the second finger trench may be disposed on the same level as an upper surface of the element isolation region.

[0007] In some implementations, a semiconductor device includes a substrate including an active region; circuit elements including a gate structure on the active region; an element isolation region defining the active region; impurity regions disposed inside the active region on both sides of the circuit elements; and a capacitor structure spaced apart from the circuit elements, wherein the capacitor structure may include: a first electrode structure including a first strap portion disposed on the substrate and extending in a first direction, and first electrodes extending from the first strap portion in a second direction, intersecting the first direction; and a second strap portion including a second strap portion extending on the substrate in the first direction and spaced apart from the first strap portion in the second direction, and second electrodes extending from the second strap portion in the second direction and arranged alternately with the first electrodes, wherein an upper surface of the first strap portion and an upper surface of the second strap portion may be disposed on at the same level as an upper surface of the gate structure.

[0008] In some implementations, a semiconductor device includes a capacitor structure, and the capacitor structure may be disposed on a substrate and includes lower electrodes having a relatively high vertical height to secure electrostatic capacity, thereby providing a semiconductor device with improved electrical characteristics.

[0009] In some implementations, a semiconductor device includes a capacitor structure including first and second strap portions provided in the same process as a circuit element, first lower electrodes connected through the first strap portion, and second lower electrodes arranged alternately with the first lower electrodes and connected through the second strap portion. Accordingly, the semiconductor device may form a routing interconnection applied to the capacitor structure through the first and second strap portions extending between a peripheral interconnection and the lower electrodes, a semiconductor device having improved integration may be provided.

[0010] Advantages and effects of the present application are not limited to the foregoing content and may be variously extended without departing from the spirit and domain of the present disclosure.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0011] The above and other aspects, features, and advantages of the present disclosure will be more clearly understood from the following detailed description, taken in conjunction with the accompanying drawings.

[0012] FIG. 1A is a schematic block diagram of an example of a semiconductor device.

[0013] FIG. 1B is a circuit diagram illustrating an example of a charge pump circuit included in a voltage generator of a semiconductor device.

[0014] FIG. 1C is a schematic perspective view of an example of a semiconductor device.

[0015] FIG. 1D is a cross-sectional view of an example of a semiconductor device.

[0016] FIG. 1E is a cross-sectional view of an example of a semiconductor device.

[0017] FIG. 2A is a schematic perspective view illustrating an example of a capacitor structure of a semiconductor device.

[0018] FIG. 2B is a perspective view illustrating an example of a semiconductor device including the capacitor structure of FIG. 2A.

[0019] FIG. 2C is a perspective view illustrating another example of a semiconductor device including the capacitor structure of FIG. 2A.

[0020] FIG. 3A is a schematic perspective view illustrating another example of a capacitor structure of a semiconductor device.

[0021] FIG. 3B is a perspective view illustrating an example of a semiconductor device including the capacitor structure of FIG. 3A.

[0022] FIG. 4A is a schematic perspective view illustrating another example of a capacitor structure of a semiconductor device.

[0023] FIG. 4B is a perspective view illustrating an example of a semiconductor device including the capacitor structure of FIG. 4A.

[0024] FIG. 5A is a schematic perspective view illustrating another example of a capacitor structure of a semiconductor device.

[0025] FIG. 5B is a plan view illustrating an example of a semiconductor device including the capacitor structure of FIG. 5A.

[0026] FIG. 5C is a cross-sectional view illustrating an example taken along line I-I' of the semiconductor device of FIG. 5B.

[0027] FIGS. 6A, 6B, and 6C are views illustrating an example of a method of manufacturing the semiconductor device of FIG. 5B.

[0028] FIG. 7 is a view schematically illustrating an example of a data storage system including a semiconductor device.

DETAILED DESCRIPTION

[0029] Hereinafter, example implementations of the present disclosure will be described with reference to the accompanying drawings. The same reference numerals are used for the same components in the drawings, and duplicate descriptions for the same components are omitted.

[0030] FIG. 1A is a schematic block diagram of an example of a semiconductor device. FIG. 1B is a circuit diagram illustrating an example of a charge pump circuit included in a voltage generator of a semiconductor device. FIG. 1C is a schematic perspective view of an example of a semiconductor device.

[0031] Referring to FIG. 1A, a semiconductor device **10** may include a memory cell array **20** and a peripheral circuit **30**. The semiconductor device **10** may be a memory device, for example, a non-volatile memory such as a flash memory, or a volatile memory such as a dynamic random access memory (DRAM) or a static random access memory (SRAM).

[0032] The memory cell array **20** may include a plurality of memory cells. The plurality of memory cells may be connected to a row decoder **33** through a plurality of word lines WL, and may be connected to a read/write circuit **35** through bit lines BL. In an example, a plurality of memory cells arranged along the same row may be connected to the same word line WL, and a plurality of memory cells arranged along the same column may be connected to the same bit line BL. In some implementations, the memory cell array **20** may include a plurality of memory blocks, and each of the memory blocks may include a plurality of memory cells.

[0033] The peripheral circuit **30** may receive an address ADDR, a command CMD, and a control signal CTRL from the outside of the semiconductor device **10**, and may transmit and receive data DATA with an external device of the semiconductor device **10**. The peripheral circuit **30** may include a row decoder **33**, a read/write circuit **35**, a control logic **37**, and a voltage generator **38** generating various voltages required for an operation. According to some implementations, the peripheral circuit **30** may further include various sub-circuits, such as an input/output circuit and an error correction circuit for correcting errors in data DATA read from the memory cell array **20**.

[0034] The control logic **37** may be connected to the row decoder **33**, the voltage generator **38**, and the input/output circuit. The control logic **37** may control an overall operation of the semiconductor device **10**. The control logic **37** may generate various internal control signals used in the semiconductor device **10** in response to the control signal CTRL. For example, the control logic **37**

may adjust a voltage level provided to word lines WL and bit lines BL when performing a memory operation such as a program operation or an erase operation.

[0035] The row decoder **33** may select some of the plurality of memory cells in response to the address ADDR, and may select at least one word line WL. The row decoder **33** may transmit a voltage for performing a memory operation to the selected word line WL.

[0036] The read/write circuit **35** may be connected to the memory cell array **20** through the bit lines BL. The read/write circuit **35** may include a writer driver or a sense amplifier. Specifically, during a program operation, the read/write circuit **35** may operate as a write driver and apply a voltage according to the data DATA to be stored in the memory cell array **20** to the bit lines BL.

Meanwhile, during a read operation, the read/write circuit **35** operates as a sense amplifier and may detect data DATA stored in the memory cell array **20**.

[0037] The voltage generator **38** may include a controller **52**, an oscillator **54**, and a charge pump **56**.

[0038] The charge pump **56** may include a plurality of charge pumps, and each of the plurality of charge pumps may include at least one switch element and at least one pumping capacitor. The charge pump **56** may provide current through the row decoder **33** to apply an operating voltage to the word line WL of the memory cell array.

[0039] The controller **52** may control an operation of the oscillator **54**. For example, the controller **52** may determine one select charge pump among the plurality of charge pumps, based on at least one of PVT (Process, Voltage, Temperature) information of the semiconductor device **10** and a target level of a power supply voltage to be supplied. The controller **52** may deactivate the remaining charge pumps except the selected charge pump.

[0040] The oscillator **54** may output a clock signal CLK. The oscillator **54** may operate in response to a control signal VGC from the controller **52**. For example, the oscillator **54** may output the clock signal CLK to at least some of the plurality of charge pumps, in response to the control signal VGC transmitted by the controller **52**.

[0041] FIG. **1B** is a circuit diagram illustrating an example of a charge pump circuit included in a voltage generator of a semiconductor device.

[0042] Referring to FIG. **1B**, a charge pump circuit **56a** may include a plurality of diodes DI, a plurality of pumping capacitors CAP1, and an output capacitor CAP2. The plurality of diodes DI may be connected to each other in series, and the plurality of pumping capacitors CAP1 may be connected to nodes between the plurality of diodes DI. A first diode may receive a power supply voltage VCC having a predetermined level, and a last diode may transmit an output current IOUT to an output node.

[0043] Each of the plurality of pumping capacitors CAP1 may be charged or discharged by the clock signal CLK and a complementary clock signal CLKB phase-converted to have an opposite phase by the clock signal CLK and an inverter INV. For example, odd-numbered pumping capacitors CAP1 may be charged or discharged by the clock signal CLK, and even-numbered pumping capacitors CAP1 may be charged or discharged by the complementary clock signal CLKB.

[0044] FIG. **1C** is a schematic perspective view of an example of a semiconductor device.

[0045] Referring to FIG. **1C**, the semiconductor device **10** may include a peripheral circuit structure PERI and a memory cell structure CELL. The memory cell structure CELL may be disposed on the peripheral circuit structure PERI. The memory cell structure CELL may be disposed on the peripheral circuit structure PERI. The memory cell structure CELL may be a region in which the memory cell array **20** of FIG. **1A** is disposed, and the peripheral circuit structure PERI may be a region in which the peripheral circuit **30** of FIG. **1A** is disposed. In some implementations, on the contrary, the memory cell structure CELL may be disposed below the peripheral circuit structure PERI.

[0046] The memory cell structure CELL may include a first region R1 and a second region R2.

[0047] The first region R1 of the memory cell structure CELL may be a region in which the memory cell array 20 is disposed. The second region R2 of the memory cell structure CELL may correspond to a region for electrically connecting memory cells of the memory cell array 20 to the peripheral circuit 30. The second region R2 may be disposed in at least one end of the first region R1 in at least one direction, for example, the first direction (X-direction).

[0048] A plurality of pumping capacitors CAP1 included in the charge pump circuits 56 and 56a of FIGS. 1A and 1B may be disposed in the peripheral circuit structure PERI. For example, the plurality of pumping capacitors CAP1 may be disposed below the second region R2 of the memory cell structure CELL in the peripheral circuit structure PERI, but the present invention is not limited thereto. In another example, the plurality of pumping capacitors CAP1 may be disposed below the first region R1 of the memory cell structure CELL in the peripheral circuit structure PERI. FIG. 1D is a cross-sectional view of an example of a semiconductor device.

[0049] Referring to FIG. 1D, the semiconductor device 10 may include a peripheral circuit structure PERI which is a first semiconductor structure including a substrate 201, and a memory cell structure CELL which is a second semiconductor structure including a plate layer 101.

[0050] The peripheral circuit structure PERI may include the substrate 201, impurity regions 205 and element isolation regions 209 within the substrate 201, circuit elements 230 disposed on the substrate 201, a peripheral region insulating layer 290, and interconnection structures 250a and 250b. In an example, the peripheral circuit structure PERI may further include an insulating trench 211 within the substrate 201 and a capacitor structure 200 disposed on the insulating trench 211.

[0051] The substrate 201 may have an upper surface extending in the first direction (X-direction) and a second direction (Y-direction). An active region may be defined on the substrate 201 by element isolation regions 209. Impurity regions 205 including impurities may be disposed in a portion of the active region. The substrate 201 may include a semiconductor material, such as a group IV semiconductor, a group III-V compound semiconductor, or a group II-VI compound semiconductor. The substrate 201 may be provided as a bulk wafer or an epitaxial layer. For example, the substrate 201 may be bulk silicon or silicon-on-insulator SOI.

[0052] The circuit elements 230 may include planar transistors. Each of the circuit element 230 may include a peripheral gate dielectric layer 231, a peripheral gate electrode 232 on the peripheral gate dielectric layer 231, a peripheral gate capping layer 234 and a peripheral gate dielectric layer 231 disposed on the peripheral gate electrode 232, a peripheral gate electrode 232, and a peripheral gate spacer 233 on a side surface of the peripheral gate capping layer 234. The impurity regions 205 may be disposed as source/drain regions in the substrate 201 on both sides of the peripheral gate electrode 232.

[0053] The peripheral region insulating layer 290 may be disposed on the circuit element 230 on the substrate 201. The peripheral region insulating layer 290 may include a plurality of insulating layers formed in different process operations. The peripheral region insulating layer 290 may be formed of an insulating material.

[0054] The interconnection structures 250a and 250b may include a contact plug 250a and interconnections 250b. However, the present disclosure is not limited thereto, and the structure of the interconnection structures 250a and 250b may be variously changed. The interconnection structures 250a and 250b may be electrically connected to the circuit elements 230 and the impurity regions 205. The interconnection structures 250a and 250b may be referred to as lower interconnection structures or circuit interconnection structures. The contact plug 250a may have a pillar shape, and the interconnections 250b may have a line shape. An electrical signal may be applied to the circuit element 230 through the interconnection structures 250a and 250b. The contact plug 250a may also be connected to the peripheral gate electrode 232 in a region not illustrated. The interconnections 250b may be connected to the contact plug 250a and may be arranged in a plurality of layers. The contact plug 250a and the interconnections 250b may include a conductive material. For example, the contact plug 250a and the interconnections 250b may

include tungsten (W), copper (Cu), or aluminum (Al), and each of the components may further include a diffusion barrier.

[0055] The capacitor structure **200** may be spaced apart from the interconnection structures **250a** and **250b** and may be disposed on the second region R2 of the peripheral circuit structure PERI. The capacitor structure **200** may be disposed on the insulating trench **211** of the substrate **201**. The capacitor structure **200** may perform a function of storing electric charges. The capacitor structure **200** may form the pumping capacitor CAP1 of the charge pump circuits **56** and **56a** described above with reference to FIGS. **1A** to **1C**.

[0056] The memory cell structure CELL may have first and second regions R1 and R2, and may include a source structure SS, gate electrodes **130** stacked on the source structure SS, interlayer insulating layers **140** stacked alternately with the gate electrodes **130**, channel structures CH arranged to penetrate through a stack structure of the gate electrodes **130**, and contact plugs **170** connected to the gate electrodes **130** and extending vertically. The memory cell structure CELL may further include a horizontal insulating layer **113** disposed below the gate electrodes **130**, substrate insulating layers **121** arranged to penetrate through the plate layer **101**, studs **180** on the contact plugs **170**, and a cell region insulating layer **190** covering the gate electrodes **130**.

[0057] In the memory cell structure CELL, the first region R1 may be a region in which the gate electrodes **130** are vertically stacked to form memory cells or are connected to contact plugs **170**. The second region R2 may be an outer region of the plate layer **101**.

[0058] The source structure SS may include the plate layer **101**, a first horizontal conductive layer **102**, and a second horizontal conductive layer **104**, which are sequentially stacked. The plate layer **101** has a plate shape, and may function as at least a portion of a common source line of a semiconductor device **100**. The plate layer **101** may include a conductive material, for example, a semiconductor material. The plate layer **101** may further include impurities. The plate layer **101** may be provided as a polycrystalline semiconductor layer, such as a polycrystalline silicon layer, or an epitaxial layer.

[0059] The first and second horizontal conductive layers **102** and **104** may be sequentially stacked and disposed on an upper surface of the plate layer **101**, in a region in which the channel structures CH are disposed. The first horizontal conductive layer **102** may function as a portion of the common source line of the semiconductor device **100**, and, for example, may function as a common source line together with the plate layer **101**. The first horizontal conductive layer **102** may be directly connected to a channel layer in the channel structure CH. The first and second horizontal conductive layers **102** and **104** may include a semiconductor material, for example, polycrystalline silicon.

[0060] The horizontal insulating layer **113** may be disposed on the plate layer **101** on the same level as the first horizontal conductive layer **102**. The horizontal insulating layer **113** may include first and second horizontal insulating layers **111** and **112** alternately stacked on the plate layer **101**. The horizontal insulating layer **113** may be layers that remain after a portion of the horizontal insulating layer **113** is replaced with the first horizontal conductive layer **102** during a manufacturing process of the semiconductor device **100**. The horizontal insulating layer **113** may include silicon oxide, silicon nitride, silicon carbide, or silicon oxynitride. The first horizontal insulating layers **111** and the second horizontal insulating layers **112** may include different insulating materials.

[0061] The substrate insulating layers **121** may penetrate through the plate layer **101**, the horizontal insulating layer **113**, and the second horizontal conductive layer **104**. The substrate insulating layer **121** may include an insulating material, for example, silicon oxide, silicon nitride, silicon carbide, or silicon oxynitride.

[0062] The gate electrodes **130** may be vertically spaced apart from each other and stacked on the plate layer **101** to form a stack structure together with the interlayer insulating layers **140**. The stack structure may include lower and upper stack structures vertically stacked. The gate electrodes

130 may include first upper gate electrodes **130U1** and **130U2** of string selection transistors, memory gate electrodes **130M** of a plurality of memory cells, and second lower gate electrodes **130L1** and **130L2** of a ground selection transistor. The number of memory gate electrodes **130M** of the memory cells may be determined according to the capacitance of the semiconductor device **100**.

[0063] The gate electrodes **130** may be vertically spaced apart from each other and stacked on the first region **R1**, and may extend to different lengths in the first direction (X-direction) to form a step structure in a stepwise shape. Due to the step structure, a lower gate electrode **130** of the gate electrodes **130** may extend to be longer than an upper gate electrode **130** thereof, and may each have contact regions **130P** exposed upwardly from the interlayer insulating layers **140**. The gate electrodes **130** may be respectively connected to the contact plugs **170** in contact regions **130P** which are end regions.

[0064] The gate electrodes **130** may include a metal material, for example, tungsten (W). According to some implementations, the gate electrodes **130** may include a polycrystalline silicon or metal silicide material. The gate electrodes **130** may entirely include the same material. In some implementations, the gate electrodes **130** may further include a diffusion barrier, for example, the diffusion barrier may include tungsten nitride (WN), tantalum nitride (TaN), or titanium nitride (TiN), or a combination thereof.

[0065] The interlayer insulating layers **140** may be disposed between the gate electrodes **130**. Similarly to the gate electrodes **130**, the interlayer insulating layers **140** may be spaced apart from each other in a direction, perpendicular to the upper surface of the plate layer **101**, and may extend in the first direction (X-direction). The interlayer insulating layers **140** may include an insulating material such as silicon oxide or silicon nitride.

[0066] The channel structures CH may extend in the third direction (Z-direction) through the gate electrodes **130**, and may be connected to the plate layer **101**. Each of the channel structures CH may form one memory cell string, and the channel structures CH may be spaced apart from each other in rows and columns on the plate layer **101**. The channel structures CH may be arranged to form a grid pattern in an X-Y plane or may be arranged in a zigzag shape in one direction. The channel structures CH may have a pillar shape and may have inclined side surfaces that become narrower as they approach the plate layer **101**.

[0067] The channel structures CH may include vertically stacked lower and upper channel structures CH1 and CH2. The channel structures CH may have a shape in which the lower channel structures CH1 and the upper channel structures CH2 are connected, and may have bent portions due to differences in width in a connection region. However, according to some implementations, the number of channel structures stacked in the third direction (Z-direction) may be variously changed. Each of the channel structures CH may include a channel layer disposed in a channel hole, a gate dielectric layer, a channel buried insulating layer, and a channel pad on an upper end.

[0068] The contact plugs **170** may be connected to the contact regions **130P** of the gate electrodes **130**. The contact plugs **170** may penetrate through at least a portion of the cell region insulating layer **190**, and may be connected to each of the contact regions **130P** of the gate electrodes **130** exposed upwardly. The contact plugs **170** may penetrate through the gate electrodes **130** below the contact regions **130P**, and may penetrate through the second horizontal conductive layer **104**, the horizontal insulating layer **113**, and the plate layer **101** and may be connected to a lower interconnection structure **250** in the peripheral circuit structure PERI.

[0069] The contact plugs **170** may be spaced apart from the gate electrodes **130** below the contact regions **130P** by the contact insulating layers **160**. The contact plugs **170** may be spaced apart from the plate layer **101**, the horizontal insulating layer **113**, and the second horizontal conductive layer **104** by the substrate insulating layers **121**.

[0070] Each of the contact plugs **170** may have a shape that extends horizontally in the contact area **130P**. The contact plug **170** may include a vertical extension portion **170V** extending in the vertical

direction (Z-direction) and a horizontal extension portion **170H** that extends horizontally from the vertical extension portion **170V** and is in contact with the gate electrode **130**. The horizontal extension portion **170H** may be disposed along a circumference of the vertical extension portion **170V**, and all side surfaces thereof may be surrounded by the gate electrode **130**. The contact plugs **170** may be spaced apart from the gate electrodes **130** below the contact regions **130P**, that is, gate electrodes **130** that are not electrically connected, by the contact insulating layers **160**.

[0071] The contact plugs **170** may include a conductive material, for example, at least one of tungsten (W), copper (Cu), aluminum (Al), and alloys thereof. In some implementations, the contact plugs **170** may include a barrier layer extending along a side surface and a bottom surface thereof, or may have an air gap therein.

[0072] The contact insulating layers **160** may be arranged to surround side surfaces of each of the contact plugs **170** below the contact regions **130P**. The contact insulating layers **160** may be spaced apart from each other in the third direction (Z-direction) around each of the contact plugs **170**. The contact insulating layers **160** may be disposed on substantially the same level as the gate electrodes **130**. The contact insulating layers **160** may include an insulating material, for example, silicon oxide, silicon nitride, or silicon oxynitride.

[0073] The studs **180** may be included in a cell interconnection structure that is electrically connected to memory cells in the memory cell structure CELL. The studs **180** may be connected to the channel structures CH and the contact plugs **170**, and may be electrically connected to the channel structures CH and the gate electrodes **130**. The studs **180** may include a metal, and may include, for example, tungsten (W), copper (Cu), or aluminum (Al).

[0074] The cell region insulating layer **190** may be disposed to cover the stack structure of the gate electrodes **130** and the contact plugs **170**. The cell region insulating layer **190** may be formed of an insulating material or may be formed of a plurality of insulating layers.

[0075] A through-plug **164** and capacitor contacts **165** are disposed in the second region R2 of the memory cell region CELL, which is an outer region of the plate layer **101**, and may extend to the peripheral circuit region PERI by penetrating through the cell region insulating layer **190**. The through-plug **164** and the capacitor contacts **165** may be arranged to connect the studs **180** of the memory cell region CELL and the lower interconnection structure **250** of the peripheral circuit region PERI. The through-plug **164** and the capacitor contacts **165** may include a conductive material, may include, for example, a metallic material such as tungsten (W), copper (Cu), or aluminum (Al). The through-plug **164** and capacitor contacts **165** may be formed in the same process operation as the contact plugs **170**, and may include the same material and may have the same internal structure.

[0076] The capacitor structure **200** may be disposed in the second region R2, and may be disposed over the peripheral circuit region PERI and the memory cell region CELL. The capacitor structure **200** may perform a function of storing electric charges.

[0077] FIG. 1E is a cross-sectional view of an example of a semiconductor device.

[0078] Referring to FIG. 1E, a semiconductor device **10d** may include a first semiconductor structure S1 and a second semiconductor structure S2 bonded using a wafer bonding manner.

[0079] The description of the peripheral circuit structure PERI described above with reference to FIG. 1D may be applied to the first semiconductor structure S1. However, the first semiconductor structure S1 may further include second bonding vias **295**, second bonding metal layers **298**, and a second bonding insulating layer **299**, which are included in a bonding structure. The second bonding vias **295** may be connected to interconnections **250b** in an uppermost portion. At least a portion of the second bonding metal layer **298** may be connected to the second bonding vias **295**. The second bonding metal layer **298** may be connected to the first bonding metal layers **198** of the second semiconductor structure S2. The second bonding metal layers **298** and the first bonding metal layers **198** may provide an electrical connection path for bonding the first semiconductor structure S1 and the second semiconductor structure S2. Some of the second bonding metal layers

298 may not be connected to lower interconnections **250b** and may be disposed only for bonding. [0080] The second bonding vias **295** and the second bonding metal layers **298** may include a conductive material, for example, copper (Cu). The second bonding insulating layer **299** may be disposed around the second bonding metal layers **298**. The second bonding insulating layer **299** may also function as a diffusion barrier for the second bonding metal layers **298**, and may include, for example, at least one of SiN, SiON, SiCN, SiOC, SiOCN, and SiO.

[0081] If there is no other explanation for the second semiconductor structure **S2**, the description of the memory cell structure CELL described above with reference to FIGS. **1A** to **1D** may be applied. The second semiconductor structure **S2** may further include studs **180** and cell interconnection lines **185**. The second semiconductor structure **S2** may further include first bonding vias **195**, first bonding metal layers **198**, and first bonding insulating layer **199**, which are included in the bonding structure. In an example, the second semiconductor structure **S2** may further include a passivation layer **106** covering an upper surface of the plate layer **101** and an upper surface of the substrate insulating layers **121**.

[0082] The studs **180** may be included in a cell interconnection structure electrically connected to the memory cells of the second semiconductor structure **S2**. The studs **180** may be connected to the channel structures CH and the contact plugs **170** and may be electrically connected to the channel structure CH and the gate electrodes **130**. The studs **180** are illustrated in a plug shape, but the present disclosure is not limited thereto and may also have a line shape. In an example, the studs **180** may include a metal, and may include, for example, tungsten (W), copper (Cu), or aluminum (Al).

[0083] The cell interconnection lines **185** may be connected to the studs **180**. However, in some implementations, the number of layers and an arrangement form of plugs and interconnection lines included the cell interconnection structure may be variously changed. The cell interconnection lines **185** may be formed of a conductive material, and may include, for example, at least one of tungsten (W), aluminum (Al), and copper (Cu).

[0084] The first bonding vias **195** and the first bonding metal layers **198** may be disposed below the cell interconnection lines **185** in the lowermost portion. The first bonding vias **195** may connect the cell interconnection lines **185** and the first bonding metal layers **198**, and the first bonding metal layers **198** may be bonded to the second bonding metal layers **298** of the first semiconductor structure **S1**. The first bonding insulating layer **199** may be bonded and connected to the second bonding insulating layer **299** of the first semiconductor structure **S1**. The first bonding vias **195** and the first bonding metal layers **198** may include a conductive material, such as copper (Cu). The second bonding insulating layer **199** may include, for example, at least one of SiO, SiN, SiCN, SiOC, SiON, and SiOCN.

[0085] The first and second semiconductor structures **S1** and **S2** may be bonded by bonding the first bonding metal layers **198** and the second bonding metal layers **298** and bonding the first bonding insulating layer **199** and the second bonding insulating layer **299**. The bonding of the first bonding metal layers **198** and the second bonding metal layers **298** may be, for example, copper (Cu)-copper (Cu) bonding, and the bonding of the first bonding insulating layer **199** and the second bonding insulating layer **299** may be, for example, dielectric-dielectric bonding such as SiCN—SiCN bonding. The first and second semiconductor structures **S1** and **S2** may be bonded by hybrid bonding including copper (Cu)-copper (Cu) bonding and dielectric-dielectric bonding.

[0086] The passivation layer **106** may be disposed on the upper surface of the plate layer **101** and may protect the semiconductor device **10d**. The passivation layer **106** may include an insulating material, for example, at least one of silicon oxide, silicon nitride, and silicon carbide. The substrate insulating layer **121** may be widely disposed in the first region **R1** and the second region **R2** so as to cover an upper end of the contact plugs **170**, an upper end of the through-plug **164**, and an upper end of the capacitor contacts **165**. However, in some implementations, an arrangement form of the substrate insulating layer **121** may be variously changed in a range in which the contact

plugs **170**, the through-plug **164** and the capacitor contacts **165** are electrically separated from the plate layer **101**.

[0087] FIG. **2A** is a schematic perspective view illustrating an example of a capacitor structure of a semiconductor device.

[0088] Referring to FIG. **2A**, the capacitor structure **200** may include a first electrode structure **210** and a second electrode structure **220**. First electrodes MC1_1, ML1_1, MC1_2, ML1_2, MC1_3 and ML1_3 included in the first electrode structure **210** and second electrodes MC2_1, ML2_1, MC2_2, ML2_2, MC2_3 and ML2_3 included in the second electrode structure **220** may be arranged alternately in the first direction (X-direction). In an example, the capacitor structure **200** may further include an insulating layer (e.g., the peripheral region insulating layer **290** in FIG. **1D**) filling a space between the first electrode structure **210** and the second electrode structure **220**.

[0089] The first electrode structure **210** and the second electrode structure **220** may have different electric potentials. In an example, each of the first electrode structure **210** and the second electrode structure **220** may receive an electrical signal through separate interconnections connected to each of the first electrode structure **210** and the second electrode structure **220**.

[0090] Each of the first electrode structure **210** and the second electrode structure **220** may be formed by stacking a plurality of contact electrodes and a plurality of interconnection electrodes in a plate shape.

[0091] The first electrode structure **210** may include a first lower contact electrode MC1_1, a first lower interconnection electrode ML1_1, a first intermediate contact electrode MC1_2, a first intermediate interconnection electrode ML1_2, a first upper contact electrode MC1_3, and a first upper interconnection electrode ML1_3, which are sequentially stacked in the third direction (Z-direction).

[0092] As the number of contact electrodes and interconnection electrodes stacked on the first lower interconnection electrode ML1_1 increases, contact electrodes and interconnection electrodes having a relatively large height may be provided and/or formed. In an example, a height of the first intermediate contact electrode MC1_2 may be higher than a height of the first lower interconnection electrode ML1_1, and a height of the first intermediate interconnection electrode ML1_2 may be higher than a height of the first intermediate contact electrode MC1_2. A height of the first upper contact electrode MC1_3 may be higher than a height of the first intermediate interconnection electrode ML1_2, and a height of the first upper interconnection electrode ML1_3 may be higher than a height of the first upper contact electrode MC1_3. For example, the height of the first lower interconnection electrode ML1_1 may be about 1000 Å, the height of the first intermediate contact electrode MC1_2 may be about 2000 Å, the height of the first intermediate interconnection electrode ML1_2 may be about 2700 Å, and the height of the first upper contact electrode MC1_3 may be approximately 3000 Å, and the height of the first upper interconnection electrode ML1_3 may be approximately 5100 Å.

[0093] A height of the first lower contact electrode MC1_1 may be higher than a height of the first lower interconnection electrode ML1_1, the first intermediate contact electrode MC1_2, the first intermediate interconnection electrode ML1_2, and the first upper contact electrode MC1_3. For example, the height of the first lower contact electrode MC1_1 in the third direction (Z-direction) may be about 3800 Å.

[0094] The second electrode structure **220** may have substantially the same structure as the first electrode structure **210**. In an example, the second electrode structure **220** may include a second lower contact electrode MC2_1, a second lower interconnection electrode ML2_1, a second intermediate contact electrode MC2_2, a second intermediate interconnection electrode ML2_2, a second upper contact electrode MC2_3, and a second upper interconnection electrode ML2_3, which are sequentially stacked in the third direction (Z-direction).

[0095] Each of the first and second lower contact electrodes MC1_1 and MC2_1, the first and second lower interconnection electrodes ML1_1 and ML2_1, the first and second intermediate

contact electrodes MC1-2 and MC2-2, the first and second intermediate interconnection electrodes ML1-2 and ML2-2, the first and second upper contact electrodes MC1-3 and MC2-3, and the first and second upper interconnection electrodes ML1-3 and ML2-3 may have a plate shape (or wall type) extending in the second direction (Y-direction) and a third direction (Z-direction).

[0096] Each of the first and second lower contact electrodes MC1-1 and MC2-1, the first and second lower interconnection electrodes ML1-1 and ML2-1, the first and second intermediate contact electrodes MC1-2 and MC2-2, the first and second intermediate interconnection electrodes ML1-2 and ML2-2, the first and second upper contact electrodes MC1-3 and MC2-3, and the first and second upper interconnection electrodes ML1-3 and ML2-3 may have inclined side surfaces that become narrower towards a lower portion.

[0097] Each of the first and second lower contact electrodes MC1-1 and MC2-1, the first and second lower interconnection electrodes ML1-1 and ML2-1, the first and second intermediate contact electrodes MC1-2 and MC2-2, the first and second intermediate interconnection electrodes ML1-2 and ML2-2, the first and second upper contact electrodes MC1-3 and MC2-3, and the first and second upper interconnection electrodes ML1-3 and ML2-3 may be formed by a single damascene process.

[0098] The first lower contact electrode MC1-1 is an electrode disposed in a lowermost portion of the first electrode structure **210** and may be disposed on the substrate (e.g., the substrate **201** in FIG. 1D). The first lower contact electrode MC1-1 may have a height higher than the height of the first lower interconnection electrode ML1-1 disposed on the first lower contact electrode MC1-1 in the third direction (Z-direction).

[0099] The second lower contact electrode MC2-1 is an electrode disposed in a lowermost portion of the second electrode structure **220**, and may be arranged alternately with the first lower contact electrode MC1-1. The second lower contact electrode MC2-1 may have a height higher than the height of the second lower interconnection electrode ML2-1 disposed on the second lower contact electrode MC2-1 in the third direction (Z-direction).

[0100] The first electrode structure **210** and the second electrode structure **220** may include a conductive material. For example, the first electrode structure **210** and the second electrode structure **220** may include a metal such as tungsten (W), titanium (Ti), tantalum (Ta), copper (Cu), or aluminum (Al), but the present disclosure is not limited thereto.

[0101] Each of the first electrode structure **210** and the second electrode structure **220** is illustrated as including three contact electrodes and three interconnection electrodes, but the present disclosure is not limited thereto, and the number of contact electrodes and interconnection electrodes of the first electrode structure **210** and the second electrode structure **220** may be variously changed.

[0102] The semiconductor device may include a capacitor structure **200**, and the capacitor structure **200** may include the first electrode structure **210** including the first lower contact electrode MC1-1 having a relatively large height in the vertical direction, and may include the second electrode structure **220** including the second lower contact electrode MC2-1 having a relatively large height in the vertical direction. Accordingly, the height of the capacitor structure **200** in the vertical direction may relatively increase, thereby providing a semiconductor device with improved electrical characteristics by securing high electrostatic capacity.

[0103] FIG. 2B is a perspective view illustrating an example of a semiconductor device including the capacitor structure of FIG. 2A.

[0104] Referring to FIG. 2B, the semiconductor device may include a capacitor structure **200** and interconnection structures **250a** and **250b**. The capacitor structure **200** and the interconnection structures **250a** and **250b** may be disposed in the peripheral circuit structure (PERI) described above with reference to FIGS. 1A to 1D. The peripheral circuit structure PERI may include a first region R1 and a second region R2 disposed in parallel with the first region R1. The interconnection structures **250a** and **250b** may be disposed on the first region R1, and the capacitor structure **200**

may be disposed on the second region **R2**.

[0105] The interconnection structures **250a** and **250b** may include a contact plug **250a** disposed on the substrate **201** and interconnections **250b** on the contact plug **250a**. The interconnection structures **250a** and **250b** may include a conductive material. For example, the interconnection structures **250a** and **250b** may include a metal such as tungsten (W), titanium (Ti), tantalum (Ta), copper (Cu), or aluminum (Al), but the present disclosure is not limited thereto.

[0106] The contact plug **250a** may include a first contact plug **251** and a second contact plug **253** disposed on impurity regions **205**. The first contact plug **251** may be disposed on a first impurity region **205a**, and the second contact plug **253** may be disposed on a second impurity region **205b**. In an example, a circuit element (e.g., the circuit element **230** of FIG. 1D) may be disposed between the first impurity region **205a** and the second impurity region **205b**. In an example, when the first impurity region **205a** is a source region, the second impurity region **205b** may be a drain region, and when the first impurity region **205a** is a drain region, the second impurity region **205b** may be a source region.

[0107] The first contact plug **251** may include a 1-1 contact plug **251a** and a 1-2 contact plug **251b** spaced apart from each other in the second direction (Y-direction) on the first impurity region **205a**. In an example, the second contact plug **253** may include a 2-1 contact plug **253a** and a 2-2 contact plug **253b** spaced apart from each other in the second direction (Y-direction) on the second impurity region **205b**. However, the present disclosure is not limited thereto, and the first contact plug **251** may include only one 1-1 contact plug **251a**, excluding the 1-2 contact plug **251b**, and the second contact plug **253** may include only the 2-1 contact plug **253a**, excluding the 2-2 contact plug **253b**.

[0108] The first contact plug **251** and the second contact plug **253** may have a pillar shape of which the width becomes narrower as they approach the substrate **201**. For example, the first contact plug **251** and the second contact plug **253** may have the shape of a square pillar or a cylinder, but the present disclosure is not limited thereto.

[0109] The interconnections **250b** may include a first peripheral interconnection **252** disposed on the first contact plug **251** and a second peripheral interconnection **254** disposed on the second contact plug **253**. In an example, the first and second peripheral interconnections **252** and **254** may have a line shape extending in the second direction (Y-direction).

[0110] The capacitor structure **200** may be disposed on an insulating trench **211** in substrate **201**. The insulating trench **211** may include a first finger trench **211a** and a second finger trench **211b** spaced apart from the first finger trench **211a**.

[0111] The first finger trench **211a** and the second finger trench **211b** may have a shallow trench isolation (STI) structure. The first finger trench **211a** and the second finger trench **211b** may have substantially the same structure. In an example, the first finger trench **211a** and the second finger trench **211b** may have a structure in which a width thereof becomes narrower toward the lower surface of the substrate **201**. The first finger trench **211a** may be regions in which electrodes disposed in a lowermost portion of the first electrode structure **210** of the capacitor structure **200** are disposed. The second finger trench **211b** may be regions in which electrodes disposed a lowermost portion of the second electrode structure **220** of the capacitor structure **200** are disposed.

[0112] The first finger trench **211a** and the second finger trench **211b** may include an insulating material filling a trench structure. For example, the insulating material may be fluoride silicate glass (FSG), undoped silicate glass (USG), boro-phospho-silicate glass (BPSG), phospho-silicate glass (PSG), flowable oxide (FOX), and plasma enhanced tetra-ethyl-ortho-silicate (PE-TEOS), or tonen silazene (TOSZ), but the present disclosure is not limited thereto.

[0113] The first electrode structure **210** may be disposed on the first finger trench **211a**, and the second electrode structure **220** may be disposed on the second finger trench **211b**. The first finger trenches **211a** and the second finger trenches **211b** may be alternately arranged at regular intervals in the first direction (X-direction). In an example, the first finger trench **211a** and the second finger

trench **211b** may extend in a second direction (Y-direction), which is an extension direction of the first electrode structure **210** and the second electrode structure **220**. In an example, a gap between the first finger trench **211a** and the second finger trench **211b** may be substantially equal to a gap between the first electrode structure **210** and the second electrode structure **220**.

[0114] The first lower contact electrode **MC1-1** and the first lower interconnection electrode **ML1_1** may be sequentially stacked on the first finger trench **211a**. In the drawing, only the first lower contact electrode **MC1-1** and the first lower interconnection electrode **ML1_1** are illustrated as electrodes of the first electrode structure **210**, but the first intermediate contact electrode **MC1_2**, the first intermediate interconnection electrode **ML1_2**, the first upper contact electrode **MC1-3** and the first upper interconnection electrode **ML1_3** may be sequentially stacked on the first lower interconnection electrode **ML1_1**.

[0115] The second lower contact electrode **MC2-1** and the second lower interconnection electrode **ML2_1** may be sequentially stacked on the second finger trench **211b**. In the drawing, only the second lower contact electrode **MC2-1** and the second lower interconnection electrode **ML2_1** are illustrated as electrodes of the second electrode structure **220**, but the second intermediate contact electrode **MC2_2**, the second intermediate interconnection electrode **ML2_2**, the second upper contact electrode **MC3_3**, the second upper contact interconnection **ML3_3** may be sequentially stacked on the second lower interconnection electrode **ML2_1**.

[0116] The first lower contact electrode **MC1-1** may penetrate through a portion of the first finger trench **211a**. A lower surface of the first lower contact electrode **MC1-1** may penetrate through an upper surface of the first finger trench **211a** and may be buried in the first finger trench **211a**. The lower surface of the first lower contact electrode **MC1-1** may be disposed on a level lower than that of the upper surface of the first finger trench **211a**, and may be disposed on a level higher than that of a lower surface of the first finger trench **211a**.

[0117] The second lower contact electrode **MC2-1** may penetrate through a portion of the second finger trench **211b**. A lower surface of the second lower contact electrode **MC2-1** may penetrate through an upper surface of the second finger trench **211b** and may be buried in the second finger trench **211b**. The lower surface of the second lower contact electrode **MC2-1** may be disposed on a level lower than that of the upper surface of the second finger trench **211b**, and may be disposed on a level higher than that of a lower surface of the second finger trench **211b**.

[0118] In some implementations, the lower surface of the first lower contact electrode **MC1-1** may be disposed on the same level as the upper surface of the first finger trench **211a**. The lower surface of the second lower contact electrode **MC2-1** may be disposed on the same level as the upper surface of the second finger trench **211b**.

[0119] The first finger trench **211a** and the second finger trench **211b** may be provided and/or formed in the same process as the element isolation region **209**. In an example, the upper surface of the first finger trench **211a** and the upper surface of the second finger trench **211b** may be disposed on the same level as the upper surface of the element isolation region **209**. In an example, the lower surface of the first finger trench **211a** and the lower surface of the second finger trench **211b** may be disposed on the same level as a lower surface of the element isolation region **209**. However, the present disclosure is not limited thereto. The lower surfaces of the first and second finger trenches **211a** and **211b** may be disposed on a level lower than that of the lower surface of the element isolation region **209**. In another example, the lower surfaces of the first and second finger trenches **211a** and **211b** may be disposed on a level higher than that of the lower surface of the element isolation region **209**. In some implementations, the first finger trench **211a** and the second finger trench **211b** may have the same shape as the element isolation region **209**, but the present disclosure is not limited thereto.

[0120] The number of first finger trenches **211a** may correspond to the number of first lower contact electrodes **MC1_1**, which are lowermost electrodes of the first electrode structure **210**, and the number of second finger trenches **211b** may correspond to the number of second lower contact

electrodes MC2_1, which are lowermost electrodes of the second electrode structure 220.

[0121] The first lower contact electrode MC1-1 and the second lower contact electrode MC2-1 may be provided and/or formed in the same process as the first and second contact plugs 251 and 253. In an example, the upper surfaces of the first and second contact plugs 251 and 253 may be disposed on the same level as the upper surfaces of the first and second lower contact electrodes MC1-1 and MC2_1.

[0122] The first lower interconnection electrode ML1_1 and the second lower interconnection electrode ML2_1 may be provided and/or formed in the same process as the first and second peripheral interconnections 252 and 254. In an example, the upper surface of the first lower interconnection electrode ML1_1 and the upper surface of the second lower interconnection electrode ML2_1 may be disposed on the same level as the upper surface of the first and second peripheral interconnections 252 and 254.

[0123] FIG. 2C is a perspective view illustrating another example of a semiconductor device including the capacitor structure of FIG. 2A.

[0124] Referring to FIG. 2C, the remaining components except for an insulating trench 211c in a substrate 201' may be identical to or similar to those illustrated in FIG. 2B.

[0125] A semiconductor device 10' may include the substrate 201', the insulating trench 211c in the substrate 201' and a capacitor structure 200 on the insulating trench 211c.

[0126] The insulating trench 211c may be provided integrally with a front surface of a region in which the capacitor structure 200 is disposed in the substrate 201'.

[0127] The insulating trench 211c may have an inclined side surface of which the width becomes narrower toward the lower surface of the substrate 201. The insulating trench 211c may include an insulating material filling the trench structure. In an example, a width of the insulating trench 211c in the first direction (X-direction) may be greater than a width of the capacitor structure 200 in the first direction (X-direction).

[0128] The first electrode structure 210 and the second electrode structure 220 may be disposed on the insulating trench 211c. In an example, the first lower contact electrode MC1-1 and the second lower contact electrode MC2-1 may penetrate through a portion of the insulating trench 211c. A lower surface of the first lower contact electrode MC1-1 and a lower surface of the second lower contact electrode MC2-1 may penetrate through an upper surface of the insulating trench 211c and may be buried in the insulating trench 211c. The lower surface of the first lower contact electrode MC1-1 and the lower surface of the second lower contact electrode MC2-1 may be disposed on a level lower than that of the upper surface of the insulating trench 211c, and may be disposed on a level higher than that of a lower surface of the insulation trench 211c. In some implementations, the lower surface of the first lower contact electrode MC1-1 and the lower surface of the second lower contact electrode MC2-1 may be disposed on the same level as the upper surface of the insulating trench 211c.

[0129] The insulating trench 211c may include an insulating material filling the trench structure.

[0130] The insulating trench 211c may be provided and/or formed in the same process as the element isolation region 209. The lower surface of the insulation trench 211c may be disposed on the same level as the lower surface of the element isolation region 209. In an example, the width of the insulating trench 211c in the first direction (X-direction) may be larger than a width of the element isolation region 209 in the first direction (X-direction). The lower surface of the insulation trench 211c may be disposed on the same level as the lower surface of the element isolation region 209.

[0131] FIG. 3A is a schematic perspective view illustrating another example of a capacitor structure of a semiconductor device.

[0132] Referring to FIG. 3A, a capacitor structure 200a may include a first electrode structure 210a and a second electrode structure 220a. First electrodes ML1_1a, ML1_2a and ML1_3a included in the first electrode structure 210a and second electrodes ML2_1a, ML2_2a and ML2_3a included

in the second electrode structure **220a** may be arranged alternately in the first direction (X-direction). In an example, the capacitor structure **200a** may further include an insulating layer (e.g., the peripheral region insulating layer **290** in FIG. 1D) filling a space between the first electrode structure **210a** and the second electrode structure **220a**.

[0133] The first electrode structure **210a** and the second electrode structure **220a** may be formed by stacking a plurality of interconnection electrodes having a plate shape.

[0134] The first electrode structure **210a** may include a first lower interconnection electrode **ML1_1a**, a first intermediate interconnection electrode **ML1_2a**, and a first upper interconnection electrode **ML1_3a**, which are sequentially stacked in the third direction (Z-direction).

[0135] A height of the first lower interconnection electrode **ML1_1a** in the third direction (Z-direction) is higher than a height of the first intermediate interconnection electrode **ML1_2a**, and may be lower than a height of the first upper interconnection electrode **ML1_3a**. However, the present disclosure is not limited thereto, and in another example, the height of the first lower interconnection electrode **ML1_1a** may be lower than the height of the first intermediate interconnection electrode **ML1_2a**.

[0136] The second electrode structure **220b** may include a second lower interconnection electrode **ML2_1a**, a second intermediate interconnection electrode **ML2_2a**, and a second upper interconnection electrode **ML2_3a**, which are sequentially stacked in the third direction (Z-direction).

[0137] A height of the second lower interconnection electrode **ML2_1a** in the third direction (Z-direction) may be higher than a height of the second intermediate interconnection electrode **ML2_2a**, and may be lower than a height of the second upper interconnection electrode **ML2_3a**. However, the present disclosure is not limited thereto, and in another example, the height of the second lower interconnection electrode **ML2_1a** may be lower than the height of the second intermediate interconnection electrode **ML2_2a**.

[0138] Each of the first and second lower interconnection electrodes **ML1_1a** and **ML2_1a**, the first and second intermediate interconnection electrodes **ML1_2a** and **ML2_2a**, and the first and second upper interconnection electrodes **ML1_3a** and **ML2_3a** may have a plate shape (or wall type) extending in the second direction (Y-direction) and the third direction (Z-direction).

[0139] Lengths of the first and second lower interconnection electrodes **ML1_1a** and **ML2_1a**, the first and second intermediate interconnection electrodes **ML1_2a** and **ML2_2a**, and the first and second upper interconnection electrodes **ML1_3a** and **ML2_3a** in the second direction (Y-direction) may be substantially identical to each other.

[0140] Each of the first and second lower interconnection electrodes **ML1_1a** and **ML2_1a**, the first and second intermediate interconnection electrodes **ML1_2a** and **ML2_2a**, and the first and second upper interconnection electrodes **ML1_3a** and **ML2_3a** may have inclined side surfaces that become narrower towards a lower portion.

[0141] Interconnection electrodes of each of the first and second lower interconnection electrodes **ML1_1a** and **ML2_1a**, the first and second intermediate interconnection electrodes **ML1_2a** and **ML2_2a**, and the first and second upper interconnection electrodes **ML1_3a** and **ML2_3a** may be formed in a dual damascene process.

[0142] The first lower interconnection electrode **ML1_1a** is an electrode disposed in a lowermost portion of the first electrode structure **210a** and may be disposed on a substrate (e.g., the substrate **201** in FIG. 1D).

[0143] The second lower interconnection electrode **ML2_1a** is an electrode disposed in a lowermost portion of the second electrode structure **220b**, and may be arranged alternately with the first lower interconnection electrode **ML1_1a** in the first direction (X-direction).

[0144] Each of the first electrode structure **210a** and the second electrode structure **220a** is illustrated as including three interconnection electrodes, but the present disclosure is not limited thereto, and the number of interconnection electrodes included in each of the first electrode

structure **210a** and the second electrode structure **220a** may be variously changed.

[0145] The semiconductor device may include the capacitor structure **200a**, and the capacitor structure **200a** may include the first electrode structure **210a** including the first lower interconnection electrode **ML1_1a** and the second electrode structure **220a** including the second lower interconnection electrode **ML2_1a**.

[0146] FIG. 3B is a perspective view illustrating an example of a semiconductor device including the capacitor structure of FIG. 3A.

[0147] Referring to FIG. 3B, a semiconductor device **10a** may include a capacitor structure **200a** and interconnection structures **250a** and **250b**.

[0148] The capacitor structure **200a** may be disposed on an insulating trench **211** in a substrate **201**. The first electrode structure **210a** may be disposed on the first finger trench **211a**, and the second electrode structure **220a** may be disposed on the second finger trench **211b**.

[0149] In some implementations, the capacitor structure **200a** may be provided on an insulating trench (e.g., the insulating trench **211c** in FIG. 2C) integrally formed on a front surface of a region in which the capacitor structure **200a** is disposed in the substrate **201**.

[0150] A first lower interconnection electrode **ML1_1a** may be disposed on the first finger trench **211a**. In the drawing, only the first lower interconnection electrode **ML1_1a** is illustrated as an electrode of the first electrode structure **210a** disposed on the first finger trench **211a**, but a first intermediate interconnection electrode **ML1_2a** and a first upper interconnection electrode **ML1_3a** may be sequentially stacked on the first lower interconnection electrode **ML1_1a**.

[0151] A second lower interconnection electrode **ML2_1a** may be disposed on the second finger trench **211b**. In the drawing, only the second lower interconnection electrode **ML2_1a** is illustrated as an electrode of the second electrode structure **220b** disposed on the second finger trench **211b**, but a second intermediate interconnection electrode **ML2_2a** and a second upper interconnection electrode **ML2_3a** may be sequentially stacked on the second lower interconnection electrode **ML2_1a**.

[0152] The first lower interconnection electrode **ML1_1a** may penetrate through a portion of the first finger trench **211a**. A lower surface of the first lower interconnection electrode **ML1_1a** may penetrate through the upper surface of the first finger trench **211a** and may be buried in the first finger trench **211a**. The lower surface of the first lower interconnection electrode **ML1_1a** may be disposed on a level lower than that of the upper surface of the first finger trench **211a**, and may be disposed on a level higher than that of the lower surface of the first finger trench **211a**.

[0153] The second lower interconnection electrode **ML2_1a** may penetrate through a portion of the second finger trench **211b**. A lower surface of the second lower interconnection electrode **ML2_1a** may penetrate through the upper surface of the second finger trench **211b** and may be buried in the second finger trench **211b**. The lower surface of the second lower interconnection electrode **ML2_1a** may be disposed on a level lower than that of the upper surface of the second finger trench **211b**, and may be disposed on a level higher than that of the lower surface of the second finger trench **211b**.

[0154] In some implementations, the first lower interconnection electrode **ML1_1a** may be disposed on the same level as the upper surface of the first finger trench **211a**. The second lower interconnection electrode **ML2_1a** may be disposed on the same level as the upper surface of the second finger trench **211b**.

[0155] The first lower interconnection electrode **ML1_1a** and the second lower interconnection electrode **ML2_1a** may be provided and/or formed in the same process as the first and second contact plugs **251** and **253**. In an example, the upper surfaces of the first and second contact plugs **251** and **253** may be disposed on the same level as the upper surface of the first lower interconnection electrode **ML1_1a** and the upper surface of the second lower interconnection electrode **ML2_1a**.

[0156] FIG. 4A is a schematic perspective view illustrating another example of a capacitor

structure of a semiconductor device.

[0157] Referring to FIG. 4A, a capacitor structure **200b** may include a first electrode structure **210b** and a second electrode structure **220b**. In an example, first electrodes **MC1_1b**, **ML1_1b**, **ML1_2b** and **ML1_3b** included in the first electrode structure **210b** may be arranged alternately in the first direction (X-direction) with second electrodes **MC2_1b**, **ML2_1b**, **ML2_2b** and **ML2_3b** included in the second electrode structure **220b**.

[0158] The first electrode structure **210b** may include a first lower contact electrode **MC1_1b**, a first intermediate electrode structure **210M**, a first intermediate interconnection electrode **ML1_2b**, and a first upper interconnection electrode **ML1_3b**, which are sequentially stacked in the third direction (Z-direction).

[0159] The first intermediate electrode structure **210M** may include a first connection portion **MS1** extending in the first direction (X-direction) and first intermediate electrodes **ML1_1b** protruding and extending from the first connection portion **MS1** in the second direction (Y-direction). The first connection portion **MS1** may electrically connect the first intermediate electrodes **ML1_1b**. In an example, a height of the first connection portion **MS1** in the third direction (Z-direction) may be substantially equal to a height of the first intermediate electrode **ML1_1b** in the third direction (Z-direction).

[0160] A height of the first lower contact electrode **MC1_1b** in the third direction (Z-direction) may be higher than a height of the first intermediate electrode structure **210M**.

[0161] The second electrode structure **220b** may include a second lower contact electrode **MC2_1b**, a second intermediate electrode structure **220M**, a second intermediate interconnection electrode **ML2_2b**, and a second upper interconnection electrode **ML2_3b**, which are sequentially stacked in the third direction (Z-direction).

[0162] The second intermediate electrode structure **220M** may include a second connection portion **MS2** extending in the first direction (X-direction), and second intermediate electrodes **ML2_1b** protruding and extending from the second connection portion **MS2** in the second direction (Y-direction) and arranged alternately with the first intermediate electrode **ML1_1b** in the first direction (X-direction). The second connection portion **MS2** may electrically connect the second intermediate electrodes **ML2_1b**. In an example, a height of the second connection portion **MS2** in the third direction (Z-direction) may be substantially equal to a height of the second intermediate electrode **ML2_1b** in the third direction (Z-direction).

[0163] The first and second strap portions **MS1** and **MS2** and the first and second intermediate electrodes **ML1_1b** and **ML2_1b** may be provided and/or formed in the same process. The first and second strap portions **MS1** and **MS2** and the first and second intermediate electrodes **ML1_1b** and **ML2_1b** may include the same material.

[0164] The first connection portion **MS1** and the second connection portion **MS2** may be spaced apart from each other in the second direction (Y-direction).

[0165] A length of the first and second lower contact electrodes **MC1_1b** and **MC2_1b** in the second direction (Y-direction) may be substantially equal to a length of the first and second intermediate electrode structures **210M** and **220M** in the second direction (Y-direction).

[0166] The first and second lower contact electrodes **MC1_1b** and **MC2_1b**, the first and second intermediate electrode structures **210M** and **220M**, the first and second intermediate interconnection electrodes **ML1_2b** and **ML2_2b**, and the first and second upper interconnection electrodes **ML1_3b** and **ML2_3b** may have a plate shape extending in the second direction (Y-direction) and the third direction (Z-direction).

[0167] Each of the first and second lower contact electrodes **ML1_1b** and **ML2_1b** and the first and second intermediate electrode structures **210M** and **220M** may be formed in a single damascene process.

[0168] The first intermediate interconnection electrode **ML1_2b** and the first upper interconnection electrode **ML1_3b** may be sequentially stacked on the first intermediate electrodes **ML1_1b** of the

first intermediate electrode structure **210M**. The second intermediate interconnection electrode **ML2_2b** and the second upper interconnection electrode **ML2_3b** may be disposed on the second intermediate electrodes **ML2_1b** of the second intermediate electrode structure **220M**. In an example, a height of the first and second upper interconnection electrodes **ML1_3b** and **ML2_3b** in the third direction (Z-direction) may be greater than a height of the first and second intermediate interconnection electrodes **ML1_2b** and **ML2_2b**.

[0169] The first lower contact electrode **MC1_1b** is an electrode disposed in a lowermost portion of the first electrode structure **210b** and may be disposed on a substrate (e.g., the substrate **201** in FIG. **1D**). The first lower contact electrode **MC1_1b** may have a height greater than the height of the first intermediate electrode structure **210M** disposed on the first lower contact electrode **MC1_1b** in the third direction (Z-direction).

[0170] The second lower contact electrode **MC2_1b** is an electrode disposed in a lowermost portion of the second electrode structure **220b** and may be arranged alternately with the first lower contact electrode **MC1_1b**. The second lower contact electrode **MC2_1b** may have a height higher than a height of the second intermediate electrode structure **220M** disposed on the second lower contact electrode **MC2_1b** in the third direction (Z-direction).

[0171] FIG. **4B** is a perspective view illustrating an example of a semiconductor device including the capacitor structure of FIG. **4A**.

[0172] Referring to FIG. **4B**, a semiconductor device **10b** may include a capacitor structure **200b** and interconnection structures **250a** and **250b**.

[0173] The capacitor structure **200b** may be disposed on first and second finger trenches **211a** and **211b** in a substrate **201**. The first electrode structure **210b** may be disposed on the first finger trench **211a**, and the second electrode structure **220b** may be disposed on the second finger trench **211b**.

[0174] In some implementations, the capacitor structure **200b** may be provided on an insulating trench (e.g., the insulating trench **211c** in FIG. **2C**) integrally formed on a front surface of a region in which the capacitor structure **200b** is disposed in the substrate **201**.

[0175] A first lower contact electrode **MC1_1b** and a first intermediate electrode structure **210M** may be sequentially stacked on the first finger trench **211a**. In the drawing, only the first lower contact electrode **MC1_1b** and the first intermediate electrode structure **210M** are illustrated as electrodes of the first electrode structure **210b** on the first finger trench **211a**, but a first intermediate interconnection electrode **ML1_2b** and a first upper interconnection electrode **ML1_3b** may be sequentially stacked on the first intermediate electrode structure **210M**.

[0176] A second lower contact electrode **MC2_1b** and a second intermediate electrode structure **220M** may be sequentially stacked on the second finger trench **211b**. In the drawing, only the second lower contact electrode **MC2_1b** and the second intermediate electrode structure **220M** are illustrated as electrodes of the second electrode structure **220b** on the second finger trench **211b**, but a second intermediate interconnection electrode **ML2_2b** and a second upper interconnection electrode **ML2_3b** may be sequentially stacked on the second intermediate electrode structure **220M**.

[0177] The first lower contact electrode **MC1_1b** may penetrate through a portion of the first finger trench **211a**. A lower surface of the first lower contact electrode **MC1_1b** may penetrate through an upper surface of the first finger trench **211a** and may be buried in the first finger trench **211a**. The lower surface of the first lower contact electrode **MC1_1b** may be disposed on a level lower than that of an upper surface of the first finger trench **211a**, and may be disposed on a level higher than that of a lower surface of the first finger trench **211a**.

[0178] The second lower contact electrode **MC2_1b** may penetrate through a portion of the second finger trench **211b**. A lower surface of the second lower contact electrode **MC2_1b** may penetrate through an upper surface of the second finger trench **211b** and may be buried in the second finger trench **211b**. The lower surface of the second lower contact electrode **MC2_1b** may be disposed on a level lower than that of the upper surface of the second finger trench **211b**, and may be disposed

on a level higher than that of a lower surface of the second finger trench **211b**.

[0179] In some implementations, the first lower contact electrode **MC1_1b** may be disposed on the same level as the upper surface of the first finger trench **211a**. The second lower contact electrode **MC2_1b** may be disposed on the same level as the upper surface of the second finger trench **211b**.

[0180] The first lower contact electrode **MC1_1b** and the second lower contact electrode **MC2_1b** may be provided and/or formed in the same process as first and second contact plugs **251** and **253**. In an example, upper surfaces of the first and second contact plugs **251** and **253** may be disposed on the same level as an upper surface of the first lower contact electrode **MC1_1b** and an upper surface of the second lower contact electrode **MC2_1b**.

[0181] The first and second intermediate electrode structures **210M** and **220M** may be provided and/or formed in the same process as first and second peripheral interconnections **252** and **254**. In an example, upper surfaces of the first and second peripheral interconnections **252** and **254** may be disposed on the same level as upper surfaces of the first and second intermediate electrode structures **210M** and **220M**.

[0182] FIG. 5A is a schematic perspective view illustrating another example of a capacitor structure of a semiconductor device.

[0183] Referring to FIG. 5A, a capacitor structure **200c** may include a first electrode structure **210c** and a second electrode structure **220c**. In an example, first electrodes **ML1_1c**, **ML1_2c** and **ML1_3c** included in the first electrode structure **210c** and second electrodes **ML2_1c**, **ML2_2c** and **ML2_3c** included in the second electrode structure **220c** may be arranged alternately in the first direction (X-direction). In an example, the capacitor structure **200c** may further include an insulating layer (e.g., the peripheral region insulating layer **290** in FIG. 1D) filling a space between the first electrode structure **210c** and the second electrode structure **220c**.

[0184] The first electrode structure **210c** and the second electrode structure **220c** may have different electric potentials. Each of the first electrode structure **210c** and the second electrode structure **220c** may receive an electrical signal through separate interconnections connected to each of the first electrode structure **210c** and the second electrode structure **220c**.

[0185] Each of the first electrode structure **210c** and the second electrode structure **220c** may be provided and/or formed by stacking a plurality of interconnection electrodes having a plate shape.

[0186] The first electrode structure **210c** may include a first lower electrode structure **210L**, a first intermediate interconnection electrode **ML1_2c**, and a first upper interconnection electrode **ML1_3c**, which are sequentially stacked in the third direction (Z-direction).

[0187] The second electrode structure **220c** may include a second lower electrode structure **220L**, a second intermediate interconnection electrode **ML2_2c**, and a second upper interconnection electrode **ML2_3c**, which are sequentially stacked in the third direction (Z-direction).

[0188] The first lower electrode structure **210L** may include a first strap portion **GS1** extending in the first direction (X-direction) and first lower electrodes **ML1_1c** protruding and extending from the first strap portion **GS1** in the second direction (Y-direction).

[0189] The first lower electrodes **ML1_1c** may extend from an upper surface of the first strap portion **GS1** in the third direction (Z-direction). The first lower electrodes **ML1_1c** may have a plate shape extending in the second direction (Y-direction) and the third direction (Z-direction).

[0190] A portion of a lower surface of the first lower electrodes **ML1_1c** may penetrate through the upper surface of the first strap portion **GS1** and may be buried in the first strap portion **GS1**. The lower surface of the first lower electrodes **ML1_1c** may be disposed on a level higher than that of a lower surface of the first strap portion **GS1**, and may be disposed on a level lower than the upper surface of the first strap portion **GS1**. The upper surface of the first lower electrodes **ML1_1c** may be disposed on a level higher than that of the upper surface of the first strap portion **GS1**.

[0191] The first intermediate interconnection electrodes **ML1_2c** and the first upper interconnection electrodes **ML1_3c** may overlap the first lower electrodes **ML1_1c** in the third direction (Z-direction).

[0192] The second lower electrode structure **220L** may include a second strap portion **GS2** extending in the first direction (X-direction) and second lower electrodes **ML2_1c** protruding and extending from the second strap portion **GS2** in the second direction (Y-direction). The second lower electrodes **ML2_1c** may be arranged alternately with the first lower electrodes **ML1_1c** in the first direction (X-direction). In an example, the second strap portion **GS2** may be spaced apart from the first strap portion **GS1** in the second direction (Y-direction).

[0193] A separation distance between the first and second strap portions **GS1** and **GS2** in the second direction (Y-direction) may be substantially equal to a width of the first lower electrodes **ML1_1c** in the second direction (Y-direction) and a width of the second lower electrodes **ML2_1c** in the second direction (Y-direction). However, the present disclosure is not limited thereto, and the separation distance between the first and second strap portions **GS1** and **GS2** in the second direction (Y-direction) may be greater than the width of the first lower electrodes **ML1_1c** in the second direction (Y-direction) and the width of the second lower electrodes **ML2_1c** in the second direction (Y-direction).

[0194] A portion of a lower surface of the second lower electrodes **ML2_1c** may penetrate an upper surface of the second strap portion **GS2** and may be buried in the second strap portion **GS2**. A lower surface of the second lower electrodes **ML1_2c** may be disposed on a level higher than that of a lower surface of the second strap portion **GS2**, and may be disposed on a level lower than the upper surface of the second strap portion **GS2**. An upper surface of the second lower electrodes **ML1_2c** may be disposed on a level higher than that of the upper surface of the second strap portion **GS2**.

[0195] The second intermediate interconnection electrodes **ML2_2c** and the second upper interconnection electrodes **ML2_3c** may overlap the second lower electrodes **ML2_1c** in the third direction (Z-direction). In an example, the second intermediate interconnection electrodes **ML2_2c** may be arranged alternately with the first intermediate interconnection electrodes **ML1_2c** in the first direction (X-direction). The second upper interconnection electrodes **ML2_3c** may be disposed alternately with the first upper interconnection electrodes **ML1_3c** arranged in the first direction (X-direction).

[0196] The first and second intermediate interconnection electrodes **ML1_2c** and **ML2_2c** and the first and second upper interconnection electrodes **ML1_3c** and **ML2_3c** may have a plate shape extending in the second direction (Y-direction) and the third direction (Z-direction).

[0197] FIG. 5B is a plan view illustrating an example of a semiconductor device including the capacitor structure of FIG. 5A. FIG. 5C is a cross-sectional view illustrating an example taken along line I-I' of the semiconductor device of FIG. 5B.

[0198] Referring to FIGS. 5B and 5C, a semiconductor device **10c** may include a capacitor structure **200c**, first and second peripheral interconnections **252** and **254**, third and fourth peripheral interconnections **256** and **258**, and a circuit element **230**.

[0199] The capacitor structure **200c**, the first and second peripheral interconnections **252** and **254**, the third and fourth peripheral interconnections **256** and **258**, and the circuit element **230** may be disposed in the peripheral circuit structure **PERI** as described above with reference to FIGS. 1A to 1D.

[0200] An element isolation region **209**, the first and second peripheral interconnections **252** and **254**, the third and fourth peripheral interconnections **256** and **258** and the circuit element **230** may be disposed in a first region **R1** of the peripheral circuit structure **PERI**. First and second finger trenches **211a** and **211b**, first and second strap trenches **GST1** and **GST2**, and the capacitor structure **200c** may be disposed in a second region **R2** of the peripheral circuit structure **PERI**.

[0201] The element isolation region **209** and impurity regions **205** may be disposed in a substrate **201** in the first region **R1**, and the first and second strap trenches **GST1** and **GST2** and the first and second finger trenches **211a** and **211b** in the substrate **201** may be disposed in the second region **R2**.

[0202] The element isolation region **209** may define an active region inside the substrate **201**. The circuit element **230** may be disposed on the substrate **201** between the element isolation regions **209**. The first and second peripheral interconnections **252** and **254** may be disposed on the substrate **201** on both sides of the circuit element **230**. The first and second peripheral interconnections **252** and **254** may extend in the second direction (Y-direction).

[0203] The impurity regions **205** may be disposed as source/drain regions in the substrate **201** on both sides of the circuit element **230**. The first peripheral interconnection **252** may be connected to the impurity region **205** through a first contact plug **251** disposed in a lower portion of the first peripheral interconnection **252**. The second peripheral interconnection **254** may be connected to the impurity region **205** through a second contact plug **253** disposed in a lower portion of the second peripheral interconnection **254**.

[0204] A height of the first and second contact plugs **251** and **253** in the third direction (Z-direction) may be higher than a height of the first and second peripheral interconnections **252** and **254** in the third direction (Z-direction).

[0205] The circuit element **230** may include a peripheral gate dielectric layer **231** disposed on the substrate **201**, a peripheral gate electrode **232** disposed on the peripheral gate dielectric layer **231**, a peripheral gate capping layer **234** on the peripheral gate electrode **232**, and a peripheral gate dielectric layer **231**, a peripheral gate electrode **232**, and a peripheral gate spacer **233** disposed on a sidewall of the peripheral gate capping layer **234**.

[0206] The peripheral gate dielectric layer **231** may include silicon oxide (SiO₂), SiON, GeON, or GeSiO. The peripheral gate electrode **232** may include a metallic material, for example, tungsten (W). According to some implementations, the peripheral gate electrode **232** may include polycrystalline silicon or a metal silicide material. The peripheral gate capping layer **234** may include an insulating material, such as silicon nitride. The peripheral gate spacer **233** may be formed of an oxide film, a nitride film, an oxynitride film, or a combination thereof. In some implementations, the peripheral gate capping layer **234** may be omitted.

[0207] The circuit element **230** and the impurity region **205** which is a source/drain region may form a peripheral transistor. The circuit element **230** may be referred to as a gate structure in this document.

[0208] The element isolation region **209** may extend in the second direction (Y-direction). The first and second strap trenches GST1 and GST2 may be spaced apart from the element isolation region **209** in the first direction (X-direction), and may extend in the first direction (X-direction). In an example, the first and second strap trenches GST1 and GST2 may be spaced apart from each other in the second direction (Y-direction). The first and second finger trenches **211a** and **211b** may extend between the first and second strap trenches GST1 and GST2 in a second direction (Y-direction). The first and second finger trenches **211a** and **211b** may connect the first and second strap trenches GST1 and GST2.

[0209] The element isolation region **209**, the first and second finger trenches **211a** and **211b**, and the first and second strap trenches GST1 and GST2 may include an insulating material filling the trench structure.

[0210] The first lower electrode structure **210L** may be disposed on the first finger trenches **211a** and the first strap trench GST1. In an example, first lower electrodes ML1_1c may be disposed on the first finger trenches **211a**, and a first strap portion GS1 may be disposed on the first strap trench GST1.

[0211] A second lower electrode structure **220L** may be disposed on the second finger trenches **211b** and the second strap trench GST2. In an example, second lower electrodes ML2_1c may be disposed on the second finger trenches **211b**, and a second strap portion GS2 may be disposed on the second strap trench GST2.

[0212] A height of the first and second strap portions GS1 and GS2 in the vertical direction (Z-direction) may be lower than a height of the first and second lower electrodes ML1_1c and

ML2_1c in the vertical direction (Z-direction).

[0213] The first and second strap portions GS1 and GS2 may have the shape of a strap extending in the first direction (X-direction). In an example, the first and second strap portions GS1 and GS2 may include an insulating layer 31, a conductive layer 32 on the insulating layer 31, and a capping layer 34 on the conductive layer 32. The insulating layer 31, the conductive layer 32 and the capping layer 34 may extend in the first direction (X-direction).

[0214] A portion of a lower surface of the first lower electrodes ML1_1c may penetrate through an upper surface of the first strap portion GS1 and may be connected to a conductive layer 32 of the first strap portion GS1. The first strap portion GS1 may connect the first lower electrodes ML1_1c.

[0215] A portion of a lower surface of the second lower electrodes ML2_1c may penetrate through an upper surface of the second strap portion GS2 and may be connected to a conductive layer 32 of the second strap portion GS2. The second strap portion GS2 may connect the second lower electrodes ML2_1c.

[0216] The first and second lower electrodes ML1_1c and ML2_1c may include a first conductive material, and the first and second strap portions GS1 and GS2 may include a second conductive material different from the first conductive material. For example, the first conductive material may include copper (Cu), and the second conductive material may include a conductive material other than copper (Cu). However, the present disclosure is not limited thereto, and the first and second lower electrodes ML1_1c and ML2_1c may include the same conductive material as the first and second strap portions GS1 and GS2.

[0217] The upper surface of the first and second strap portions GS1 and GS2 may be disposed on the same level as an upper surface of the circuit element 230. In an example, an upper surface of the capping layer 34 of the first and second strap portions GS1 and GS2 may be disposed on the same level as an upper surface of the peripheral gate capping layer 234 of the circuit element 230. An upper surface of the conductive layer 32 of the first and second strap portions GS1 and GS2 may be disposed on the same level as an upper surface of the peripheral gate electrode 232 of the circuit element 230. An upper surface of the insulating layer 31 of the first and second strap portions GS1 and GS2 may be disposed on the same level as an upper surface of the peripheral gate dielectric layer 231 of the circuit element 230.

[0218] The first and second strap portions GS1 and GS2 may be provided and/or formed in the same process as the circuit element 230. In an example, the insulating layer 31 of the first and second strap portions GS1 and GS2 may include the same material as the peripheral gate dielectric layer 231 of the circuit element 230. The conductive layer 32 of the first and second strap portions GS1 and GS2 may include the same material as the peripheral gate electrode 232 of the circuit element 230. In an example, the capping layer 34 of the first and second strap portions GS1 and GS2 may include the same material as the peripheral gate capping layer 234 of the circuit element 230. However, the present disclosure is not limited thereto. In an example, the first and second strap portions GS1 and GS2 may be formed in a process different from that of the circuit element 230, and the first and second strap portions GS1 and GS2 may include a material different from that of the circuit element 230.

[0219] The first and second strap portions GS1 and GS2 may extend from the second region R2 to the first region R1. For example, the first and second strap portions GS1 and GS2 may extend to an area adjacent to the circuit element 230.

[0220] A third contact plug 255, a fourth contact plug 257, a third peripheral interconnection 256 disposed on the third contact plug 255, and a fourth peripheral interconnection 258 disposed on the fourth contact plug 257 may be disposed on the first and second strap portions GS1 and GS2 extending toward the first region R1. In an example, a third-first contact plug 255a may be disposed on the first strap portion GS1 extending toward the first region R1. A fourth-first contact plug 257a may be disposed on the second strap portion GS2 extending toward the first region R1. A third peripheral interconnection 256 may be disposed on the third-first contact plug

255a. A fourth peripheral interconnection **258** may be disposed on the fourth-first contact plug **257a**.

[0221] The first lower electrodes **ML1_1c** may be electrically connected to the circuit element **230** through the third-first contact plug **255a** and the third peripheral interconnection **256**. That is, a first signal may be applied to the first lower electrodes **ML1_1c** through the third-first contact plug **255a** and the third peripheral interconnection **256**.

[0222] The second lower electrodes **ML2_1c** may be electrically connected to the circuit element **230** through the fourth-first contact plug **257a** and the fourth peripheral interconnection **258**. That is, a second signal having a potential different from the first signal may be applied to the second lower electrodes **ML2_1c** through the fourth-first contact plug **257a** and the fourth peripheral interconnection **258**.

[0223] The third-first contact plug **255a** may penetrate through the upper surface of the first strap portion **GS1** and may be connected to the conductive layer **32** of the first strap portion **GS1**. A lower surface of the third contact plug **255a** may be disposed on a level lower than that of the upper surface of the first strap portion **GS1**. A lower surface of the fourth-first contact plug **257a** may be disposed on a level lower than that of the upper surface of the second strap portion **GS2**.

[0224] The third peripheral interconnection **256** and the fourth peripheral interconnection **258** may extend in the second direction (Y-direction) and may be spaced apart from each other in the second direction (Y-direction).

[0225] The third and fourth peripheral interconnections **256** and **258** may be formed in the same process as the first and second peripheral interconnections **252** and **254**. The third contact plug **255a** and the fourth contact plug **257a** may be formed in the same process as the first and second contact plugs **251** and **253**.

[0226] The semiconductor device **10c** may the first and second strap portions provided in the same process as the circuit element, the first lower electrodes connected through the first strap portion, and a capacitor structure including second lower electrodes arranged alternately with the first lower electrodes and connected through a second strap portion. Accordingly, the semiconductor device may form a routing interconnection applied to the capacitor structure through the first and second strap portions extending between the peripheral interconnection and the lower electrode, the semiconductor device with improved integration may be provided.

[0227] FIGS. **6A**, **6B**, and **6C** are views illustrating an example of a method of manufacturing the semiconductor device of FIG. **5B**.

[0228] Referring to FIG. **6A**, a method of manufacturing a semiconductor device may include an operation of forming an element isolation region **209** in a substrate **201**, first and second strap trenches **GST1** and **GST2**, and first and second finger trenches **211a** and **211b** between the first and second strap trenches **GST1** and **GST2**.

[0229] The element isolation region **209** and first and second finger trenches **211a** and **211b** spaced apart from the element isolation region **209** in the first direction (X-direction) may be formed in the substrate **201**. The first and second finger trenches **211a** and **211b** may be alternately arranged in the first direction (X-direction).

[0230] The element isolation region **209** and the first and second finger trenches **211a** and **211b** may be formed in a shallow trench isolation (STI) process. The shallow trench isolation process may be a process of forming isolation trenches in the substrate **201** and filling the isolation trenches with an insulating material such as silicon oxide.

[0231] The first and second strap trenches **GST1** and **GST2** extending in the first direction (X-direction) between the element isolation region **209** and the first and second finger trenches **211a** and **211b** in the substrate **201** may be formed through the shallow trench isolation process. In an example, the first and second strap trenches **GST1** and **GST2** may be formed to extend from the second region **R2** to the first region **R1**. For example, the first and second strap trenches **GST1** and **GST2** may be formed to extend from the second region **R2** to a region adjacent to the element

isolation region **209** of the first region **R1**.

[0232] Referring to FIG. **6B**, a method of manufacturing a semiconductor device may include an operation of forming the first strap portion **GS1** on the first strap trench **GST1**, and forming the second strap portion **GS2** on the second strap portion **GST2**.

[0233] The first strap portion **GS1** may be formed to overlap the first strap trench **GST1** and extend in the first direction (X-direction). The second strap portion **GS2** may be formed to overlap the second strap trench **GST2** and extend in the first direction (X-direction). In an example, a process of forming the first and second strap portions **GS1** and **GS2** may include a process of sequentially forming an insulating layer **31**, a conductive layer **32**, and a capping layer **34**.

[0234] The first and second strap portions **GS1** and **GS2** may be formed in the same process as the circuit element (e.g., the circuit element **230** of FIG. **5C**).

[0235] Referring to FIG. **6C**, a method of manufacturing a semiconductor device includes an operation of forming first lower electrodes **ML1_1c** on the first strap portion **GS1** and second lower electrodes **ML2_1c** on the second strap portion **GS2**.

[0236] The first lower electrodes **ML1_1c** and the second lower electrodes **ML2_1c** may be formed to have a plate shape in which the first lower electrodes **ML1_1c** and the second lower electrodes **ML2_1c** are alternated in the first direction (X-direction) and extend in the second direction (Y-direction) and the third direction (Z-direction). In an example, the first and second lower electrodes **ML1_1c** and **ML2_1c** may be formed in a damascene process.

[0237] The first lower electrodes **ML1_1c** may be formed on first finger trenches **211a**, and the second lower electrodes **ML2_1c** may be formed on second finger trenches **211b**.

[0238] The first strap portion **GS1** and the first lower electrodes **ML1_1c** connected through the first strap portion **GS1** may form a first lower electrode structure **210L** of a capacitor structure **200c**. The second strap portion **GS2** and the second lower electrodes **ML2_1c** connected through the second strap portion **GS2** may form a second lower electrode structure **220L** of the capacitor structure **200c**.

[0239] The method of manufacturing a semiconductor device may include an operation of forming first contact structures **255** and **256** on the first strap portion **GS1**, and forming second contact structures **257** and **258** on the second strap portion **GS2**.

[0240] First contact structures **255** and **256** and second contact structures **257** and **258** may be formed in a region between the element isolation region **209** and the first and second lower electrodes **ML1_1c** and **ML2_1c**.

[0241] The first contact structures **255** and **256** may include a third contact plug **255** and a third peripheral interconnection **256** formed on the third contact plug **255**. The third contact plug **255** may include a third-first contact plug **255a** disposed on the first strap portion **GS1** and a third-two contact plug **255b** spaced apart from the third-first contact plug **255a** in the second direction (Y-direction). The third-two contact plug **255b** may be connected to a circuit element (e.g., the circuit element **230** of FIG. **5C**). The third peripheral interconnection **256** may be formed in the form of a line extending in the second direction (Y-direction) on the third contact plug **255**.

[0242] The second contact structures **257** and **258** may include a fourth contact plug **257** and a fourth peripheral interconnection **258** formed on the fourth contact plug **257**. The fourth contact plug **257** may include a fourth-first contact plug **257a** disposed on the second strap portion **GS2** and a fourth-second contact plug **257b** spaced apart from the fourth-first contact plug **257a** in the second direction (Y-direction). The fourth-second contact plug **257b** may be connected to a circuit element (e.g., the circuit element **230** of FIG. **5B**). The fourth peripheral interconnection **258** may be formed in the form of a line extending in the second direction (Y-direction) on the fourth contact plug **257**.

[0243] The method of manufacturing a semiconductor device may include forming the first and second strap portions in the same process as the circuit element, and forming first lower electrodes connected through the first strap portion and second lower electrodes disposed alternately with the

first lower electrodes and connected through the second strap portion, thereby manufacturing the capacitor structure. Accordingly, the first and second strap portions, which are routing interconnections of the capacitor structure, may be formed using the existing circuit element manufacturing process, thereby increasing the integration of the semiconductor device and improve manufacturing process efficiency.

[0244] FIG. 7 is a view schematically illustrating an example of a data storage system including a semiconductor device.

[0245] Referring to FIG. 7, a data storage system **1000** may include a semiconductor device **1100** and a controller **1200** electrically connected to the semiconductor device **1100**. The data storage system **1000** may be a storage device including one or a plurality of semiconductor devices **1100** or an electronic device including the storage device. For example, the data storage system **1000** may be a solid state drive device (SSD) device, a universal serial bus (USB) device, a computing system, a medical device, or a communication device, including one or a plurality of semiconductor devices **1100**.

[0246] The semiconductor device **1100** may be a non-volatile memory device, for example, the NAND flash memory device described above with reference to FIGS. 1A to 1E. The semiconductor device **1100** may include a first structure **1100F** and a second structure **1100S** on the first structure **1100F**. In some implementations, the first structure **1100F** may be disposed next to the second structure **1100S**. The first structure **1100F** may be a peripheral circuit structure including a decoder circuit **1110**, a page buffer **1120**, and a logic circuit **1130**. The second structure **1100S** may be a memory cell structure including a bit line BL, a common source line CSL, word lines WL, first and second gate upper lines UL1 and UL2, first and second gate lower lines LL1 and LL2, and memory cell strings CSTR between the bit line BL and the common source line CSL.

[0247] In the second structure **1100S**, each of the memory cell strings CSTR may include lower transistors LT1 and LT2 adjacent to the common source line CSL, upper transistors UT1 and UT2 adjacent to the bit line BL, and a plurality of memory cell transistors MCT disposed between the lower transistors LT1 and LT2 and the upper transistors UT1 and UT2. The number of lower transistors LT1 and LT2 and the number of upper transistors UT1 and UT2 may be variously modified according to some implementations.

[0248] In some implementations, the upper transistors UT1 and UT2 may include a string select transistor, and the lower transistors LT1 and LT2 may include a ground selection transistor. The gate lower lines LL1 and LL2 may be gate electrodes of the lower transistors LT1 and LT2, respectively. The word lines WL may be gate electrodes of the memory cell transistors MCT, and the gate upper lines UL1 and UL2 may be gate electrodes of the upper transistors UT1 and UT2, respectively.

[0249] In some implementations, the lower transistors LT1 and LT2 may include a lower erase control transistor LT1 and a ground selection transistor LT2 connected in series. The upper transistors UT1 and UT2 may include a string select transistor UT1 and an upper erase control transistor UT2 connected in series. At least one of the lower erase control transistor LT1 and the upper erase control transistor UT2 may be used in an erase operation to delete data stored in the memory cell transistors MCT using a GIDL phenomenon.

[0250] The common source line CSL, the first and second gate lower lines LL1 and LL2, the word lines WL, and the first and second gate upper lines UL1 and UL2 may be electrically connected to the decoder circuit **1110** through first connection interconnections **1115** extending to the second structure **1100S** in the first structure **1100F**. The bit lines BL may be electrically connected to the page buffer **1120** through second connection interconnections **1125** extending to the second structure **1100S** in the first structure **1100F**.

[0251] In the first structure **1100F**, the decoder circuit **1110** and the page buffer **1120** may perform a control operation on at least one selected memory cell transistor among the plurality of memory cell transistors MCT. The decoder circuit **1110** and page buffer **1120** may be controlled by the logic

circuit **1130**. The semiconductor device **1100** may communicate with the controller **1200** through the input/output pad **1101** electrically connected to the logic circuit **1130**. The input/output pad **1101** may be electrically connected to the logic circuit **1130** through an input/output connection interconnection **1135** extending to the second structure **1100S** in the first structure **1100F**.

[0252] The controller **1200** may include a processor **1210**, a NAND controller **1220**, and a host interface **1230**. According to some implementations, the data storage system **1000** may include a plurality of semiconductor devices **1100**, and in this case, the controller **1200** may control a plurality of semiconductor devices **1100**.

[0253] The processor **1210** may control an overall operation of the data storage system **1000**, including the controller **1200**. The processor **1210** may operate according to predetermined firmware, and may control the NAND controller **1220** to access the semiconductor device **1100**. The NAND controller **1220** may include a controller interface **1221** configured to process communication with the semiconductor device **1100**. Through the controller interface **1221**, control commands for controlling the semiconductor device **1100**, data to be recorded in the memory cell transistors (MCT) of the semiconductor device **1100**, and data to be read from the memory cell transistors MCT of the semiconductor device **1100** may be transmitted. The host interface **1230** may provide a communication function between the data storage system **1000** and an external host. When receiving a control command from the external host through the host interface **1230**, the processor **1210** may control the semiconductor device **1100** in response to control commands.

[0254] While this specification contains many specific implementation details, these should not be construed as limitations on the scope of any invention or on the scope of what may be claimed, but rather as descriptions of features that may be specific to particular implementations of particular inventions. Certain features that are described in this specification in the context of separate implementations can also be implemented in combination in a single implementation. Conversely, various features that are described in the context of a single implementation can also be implemented in multiple implementations separately or in any suitable subcombination. Moreover, although features may be described above as acting in certain combinations, one or more features from a combination can in some cases be excised from the combination, and the combination may be directed to a subcombination or variation of a subcombination.

[0255] While example implementations have been illustrated and described above, it will be apparent to those skilled in the art that modifications and variations could be made within a scope not departing from the spirit and region of the present disclosure as defined by the appended claims.

Claims

1. A semiconductor device, comprising: a first semiconductor structure including a substrate, an active region within the substrate, a plurality of circuit elements on the substrate, an element isolation region defining the active region, a plurality of impurity regions disposed within the active region on both sides of the plurality of circuit elements, an interconnection structure electrically connected with the plurality of circuit elements, and a capacitor structure spaced apart from the interconnection structure in a first direction; and a second semiconductor structure including a plate layer disposed on the first semiconductor structure, a plurality of gate electrodes sequentially stacked and spaced apart from each other in a perpendicular direction on the plate layer, and a plurality of channel structures, the perpendicular direction being perpendicular to an upper surface of the plate layer, and the plurality of channel structures extending through the plurality of gate electrodes in the perpendicular direction, wherein the capacitor structure includes: a first electrode structure including a first strap portion and a plurality of first electrodes, the first strap portion disposed on the substrate, the first electrode structure extending in the first direction, the plurality of first electrodes extending from the first strap portion in a second direction, the

second direction intersecting the first direction; and a second electrode structure including a second strap portion and a plurality of second electrodes, the second strap portion extending on the substrate in the first direction and spaced apart from the first strap portion in the second direction, the plurality of second electrodes extending from the second strap portion in the second direction and arranged alternately with the plurality of first electrodes, wherein the plurality of first electrodes have a plate shape extending from an upper surface of the first strap portion in a vertical direction, the vertical direction intersecting the first direction and the second direction, and wherein the plurality of second electrodes have a plate shape extending from an upper surface of the second strap portion in the vertical direction.

2. The semiconductor device of claim 1, wherein each circuit element of the plurality of circuit elements includes a gate structure and a gate electrode, the gate structure including a gate insulating layer on the substrate, and the gate electrode being on the gate insulating layer, wherein the first strap portion and the second strap portion include an insulating layer extending in the first direction and a conductive layer on the insulating layer, and wherein an upper surface of the first strap portion and an upper surface of the second strap portion are disposed on substantially the same level as an upper surface of the gate structure.

3. The semiconductor device of claim 1, wherein the first strap portion and the second strap portion include a first conductive material, and the plurality of first electrodes and the plurality of second electrodes include a second conductive material different from the first conductive material.

4. The semiconductor device of claim 1, wherein the interconnection structure includes a first contact structure and a second contact structure, the first contact structure electrically connected with the first electrode structure and the second contact structure electrically connected with the second electrode structure, wherein the first contact structure includes a first contact plug and a first contact line, the first contact plug disposed on the first strap portion and the first contact line extending on the first contact plug in the second direction, and wherein the second contact structure includes a second contact plug and a second contact line, the second contact plug disposed on the second strap portion and the second contact line extending on the second contact plug in the second direction.

5. The semiconductor device of claim 1, wherein a lower surface of the plurality of first electrodes extends through a portion of the first strap portion and faces a lower surface of the first strap portion, and wherein a lower surface of the plurality of second electrodes extends through a portion of the second strap portion and faces a lower surface of the second strap portion.

6. The semiconductor device of claim 1, comprising: a first strap trench extending within the substrate in the first direction and overlapping the first strap portion; a second strap trench extending within the substrate in the first direction, spaced apart from the first strap trench in the second direction, and overlapping the second strap portion; and at least one finger trench extending between the first strap trench and the second strap trench within the substrate in the second direction, the at least one finger trench connecting the first strap trench and the second strap trench, and the at least one finger trench overlapping the plurality of first electrodes and the plurality of second electrodes, wherein the first strap trench, the second strap trench, and the at least one finger trench are filled with an insulating material.

7. The semiconductor device of claim 6, wherein the at least one finger trench includes a first finger trench and a second finger trench, the first finger trench overlapping each of the plurality of first electrodes, and the second finger trench overlapping each of the plurality of second electrodes and spaced apart from the first finger trench in the first direction.

8. The semiconductor device of claim 6, wherein an upper surface of the at least one finger trench is disposed on the same level as an upper surface of the element isolation region.

9. The semiconductor device of claim 1, wherein the interconnection structure includes a third contact plug and a third contact interconnection, the third contact plug disposed on an impurity region and the third contact interconnection disposed on the third contact plug and extending in the

second direction, and wherein an upper surface of the third contact interconnection is disposed on a level higher than a level of an upper surface of the plurality of first electrodes and a level of an upper surface of the plurality of second electrodes.

10. The semiconductor device of claim 1, wherein the first electrode structure includes a plurality of first intermediate electrodes disposed on the plurality of first electrodes and a plurality of first upper electrodes disposed on the plurality of first intermediate electrodes, wherein the second electrode structure includes second intermediate electrodes disposed on the second electrodes and second upper electrodes disposed on the second intermediate electrodes, wherein the first intermediate electrodes and the second intermediate electrodes are spaced apart from each other in the first direction and alternately arranged, and have a plate shape extending in the vertical direction, and wherein the first upper electrodes and the second upper electrodes are spaced apart from each other in the first direction and alternately arranged, and have the plate shape extending in the vertical direction.

11. The semiconductor device of claim 1, wherein a separation distance between the first strap portion and the second strap portion in the second direction is substantially equal to a width of the first electrodes in the second direction.

12. A semiconductor device, comprising: a substrate including an active region; a plurality of circuit elements on the active region; an element isolation region defining the active region; a plurality of impurity regions disposed within the active region on both sides of the plurality of circuit elements; a capacitor structure spaced apart from the plurality of circuit elements; and a first finger trench spaced apart from the plurality of circuit elements and extending within the substrate in a first direction, and a second finger trench extending in the first direction and arranged alternately with the first finger trench, wherein the capacitor structure includes: a plurality of first lower electrodes disposed on the first finger trench; and a plurality of second lower electrodes disposed on the second finger trench and arranged alternately with the plurality of first lower electrodes, wherein the plurality of first lower electrodes and the plurality of second lower electrodes have a plate shape extending in the first direction and a vertical direction, the vertical direction intersecting the first direction, and wherein an upper surface of the first finger trench and an upper surface of the second finger trench are disposed on the same level as an upper surface of the element isolation region.

13. The semiconductor device of claim 12, wherein the first finger trench and the second finger trench are arranged alternately at a plurality of regular intervals.

14. The semiconductor device of claim 12, wherein a lower surface of the plurality of first lower electrodes and a lower surface of the plurality of second lower electrodes are disposed on a level lower than a level of the upper surface of the first finger trench and a level of the upper surface of the second finger trench.

15. The semiconductor device of claim 12, comprising: a first intermediate interconnection disposed on the plurality of first lower electrodes; and a second intermediate interconnection disposed on the plurality of second lower electrodes, wherein a height of the first intermediate interconnection and the second intermediate interconnection in the vertical direction is lower than a height of the plurality of first lower electrodes and the plurality of second lower electrodes in the vertical direction.

16. The semiconductor device of claim 12, comprising: an interconnection structure electrically connected with the plurality of circuit elements, wherein the interconnection structure includes a third contact plug and a third contact line, the third contact plug disposed on the impurity region and the third contact line disposed on the third contact plug and extending in the first direction, and wherein an upper surface of the third contact line is disposed on a level higher than a level of an upper surface of the plurality of first lower electrodes and a level of an upper surface of the plurality of second lower electrodes.

17. The semiconductor device of claim 12, comprising: a first intermediate electrode structure

disposed on the plurality of first lower electrodes; and a second intermediate electrode structure disposed on the plurality of second lower electrodes, wherein the first intermediate electrode structure includes a first connection portion and a plurality of first intermediate electrodes, the first connection portion extending in a second direction, the second direction intersecting the first direction, and the plurality of first intermediate electrodes extending from the first connection portion in the first direction and overlapping the plurality of first lower electrodes, and wherein the second intermediate electrode structure includes a second connection portion and a plurality of second intermediate electrodes, the second connection portion extending in the second direction, and the plurality of second intermediate electrodes extending from the second connection portion in the first direction and overlapping the plurality of second lower electrodes.

18. The semiconductor device of claim 12, comprising: a first strap portion extending on the substrate in a second direction, the second direction intersecting the first direction, and the first strap portion connecting the plurality of first lower electrodes; and a second strap portion extending in the second direction, connecting the plurality of second lower electrodes, and spaced apart from the first strap portion in the first direction, wherein the plurality of first lower electrodes extend in the vertical direction through a portion of an upper surface of the first strap portion, and wherein the plurality of second lower electrodes extend in the vertical direction through a portion of an upper surface of the second strap portion.

19. A semiconductor device, comprising: a substrate including an active region; a plurality of circuit elements including a gate structure on the active region; an element isolation region defining the active region; a plurality of impurity regions disposed within the active region on both sides of the plurality of circuit elements; and a capacitor structure spaced apart from the plurality of circuit elements, wherein the capacitor structure includes: a first electrode structure including a first strap portion and a plurality of first electrodes, the first strap portion disposed on the substrate and extending in a first direction, and the plurality of first electrodes extending from the first strap portion in a second direction, the second direction intersecting the first direction; and a second electrode structure including a second strap portion and a plurality of second electrodes, the second strap portion extending on the substrate in the first direction and spaced apart from the first strap portion in the second direction, and the plurality of second electrodes extending from the second strap portion in the second direction and arranged alternately with the plurality of first electrodes, wherein an upper surface of the first strap portion and an upper surface of the second strap portion are disposed on at the same level as an upper surface of the gate structure.

20. The semiconductor device of claim 19, comprising: a first contact structure electrically connected with the first electrode structure and a second contact structure electrically connected with the second electrode structure, wherein the first contact structure includes a first contact plug and a first contact line, the first contact plug disposed on the first strap portion and the first contact line extending on the first contact plug in the second direction, and wherein the second contact structure includes a second contact plug and a second contact line, the second contact plug disposed on the second strap portion and the second contact line extending on the second contact plug in the second direction.
