

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12414123
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Takeda; Kazuki et al.

Number of BD and CCE for cross-carrier scheduling from an S-Cell to a P-Cell

Abstract

This disclosure provides systems, devices, apparatus, and methods, including computer programs encoded on storage media, for determining numbers of BDs and CCEs for cross-carrier scheduling from a SCell to a PCell/PCell. A UE may concurrently monitor, on different component carriers, a first PDCCH and a second PDCCH having different SCSs. The PDCCHs may each be configured to schedule PDSCH or PUSCH on a same component carrier of the different component carriers. Each of the PDCCHs may be associated with a respective number of PDCCH candidates or a respective number of non-overlapped CCEs, the respective numbers further associated with respective maximum numbers based on the different SCSs. A first sum of the respective number of PDCCH candidates or a second sum of the non-overlapped CCEs may be less than or equal to N times the lower of the respective maximum numbers.

Inventors: Takeda; Kazuki (Tokyo, JP), Xu; Huilin (Temecula, CA), Gaal; Peter (San Diego, CA)

Applicant: QUALCOMM Incorporated (San Diego, CA)

Family ID: 80114155

Assignee: QUALCOMM Incorporated (San Diego, CA)

Appl. No.: 17/356458

Filed: June 23, 2021

Prior Publication Data

Document Identifier	Publication Date
US 20220046683 A1	Feb. 10, 2022

Related U.S. Application Data

Publication Classification

Int. Cl.: **H04W72/23** (20230101); **H04L27/26** (20060101); **H04W24/08** (20090101);
H04W72/0453 (20230101); **H04W72/1273** (20230101)

U.S. Cl.:

CPC **H04W72/23** (20230101); **H04L27/26025** (20210101); **H04W24/08** (20130101);
H04W72/0453 (20130101); **H04W72/1273** (20130101);

Field of Classification Search

CPC: H04W (72/23)

References Cited**U.S. PATENT DOCUMENTS**

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2012/0218969	12/2011	Tan	370/329	H04L 5/0051
2015/0327223	12/2014	Zhang	370/329	H04W 72/23
2019/0223164	12/2018	He	N/A	H04W 76/27
2021/0058189	12/2020	Xiao	N/A	H04L 5/0042
2021/0136770	12/2020	Nakashima	N/A	H04W 72/0453
2021/0377996	12/2020	Lee	N/A	H04L 5/001
2023/0077644	12/2022	Shi	N/A	H04L 5/0053
2023/0080720	12/2022	Yoon	N/A	H04W 72/0453

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
104126328	12/2013	CN	N/A
104823395	12/2014	CN	N/A
108886457	12/2017	CN	N/A
110474737	12/2018	CN	N/A
3780468	12/2020	EP	N/A
2013526116	12/2012	JP	N/A
2019214596	12/2018	WO	N/A

OTHER PUBLICATIONS

CMCC: “Discussion on Remaining Issues for PDCCH and Search Space”, 3GPP TSG RAN WG1 Meeting #94, 3GPP Draft, R1-1808833, 3rd Generation Partnership Project (3GPP), Mobile Competence Centre, 650, Route Des Lucioles, F-06921 Sophia-Antipolis Cedex, France, vol. RAN WG1, No. Gothenburg, Sweden, Aug. 20, 2018-Aug. 24, 2018, 3 Pages, Aug. 11, 2018 (Aug. 11, 2018), XP051516206, Retrieved from the Internet: URL:

<http://www.3gpp.org/ftp/tsg%5Fran/WG1%5FRL1/TSGR1%5F94/Docs/R1%2D1808833%2Ezip> [retrieved on Aug. 11, 2018] sections 1-4. cited by applicant

International Search Report and Written Opinion—PCT/US2021/038986—ISA/EPO—dated Oct. 11, 2021. cited by applicant

Primary Examiner: Mattis; Jason E

Attorney, Agent or Firm: Procopio, Cory, Hargreaves & Savitch

Background/Summary

CROSS REFERENCE TO RELATED APPLICATION(S) (1) This application claims the benefit of and priority to U.S. Provisional Application Ser. No. 63/062,607, entitled "Number of BD and CCE for Cross-Carrier Scheduling from a S-Cell to a P-Cell" and filed on Aug. 7, 2020, which is expressly incorporated by reference herein in its entirety.

TECHNICAL FIELD

(1) The present disclosure relates generally to communication systems, and more particularly, to numbers of blind decodings (BDs) and control channel elements (CCEs) for cross-carrier scheduling from a secondary cell (SCell) to a primary cell (PCell)/primary-secondary cell (PSCell).

INTRODUCTION

(2) Wireless communication systems are widely deployed to provide various telecommunication services such as telephony, video, data, messaging, and broadcasts. Typical wireless communication systems may employ multiple-access technologies capable of supporting communication with multiple users by sharing available system resources. Examples of such multiple-access technologies include code division multiple access (CDMA) systems, time division multiple access (TDMA) systems, frequency division multiple access (FDMA) systems, orthogonal frequency division multiple access (OFDMA) systems, single-carrier frequency division multiple access (SC-FDMA) systems, and time division synchronous code division multiple access (TD-SCDMA) systems.

(3) These multiple access technologies have been adopted in various telecommunication standards to provide a common protocol that enables different wireless devices to communicate on a municipal, national, regional, and even global level. An example telecommunication standard is 5G New Radio (NR). 5G NR is part of a continuous mobile broadband evolution promulgated by Third Generation Partnership Project (3GPP) to meet new requirements associated with latency, reliability, security, scalability (e.g., with Internet of Things (IoT)), and other requirements. 5G NR includes services associated with enhanced mobile broadband (eMBB), massive machine type communications (mMTC), and ultra-reliable low latency communications (URLLC). Some aspects of 5G NR may be based on the 4G Long Term Evolution (LTE) standard. There exists a need for further improvements in 5G NR technology. These improvements may also be applicable to other multi-access technologies and the telecommunication standards that employ these technologies.

BRIEF SUMMARY

(4) The following presents a simplified summary of one or more aspects in order to provide a basic understanding of such aspects. This summary is not an extensive overview of all contemplated aspects, and is intended to neither identify key or critical elements of all aspects nor delineate the scope of any or all aspects. Its sole purpose is to present some concepts of one or more aspects in a simplified form as a prelude to the more detailed description that is presented later.

(5) In cross-carrier scheduling operations, data may be scheduled from a SCell to either a PCell or a PSCell. In some cases, cross-carrier scheduling may be associated with two scheduling cells that are configured to schedule data on a same PCell/PSCell. While such techniques may increase a number of physical downlink control channel (PDCCH) candidates that may schedule data on the

PCell/PSCell, processing capabilities of a user equipment (UE) may limit the number of PDCCH candidates that the UE may be configured to process.

(6) Accordingly, a total number of PDCCH candidates to be received from the SCell and the PCell/PSCell may need to be regulated based on the processing capabilities of the UE. In a first aspect, e.g., where the SCell and the PCell/PSCell use different numerologies, the maximum number of PDCCH candidates may be based on a predefined budget for the component carrier (CC) with the lowest subcarrier spacing (SCS). That is, the total budget across both CCs may not exceed the budget associated with the lowest SCS. In a second aspect, the maximum number of PDCCH candidates may be counted separately per cell. UE capability information reported to the network may indicate whether the UE is configured to process the number of PDCCH candidates associated with the respective CCs.

(7) In an aspect of the disclosure, a method, a computer-readable medium, and an apparatus are provided. The apparatus may be a UE that includes a memory and at least one processor coupled to the memory. The memory may include instructions that, when executed by the at least one processor, cause the at least one processor to monitor a first PDCCH on a first CC, the first PDCCH being configured to schedule one of a first physical downlink shared channel (PDSCH) or a first physical uplink shared channel (PUSCH) on a second CC, the first PDCCH having a first subcarrier spacing, the first PDCCH in association with the scheduling of the at least one of the first PDSCH or the first PUSCH on the second CC being associated with at least one of a first number of PDCCH candidates or a first number of non-overlapped CCEs, the first PDCCH having a first maximum number in association with the at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs based on the first subcarrier spacing; and monitor a second PDCCH on a second CC different than the first CC concurrently with the monitoring of the first PDCCH, the second PDCCH being configured to schedule one of a second PDSCH or a second PUSCH on the second CC, the second PDCCH having a second subcarrier spacing less than or equal to the first subcarrier spacing, the second PDCCH in association with the scheduling of the at least one of the second PDSCH or the second PUSCH on the second CC being associated with at least one of a second number of PDCCH candidates or a second number of non-overlapped CCEs, the second PDCCH having a second maximum number in association with the at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs based on the second subcarrier spacing, where at least one of a first sum of the first number of PDCCH candidates and the second number of PDCCH candidates is less than or equal to N times the second maximum number in association with the second number of PDCCH candidates, or a second sum of the first number of non-overlapped CCEs and the second number of non-overlapped CCEs is less than or equal to N times the second maximum number in association with the second number of non-overlapped CCEs.

(8) In an aspect of the disclosure, a method, a computer-readable medium, and an apparatus are provided. The apparatus may be a base station that includes a memory and at least one processor coupled to the memory. The memory may include instructions that, when executed by the at least one processor, cause the at least one processor to configure a first PDCCH on a first CC for a UE, the first PDCCH being configured to schedule one of a first physical downlink shared channel (PDSCH) or a first PUSCH on a second CC, the first PDCCH having a first subcarrier spacing, the first PDCCH in association with the scheduling of the at least one of the first PDSCH or the first PUSCH on the second CC being associated with at least one of a first number of PDCCH candidates or a first number of non-overlapped CCEs, the first PDCCH having a first maximum number in association with the at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs based on the first subcarrier spacing; configure a second PDCCH on a second CC different than the first CC, the second PDCCH being configured to schedule one of a second PDSCH or a second PUSCH on the second CC, the second PDCCH being concurrent with the first PDCCH, the second PDCCH having a second subcarrier spacing less than or equal to the

first subcarrier spacing; the second PDCCH in association with the scheduling of the at least one of the second PDSCH or the second PUSCH on the second CC being associated with at least one of a second number of PDCCH candidates or a second number of non-overlapped CCEs, the second PDCCH having a second maximum number in association with the at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs based on the second subcarrier spacing; and transmit, on at least one of the first PDCCH or the second PDCCH, downlink control information (DCI) scheduling one of the first PDSCH, the first PUSCH, the second PDSCH, or the second PUSCH on the second CC, the DCI being associated with at least one of a first sum of the first number of PDCCH candidates and the second number of PDCCH candidates is less than or equal to N times the second maximum number in association with the second number of PDCCH candidates, or a second sum of the first number of non-overlapped CCEs and the second number of non-overlapped CCEs is less than or equal to N times the second maximum number in association with the second number of non-overlapped CCEs.

(9) To the accomplishment of the foregoing and related ends, the one or more aspects comprise the features hereinafter fully described and particularly pointed out in the claims. The following description and the annexed drawings set forth in detail certain illustrative features of the one or more aspects. These features are indicative, however, of but a few of the various ways in which the principles of various aspects may be employed, and this description is intended to include all such aspects and their equivalents.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a diagram illustrating an example of a wireless communications system and an access network.
- (2) FIG. 2A is a diagram illustrating an example of a first frame, in accordance with various aspects of the present disclosure.
- (3) FIG. 2B is a diagram illustrating an example of DL channels within a subframe, in accordance with various aspects of the present disclosure.
- (4) FIG. 2C is a diagram illustrating an example of a second frame, in accordance with various aspects of the present disclosure.
- (5) FIG. 2D is a diagram illustrating an example of UL channels within a subframe, in accordance with various aspects of the present disclosure.
- (6) FIG. 3 is a diagram illustrating an example of a base station and user equipment (UE) in an access network.
- (7) FIG. 4 is a call flow diagram illustrating communications between a UE and a base station.
- (8) FIG. 5 is a diagram illustrating cross-carrier scheduling from a secondary cell (SCell) to a primary cell (PCell).
- (9) FIGS. 6A-6B illustrate diagrams associated with determining a number of physical downlink control channel (PDCCH) blind decodings (BDs) and non-overlapping control channel elements (CCEs).
- (10) FIG. 7 is a flowchart of a method of wireless communication to be performed at a UE.
- (11) FIG. 8 is a flowchart of a method of wireless communication to be performed at a base station.
- (12) FIG. 9 is a diagram illustrating an example of a hardware implementation for an example apparatus.
- (13) FIG. 10 is a diagram illustrating an example of a hardware implementation for an example apparatus.

DETAILED DESCRIPTION

- (14) The detailed description set forth below in connection with the appended drawings is intended

as a description of various configurations and is not intended to represent the only configurations in which the concepts described herein may be practiced. The detailed description includes specific details for the purpose of providing a thorough understanding of various concepts. However, it will be apparent to those skilled in the art that these concepts may be practiced without these specific details. In some instances, well known structures and components are shown in block diagram form in order to avoid obscuring such concepts.

(15) Several aspects of telecommunication systems will now be presented with reference to various apparatus and methods. These apparatus and methods will be described in the following detailed description and illustrated in the accompanying drawings by various blocks, components, circuits, processes, algorithms, etc. (collectively referred to as “elements”). These elements may be implemented using electronic hardware, computer software, or any combination thereof. Whether such elements are implemented as hardware or software depends upon the particular application and design constraints imposed on the overall system.

(16) By way of example, an element, or any portion of an element, or any combination of elements may be implemented as a “processing system” that includes one or more processors. Examples of processors include microprocessors, microcontrollers, graphics processing units (GPUs), central processing units (CPUs), application processors, digital signal processors (DSPs), reduced instruction set computing (RISC) processors, systems on a chip (SoC), baseband processors, field programmable gate arrays (FPGAs), programmable logic devices (PLDs), state machines, gated logic, discrete hardware circuits, and other suitable hardware configured to perform the various functionality described throughout this disclosure. One or more processors in the processing system may execute software. Software shall be construed broadly to mean instructions, instruction sets, code, code segments, program code, programs, subprograms, software components, applications, software applications, software packages, routines, subroutines, objects, executables, threads of execution, procedures, functions, etc., whether referred to as software, firmware, middleware, microcode, hardware description language, or otherwise.

(17) Accordingly, in one or more example embodiments, the functions described may be implemented in hardware, software, or any combination thereof. If implemented in software, the functions may be stored on or encoded as one or more instructions or code on a computer-readable medium. Computer-readable media includes computer storage media. Storage media may be any available media that can be accessed by a computer. By way of example, and not limitation, such computer-readable media can comprise a random-access memory (RAM), a read-only memory (ROM), an electrically erasable programmable ROM (EEPROM), optical disk storage, magnetic disk storage, other magnetic storage devices, combinations of the aforementioned types of computer-readable media, or any other medium that can be used to store computer executable code in the form of instructions or data structures that can be accessed by a computer.

(18) FIG. 1 is a diagram illustrating an example of a wireless communications system and an access network **100**. The wireless communications system (also referred to as a wireless wide area network (WWAN)) includes base stations **102**, UEs **104**, an Evolved Packet Core (EPC) **160**, and another core network **190** (e.g., a 5G Core (5GC)). The base stations **102** may include macrocells (high power cellular base station) and/or small cells (low power cellular base station). The macrocells include base stations. The small cells include femtocells, picocells, and microcells.

(19) The base stations **102** configured for 4G LTE (collectively referred to as Evolved Universal Mobile Telecommunications System (UMTS) Terrestrial Radio Access Network (E-UTRAN)) may interface with the EPC **160** through first backhaul links **132** (e.g., S1 interface). The base stations **102** configured for 5G NR (collectively referred to as Next Generation RAN (NG-RAN)) may interface with core network **190** through second backhaul links **184**. In addition to other functions, the base stations **102** may perform one or more of the following functions: transfer of user data, radio channel ciphering and deciphering, integrity protection, header compression, mobility control functions (e.g., handover, dual connectivity), inter-cell interference coordination, connection setup

and release, load balancing, distribution for non-access stratum (NAS) messages, NAS node selection, synchronization, radio access network (RAN) sharing, multimedia broadcast multicast service (MBMS), subscriber and equipment trace, RAN information management (RIM), paging, positioning, and delivery of warning messages. The base stations **102** may communicate directly or indirectly (e.g., through the EPC **160** or core network **190**) with each other over third backhaul links **134** (e.g., X2 interface). The first backhaul links **132**, the second backhaul links **184**, and the third backhaul links **134** may be wired or wireless.

(20) The base stations **102** may wirelessly communicate with the UEs **104**. Each of the base stations **102** may provide communication coverage for a respective geographic coverage area **110**. There may be overlapping geographic coverage areas **110**. For example, the small cell **102'** may have a coverage area **110'** that overlaps the coverage area **110** of one or more macro base stations **102**. A network that includes both small cell and macrocells may be known as a heterogeneous network. A heterogeneous network may also include Home Evolved Node Bs (eNBs) (HeNBs), which may provide service to a restricted group known as a closed subscriber group (CSG). The communication links **120** between the base stations **102** and the UEs **104** may include uplink (UL) (also referred to as reverse link) transmissions from a UE **104** to a base station **102** and/or downlink (DL) (also referred to as forward link) transmissions from a base station **102** to a UE **104**. The communication links **120** may use multiple-input and multiple-output (MIMO) antenna technology, including spatial multiplexing, beamforming, and/or transmit diversity. The communication links may be through one or more carriers. The base stations **102**/UEs **104** may use spectrum up to Y MHz (e.g., 5, 10, 15, 20, 100, 400, etc. MHz) bandwidth per carrier allocated in a carrier aggregation of up to a total of Yx MHz (x component carriers) used for transmission in each direction. The carriers may or may not be adjacent to each other. Allocation of carriers may be asymmetric with respect to DL and UL (e.g., more or fewer carriers may be allocated for DL than for UL). The component carriers may include a primary component carrier and one or more secondary component carriers. A primary component carrier may be referred to as a primary cell (PCell) and a secondary component carrier may be referred to as a secondary cell (SCell).

(21) Certain UEs **104** may communicate with each other using device-to-device (D2D) communication link **158**. The D2D communication link **158** may use the DL/UL WWAN spectrum. The D2D communication link **158** may use one or more sidelink channels, such as a physical sidelink broadcast channel (PSBCH), a physical sidelink discovery channel (PSDCH), a physical sidelink shared channel (PSSCH), and a physical sidelink control channel (PSCCH). D2D communication may be through a variety of wireless D2D communications systems, such as for example, WiMedia, Bluetooth, ZigBee, Wi-Fi based on the Institute of Electrical and Electronics Engineers (IEEE) 802.11 standard, LTE, or NR.

(22) The wireless communications system may further include a Wi-Fi access point (AP) **150** in communication with Wi-Fi stations (STAs) **152** via communication links **154**, e.g., in a 5 GHz unlicensed frequency spectrum or the like. When communicating in an unlicensed frequency spectrum, the STAs **152**/AP **150** may perform a clear channel assessment (CCA) prior to communicating in order to determine whether the channel is available.

(23) The small cell **102'** may operate in a licensed and/or an unlicensed frequency spectrum. When operating in an unlicensed frequency spectrum, the small cell **102'** may employ NR and use the same unlicensed frequency spectrum (e.g., 5 GHz, or the like) as used by the Wi-Fi AP **150**. The small cell **102'**, employing NR in an unlicensed frequency spectrum, may boost coverage to and/or increase capacity of the access network.

(24) The electromagnetic spectrum is often subdivided, based on frequency/wavelength, into various classes, bands, channels, etc. In 5G NR, two initial operating bands have been identified as frequency range designations FR1 (410 MHz-7.125 GHz) and FR2 (24.25 GHz-52.6 GHz). The frequencies between FR1 and FR2 are often referred to as mid-band frequencies. Although a portion of FR1 is greater than 6 GHz, FR1 is often referred to (interchangeably) as a “sub-6 GHz”

band in various documents and articles. A similar nomenclature issue sometimes occurs with regard to FR2, which is often referred to (interchangeably) as a “millimeter wave” band in documents and articles, despite being different from the extremely high frequency (EHF) band (30 GHz-300 GHz) which is identified by the International Telecommunications Union (ITU) as a “millimeter wave” band.

(25) With the above aspects in mind, unless specifically stated otherwise, it should be understood that the term “sub-6 GHz” or the like if used herein may broadly represent frequencies that may be less than 6 GHz, may be within FR1, or may include mid-band frequencies. Further, unless specifically stated otherwise, it should be understood that the term “millimeter wave” or the like if used herein may broadly represent frequencies that may include mid-band frequencies, may be within FR2, or may be within the EHF band.

(26) A base station **102**, whether a small cell **102'** or a large cell (e.g., macro base station), may include and/or be referred to as an eNB, gNodeB (gNB), or another type of base station. Some base stations, such as gNB **180** may operate in a traditional sub 6 GHz spectrum, in millimeter wave frequencies, and/or near millimeter wave frequencies in communication with the UE **104**. When the gNB **180** operates in millimeter wave or near millimeter wave frequencies, the gNB **180** may be referred to as a millimeter wave base station. The millimeter wave base station **180** may utilize beamforming **182** with the UE **104** to compensate for the path loss and short range. The base station **180** and the UE **104** may each include a plurality of antennas, such as antenna elements, antenna panels, and/or antenna arrays to facilitate the beamforming.

(27) The base station **180** may transmit a beamformed signal to the UE **104** in one or more transmit directions **182'**. The UE **104** may receive the beamformed signal from the base station **180** in one or more receive directions **182''**. The UE **104** may also transmit a beamformed signal to the base station **180** in one or more transmit directions. The base station **180** may receive the beamformed signal from the UE **104** in one or more receive directions. The base station **180**/UE **104** may perform beam training to determine the best receive and transmit directions for each of the base station **180**/UE **104**. The transmit and receive directions for the base station **180** may or may not be the same. The transmit and receive directions for the UE **104** may or may not be the same.

(28) The EPC **160** may include a Mobility Management Entity (MME) **162**, other MMEs **164**, a Serving Gateway **166**, a Multimedia Broadcast Multicast Service (MBMS) Gateway **168**, a Broadcast Multicast Service Center (BM-SC) **170**, and a Packet Data Network (PDN) Gateway **172**. The MME **162** may be in communication with a Home Subscriber Server (HSS) **174**. The MME **162** is the control node that processes the signaling between the UEs **104** and the EPC **160**. Generally, the MME **162** provides bearer and connection management. All user Internet protocol (IP) packets are transferred through the Serving Gateway **166**, which itself is connected to the PDN Gateway **172**. The PDN Gateway **172** provides UE IP address allocation as well as other functions. The PDN Gateway **172** and the BM-SC **170** are connected to the IP Services **176**. The IP Services **176** may include the Internet, an intranet, an IP Multimedia Subsystem (IMS), a PS Streaming Service, and/or other IP services. The BM-SC **170** may provide functions for MBMS user service provisioning and delivery. The BM-SC **170** may serve as an entry point for content provider MBMS transmission, may be used to authorize and initiate MBMS Bearer Services within a public land mobile network (PLMN), and may be used to schedule MBMS transmissions. The MBMS Gateway **168** may be used to distribute MBMS traffic to the base stations **102** belonging to a Multicast Broadcast Single Frequency Network (MBSFN) area broadcasting a particular service, and may be responsible for session management (start/stop) and for collecting eMBMS related charging information.

(29) The core network **190** may include an Access and Mobility Management Function (AMF) **192**, other AMFs **193**, a Session Management Function (SMF) **194**, and a User Plane Function (UPF) **195**. The AMF **192** may be in communication with a Unified Data Management (UDM) **196**. The AMF **192** is the control node that processes the signaling between the UEs **104** and the core

network **190**. Generally, the AMF **192** provides QoS flow and session management. All user Internet protocol (IP) packets are transferred through the UPF **195**. The UPF **195** provides UE IP address allocation as well as other functions. The UPF **195** is connected to the IP Services **197**. The IP Services **197** may include the Internet, an intranet, an IP Multimedia Subsystem (IMS), a Packet Switch (PS) Streaming (PSS) Service, and/or other IP services.

(30) The base station may include and/or be referred to as a gNB, Node B, eNB, an access point, a base transceiver station, a radio base station, a radio transceiver, a transceiver function, a basic service set (BSS), an extended service set (ESS), a transmit reception point (TRP), or some other suitable terminology. The base station **102** provides an access point to the EPC **160** or core network **190** for a UE **104**. Examples of UEs **104** include a cellular phone, a smart phone, a session initiation protocol (SIP) phone, a laptop, a personal digital assistant (PDA), a satellite radio, a global positioning system, a multimedia device, a video device, a digital audio player (e.g., MP3 player), a camera, a game console, a tablet, a smart device, a wearable device, a vehicle, an electric meter, a gas pump, a large or small kitchen appliance, a healthcare device, an implant, a sensor/actuator, a display, or any other similar functioning device. Some of the UEs **104** may be referred to as IoT devices (e.g., parking meter, gas pump, toaster, vehicles, heart monitor, etc.). The UE **104** may also be referred to as a station, a mobile station, a subscriber station, a mobile unit, a subscriber unit, a wireless unit, a remote unit, a mobile device, a wireless device, a wireless communications device, a remote device, a mobile subscriber station, an access terminal, a mobile terminal, a wireless terminal, a remote terminal, a handset, a user agent, a mobile client, a client, or some other suitable terminology.

(31) Referring again to FIG. **1**, in certain aspects, the UE **104** and/or the base station **180** may include a cross-carrier scheduling component **198** configured to monitor concurrently, on different CCs, a first and second PDCCH having different SCSs, each of the PDCCHs being configured to schedule PDSCH or PUSCH on a same CC and being associated with respective maximum numbers of PDCCH candidates or non-overlapped CCEs based on the different SCSs, a sum of respective numbers of PDCCH candidates or non-overlapped CCEs for the respective PDCCHs being less than or equal to N times the lower of the respective maximum numbers. Although the following description may be focused on 5G NR, the concepts described herein may be applicable to other similar areas, such as LTE, LTE-A, CDMA, GSM, and other wireless technologies.

(32) FIG. **2A** is a diagram **200** illustrating an example of a first subframe within a 5G NR frame structure. FIG. **2B** is a diagram **230** illustrating an example of DL channels within a 5G NR subframe. FIG. **2C** is a diagram **250** illustrating an example of a second subframe within a 5G NR frame structure. FIG. **2D** is a diagram **280** illustrating an example of UL channels within a 5G NR subframe. The 5G NR frame structure may be frequency division duplexed (FDD) in which for a particular set of subcarriers (carrier system bandwidth), subframes within the set of subcarriers are dedicated for either DL or UL, or may be time division duplexed (TDD) in which for a particular set of subcarriers (carrier system bandwidth), subframes within the set of subcarriers are dedicated for both DL and UL. In the examples provided by FIGS. **2A**, **2C**, the 5G NR frame structure is assumed to be TDD, with subframe 4 being configured with slot format 28 (with mostly DL), where D is DL, U is UL, and F is flexible for use between DL/UL, and subframe 3 being configured with slot format 1 (with all UL). While subframes 3, 4 are shown with slot formats 1, 28, respectively, any particular subframe may be configured with any of the various available slot formats 0-61. Slot formats 0, 1 are all DL, UL, respectively. Other slot formats 2-61 include a mix of DL, UL, and flexible symbols. UEs are configured with the slot format (dynamically through DL control information (DCI), or semi-statically/statically through radio resource control (RRC) signaling) through a received slot format indicator (SFI). Note that the description infra applies also to a 5G NR frame structure that is TDD.

(33) Other wireless communication technologies may have a different frame structure and/or different channels. A frame (10 ms) may be divided into 10 equally sized subframes (1 ms). Each

subframe may include one or more time slots. Subframes may also include mini-slots, which may include 7, 4, or 2 symbols. Each slot may include 7 or 14 symbols, depending on the slot configuration. For slot configuration 0, each slot may include 14 symbols, and for slot configuration 1, each slot may include 7 symbols. The symbols on DL may be cyclic prefix (CP) OFDM (CP-OFDM) symbols. The symbols on UL may be CP-OFDM symbols (for high throughput scenarios) or discrete Fourier transform (DFT) spread OFDM (DFT-s-OFDM) symbols (also referred to as single carrier frequency-division multiple access (SC-FDMA) symbols) (for power limited scenarios; limited to a single stream transmission). The number of slots within a subframe is based on the slot configuration and the numerology. For slot configuration 0, different numerologies 0 to 4 allow for 1, 2, 4, 8, and 16 slots, respectively, per subframe. For slot configuration 1, different numerologies 0 to 2 allow for 2, 4, and 8 slots, respectively, per subframe. Accordingly, for slot configuration 0 and numerology μ , there are 14 symbols/slot and $2 \cdot \sup.\mu$ slots/subframe. The subcarrier spacing and symbol length/duration are a function of the numerology. The subcarrier spacing may be equal to $2 \cdot \sup.\mu \cdot 15$ kHz, where μ is the numerology 0 to 4. As such, the numerology $\mu=0$ has a subcarrier spacing of 15 kHz and the numerology $\mu=4$ has a subcarrier spacing of 240 kHz. The symbol length/duration is inversely related to the subcarrier spacing. FIGS. 2A-2D provide an example of slot configuration 0 with 14 symbols per slot and numerology $\mu=2$ with 4 slots per subframe. The slot duration is 0.25 ms, the subcarrier spacing is 60 kHz, and the symbol duration is approximately 16.67 μ s. Within a set of frames, there may be one or more different bandwidth parts (BWPs) (see FIG. 2B) that are frequency division multiplexed. Each BWP may have a particular numerology.

(34) A resource grid may be used to represent the frame structure. Each time slot includes a resource block (RB) (also referred to as physical RBs (PRBs)) that extends 12 consecutive subcarriers. The resource grid is divided into multiple resource elements (REs). The number of bits carried by each RE depends on the modulation scheme.

(35) As illustrated in FIG. 2A, some of the REs carry reference (pilot) signals (RS) for the UE. The RS may include demodulation RS (DM-RS) (indicated as R for one particular configuration, but other DM-RS configurations are possible) and channel state information reference signals (CSI-RS) for channel estimation at the UE. The RS may also include beam measurement RS (BRS), beam refinement RS (BRRS), and phase tracking RS (PT-RS).

(36) FIG. 2B illustrates an example of various DL channels within a subframe of a frame. The physical downlink control channel (PDCCH) carries DCI within one or more control channel elements (CCEs) (e.g., 1, 2, 4, 8, or 16 CCEs), each CCE including six RE groups (REGs), each REG including 12 consecutive REs in an OFDM symbol of an RB. A PDCCH within one BWP may be referred to as a control resource set (CORESET). A UE is configured to monitor PDCCH candidates in a PDCCH search space (e.g., common search space, UE-specific search space) during PDCCH monitoring occasions on the CORESET, where the PDCCH candidates have different DCI formats and different aggregation levels. Additional BWPs may be located at greater and/or lower frequencies across the channel bandwidth. A primary synchronization signal (PSS) may be within symbol 2 of particular subframes of a frame. The PSS is used by a UE 104 to determine subframe/symbol timing and a physical layer identity. A secondary synchronization signal (SSS) may be within symbol 4 of particular subframes of a frame. The SSS is used by a UE to determine a physical layer cell identity group number and radio frame timing. Based on the physical layer identity and the physical layer cell identity group number, the UE can determine a physical cell identifier (PCI). Based on the PCI, the UE can determine the locations of the aforementioned DM-RS. The physical broadcast channel (PBCH), which carries a master information block (MIB), may be logically grouped with the PSS and SSS to form a synchronization signal (SS)/PBCH block (also referred to as SS block (SSB)). The MIB provides a number of RBs in the system bandwidth and a system frame number (SFN). The physical downlink shared channel (PDSCH) carries user data, broadcast system information not transmitted through the PBCH such as system information

blocks (SIBs), and paging messages.

(37) As illustrated in FIG. 2C, some of the REs carry DM-RS (indicated as R for one particular configuration, but other DM-RS configurations are possible) for channel estimation at the base station. The UE may transmit DM-RS for the physical uplink control channel (PUCCH) and DM-RS for the physical uplink shared channel (PUSCH). The PUSCH DM-RS may be transmitted in the first one or two symbols of the PUSCH. The PUCCH DM-RS may be transmitted in different configurations depending on whether short or long PUCCHs are transmitted and depending on the particular PUCCH format used. The UE may transmit sounding reference signals (SRS). The SRS may be transmitted in the last symbol of a subframe. The SRS may have a comb structure, and a UE may transmit SRS on one of the combs. The SRS may be used by a base station for channel quality estimation to enable frequency-dependent scheduling on the UL.

(38) FIG. 2D illustrates an example of various UL channels within a subframe of a frame. The PUCCH may be located as indicated in one configuration. The PUCCH carries uplink control information (UCI), such as scheduling requests, a channel quality indicator (CQI), a precoding matrix indicator (PMI), a rank indicator (RI), and hybrid automatic repeat request (HARD) ACK/NACK feedback. The PUSCH carries data, and may additionally be used to carry a buffer status report (BSR), a power headroom report (PHR), and/or UCI.

(39) FIG. 3 is a block diagram of a base station **310** in communication with a UE **350** in an access network. In the DL, IP packets from the EPC **160** may be provided to a controller/processor **375**. The controller/processor **375** implements layer 3 and layer 2 functionality. Layer 3 includes a radio resource control (RRC) layer, and layer 2 includes a service data adaptation protocol (SDAP) layer, a packet data convergence protocol (PDCP) layer, a radio link control (RLC) layer, and a medium access control (MAC) layer. The controller/processor **375** provides RRC layer functionality associated with broadcasting of system information (e.g., MIB, SIBs), RRC connection control (e.g., RRC connection paging, RRC connection establishment, RRC connection modification, and RRC connection release), inter radio access technology (RAT) mobility, and measurement configuration for UE measurement reporting; PDCP layer functionality associated with header compression/decompression, security (ciphering, deciphering, integrity protection, integrity verification), and handover support functions; RLC layer functionality associated with the transfer of upper layer packet data units (PDUs), error correction through ARQ, concatenation, segmentation, and reassembly of RLC service data units (SDUs), re-segmentation of RLC data PDUs, and reordering of RLC data PDUs; and MAC layer functionality associated with mapping between logical channels and transport channels, multiplexing of MAC SDUs onto transport blocks (TBs), demultiplexing of MAC SDUs from TBs, scheduling information reporting, error correction through HARQ, priority handling, and logical channel prioritization.

(40) The transmit (TX) processor **316** and the receive (RX) processor **370** implement layer 1 functionality associated with various signal processing functions. Layer 1, which includes a physical (PHY) layer, may include error detection on the transport channels, forward error correction (FEC) coding/decoding of the transport channels, interleaving, rate matching, mapping onto physical channels, modulation/demodulation of physical channels, and MIMO antenna processing. The TX processor **316** handles mapping to signal constellations based on various modulation schemes (e.g., binary phase-shift keying (BPSK), quadrature phase-shift keying (QPSK), M-phase-shift keying (M-PSK), M-quadrature amplitude modulation (M-QAM)). The coded and modulated symbols may then be split into parallel streams. Each stream may then be mapped to an OFDM subcarrier, multiplexed with a reference signal (e.g., pilot) in the time and/or frequency domain, and then combined together using an Inverse Fast Fourier Transform (IFFT) to produce a physical channel carrying a time domain OFDM symbol stream. The OFDM stream is spatially precoded to produce multiple spatial streams. Channel estimates from a channel estimator **374** may be used to determine the coding and modulation scheme, as well as for spatial processing. The channel estimate may be derived from a reference signal and/or channel condition feedback

transmitted by the UE **350**. Each spatial stream may then be provided to a different antenna **320** via a separate transmitter **318** TX. Each transmitter **318** TX may modulate an RF carrier with a respective spatial stream for transmission.

(41) At the UE **350**, each receiver **354** RX receives a signal through its respective antenna **352**. Each receiver **354** RX recovers information modulated onto an RF carrier and provides the information to the receive (RX) processor **356**. The TX processor **368** and the RX processor **356** implement layer 1 functionality associated with various signal processing functions. The RX processor **356** may perform spatial processing on the information to recover any spatial streams destined for the UE **350**. If multiple spatial streams are destined for the UE **350**, they may be combined by the RX processor **356** into a single OFDM symbol stream. The RX processor **356** then converts the OFDM symbol stream from the time-domain to the frequency domain using a Fast Fourier Transform (FFT). The frequency domain signal comprises a separate OFDM symbol stream for each subcarrier of the OFDM signal. The symbols on each subcarrier, and the reference signal, are recovered and demodulated by determining the most likely signal constellation points transmitted by the base station **310**. These soft decisions may be based on channel estimates computed by the channel estimator **358**. The soft decisions are then decoded and deinterleaved to recover the data and control signals that were originally transmitted by the base station **310** on the physical channel. The data and control signals are then provided to the controller/processor **359**, which implements layer 3 and layer 2 functionality.

(42) The controller/processor **359** can be associated with a memory **360** that stores program codes and data. The memory **360** may be referred to as a computer-readable medium. In the UL, the controller/processor **359** provides demultiplexing between transport and logical channels, packet reassembly, deciphering, header decompression, and control signal processing to recover IP packets from the EPC **160**. The controller/processor **359** is also responsible for error detection using an ACK and/or NACK protocol to support HARQ operations.

(43) Similar to the functionality described in connection with the DL transmission by the base station **310**, the controller/processor **359** provides RRC layer functionality associated with system information (e.g., MIB, SIBs) acquisition, RRC connections, and measurement reporting; PDCP layer functionality associated with header compression/decompression, and security (ciphering, deciphering, integrity protection, integrity verification); RLC layer functionality associated with the transfer of upper layer PDUs, error correction through ARQ, concatenation, segmentation, and reassembly of RLC SDUs, re-segmentation of RLC data PDUs, and reordering of RLC data PDUs; and MAC layer functionality associated with mapping between logical channels and transport channels, multiplexing of MAC SDUs onto TBs, demultiplexing of MAC SDUs from TBs, scheduling information reporting, error correction through HARQ, priority handling, and logical channel prioritization.

(44) Channel estimates derived by a channel estimator **358** from a reference signal or feedback transmitted by the base station **310** may be used by the TX processor **368** to select the appropriate coding and modulation schemes, and to facilitate spatial processing. The spatial streams generated by the TX processor **368** may be provided to different antenna **352** via separate transmitters **354**TX. Each transmitter **354**TX may modulate an RF carrier with a respective spatial stream for transmission.

(45) The UL transmission is processed at the base station **310** in a manner similar to that described in connection with the receiver function at the UE **350**. Each receiver **318**RX receives a signal through its respective antenna **320**. Each receiver **318**RX recovers information modulated onto an RF carrier and provides the information to a RX processor **370**.

(46) The controller/processor **375** can be associated with a memory **376** that stores program codes and data. The memory **376** may be referred to as a computer-readable medium. In the UL, the controller/processor **375** provides demultiplexing between transport and logical channels, packet reassembly, deciphering, header decompression, control signal processing to recover IP packets

from the UE 350. IP packets from the controller/processor 375 may be provided to the EPC 160. The controller/processor 375 is also responsible for error detection using an ACK and/or NACK protocol to support HARQ operations.

(47) At least one of the TX processor 368, the RX processor 356, and the controller/processor 359 may be configured to perform aspects in connection with the cross-carrier scheduling component 198 of FIG. 1.

(48) At least one of the TX processor 316, the RX processor 370, and the controller/processor 375 may be configured to perform aspects in connection with the cross carrier scheduling component 198 of FIG. 1.

(49) Wireless communication systems may be configured to share available system resources and provide various telecommunication services (e.g., telephony, video, data, messaging, broadcasts, etc.) based on multiple-access technologies such as CDMA systems, TDMA systems, FDMA systems, OFDMA systems, SC-FDMA systems, TD-SCDMA systems, etc. that support communication with multiple users. In many cases, common protocols that facilitate communications with wireless devices are adopted in various telecommunication standards. For example, communication methods associated with eMBB, mMTC, and URLLC may be incorporated in the 5G NR telecommunication standard, while other aspects may be incorporated in the 4G LTE standard. As mobile broadband technologies are part of a continuous evolution, further improvements in mobile broadband remain useful to continue the progression of such technologies.

(50) FIG. 4 is a call flow diagram 400 illustrating communications between a UE 402 and a base station 404. At 406, the UE 402 may transmit UE capability information to the base station 404. For example, the UE 402 may transmit an indication of processing capabilities of the UE 402 for a number of blind decodes (BDs) and/or a number of CCEs. The processing capabilities may be indicated based on N times a maximum number of PDCCH candidates (e.g., $N=1$, $N \geq 1$, etc.).

(51) At 410a, the base station 404 may configure a first PDCCH on a first component carrier (CC) for scheduling a first PDSCH or a first PUSCH on a second CC different from the first CC. At 410b, the base station 404 may similarly configure a second PDCCH on a second CC for scheduling the second PDSCH or the second PUSCH on the second CC. In examples, the base station 404 may configure the first PDCCH and the second PDCCH, at 410a-410b, after receiving the UE capability information, at 406.

(52) At 408a, the UE 402 may monitor for the first PDCCH on the first CC. The first PDCCH may be configured to schedule the first PDSCH or the first PUSCH on the second CC. At 408b, concurrent with the monitoring of the first PDCCH, the UE 402 may monitor for the second PDCCH on the second CC different from the first CC. The second PDCCH may be similarly configured to schedule second PDSCH or second PUSCH on the second CC. At 412, the base station 404 may transmit DCI for scheduling the first/second PDSCH/PUSCH on the second CC, where a sum of PDCCH candidates or non-overlapping CCEs may be less than a predefined threshold.

(53) FIG. 5 is a diagram 500 illustrating cross-carrier scheduling from a secondary cell (SCell) 504 to a primary cell (PCell) 502. In further configurations, the cross-carrier scheduling may be from the SCell 504 to a primary-secondary cell (PSCell).

(54) Dynamic spectrum sharing (DSS) in frequency range 1 (FR1) may include PDCCH enhancements for cross-carrier scheduling including a first RAN and to a second RAN. For instance, PDCCH associated with the SCell 504 may be used for scheduling PDSCH or PUSCH, at 508 and 514, on the PCell 502 or on the PSCell. PDCCH scheduling of the PDSCH may occur on multiple cells via a single DCI. In examples, a DCI size may be decreased in association with limiting a number of cells that may be scheduled at a same time to 2 cells. A total PDCCH blind decoding (BD) allocation may not be changed as a result of such operations. Such enhancements are not specific to DSS and may be generally applicable to cross-carrier scheduling in carrier aggregation.

(55) Operational frequency bands for DSS may be based on lower frequency bands for which an NR system may use a subcarrier spacing (SCS) of 15 kHz. Such carriers may be used as an “anchor” for both LTE UEs and NR UEs to ensure a threshold level of connectivity and coverage. In cases of carrier aggregation, the anchor carrier may correspond to the PCell **502**. If the carrier corresponds to a DSS carrier, resource availability may be restricted. Given that an increased number of NR carriers on mid-bands/high bands may not use DSS, cross-carrier scheduling may be enabled from the SCell **504** on a mid-band/high band to the PCell **502**. Since the carrier on the mid-band/high band may be based on, e.g., 30 kHz SCS, cross-carrier scheduling from the SCell **504** to the PCell **502**/PSCell may correspond to different numerologies between the SCell **504** and the PCell **502**/PSCell. Accordingly, cross-carrier scheduling from the SCell **504** to the PCell **502**/PSCell may be configured for a SCS of 30 kHz or 15 kHz for the SCell **504** (e.g., the scheduling cell) and a SCS of 15 kHz for the PCell **502**/PSCell (e.g., the scheduled cell).

(56) Some cross-carrier scheduling techniques may support different numerologies between the scheduling cell and the scheduled cell. That is, cross-carrier scheduling from the SCell **504** to the PCell **502**/PSCell may be based on the different numerologies. In examples, cross-carrier scheduling from the SCell **504** to the PCell **502**/PSCell may be used for non-fallback DCI with a carrier indication field (CIF) (e.g., CIF=0) that is monitored on a first UE-specific search space (USS) **510**. The cross-carrier scheduling may use the CIF in the DCI to indicate which carrier the DCI may schedule the PDSCH/PUSCH, at **508**. The UE may determine PDCCH candidates for the DCI scheduling from the SCell **504** to the PCell **502**/PSCell based on a value of n_{CI} for a hash function unless, e.g., search space sharing is enabled based on UE capabilities and conditions. If the PDSCH of the PCell **502** and the PDCCH of the SCell **504** use different SCSs, a PDSCH preparation time may be provided.

(57) In cases where there is one scheduling cell for each scheduled cell, common search spaces (CSS) **506** may be located on the PCell **502**. Since the CSS **506** of the PCell **502**/PSCell may be associated with functionalities such as system information, paging, random access, fallback operations, hypothetical block error rate (BLER) calculations for a radio link failure (RLF)/link recovery (LR) procedure, etc., maintaining the CSS **506** in the PCell **502**/PSCell may provide improved functionality. While no more than one scheduling cell (e.g., SCell **504**) may be needed for a given scheduled cell (e.g., PCell **502**/PSCell), some NR systems may include more than one scheduling cell for the given scheduled cell. In instances where cross-carrier scheduling is configured for performing the DSS operation on the PCell **502**/PSCell, one SCell **504** may still be configured as the scheduling cell for the PCell **502**/PSCell.

(58) If unicast data scheduling is available from both the scheduling cell (e.g., SCell **504**) and the CSS **506** of the scheduled cell (e.g., PCell **502**/PSCell), the UE may not be able to determine from which scheduling cell the UE receives a scheduling grant for PDSCH or PUSCH, at **508**, at each scheduling instance. Therefore, the unicast data scheduling may solely be available from the SCell **504**. In examples, the UE may be configured to process time-overlapping unicast PDSCH and system information (SI)-radio network temporary identifier (RNTI)(SI-RNTI) PDSCH during paging-RNTI (P-RNTI) triggered SI acquisition for FR1. CSS monitoring may be maintained on the PCell **502**/PSCell, so that UE operations associated with system information reception, paging, fallback, RLF, etc. may remain unchanged. DCI with cell-RNTI (C-RNTI) on the CSS **506** of the PCell **502** may be used, e.g., not for unicast data, but for PDCCH ordering.

(59) The diagram **500** shows an example of the cross-carrier scheduling from the SCell **504** to the PCell **502**. More specifically, multiple PDCCH candidates (e.g., BDs) may be associated with both the PCell **502** and the SCell **504**. Thus, the SCell **504** may schedule PDSCH or PUSCH, at **508**, on the PCell **502** via cross-carrier scheduling. If the CSS **506** is moved to the SCell **504**, the PCell **502** may have no associated PDCCH candidates. However, since the PCell **502** provides functionality for UE mobility and coverage, the CSS **506** may be maintained on the PCell **502**. Thus, in the diagram **500**, the CSS **506** may be maintained on the PCell **502**, while the first USS **510** may be

located on the SCell **504** for the cross-carrier scheduling. Therefore, PDCCH candidates of the PCell **502** and the SCell **504** may schedule PDSCH or PUSCH, at **508**, on the PCell **502**. For example, all 8 PDCCH candidates illustrated in the diagram **500** associated with the CSS **506** and the first USS **510** may be used for scheduling data on the PCell **502**. A second USS **512** (e.g., with CIF=1) may be located on the SCell **504** for PDCCH candidates of the SCell **504** to schedule PDSCH or PUSCH, at **514**, on the SCell **504**. For example, the two PDCCH candidates illustrated in the diagram **500** as being associated with the second USS **512** may be used for scheduling data on the SCell **504**.

(60) A number of BDs and a number of CCEs that a UE may process at a same time may be based on certain limitations. For example, the UE may not process more BDs and/or CCEs at one time than a predefined threshold number. In instances where the UE supports the cross-carrier scheduling from the PCell **502** to the SCell **504**, there may be one scheduling cell for a given scheduled cell. For example, for the PDSCH or PUSCH, at **514**, on the SCell **504** in the diagram **500** there may be one scheduling cell (e.g., the PCell **502**). However, for the PDSCH or PUSCH, at **508**, on the PCell **502** in the diagram **500** there may be multiple scheduling cells (e.g., the PCell **502** and the SCell **504**). Thus, the maximum number of BDs and non-overlapping CCEs may be regulated so that a PDCCH allocation is not exceeded.

(61) FIGS. **6A-6B** illustrate diagrams **600-650** associated with determining a number of PDCCH candidates (e.g., BDs) and a number of non-overlapping CCEs. If two scheduling cells are used for scheduling on the PCell/PSCell, a number of PDCCH BDs/CCEs may be determined based on a count/allocation. That is, the numbers of BDs/CCEs per span/slot may be limited for a given scheduled cell based on processing capabilities of the UE. In the diagram **600**, a maximum number of BDs and non-overlapping CCEs may be determined based on a predefined allocation corresponding to the lower SCS (e.g., 15 kHz) of the component carriers (e.g., the lower of a first SCS for the SCell and a second SCS for the PCell/PSCell). In the diagram **650**, a maximum number of BDs and non-overlapping CCEs may be determined based on allocations that are separately predefined for the PCell/PSCell and the SCell.

(62) The two component carriers indicated in the diagrams **600-650** for the SCell and the PCell/PSCell may have different SCSs. For example, a first SCS of the SCell may be 60 kHz and a second SCS of the PCell/PSCell may be 15 kHz. Based on the different SCSs of the respective component carriers, the PDCCH monitoring occasions may be different for the first component carrier and the second component carrier. For example, the PCell/PSCell may be associated with one monitoring occasion per slot, whereas the SCell may be associated with four monitoring occasions per slot. The PDCCH monitoring occasions for the PCell/PSCell may be associated with PDCCH candidates received from the CSS and the PDCCH monitoring occasions for the SCell may be associated with PDCCH candidates received from the USS.

(63) In the diagram **600**, the numbers of BDs and non-overlapping CCEs per span/slot may be counted over the data scheduling cell for the PCell/PSCell. The counted number of BDs and non-overlapping CCEs may not be more than the predefined allocation per span/slot per component carrier (e.g., there may be no overscheduling of the PDCCH). In examples, a BD allocation per span/slot per component carrier may be up to 44 BDs for a 15 kHz carrier. As such, 44 BDs may be the BD allocation (e.g., the maximum number that may not be exceeded) over the carrier for the PCell/PSCell.

(64) If the scheduling cell (e.g., SCell) and the scheduled cell (e.g., PCell/PSCell) use different numerologies, the per span/slot threshold may be determined based on the lower SCS (e.g., the per span/slot having the component carrier with the lower SCS). In the diagram **600**, the per span/slot threshold of the component carrier with the lowest SCS may correspond to the 15 kHz carrier (e.g., the span/slot of the PDCCH monitoring occasion for the PCell/PSCell). The number of BDs across the PCell/PSCell and the SCell may not exceed the lower BD allocation of the multiple scheduling carriers. In this manner, the BD allocation may be capped based on a per cell budget, even though

the number of BDs may extend across the multiple scheduling carriers.

(65) In the diagram **650**, the number of BDs or non-overlapping CCEs may be defined per scheduling cell, including data scheduling on the PCell/PSCell. That is, the number of BDs or non-overlapping CCEs may be counted separately per cell. For example, the PDCCH monitoring occasion for the PCell/PSCell may have up to 44 PDCCH candidates (e.g., BDs) and the PDCCH monitoring occasion for the SCell may have up to 44 PDCCH candidates. The UE may report UE capability information to the network indicative of whether the UE is configured to process 88 PDCCH candidates (e.g., 44+44) or whether the UE is solely configured, e.g., to process up to 44 PDCCH candidates over all of the carriers.

(66) Accordingly, the numbers of BDs and non-overlapping CCEs per span/slot may be counted per scheduling cell for scheduling the PCell/PSCell. The counted number of BDs and non-overlapping CCEs for a given scheduling cell per span/slot may not be more than a predefined allocation per span/slot per carrier. While the diagram **650** similarly indicates that there may be no PDCCH overscheduling, the per carrier allocation in the diagram **650** may be available for each of the scheduling cells. The UE may be configured to report UE capability information regarding the number of BD and non-overlapping CCEs per span/slot for the PCell/PSCell, such that configurations having the total number of BDs/non-overlapping CCEs over the carriers per span/slot for the PCell/PSCell may not exceed the predetermined allocations per span/slot per carrier.

(67) The UE may report the processing capability of the UE to the network via capability signalling. In examples, if the UE reports the value N via the capability signalling where, e.g., N may be determined based on a hash function, the UE may support a total number of BDs/non-overlapping CCEs over the carriers per span/slot for the PCell/PSCell of up to N times the predetermined allocations per span/slot per carrier. For example, if the UE reports N=2, the UE may support 44+44 BDs/non-overlapping CCEs. If the UE reports N=1, the UE may support a total number of BDs/non-overlapping CCEs over the carriers per span/slot for the PCell/PSCell that is not more than the predetermined allocations per span/slot per carrier (e.g., 44 PDCCH candidates over the carriers).

(68) FIG. 7 is a flowchart **700** of a method of wireless communication. The method may be performed by a UE, e.g., the UE **104**, which may include the memory **360** and which may be the entire UE **104** or a component of the UE **104**, such as the TX processor **368**, the RX processor **356**, and/or the controller/processor **359**.

(69) At **701**, the UE may transmit capability information in association with concurrent monitoring of a first PDCCH and a second PDCCH. For example, referring to FIG. 4, the UE **402** may transmit, at **406**, UE capability information to the base station **404**. The capability information may indicate a value for N, where $N \geq 1$.

(70) At **702**, the UE may monitor a first PDCCH on a first CC. For example, referring to FIG. 4, the UE **402** may monitor, at **408a**, a first PDCCH on the first CC.

(71) At **702a**, the first PDCCH may be configured to schedule one of a first PDSCH or a first PUSCH on a second CC. For example, referring to FIG. 5, the PDCCH associated with the SCell may be configured to schedule PDSCH or PUSCH on the PCell.

(72) At **702b**, the first PDCCH may have a first subcarrier spacing. For example, referring to FIGS. 6A-6B, the SCS of the SCell may be 60 kHz.

(73) At **702c**, the first PDCCH in association with the scheduling of the at least one of the first PDSCH or the first PUSCH on the second CC may be associated with at least one of a first number of PDCCH candidates or a first number of non-overlapped CCEs. For example, referring to FIGS. 5 and 6A-6B, the PDCCH associated with the cross-carrier scheduling of the PDSCH/PUSCH from the SCell to the PCell may be further associated with a number of BDs in a PDCCH monitoring occasion or a number of non-overlapping CCEs, as indicated in the diagrams **600-650**.

(74) At **702d**, the first PDCCH may have a first maximum number in association with the at least

one of the first number of PDCCH candidates or the first number of non-overlapped CCEs based on the first subcarrier spacing. For example, referring to FIG. 6B, the diagram 650 indicates that the number of BDs and non-overlapping CCEs for the SCell may not exceed a defined budget of the SCell based on the SCS of 60 kHz.

(75) At 704, the UE may monitor a second PDCCH on a second CC different than the first CC concurrently with the monitoring of the first PDCCH. For example, referring to FIG. 4, the UE 402 may monitor, at 408b, a second PDCCH on a second CC different from the first CC. The monitoring, at 408b, for the second PDCCH may be performed concurrently with the monitoring, at 408a, for the first PDCCH. As illustrated in the diagrams 600-650, the first CC may be associated with the SCell and the second CC may be associated with one of the PCell or the PSCell. In aspects, the first CC and the second CC may be in different frequency bands. For example, the first CC may be associated with a higher frequency range than the second CC.

(76) At 704a, the second PDCCH may be configured to schedule one of a second PDSCH or a second PUSCH on the second CC. For example, referring to FIG. 5, the PDCCH associated with the PCell may be configured to schedule PDSCH or PUSCH on the PCell.

(77) At 704b, the second PDCCH may have a second subcarrier spacing less than or equal to the first subcarrier spacing. For example, referring to FIGS. 6A-6B, the SCS of the PCell may be 15 kHz, which is less than the SCS of the SCell (e.g., 60 kHz). That is, the second subcarrier spacing may be less than the first subcarrier spacing.

(78) At 704c, the second PDCCH in association with the scheduling of the at least one of the second PDSCH or the second PUSCH on the second CC may be associated with at least one of a second number of PDCCH candidates or a second number of non-overlapped CCEs. For example, referring to FIGS. 5 and 6A-6B, the PDCCH associated with the PDSCH/PUSCH of the PCell may be further associated with a number of BDs in a PDCCH monitoring occasion or a number of non-overlapping CCEs, as indicated in the diagrams 600-650.

(79) At 704d, the second PDCCH may have a second maximum number in association with the at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs based on the second subcarrier spacing. For example, referring to FIG. 6B, the diagram 650 indicates that the number of BDs and non-overlapping CCEs for the PCell may not exceed a defined budget of the PCell based on the SCS of 15 kHz.

(80) At 706, a first sum of the first number of PDCCH candidates and the second number of PDCCH candidates may be less than or equal to N times the second maximum number in association with the second number of PDCCH candidates. For example, if the maximum number of PDCCH candidates is 44, referring to FIGS. 6A-6B, N times the total number of PDCCH candidates associated with the PCell and the SCell may be less than 44. In aspects, the value of N may be $N=1$. As a result, the total number of PDCCH candidates associated with the PCell and the SCell may not be more than 44. Additionally or alternatively, at 706, a second sum of the first number of non-overlapped CCEs and the second number of non-overlapped CCEs may be less than or equal to N times the second maximum number in association with the second number of non-overlapped CCEs.

(81) FIG. 8 is a flowchart 800 of a method of wireless communication. The method may be performed by a base station, e.g., the base station 102, which may include the memory 376 and which may be the entire base station 102 or a component of the base station 102, such as the TX processor 316, the RX processor 370, and/or the controller/processor 375.

(82) At 801, the base station may receive, from a UE, capability information in association with configuration of a first PDCCH and a second PDCCH. For example, referring to FIG. 4, the base station 404 may receive, at 406, UE capability information from the UE 402. The capability information may indicate a value for N, where $N \geq 1$.

(83) At 802, the base station may configure a first PDCCH on a first CC for a UE. For example, referring to FIG. 4, the base station 404 may configure, at 410a, a first PDCCH on the first CC for

the UE **402**.

(84) At **802a**, the first PDCCH may be configured to schedule one of a PDSCH or a first PUSCH on a second CC. For example, referring to FIG. 5, the PDCCH associated with the SCell may be configured to schedule PDSCH or PUSCH on the PCell.

(85) At **802b**, the first PDCCH may have a first subcarrier spacing. For example, referring to FIGS. 6A-6B, the SCS of the SCell may be 60 kHz.

(86) At **802c**, the first PDCCH in association with the scheduling of the at least one of the first PDSCH or the first PUSCH on the second CC may be associated with at least one of a first number of PDCCH candidates or a first number of non-overlapped CCEs. For example, referring to FIGS. 5 and 6A-6B, the PDCCH associated with the cross-carrier scheduling of the PDSCH/PUSCH from the SCell to the PCell may be further associated with a number of BDs in a PDCCH monitoring occasion or a number of non-overlapping CCEs, as indicated in the diagrams **600-650**.

(87) At **802d**, the first PDCCH may have a first maximum number in association with the at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs based on the first subcarrier spacing. For example, referring to FIG. 6B, the diagram **650** indicates that the number of BDs and non-overlapping CCEs for the SCell may not exceed a defined budget of the SCell based on the SCS of 60 kHz.

(88) At **804**, the base station may configure a second PDCCH on a second CC different than the first CC, the second PDCCH being concurrent with the first PDCCH. For example, referring to FIG. 4, the base station **404** may configure, at **410b**, a second PDCCH on a second CC for the UE **402** for scheduling a second PDSCH/second PUSCH on the second CC. As illustrated in the diagrams **600-650**, the first CC may be associated with the SCell and the second CC may be associated with one of the PCell or the PSCell. In aspects, the first CC and the second CC may be in different frequency bands. For example, the first CC may be associated with a higher frequency range than the second CC.

(89) At **804a**, the second PDCCH may be configured to schedule one of a second PDSCH or a second PUSCH on the second CC. For example, referring to FIG. 5, the PDCCH associated with the PCell may be configured to schedule PDSCH or PUSCH on the PCell.

(90) At **804b**, the second PDCCH may have a second subcarrier spacing less than or equal to the first subcarrier spacing. For example, referring to FIGS. 6A-6B, the SCS of the PCell may be 15 kHz, which is less than the SCS of the SCell (e.g., 60 kHz). That is, the second subcarrier spacing may be less than the first subcarrier spacing.

(91) At **804c**, the second PDCCH in association with the scheduling of the at least one of the second PDSCH or the second PUSCH on the second CC may be associated with at least one of a second number of PDCCH candidates or a second number of non-overlapped CCEs. For example, referring to FIGS. 5 and 6A-6B, the PDCCH associated with the PDSCH/PUSCH of the PCell may be further associated with a number of BDs in a PDCCH monitoring occasion or a number of non-overlapping CCEs, as indicated in the diagrams **600-650**.

(92) At **804d**, the second PDCCH may have a second maximum number in association with the at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs based on the second subcarrier spacing. For example, referring to FIG. 6B, the diagram **650** indicates that the number of BDs and non-overlapping CCEs for the PCell may not exceed a defined budget of the PCell based on the SCS of 15 kHz.

(93) At **806**, the base station may transmit, on at least one of the first PDCCH or the second PDCCH, DCI scheduling one of the first PDSCH, the first PUSCH, the second PDSCH, or the second PUSCH on the second CC. For example, referring to FIG. 4, the base station **404** may transmit, at **412**, DCI scheduling first/second PDSCH/PUSCH on the second CC. The sum of the PDCCH candidates and/or non-overlapping CCEs transmitted, at **412**, may be less than a predefined threshold.

(94) At **808**, the DCI may be associated with a first sum of the first number of PDCCH candidates

and the second number of PDCCH candidates, where the first sum may be less than or equal to N times the second maximum number in association with the second number of PDCCH candidates. For example, if the maximum number of PDCCH candidates is 44, referring to FIGS. 6A-6B, N times the total number of PDCCH candidates associated with the PCell and the SCell may be less than 44. In aspects, the value of N may be N=1. As a result, the total number of PDCCH candidates associated with the PCell and the SCell may not be more than 44. Additionally or alternatively, at **808**, the DCI may be associated with a second sum of the first number of non-overlapped CCEs and the second number of non-overlapped CCEs, where the second sum may be less than or equal to N times the second maximum number in association with the second number of non-overlapped CCEs.

(95) FIG. 9 is a diagram **900** illustrating an example of a hardware implementation for an apparatus **902**. The apparatus **902** is a UE and includes a cellular baseband processor **904** (also referred to as a modem) coupled to a cellular RF transceiver **922** and one or more subscriber identity modules (SIM) cards **920**, an application processor **906** coupled to a secure digital (SD) card **908** and a screen **910**, a Bluetooth module **912**, a wireless local area network (WLAN) module **914**, a Global Positioning System (GPS) module **916**, and a power supply **918**. The cellular baseband processor **904** communicates through the cellular RF transceiver **922** with the UE **104** and/or BS **102/180**. The cellular baseband processor **904** may include a computer-readable medium/memory. The computer-readable medium/memory may be non-transitory. The cellular baseband processor **904** is responsible for general processing, including the execution of software stored on the computer-readable medium/memory. The software, when executed by the cellular baseband processor **904**, causes the cellular baseband processor **904** to perform the various functions described supra. The computer-readable medium/memory may also be used for storing data that is manipulated by the cellular baseband processor **904** when executing software. The cellular baseband processor **904** further includes a reception component **930**, a communication manager **932**, and a transmission component **934**. The communication manager **932** includes the one or more illustrated components. The components within the communication manager **932** may be stored in the computer-readable medium/memory and/or configured as hardware within the cellular baseband processor **904**. The cellular baseband processor **904** may be a component of the UE **350** and may include the memory **360** and/or at least one of the TX processor **368**, the RX processor **356**, and the controller/processor **359**. In one configuration, the apparatus **902** may be a modem chip and include just the baseband processor **904**, and in another configuration, the apparatus **902** may be the entire UE (e.g., see **350** of FIG. 3) and include the aforesaid additional modules of the apparatus **902**.

(96) The communication manager **932** includes a monitor component **940** that is configured, e.g., as described in connection with **702** and **704**, to monitor a first PDCCH on a first CC; and monitor a second PDCCH on a second CC different than the first CC concurrently with the monitoring of the first PDCCH. The transmission component **934** is configured, e.g., as described in connection with **701**, to transmit capability information in association with the concurrent monitoring of the first PDCCH and the second PDCCH.

(97) The apparatus may include additional components that perform each of the blocks of the algorithm in the aforementioned flowcharts of FIG. 7. As such, each block in the aforementioned flowcharts of FIG. 7 may be performed by a component and the apparatus may include one or more of those components. The components may be one or more hardware components specifically configured to carry out the stated processes/algorithm, implemented by a processor configured to perform the stated processes/algorithm, stored within a computer-readable medium for implementation by a processor, or some combination thereof.

(98) In one configuration, the apparatus **902**, and in particular the cellular baseband processor **904**, includes means for monitoring a first physical downlink control channel (PDCCH) on a first component carrier (CC), the first PDCCH being configured to schedule one of a first physical downlink shared channel (PDSCH) or a first physical uplink shared channel (PUSCH) on a second

CC, the first PDCCH having a first subcarrier spacing, the first PDCCH in association with the scheduling of the one of the first PDSCH or the first PUSCH on the second CC being associated with at least one of a first number of PDCCH candidates or a first number of non-overlapped control channel elements (CCEs), the first PDCCH having a first maximum number in association with the at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs based on the first subcarrier spacing; and means for monitoring a second PDCCH on a second CC different than the first CC concurrently with the monitoring of the first PDCCH, the second PDCCH being configured to schedule one of a second PDSCH or a second PUSCH on the second CC, the second PDCCH having a second subcarrier spacing less than or equal to the first subcarrier spacing, the second PDCCH in association with the scheduling of the at least one of the second PDSCH or the second PUSCH on the second CC being associated with at least one of a second number of PDCCH candidates or a second number of non-overlapped CCEs, the second PDCCH having a second maximum number in association with the at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs based on the second subcarrier spacing, where at least one of a first sum of the first number of PDCCH candidates and the second number of PDCCH candidates is less than or equal to N times the second maximum number in association with the second number of PDCCH candidates, or a second sum of the first number of non-overlapped CCEs and the second number of non-overlapped CCEs is less than or equal to N times the second maximum number in association with the second number of non-overlapped CCEs. The aforementioned means may be one or more of the aforementioned components of the apparatus **902** configured to perform the functions recited by the aforementioned means. As described supra, the apparatus **902** may include the TX Processor **368**, the RX Processor **356**, and the controller/processor **359**. As such, in one configuration, the aforementioned means may be the TX Processor **368**, the RX Processor **356**, and the controller/processor **359** configured to perform the functions recited by the aforementioned means.

(99) FIG. **10** is a diagram **1000** illustrating an example of a hardware implementation for an apparatus **1002**. The apparatus **1002** is a BS and includes a baseband unit **1004**. The baseband unit **1004** may communicate through a cellular RF transceiver with the UE **104**. The baseband unit **1004** may include a computer-readable medium/memory. The baseband unit **1004** is responsible for general processing, including the execution of software stored on the computer-readable medium/memory. The software, when executed by the baseband unit **1004**, causes the baseband unit **1004** to perform the various functions described supra. The computer-readable medium/memory may also be used for storing data that is manipulated by the baseband unit **1004** when executing software. The baseband unit **1004** further includes a reception component **1030**, a communication manager **1032**, and a transmission component **1034**. The communication manager **1032** includes the one or more illustrated components. The components within the communication manager **1032** may be stored in the computer-readable medium/memory and/or configured as hardware within the baseband unit **1004**. The baseband unit **1004** may be a component of the BS **310** and may include the memory **376** and/or at least one of the TX processor **316**, the RX processor **370**, and the controller/processor **375**.

(100) The communication manager **1032** includes a configuration component **1040** that is configured, e.g., as described in connection with **802** and **804**, to configure a first PDCCH on a first CC for a UE; and configure a second PDCCH on a second CC different than the first CC. The transmission component **1034** is configured, e.g., as described in connection with **806**, to transmit, on at least one of the first PDCCH or the second PDCCH, DCI scheduling one of the first PDSCH, the first PUSCH, the second PDSCH, or the second PUSCH on the second CC.

(101) The apparatus may include additional components that perform each of the blocks of the algorithm in the aforementioned flowcharts of FIG. **8**. As such, each block in the aforementioned flowcharts of FIG. **8** may be performed by a component and the apparatus may include one or more of those components. The components may be one or more hardware components specifically

configured to carry out the stated processes/algorithm, implemented by a processor configured to perform the stated processes/algorithm, stored within a computer-readable medium for implementation by a processor, or some combination thereof.

(102) In one configuration, the apparatus **1002**, and in particular the baseband unit **1004**, includes means for configuring a first physical downlink control channel (PDCCH) on a first component carrier (CC) for a user equipment (UE), the first PDCCH being configured to schedule one of a first physical downlink shared channel (PDSCH) or a first physical uplink shared channel (PUSCH) on a second CC, the first PDCCH having a first subcarrier spacing, the first PDCCH in association with the scheduling of the one of the first PDSCH or the first PUSCH on the second CC being associated with at least one of a first number of PDCCH candidates or a first number of non-overlapped control channel elements (CCEs), the first PDCCH having a first maximum number in association with the at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs based on the first subcarrier spacing; means for configuring a second PDCCH on a second CC different than the first CC, the second PDCCH being configured to schedule one of a second PDSCH or a second PUSCH on the second CC, the second PDCCH being concurrent with the first PDCCH, the second PDCCH having a second subcarrier spacing less than or equal to the first subcarrier spacing, the second PDCCH in association with the scheduling of the at least one of the second PDSCH or the second PUSCH on the second CC being associated with at least one of a second number of PDCCH candidates or a second number of non-overlapped CCEs, the second PDCCH having a second maximum number in association with the at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs based on the second subcarrier spacing; and means for transmitting, on at least one of the first PDCCH or the second PDCCH, downlink control information (DCI) scheduling one of the first PDSCH, the first PUSCH, the second PDSCH, or the second PUSCH on the second CC, the DCI being associated with at least one of a first sum of the first number of PDCCH candidates and the second number of PDCCH candidates is less than or equal to N times the second maximum number in association with the second number of PDCCH candidates, or a second sum of the first number of non-overlapped CCEs and the second number of non-overlapped CCEs is less than or equal to N times the second maximum number in association with the second number of non-overlapped CCEs. The aforementioned means may be one or more of the aforementioned components of the apparatus **1002** configured to perform the functions recited by the aforementioned means. As described supra, the apparatus **1002** may include the TX Processor **316**, the RX Processor **370**, and the controller/processor **375**. As such, in one configuration, the aforementioned means may be the TX Processor **316**, the RX Processor **370**, and the controller/processor **375** configured to perform the functions recited by the aforementioned means.

(103) Accordingly, a total number of PDCCH candidates to be received from the SCell and the PCell/PSCell may need to be regulated based on the processing capabilities of the UE. In a first aspect, e.g., where the SCell and the PCell/PSCell use different numerologies, the maximum number of PDCCH candidates may be based on a predefined budget for the CC with the lowest SCS. That is, the total budget across both CCs may not exceed the budget associated with the lowest SCS. In a second aspect, the maximum number of PDCCH candidates may be counted separately per cell. UE capability information reported to the network may indicate whether the UE is configured to process the number of PDCCH candidates associated with the respective CCs.

(104) It is understood that the specific order or hierarchy of blocks in the processes/flowcharts disclosed is an illustration of example approaches. Based upon design preferences, it is understood that the specific order or hierarchy of blocks in the processes/flowcharts may be rearranged. Further, some blocks may be combined or omitted. The accompanying method claims present elements of the various blocks in a sample order, and are not meant to be limited to the specific order or hierarchy presented.

(105) The previous description is provided to enable any person skilled in the art to practice the

various aspects described herein. Various modifications to these aspects will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other aspects. Thus, the claims are not intended to be limited to the aspects shown herein, but is to be accorded the full scope consistent with the language claims, wherein reference to an element in the singular is not intended to mean “one and only one” unless specifically so stated, but rather “one or more.” Terms such as “if,” “when,” and “while” should be interpreted to mean “under the condition that” rather than imply an immediate temporal relationship or reaction. That is, these phrases, e.g., “when,” do not imply an immediate action in response to or during the occurrence of an action, but simply imply that if a condition is met then an action will occur, but without requiring a specific or immediate time constraint for the action to occur. The word “exemplary” is used herein to mean “serving as an example, instance, or illustration.” Any aspect described herein as “exemplary” is not necessarily to be construed as preferred or advantageous over other aspects. Unless specifically stated otherwise, the term “some” refers to one or more. Combinations such as “at least one of A, B, or C,” “one or more of A, B, or C,” “at least one of A, B, and C,” “one or more of A, B, and C,” and “A, B, C, or any combination thereof” include any combination of A, B, and/or C, and may include multiples of A, multiples of B, or multiples of C. Specifically, combinations such as “at least one of A, B, or C,” “one or more of A, B, or C,” “at least one of A, B, and C,” “one or more of A, B, and C,” and “A, B, C, or any combination thereof” may be A only, B only, C only, A and B, A and C, B and C, or A and B and C, where any such combinations may contain one or more member or members of A, B, or C. All structural and functional equivalents to the elements of the various aspects described throughout this disclosure that are known or later come to be known to those of ordinary skill in the art are expressly incorporated herein by reference and are intended to be encompassed by the claims. Moreover, nothing disclosed herein is intended to be dedicated to the public regardless of whether such disclosure is explicitly recited in the claims. The words “module,” “mechanism,” “element,” “device,” and the like may not be a substitute for the word “means.” As such, no claim element is to be construed as a means plus function unless the element is expressly recited using the phrase “means for.”

(106) The following aspects are illustrative only and may be combined with other aspects or teachings described herein, without limitation.

(107) Aspect 1 is an apparatus for wireless communication to be performed at a UE including at least one processor coupled to a memory and configured to monitor a first PDCCH on a first CC, the first PDCCH being configured to schedule one of a first PDSCH or a first PUSCH on a second CC, the first PDCCH having a first maximum number in association with at least one of a first number of PDCCH candidates or a first number of non-overlapped CCEs; and monitor a second PDCCH on a second CC different than the first CC concurrently with the monitoring of the first PDCCH, the second PDCCH being configured to schedule one of a second PDSCH or a second PUSCH on the second CC, the second PDCCH having a second maximum number in association with at least one of a second number of PDCCH candidates or a second number of non-overlapped CCEs, at least one of a first sum of the first number of PDCCH candidates and the second number of PDCCH candidates is less than or equal to N times the second maximum number in association with the second number of PDCCH candidates, or a second sum of the first number of non-overlapped CCEs and the second number of non-overlapped CCEs is less than or equal to N times the second maximum number in association with the second number of non-overlapped CCEs.

(108) Aspect 2 may be combined with aspect 1 and includes that the first PDCCH in association with the scheduling of the one of the first PDSCH or the first PUSCH on the second CC is associated with at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs, and the second PDCCH in association with the scheduling of the at least one of the second PDSCH or the second PUSCH on the second CC is associated with at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs.

(109) Aspect 3 may be combined with any of aspects 1-2 and includes that the first PDCCH

includes a first subcarrier spacing, and the second PDCCH includes a second subcarrier spacing that is less than or equal to the first subcarrier spacing.

(110) Aspect 4 may be combined with any of aspects 1-3 and includes that the first maximum number in association with the at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs is based on the first subcarrier spacing, and the second maximum number in association with the at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs is based on the second subcarrier spacing.

(111) Aspect 5 may be combined with any of aspects 1-4 and includes that the first CC is associated with an SCell, and the second CC is associated with one of a PCell or a PSCell.

(112) Aspect 6 may be combined with any of aspects 1-5 and includes that the first CC and the second CC are in different frequency bands.

(113) Aspect 7 may be combined with any of aspects 1-6 and includes that the first CC is associated with a higher frequency range than the second CC.

(114) Aspect 8 may be combined with any of aspects 1-7 and includes that N is a multiplier associated with a processing capability of the UE to process at least one of a total number of PDCCH candidates or a total number of non-overlapped CCEs, the total number of PDCCH candidates including the first number of PDCCH candidates and the second number of PDCCH candidates, the total number of non-overlapped CCEs including the first number of non-overlapped CCEs and the second number of non-overlapped CCEs.

(115) Aspect 9 may be combined with any of aspects 1-8 and includes that $N=1$.

(116) Aspect 10 may be combined with any of aspects 1-9 and includes that the at least one processor is further configured to transmit capability information in association with the concurrent monitoring of the first PDCCH and the second PDCCH, the capability information indicating a value for N, where $N \geq 1$.

(117) Aspect 11 is an apparatus for wireless communication to be performed at a base station including at least one processor coupled to a memory and configured to configure a first PDCCH on a first CC for a UE, the first PDCCH being configured to schedule one of a first PDSCH or a PUSCH on a second CC, the first PDCCH having a first maximum number in association with at least one of a first number of PDCCH candidates or a first number of non-overlapped CCEs; configure a second PDCCH on a second CC different than the first CC, the second PDCCH being configured to schedule one of a second PDSCH or a second PUSCH on the second CC, the second PDCCH being concurrent with the first PDCCH, the second PDCCH having a second maximum number in association with at least one of a second number of PDCCH candidates or a second number of non-overlapped CCEs; and transmit, on at least one of the first PDCCH or the second PDCCH, DCI scheduling one of the first PDSCH, the first PUSCH, the second PDSCH, or the second PUSCH on the second CC, the DCI associated with at least one of a first sum of the first number of PDCCH candidates and the second number of PDCCH candidates being less than or equal to N times the second maximum number in association with the second number of PDCCH candidates, or a second sum of the first number of non-overlapped CCEs and the second number of non-overlapped CCEs being less than or equal to N times the second maximum number in association with the second number of non-overlapped CCEs.

(118) Aspect 12 may be combined with aspect 11 and includes that the first PDCCH in association with the scheduling of the one of the first PDSCH or the first PUSCH on the second CC is associated with at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs, and the second PDCCH in association with the scheduling of the at least one of the second PDSCH or the second PUSCH on the second CC is associated with at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs.

(119) Aspect 13 may be combined with any of aspects 11-12 and includes that the first PDCCH includes a first subcarrier spacing, and the second PDCCH includes a second subcarrier spacing that is less than or equal to the first subcarrier spacing.

- (120) Aspect 14 may be combined with any of aspects 11-13 and includes that the first maximum number in association with the at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs is based on the first subcarrier spacing, and the second maximum number in association with the at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs is based on the second subcarrier spacing.
- (121) Aspect 15 may be combined with any of aspects 11-14 and includes that the first CC is associated with an SCell, and the second CC is associated with one of a PCell or a PSCell.
- (122) Aspect 16 may be combined with any of aspects 11-15 and includes that the first CC and the second CC are in different frequency bands.
- (123) Aspect 17 may be combined with any of aspects 11-16 and includes that the first CC is associated with a higher frequency range than the second CC.
- (124) Aspect 18 may be combined with any of aspects 11-17 and includes that N is a multiplier associated with a processing capability of the UE to process at least one of a total number of PDCCH candidates or a total number of non-overlapped CCEs, the total number of PDCCH candidates including the first number of PDCCH candidates and the second number of PDCCH candidates, the total number of non-overlapped CCEs including the first number of non-overlapped CCEs and the second number of non-overlapped CCEs.
- (125) Aspect 19 may be combined with any of aspects 11-18 and includes that $N=1$.
- (126) Aspect 20 may be combined with any of aspects 11-19 and includes that the at least one processor is further configured to receive, from the UE, capability information in association with concurrent configuration of the first PDCCH and the second PDCCH, the capability information indicating a value for N, where $N \geq 1$.
- (127) Aspect 21 may be combined with any of aspects 1-20 and further includes that a transceiver is coupled to the at least one processor.
- (128) Aspect 22 is a method of wireless communication for implementing any of aspects 1-21.
- (129) Aspect 23 is an apparatus for wireless communication including means for implementing any of aspects 1-21.
- (130) Aspect 24 is a computer-readable medium storing computer executable code, the code when executed by at least one processor causes the at least one processor to implement any of aspects 1-21.

Claims

1. An apparatus for wireless communication to be performed at a user equipment (UE), comprising: memory; and at least one processor coupled to the memory and configured to: monitor a first physical downlink control channel (PDCCH) on a first component carrier (CC) associated with a secondary cell (SCell), the first PDCCH being configured to schedule one of a first physical downlink shared channel (PDSCH) or a first physical uplink shared channel (PUSCH) on a second CC associated with one of a primary cell (PCell) or a primary secondary cell (PSCell), the first PDCCH having a first maximum number in association with at least one of a first number of PDCCH candidates or a first number of non-overlapped control channel elements (CCEs), wherein the first maximum number is defined for the first CC; monitor a second PDCCH on the second CC concurrently with the monitoring of the first PDCCH, the second PDCCH being configured to schedule one of a second PDSCH or a second PUSCH on the second CC, the second PDCCH having a second maximum number in association with at least one of a second number of PDCCH candidates or a second number of non-overlapped CCEs, wherein the second maximum number is defined for the second CC; and receive, via at least one of the first PDCCH or the second PDCCH, downlink control information (DCI) scheduling one of the first PDSCH, the first PUSCH, the second PDSCH, or the second PUSCH on the second CC, wherein at least one of a first sum of the first number of PDCCH candidates and the second number of PDCCH candidates is less than or

equal to N times the second maximum number in association with the second number of PDCCH candidates or N times the first maximum number in association with the first number of PDCCH candidates, or a second sum of the first number of non-overlapped CCEs and the second number of non-overlapped CCEs is less than or equal to N times the second maximum number in association with the second number of non-overlapped CCEs or N times the first maximum number in association with the first number of non-overlapped CCEs, wherein N is a positive integer, and wherein N is based on a hash function.

2. The apparatus of claim 1, wherein the first PDCCH in association with the scheduling of the one of the first PDSCH or the first PUSCH on the second CC is associated with at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs, and wherein the second PDCCH in association with the scheduling of the at least one of the second PDSCH or the second PUSCH on the second CC is associated with at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs.

3. The apparatus of claim 1, wherein the first PDCCH includes a first subcarrier spacing, and wherein the second PDCCH includes a second subcarrier spacing that is less than or equal to the first subcarrier spacing.

4. The apparatus of claim 3, wherein the first maximum number in association with the at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs is based on the first subcarrier spacing, and wherein the second maximum number in association with the at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs is based on the second subcarrier spacing.

5. The apparatus of claim 1, wherein one of the PCell or the PSCell is associated with a first scheduling cell and a second scheduling cell.

6. The apparatus of claim 5, wherein the first CC and the second CC are in different frequency bands.

7. The apparatus of claim 6, wherein the first CC is associated with a higher frequency range than the second CC.

8. The apparatus of claim 1, wherein N is a multiplier associated with a processing capability of the UE to process at least one of a total number of PDCCH candidates or a total number of non-overlapped CCEs, the total number of PDCCH candidates including the first number of PDCCH candidates and the second number of PDCCH candidates, the total number of non-overlapped CCEs including the first number of non-overlapped CCEs and the second number of non-overlapped CCEs.

9. The apparatus of claim 8, wherein $N=1$.

10. The apparatus of claim 1, wherein the at least one processor is further configured to transmit capability information in association with the concurrent monitoring of the first PDCCH and the second PDCCH, the capability information indicating a value for N, where $N \geq 1$.

11. An apparatus for wireless communication to be performed at a base station, comprising: memory; and at least one processor coupled to the memory and configured to: configure, for a user equipment (UE), a first physical downlink control channel (PDCCH) on a first component carrier (CC) associated with a secondary cell (SCell), the first PDCCH being configured to schedule one of a first physical downlink shared channel (PDSCH) or a first physical uplink shared channel (PUSCH) on a second CC associated with one of a primary cell (PCell) or a primary secondary cell (PSCell), the first PDCCH having a first maximum number in association with at least one of a first number of PDCCH candidates or a first number of non-overlapped control channel elements (CCEs), wherein the first maximum number is defined for the first CC; configure, for the UE, a second PDCCH on the second CC, the second PDCCH being configured to schedule one of a second PDSCH or a second PUSCH on the second CC, the second PDCCH being concurrent with the first PDCCH, the second PDCCH having a second maximum number in association with at least one of a second number of PDCCH candidates or a second number of non-overlapped CCEs,

wherein the second maximum number is defined for the second CC; and transmit, via at least one of the first PDCCH or the second PDCCH, downlink control information (DCI) scheduling one of the first PDSCH, the first PUSCH, the second PDSCH, or the second PUSCH on the second CC, the DCI associated with at least one of a first sum of the first number of PDCCH candidates and the second number of PDCCH candidates being less than or equal to N times the second maximum number in association with the second number of PDCCH candidates or N times the first maximum number in association with the first number of PDCCH candidates, or a second sum of the first number of non-overlapped CCEs and the second number of non-overlapped CCEs being less than or equal to N times the second maximum number in association with the second number of non-overlapped CCEs or N times the first maximum number in association with the first number of non-overlapped CCEs, wherein N is a positive integer, and wherein N is based on a hash function.

12. The apparatus of claim 11, wherein the first PDCCH in association with the scheduling of the one of the first PDSCH or the first PUSCH on the second CC is associated with at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs, and wherein the second PDCCH in association with the scheduling of the at least one of the second PDSCH or the second PUSCH on the second CC is associated with at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs.

13. The apparatus of claim 11, wherein the first PDCCH includes a first subcarrier spacing, and wherein the second PDCCH includes a second subcarrier spacing that is less than or equal to the first subcarrier spacing.

14. The apparatus of claim 13, wherein the first maximum number in association with the at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs is based on the first subcarrier spacing, and wherein the second maximum number in association with the at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs is based on the second subcarrier spacing.

15. The apparatus of claim 11, wherein one of the PCell or the PSCell is associated with a first scheduling cell and a second scheduling cell.

16. The apparatus of claim 15, wherein the first CC and the second CC are in different frequency bands.

17. The apparatus of claim 16, wherein the first CC is associated with a higher frequency range than the second CC.

18. The apparatus of claim 11, wherein N is a multiplier associated with a processing capability of the UE to process at least one of a total number of PDCCH candidates or a total number of non-overlapped CCEs, the total number of PDCCH candidates including the first number of PDCCH candidates and the second number of PDCCH candidates, the total number of non-overlapped CCEs including the first number of non-overlapped CCEs and the second number of non-overlapped CCEs.

19. The apparatus of claim 11, wherein $N=1$.

20. The apparatus of claim 11, wherein the at least one processor is further configured to receive, from the UE, capability information in association with concurrent configuration of the first PDCCH and the second PDCCH, the capability information indicating a value for N , where $N \geq 1$.

21. A method of wireless communication to be performed at a user equipment (UE), comprising: monitoring a first physical downlink control channel (PDCCH) on a first component carrier (CC) associated with a secondary cell (SCell), the first PDCCH being configured to schedule one of a first physical downlink shared channel (PDSCH) or a first physical uplink shared channel (PUSCH) on a second CC associated with one of a primary cell (PCell) or a primary secondary cell (PSCell), the first PDCCH having a first maximum number in association with at least one of a first number of PDCCH candidates or a first number of non-overlapped control channel elements (CCEs), wherein the first maximum number is defined for the first CC; monitoring a second PDCCH on a second CC concurrently with the monitoring of the first PDCCH, the second PDCCH

being configured to schedule one of a second PDSCH or a second PUSCH on the second CC, the second PDCCH having a second maximum number in association with at least one of a second number of PDCCH candidates or a second number of non-overlapped CCEs, wherein the second maximum number is defined for the second CC; and receiving, via at least one of the first PDCCH or the second PDCCH, downlink control information (DCI) scheduling one of the first PDSCH, the first PUSCH, the second PDSCH, or the second PUSCH on the second CC, wherein at least one of a first sum of the first number of PDCCH candidates and the second number of PDCCH candidates is less than or equal to N times the second maximum number in association with the second number of PDCCH candidates or N times the first maximum number in association with the first number of PDCCH candidates, or a second sum of the first number of non-overlapped CCEs and the second number of non-overlapped CCEs is less than or equal to N times the second maximum number in association with the second number of non-overlapped CCEs or N times the first maximum number in association with the first number of non-overlapped CCEs, wherein N is a positive integer, and wherein N is based on a hash function.

22. The method of claim 21, wherein the first PDCCH in association with the scheduling of the one of the first PDSCH or the first PUSCH on the second CC is associated with at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs, and wherein the second PDCCH in association with the scheduling of the at least one of the second PDSCH or the second PUSCH on the second CC is associated with at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs.

23. The method of claim 21, wherein the first PDCCH includes a first subcarrier spacing, and wherein the second PDCCH includes a second subcarrier spacing that is less than or equal to the first subcarrier spacing.

24. The method of claim 23, wherein the first maximum number in association with the at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs is based on the first subcarrier spacing, and wherein the second maximum number in association with the at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs is based on the second subcarrier spacing.

25. The method of claim 21, wherein one of the PCell or the PSCell is associated with a first scheduling cell and a second scheduling cell.

26. A method of wireless communication to be performed at a base station, comprising: configuring, for a user equipment (UE), a first physical downlink control channel (PDCCH) on a first component carrier (CC) associated with a secondary cell (SCell), the first PDCCH being configured to schedule one of a first physical downlink shared channel (PDSCH) or a first physical uplink shared channel (PUSCH) on a second CC associated with one of a primary cell (PCell) or a primary secondary cell (PSCell), the first PDCCH having a first maximum number in association with at least one of a first number of PDCCH candidates or a first number of non-overlapped control channel elements (CCEs), wherein the first maximum number is defined for the first CC; configuring a second PDCCH on the second CC, the second PDCCH being configured to schedule one of a second PDSCH or a second PUSCH on the second CC, the second PDCCH being concurrent with the first PDCCH, the second PDCCH having a second maximum number in association with at least one of a second number of PDCCH candidates or a second number of non-overlapped CCEs, wherein the second maximum number is defined for the second CC; and transmitting, via at least one of the first PDCCH or the second PDCCH, downlink control information (DCI) scheduling one of the first PDSCH, the first PUSCH, the second PDSCH, or the second PUSCH on the second CC, the DCI associated with at least one of a first sum of the first number of PDCCH candidates and the second number of PDCCH candidates being less than or equal to N times the second maximum number in association with the second number of PDCCH candidates or N times the first maximum number in association with the first number of PDCCH candidates, or a second sum of the first number of non-overlapped CCEs and the second number of

non-overlapped CCEs being less than or equal to N times the second maximum number in association with the second number of non-overlapped CCEs or N times the first maximum number in association with the first number of non-overlapped CCEs, wherein N is a positive integer, and wherein N is based on a hash function.

27. The method of claim 26, wherein the first PDCCH in association with the scheduling of the one of the first PDSCH or the first PUSCH on the second CC is associated with at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs, and wherein the second PDCCH in association with the scheduling of the at least one of the second PDSCH or the second PUSCH on the second CC is associated with at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs.

28. The method of claim 26, wherein the first PDCCH includes a first subcarrier spacing, and wherein the second PDCCH includes a second subcarrier spacing that is less than or equal to the first subcarrier spacing.

29. The method of claim 28, wherein the first maximum number in association with the at least one of the first number of PDCCH candidates or the first number of non-overlapped CCEs is based on the first subcarrier spacing, and wherein the second maximum number in association with the at least one of the second number of PDCCH candidates or the second number of non-overlapped CCEs is based on the second subcarrier spacing.

30. The method of claim 26, wherein one of the PCell or the PSCell is associated with a first scheduling cell and a second scheduling cell.

31. An apparatus for wireless communication at a user equipment (UE), comprising: memory; and at least one processor coupled to the memory and configured to: monitor a first physical downlink control channel (PDCCH) on a first component carrier (CC) associated with a secondary cell (SCell) without monitoring for a common search space (CSS), the first PDCCH being configured to schedule one of a first physical downlink shared channel (PDSCH) or a first physical uplink shared channel (PUSCH) on a second CC associated with one of a primary cell (PCell) or a primary secondary cell (PSCell), the first PDCCH having a first maximum number in association with at least one of a first number of PDCCH candidates or a first number of non-overlapped control channel elements (CCEs), wherein the first maximum number is defined for the first CC, wherein a first subcarrier spacing for the PCell or the PSCell is less than or equal to a second subcarrier spacing for the SCell; monitor a second PDCCH and the CSS on the second CC, the second PDCCH being configured to schedule one of a second PDSCH or a second PUSCH on the second CC, the second PDCCH having a second maximum number in association with at least one of a second number of PDCCH candidates or a second number of non-overlapped CCEs, wherein the second maximum number is defined for the second CC, wherein to monitor the second PDCCH, the at least one processor is configured to monitor no more than a maximum quantity of total PDCCH candidates per slot or a maximum quantity of total CCEs per slot, wherein the maximum quantity of total PDCCH candidates per slot is based on the first number of PDCCH candidates and the second number of PDCCH candidates or the maximum quantity of total CCEs per slot is based on the first number of CCEs and the second number of CCEs; and receive, via at least one of the first PDCCH or the second PDCCH, downlink control information (DCI) scheduling one of the first PDSCH, the first PUSCH, the second PDSCH, or the second PUSCH on the second CC.
