

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12415031
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Kamen; Dean et al.

Wearable pump assembly

Abstract

A wearable infusion pump assembly includes a reusable housing assembly, and a disposable housing assembly including a reservoir for receiving an infusible fluid. A releasable engagement assembly is configured to allow the reusable housing assembly to releasably engage the disposable housing assembly. A detachable external infusion set is configured to deliver the infusible fluid to a user.

Inventors: Kamen; Dean (Bedford, NH), Gray; Larry B. (Merrimack, NH), Lanigan; Richard J. (Concord, NH), Kerwin; John Matthew (Manchester, NH), Fichera; Stephen Lewis (Salem, NH)

Applicant: DEKA Products Limited Partnership (Manchester, NH)

Family ID: 1000008821168

Assignee: DEKA PRODUCTS LIMITED PARTNERSHIP (Manchester, NH)

Appl. No.: 17/703313

Filed: March 24, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20220211937 A1	Jul. 07, 2022

Related U.S. Application Data

continuation parent-doc US 15388341 20161222 US 11285259 child-doc US 17703313
continuation parent-doc US 12347982 20081231 US 9526830 child-doc US 15388341
us-provisional-application US 61101105 20080929
us-provisional-application US 61101115 20080929
us-provisional-application US 61101077 20080929
us-provisional-application US 61101053 20080929
us-provisional-application US 61023645 20080125
us-provisional-application US 61018042 20071231
us-provisional-application US 61017989 20071231
us-provisional-application US 61018339 20071231
us-provisional-application US 61018054 20071231
us-provisional-application US 61018002 20071231

Publication Classification

Int. Cl.: A61M5/142 (20060101); A61J1/20 (20060101); A61M5/14 (20060101); A61M5/145 (20060101); A61M5/168 (20060101); A61M5/172 (20060101); F04B7/00 (20060101); F04B43/02 (20060101); F04B43/09 (20060101); G01F22/00 (20060101); G05D7/06 (20060101); A61B5/00 (20060101); A61B5/155 (20060101); A61M5/158 (20060101); A61M5/162 (20060101); A61M5/36 (20060101); A61M5/50 (20060101); F04B43/12 (20060101); G05B23/02 (20060101); G08C17/02 (20060101); H04B7/26 (20060101)

U.S. Cl.:

CPC **A61M5/14248** (20130101); **A61J1/20** (20130101); **A61M5/1413** (20130101); **A61M5/142** (20130101); **A61M5/14212** (20130101); **A61M5/14216** (20130101); **A61M5/14224** (20130101); **A61M5/14244** (20130101); **A61M5/1452** (20130101); **A61M5/14586** (20130101); **A61M5/168** (20130101); **A61M5/16804** (20130101); **A61M5/16809** (20130101); **A61M5/16831** (20130101); **A61M5/172** (20130101); **F04B7/00** (20130101); **F04B43/02** (20130101); **F04B43/09** (20130101); **G01F22/00** (20130101); **G05D7/0676** (20130101); A61B5/0024 (20130101); A61B5/1427 (20130101); A61B5/6833 (20130101); A61B2560/0412 (20130101); A61M2005/1402 (20130101); A61M2005/14208 (20130101); A61M2005/14252 (20130101); A61M2005/14268 (20130101); A61M2005/14506 (20130101); A61M5/158 (20130101); A61M2005/1583 (20130101); A61M2005/1585 (20130101); A61M2005/1586 (20130101); A61M5/162 (20130101); A61M5/16813 (20130101); A61M2005/16863 (20130101); A61M5/16886 (20130101); A61M5/1723 (20130101); A61M5/365 (20130101); A61M5/5086 (20130101); A61M2205/0266 (20130101); A61M2205/0294 (20130101); A61M2205/04 (20130101); A61M2205/16 (20130101); A61M2205/18 (20130101); A61M2205/3303 (20130101); A61M2205/3331 (20130101); A61M2205/3337 (20130101); A61M2205/3368 (20130101); A61M2205/3375 (20130101); A61M2205/3379 (20130101); A61M2205/3523 (20130101); A61M2205/3546 (20130101); A61M2205/3569 (20130101); A61M2205/3576 (20130101); A61M2205/3592 (20130101); A61M2205/50 (20130101); A61M2205/502 (20130101); A61M2205/52 (20130101); A61M2205/581 (20130101); A61M2205/582 (20130101); A61M2205/583 (20130101); A61M2205/6018 (20130101); A61M2205/8206 (20130101); A61M2205/8237 (20130101); A61M2206/22 (20130101); A61M2207/00 (20130101); A61M2209/045 (20130101); A61M2209/086 (20130101); A61M2230/201 (20130101); F04B43/1253 (20130101); G05B23/02 (20130101); G05D7/0647 (20130101); G08C17/02 (20130101); H04B7/2609 (20130101); Y10T29/49236 (20150115); Y10T29/494 (20150115); Y10T29/49412 (20150115); Y10T29/49826 (20150115); Y10T29/49828 (20150115)

Field of Classification Search

CPC: A61M (5/14248); A61M (5/1413); A61M (5/14244); A61M (5/16809); A61M (5/172); A61M (2005/14208)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2122722	12/1937	O'Neill	N/A	N/A
2308974	12/1942	Harper	N/A	N/A
2677372	12/1953	Barnish, Jr. et al.	N/A	N/A
3075382	12/1962	Mathias	N/A	N/A
3261330	12/1965	Arant et al.	N/A	N/A
3512748	12/1969	Wilson	N/A	N/A
3631847	12/1971	Hobbs, II	N/A	N/A
3722557	12/1972	Huggins	N/A	N/A
3752510	12/1972	Windischman et al.	N/A	N/A
3762673	12/1972	Koslovsky	N/A	N/A
3811121	12/1973	Heim et al.	N/A	N/A
3811122	12/1973	Raber et al.	N/A	N/A
3833030	12/1973	Waldbauer, Jr. et al.	N/A	N/A
3837339	12/1973	Aisenberg et al.	N/A	N/A
3887393	12/1974	La Rue, Jr.	N/A	N/A
3915171	12/1974	Shermeta	N/A	N/A
3951147	12/1975	Tucker et al.	N/A	N/A
3965946	12/1975	D'Alo	N/A	N/A
D248873	12/1977	Raitto	N/A	N/A
4123631	12/1977	Lewis	N/A	N/A
D254446	12/1979	Raitto	N/A	N/A
4206274	12/1979	Peels	N/A	N/A
4215701	12/1979	Raitto	N/A	N/A
4258711	12/1980	Tucker et al.	N/A	N/A
4261561	12/1980	Ilon	N/A	N/A
4265241	12/1980	Portner et al.	N/A	N/A
4269908	12/1980	Stemme	N/A	N/A
4270532	12/1980	Franetzki et al.	N/A	N/A
4273121	12/1980	Jassawalla	N/A	N/A
4278225	12/1980	Phelps	N/A	N/A
4282872	12/1980	Franetzki et al.	N/A	N/A
4296949	12/1980	Muettert et al.	N/A	N/A
4303376	12/1980	Siekmann	N/A	N/A
4331262	12/1981	Snyder et al.	N/A	N/A
4360019	12/1981	Portner et al.	N/A	N/A

4371594	12/1982	Ohara et al.	N/A	N/A
4373527	12/1982	Fischell	N/A	N/A
4391883	12/1982	Williamson et al.	N/A	N/A
4392849	12/1982	Peter et al.	N/A	N/A
4395259	12/1982	Prestele et al.	N/A	N/A
4411652	12/1982	Kramer et al.	N/A	N/A
4437859	12/1983	Whitehouse et al.	N/A	N/A
4443218	12/1983	DeCant, Jr. et al.	N/A	N/A
4453523	12/1983	Poehlman	N/A	N/A
4453931	12/1983	Pastrone	N/A	N/A
4464170	12/1983	Clemens et al.	N/A	N/A
4469481	12/1983	Kobayashi	N/A	N/A
4474061	12/1983	Parker	N/A	N/A
4475901	12/1983	Kraegen et al.	N/A	N/A
4486190	12/1983	Reinicke	N/A	N/A
4494950	12/1984	Fischell	N/A	N/A
4498843	12/1984	Schneider et al.	N/A	N/A
4525165	12/1984	Fischell	N/A	N/A
4533346	12/1984	Cosgrove, Jr. et al.	N/A	N/A
4542532	12/1984	McQuilkin	N/A	N/A
4543093	12/1984	Christinger	N/A	N/A
4550731	12/1984	Batina et al.	N/A	N/A
4559037	12/1984	Franetzki et al.	N/A	N/A
4559038	12/1984	Berg et al.	N/A	N/A
4562751	12/1985	Nason et al.	N/A	N/A
4596575	12/1985	Rosenberg et al.	N/A	N/A
4604090	12/1985	Reinicke	N/A	N/A
4626243	12/1985	Singh et al.	N/A	N/A
4633878	12/1986	Bombardieri	N/A	N/A
4641154	12/1986	Mikalsen	N/A	N/A
4645489	12/1986	Krumme et al.	N/A	N/A
4657490	12/1986	Abbott	N/A	N/A
4673396	12/1986	Urbaniak	N/A	N/A
4678408	12/1986	Nason et al.	N/A	N/A
4685903	12/1986	Cable et al.	N/A	N/A
4690878	12/1986	Nakamura	N/A	N/A
4696671	12/1986	Epstein et al.	N/A	N/A
4699615	12/1986	Fischell et al.	N/A	N/A
4704902	12/1986	Doshi	N/A	N/A
4723947	12/1987	Konopka	N/A	N/A
4731051	12/1987	Fischell	N/A	N/A
4731726	12/1987	Allen, III	N/A	N/A
4734092	12/1987	Millerd	N/A	N/A
4735441	12/1987	Stephens	N/A	N/A
4741731	12/1987	Starck et al.	N/A	N/A
4743895	12/1987	Alexander	N/A	N/A
4747828	12/1987	Tseo	N/A	N/A
4790028	12/1987	Ramage	N/A	N/A
4803625	12/1988	Fu et al.	N/A	N/A
4804368	12/1988	Skakoon et al.	N/A	N/A
4809697	12/1988	Causey, III et al.	N/A	N/A
4811595	12/1988	Marciniak et al.	N/A	N/A
4826810	12/1988	Aoki	N/A	N/A
4849852	12/1988	Mullins	N/A	N/A
4856340	12/1988	Garrison	N/A	N/A
4871351	12/1988	Feingold	N/A	N/A
4880712	12/1988	Gordecki	N/A	N/A
4881063	12/1988	Fawcett	N/A	N/A
4898578	12/1989	Rubalcaba, Jr.	N/A	N/A
4919650	12/1989	Feingold et al.	N/A	N/A
4930494	12/1989	Takehana et al.	N/A	N/A
4959640	12/1989	Hall	N/A	N/A
4972508	12/1989	King	N/A	N/A
4976162	12/1989	Kamen	N/A	N/A
4988337	12/1990	Ito	N/A	N/A

4997423	12/1990	Ojuda et al.	N/A	N/A
5009646	12/1990	Sudo et al.	N/A	N/A
5019974	12/1990	Beckers	N/A	N/A
5034004	12/1990	Crankshaw	N/A	N/A
5049141	12/1990	Olive	N/A	N/A
5050612	12/1990	Matsumura	N/A	N/A
5055001	12/1990	Natwick et al.	N/A	N/A
5055830	12/1990	Cousins et al.	N/A	N/A
5056744	12/1990	Ludwig	N/A	N/A
5063291	12/1990	Buehring	N/A	N/A
5067532	12/1990	Lang et al.	N/A	N/A
5067943	12/1990	Burke	N/A	N/A
5075653	12/1990	Ito et al.	N/A	N/A
5078683	12/1991	Sancoff et al.	N/A	N/A
5080653	12/1991	Voss et al.	N/A	N/A
5100380	12/1991	Epstein et al.	N/A	N/A
5101814	12/1991	Palti	N/A	N/A
5102388	12/1991	Richmond	N/A	N/A
5103216	12/1991	Sisselman	N/A	N/A
5104374	12/1991	Bishko et al.	N/A	N/A
5150314	12/1991	Garratt et al.	N/A	N/A
5153827	12/1991	Coutr� et al.	N/A	N/A
5163909	12/1991	Stewart	N/A	N/A
5165407	12/1991	Wilson et al.	N/A	N/A
5174716	12/1991	Hora et al.	N/A	N/A
5176502	12/1992	Sanderson et al.	N/A	N/A
5176644	12/1992	Srisathapat et al.	N/A	N/A
5176662	12/1992	Bartholomew et al.	N/A	N/A
5187746	12/1992	Narisawa	N/A	N/A
5191855	12/1992	Conforti	N/A	N/A
5197322	12/1992	Indravudh	N/A	N/A
5197895	12/1992	Stupecky	N/A	N/A
5211201	12/1992	Kamen et al.	N/A	N/A
5211626	12/1992	Frank et al.	N/A	N/A
5216597	12/1992	Beckers	N/A	N/A
5217442	12/1992	Davis	N/A	N/A
5222946	12/1992	Kamen	N/A	N/A
5248569	12/1992	Pine et al.	N/A	N/A
5254093	12/1992	Bartlett et al.	N/A	N/A
5254096	12/1992	Rondelet et al.	N/A	N/A
5257971	12/1992	Lord et al.	N/A	N/A
5257980	12/1992	VanAntwerp et al.	N/A	N/A
5266013	12/1992	Aubert et al.	N/A	N/A
5270702	12/1992	Krolak	N/A	N/A
5290639	12/1993	Mallory	N/A	N/A
5307263	12/1993	Brown	N/A	N/A
5314416	12/1993	Lewis et al.	N/A	N/A
5317506	12/1993	Coutr� et al.	N/A	N/A
5337215	12/1993	Sunderland et al.	N/A	N/A
5338157	12/1993	Blomquist	N/A	N/A
5339821	12/1993	Fujimoto	N/A	N/A
5341291	12/1993	Roizen et al.	N/A	N/A
5349852	12/1993	Kamen et al.	N/A	N/A
5350411	12/1993	Ryan et al.	N/A	N/A
5357427	12/1993	Langen et al.	N/A	N/A
5364346	12/1993	Schrezenmeir	N/A	N/A
5368562	12/1993	Blomquist et al.	N/A	N/A
5370622	12/1993	Livingston et al.	N/A	N/A
5372133	12/1993	Hogen Esch	N/A	N/A
5376070	12/1993	Purvis et al.	N/A	N/A
5380173	12/1994	Hellstrom	N/A	N/A
5383865	12/1994	Michel	N/A	N/A
5390671	12/1994	Lord et al.	N/A	N/A
5391157	12/1994	Harris et al.	N/A	N/A
5399166	12/1994	Laing	N/A	N/A

5399823	12/1994	McCusker	N/A	N/A
5403648	12/1994	Chan et al.	N/A	N/A
5411482	12/1994	Campbell	N/A	N/A
5427737	12/1994	Glazer et al.	N/A	N/A
5429602	12/1994	Hauser	N/A	N/A
5429605	12/1994	Richling et al.	N/A	N/A
5433710	12/1994	VanAntwerp et al.	N/A	N/A
5439444	12/1994	Andersen et al.	N/A	N/A
5456940	12/1994	Funderburk	N/A	N/A
5460618	12/1994	Harreld	N/A	N/A
5462525	12/1994	Srisathapat et al.	N/A	N/A
5464392	12/1994	Epstein et al.	N/A	N/A
5466218	12/1994	Srisathapat et al.	N/A	N/A
5472317	12/1994	Field et al.	N/A	N/A
5476460	12/1994	Montalvo	N/A	N/A
5478211	12/1994	Dominiak et al.	N/A	N/A
5482446	12/1995	Williamson et al.	N/A	N/A
5487738	12/1995	Sciulli	N/A	N/A
5497772	12/1995	Schulman et al.	N/A	N/A
5505709	12/1995	Funderburk et al.	N/A	N/A
5514103	12/1995	Srisathapat et al.	N/A	N/A
5526844	12/1995	Kamen et al.	N/A	N/A
5527307	12/1995	Srisathapat et al.	N/A	N/A
5528359	12/1995	Taguchi	N/A	N/A
5533381	12/1995	Seale	N/A	N/A
5533389	12/1995	Kamen et al.	N/A	N/A
5543588	12/1995	Bisset et al.	N/A	N/A
5545140	12/1995	Conero et al.	N/A	N/A
5545152	12/1995	Funderburkl et al.	N/A	N/A
5558640	12/1995	Pfeiler et al.	N/A	N/A
5569186	12/1995	Lord et al.	N/A	N/A
5569187	12/1995	Kaiser	N/A	N/A
5573506	12/1995	Vasko	N/A	N/A
5575310	12/1995	Kamen et al.	N/A	N/A
5575631	12/1995	Jester	N/A	N/A
5582593	12/1995	Hultman	N/A	N/A
5582793	12/1995	Glazer et al.	N/A	N/A
5584813	12/1995	Livingston et al.	N/A	N/A
5586868	12/1995	Lawless et al.	N/A	N/A
5593390	12/1996	Castellano et al.	N/A	N/A
5594368	12/1996	Usami	N/A	N/A
5607418	12/1996	Arzbaecher	N/A	N/A
5609060	12/1996	Dent	N/A	N/A
5609575	12/1996	Larson et al.	N/A	N/A
5620312	12/1996	Hyman et al.	N/A	N/A
5626144	12/1996	Tacklind et al.	N/A	N/A
5630710	12/1996	Tune et al.	N/A	N/A
5637095	12/1996	Nason et al.	N/A	N/A
5637420	12/1996	Jones, Jr. et al.	N/A	N/A
5641892	12/1996	Larkins et al.	N/A	N/A
5643212	12/1996	Coutr� et al.	N/A	N/A
5647853	12/1996	Feldmann et al.	N/A	N/A
5651775	12/1996	Walker et al.	N/A	N/A
5658133	12/1996	Anderson et al.	N/A	N/A
5660176	12/1996	Iliff	N/A	N/A
5660529	12/1996	Hill	N/A	N/A
5665065	12/1996	Colman et al.	N/A	N/A
5669887	12/1996	Cooper	N/A	N/A
5678568	12/1996	Uchikubo et al.	N/A	N/A
5681285	12/1996	Ford et al.	N/A	N/A
5685844	12/1996	Marttila	N/A	N/A
5687734	12/1996	Dempsey et al.	N/A	N/A
5704366	12/1997	Tacklind et al.	N/A	N/A
5704520	12/1997	Gross	N/A	N/A
5713857	12/1997	Grimard et al.	N/A	N/A

5713865	12/1997	Manning et al.	N/A	N/A
5716725	12/1997	Riveron et al.	N/A	N/A
5727241	12/1997	Yamano et al.	N/A	N/A
5733673	12/1997	Kunert	N/A	N/A
5752940	12/1997	Grimard	N/A	N/A
5755683	12/1997	Houle et al.	N/A	N/A
5755744	12/1997	Shaw et al.	N/A	N/A
5764159	12/1997	Neftel	N/A	N/A
5769608	12/1997	Seale	N/A	N/A
5772635	12/1997	Dastur et al.	N/A	N/A
5772637	12/1997	Heinzmann et al.	N/A	N/A
5779665	12/1997	Mastrototaro et al.	N/A	N/A
5785681	12/1997	Indravudh	N/A	N/A
5788673	12/1997	Young et al.	N/A	N/A
5788678	12/1997	Van Antwerp	N/A	N/A
5795337	12/1997	Grimard	N/A	N/A
5800387	12/1997	Duffy et al.	N/A	N/A
5800420	12/1997	Gross et al.	N/A	N/A
5807336	12/1997	Russo et al.	N/A	N/A
5814015	12/1997	Gargano et al.	N/A	N/A
5822715	12/1997	Worthington et al.	N/A	N/A
5827262	12/1997	Neftel et al.	N/A	N/A
5832448	12/1997	Brown	N/A	N/A
5840020	12/1997	Heinonen et al.	N/A	N/A
5840026	12/1997	Uber, III et al.	N/A	N/A
5846258	12/1997	Takayanagi et al.	N/A	N/A
5851197	12/1997	Marano et al.	N/A	N/A
5851692	12/1997	Potts	N/A	N/A
5855509	12/1998	White et al.	N/A	N/A
5861018	12/1998	Feierbach	N/A	N/A
5868669	12/1998	Iliff	N/A	N/A
5871465	12/1998	Vasko	N/A	N/A
5871478	12/1998	Berrigan	N/A	N/A
5879163	12/1998	Brown et al.	N/A	N/A
5882256	12/1998	Shropshire	N/A	N/A
5885245	12/1998	Lynch et al.	N/A	N/A
5897493	12/1998	Brown	N/A	N/A
5899855	12/1998	Brown	N/A	N/A
5913310	12/1998	Brown	N/A	N/A
5918603	12/1998	Brown	N/A	N/A
5925021	12/1998	Castellano et al.	N/A	N/A
5927351	12/1998	Zhu et al.	N/A	N/A
5928202	12/1998	Linnebjerg	N/A	N/A
5931791	12/1998	Saltzstein et al.	N/A	N/A
5933136	12/1998	Brown	N/A	N/A
5935105	12/1998	Manning et al.	N/A	N/A
5940801	12/1998	Brown	N/A	N/A
5951521	12/1998	Mastrototaro et al.	N/A	N/A
5954697	12/1998	Srisathapat et al.	N/A	N/A
5954700	12/1998	Kovelman	N/A	N/A
5956501	12/1998	Brown	N/A	N/A
5957890	12/1998	Mann et al.	N/A	N/A
5960403	12/1998	Brown	N/A	N/A
5973623	12/1998	Gupta et al.	N/A	N/A
5997476	12/1998	Brown	N/A	N/A
5997546	12/1998	Foster et al.	N/A	N/A
6007941	12/1998	Hermann et al.	N/A	N/A
6009339	12/1998	Bentsen et al.	N/A	N/A
6014587	12/1999	Shaw et al.	N/A	N/A
6032119	12/1999	Brown et al.	N/A	N/A
6056718	12/1999	Funderburk et al.	N/A	N/A
6073036	12/1999	Heikkinen et al.	N/A	N/A
6090081	12/1999	Sudo et al.	N/A	N/A
6093172	12/1999	Funderburk et al.	N/A	N/A
6101478	12/1999	Brown	N/A	N/A

6110152	12/1999	Kovelman	N/A	N/A
6119684	12/1999	Nöhl et al.	N/A	N/A
6135949	12/1999	Russo et al.	N/A	N/A
6165154	12/1999	Gray et al.	N/A	N/A
6171287	12/2000	Lynn et al.	N/A	N/A
6206856	12/2000	Mahurkar	N/A	N/A
6208107	12/2000	Maske et al.	N/A	N/A
6211856	12/2000	Choi et al.	N/A	N/A
6225711	12/2000	Gupta et al.	N/A	N/A
6241704	12/2000	Peterson et al.	N/A	N/A
6246992	12/2000	Brown	N/A	N/A
6248093	12/2000	Moberg	N/A	N/A
6253804	12/2000	Safabash	N/A	N/A
6254586	12/2000	Mann et al.	N/A	N/A
6259587	12/2000	Sheldon et al.	N/A	N/A
6264631	12/2000	Willis et al.	N/A	N/A
6269340	12/2000	Ford et al.	N/A	N/A
6270455	12/2000	Brown	N/A	N/A
6280416	12/2000	Van Antwerp et al.	N/A	N/A
6283943	12/2000	Dy et al.	N/A	N/A
6293925	12/2000	Safabash et al.	N/A	N/A
6309375	12/2000	Flines et al.	N/A	N/A
6311868	12/2000	Krietemeier et al.	N/A	N/A
6321158	12/2000	DeLorme et al.	N/A	N/A
6341629	12/2001	Clark et al.	N/A	N/A
6362591	12/2001	Moberg	N/A	N/A
6364213	12/2001	Baltz	N/A	N/A
6375638	12/2001	Nason et al.	N/A	N/A
6416293	12/2001	Bouchard et al.	N/A	N/A
6423035	12/2001	Das et al.	N/A	N/A
6427088	12/2001	Bowman, IV et al.	N/A	N/A
6428509	12/2001	Fielder	N/A	N/A
6447470	12/2001	Bodenschatz et al.	N/A	N/A
6447481	12/2001	Duchon et al.	N/A	N/A
6453956	12/2001	Safabash	N/A	N/A
6458102	12/2001	Mann et al.	N/A	N/A
6458424	12/2001	Yoshida et al.	N/A	N/A
6461329	12/2001	Van Antwerp et al.	N/A	N/A
6461331	12/2001	Van Antwerp	N/A	N/A
6466203	12/2001	Van Ee	N/A	N/A
6475183	12/2001	Epstein et al.	N/A	N/A
6475196	12/2001	Vachon	N/A	N/A
6485461	12/2001	Mason et al.	N/A	N/A
6485465	12/2001	Moberg et al.	N/A	N/A
6506179	12/2002	Tiefenthal et al.	N/A	N/A
6520938	12/2002	Funderburk et al.	N/A	N/A
6537268	12/2002	Gibson et al.	N/A	N/A
6549423	12/2002	Brodnick	N/A	N/A
6551276	12/2002	Mann et al.	N/A	N/A
6551277	12/2002	Ford	N/A	N/A
6554798	12/2002	Mann et al.	N/A	N/A
6554800	12/2002	Nezhadian et al.	N/A	N/A
6555986	12/2002	Moberg	N/A	N/A
6558320	12/2002	Causey, III et al.	N/A	N/A
6558351	12/2002	Steil et al.	N/A	N/A
6562001	12/2002	Lebel et al.	N/A	N/A
6564105	12/2002	Starkweather et al.	N/A	N/A
6569462	12/2002	Cornelli et al.	N/A	N/A
6571128	12/2002	Lebel et al.	N/A	N/A
6572542	12/2002	Houben et al.	N/A	N/A
6574958	12/2002	MacGregor	N/A	N/A
6577899	12/2002	Lebel et al.	N/A	N/A
6581648	12/2002	Zolentroff et al.	N/A	N/A
RE38189	12/2002	Walker et al.	N/A	N/A
6585644	12/2002	Lebel et al.	N/A	N/A

6585695	12/2002	Adair et al.	N/A	N/A
6589229	12/2002	Connelly et al.	N/A	N/A
6591876	12/2002	Safabash	N/A	N/A
6592551	12/2002	Cobb	N/A	N/A
6595756	12/2002	Gray et al.	N/A	N/A
6604908	12/2002	Bryant et al.	N/A	N/A
6607509	12/2002	Bobroff et al.	N/A	N/A
D480477	12/2002	Bush et al.	N/A	N/A
6641533	12/2002	Causey, III et al.	N/A	N/A
6642936	12/2002	Engholm et al.	N/A	N/A
6648821	12/2002	Lebel et al.	N/A	N/A
6652510	12/2002	Lord et al.	N/A	N/A
6656148	12/2002	Das et al.	N/A	N/A
6656158	12/2002	Mahoney et al.	N/A	N/A
6656159	12/2002	Flaherty	N/A	N/A
6659948	12/2002	Lebel et al.	N/A	N/A
6665909	12/2002	Collins et al.	N/A	N/A
6669669	12/2002	Flaherty et al.	N/A	N/A
6684058	12/2003	Karacaoglu et al.	N/A	N/A
6685678	12/2003	Evans et al.	N/A	N/A
6687546	12/2003	Lebel et al.	N/A	N/A
6689091	12/2003	Bui et al.	N/A	N/A
6691043	12/2003	Ribeiro, Jr.	N/A	N/A
6692457	12/2003	Flaherty	N/A	N/A
6694191	12/2003	Starkweather et al.	N/A	N/A
6699218	12/2003	Flaherty et al.	N/A	N/A
6702779	12/2003	Connelly et al.	N/A	N/A
6704034	12/2003	Rodriguez et al.	N/A	N/A
6716195	12/2003	Nolan, Jr. et al.	N/A	N/A
6723072	12/2003	Flaherty et al.	N/A	N/A
6733446	12/2003	Lebel et al.	N/A	N/A
6740059	12/2003	Flaherty	N/A	N/A
6740072	12/2003	Starkweather et al.	N/A	N/A
6740075	12/2003	Lebel et al.	N/A	N/A
6743205	12/2003	Nolan, Jr. et al.	N/A	N/A
6744350	12/2003	Blomquist	N/A	N/A
6749586	12/2003	Vasko	N/A	N/A
6749587	12/2003	Flaherty	N/A	N/A
6752299	12/2003	Shetler et al.	N/A	N/A
6752785	12/2003	Van Antwerp et al.	N/A	N/A
6752787	12/2003	Causey, III et al.	N/A	N/A
6758810	12/2003	Lebel et al.	N/A	N/A
6768425	12/2003	Flaherty et al.	N/A	N/A
6770067	12/2003	Lorenzen et al.	N/A	N/A
6772650	12/2003	Ohyama et al.	N/A	N/A
6800071	12/2003	McConnell et al.	N/A	N/A
6801420	12/2003	Talbot et al.	N/A	N/A
6805693	12/2003	Gray et al.	N/A	N/A
6810290	12/2003	Lebel et al.	N/A	N/A
6811533	12/2003	Lebel et al.	N/A	N/A
6811534	12/2003	Bowman, IV et al.	N/A	N/A
6813519	12/2003	Lebel et al.	N/A	N/A
6817990	12/2003	Yap et al.	N/A	N/A
6827702	12/2003	Lebel et al.	N/A	N/A
6830558	12/2003	Flaherty et al.	N/A	N/A
6845465	12/2004	Hashemi	N/A	N/A
6852104	12/2004	Blomquist	N/A	N/A
6854620	12/2004	Ramey	N/A	N/A
6872200	12/2004	Mann et al.	N/A	N/A
6873268	12/2004	Lebel et al.	N/A	N/A
6879930	12/2004	Sinclair et al.	N/A	N/A
6902207	12/2004	Lickliter	N/A	N/A
6930602	12/2004	Villaseca et al.	N/A	N/A
6932584	12/2004	Gray et al.	N/A	N/A
6936029	12/2004	Mann et al.	N/A	N/A

6939324	12/2004	Gonnelli et al.	N/A	N/A
6945760	12/2004	Gray et al.	N/A	N/A
6950708	12/2004	Bowman IV et al.	N/A	N/A
6958705	12/2004	Lebel et al.	N/A	N/A
6960192	12/2004	Flaherty et al.	N/A	N/A
6960195	12/2004	Heinz et al.	N/A	N/A
6964643	12/2004	Hovland et al.	N/A	N/A
6974437	12/2004	Lebel et al.	N/A	N/A
6978517	12/2004	Collins et al.	N/A	N/A
6979326	12/2004	Mann et al.	N/A	N/A
6994619	12/2005	Scholten	N/A	N/A
6997905	12/2005	Gillespie, Jr. et al.	N/A	N/A
6997907	12/2005	Safabash et al.	N/A	N/A
6997910	12/2005	Howlett et al.	N/A	N/A
6997920	12/2005	Mann et al.	N/A	N/A
6997921	12/2005	Gray et al.	N/A	N/A
6999854	12/2005	Roth	N/A	N/A
7011608	12/2005	Spencer	N/A	N/A
7018360	12/2005	Flaherty et al.	N/A	N/A
7021560	12/2005	Gray et al.	N/A	N/A
7024245	12/2005	Lebel et al.	N/A	N/A
7025226	12/2005	Ramey	N/A	N/A
7025743	12/2005	Mann et al.	N/A	N/A
7029455	12/2005	Flaherty	N/A	N/A
7029456	12/2005	Ware et al.	N/A	N/A
7033339	12/2005	Lynn	N/A	N/A
7041082	12/2005	Blomquist et al.	N/A	N/A
7045361	12/2005	Heiss et al.	N/A	N/A
7050927	12/2005	Sinclair et al.	N/A	N/A
7052251	12/2005	Nason et al.	N/A	N/A
7061140	12/2005	Zhang et al.	N/A	N/A
7063684	12/2005	Moberg	N/A	N/A
7064230	12/2005	Titterington et al.	N/A	N/A
7066029	12/2005	Beavis et al.	N/A	N/A
7074209	12/2005	Evans et al.	N/A	N/A
7075512	12/2005	Fabre et al.	N/A	N/A
7083719	12/2005	Bowman, Jr. et al.	N/A	N/A
7098803	12/2005	Mann et al.	N/A	N/A
7109878	12/2005	Mann et al.	N/A	N/A
7115113	12/2005	Evans et al.	N/A	N/A
7131967	12/2005	Gray et al.	N/A	N/A
7137964	12/2005	Flaherty	N/A	N/A
7144384	12/2005	Gorman et al.	N/A	N/A
7146977	12/2005	Beavis et al.	N/A	N/A
7238164	12/2006	Childers et al.	N/A	N/A
7297132	12/2006	Perlo et al.	N/A	N/A
7303549	12/2006	Flaherty et al.	N/A	N/A
7305984	12/2006	Altobelli et al.	N/A	N/A
7342660	12/2007	Altobelli et al.	N/A	N/A
7548314	12/2008	Altobelli et al.	N/A	N/A
7559524	12/2008	Gray et al.	N/A	N/A
7621687	12/2008	Rehkemper et al.	N/A	N/A
7766885	12/2009	Olsen	N/A	N/A
7806166	12/2009	Tilton et al.	N/A	N/A
7819840	12/2009	Burnside et al.	N/A	N/A
7867189	12/2010	Childers et al.	N/A	N/A
8137314	12/2011	Mounce et al.	N/A	N/A
8273049	12/2011	Demers et al.	N/A	N/A
8414563	12/2012	Kamen et al.	N/A	N/A
8545445	12/2012	Kamen et al.	N/A	N/A
9526830	12/2015	Kamen	N/A	A61M 5/16809
10933187	12/2020	Murphy et al.	N/A	N/A
11027058	12/2020	Lanier, Jr. et al.	N/A	N/A
2001/0034502	12/2000	Moberg et al.	N/A	N/A
2001/0041869	12/2000	Causey, III et al.	N/A	N/A

2001/0056258	12/2000	Evans	N/A	N/A
2002/0002326	12/2001	Causey, III et al.	N/A	N/A
2002/0013613	12/2001	Haller et al.	N/A	N/A
2002/0013614	12/2001	Thompson	N/A	N/A
2002/0022798	12/2001	Connelly et al.	N/A	N/A
2002/0022807	12/2001	Duchon et al.	N/A	N/A
2002/0038392	12/2001	De La Huerga	N/A	N/A
2002/0040208	12/2001	Flaherty et al.	N/A	N/A
2002/0043951	12/2001	Moberg	N/A	N/A
2002/0045856	12/2001	Jaafar et al.	N/A	N/A
2002/0052539	12/2001	Haller et al.	N/A	N/A
2002/0052574	12/2001	Hochman et al.	N/A	N/A
2002/0056114	12/2001	Fillebrown et al.	N/A	N/A
2002/0072720	12/2001	Hague et al.	N/A	N/A
2002/0072733	12/2001	Flaherty	N/A	N/A
2002/0077852	12/2001	Ford et al.	N/A	N/A
2002/0082665	12/2001	Haller et al.	N/A	N/A
2002/0091454	12/2001	Vasko	N/A	N/A
2002/0107481	12/2001	Reilly et al.	N/A	N/A
2002/0116080	12/2001	Birnbach et al.	N/A	N/A
2002/0123672	12/2001	Christophersom et al.	N/A	N/A
2002/0126036	12/2001	Flaherty et al.	N/A	N/A
2002/0143290	12/2001	Bui et al.	N/A	N/A
2002/0158838	12/2001	Smith et al.	N/A	N/A
2002/0165477	12/2001	Dunshee	N/A	N/A
2002/0169439	12/2001	Flaherty	N/A	N/A
2002/0173748	12/2001	McConnell et al.	N/A	N/A
2002/0193679	12/2001	Malave et al.	N/A	N/A
2002/0193724	12/2001	Stebbins et al.	N/A	N/A
2002/0193846	12/2001	Pool et al.	N/A	N/A
2003/0073952	12/2002	Flaherty et al.	N/A	N/A
2003/0076306	12/2002	Zadesky et al.	N/A	N/A
2003/0088238	12/2002	Poulsen et al.	N/A	N/A
2003/0114836	12/2002	Estes et al.	N/A	N/A
2003/0125672	12/2002	Adair et al.	N/A	N/A
2003/0132922	12/2002	Philipp	N/A	N/A
2003/0136189	12/2002	Lauman et al.	N/A	N/A
2003/0141981	12/2002	Bui et al.	N/A	N/A
2003/0161744	12/2002	Vilks et al.	N/A	N/A
2003/0163089	12/2002	Bynum	N/A	N/A
2003/0163090	12/2002	Blomquist et al.	N/A	N/A
2003/0187525	12/2002	Mann et al.	N/A	N/A
2003/0191431	12/2002	Mann et al.	N/A	N/A
2003/0195462	12/2002	Mann et al.	N/A	N/A
2003/0198558	12/2002	Nason et al.	N/A	N/A
2003/0212364	12/2002	Mann et al.	N/A	N/A
2003/0212379	12/2002	Bylund et al.	N/A	N/A
2003/0220598	12/2002	Busby et al.	N/A	N/A
2003/0221118	12/2002	Walker	N/A	N/A
2003/0229311	12/2002	Morris et al.	N/A	N/A
2003/0233069	12/2002	Gillespie, Jr. et al.	N/A	N/A
2004/0003493	12/2003	Adair et al.	N/A	N/A
2004/0015131	12/2003	Flaherty et al.	N/A	N/A
2004/0046137	12/2003	Herbert et al.	N/A	N/A
2004/0059315	12/2003	Erickson et al.	N/A	N/A
2004/0059316	12/2003	Smedegaard	N/A	N/A
2004/0064088	12/2003	Gorman et al.	N/A	N/A
2004/0064096	12/2003	Flaherty et al.	N/A	N/A
2004/0068230	12/2003	Estes et al.	N/A	N/A
2004/0073095	12/2003	Causey, III et al.	N/A	N/A
2004/0073161	12/2003	Tachibana	N/A	N/A
2004/0078028	12/2003	Flaherty et al.	N/A	N/A
2004/0082918	12/2003	Evans et al.	N/A	N/A
2004/0092873	12/2003	Moberg	N/A	N/A
2004/0106899	12/2003	McMichael et al.	N/A	N/A

2004/0115067	12/2003	Rush et al.	N/A	N/A
2004/0116893	12/2003	Spohn et al.	N/A	N/A
2004/0116905	12/2003	Pedersen et al.	N/A	N/A
2004/0121767	12/2003	Simpson et al.	N/A	N/A
2004/0124549	12/2003	Curran	N/A	N/A
2004/0127958	12/2003	Mazar et al.	N/A	N/A
2004/0133166	12/2003	Moberg et al.	N/A	N/A
2004/0140304	12/2003	Leyendecker	N/A	N/A
2004/0147874	12/2003	Kliem et al.	N/A	N/A
2004/0152961	12/2003	Carlson et al.	N/A	N/A
2004/0158193	12/2003	Bui et al.	N/A	N/A
2004/0162528	12/2003	Horvath et al.	N/A	N/A
2004/0172301	12/2003	Mihai et al.	N/A	N/A
2004/0173024	12/2003	McKeon	N/A	N/A
2004/0176667	12/2003	Mihai et al.	N/A	N/A
2004/0176725	12/2003	Stutz, Jr. et al.	N/A	N/A
2004/0193090	12/2003	Lebel et al.	N/A	N/A
2004/0204673	12/2003	Flaherty	N/A	N/A
2004/0207404	12/2003	Zhang et al.	N/A	N/A
2004/0235446	12/2003	Flaherty et al.	N/A	N/A
2004/0243065	12/2003	McConnell et al.	N/A	N/A
2004/0260233	12/2003	Garibotto et al.	N/A	N/A
2005/0015056	12/2004	Duchon et al.	N/A	N/A
2005/0021000	12/2004	Adair et al.	N/A	N/A
2005/0022274	12/2004	Campbell et al.	N/A	N/A
2005/0027254	12/2004	Vasko	N/A	N/A
2005/0035956	12/2004	Sinclair et al.	N/A	N/A
2005/0038325	12/2004	Moll	N/A	N/A
2005/0048900	12/2004	Scholten	N/A	N/A
2005/0052429	12/2004	Philipp	N/A	N/A
2005/0055242	12/2004	Bello et al.	N/A	N/A
2005/0055244	12/2004	Mullan et al.	N/A	N/A
2005/0062732	12/2004	Sinclair et al.	N/A	N/A
2005/0063857	12/2004	Alheidt et al.	N/A	N/A
2005/0065464	12/2004	Talbot et al.	N/A	N/A
2005/0065466	12/2004	Vedrine	N/A	N/A
2005/0065817	12/2004	Mihai et al.	N/A	N/A
2005/0069425	12/2004	Gray et al.	N/A	N/A
2005/0085760	12/2004	Ware et al.	N/A	N/A
2005/0137530	12/2004	Campbell et al.	N/A	N/A
2005/0137573	12/2004	McLaughlin	N/A	N/A
2005/0148938	12/2004	Blomquist	N/A	N/A
2005/0171491	12/2004	Minh Miner et al.	N/A	N/A
2005/0171512	12/2004	Flaherty	N/A	N/A
2005/0171513	12/2004	Mann et al.	N/A	N/A
2005/0177111	12/2004	Ozeri et al.	N/A	N/A
2005/0182366	12/2004	Vogt et al.	N/A	N/A
2005/0182389	12/2004	LaPorte et al.	N/A	N/A
2005/0187515	12/2004	Varrichio et al.	N/A	N/A
2005/0187593	12/2004	Housworth et al.	N/A	N/A
2005/0192494	12/2004	Ginsberg	N/A	N/A
2005/0192561	12/2004	Mernoe	N/A	N/A
2005/0197654	12/2004	Edman et al.	N/A	N/A
2005/0203461	12/2004	Flaherty et al.	N/A	N/A
2005/0215982	12/2004	Malave et al.	N/A	N/A
2005/0222631	12/2004	Dalal et al.	N/A	N/A
2005/0224705	12/2004	Tobiason et al.	N/A	N/A
2005/0230575	12/2004	Zelenski et al.	N/A	N/A
2005/0234404	12/2004	Vilks et al.	N/A	N/A
2005/0238503	12/2004	Rush et al.	N/A	N/A
2005/0238507	12/2004	DiIanni et al.	N/A	N/A
2005/0245878	12/2004	Mernoe et al.	N/A	N/A
2005/0250368	12/2004	Singer et al.	N/A	N/A
2005/0252260	12/2004	Chu	N/A	N/A
2005/0261660	12/2004	Singer et al.	N/A	N/A

2005/0267363	12/2004	Duchon et al.	N/A	N/A
2005/0267550	12/2004	Hess et al.	N/A	N/A
2005/0273059	12/2004	Mernoe et al.	N/A	N/A
2005/0273081	12/2004	Olsen	N/A	N/A
2005/0273082	12/2004	Olsen	N/A	N/A
2005/0285880	12/2004	Lai et al.	N/A	N/A
2006/0016800	12/2005	Paradiso et al.	N/A	N/A
2006/0025663	12/2005	Talbot	128/903	A61B 5/412
2006/0026535	12/2005	Hotelling et al.	N/A	N/A
2006/0026536	12/2005	Hotelling et al.	N/A	N/A
2006/0038791	12/2005	Mackey	N/A	N/A
2006/0041229	12/2005	Garibotto et al.	N/A	N/A
2006/0066581	12/2005	Lyon et al.	N/A	N/A
2006/0097991	12/2005	Hotelling et al.	N/A	N/A
2006/0100591	12/2005	Alheidt et al.	N/A	N/A
2006/0106346	12/2005	Sullivan et al.	N/A	N/A
2006/0122577	12/2005	Poulsen et al.	N/A	N/A
2006/0129112	12/2005	Lynn	N/A	N/A
2006/0144942	12/2005	Evans et al.	N/A	N/A
2006/0160670	12/2005	Spencer	N/A	N/A
2006/0161870	12/2005	Hotelling et al.	N/A	N/A
2006/0161871	12/2005	Hotelling et al.	N/A	N/A
2006/0173406	12/2005	Hayes et al.	N/A	N/A
2006/0173444	12/2005	Choy et al.	N/A	N/A
2006/0178633	12/2005	Garibotto et al.	N/A	N/A
2006/0178836	12/2005	Bai et al.	N/A	N/A
2006/0184084	12/2005	Ware et al.	N/A	N/A
2006/0184123	12/2005	Gillespie, Jr. et al.	N/A	N/A
2006/0184154	12/2005	Moberg et al.	N/A	N/A
2006/0200257	12/2005	Kirste et al.	N/A	N/A
2006/0227117	12/2005	Proctor	N/A	N/A
2006/0229557	12/2005	Fathallah et al.	N/A	N/A
2006/0232554	12/2005	Wong et al.	N/A	N/A
2006/0236262	12/2005	Bathiche et al.	N/A	N/A
2006/0236263	12/2005	Bathiche et al.	N/A	N/A
2006/0253085	12/2005	Geismar et al.	N/A	N/A
2006/0264889	12/2005	Moberg et al.	N/A	N/A
2006/0264894	12/2005	Moberg et al.	N/A	N/A
2006/0276714	12/2005	Holt et al.	N/A	N/A
2006/0282290	12/2005	Flaherty et al.	N/A	N/A
2006/0287783	12/2005	Walker	N/A	N/A
2007/0049870	12/2006	Gray et al.	N/A	N/A
2007/0088259	12/2006	Chu et al.	N/A	N/A
2007/0088271	12/2006	Richards	N/A	N/A
2007/0106218	12/2006	Yodfat et al.	N/A	N/A
2007/0118405	12/2006	Campbell et al.	N/A	N/A
2007/0133736	12/2006	Chen et al.	N/A	N/A
2007/0167912	12/2006	Causey et al.	N/A	N/A
2007/0179549	12/2006	Russie	N/A	N/A
2007/0219480	12/2006	Kamen et al.	N/A	N/A
2007/0219496	12/2006	Kamen et al.	N/A	N/A
2007/0219597	12/2006	Kamen et al.	N/A	N/A
2007/0228071	12/2006	Kamen et al.	N/A	N/A
2007/0265533	12/2006	Tran	N/A	N/A
2007/0265813	12/2006	Unal et al.	N/A	N/A
2008/0009824	12/2007	Moberg et al.	N/A	N/A
2008/0097315	12/2007	Miner et al.	N/A	N/A
2008/0097375	12/2007	Bikovsky	N/A	N/A
2008/0097381	12/2007	Moberg et al.	N/A	N/A
2008/0119790	12/2007	Hawkins et al.	N/A	N/A
2008/0125064	12/2007	Das et al.	N/A	N/A
2008/0160492	12/2007	Campbell et al.	N/A	N/A
2008/0161757	12/2007	Nayak et al.	N/A	N/A
2008/0208627	12/2007	Skyggebjerg	N/A	N/A
2008/0215035	12/2007	Yodfat et al.	N/A	N/A

2008/0294094	12/2007	Mhatre et al.	N/A	N/A
2008/0294142	12/2007	Patel	604/151	A61M 5/16831
2008/0312584	12/2007	Montgomery	600/300	G16H 40/67
2008/0312585	12/2007	Brukalo et al.	N/A	N/A
2009/0198215	12/2008	Chong et al.	N/A	N/A
2009/0213373	12/2008	Altobelli et al.	N/A	N/A
2009/0275896	12/2008	Kamen et al.	N/A	N/A
2009/0299277	12/2008	Kamen et al.	N/A	N/A
2009/0299289	12/2008	Kamen et al.	N/A	N/A
2011/0009824	12/2010	Yodfat et al.	N/A	N/A
2011/0029260	12/2010	Altobelli et al.	N/A	N/A
2011/0079220	12/2010	Altobelli et al.	N/A	N/A
2011/0144616	12/2010	Michaud et al.	N/A	N/A
2011/0190694	12/2010	Lanier, Jr. et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2 493 649	12/2004	CA	N/A
1476566	12/2003	CN	N/A
1556716	12/2003	CN	N/A
2673404	12/2004	CN	N/A
1688344	12/2004	CN	N/A
4329229	12/1994	DE	N/A
19627619	12/1997	DE	N/A
142866	12/1984	EP	N/A
0 209 677	12/1986	EP	N/A
0 338 671	12/1988	EP	N/A
0 420 620	12/1990	EP	N/A
0 724 889	12/1995	EP	N/A
0 763 368	12/1996	EP	N/A
806738	12/1996	EP	N/A
0 554 995	12/1996	EP	N/A
0 816 677	12/1997	EP	N/A
0 970 655	12/1999	EP	N/A
1 095 668	12/2000	EP	N/A
1338295	12/2002	EP	N/A
0 830 597	12/2003	EP	N/A
1464351	12/2003	EP	N/A
1109586	12/2003	EP	N/A
1473050	12/2003	EP	N/A
1115435	12/2004	EP	N/A
1347705	12/2004	EP	N/A
1007137	12/2005	EP	N/A
1423079	12/2005	EP	N/A
1 135 056	12/2005	EP	N/A
1688085	12/2005	EP	N/A
1702635	12/2005	EP	N/A
1545657	12/2005	EP	N/A
1546556	12/2005	EP	N/A
1341569	12/2006	EP	N/A
1461070	12/2006	EP	N/A
1309366	12/2006	EP	N/A
0 944 648	12/2006	EP	N/A
1646412	12/2006	EP	N/A
2053378	12/1980	GB	N/A
2218831	12/1988	GB	N/A
3155758	12/2000	JP	N/A
2005-507688	12/2004	JP	N/A
2005-525141	12/2004	JP	N/A
2006-504476	12/2005	JP	N/A
20065033598	12/2005	JP	N/A
2007502148	12/2006	JP	N/A
2007-097009	12/2006	JP	N/A
2007-207106	12/2006	JP	N/A
1131285	12/1994	RU	N/A
2111018	12/1997	RU	N/A

2240142	12/2003	RU	N/A
8505657	12/1984	WO	N/A
92/08957	12/1991	WO	N/A
93/09409	12/1992	WO	N/A
9323096	12/1992	WO	N/A
94/08647	12/1993	WO	N/A
95/24229	12/1994	WO	N/A
95/27852	12/1994	WO	N/A
95/31233	12/1994	WO	N/A
96/08281	12/1995	WO	N/A
96/14100	12/1995	WO	N/A
96/20745	12/1995	WO	N/A
96/36389	12/1995	WO	N/A
96/40330	12/1995	WO	N/A
199641156	12/1995	WO	N/A
97/09923	12/1996	WO	N/A
97/21456	12/1996	WO	N/A
97/40482	12/1996	WO	N/A
98/14234	12/1997	WO	N/A
98/20439	12/1997	WO	N/A
98/24358	12/1997	WO	N/A
98/42407	12/1997	WO	N/A
98/49659	12/1997	WO	N/A
98/59487	12/1997	WO	N/A
99/08183	12/1998	WO	N/A
99/10801	12/1998	WO	N/A
99/18532	12/1998	WO	N/A
99/22236	12/1998	WO	N/A
99/48546	12/1998	WO	N/A
99/59663	12/1998	WO	N/A
00/10628	12/1999	WO	N/A
00/28217	12/1999	WO	N/A
00/30529	12/1999	WO	N/A
01/00261	12/2000	WO	N/A
01/52990	12/2000	WO	N/A
01/061616	12/2000	WO	N/A
01/70304	12/2000	WO	N/A
01/76684	12/2000	WO	N/A
02/04047	12/2001	WO	N/A
02/20073	12/2001	WO	N/A
02/28454	12/2001	WO	N/A
02/34331	12/2001	WO	N/A
02/40083	12/2001	WO	N/A
02/49509	12/2001	WO	N/A
02/56945	12/2001	WO	N/A
02/067122	12/2001	WO	N/A
02/070049	12/2001	WO	N/A
02/074406	12/2001	WO	N/A
2002068015	12/2001	WO	N/A
03/024504	12/2002	WO	N/A
03/033051	12/2002	WO	N/A
03/037403	12/2002	WO	N/A
03/053498	12/2002	WO	N/A
03/059372	12/2002	WO	N/A
03/059422	12/2002	WO	N/A
2003/059372	12/2002	WO	N/A
03/063932	12/2002	WO	N/A
03/071930	12/2002	WO	N/A
03/074121	12/2002	WO	N/A
03/089789	12/2002	WO	N/A
03/090509	12/2002	WO	N/A
03/090819	12/2002	WO	N/A
03/090838	12/2002	WO	N/A
03/094075	12/2002	WO	N/A
03/099351	12/2002	WO	N/A

03/103758	12/2002	WO	N/A
03/103763	12/2002	WO	N/A
2004/006981	12/2003	WO	N/A
2004/006982	12/2003	WO	N/A
2004/007133	12/2003	WO	N/A
2004/008956	12/2003	WO	N/A
2007/000427	12/2003	WO	N/A
2004009160	12/2003	WO	N/A
2004/022136	12/2003	WO	N/A
2004/028596	12/2003	WO	N/A
2004/030716	12/2003	WO	N/A
2004/030717	12/2003	WO	N/A
2004/032994	12/2003	WO	N/A
2004/035116	12/2003	WO	N/A
2004030726	12/2003	WO	N/A
2004/041330	12/2003	WO	N/A
2004/058327	12/2003	WO	N/A
2004/060436	12/2003	WO	N/A
2004056412	12/2003	WO	N/A
2004/069095	12/2003	WO	N/A
2004/070548	12/2003	WO	N/A
2004/070557	12/2003	WO	N/A
2004/070994	12/2003	WO	N/A
2004/070995	12/2003	WO	N/A
2004/093648	12/2003	WO	N/A
2004/098390	12/2003	WO	N/A
2004/098454	12/2003	WO	N/A
2004/098683	12/2003	WO	N/A
2004/098684	12/2003	WO	N/A
2005/000378	12/2004	WO	N/A
2005/000382	12/2004	WO	N/A
2005/009514	12/2004	WO	N/A
2005/010796	12/2004	WO	N/A
2005/016411	12/2004	WO	N/A
2005/019766	12/2004	WO	N/A
2005/019987	12/2004	WO	N/A
2005/039671	12/2004	WO	N/A
2005/094920	12/2004	WO	N/A
2005/097235	12/2004	WO	N/A
2005/101279	12/2004	WO	N/A
2005/102416	12/2004	WO	N/A
2005/112899	12/2004	WO	N/A
2005/121938	12/2004	WO	N/A
2006/001929	12/2005	WO	N/A
2006/015922	12/2005	WO	N/A
2006/018425	12/2005	WO	N/A
2006/018425	12/2005	WO	N/A
2006/018447	12/2005	WO	N/A
2006/018447	12/2005	WO	N/A
2006/023147	12/2005	WO	N/A
2006/024671	12/2005	WO	N/A
2006/024672	12/2005	WO	N/A
2006/032623	12/2005	WO	N/A
2006/042811	12/2005	WO	N/A
2006/042811	12/2005	WO	N/A
2006/061354	12/2005	WO	N/A
2006/072416	12/2005	WO	N/A
2006/075016	12/2005	WO	N/A
2006/077262	12/2005	WO	N/A
2006/077263	12/2005	WO	N/A
2006/081975	12/2005	WO	N/A
2006/083831	12/2005	WO	N/A
2006/084464	12/2005	WO	N/A
2006/086980	12/2005	WO	N/A
2006/089547	12/2005	WO	N/A

2006/089548	12/2005	WO	N/A
2006/089965	12/2005	WO	N/A
2006/096746	12/2005	WO	N/A
2006/097453	12/2005	WO	N/A
2006/108775	12/2005	WO	N/A
2006/108809	12/2005	WO	N/A
2006/116997	12/2005	WO	N/A
2006/120253	12/2005	WO	N/A
2006/125692	12/2005	WO	N/A
2007/000425	12/2006	WO	N/A
2007/000426	12/2006	WO	N/A
2004/052277	12/2006	WO	N/A
2007/092618	12/2006	WO	N/A
2007/092637	12/2006	WO	N/A
2007/104756	12/2006	WO	N/A
2009/137777	12/2008	WO	N/A

OTHER PUBLICATIONS

U.S. Appl. No. 61/017,989, filed Dec. 31, 2007. cited by applicant

U.S. Appl. No. 61/018,002, filed Dec. 31, 2007. cited by applicant

U.S. Appl. No. 61/018,042, filed Dec. 31, 2007. cited by applicant

U.S. Appl. No. 61/018,054, filed Dec. 31, 2007. cited by applicant

U.S. Appl. No. 61/018,339, filed Dec. 31, 2007. cited by applicant

U.S. Appl. No. 61/023,645, filed Jan. 25, 2008. cited by applicant

U.S. Appl. No. 61/101,053, filed Sep. 29, 2008. cited by applicant

U.S. Appl. No. 61/101,077, filed Sep. 29, 2008. cited by applicant

U.S. Appl. No. 61/101,105, filed Sep. 29, 2008. cited by applicant

U.S. Appl. No. 61/101,115, filed Sep. 29, 2008. cited by applicant

U.S. Appl. No. 12/347,982, filed Dec. 31, 2008. cited by applicant

U.S. Appl. No. 15/388,341, filed Dec. 22, 2016. cited by applicant

Chinese Office Action for Chinese application No. 201410310254.3 dated Sep. 2, 2016 and its English translation (16 pages). cited by applicant

CN Search Report and English Translation for CN Application No. 201910340716.9 dated Jun. 24, 2021; 5 pages. cited by applicant

Decision on Grant issued in corresponding Russian Appln. No. 2008136190/14(046261) dated Oct. 11, 2011 and its English translation (24 pages). cited by applicant

European Search Report for corresponding European application No. 16197762 dated Mar. 30, 2017; 2 pages. cited by applicant

European Search Report for corresponding European application No. EP12183105 dated Feb. 3, 2016. cited by applicant

European Search Report issued in corresponding European Application No. 12183108 dated Aug. 6, 2015. cited by applicant

Examination Report from corresponding European Application No. 07 750 336.5 dated Aug. 26, 2010; 7 pages. cited by applicant

Examination Report from corresponding European Application No. 07 763 303.0 dated Aug. 4, 2009; 4 pages. cited by applicant

Examination report, dated Feb. 22, 2010, received in European Patent Application No. 07763498.8, 5 pages. cited by applicant

Extended European Search Report for corresponding European Application No. 20197606.5 dated Nov. 10, 2020; 8 pages. cited by applicant

Extended Search Report from corresponding European Application No. 11154417.7 dated Jul. 21, 2011; 7 pages. cited by applicant

Extended Search Report from corresponding European Application No. 11154418.5 dated Jul. 21, 2011; 7 pages. cited by applicant

Indian First Examination Report and English Translation for IN Application No. 201748013557 dated Aug. 31, 2021; 6 pages. cited by applicant

International Preliminary Report on Patentability from corresponding International Application No. PCT/US2007/003490 dated Aug. 12, 2008; 12 pages. cited by applicant

International Preliminary Report on Patentability from corresponding International Application No. PCT/US2007/003567 dated Aug. 21, 2008; 11 pages. cited by applicant

International Preliminary Report on Patentability from corresponding International Application No. PCT/US2007/003587 dated Aug. 12, 2008; 10 pages. cited by applicant

International Preliminary Report on Patentability from corresponding International Application No. PCT/US2007/003634 dated Aug. 12, 2008; 8 pages. cited by applicant

International Preliminary Report on Patentability from International Appln. No. PCT/US2010/062426 dated Jul. 4, 2012; 8 pages. cited by applicant

International Preliminary Report on Patentability from International Appln. No. PCT/US2010/062443 dated Jul. 4, 2012; 12 pages. cited by applicant

International Preliminary Report on Patentability issued in corresponding International Appln. No. PCT/US2011/022073 dated Jul. 24, 2012. cited by applicant

International Preliminary Report on Patentability issued in corresponding International Appln. No. PCT/US2011/023757 dated Aug. 7, 2012. cited by applicant

International Preliminary Report on Patentability, dated Jul. 6, 2010, received in international patent application No. PCT/US08/088688, 11 pages. cited by applicant
International Search Report and Written Opinion from corresponding International Application No. PCT/US2007/003490 dated Nov. 28, 2007; 20 pages. cited by applicant
International Search Report and Written Opinion from corresponding International Application No. PCT/US2007/003567 dated Oct. 17, 2007; 18 pages. cited by applicant
International Search Report and Written Opinion from corresponding International Application No. PCT/US2007/003587 dated Nov. 12, 2007; 18 pages. cited by applicant
International Search Report and Written Opinion from corresponding International Application No. PCT/US2007/003634 dated Oct. 2, 2007; 17 pages. cited by applicant
International Search Report and Written Opinion from corresponding International Application No. PCT/US2010/042150 dated Jun. 28, 2011; 14 pages. cited by applicant
International Search Report and Written Opinion from PCT/US2012/071280 dated Mar. 7, 2013; 13 pages. cited by applicant
International Search Report and Written Opinion, dated Jul. 10, 2009, received in international patent application No. PCT/US08/88688, 17 pages. cited by applicant
Japanese Office Action and English Translation for JP Application No. 2020-078108 dated Sep. 1, 2021; 6 pages. cited by applicant
Japanese Office Action for corresponding Japanese application No. 2014-076655 dated Mar. 1, 2017; 9 pages. cited by applicant
Japanese Office Action for corresponding JP Application No. 2020-020566 dated Oct. 29, 2020; 7 pages. cited by applicant
Notice of Opposition from corresponding European Appln. No. 07763686.8 dated Apr. 18, 2012 (47 pages). cited by applicant
Office Action from corresponding Chinese Application No. 200780007306.8 dated Jan. 31, 2011; 16 pages with translation. cited by applicant
Office Action from corresponding Chinese Application No. 200780007335.4 dated Jan. 18, 2011; 7 pages with translation. cited by applicant
Office Action from corresponding Chinese Application No. 200780007416.4 dated Dec. 6, 2010; 15 pages with translation. cited by applicant
Office Action issued in corresponding Japanese Application No. 2010-540955 dated Feb. 20, 2014 with translation; 10 pages. cited by applicant
Office Action issued in corresponding Russian Application No. 2010132226 dated May 13, 2013 with translation; 8 pages. cited by applicant
Office Action issued in corresponding Russian Application No. 2010132226 dated Nov. 14, 2013 with translation; 24 pages. cited by applicant
Official Action issued in corresponding Japanese application No. 2010-540955 dated Mar. 5, 2013 with translation; 10 pages. cited by applicant
Official Action issued in corresponding Japanese Appln. No. 2008-554376 dated Dec. 15, 2011 with translation (10 pages). cited by applicant
Official Action issued in corresponding Japanese Appln. No. 2008-554411 dated Nov. 18, 2011 with translation (9 pages). cited by applicant
Partial European Search Report issued in corresponding European Appln. No. 11154419.3 dated Nov. 14, 2011 (6 pages). cited by applicant
Partial International Search Report from corresponding International Application No. PCT/US2010/042150 dated Jan. 12, 2011; 7 pages. cited by applicant
Partial Search Report from corresponding European Application No. 11154414.4 dated Jul. 21, 2011; 7 pages. cited by applicant
Search Report for Chinese Application No. 201510595484.3 dated Dec. 11, 2017; 4 pages. cited by applicant
Office Action dated Feb. 10, 2025 in corresponding Canadian Application No. 3,213,521. cited by applicant

Primary Examiner: Ponton; James D

Assistant Examiner: Doubrava; John A

Attorney, Agent or Firm: McCormick, Paulding & Huber PLLC

Background/Summary

CROSS REFERENCE TO RELATED APPLICATIONS (1) The present application is continuation of U.S. patent application Ser. No. 15/388,341 filed on Dec. 22, 2016, which is a continuation of U.S. patent application Ser. No. 12/347,982 filed on Dec. 31, 2008, which claims the benefit of the following provisional patent applications: U.S. Provisional Patent Application No. 61/018,054, filed Dec. 31, 2007; U.S. Provisional Patent Application No. 61/018,042, filed Dec. 31, 2007; U.S. Provisional Patent Application No. 61/017,989, filed Dec. 31, 2007; U.S. Provisional Patent Application No. 61/018,002, filed Dec. 31, 2007; U.S. Provisional Patent Application No. 61/018,339, filed Dec. 31, 2007; U.S. Provisional Patent Application No. 61/023,645, filed Jan. 25, 2008; U.S. Provisional Patent Application No. 61/101,053, filed Sep. 29, 2008; U.S. Provisional Patent Application No. 61/101,077, filed Sep. 29, 2008; U.S. Provisional Patent Application No. 61/101,105, filed Sep. 29, 2008 and U.S. Provisional Patent Application No. 61/101,115, filed Sep. 29, 2008. All of the above-identified applications are hereby incorporated herein by reference in their entireties.

TECHNICAL FIELD

(1) This application relates generally to fluid delivery systems, and more particularly to infusion pump assemblies.

BACKGROUND

(2) Many potentially valuable medicines or compounds, including biologicals, are not orally active due to poor absorption, hepatic metabolism or other pharmacokinetic factors. Additionally, some therapeutic compounds, although they can be orally absorbed, are sometimes required to be administered so often it is difficult for a patient to maintain the desired schedule. In these cases, parenteral delivery is often employed or could be employed.

(3) Effective parenteral routes of drug delivery, as well as other fluids and compounds, such as subcutaneous injection, intramuscular injection, and intravenous (IV) administration include puncture of the skin with a needle or stylet. Insulin is an example of a therapeutic fluid that is self-injected by millions of diabetic patients. Users of parenterally delivered drugs may benefit from a wearable device that would automatically deliver needed drugs/compounds over a period of time.

(4) To this end, there have been efforts to design portable and wearable devices for the controlled release of therapeutics. Such devices are known to have a reservoir such as a cartridge, syringe, or bag, and to be electronically controlled. These devices suffer from a number of drawbacks including the malfunction rate. Reducing the size, weight and cost of these devices is also an ongoing challenge. Additionally, these devices often apply to the skin and pose the challenge of frequent re-location for application.

SUMMARY OF THE INVENTION

(5) According to a first implementation, a wearable infusion pump assembly includes a reusable housing assembly and a disposable housing assembly including a reservoir for receiving an infusible fluid. A releasable engagement assembly is configured to allow the reusable housing assembly to releasably engage the disposable housing assembly. The wearable infusion pump assembly further includes a detachable external infusion set configured to deliver the infusible fluid to a user.

(6) One or more of the following features may be included. The reusable housing assembly may include a mechanical control assembly having a pump assembly and at least one valve assembly. The reusable housing assembly may further include an electrical control assembly configured to provide one or more control signals to the mechanical control assembly and to effectuate the delivery of the infusible fluid to the user via the detachable external infusion set. The mechanical control assembly may include at least one shape-memory actuator.

(7) The detachable external infusion set may be a tethered infusion set. The detachable external infusion set may include a first disconnect assembly configured to releasably couple the detachable external infusion set to one of the reusable housing assembly and the disposable housing assembly. The detachable external infusion set may include a cannula assembly, a tubing assembly, and a second disconnect assembly configured to releasably couple the tubing assembly to the cannula assembly.

(8) According to another implementation, a wearable infusion pump assembly includes a reusable housing assembly, and a disposable housing assembly including a reservoir for receiving an infusible fluid. The wearable infusion pump assembly further includes a releasable engagement assembly configured to allow the reusable housing assembly to rotationally engage the disposable housing assembly.

(9) One or more of the following features may be included. The releasable engagement assembly may include a sealing assembly configured to provide a seal between the reusable housing assembly and the disposable housing assembly. The sealing assembly may include an o-ring assembly. The sealing assembly may include an over molded seal assembly. The sealing assembly may be a watertight seal assembly.

(10) The wearable infusion pump assembly may further include a peripheral tubing storage assembly configured to store at least a portion of an external infusion set about a periphery of the wearable infusion pump assembly.

(11) According to yet another implementation, a wearable infusion pump assembly includes a reusable housing assembly, and a disposable housing assembly including a reservoir for receiving an infusible fluid. A releasable engagement assembly is configured to allow the reusable housing assembly to releasably engage the disposable housing assembly. The wearable infusion pump assembly further includes a bolus switch assembly configured to effectuate a bolus infusion event.

(12) One or more of the following features may be included. The wearable infusion pump may further include at least one processor, and a computer readable medium coupled to the at least one processor. The computer readable medium includes a plurality of instructions stored thereon which, when executed by the at least one processor, may cause the at least one processor to perform operations including receiving an initiation signal from the switch assembly indicative of a bolus infusion event. The computer readable medium may further include instructions for receiving a dose signal from the switch assembly indicative of at least a portion of a bolus quantity of the infusible fluid, and rendering an audible quantity signal in response to the dose signal. The computer readable medium may also include instructions for receiving an approval signal from the switch assembly indicative of a concurrence with the audible quantity signal. The computer readable medium may further include instructions for administering the bolus quantity of the infusible fluid.

(13) According to still another implementation, a wearable infusion pump assembly includes a fluidless reusable housing assembly, and a disposable housing assembly including a reservoir for receiving an infusible fluid. A releasable engagement assembly is configured to allow the reusable housing assembly to releasably engage the disposable housing assembly.

(14) One or more of the following features may be included. The wearable infusion pump assembly may include an external infusion set that may be configured to deliver the infusible fluid to a user. The external infusion set may be a detachable external infusion set. The external infusion set may include a first disconnect assembly configured to releasably couple the external infusion set to the disposable housing assembly. The external infusion set may include a cannula assembly, a tubing assembly, and a second disconnect assembly configured to releasably couple the tubing assembly to the cannula assembly.

(15) The details of one or more embodiments are set forth in the accompanying drawings and the description below. Other features and advantages will become apparent from the description, the drawings, and the claims.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a side view of an infusion pump assembly;
- (2) FIG. 2 is a perspective view of the infusion pump assembly of FIG. 1;
- (3) FIG. 3 is an exploded view of various components of the infusion pump assembly of FIG. 1;
- (4) FIG. 4 is a cross-sectional view of the disposable housing assembly of the infusion pump assembly of FIG. 1;
- (5) FIGS. 5A-5C are cross-sectional views of an embodiment of a septum access assembly;
- (6) FIGS. 6A-6B are cross-sectional views of another embodiment of a septum access assembly;
- (7) FIGS. 7A-7B are partial top views of another embodiment of a septum access assembly;
- (8) FIGS. 8A-8B are cross-sectional views of another embodiment of a septum access assembly;
- (9) FIG. 9 is a perspective view of the infusion pump assembly of FIG. 1 showing an external infusion set;
- (10) FIGS. 10A-10E depict a plurality of hook-and-loop fastener configurations;
- (11) FIG. 11A is an isometric view of a remote control assembly and an alternative embodiment of the infusion pump assembly of FIG. 1;
- (12) FIGS. 11B-11R depicts various views of high level schematics and flow charts of the infusion pump assembly of FIG. 1;
- (13) FIGS. 12A-12F is a plurality of display screens rendered by the remote control assembly of FIG. 11A;
- (14) FIG. 13 is an isometric view of an alternative embodiment of the infusion pump assembly of FIG. 1;
- (15) FIG. 14 is an isometric view of the infusion pump assembly of FIG. 13;
- (16) FIG. 15 is an isometric view of the infusion pump assembly of FIG. 13;
- (17) FIG. 16 is an isometric view of an alternative embodiment of the infusion pump assembly of FIG. 1;
- (18) FIG. 17 is an plan view of the infusion pump assembly of FIG. 16;
- (19) FIG. 18 is a plan view of the infusion pump assembly of FIG. 16;
- (20) FIG. 19A is an exploded view of various components of the infusion pump assembly of FIG. 16;
- (21) FIG. 19B is an isometric view of a portion of the infusion pump assembly of FIG. 16;
- (22) FIG. 20 is a cross-sectional view of the disposable housing assembly of the infusion pump assembly of FIG. 16;
- (23) FIG. 21 is a diagrammatic view of a fluid path within the infusion pump assembly of FIG. 16;
- (24) FIGS. 22A-22C are diagrammatic views of a fluid path within the infusion pump assembly of FIG. 16;
- (25) FIG. 23 is an exploded view of various components of the infusion pump assembly of FIG. 16;
- (26) FIG. 24 is a cutaway isometric view of a pump assembly of the infusion pump assembly of FIG. 16;
- (27) FIGS. 25A-25D are other isometric views of the pump assembly of FIG. 24;
- (28) FIG. 26A-26B are isometric views of a measurement valve assembly of the infusion pump assembly of FIG. 16;
- (29) FIG. 27A-27B are side views of the measurement valve assembly of FIGS. 26A-26B;
- (30) FIGS. 28A-28D are views of a measurement valve assembly of the infusion pump assembly of FIG. 16;
- (31) FIG. 29 is an isometric view of an alternative embodiment of the infusion pump assembly of FIG. 1;
- (32) FIG. 30 is an isometric view of an alternative embodiment of the infusion pump assembly of FIG. 1;
- (33) FIG. 31 is another view of the alternative embodiment infusion pump assembly of FIG. 9;
- (34) FIG. 32 is an exploded view of another embodiment of an infusion pump assembly;
- (35) FIG. 33 is another exploded view of the infusion pump assembly of FIG. 32;
- (36) FIGS. 34A-34B depict another embodiment of an infusion pump assembly;
- (37) FIGS. 35A-35C are atop view, side view, and bottom view of a reusable housing assembly of the infusion pump assembly of FIG. 32;
- (38) FIG. 36 is an exploded view of the reusable housing assembly of FIGS. 35A-35C;
- (39) FIG. 37 is an exploded view of the reusable housing assembly of FIGS. 35A-35C;
- (40) FIG. 38A is an exploded view of the reusable housing assembly of FIGS. 35A-35C;
- (41) FIG. 38B-38D are top, side and bottom views of one embodiment of a dust cover;
- (42) FIGS. 39A-39C are a top view, side view, and bottom view of an electrical control assembly of the reusable housing assembly of FIGS. 35A-35C;
- (43) FIGS. 40A-40C are a top view, side view, and bottom view of a base plate of the reusable housing assembly of FIGS. 35A-35C;
- (44) FIGS. 41A-41B are a perspective top view and a perspective bottom view of the base plate of FIGS. 40A-40C;
- (45) FIGS. 42A-42C are a top view, side view, and bottom view of a base plate of the reusable housing assembly of FIGS. 35A-35C;
- (46) FIGS. 43A-43B depict a mechanical control assembly of the reusable housing assembly of FIGS. 35A-35C;
- (47) FIGS. 44A-44C depict the mechanical control assembly of the reusable housing assembly of FIGS. 35A-35C;
- (48) FIGS. 45A-45B depict the pump plunger and reservoir valve of the mechanical control assembly of the reusable housing assembly of FIGS. 35A-35C;
- (49) FIGS. 46A-46E depict various views of the plunger pump and reservoir valve of the mechanical control assembly of the reusable housing assembly of FIGS. 35A-35C;
- (50) FIGS. 47A-47B depict the measurement valve of the mechanical control assembly of the reusable housing assembly of FIGS. 35A-35C;
- (51) FIG. 48 is an exploded view of the disposable housing assembly of the infusion pump assembly of FIG. 32;
- (52) FIG. 49A is a plan view of the disposable housing assembly of FIG. 48;
- (53) FIG. 49B is a sectional view of the disposable housing assembly of FIG. 49A taken along line B-B;
- (54) FIG. 49C is a sectional view of the disposable housing assembly of FIG. 49A taken along line C-C;

(55) FIGS. 50A-50C depict the base portion of the disposable housing assembly of FIG. 48;
(56) FIGS. 51A-51C depict the fluid pathway cover of the disposable housing assembly of FIG. 48;
(57) FIGS. 52A-52C depict the membrane assembly of the disposable housing assembly of FIG. 48;
(58) FIGS. 53A-53C depict the top portion of the disposable housing assembly of FIG. 48;
(59) FIGS. 54A-54C depict the valve membrane insert of the disposable housing assembly of FIG. 48;
(60) FIGS. 55A-55B depict the locking ring assembly of the infusion pump assembly of FIG. 32;
(61) FIG. 56A-56C depict the locking ring assembly of the infusion pump assembly of FIG. 32;
(62) FIGS. 57-58 is an isometric view of an infusion pump assembly and a fill adapter;
(63) FIGS. 59-64 are various views of the fill adapter of FIG. 57;
(64) FIG. 65 is an isometric view of another embodiment of a fill adapter;
(65) FIGS. 66-67 depict an infusion pump assembly and another embodiment of a fill adapter;
(66) FIGS. 68-74 are various views of the fill adapter of FIG. 66;
(67) FIGS. 75-80 depict various views of an embodiment of a battery charger;
(68) FIGS. 81-89B depict various embodiments of battery chargers/docking stations;
(69) FIGS. 90A-90C are various views of a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(70) FIGS. 91A-91I are various views of a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(71) FIGS. 92A-92I are various views of a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(72) FIGS. 93A-93I are various views of a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(73) FIGS. 94A-94F are various views of a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(74) FIG. 95 is an exploded view of a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(75) FIG. 96 is a diagrammatic view of a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(76) FIG. 97 is a two-dimensional graph of a performance characteristic of the volume sensor assembly of FIG. 96;
(77) FIG. 98 is a two-dimensional graph of a performance characteristic of the volume sensor assembly of FIG. 96;
(78) FIG. 99 is a two-dimensional graph of a performance characteristic of the volume sensor assembly of FIG. 96;
(79) FIG. 100 is a diagrammatic view of a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(80) FIG. 101 is a two-dimensional graph of a performance characteristic of the volume sensor assembly of FIG. 100;
(81) FIG. 102 is a two-dimensional graph of a performance characteristic of the volume sensor assembly of FIG. 100;
(82) FIG. 103 is a diagrammatic view of a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(83) FIG. 104 is a two-dimensional graph of a performance characteristic of a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(84) FIG. 105 is a two-dimensional graph of a performance characteristic of a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(85) FIG. 106 is a two-dimensional graph of a performance characteristic of a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(86) FIG. 107 is a two-dimensional graph of a performance characteristic of a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(87) FIG. 108 is a two-dimensional graph of a performance characteristic of a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(88) FIG. 109 is a diagrammatic view of a control model for a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(89) FIG. 110 is a diagrammatic view of an electrical control assembly for the volume sensor assembly included within the infusion pump assembly of FIG. 1;
(90) FIG. 111 is a diagrammatic view of a volume controller for the volume sensor assembly included within the infusion pump assembly of FIG. 1;
(91) FIG. 112 is a diagrammatic view of a feed forward controller of the volume controller of FIG. 111;
(92) FIGS. 113-114 diagrammatically depicts an implementation of an SMA controller of the volume controller of FIG. 111;
(93) FIG. 114A-114B is an alternate implementation of an SMA controller;
(94) FIG. 115 diagrammatically depicts a multi-processor control configuration that may be included within the infusion pump assembly of FIG. 1;
(95) FIG. 116 is a diagrammatic view of a multi-processor control configuration that may be included within the infusion pump assembly of FIG. 1;
(96) FIG. 117A-117B diagrammatically depicts multi-processor functionality;
(97) FIG. 118 diagrammatically depicts multi-processor functionality;
(98) FIG. 119 diagrammatically depicts multi-processor functionality;
(99) FIGS. 120A-120E graphically depicts various software layers;
(100) 120B-120C depict various state diagrams;
(101) 120D graphically depicts device interaction;
(102) 120E graphically depicts device interaction;
(103) FIG. 121 diagrammatically depicts a volume sensor assembly included within the infusion pump assembly of FIG. 1;
(104) FIG. 122 diagrammatically depicts an inter-connection of the various systems of the infusion pump assembly of FIG. 1;
(105) FIG. 123 diagrammatically depicts basal-bolus infusion events;
(106) FIG. 124 diagrammatically depicts basal-bolus infusion events;
(107) FIG. 125A-125G depicts a hierarchical state machine;
(108) FIG. 126A-126M depicts a hierarchical state machine;
(109) FIG. 127 is an exemplary diagram of a split ring resonator antenna;

(110) FIG. **128** is an exemplary diagram of a medical device configured to utilize a split ring resonator antenna;
(111) FIG. **129** is an exemplary diagram of a split ring resonator antenna and transmission line from a medical infusion device;
(112) FIG. **130** is a graph of the return loss of a split ring resonator antenna prior to contact with human skin;
(113) FIG. **130A** is a graph of the return loss of a split ring resonator antenna during contact with human skin;
(114) FIG. **131** is an exemplary diagram of a split ring resonator antenna integrated into a device which operates within close proximity to dielectric material;
(115) FIG. **132** is a diagram of the dimensions of the inner and outer portion of the exemplary embodiment;
(116) FIG. **133** is a graph of the return loss of a non-split ring resonator antenna prior to contact with human skin; and
(117) FIG. **133A** is a graph of the return loss of a non-split ring resonator antenna during contact with human skin.
(118) Like reference symbols in the various drawings indicate like elements.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

(119) Referring to FIGS. **1-3**, an infusion pump assembly **100** may include a reusable housing assembly **102**. Reusable housing assembly **102** may be constructed from any suitable material, such as a hard or rigid plastic, that will resist compression. For example, use of durable materials and parts may improve quality and reduce costs by providing a reusable portion that lasts longer and is more durable, providing greater protection to components disposed therein.

(120) Reusable housing assembly **102** may include mechanical control assembly **104** having a pump assembly **106** and at least one valve assembly **108**. Reusable housing assembly **102** may also include electrical control assembly **110** configured to provide one or more control signals to mechanical control assembly **104** and effectuate the basal and/or bolus delivery of an infusible fluid to a user. Disposable housing assembly **114** may include valve assembly **108** which may be configured to control the flow of the infusible fluid through a fluid path. Reusable housing assembly **102** may also include pump assembly **106** which may be configured to pump the infusible fluid from the fluid path to the user.

(121) Electrical control assembly **110** may monitor and control the amount of infusible fluid that has been and/or is being pumped. For example, electrical control assembly **110** may receive signals from volume sensor assembly **148** and calculate the amount of infusible fluid that has just been dispensed and determine, based upon the dosage required by the user, whether enough infusible fluid has been dispensed. If enough infusible fluid has not been dispensed, electrical control assembly **110** may determine that more infusible fluid should be pumped. Electrical control assembly **110** may provide the appropriate signal to mechanical control assembly **104** so that any additional necessary dosage may be pumped or electrical control assembly **110** may provide the appropriate signal to mechanical control assembly **104** so that the additional dosage may be dispensed with the next dosage. Alternatively, if too much infusible fluid has been dispensed, electrical control assembly **110** may provide the appropriate signal to mechanical control assembly **104** so that less infusible fluid may be dispensed in the next dosage.

(122) Mechanical control assembly **104** may include at least one shape-memory actuator **112**. Pump assembly **106** and/or valve assembly **108** of mechanical control assembly **104** may be actuated by at least one shape-memory actuator, e.g., shape-memory actuator **112**, which may be a shape-memory wire in wire or spring configuration. Shape memory actuator **112** may be operably connected to and activated by electrical control assembly **110**, which may control the timing and the amount of heat and/or electrical energy used to actuate mechanical control assembly **104**. Shape memory actuator **112** may be, for example, a conductive shape-memory alloy wire that changes shape with temperature. The temperature of shape-memory actuator **112** may be changed with a heater, or more conveniently, by application of electrical energy. Shape memory actuator **112** may be a shape memory wire constructed of nickel/titanium alloy, such as NITINOL™ or FLEXINOL®.

(123) Infusion pump assembly **100** may include a volume sensor assembly **148** configured to monitor the amount of fluid infused by infusion pump assembly **100**. For example, volume sensor assembly **148** may employ, for example, acoustic volume sensing. Acoustic volume measurement technology is the subject of U.S. Pat. Nos. 5,575,310 and 5,755,683 assigned to DEKA Products Limited Partnership, as well as U.S. patent application Publication Nos. US 2007/0228071 A1, US 2007/0219496 A1, US 2007/0219480 A1, US 2007/0219597 A1, the entire disclosures of all of which are incorporated herein by reference. Other alternative techniques for measuring fluid flow may also be used; for example, Doppler-based methods; the use of Hall-effect sensors in combination with a vane or flapper valve; the use of a strain beam (for example, related to a flexible member over a fluid reservoir to sense deflection of the flexible member); the use of capacitive sensing with plates; or thermal time of flight methods. One such alternative technique is disclosed in U.S. patent application Ser. No. 11/704,899, entitled Fluid Delivery Systems and Methods, filed 9 Feb. 2007, the entire disclosure of which is incorporated herein by reference. Infusion pump assembly **100** may be configured so that the volume measurements produced by volume sensor assembly **148** may be used to control, through a feedback loop, the amount of infusible fluid that is infused into the user.

(124) Infusion pump assembly **100** may further include a disposable housing assembly **114**. For example, disposable housing assembly **114** may be configured for a single use or for use for a specified period of time, e.g., three days or any other amount of time. Disposable housing assembly **114** may be configured such that any components in infusion pump assembly **100** that come in contact with the infusible fluid are disposed on and/or within disposable housing assembly **114**. For example, a fluid path or channel including a reservoir, may be positioned within disposable housing assembly **114** and may be configured for a single use or for a specified number of uses before disposal. The disposable nature of disposable housing assembly **114** may improve sanitation of infusion pump assembly **100**.

(125) Referring also to FIG. **4**, disposable housing assembly **114** may be configured to releasably engage reusable housing assembly **102**, and includes a cavity **116** that has a reservoir **118** for receiving an infusible fluid (not shown), e.g., insulin. Such releasable engagement may be accomplished by a screw-on, a twist-lock or a compression fit configuration, for example. Disposable housing assembly **114** and/or reusable housing assembly **102** may include an alignment assembly configured to assist in aligning disposable housing assembly **114** and reusable housing assembly **102** for engagement in a specific orientation. Similarly, base nub **120** and top nub **122** may be used as indicators of alignment and complete engagement.

(126) Cavity **116** may be at least partially formed by and integral to disposable housing assembly **114**. Cavity **116** may include a membrane assembly **124** for at least partially defining reservoir **118**. Reservoir **118** may be further defined by disposable housing

assembly **114**, e.g., by a recess **126** formed in base portion **128** of disposable housing assembly **114**. For example, membrane assembly **124** may be disposed over recess **126** and attached to base portion **128**, thereby forming reservoir **118**. Membrane assembly **124** may be attached to base portion **128** by conventional means, such as gluing, heat sealing, and/or compression fitting, such that a seal **130** is formed between membrane assembly **124** and base portion **128**. Membrane assembly **124** may be flexible and the space formed between membrane assembly **124** and recess **126** in base portion **128** may define reservoir **118**. Reservoir **118** may be non-pressurized and in fluid communication with a fluid path (not shown). Membrane assembly **124** may be at least partially collapsible and cavity **116** may include a vent assembly, thereby advantageously preventing the buildup of a vacuum in reservoir **118** as the infusible fluid is delivered from reservoir **118** to the fluid path. In a preferred embodiment, membrane assembly **124** is fully collapsible, thus allowing for the complete delivery of the infusible fluid. Cavity **116** may be configured to provide sufficient space to ensure there is always some air space even when reservoir **118** is filled with infusible fluid.

(127) The membranes and reservoirs described herein may be made from materials including but not limited to silicone, NITRILE, and any other material having desired resilience and properties for functioning as described herein. Additionally, other structures could serve the same purpose.

(128) The use of a partially collapsible non pressurized reservoir may advantageously prevent the buildup of air in the reservoir as the fluid in the reservoir is depleted. Air buildup in a vented reservoir could prevent fluid egress from the reservoir, especially if the system is tilted so that an air pocket intervenes between the fluid contained in the reservoir and the septum of the reservoir. Tilting of the system is expected during normal operation as a wearable device.

(129) Reservoir **118** may be conveniently sized to hold an insulin supply sufficient for delivery over one or more days. For example, reservoir **118** may hold about 1.00 to 3.00 ml of insulin. A 3.00 ml insulin reservoir may correspond to approximately a three day supply for about 90% of potential users. In other embodiments, reservoir **118** may be any size or shape and may be adapted to hold any amount of insulin or other infusible fluid. In some embodiments, the size and shape of cavity **116** and reservoir **118** is related to the type of infusible fluid that cavity **116** and reservoir **118** are adapted to hold.

(130) Disposable housing assembly **114** may include a support member **132** (FIG. 3) configured to prevent accidental compression of reservoir **118**. Compression of reservoir **118** may result in an unintentional dosage of infusible fluid being forced through the fluid path to the user. In a preferred embodiment, reusable housing assembly **102** and disposable housing assembly **114** may be constructed of a rigid material that is not easily compressible. However, as an added precaution, support member **132** may be included within disposable housing assembly **114** to prevent compression of infusion pump assembly **100** and cavity **116** therein. Support member **132** may be a rigid projection from base portion **128**. For example, support member **132** may be disposed within cavity **116** and may prevent compression of reservoir **118**.

(131) As discussed above, cavity **116** may be configured to provide sufficient space to ensure there is always some air space even when reservoir **118** is filled with infusible fluid. Accordingly, in the event that infusion pump assembly **100** is accidentally compressed, the infusible fluid may not be forced through cannula assembly **136** (e.g., shown in FIG. 9).

(132) Cavity **116** may include a septum assembly **146** (FIG. 3) configured to allow reservoir **118** to be filled with the infusible fluid. Septum assembly **146** may be a conventional septum made from rubber or plastic and have a one-way fluid valve configured to allow a user to fill reservoir **118** from a syringe or other filling device. In some embodiments, septum **146** may be located on the top of membrane assembly **124**. In these embodiments, cavity **116** may include a support structure (e.g., support member **132** in FIG. 3) for supporting the area about the back side of the septum so as to maintain the integrity of the septum seal when a needle is introducing infusible fluid into cavity **116**. The support structure may be configured to support the septum while still allowing the introduction of the needle for introducing infusible fluid into cavity **116**.

(133) Infusion pump assembly **100** may include an overflow prevention assembly (not shown) that may e.g., protrude into cavity **116** and may e.g., prevent the overfilling of reservoir **118**.

(134) In some embodiments, reservoir **118** may be configured to be filled a plurality of times. For example, reservoir **118** may be refillable through septum assembly **146**. As infusible fluid may be dispensed to a user, electronic control assembly **110** may monitor the fluid level of the infusible fluid in reservoir **118**. When the fluid level reaches a low point, electronic control assembly **110** may provide a signal, such as a light or a vibration, to the user that reservoir **118** needs to be refilled. A syringe, or other filling device, may be used to fill reservoir **118** through septum **146**.

(135) Reservoir **118** may be configured to be filled a single time. For example, a refill prevention assembly (not shown) may be utilized to prevent the refilling of reservoir **118**, such that disposable housing assembly **114** may only be used once. The refill prevention assembly (not shown) may be a mechanical device or an electro-mechanical device. For example, insertion of a syringe into septum assembly **146** for filling reservoir **118** may trigger a shutter to close over septum **146** after a single filling, thus preventing future access to septum **146**. Similarly, a sensor may indicate to electronic control assembly **110** that reservoir **118** has been filled once and may trigger a shutter to close over septum **146** after a single filling, thus preventing future access to septum **146**. Other means of preventing refilling may be utilized and are considered to be within the scope of this disclosure.

(136) As discussed above, disposable housing assembly **114** may include septum assembly **146** that may be configured to allow reservoir **118** to be filled with the infusible fluid. Septum assembly **146** may be a conventional septum made from rubber or any other material that may function as a septum, or, in other embodiments, septum assembly **146** may be, but is not limited to, a plastic, or other material, one-way fluid valve. In various embodiments, including the exemplary embodiment, septum assembly **146** is configured to allow a user to fill reservoir **118** from a syringe or other filling device. Disposable housing assembly **114** may include a septum access assembly that may be configured to limit the number of times that the user may refill reservoir **118**.

(137) For example and referring also to FIGS. 5A-5C, septum access assembly **152** may include shutter assembly **154** that may be held in an "open" position by a tab assembly **156** that is configured to fit within a slot assembly **158**. Upon penetrating septum **146** with filling syringe **160**, shutter assembly **154** may be displaced downward, resulting in tab assembly **156** disengaging from slot assembly **158**. Once disengaged, spring assembly **162** may displace shutter assembly **154** in the direction of arrow **164**, resulting in septum **146** no longer being accessible to the user.

(138) Referring also to FIG. 6A, an alternative-embodiment septum access assembly **166** is shown in the “open” position. In a fashion similar to that of septum access assembly **152**, septum access assembly **166** includes shutter assembly **168** and spring assembly **170**.

(139) Referring also to FIG. 6B, an alternative-embodiment of septum access assembly **172** is shown in the “open” position where tab **178** may engage slot **180**. In a fashion similar to that of septum access assembly **166**, septum access assembly **172** may include shutter assembly **174** and spring assembly **176**. Once shutter assembly **172** moves to the “closed” position (e.g., which may prevent further access of septum **146** by the user), tab **178** may at least partially engage slot **180a**. Engagement between tab **178** and slot **180a** may lock shutter assembly **172** in the “closed” position to inhibit tampering and reopening of shutter assembly **172**. Spring tab **182** of shutter assembly **172** may bias tab **178** into engagement with slot **180a**.

(140) However, in various embodiments, septum access assemblies may not be actuated linearly. For example and referring also to FIGS. 7A-7B, there is shown alternative embodiment septum access assembly **184** that includes shutter assembly **186** that is configured to pivot about axis **188**. When positioned in the open position (as shown in FIG. 7A), septum **146** may be accessible due to passage **190** (in shutter assembly **186**) being aligned with passage **192** in e.g., a surface of disposable housing assembly **114**. However, in a fashion similar to septum access assemblies **166**, **172**, upon penetrating septum **146** with filling syringe **160** (See FIG. 6B), shutter assembly **186** may be displaced in a clockwise fashion, resulting in passage **190** (in shutter assembly **186**) no longer being aligned with passage **192** in e.g., a surface of disposable housing assembly **114**, thus preventing access to septum **146**.

(141) Referring also to FIGS. 8A-8B, an alternative-embodiment septum access assembly **194** is shown. In a fashion similar to that of septum access assemblies **166**, **172**, septum access assembly **194** includes shutter assembly **196** and spring assembly **198** that is configured to bias shutter assembly **196** in the direction of arrow **200**. Filling assembly **202** may be used to fill reservoir **118**. Filling assembly **202** may include shutter displacement assembly **204** that may be configured to displace shutter assembly **196** in the direction of arrow **206**, which in turn aligns passage **208** in shutter assembly **196** with septum **146** and passage **210** in septum access assembly **194**, thus allowing filling syringe assembly **212** to penetrate septum **146** and fill reservoir **118**.

(142) Infusion pump assembly **100** may include a sealing assembly **150** (FIG. 3) configured to provide a seal between reusable housing assembly **102** and disposable housing assembly **114**. For example, when reusable housing assembly **102** and disposable housing assembly **114** are engaged by e.g. rotational screw-on engagement, twist-lock engagement or compression engagement, reusable housing assembly **102** and disposable housing assembly **114** may fit together snugly, thus forming a seal. In some embodiments, it may be desirable for the seal to be more secure. Accordingly, sealing assembly **150** may include an o-ring assembly (not shown). Alternatively, sealing assembly **150** may include an over molded seal assembly (not shown). The use of an o-ring assembly or an over molded seal assembly may make the seal more secure by providing a compressible rubber or plastic layer between reusable housing assembly **102** and disposable housing assembly **114** when engaged thus preventing penetration by outside fluids. In some instances, the o-ring assembly may prevent inadvertent disengagement. For example, sealing assembly **150** may be a watertight seal assembly and, thus, enable a user to wear infusion pump assembly **100** while swimming, bathing or exercising.

(143) Referring also to FIG. 9, infusion pump assembly **100** may include an external infusion set **134** configured to deliver the infusible fluid to a user. External infusion set **134** may be in fluid communication with cavity **118**, e.g. by way of the fluid path. External infusion set **134** may be disposed adjacent to infusion pump assembly **100**. Alternatively, external infusion set **134** may be configured for application remote from infusion pump assembly **100**, as discussed in greater detail below. External infusion set **134** may include a cannula assembly **136**, which may include a needle or a disposable cannula **138**, and tubing assembly **140**. Tubing assembly **140** may be in fluid communication with reservoir **118**, for example, by way of the fluid path, and with cannula assembly **138** for example, either directly or by way of a cannula interface **142**.

(144) External infusion set **134** may be a tethered infusion set, as discussed above regarding application remote from infusion pump assembly **100**. For example, external infusion set **134** may be in fluid communication with infusion pump assembly **100** through tubing assembly **140**, which may be of any length desired by the user (e.g., 3-18 inches). Though infusion pump assembly **100** may be worn on the skin of a user with the use of adhesive patch **144**, the length of tubing assembly **140** may enable the user to alternatively wear infusion pump assembly **100** in a pocket. This may be beneficial to users whose skin is easily irritated by application of adhesive patch **144**. Similarly, wearing and/or securing infusion pump assembly **100** in a pocket may be preferable for users engaged in physical activity.

(145) In addition to/as an alternative to adhesive patch **144**, a hook and loop fastener system (e.g. such as hook and loop fastener systems offered by Velcro USA Inc. of Manchester, NH) may be utilized to allow for easy attachment/removal of an infusion pump assembly (e.g., infusion pump assembly **100**) from the user. Accordingly, adhesive patch **144** may be attached to the skin of the user and may include an outward facing hook or loop surface. Additionally, the lower surface of disposable housing assembly **114** may include a complementary hook or loop surface. Depending upon the separation resistance of the particular type of hook and loop fastener system employed, it may be possible for the strength of the hook and loop connection to be stronger than the strength of the adhesive to skin connection. Accordingly, various hook and loop surface patterns may be utilized to regulate the strength of the hook and loop connection.

(146) Referring also to FIGS. 10A-10E, five examples of such hook and loop surface patterns are shown. Assume for illustrative purposes that the entire lower surface of disposable housing assembly **114** is covered in a “loop” material. Accordingly, the strength of the hook and loop connection may be regulated by varying the pattern (i.e., amount) of the “hook” material present on the surface of adhesive patch **144**. Examples of such patterns may include but are not limited to: a singular outer circle **220** of “hook” material (as shown in FIG. 10A); a plurality of concentric circles **222**, **224** of “hook” material (as shown in FIG. 10B); a plurality of radial spokes **226** of “hook” material (as shown in FIG. 10C); a plurality of radial spokes **228** of “hook” material in combination with a single outer circle **230** of “hook” material (as shown in FIG. 10D); and a plurality of radial spokes **232** of “hook” material in combination with a plurality of concentric circles **234**, **236** of “hook” material (as shown in FIG. 10E).

(147) Additionally and referring also to FIG. 11A, in one exemplary embodiment of the above-described infusion pump assembly,

infusion pump assembly **100'** may be configured via a remote control assembly **300**. In this particular embodiment, infusion pump assembly **100'** may include telemetry circuitry (not shown) that allows for communication (e.g., wired or wireless) between infusion pump assembly **100'** and e.g., remote control assembly **300**, thus allowing remote control assembly **300** to remotely control infusion pump assembly **100'**. Remote control assembly **300** (which may also include telemetry circuitry (not shown) and may be capable of communicating with infusion pump assembly **100'**) may include display assembly **302** and input assembly **304**. Input assembly **304** may include slider assembly **306** and switch assemblies **308, 310**. In other embodiments, the input assembly may include a jog wheel, a plurality of switch assemblies, or the like.

(148) Remote control assembly **300** may include the ability to pre-program basal rates, bolus alarms, delivery limitations, and allow the user to view history and to establish user preferences. Remote control assembly **300** may also include a glucose strip reader.

(149) During use, remote control assembly **300** may provide instructions to infusion pump assembly **100'** via wireless communication channel **312** established between remote control assembly **300** and infusion pump assembly **100'**. Accordingly, the user may use remote control assembly **300** to program/configure infusion pump assembly **100'**. Some or all of the communication between remote control assembly **300** and infusion pump assembly **100'** may be encrypted to provide an enhanced level of security.

(150) Communication between remote control assembly **300** and infusion pump assembly **100'** may be accomplished utilizing a standardized communication protocol. Further, communication between the various components included within infusion pump assembly **100, 100'** may be accomplished using the same protocol. One example of such a communication protocol is the Packet Communication Gateway Protocol (PCGP) developed by DEKA Research & Development of Manchester, NH. As discussed above, infusion pump assembly **100, 100'** may include electrical control assembly **110** that may include one or more electrical components. For example, electrical control assembly **110** may include a plurality of data processors (e.g. a supervisor processor and a command processor) and a radio processor for allowing infusion pump assembly **100, 100'** to communicate with remote control assembly **300**. Further, remote control assembly **300** may include one or more electrical components, examples of which may include but are not limited to a command processor and a radio processor for allowing remote control assembly **300** to communicate with infusion pump assembly **100, 100'**. A high-level diagrammatic view of one example of such a system is shown in FIG. **11B**.

(151) Each of these electrical components may be manufactured from a different component provider and, therefore, may utilize native (i.e. unique) communication commands. Accordingly, through the use of a standardized communication protocol, efficient communication between such disparate components may be accomplished.

(152) PCGP may be a flexible extendable software module that may be used on the processors within infusion pump assembly **100, 100'** and remote control assembly **300** to build and route packets. PCGP may abstract the various interfaces and may provide a unified application programming interface (API) to the various applications being executed on each processor. PCGP may also provide an adaptable interface to the various drivers. For illustrative purposes only, PCGP may have the conceptual structure illustrated in FIG. **11C** for any given processor.

(153) PCGP may ensure data integrity by utilizing cyclic redundancy checks (CRCs). PCGP may also provide guaranteed delivery status. For example, all new messages should have a reply. If such a reply isn't sent back in time, the message may time out and PCGP may generate a negative acknowledge reply message for the application (i.e., a NACK). Accordingly, the message-reply protocol may let the application know whether the application should retry sending a message.

(154) PCGP may also limit the number of messages in-flight from a given node, and may be coupled with a flow-control mechanism at the driver level to provide a deterministic approach to message delivery and may let individual nodes have different quantities of buffers without dropping packets. As a node runs out of buffers, drivers may provide back pressure to other nodes and prevent sending of new messages.

(155) PCGP may use a shared buffer pool strategy to minimize data copies, and may avoid mutual exclusions, which may have a small affect on the API used to send/receive messages to the application, and a larger affect on the drivers. PCGP may use a "Bridge" base class that provides routing and buffer ownership. The main PCGP class may be sub-classed from the bridge base class. Drivers may either be derived from a bridge class, or talk to or own a derived bridge class.

(156) PCGP may be designed to work in an embedded environment with or without an operating system by using a semaphore to protect shared data such that some calls can be re-entrant and run on a multiple threads. One illustrative example of such an implementation is shown in FIG. **11D**. PCGP may operate the same way in both environments, but there may be versions of the call for specific processor types (e.g., the ARM 9/OS version). So while the functionality may be the same, there may be an operating system abstraction layer with slightly different calls tailored for e.g., the ARM 9 Nucleus OS environment.

(157) Referring also to FIG. **11E**, PCGP may: allow multiple Send/Reply calls to occur (on Pilot's ARM 9 on multiple tasks re-entrant); have multiple drivers running asynchronously for RX and TX on different interfaces; and provide packet ordering for send/receive, and deterministic timeout on message send.

(158) Each software object may ask the buffer manager for the next buffer to use, and may then give that buffer to another object. Buffers may pass from one exclusive owner to another autonomically, and queues may occur automatically by ordering buffers by sequence number. When a buffer is no longer in use, the buffer may be recycled (e.g., object attempts to give the buffer to itself, or frees it for the buffer manager to re-allocate later). Accordingly, data generally doesn't need to be copied, and routing simply writes over the buffer ownership byte.

(159) Such an implementation of PCGP may provide various benefits, examples of which may include but are not limited to: dropping a message due to lack of buffers may be impossible, as once a message is put into a buffer, the message may live there until it is transferred or received by the application; data may not need to be copied, as offsets are used to access driver, PCGP and payload sections of a buffer; drivers may exchange ownership of message data by writing over one byte (i.e., the buffer ownership byte); there may be no need for multiple exclusions except for re-entrant calls, as a mutual exclusion may be needed only when a single buffer owner could simultaneously want to use a buffer or get a new sequence number; there may be fewer rules for

application writers to follow to implement a reliable system; drivers may use ISR/push/pull and polled data models, as there are a set of calls provided to push/pull data out of the buffer management system from the drivers; drivers may not do much work beyond TX and RX, as drivers may not copy, CRC or check anything but the destination byte and CRC and other checks may be done off of the ISR hot path later; as the buffer manager may order access by sequence number, queue ordering may automatically occur; and a small code/variable foot print may be utilized; hot path code may be small and overhead may be low.

(160) As shown in FIG. 11F, when a message needs to be sent, the PCGP may build the packet quickly and may insert it into the buffer management system. Once in the buffer management system, a call to “packetProcessor” may apply protocol rules and may give the messages to the drivers/application.

(161) To send a new message or send a reply, PCGP may: check the call arguments to e.g., make sure the packet length is legal, destination is ok, etc.; avoid trying to send a message across a link that is down unless the down link is the radio node, which may allow PCGP to be used by the radio processors to establish a link, pair, etc. and may notify the application when PCGP is trying to talk across a link that is not functional (instead of timing out); obtain a sequence number for a new message or utilize an existing sequence number for an existing message; build the packet, copy the payload data and write in the CRC, wherein (from this point forward) the packet integrity may be protected by the CRC; and either give the message to the buffer manager as a reply or as a new message, and check to see if putting this buffer into the buffer manager would exceed the maximum number of en-queued send messages.

(162) Referring also to FIGS. 11G-11H, PCGP may work by doing all of the main work on one thread to avoid mutual exclusions, and to avoid doing considerable work on the send/reply or driver calls. The “packetProcessor” call may have to apply protocol rules to replies, new sent messages, and received messages. Reply messages may simply get routed, but new messages and received messages may have rules for routing the messages. In each case, the software may loop while a message of the right type is available to apply protocol rules until it cannot process the packets.

(163) Sending a new message may conform to the following rules: only two messages may be allowed “in-flight” on the network; and enough data about an in-flight message may be stored to match the response and handle timeout.

(164) Receiving a message may conform to the following rules: responses that match may clear out the “in-flight” information slot so a new packet can be sent; responses that do not match may be dropped; new messages may be for the protocol (e.g., getting/clearing network statistics for this node); to receive a message, the buffer may be given up to the application and may use a call back; and the buffer may be freed or left owned by the application.

(165) Accordingly, PCGP may be configured such that: the call back function may copy the payload data out or may use it completely before returning; the call back function owns the buffer and may reference the buffer and the buffer's payload by the payload address, wherein the message may be processed later; applications may poll the PCGP system for received messages; and applications may use the call back to set an event and then poll for received messages.

(166) The communication system may have a limited number of buffers. When PCGP runs out of buffers, drivers may stop receiving new packets and the application may be told that the application cannot send new packets. To avoid this and maintain optimal performance, the application may try to perform one or more procedures, examples of which may include but are not limited to: a) The application should keep PCGP up to date with radio status: Specifically, if the link goes down and PCGP doesn't know, PCGP may accept and queue new messages to send (or not timeout messages optimally), which may jam the send queue and delay the application from using the link optimally. b) The application should call “decrement timeouts” regularly: Optimally, every 20-100 milliseconds unless the processor is asleep. In general, a message moves fast (milliseconds) slow (seconds) or not at all. Timeouts are an attempt to remove “in-flight” messages that should be dropped to free up buffers and bandwidth. Doing this less often may delay when a new message gets sent, or when the application can queue a new message. c) The application should ask PCGP if it has work to do that is pending before going to sleep: If PCGP has nothing to do, driver activity may wake up the system and thus PCGP, and then PCGP won't need a call to “packetProcessor” or “decrement timeouts” until new packets enter the system. Failure to do this may cause messages that could have been sent/forwarded/received successfully to be dropped due to a timeout condition. d) The application should not hold onto received messages indefinitely: The message system relies on prompt replies. If the application is sharing PCGP buffers, then holding onto a message means holding onto a PCGP buffer. The receiving node doesn't know if the sending node has timeout configured for slow or fast radio. This means when a node receives a message it should assume the network's fast timeout speed. e) The application should call the “packetProcessor” often: The call may cause new messages queued by the application to get sent and may handle receipt of new messages. The call may also cause buffers to re-allocate and calling it infrequently may delay message traffic.

(167) As shown in FIG. 11I, at some point the RX driver may be asked to receive a message from the other side of the interface. To ensure a message does not get dropped, the RX driver may ask the buffer manager if there is an available buffer for storing a new message. The driver may then ask for a buffer pointer and may start filling the buffer with received data. When a complete message is received, the RX driver may call a function to route the packet. The route function may examine the destination byte in the packet header and may change the owner to either the other driver, or the application, or may detect that the packet is bad and may drop the packet by freeing the buffer.

(168) PCGP RX overhead may consist of asking for the next available buffer and calling the route function. An example of code that performs such a function is as follows:

```
(169) TABLE-US-00001    @ Receive request uint8 i=0, *p; if (Bridge::canReceiveFlowControl( )) {    p =  
Bridge::nextBufferRX( );    while (not done) { p[i] = the next byte; }    Bridge::route(p); }
```

(170) A driver may perform a TX by asking the buffer manager for the pointer to the next buffer to send. The TX driver may then ask the other side of the interface if it can accept a packet. If the other side denies the packet, the TX driver may do nothing to the buffer, as its status has not changed. Otherwise, the driver may send the packet and may recycle/free the buffer. An example of code that performs such a function is as follows:

```
(171) TABLE-US-00002    uint8 *p = Bridge::nextBufferTX( ); if (p != (uint8 *)0) {    send the buffer p;    Bridge::recycle(p); }
```

(172) To avoid forwarding packets that are past the maximum message system timeout time, asking for the nextBuffer may call

the BufferManager::first(uint8 owner) function that may scan for buffers to free. Accordingly, full TX buffers with no hope of making a timeout may be freed on the thread that owns the buffer. Abridge that is doing TX (i.e., while looking for the next TX buffer) may free all of the TX buffers that are expired before receiving the next TX buffer for processing.

(173) As shown in FIG. 11J-11L, during the buffer allocation process, buffers marked free may be transferred to the drivers to receive new packets, or to PCGP to receive new payloads for TX. Allocation from “free” may be done by the “packetProcessor” function. The number of sends and receives between “packetProcessor” calls may dictate how many LT_Driver_RX, GT_Driver_RX and PCGP_Free buffers need to be allocated. LT_Driver may represent drivers that handle addresses that are less than the node address. GT_Driver may represent drivers that handle addresses that are greater than the node address.

(174) When a driver receives a packet, the driver may put the data into an RX buffer that gets handed to the router. The router may then reassign the buffer to PCGP_Receive or to the other driver's TX (not shown). If the buffer contains obviously invalid data, the buffer may transition to free.

(175) After a router marks a buffer for TX, the driver may discover the buffer is TX and may send the message. After sending the message, the buffer may immediately become an RX buffer if the driver was low in RX buffers, or the buffer may be freed for re-allocation.

(176) During the “packetProcessor” call, PCGP may process all buffers that the router marked as PCGP_Receive. At this point, data may be acted upon, so the CRC and other data items may be checked. If the data is corrupted, a statistic may be incremented and the buffer may be freed. Otherwise, the buffer may be marked as owned by the application. Buffers marked as owned by the application may be either recycled for the use of PCGP or freed for reallocation by the buffer manager.

(177) When the application wants to send a new message, it may be done in a re-entrant friendly/mutual exclusion manner. If the buffer may be allocated, PCGP may mark the buffer as busy. Once marked busy, no other thread calling the send or reply functions may grab this buffer, as it is owned by this function call's invocation. The remainder of the process of error checking and building the message may be done outside the isolated race condition mutual exclusion guarded code. The buffer may either transition to free or may become a valid filled CRC-checked buffer and passed to the router. These buffers may not be routed immediately and may be queued so that messages can be sent later (assuming that protocol rules allow). Reply messages may be marked differently than new send messages because reply messages may be routed with a higher priority than regular send messages and reply messages may have no rules limiting how many/when they can be sent.

(178) PCGP was designed to work with flow control, and flow control may negotiate the transfer of messages from one node to another node so that a buffer is never dropped because the other side of an interface lacks a buffer (which may cause back pressure on the sending node).

(179) Flow control may be apart of the shared buffer format. The first two bytes may be reserved for the driver so that the driver never needs to shift the packet bytes. Two bytes may be used so that one byte is the DMA length-1, and the second byte is to control the flow of messages. These same two bytes may be synchronizing bytes if a PCGP message is transmitted over RS232.

(180) When a packet is “in-flight”, the packet may be in the process of being sent by a driver on the way to its destination, being processed by the destination, or being sent back as a response.

(181) Typical delays are as follows:

(182) TABLE-US-00003 Interface/ Delay Delay cause (seconds) Notes SPI <3 Roughly 400 kbps I2C <1 Waking a <6? Clock calibration, min. CC2510 sleep time Flow control <0.2 RF link 20 to 2000 Interference/ Minutes, never separation

(183) Accordingly, messages tend to complete the round trip either: quickly (e.g., <50 ms); slowly (e.g., one or more seconds); or not at all.

(184) PCGP may use two different times (set at initialization) for all timeouts, one for when the RF link is in fast heartbeat mode, and another for when the RF link is in slow mode. If a message is in-flight and the link status changes from fast to slow, the timeout may be adjusted and the difference between fast and slow may be added to the time-to-live counter for the packet. No additional transitions back and forth may affect the time-to-live time for the message.

(185) There is a second timeout that may be twice as long as the slow timeout that is used to monitor buffer allocation inside PCGP. Accordingly, if a message is “stuck” inside a driver and hasn't been sent due to e.g., flow control or hardware damage, the buffer may be freed by the buffer manager, resulting in the buffer being dropped. For a “new” message, this may mean that the packet already timed out and the application was already given a reply saying the message wasn't delivered, resulting in the buffer being freed. Since the driver polls the buffer manager for buffers that need to be sent, the buffer is freed up so that a message that could be sent is handed to the driver the next time that it unblocks. For a reply message, the reply may simply get dropped and the sending node may time out.

(186) The PCGP messaging system may pass messages that contain header information and payload. Outside of PCGP, the header may be a set of data items in a call signature. However, internal to PCGP, there may be a consistent, driver friendly byte layout. Drivers may insert bytes either into the PCGP packet or before the PCGP packet such: DE, CA: Synch bytes for use with RS232, nominal value of 0xDE, 0xCA or 0x5A, 0xA5. LD: Driver DMA length byte, equals amount driver is pushing in this DMA transfer, which is the total size, not including the size byte or synch bytes. Cmd: Driver command and control byte used for flow control. LP: PCGP packet length, always the total header+payload size in bytes+CRC size. LD=LP+1. Dst: Destination address. Src: Source address Cmd: Command byte Scd: Sub command byte AT: Application Tag is defined by the application and has no significance to PCGP. It allows the application to attach more information to a message e.g., the thread from which the message originated. SeqNum: thirty-two bit sequence number is incremented by PCGP for a new message sent, guarantees the number will not wrap, acts as a token, endianness isn't relevant. CRC16: A sixteen bit CRC of the PCGP header and payload.

(187) An example of a message with no payload, cmd=1, subcmd=2 is as follows:

(188) 0xDE, 0xCA, 0xC, 0x5, 0x14, 1, 2, 0, 0, 0, 0, 0x1, crchigh, crclow.

(189) 0x0D, cmd, 0xC, 0x5, 0x14, 1, 2, 0, 0, 0, 0, 0x1, crchigh, crclow.

(190) There may be several advantages to this methodology, examples of which may include but are not limited to: Most of our hardware DMA engines may use the first byte to define how many additional bytes to move, so in this methodology, drivers and

PCGP may share buffers. A byte may be provided right after the DMA length to pass flow control information between drivers. Driver length and "Cmd" byte may be outside the CRC region so they may be altered by the driver, may be owned by the driver transport mechanism, and the driver may guard for invalid lengths. There may be a separate PGCP packet length byte that is CRC protected. Accordingly, the application may trust the that payload length is correct. The endianness of the sequence number may not be relevant, as it is just a byte pattern that may be matched that happens to also be a thirty-two bit integer. The sequence number may be four bytes aligned to the edge of the shared buffer pool length. There may be optional RS232 synchronizing bytes so that users may move cables around while debugging a message stream and both sides of the interface may resynchronize. The application, driver and PCGP may share buffers and may release them by pointer.

(191) PCGP may not be an event driven software design, but may be used in event driven architectures by how the sub-classes are written. Data may be exchanged between the classes conceptually (as shown in FIG. 11M-11N).

(192) Some event model in the driver may wake the driver, may receive a message and may pass the message through the bridge into the buffer manager that routes the message to new owner of the new message (through a bridge to either a driver or PCGP).

(193) The following summarizes some exemplary events:

(194) TABLE-US-00004 Event: Possible use: Where this occurs: When a new send or reply Decide to run Inside is queued, or decTimeouts packetProcessor. PCGP: :sendInternal generates a timeout reply. When a messages is Decide to run BufferManager: :give received for PCGP. packetProcessor. When a driver has Wake driver for TX. BufferManager: :give something new to send. When a Driver RX Turn off flow control. BufferManager: :give buffer becomes available.

(195) The following illustrative example shows how the PCGP event model may work with Nucleus to wakeup the PCGP task after every message send, reply, or decTimeout that generated a NACK:

```
(196) TABLE-US-00005 class Pcgpos : public Pcgp {    virtual void schedulePacketProcessor(void)    {  
OS_EventGrp_Set(g_RCVEvGrps[EVG_RF_TASK].pEvgHandle,    RfRadioTxEvent, OS_EV_OR_NO_CLEAR);    }  
}
```

(197) The following is a pseudo code driver that is event based, illustrating how driver events work. The Driver subclasses Bridge and overrides hasMessagesToSend and flowControlTurnedOff to schedule the TX and RX functions to run if they aren't already running.

```
(198) TABLE-US-00006    class SPI_Driver : public Bridge {    virtual void hasMessagesToSend()    {  
Trigger_ISR(TX_ISR, this);    }    virtual void flowControlTurnedOff()    {    Trigger_ISR(RX_ISR, this);    }    static void  
TX_RetryTimer()    {    Trigger_ISR(TX_ISR, this);    }    static void TX_ISR(Bridge *b)    {    DisableISRs();    do  
    {    uint8 *p = b->nextBufferTX();    if (p == null) break;    if (b->_bufferManager-  
>bufferTimedOut(p)==false)    {    if (OtherSideSPI_FlowControl() == false)    {    Trigger  
TX_RetryTimer in 20 msec.    break;    }    send(p);    }    free(p)    } while (true);  
EnableISRs();    }    static void RX_ISR(Bridge *b)    {    DisableISRs();    do    {    uint8* p = b-  
>nextBufferRX();    if (p == null) break;    uint i;    while (not done receiving)    p[i++] = getChar();  
b->route(p);    } while (true);    EnableISRs();    } }
```

(199) The following statistics may be supported by PCGP: Number of packets sent; Number of packets received; CRC errors; Timeouts; and Buffer unavailable (ran out of buffers)

(200) PCGP may be designed to run in multiple processing environments. Most parameters may be run time configured because it facilitates testing, and any run time fine tuning for performance. Other parameters may be compile time e.g., anything that alters memory allocation must be done statically at compile time.

(201) The following may be compile time configuration #defines that may vary where PCGP is implemented: # driver bytes: may be two bytes reserved in the common buffer scheme for the driver, but this may be a compile time option to accommodate other drivers such as RF protocol. #RX driver buffers: may be tuned to how many buffers would be good for that processor/traffic flow, etc. #PCGP RX buffers: may be tuned to how many buffers would be good for that processor/traffic flow, etc. Total # of buffers: may be tuned to how many buffers should be at that processor.

(202) The CRC may be used to ensure data integrity. If a CRC is invalid, it may not be delivered to the application and the CRC error may be tracked. The message may eventually timeout and may be retried by the originator.

(203) Likewise, if the messaging system informs the application that a message was delivered when it was not, this may be a hazard to the system. The Stop Bolus Command is an example of such a command. This may be mitigated by the Request/Action sequence of messages which may be required by the application to change therapy. The Controller may receive a matching command from the Pump application to consider the message delivered.

(204) DEKA may provide a reference way of interfacing PCGP into the Nucleus OS system on the ARM 9 (as shown in FIG. 110).

(205) As shown in FIG. 11P, the pcgpOS.cpp file may instantiate a PCGP node instance (Pcgpos, a Bridge, etc.) and may provide through pcgpOS.h a 'C' linkable set of function calls that provide a 'C' language interface to the C++ code. This may simplify the 'C' code as the objects acted upon are implicit.

(206) The following general rules may be applied: PCGP may run on all nodes: any driver may support a generic driver interface. Race conditions may not be permitted. May support half duplex on the SPI port between slave processor and master processor. Data transfer may not be attempted; as it either succeeds or returns fail/false. May require low overhead (time, processing, bandwidth wasted). May support CC2510 operating at DMA (fast) SPI clock rates.

(207) SPI flow control may prevent data from being sent if the receiving side does not currently have an empty buffer to place the packet. This may be accomplished by asking for permission to send and waiting for a response indicating that you have been cleared to do so. There may also be a way to tell the other side that there are currently no free buffers and the transfer should be attempted at a later time.

(208) All transmission may begin with a length byte that indicates the number of bytes to be sent, not including the length byte itself. Following the length may be a single byte indicating the command being sent.

(209) The actual transmission of a packet may be the length of packet plus one for the command byte, followed by the command byte for a message appended and finally the packet itself.

(210) In addition to the command bytes that will be sent, an additional hardware line called the FlowControl line may be added to the traditional four SPI signals. The purpose of this line is to allow the protocol to run as quickly as possible without a need for preset delays. It also allows the slave processor to tell the master processor that it has a packet waiting to be sent, thus eliminating the need for the master processor to poll the slave processor for status.

(211) The following exemplary command values may be used:

(212) Commands to be Sent by the Master Processor:

(213) TABLE-US-00007 Command Value Description M_RTS 0xC1 Master is requesting to send a packet M_MSG_APPENDED 0xC2 Master is sending a packet M_CTS 0xC3 Master is tell slave it is Cleared to Send M_ERROR 0xC4 An Error condition has been encountered

Commands to be Sent by the Slave Processor:

(214) TABLE-US-00008 Command Value Description S_PREPARING_FOR_RX 0xA1 Slave is prepare the dma to receive a packet S_RX_BUFF_FULL 0xA2 Slave is currently out of RX buffers, retry later S_MSG_APPENDED 0xA3 Slave is sending a packet S_ERROR 0xA4 An Error condition has been encountered

(215) As illustrated in FIG. 11Q, when the slave processor has a packet to send to the master processor, the slave processor may notify the master processor (by asserting the FlowControl line) that it has a pending packet that is waiting to be sent. Doing so may result in an IRQ on the master processor at which time the master processor may decide when to go retrieve the message from the slave processor. Retrieving the packet may be delayed at the discretion of the master processor, and the master processor may even decide to attempt to send a packet to the slave processor before retrieving from the slave processor.

(216) The master processor may begin the retrieval by sending the slave processor M_CTS commands; this shall be repeated until the slave processor responds by sending the S_MSG_APPENDED command along with the packet itself. The FlowControl line may be cleared after the packet has been sent. If a M_CTS command is received by the slave processor when one is not expected, the M_CTS command may be ignored.

(217) As illustrated in FIG. 11R, when the master processor has a packet to send to the slave processor, the master processor may initiate the transfer by sending a M_RTS command. Upon receiving the M_RTS command, if the slave processor currently has a send packet pending, the slave processor will lower the FlowControl line so that it may be re-used as a Cleared To Send signal. The slave processor may then tell the master processor that it is in the process of preparing the SPI DMA to receive the packet, during which time the master processor may stop clocking bytes onto the bus and may allow the slave processor to finish preparing for the receive.

(218) The slave processor may then indicate it is ready to receive the full packet by raising the FlowControl line (which is now used as the CTS signal). Upon receiving the CTS signal, the master processor may proceed to send the M_MSG_APPENDED command along with the packet itself.

(219) After the completion of the transfer, the slave processor may lower the FlowControl line. If a packet was pending at the start of the transfer, or a send occurred on the slave processor when the packet was being received, the slave processor may reassert the FlowControl line now indicating that it has a pending packet.

(220) Referring again to FIG. 11A, infusion pump assembly **100, 100'** may include switch assembly **318** coupled to electrical control assembly **110** (FIG. 3) that may allow a user (not shown) to perform at least one, and in some embodiments, a plurality of tasks. One illustrative example of such a task is the administration of a bolus dose of the infusible fluid (e.g., insulin) without the use of a display assembly. Remote control assembly **300** may allow the user to enable/disable/configure infusion pump assembly **100, 100'** to administer the bolus dose of insulin.

(221) Referring also to FIG. 12A, slider assembly **306** may be configured, at least in part, to enable the user to manipulate the menu-based information rendered on display assembly **302**. An example of slider assembly **306** may include a capacitive slider assembly, which may be implemented using a CY8C21434-24LFXI PSOC offered by Cypress Semiconductor of San Jose, California, the design an operation of which are described within the "CSD User Module" published by Cypress Semiconductor. For example, via slider assembly **306**, the user may slide their finger in the direction of arrow **314**, resulting in the highlighted portion of the information included within main menu **350** (shown in FIG. 12A) rendered on display assembly **302** scrolling upward. Alternatively, the user may slide their finger in the direction of arrow **316**, resulting in the highlighted portion of the information included within main menu **350** rendered on display assembly **302** scrolling downward.

(222) Slider assembly **306** may be configured so that the rate at which e.g. the highlighted portion of main menu **350** scrolls "upward" or "downward" varies depending upon the displacement of the finger of the user with respect to point of origin **320**. Therefore, if the user wishes to quickly scroll "upward", the user may position their finger near the top of slider assembly **306**. Likewise, if the user wishes to quickly scroll "downward", the user may position their finger near the bottom of slider assembly **306**. Additionally, if the user wishes to slowly scroll "upward", the user may position their finger slightly "upward" with respect to point of origin **320**. Further, if the user wishes to slowly scroll "downward", the user may position their finger slightly "downward" with respect to point of origin **320**. Once the appropriate menu item is highlighted, the user may select the highlighted menu item via one or more switch assemblies **308, 310**.

(223) Referring also to FIGS. 12B-12F, assume for illustrative purposes that infusion pump assembly **100, 100'** is an insulin pump and the user wishes to configure infusion pump assembly **100, 100'** so that when switch assembly **318** is depressed by the user, a 0.20 unit bolus dose of insulin is administered. Accordingly, the user may use slider assembly **306** to highlight "Bolus" within main menu **350** rendered on display assembly **302**. The user may then use switch assembly **308** to select "Bolus". Once selected, processing logic (not shown) within remote control assembly **300** may then render submenu **352** on display assembly **302** (as shown in FIG. 12B).

(224) The user may then use slider assembly **306** to highlight "Manual Bolus" within submenu **352**, which may be selected using switch assembly **308**. Processing logic (not shown) within remote control assembly **300** may then render submenu **354** on display

assembly **302** (as shown in FIG. 12C).

(225) The user may then use slider assembly **306** to highlight “Bolus: 0.0 Units” within submenu **354**, which may be selected using switch assembly **308**. Processing logic (not shown) within remote control assembly **300** may then render submenu **356** on display assembly **302** (as shown in FIG. 12D).

(226) The user may then use slider assembly **306** to adjust the “Bolus” insulin amount to “0.20 units”, which may be selected using switch assembly **308**. Processing logic (not shown) within remote control assembly **300** may then render submenu **358** on display assembly **302** (as shown in FIG. 12E).

(227) The user **14** may then use slider assembly **306** to highlight “Confirm”, which may be selected using switch assembly **308**. Processing logic (not shown) within remote control assembly **300** may then generate the appropriate signals that may be sent to the above-described telemetry circuitry (not shown) included within remote control assembly **300**. The telemetry circuitry (not shown) included within the remote control assembly may then transmit, via wireless communication channel **312** established between remote control assembly **300** and infusion pump assembly **100'**, the appropriate configuration commands to configure infusion pump assembly **100'** so that whenever switch assembly **318** is depressed by the user, a 0.20 unit bolus dose of insulin is administered.

(228) Once the appropriate commands are successfully transmitted, processing logic (not shown) within remote control assembly **300** may once again render submenu **350** on display assembly **302** (as shown in FIG. 12F).

(229) Specifically and once programmed via remote control assembly **300**, the user may depress switch assembly **318** of infusion pump assembly **100'** to administer the above-described 0.20 unit bolus dose of insulin. Via the above-described menuing system included within remote control assembly **300**, the user may define a quantity of insulin to be administered each time that the user depresses switch assembly **318**. While this particular example specifies that a single depression of switch assembly **318** is equivalent to 0.20 units of insulin, this is for illustrative purposes only and is not intended to be a limitation of this disclosure, as other values (e.g. 1.00 units of insulin per depression) are equally applicable.

(230) Assume for illustrative purposes that the user wishes to administer a 2.00 unit bolus dose of insulin. To activate the above-described bolus dose administration system, the user may be required to press and hold switch assembly **318** for a defined period of time (e.g. five seconds), at which point infusion pump assembly **100, 100'** may generate an audible signal indicating to the user that infusion pump assembly **100, 100'** is ready to administer a bolus dose of insulin via switch assembly **318**. Accordingly, the user may depress switch assembly **318** ten times (i.e., 2.00 units is ten 0.20 unit doses). After each time that switch assembly **318** is depressed, infusion pump assembly **100, 100'** may provide an audible response to the user via an internal speaker/sound generation device (not shown). Accordingly, the user may depress switch assembly **318** the first time and infusion pump assembly **100, 100'** may generate a confirmation beep in response, thus indicating to the user that infusion pump assembly **100, 100'** received the command for (in this particular example) 0.20 units of insulin. As the desired bolus dose is 2.00 units of insulin, the user may repeat this procedure nine more times in order to effectuate a bolus dose of 2.00 units, wherein infusion pump assembly **100, 100'** generates a confirmation beep after each depression of switch assembly **318**.

(231) While in this particular example, infusion pump assemblies **100, 100'** are described as providing one beep after each time the user depresses switch assembly **318**, this is for illustrative purposes only and is not intended to be a limitation of this disclosure. Specifically, infusion pump assembly **100, 100'** may be configured to provide a single beep for each defined quantity of insulin. As discussed above, a single depression of switch assembly **318** may be equivalent to 0.20 units of insulin.

Accordingly, infusion pump assembly **100, 100'** may be configured to provide a single beep for each 0.10 units of insulin.

Accordingly, if infusion pump assembly **100, 100'** is configured such that a single depression of switch assembly **318** is equivalent to 0.20 units of insulin, each time switch assembly **318** is depressed, infusion pump assembly **100, 100'** may provide the user with two beeps (i.e. one for each 0.10 units of insulin).

(232) Once the user has depressed switch assembly **318** on infusion pump assembly **100'** a total of ten times, the user may simply wait for infusion pump assembly **100, 100'** to acknowledge receipt of the instructions to administer a 2.00 unit bolus dose of insulin (as opposed to the confirmation beep received at each depression of switch assembly **318**). Once a defined period of time (e.g., two seconds) passes, infusion pump assembly **100, 100'** may provide an audible confirmation to the user concerning the quantity of units to be administered via the bolus insulin dose that the user just requested. For example, as (in this example) infusion pump assembly **100, 100'** was programmed by the user so that a single depression of switch assembly **318** is equivalent to 0.20 units of insulin, infusion pump assembly **100, 100'** may beep ten times (i.e., 2.00 units is ten 0.20 unit doses).

(233) When providing feedback to the user concerning the quantity of units to be administered via the bolus insulin dose, infusion pump assembly **100, 100'** may provide a multifrequency audible confirmation. For example and continuing with the above-stated example in which ten beeps are to be provided to the user, infusion pump assembly **100, 100'** may group the beeps into groups of five (to facilitate easier counting by the user) and the beeps within each group of five may be rendered by infusion pump assembly **100, 100'** so that each subsequent beep has a higher frequency than the preceding beep (in a manner similar to a musical scale).

Accordingly and continuing with the above-stated example, infusion pump assembly **100, 100'** may render a 1,000 Hz beep, followed by an 1,100 Hz beep, followed by a 1,200 Hz beep, followed by a 1,300 Hz beep, followed by a 1,400 Hz beep (thus completing a group of five beeps), followed by a short pause, and then a 1,000 Hz beep, followed by an 1,100 Hz beep, followed by a 1,200 Hz beep, followed by a 1,300 Hz beep, followed by a 1,400 Hz beep (thus completing the second group of five beeps). According to various additional/alternative embodiments the multifrequency audible confirmation may utilize various numbers of tones incrementing in frequency. For example, an embodiment may utilize twenty different tones incrementing in frequency. However, the number of tones should not be construed as a limitation of the present disclosure as number of tones may vary according to design criteria and user need.

(234) Once infusion pump assembly **100, 100'** completes the rendering of the multifrequency audible confirmation (i.e. the ten beeps described above), the user may, within a defined period of time (e.g. two seconds), depress switch assembly **318** to provide a confirmation signal to infusion pump assembly **100, 100'**, indicating that the multifrequency audible confirmation was accurate and indicative of the size of the bolus dose of insulin to be administered (i.e. 2.00 units). Upon receiving this confirmation signal,

infusion pump assembly **100**, **100'** may render a “confirmation received” audible tone and effectuate the delivery of (in this particular example) the 2.00 unit bolus dose of insulin. In the event that infusion pump assembly **100**, **100'** fails to receive the above-described confirmation signal, infusion pump assembly **100**, **100'** may render a “confirmation failed” audible tone and will not effectuate the delivery of the bolus dose of insulin. Accordingly, if the multifrequency audible confirmation was not accurate/indicative of the size of the bolus dose of insulin to be administered, the user may simply not provide the above-described confirmation signal, thereby canceling the delivery of the bolus dose of insulin.

(235) As discussed above, in one exemplary embodiment of the above-described infusion pump assembly, infusion pump assembly **100'** may be used to communicate with a remote control assembly **300**. When such a remote control assembly **300** is utilized, infusion pump assembly **100'** and remote control assembly **300** may routinely contact each other to ensure that the two devices are still in communication with each other. For example, infusion pump assembly **100'** may “ping” remote control assembly **300** to ensure that remote control assembly **300** is present and active. Further, remote control assembly **300** may “ping” infusion pump assembly **100'** to ensure that infusion pump assembly **100'** is still present and active. In the event that one of infusion pump assembly **100'** and remote control assembly **300** fails to establish communication with the other assembly, the assembly that is unable to establish communication may sound a “separation” alarm. For example, assume that remote control assembly **300** is left in the car of the user, while infusion pump assembly **100'** is in the pocket of the user. Accordingly and after a defined period of time, infusion pump assembly **100'** may begin sounding the “separation” alarm, indicating that communication with remote control assembly **300** cannot be established. Using switch assembly **318**, the user may acknowledge/silence this “separation” alarm.

(236) As the user may define and administer a bolus insulin dose via switch assembly **318** of infusion pump assembly **100'** while remote control assembly **300** is not in communication with infusion pump assembly **100'**, infusion pump assembly **100'** may store information concerning the administered bolus insulin dose within a log file (not shown) stored within infusion pump assembly **100'**. This log file (not shown) may be stored within nonvolatile memory (not shown) included within infusion pump assembly **100'**. Upon communication being reestablished between infusion pump assembly **100'** and remote control assembly **300**, infusion pump assembly **100'** may provide the information concerning the administered bolus insulin dose stored within the log file (not shown) of infusion pump assembly **100'** to remote control assembly **300**.

(237) Further, if the user anticipates separating remote control assembly **300** from infusion pump assembly **100'**, the user (via the above-described menuing system) may configure infusion pump assembly **100'** and remote control assembly **300** to be in “separation” mode, thus eliminating the occurrence of the above-described “separation” alarms. However, the devices may continue to “ping” each other so that when they come back into communication with each other, infusion pump assembly **100'** and remote control assembly **300** may automatically exit “separation” mode.

(238) Further, if the user anticipates traveling in an airplane, the user (via the above-described menuing system of remote control assembly **300**) may configure infusion pump assembly **100'** and remote control assembly **300** to be in “airplane” mode, in which each of infusion pump assembly **100'** and remote control assembly **300** suspend any and all data transmissions. While in “airplane” mode, infusion pump assembly **100'** and remote control assembly **300** may or may not continue to receive data.

(239) Switch assembly **318** may be used to perform additional functions, such as: checking the battery life of reusable housing assembly **102**; pairing reusable housing assembly **102** with remote control assembly **300**; and aborting the administration of a bolus dose of infusible fluid.

(240) Checking Battery Life: Reusable housing assembly **102** may include a rechargeable battery assembly that may be capable of powering infusion pump assembly **100**, **100'** for approximately three days (when fully charged). Such a rechargeable battery assembly may have a usable life of a predetermined number of usable hours, for example, or years, or other predetermined length of usage. However, the predetermined life may depend on many factors, including but not limited to, one or more of the following: climate, daily usage, and number of recharges. Whenever reusable housing assembly **102** is disconnected from disposable housing assembly **114**, infusion pump assembly **100**, **100'** may perform a battery check on the above-described rechargeable battery assembly whenever switch assembly **318** is depressed for a defined period of time (e.g. in excess of two seconds). In the event that the above-described rechargeable battery assembly is determined to be charged above a desired threshold, infusion pump assembly **100**, **100'** may render a “battery pass” tone. Alternatively, in the event that the above-described rechargeable battery assembly is determined to be charged below a desired threshold, infusion pump assembly **100**, **100'** may render a “battery fail” tone. Infusion pump assembly **100**, **100'** may include components and/or circuitry to determine whether reusable housing assembly **102** is disconnected from disposable housing assembly **114**.

(241) Pairing: As discussed above and in one exemplary embodiment of the above-described infusion pump assembly, infusion pump assembly **100'** may be used to communicate with remote control assembly **300**. In order to effectuate communication between infusion pump assembly **100'** and remote control assembly **300**, a pairing process may be performed. During such a pairing process, one or more infusion pump assemblies (e.g. infusion pump assembly **100'**) may be configured to communicate with remote control assembly **300** and (conversely) remote control assembly **300** may be configured to communicate with one or more infusion pump assemblies (e.g. infusion pump assembly **100'**). Specifically, the serial numbers of the infusion pump assemblies (e.g. infusion pump assembly **100'**) may be recorded within a pairing file (not shown) included within remote control assembly **300** and the serial number of remote control assembly **300** may be recorded within a pairing file (not shown) included within the infusion pump assemblies (e.g. infusion pump assembly **100'**).

(242) According to an embodiment, in order to effectuate such a pairing procedure, the user may simultaneously hold down one or more switch assemblies on both remote control assembly **300** and infusion pump assembly **100'**. For example, the user may simultaneously hold down switch assembly **310** included within remote control assembly **300** and switch assembly **318** included within infusion pump assembly **100'** for a defined period exceeding e.g. five seconds. Once this defined period is reached, one or more of remote control assembly **300** and infusion pump assembly **100'** may generate an audible signal indicating that the above-described pairing procedure has been effectuated.

(243) According to another embodiment, prior to performing the pairing process, the user may uncouple reusable housing

assembly **102** from disposable housing assembly **114**. By requiring this initial step, further assurance is provided that an infusion pump assembly being worn by a user may not be surreptitiously paired with a remote control assembly.

(244) Once uncoupled, the user may enter pairing mode via input assembly **304** of remote control assembly **300**. For example, the user may enter pairing mode on remote control assembly **300** via the above-described menuing system in combination with e.g., switch assembly **310**. The user may be prompted on display assembly **302** of remote control assembly **300** to depress and hold switch assembly **318** on infusion pump assembly **100'**. Additionally, remote control assembly **304** may switch to a low power mode to e.g., avoid trying to pair with distant infusion pump assemblies. The user may then depress and hold switch assembly **318** on infusion pump assembly **100'** so that infusion pump assembly **100'** enters a receive mode and waits for a pairing command from remote control assembly **300**.

(245) Remote control assembly **300** may then transmit a pairing request to infusion pump assembly **100'**, which may be acknowledged by infusion pump assembly **100'**. Infusion pump assembly **100'** may perform a security check on the pairing request received from remote control assembly **300** and (if the security check passes) infusion pump assembly **100'** may activate a pump pairing signal (i.e., enter active pairing mode). Remote control assembly **300** may perform a security check on the acknowledgment received from infusion pump assembly **100'**.

(246) The acknowledgment received from infusion pump assembly **100'** may define the serial number of infusion pump assembly **100'** and remote control assembly **300** may display that serial number on display assembly **302** of remote control assembly **300**. The user may be asked if they wish to pair with the pump found. If the user declines, the pairing process may be aborted. If the user agrees to the pairing process, remote control assembly **300** may prompt the user (via display assembly **302**) to depress and hold switch assembly **318** on infusion pump assembly **100'**.

(247) The user may then depress and hold switch assembly **318** on infusion pump assembly **100'** and depress and hold e.g. switch assembly **310** on remote control assembly **300**.

(248) Remote control assembly **300** may confirm that remote switch assembly **310** was held (which may be reported to infusion pump assembly **100'**). Infusion pump assembly **100'** may perform a security check on the confirmation received from remote control assembly **300** to confirm the integrity of same. If the integrity of the confirmation received is not verified, the pairing process is aborted. If the integrity of the confirmation received is verified, any existing remote pair configuration file is overwritten to reflect newly-paired remote control assembly **300**, the pump pairing completed signal is activated, and the pairing process is completed.

(249) Additionally, infusion pump assembly **100'** may confirm that switch assembly **318** was held (which may be reported to remote control assembly **300**). Remote control assembly **300** may perform a security check on the confirmation received from infusion pump assembly **100'** to confirm the integrity of same. If the integrity of the confirmation received is not verified, the pairing process is aborted. If the integrity of the confirmation received is verified, a pair list file within remote control assembly **300** may be modified to add infusion pump assembly **100'**. Typically, remote control assembly **300** may be capable of pairing with multiple infusion pump assemblies, while infusion pump assembly **100'** may be capable of only pairing with a single remote control assembly. The pairing completed signal may be activated and the pairing process may be completed.

(250) When the pairing process is completed, one or more of remote control assembly **300** and infusion pump assembly **100'** may generate an audible signal indicating that the above-described pairing procedure has been successfully effectuated.

(251) Aborting Bolus Dose: in the event that the user wishes to cancel a bolus dose of e.g. insulin being administered by infusion pump assembly **100'**, the user may depress switch assembly **318** (e.g., shown in FIGS. **1** & **2**) for a defined period exceeding e.g. five seconds. Once this defined period is reached, infusion pump assembly **100'** may render an audible signal indicating that the above-described cancellation procedure has been effectuated.

(252) While switch assembly **318** is shown as being positioned on the top of infusion pump assembly **100, 100'**, this is for illustrative purposes only and is not intended to be a limitation of this disclosure, as other configurations are possible. For example, switch assembly **318** may be positioned about the periphery of infusion pump assembly **100, 100'**.

(253) Referring also to FIGS. **13-15**, there is shown an alternative-embodiment infusion pump assembly **400**. As with pump assembly **100, 100'**, infusion pump assembly **400** may include reusable housing assembly **402** and disposable housing assembly **404**.

(254) In a fashion similar to reusable housing assembly **102**, reusable housing assembly **402** may include a mechanical control assembly (that includes at least one pump assembly and at least one valve assembly). Reusable housing assembly **402** may also include an electrical control assembly that is configured to provide control signals to the mechanical control assembly and effectuate the delivery of an infusible fluid to a user. The valve assembly may be configured to control the flow of the infusible fluid through a fluid path and the pump assembly may be configured to pump the infusible fluid from the fluid path to the user.

(255) In a fashion similar to disposable housing assembly **114**, disposable housing assembly **404** may be configured for a single use or for use for a specified period of time, e.g., e.g., three days or any other amount of time. Disposable housing assembly **404** may be configured such that any components in infusion pump assembly **400** that come in contact with the infusible fluid are disposed on and/or within disposable housing assembly **404**.

(256) In this particular embodiment of the infusion pump assembly, infusion pump assembly **400** may include switch assembly **406** positioned about the periphery of infusion pump assembly **400**. For example, switch assembly **406** may be positioned along a radial edge of infusion pump assembly **400**, which may allow for easier use by a user. Switch assembly **406** may be covered with a waterproof membrane configured to prevent the infiltration of water into infusion pump assembly **400**. Reusable housing assembly **402** may include main body portion **408** (housing the above-described mechanical and electrical control assemblies) and locking ring assembly **410** that may be configured to rotate about main body portion **408** (in the direction of arrow **412**).

(257) In a fashion similar to reusable housing assembly **102** and disposable housing assembly **114**, reusable housing assembly **402** may be configured to releasably engage disposable housing assembly **404**. Such releasable engagement may be accomplished by a screw-on, a twist-lock or a compression fit configuration, for example. In an embodiment in which a twist-lock configuration is utilized, the user of infusion pump assembly **400** may first properly position reusable housing assembly **402** with respect to

disposable housing assembly **404** and may then rotate locking ring assembly **410** (in the direction of arrow **412**) to releasably engage reusable housing assembly **402** with disposable housing assembly **404**.

(258) Through the use of locking ring assembly **410**, reusable housing assembly **402** may be properly positioned with respect to disposable housing assembly **404** and then releasably engaged by rotating locking ring assembly **410**, thus eliminating the need to rotate reusable housing assembly **402** with respect to disposable housing assembly **404**. Accordingly, reusable housing assembly **402** may be properly aligned with disposable housing assembly **404** prior to engagement, and such alignment may not be disturbed during the engagement process. Locking ring assembly **410** may include a latching mechanism (not shown) that may prevent the rotation of locking ring assembly **410** until reusable housing assembly **402** and disposable housing assembly **404** are properly positioned with respect to each other.

(259) Referring also to FIGS. **16-18**, there is shown an alternative-embodiment infusion pump assembly **500**. As with pump assembly **100**, **100'**, infusion pump assembly **500** may include reusable housing assembly **502** and disposable housing assembly **504**.

(260) In a fashion similar to reusable housing assembly **402**, reusable housing assembly **502** may include a mechanical control assembly (that includes at least one pump assembly and at least one valve assembly). Reusable housing assembly **502** may also include an electrical control assembly that is configured to provide control signals to the mechanical control assembly and effectuate the delivery of an infusible fluid to a user. The valve assembly may be configured to control the flow of the infusible fluid through a fluid path and the pump assembly may be configured to pump the infusible fluid from the fluid path to the user.

(261) In a fashion similar to disposable housing assembly **404**, disposable housing assembly **504** may be configured for a single use or for use for a specified period of time, e.g., e.g., three days or any other amount of time. Disposable housing assembly **504** may be configured such that any components in infusion pump assembly **500** that come in contact with the infusible fluid are disposed on and/or within disposable housing assembly **504**.

(262) In this particular embodiment of the infusion pump assembly, infusion pump assembly **500** may include switch assembly **506** positioned about the periphery of infusion pump assembly **500**. For example, switch assembly **506** may be positioned along a radial edge of infusion pump assembly **500**, which may allow for easier use by a user. Switch assembly **506** may be covered with a waterproof membrane and/or an o-ring or other sealing mechanism may be included on the stem **507** of the switch assembly **506** configured to prevent the infiltration of water into infusion pump assembly **500**. However, in some embodiments, switch assembly **506** may include an overmolded rubber button, thus providing functionality as a waterproof seal without the use of a waterproof membrane or an o-ring. However, in still other embodiments, the overmolded rubber button may additionally be covered by a waterproof membrane and/or include an o-ring. Reusable housing assembly **502** may include main body portion **508** (housing the above-described mechanical and electrical control assemblies) and locking ring assembly **510** that may be configured to rotate about main body portion **508** (in the direction of arrow **512**).

(263) In a fashion similar to reusable housing assembly **402** and disposable housing assembly **404**, reusable housing assembly **502** may be configured to releasably engage disposable housing assembly **504**. Such releasable engagement may be accomplished by a screw-on, a twist-lock or a compression fit configuration, for example. In an embodiment in which a twist-lock configuration is utilized, the user of infusion pump assembly **500** may first properly position reusable housing assembly **502** with respect to disposable housing assembly **504** and may then rotate locking ring assembly **510** (in the direction of arrow **512**) to releasably engage reusable housing assembly **502** with disposable housing assembly **404**.

(264) As locking ring assembly **510** included within infusion pump assembly **500** may be taller (i.e., as indicated by arrow **514**) than locking ring assembly **410**, locking ring assembly **510** may include a passage **516** through which button **506** may pass. Accordingly, when assembling reusable housing assembly **502**, locking ring assembly **510** may be installed onto main body portion **508** (in the direction of arrow **518**). Once locking ring assembly **510** is installed onto main body portion **508**, one or more locking tabs (not shown) may prevent locking ring assembly **510** from being removed from main body portion **508**. The portion of switch assembly **506** that protrudes through passage **516** may then be pressed into main body portion **508** (in the direction of arrow **520**), thus completing the installation of switch assembly **506**.

(265) Although button **506** is shown in various locations on infusion pump assembly **500**, button **506**, in other embodiments, may be located anywhere desirable on infusion pump assembly **500**.

(266) Through the use of locking ring assembly **510**, reusable housing assembly **502** may be properly positioned with respect to disposable housing assembly **504** and then releasably engaged by rotating locking ring assembly **510**, thus eliminating the need to rotate reusable housing assembly **502** with respect to disposable housing assembly **504**. Accordingly, reusable housing assembly **502** may be properly aligned with disposable housing assembly **504** prior to engagement, and such alignment may not be disturbed during the engagement process. Locking ring assembly **510** may include a latching mechanism (not shown) that prevents the rotation of locking ring assembly **510** until reusable housing assembly **502** and disposable housing assembly **504** are properly positioned with respect to each other. Passage **516** may be elongated to allow for the movement of locking ring **510** about switch assembly **506**.

(267) Referring also to FIGS. **19A-19B** & **20-21**, there are shown various views of infusion pump assembly **500**, which is shown to include reusable housing assembly **502**, switch assembly **506**, and main body portion **508**. As discussed above, main body portion **508** may include a plurality of components, examples of which may include but are not limited to volume sensor assembly **148**, printed circuit board **600**, vibration motor assembly **602**, shape memory actuator anchor **604**, switch assembly **506**, battery **606**, antenna assembly **608**, pump assembly **106**, measurement valve assembly **610**, volume sensor valve assembly **612** and reservoir valve assembly **614**. To enhance clarity, printed circuit board **600** has been removed from FIG. **19B** to allow for viewing of the various components positioned beneath printed circuit board **600**.

(268) The various electrical components that may be electrically coupled with printed circuit board **600** may utilize spring-biased terminals that allow for electrical coupling without the need for soldering the connections. For example, vibration motor assembly **602** may utilize a pair of spring-biased terminals (one positive terminal and one negative terminal) that are configured to press against corresponding conductive pads on printed circuit board **600** when vibration motor assembly **602** is positioned on printed

circuit board **600**. However, in the exemplary embodiment, vibration motor assembly **602** is soldered directly to the printed circuit board.

(269) As discussed above, volume sensor assembly **148** may be configured to monitor the amount of fluid infused by infusion pump assembly **500**. For example, volume sensor assembly **148** may employ acoustic volume sensing, which is the subject of U.S. Pat. Nos. 5,575,310 and 5,755,683 assigned to DEKA Products Limited Partnership, as well as the U.S. patent application Publication Nos. US 2007/0228071 A1, US 2007/0219496 A1, US 2007/0219480 A1, US 2007/0219597 A1, the entire disclosures of all of which are incorporated herein by reference.

(270) Vibration motor assembly **602** may be configured to provide a vibration-based signal to the user of infusion pump assembly **500**. For example, in the event that the voltage of battery **606** (which powers infusion pump assembly **500**) is below the minimum acceptable voltage, vibration motor assembly **602** may vibrate infusion pump assembly **500** to provide a vibration-based signal to the user of infusion pump assembly **500**. Shape memory actuator anchor **604** may provide a mounting point for the above-described shape memory actuator (e.g. shape memory actuator **112**). As discussed above, shape memory actuator **112** may be, for example, a conductive shape-memory alloy wire that changes shape with temperature. The temperature of shape-memory actuator **112** may be changed with a heater, or more conveniently, by application of electrical energy. Accordingly, one end of shape memory actuator **112** may be rigidly affixed (i.e., anchored) to shape memory actuator anchor **604** and the other end of shape memory actuator **112** may be applied to e.g. a valve assembly and/or a pump actuator. Therefore, by applying electrical energy to shape memory actuator **112**, the length of shape memory actuator **112** may be controlled and, therefore, the valve assembly and/or the pump actuator to which it is attached may be manipulated.

(271) Antenna assembly **608** may be configured to allow for wireless communication between e.g. infusion pump assembly **500** and remote control assembly **300** (FIG. **11**). As discussed above, remote control assembly **300** may allow the user to program infusion pump assembly **500** and e.g. configure bolus infusion events. As discussed above, infusion pump assembly **500** may include one or more valve assemblies configured to control the flow of the infusible fluid through a fluid path (within infusion pump assembly **500**) and pump assembly **106** may be configured to pump the infusible fluid from the fluid path to the user. In this particular embodiment of infusion pump assembly **500**, infusion pump assembly **500** is shown to include three valve assemblies, namely measurement valve assembly **610**, volume sensor valve assembly **612**, and reservoir valve assembly **614**.

(272) As discussed above and referring also to FIG. **21**, the infusible fluid may be stored within reservoir **118**. In order to effectuate the delivery of the infusible fluid to the user, the processing logic (not shown) included within infusion pump assembly **500** may energize shape memory actuator **112**, which may be anchored on one end using shape memory actuator anchor **604**. Referring also to FIG. **22A**, shape memory actuator **112** may result in the activation of pump assembly **106** and reservoir valve assembly **614**. Reservoir valve assembly **614** may include reservoir valve actuator **614A** and reservoir valve **614B**, and the activation of reservoir valve assembly **614** may result in the downward displacement of reservoir valve actuator **614A** and the closing of reservoir valve **614B**, resulting in the effective isolation of reservoir **118**. Further, pump assembly **106** may include pump plunger **106A** and pump chamber **106B** and the activation of pump assembly **106** may result in pump plunger **106A** being displaced in a downward fashion into pump chamber **106B** and the displacement of the infusible fluid (in the direction of arrow **616**).

(273) Volume sensor valve assembly **612** may include volume sensor valve actuator **612A** and volume sensor valve **612B**. Referring also to FIG. **22B**, volume sensor valve actuator **612A** may be closed via a spring assembly that provides mechanical force to seal volume sensor valve **612B**. However, when pump assembly **106** is activated, if the displaced infusible fluid is of sufficient pressure to overcome the mechanical sealing force of volume sensor valve assembly **612**, the displacement of the infusible fluid occurs in the direction of arrow **618**. This may result in the filling of volume sensor chamber **620** included within volume sensor assembly **148**. Through the use of speaker assembly **622**, port assembly **624**, reference microphone **626**, spring diaphragm **628**, invariable volume microphone **630**, volume sensor assembly **148** may determine the volume of infusible fluid included within volume sensor chamber **620**.

(274) Referring also to FIG. **22C**, once the volume of infusible fluid included within volume sensor chamber **620** is calculated, shape memory actuator **632** may be energized, resulting in the activation of measurement valve assembly **610**, which may include measurement valve actuator **610A** and measurement valve **610B**. Once activated and due to the mechanical energy asserted on the infusible fluid within volume sensor chamber **620** by spring diaphragm **628**, the infusible fluid within volume sensor chamber **620** may be displaced (in the direction of arrow **634**) through disposable cannula **138** and into the body of the user.

(275) Referring also to FIG. **23**, there is shown an exploded view of infusion pump assembly **500**. Shape memory actuator **632** may be anchored (on a first end) to shape memory actuator anchor **636**. Additionally, the other end of shape memory actuator **632** may be used to provide mechanical energy to valve assembly **638**, which may activate measurement valve assembly **610**. Volume sensor assembly spring retainer **642** may properly position volume sensor assembly **148** with respect to the various other components of infusion pump assembly **500**. Valve assembly **638** may be used in conjunction with shape memory actuator **112** to activate pump plunger **106A**. Measurement valve **610B**, volume sensor valve **612B** and/or reservoir valve **614B** may be self-contained valves that are configured to allow for installation during assembly of infusion pump assembly **500** by pressing the valves upward into the lower surface of main body portion **508**.

(276) Referring also to FIG. **24** & FIGS. **25A-25D**, there is shown a more-detailed view of pump assembly **106**. Pump actuator assembly **644** may include pump actuator support structure **646**, bias spring **648**, and lever assembly **650**.

(277) Referring also to FIGS. **26A-26B** & FIGS. **27A-27B**, there is shown a more-detailed view of measurement valve assembly **610**. As discussed above, valve assembly **638** may activate measurement valve assembly **610**.

(278) Referring also to FIGS. **28A-28D**, infusion pump assembly **500** may include measurement valve assembly **610**. As discussed above, valve assembly **638** may be activated via shape memory actuator **632** and actuator assembly **640**. Accordingly, to infuse the quantity of infusible fluid stored within volume sensor chamber **620**, shape memory actuator **632** may need to activate valve assembly **638** for a considerable period of time (e.g. one minute or more). As this would consume a considerable amount of power from battery **606**, measurement valve assembly **610** may allow for the temporary activation of valve assembly **638**, at

which point measurement valve latch **656** may prevent valve assembly **638** from returning to its non-activated position. Shape memory actuator **652** may be anchored on a first end using electrical contact **654**. The other end of shape memory actuator **652** may be connected to a valve latch **656**. When shape memory actuator **652** is activated, shape memory actuator **652** may pull valve latch **656** forward and release valve assembly **638**. As such, measurement valve assembly **610** may be activated via shape memory actuator **632**. Once measurement valve assembly **610** has been activated, valve latch **656** may automatically latch valve assembly **638** in the activated position. Actuating shape memory actuator **652** may pull valve latch **656** forward and release valve assembly **638**. Assuming shape memory actuator **632** is no longer activated, measurement valve assembly **610** may move to a de-activated state once valve latch **656** has released valve assembly **638**. Accordingly, through the use of measurement valve assembly **610**, shape memory actuator **632** does not need to be activated during the entire time that it takes to infuse the quantity of infusible fluid stored within volume sensor chamber **620**.

(279) As discussed above, the above-described infusion pump assemblies (e.g., infusion pumps assemblies **100**, **100'**, **400**, **500**) may include an external infusion set **134** configured to deliver the infusible fluid to a user. External infusion set **134** may include a cannula assembly **136**, which may include a needle or a disposable cannula **138**, and tubing assembly **140**. Tubing assembly **140** may be in fluid communication with reservoir **118**, for example, by way of the fluid path, and with cannula assembly **138** for example, either directly or by way of a cannula interface **142**.

(280) Referring also to FIG. **29**, there is shown an alternative embodiment infusion pump assembly **700** that is configured to store a portion of tubing assembly **140**. Specifically, infusion pump assembly **700** may include peripheral tubing storage assembly **702** that is configured to allow the user to wind a portion of tubing assembly **140** about the periphery of infusion pump assembly **700** (in a manner similar to that of a yoyo). Peripheral tubing storage assembly **702** may be positioned about the periphery of infusion pump assembly **700**. Peripheral tubing storage assembly **702** may be configured as an open trough into which a portion of tubing assembly **140** may be wound. Alternatively, peripheral tubing storage assembly **702** may include one or more divider portions **704**, **706** that form a plurality of narrower troughs that may be sized to generate an interference fit between the walls of the narrower trough and the exterior surface of the portion of tubing **140**. When peripheral tubing storage assembly **702** includes plurality of divider portions **704**, **706**, the resulting narrower troughs may be wound in a spiral fashion about the periphery of infusion pump assembly **700** (in a manner similar to the thread of a screw).

(281) Referring also to FIGS. **30-31**, there is shown an alternative embodiment infusion pump assembly **750** that is configured to store a portion of tubing assembly **140**. Specifically, infusion pump assembly **750** may include peripheral tubing storage assembly **752** that is configured to allow the user to wind a portion of tubing assembly **140** about the periphery of infusion pump assembly **750** (again, in a manner similar to that of a yoyo). Peripheral tubing storage assembly **752** may be positioned about the periphery of infusion pump assembly **750**. Peripheral tubing storage assembly **752** may be configured as an open trough into which a portion of tubing assembly **140** is wound. Alternatively, peripheral tubing storage assembly **752** may include one or more divider portions **754**, **756** that form a plurality of narrower troughs that may be sized to generate an interference fit between the walls of the narrower trough and the exterior surface of the portion of tubing **140**. When peripheral tubing storage assembly **752** includes plurality of divider portions **754**, **756**, the resulting narrower trough may be wound in a spiral fashion about the periphery of infusion pump assembly **750** (again, in a manner similar to the thread of a screw).

(282) Infusion pump assembly **750** may include tubing retainer assembly **758**. Tubing retainer assembly **758** may be configured to releasably secure tubing assembly **140** so as to prevent tubing assembly **140** from unraveling from around infusion pump assembly **750**. In one embodiment of tubing retainer assembly **758**, tubing retainer assembly **758** may include downward facing pin assembly **760** positioned above upward facing pin assembly **762**. The combination of pin assemblies **760**, **762** may define a “pinch point” through which tubing assembly **140** may be pushed. Accordingly, the user may wrap tubing assembly **140** around the periphery of infusion pump assembly **750**, wherein each loop of tubing assembly **140** is secured within peripheral tubing storage assembly **752** via tubing retainer assembly **758**. In the event that the user wishes to lengthen the unsecured portion of tubing assembly **140**, the user may release one loop of tubing assembly **140** from tubing retainer assembly **758**. Conversely, in the event that the user wishes to shorten the unsecured portion of tubing assembly **140**, the user may secure one additional loop of tubing assembly **140** within tubing retainer assembly **758**.

(283) Referring also to FIGS. **32-33**, there is shown an exemplary embodiment of infusion pump assembly **800**. As with infusion pump assemblies **100**, **100'**, **400**, and **500**, infusion pump assembly **800** may include reusable housing assembly **802** and disposable housing assembly **804**.

(284) With reference also to FIGS. **34A-34B**, in a fashion similar to infusion pump assembly **100**, reusable housing assembly **802** may be configured to releasably engage disposable housing assembly **804**. Such releasable engagement may be effectuated by a screw-on, twist-lock, or compression fit configuration, for example. Infusion pump assembly **800** may include locking ring assembly **806**. For example, reusable housing assembly **802** may be properly positioned relative to disposable housing assembly, and locking ring assembly **806** may be rotated to releasably engage reusable housing assembly **802** and disposable housing assembly **804**.

(285) Locking ring assembly **806** may include nub **808** that may facilitate rotation of locking ring assembly **806**. Additionally, the position of nub **808**, e.g., relative to tab **810** of disposable housing assembly **804**, may provide verification that reusable housing assembly **802** is fully engaged with disposable housing assembly **804**. For example, as shown in FIG. **34A**, when reusable housing assembly **802** is properly aligned with disposable housing assembly **804**, nub **808** may be aligned in a first position relative to tab **810**. Upon achieving a fully engaged condition, by rotation locking ring assembly **806**, nub **808** may be aligned in a second position relative to tab **810**, as shown in FIG. **34B**.

(286) Referring also to FIGS. **35A-35C** and FIGS. **36-38A**, in a fashion similar to reusable housing assembly **102**, reusable housing assembly **802** may include mechanical control assembly **812** (e.g., which may include valve assembly **814**, shown in FIG. **36**, including one or more valves and one or more pumps for pumping and controlling the flow of the infusible fluid). Reusable housing assembly **802** may also include an electrical control assembly **816** that may be configured to provide control signals to the mechanical control assembly **812** to effectuate the delivery of an infusible fluid to the user. Valve assembly **814** may be configured

to control the flow of the infusible fluid through a fluid path and the pump assembly may be configured to pump the infusible fluid from the fluid path to the user.

(287) Mechanical control assembly **812** and electrical control assembly **816** may be contained within a housing defined by base plate **818**, body **820**. In some embodiments one or more of base plate **818** and body **820** may provide electromagnetic shielding. In such an embodiment, the electromagnetic shielding may prevent and/or reduce electromagnetic interference received by electrical control assembly **816** and/or created by electrical control assembly **816**. Additionally/alternatively, EMI shield **822** may be included, as shown in FIG. 36 and FIG. 37. EMI shield **822** may provide shielding against generated and/or received electromagnetic interference.

(288) Reusable housing assembly **802** may include a switch assembly that may be configured to receive user commands (e.g., for bolus delivery, pairing with a remote control assembly, or the like). The switch assembly may include button **824** that may be disposed in opening **826** of body **820**. As shown, e.g., in FIG. 35B, locking ring assembly **806** may include radial slot **828** that may be configured to allow locking ring assembly **806** to be rotated relative to body **820** while still providing facile access to button **824**.

(289) Referring also to FIGS. 39A-39C, electrical control assembly **816** may include printed circuit board **830** as well as battery **832**. Printed circuit board **830** may include the various control electronics for monitoring and controlling the amount of infusible fluid that has been and/or is being pumped. For example, electrical control assembly **816** may measure the amount of infusible fluid that has just been dispensed, and determine, based upon the dosage required by the user, whether enough infusible fluid has been dispensed. If not enough infusible fluid has been dispensed, electrical control assembly **816** may determine that more infusible fluid should be pumped. Electrical control assembly **816** may provide the appropriate signal to mechanical control assembly **812** so that any additional necessary dosage may be pumped or electrical control assembly **816** may provide the appropriate signal to mechanical control assembly **812** so that the additional dosage may be dispensed with the next dosage. Alternatively, if too much infusible fluid has been dispensed, electrical control assembly **816** may provide the appropriate signal to mechanical control assembly **812** so that less infusible fluid may be dispensed in the next dosage. Electrical control assembly **816** may include one or more microprocessors. In an exemplary embodiment, electrical control assembly **816** may include three microprocessors. One processor (e.g., which may include, but is not limited to a CC2510 microcontroller/RF transceiver, available from Chipcon AS, of Oslo, Norway) may be dedicated to radio communication, e.g., for communicating with a remote control assembly. Two additional microprocessors (example of which may include, but is not limited to an MSP430 microcontroller, available from Texas Instruments Inc. of Dallas, Texas) may be dedicated to issuing and carrying out commands (e.g., to dispense a dosage of infusible fluid, process feedback signals from a volume measurement device, and the like).

(290) As shown in FIG. 35C, base plate **818** may provide access to electrical contacts **834**, e.g., which may be electrically coupled to electrical control assembly **816** for recharging battery **832**. Base plate **818** may include one or more features (e.g., openings **836**, **838**) which may be configured to facilitate proper alignment with disposable housing assembly **804** by way of cooperating features (e.g., tabs) of disposable housing assembly **804**. Additionally, as shown in FIGS. 40A-40C, 41A-41B, and 42A-42C, base plate **818** may include various features for mounting valve assembly **814** and electrical control assembly **816**, as well as providing access to disposable housing assembly **804** by valve assembly **814**.

(291) Locking ring assembly **806** may include grip inserts **840**, **842**, e.g., which may include an elastomeric or textured material that may facilitate gripping and twisting locking ring assembly **806**, e.g., for engaging/disengaging reusable housing assembly **802** and disposable housing assembly **804**. Additionally, locking ring assembly **806** may include a sensing component (e.g., magnet **844**) that may interact with a component of reusable housing assembly **802** (e.g., a Hall Effect sensor), e.g., to provide an indication of the nature of a mating component (e.g., which in some embodiments may include, but is not limited to, one or more of disposable housing assembly **804**, a charging station, or a filling station) and/or of whether reusable housing assembly **802** is properly engaged with the mating component. In the exemplary embodiment, a Hall Effect sensor (not shown) may be located on the pump printed circuit board. The Hall Effect sensor may detect when the locking ring has been rotated to a closed position. Thus, the Hall Effect sensor together with magnet **844** may provide a system for determining whether the locking ring has been rotated to a closed position.

(292) The sensing component (magnet) **844** together with the reusable housing assembly components, i.e., in the exemplary embodiment, the Hall Effect sensor, may work to provide for a determination of whether the reusable housing assembly is properly attached to the intended component or device. Locking ring assembly **806** may not turn without being attached to a component, i.e., disposable housing assembly **804**, a dust cover or a charger. Thus, the sensing component together with the reusable housing assembly component may function to provide many advantageous safety features to the infusion pump system. These features may include, but are not limited to, one or more of the following. Where the system does not detect being attached to a disposable assembly, a dust cover or a charger, the system may notify, alert or alarm the user as the reusable portion, e.g., the valves and pumping components, may be vulnerable to contamination or destruction which may compromise the integrity of the reusable assembly. Thus, the system may provide for an integrity alarm to alert the user of potential reusable integrity threats. Also, where the system senses the reusable assembly is attached to a dust cover, the system may power off or reduce power to conserve power. This may provide for more efficient use of power where the reusable assembly is not connecting to a component in which it needs to interact.

(293) Reusable housing assembly **802** may attach to a number of different components, including but not limited to, a disposable housing assembly, a dust cover or a battery charger/battery charging station. In each case, the Hall Effect sensor may detect that the locking ring is in the closed position, and therefore, that reusable housing assembly **802** is releasably engaged to a disposable housing assembly, a dust cover, or a battery charger/battery charging station (or, another component). The infusion pump system may determine the component to which it is attached by using the AVS system described in more detail below or by an electronic contact. Referring now also to FIGS. 38B-38D, one embodiment of a dust cover (e.g., dust cover **839**) is shown. In the exemplary embodiment, dust cover **839** may include features **841**, **843**, **845**, **847** such that the locking ring of reusable housing assembly **802** may releasably engage dust cover **839**. In addition, dust cover **839** may further include recess region **849** for accommodating the

valving and pumping features of reusable housing assembly **804**. For example, with respect to the dust cover, the AVS system may determine that a dust cover, and not a disposable housing assembly, is connected to the reusable housing assembly. The AVS system may distinguish using a look-up table or other comparative data and comparing the measurement data with characteristic dust cover or empty disposable housing assembly data. With respect to the battery charger, the battery charger, in the exemplary embodiments, may include electric contacts. When the reusable housing assembly is attached to the battery charger, the infusion pump assembly electronic system may sense that the contacts have been made, and will thus indicate that the reusable housing assembly is attached to a battery charger.

(294) Referring also to FIGS. **43A-45B** and FIGS. **44A-44C** an embodiment of valve assembly **814**, which may include one or more valves and one or more pumps, is shown. As with infusion pump assemblies **100**, **100'**, **400**, and **500**, valve assembly **814** may generally include reservoir valve **850**, plunger pump **852**, volume sensor valve **854**, and measurement valve **856**. Similar to the previous description, reservoir valve **850** and plunger pump **852** may be actuated by shape memory actuator **858**, which may be anchored (on a first end) to shape memory actuator anchor **860**. Additionally, measurement valve **856** may be actuated, via valve actuator **862**, by shape memory actuator **864**, which may be anchored (on a first end) to shape memory actuator anchor **866**. In a similar manner as discussed above, measurement valve may be maintained in an open position via measurement valve latch assembly **868**. Measurement valve **856** may be released via actuation of shape memory actuator **870**, which may be anchored (on a first end) by shape memory actuator anchor **872**. In some embodiments, shape memory actuator anchor **860** may be potted onto the reusable housing assembly. Using this process during manufacture ensures shape memory length actuator **858** is installed and maintains the desired length and tension/strain.

(295) Referring also to FIGS. **45A-45B** and FIGS. **46A-46E**, shape memory actuator **858** (e.g., which may include one or more shape memory wires) may actuate plunger pump **852** via actuator assembly **874**. Actuator assembly **874** may include bias spring **876** and lever assembly **878**. Actuator assembly **874** may actuate both plunger pump **852** and measurement valve **850**.

(296) Referring also to FIGS. **47A-47B**, measurement valve **856** may be actuated by shape memory actuator **864**, via valve actuator **862** and lever assembly **878**. Once actuated, measurement valve latch assembly **868** may maintain measurement valve **856** in an open position. Measurement valve latch assembly **868** actuated by shape memory actuator **870** to release measurement valve **856**, allowing it to return to a closed position.

(297) Disposable housing assembly **804** may be configured for a single use or for use for a specified period of time, e.g., e.g., three days or any other amount of time. Disposable housing assembly **804** may be configured such that any of the component of infusion pump assembly **800** that come in contact with the infusible fluid may be disposed on and/or within disposable housing assembly **804**. As such, the risk of contaminating the infusible fluid may be reduced.

(298) Referring also to FIG. **48** and FIGS. **49A-49C**, disposable housing assembly **804** may include base portion **900**, membrane assembly **902**, and top portion **904**. Base portion **900** may include recess **906** that together with membrane assembly **902** defines reservoir **908** for receiving an infusible fluid (not shown), e.g., insulin. Referring also to FIGS. **50A-50C**, recess **906** may be at least partially formed by and integral with base portion **900**. Membrane assembly **902** may be sealingly engaged with base portion **900**, e.g., by being compressively pinched between base portion **900** and top portion **904**. Top portion **904** may be attached to base portion **900** by conventional means, such as gluing, heat sealing, ultrasonic welding, and compression fitting.

Additionally/alternatively, membrane assembly **902** may be attached to base portion **900**, e.g., via gluing, ultrasonic welding, heat sealing, and the like, to provide a seal between membrane assembly **902** and base portion **900**.

(299) Still referring to FIGS. **48** and **50A**, recess **906**, in the exemplary embodiment, includes raised portion **901** which includes area **903** about fluid openings **905** leading to the fluid line. Raised portion **901**, in the exemplary embodiment, extends about the perimeter of recess **906**. However, in other embodiments, raised portion **901** may not extend the entire perimeter, but may be partially about the perimeter. Area **903** about fluid openings **905** may be shaped as shown in the exemplary embodiment, including an angled portion, which in some embodiments, includes 45 degree angles, however in other embodiments, the angle may be greater or lesser. In some embodiments, the pump may not generate a sufficient enough vacuum to collapse the reservoir so as to eliminate the entire volume of fluid that may be stored in the reservoir. Raised portion **901** may act to minimize wasted fluid.

(300) Fluid openings **905**, which, in the exemplary embodiment, may include three openings, however, in other embodiments may include more openings or fewer openings, may be surrounded by area **903** of the raised portion. In the exemplary embodiment, fluid openings **905** may be narrow in the center, thus creating a surface tension that may prevent the air from being drawn into the opening. In the exemplary embodiment, this area may be designed to encourage any air that is present in the reservoir to be drawn above one of fluid openings **905** rather than be pulled through fluid openings **905** and into the fluid line. Additionally, because there may be more than one fluid opening **905**, where an air bubble is caught above one, the air may not prevent fluid from flowing through the other two openings.

(301) Referring also to FIGS. **51A-51C**, disposable housing assembly **804** may also include fluid pathway cover **910**. Fluid pathway cover **910** may be received in cavity **912** formed on/within base portion **900**. Fluid pathway cover **910** may, in some embodiments, include at least a portion of one or more channels (e.g., channel **914**). The channels included in fluid pathway cover **910** may fluidly couple one or more volcano valve features (e.g. volcano valves **916**) included on base portion **900**. Volcano valves **916** may include a protrusion having an opening extending through it. Additionally, fluid pathway cover **910** and base portion **900** may each define a portion of recess (e.g., recess portions **918**, **920** included in base portion **900** and fluid pathway cover **910** respectively) for fluidly coupling to an infusion set (e.g., including cannula **922**). Cannula **922** may be coupled to disposable housing assembly **804** by conventional means (e.g., gluing, heat sealing, compression fit, or the like). The fluid pathways defined by fluid pathway cover **910** and the volcano valves (e.g., volcano valves **916**) of base portion **900** may define a fluid pathway between reservoir **908** and cannula **922** for the delivery of the infusible fluid to the user via the infusion set. However, in some embodiments, fluid path cover **910** may include at least a portion of the fluid path, and in some embodiments, fluid path cover **910** may not include at least a portion of the fluid path. In the exemplary embodiment, fluid pathway cover **910** may be laser welded to base portion **900**. However, in other embodiments, fluid pathway cover **910** may also be connected to base portion **900** by conventional means (e.g., gluing, heat sealing, ultrasonic welding, compression fit, or the like) to achieve a

generally fluid tight seal between fluid pathway cover **910** and base portion **900**.

(302) With reference also to FIGS. **54A-54C**, disposable housing assembly **804** may further include valve membrane cover **924**. Valve membrane cover **924** may be at least partially disposed over the volcano valves (e.g., volcano valve **916**) and pumping recess **926** included on/within base portion **900**. Valve membrane cover **924** may include a flexible material, e.g., which may be selectively engaged against the volcano valves by reservoir valve **850**, volume sensor valve **854**, and measurement valve **856** of reusable housing assembly **802**, e.g., for controlling the flow of the infusible fluid. Additionally, valve membrane cover **924** may be resiliently deformed into pumping recess **926** by plunger pump **852** to effectuate pumping of the infusible fluid. Valve membrane cover **924** may be engaged between base portion **900** and top portion **904** of disposable housing assembly **804** to form seal **928** between valve membrane cover **924** and base portion **900**. For example, in the exemplary embodiment, valve membrane cover **924** may be overmolded onto base portion **900**. In other embodiment, valve membrane cover **924** may be compressively pinched between base portion **900** and top portion **904** to form seal **928**. Additionally/alternatively, valve membrane insert may be connected to one or more of base portion **900** and top portion **904**, e.g., by gluing, heat sealing, or the like.

(303) Referring also to FIGS. **53A-C**, top portion **904** may include alignment tabs **930**, **932** that may be configured to be at least partially received in openings **836**, **838** of base plate **818** of reusable housing assembly **802** to ensure proper alignment between reusable housing assembly **802** and disposable housing assembly **804**. Additionally, top portion **904** may include one or more radial tabs **934**, **936**, **938**, **940** configured to be engaged by cooperating tabs **942**, **944**, **946**, **948** of locking ring assembly **806**. The one or more radial tabs (e.g., radial tab **940**) may include stops (e.g., alignment tab stop **950**, which may be used for welding, it's the tab that fits in the recess to locate and ultrasonically weld), e.g., which may prevent further rotation of locking ring assembly **806** once reusable housing assembly **802** and disposable housing assembly **804** are fully engaged.

(304) As discussed above, valve membrane insert **924** may allow for pumping and flow of the infusible fluid by reservoir valve **850**, plunger pump **852**, volume sensor valve **854**, and measurement valve **856**. Accordingly, top portion **904** may include one or more openings (e.g., openings **952**, **954**, **956**) that may expose at least a portion of valve membrane insert **924** for actuation by reservoir valve **850**, plunger pump **852**, volume sensor valve **854**, and measurement valve **856**. Additionally, top portion **904** may include one or more openings **958**, **960**, **962** which may be configured to allow the fill volume to be controlled during filling of reservoir **908**, as will be discussed in greater detail below. Reservoir assembly **902** may include ribs **964**, **966**, **968** (e.g., as shown in FIG. **52A**), which may be at least partially received in respective openings **958**, **960**, **962**. As will be described in greater detail below, a force may be applied to one or more of ribs **964**, **966**, **968** to, at least temporarily, reduce the volume of reservoir **908**.

(305) In some embodiments, it may be desirable to provide a seal between reusable housing assembly **802** and disposable housing assembly **804**. Accordingly, disposable housing assembly **804** may include sealing assembly **970**. Sealing assembly **970** may include, for example, an elastomeric member that may provide a compressible rubber or plastic layer between reusable housing assembly **802** and disposable housing assembly **804** when engaged, thus preventing inadvertent disengagement and penetration by outside fluids. For example, sealing assembly **970** may be a watertight seal assembly and, thus, enable a user to wear infusion pump assembly **800** while swimming, bathing or exercising.

(306) In a fashion similar to, e.g., disposable housing assembly **114**, disposable housing assembly **802** may, in some embodiments, be configured to have reservoir **908** filled a plurality of times. However, in some embodiments, disposable housing assembly **114** may be configured such that reservoir **908** may not be refilled. Referring also to FIGS. **57-64**, fill adapter **1000** may be configured to be coupled to disposable housing assembly **804** for refilling reservoir **908** using a syringe (not shown). Fill adapter **1000** may include locking tabs **1002**, **1004**, **1006**, **1008** that may be configured to engage radial tabs **934**, **936**, **938**, **940** of disposable housing assembly **804** in a manner generally similar to tabs **942**, **944**, **946**, **948** of locking ring assembly **806**. Accordingly, fill adapter **1000** may be releasably engaged with disposable housing assembly **804** by aligning fill adapter **1000** with disposable housing assembly **804** and rotating fill adapter **1000** and disposable housing assembly **804** relative to one another to releasably engage locking tabs **1002**, **1004**, **1006**, **1008** with radial tabs **934**, **936**, **938**, **940**.

(307) Fill adapter **1000** may further include filling aid **1010**, which may include guide passage **1012**, e.g., which may be configured to guide a needle of a syringe (not shown) to a septum of disposable housing assembly **804** to allow reservoir **908** of disposable housing assembly **804** to be filled by the syringe. In some embodiments, guide passage **1012** may be an angled bevel or other gradual angled bevel to further guide a syringe to a septum. Fill adapter **1000** may facilitate filling reservoir **908** by providing a relatively large insertion area, e.g., at the distal opening of guide passage **1012**. Guide passage **1012** may generally taper to a smaller proximal opening that may be properly aligned with the septum of disposable housing assembly **804**, when fill adapter **1000** is engaged with disposable housing assembly **804**. Accordingly, fill adapter **1000** may reduce the dexterity and aim necessary to properly insert a needle through the septum of disposable housing assembly **804** for the purpose of filling reservoir **908**.

(308) As discussed above, disposable housing assembly **804** may configured to facilitate controlling the quantity of infusible fluid delivered to reservoir **908** during filling. For example, membrane assembly **902** of disposable housing assembly **804** may include ribs **964**, **966**, **968** that may be depressed and at least partially displaced into reservoir **908**, thereby reducing the volume of reservoir **908**. Accordingly, when infusible fluid is delivered to reservoir **908**, the volume of fluid that may be accommodated by reservoir **908** may be correspondingly reduced. Ribs **964**, **966**, **968** may be accessible via openings **958**, **960**, **962** in top portion **904** of disposable housing assembly **804**.

(309) Fill adapter **1000** may include one or more button assemblies (e.g., button assemblies **1014**, **1016**, **1018**) corresponding to ribs **964**, **966**, **968**. That is, when fill adapter **1000** is releasably engaged with disposable housing assembly **804**, buttons **1014**, **1016**, **1018** may be aligned with ribs **964**, **966**, **968**. Button assemblies **1014**, **1016**, **1018** may be, for example, cantilever members capable of being depressed. When fill adapter **1000** is releasably engaged with disposable housing assembly **804**, one or more of button assemblies **1014**, **1016**, **1018** may be depressed, and may correspondingly displace a respective one of ribs **964**, **966**, **698** into reservoir **908**, causing an attendant reduction in the volume of reservoir **908**.

(310) For example, assume for illustrative purposes that reservoir **908** has a maximum capacity of 3.00 mL. Further, assume that button assembly **1014** is configured to displace rib **964** into disposable housing assembly **804**, resulting in a 0.5 mL reduction in

the 3.00 mL capacity of disposable housing assembly **804**. Further, assume that button assembly **1016** is configured to displace rib **966** into disposable housing assembly **804**, also resulting in a 0.5 mL reduction in the 3.00 mL capacity of disposable housing assembly **804**. Further, assume that button assembly **1018** is configured to displace slot assembly **968** into disposable housing assembly **804**, also resulting in a 0.5 mL reduction in the 3.00 mL capacity of disposable housing assembly **804**. Therefore, if the user wishes to fill reservoir **908** within disposable housing assembly **804** with 2.00 mL of infusible fluid, in some embodiments, the user may first fill the reservoir to the 3.00 mL capacity and then depresses button assemblies **1016** and **1014** (resulting in the displacement of rib **966** into disposable housing assembly **804**), effectively reducing the 3.00 mL capacity of reservoir **908** within disposable housing assembly **804** to 2.00 mL. In some embodiments, the user may first depress a respective number of button assemblies, effectively reducing the capacity of reservoir **908**, and then fill reservoir **908**. Although a particular number of button assemblies are shown, representing the exemplary embodiment, in other embodiments, the number of button assemblies may vary from a minimum of 1 to as many as is desired. Additionally, although for descriptive purposes, and in the exemplary embodiment, each button assembly may displace 0.5 mL, in other embodiments, the volume of displacement per button may vary. Additionally, the reservoir may be, in various embodiments, include a larger or smaller volume than described in the exemplary embodiment.

(311) According to the above-described configuration, the button assemblies (e.g., button assemblies **1014**, **1016**, **1018**) may be employed, at least in part, to control the fill volume of reservoir **908**. By not depressing any of the button assemblies, the greatest fill volume of reservoir **908** may be achieved. Depressing one button assembly (e.g., button assembly **1014**) may allow the second greatest fill volume to be achieved. Depressing two button assemblies (e.g., button assemblies **1014**, **1016**) may achieve the third greatest fill volume. Depressing all three button assemblies (e.g., button assemblies **1014**, **1016**, **1018**) may allow the smallest fill volume to be achieved.

(312) Further, in an embodiment button assemblies **1014**, **1016**, **1018** may be utilized, at least in part, to facilitate filling of reservoir **908**. For example, once a filling needle (e.g., which may be fluidly coupled to a vial of infusible fluid) has been inserted into reservoir **908**, button assemblies **1014**, **1016**, **1018** may be depressed to pump at least a portion of any air that may be contained within reservoir into the vial of infusible fluid. Button assemblies **1014**, **1016**, **1018** may subsequently be released to allow infusible fluid to flow from the vial into reservoir **908**. Once reservoir **908** has been filled with the infusible fluid, one or more button assemblies (e.g., one or more of button assemblies **1014**, **1016**, **1018**) may be depressed, thereby squeezing at least a portion of the infusible fluid from reservoir **908** (e.g., via a needle used to fill reservoir **908** and back into the vial of infusible fluid). As discussed above, the volume of infusible fluid contained within reservoir **908** may be controlled, e.g., depending upon how many button assemblies are depressed (e.g., which may control how much infusible fluid is squeezed back into the vial of infusible fluid).

(313) With particular reference to FIGS. **62-64**, filling aid **1010** may be pivotally coupled to fill adapter base plate **1020**. For example, filling aid **1010** may include pivot members **1022**, **1024** that may be configured to be received in pivot supports **1026**, **1028**, thereby allowing filling aid to pivot between an open position (e.g., as shown in FIGS. **57-61**) and a closed position (e.g., as shown in FIGS. **63-64**). The closed position may be suitable, e.g., for packaging fill adapter **1000**, storage of fill adapter **1000**, or the like. In order to ensure that filling aid **1010** is properly oriented for filling reservoir **908**, fill adapter **1000** may include support member **1030**. To properly orient filling aid **1010**, a user may pivot filling aid **1010** to a fully open position, wherein filling aid **1010** may contact support member **1030**.

(314) According to an alternative embodiment, and referring also to FIG. **65**, fill adapter **1050** may be configured to releasably engage disposable housing assembly **804** via a plurality of locking tabs (e.g., locking tabs **1052**, **1054**). Additionally, fill adapter **1050** may include a plurality of button assemblies (e.g., button assemblies **1056**, **1058**, **1060**) that may interact with ribs **964**, **966**, **968** of disposable housing assembly **804** to adjust a fill volume of reservoir **908**. Fill adapter **1050** may further include filling aid **1062**, having guide passage **1064** configured to align a needle of a syringe with the septum of disposable housing **804**, e.g., for accessing reservoir **908** for the purpose of filling reservoir **908** with an infusible fluid. Filling aid **1062** may be connected to base plate **1066**, e.g., as an integral component therewith, by gluing, heat sealing, compression fit, or the like.

(315) Referring also to FIGS. **66-74**, vial fill adapter **1100** may be configured to facilitate filling reservoir **908** of disposable housing assembly **804** directly from a vial. Similar to fill adapter **1000**, vial fill adapter **1100** may include locking tabs **1102**, **1104**, **1106**, **1108** that may be configured to engage radial tabs **934**, **936**, **938**, **940** of disposable housing assembly in a manner generally similar to tabs **942**, **944**, **946**, **948** of locking ring assembly **806**. Accordingly, vial fill adapter **1100** may be releasably engaged with disposable housing assembly **804** by aligning vial fill adapter **1100** with disposable housing assembly **804** and rotating vial fill adapter **1100** and disposable housing assembly **804** relative to one another to releasably engage locking tabs **1102**, **1104**, **1106**, **1108** with radial tabs **934**, **936**, **938**, **940**.

(316) As discussed above, disposable housing assembly **804** may be configured to facilitate controlling the quantity of infusible fluid delivered to reservoir **908** during filling. For example, membrane assembly **902** of disposable housing assembly **804** may include ribs **964**, **966**, **968** that may be depressed and at least partially displaced into reservoir **908**, thereby reducing the volume of reservoir **908**. Accordingly, when infusible fluid is delivered to reservoir **908**, the volume of fluid that may be accommodated by reservoir **908** may be correspondingly reduced. Ribs **964**, **966**, **968** may be accessible via openings **958**, **960**, **962** in top portion **904** of disposable housing assembly **804**.

(317) Vial fill adapter **1100** may include one or more button assemblies (e.g., button assemblies **1110**, **1112**, **1114**) corresponding to ribs **964**, **966**, **968** (e.g., shown in FIG. **52A**). That is, when vial fill adapter **1100** is releasably engaged with disposable housing assembly **804**, buttons **1110**, **1112**, **1114** may be aligned with ribs **964**, **966**, **968**. Button assemblies **1110**, **1112**, **1114** may be, for example, cantilever members capable of being depressed. When vial fill adapter **1100** is releasably engaged with disposable housing assembly **804**, one or more of button assemblies **1110**, **1112**, **1114** may be depressed, and may correspondingly displace a respective one of ribs **964**, **966**, **968** into reservoir **908**, thereby reducing the volume of reservoir **908**.

(318) For example, assume for illustrative purposes that reservoir **908** has a maximum capacity of 3.00 mL. Further, assume that button assembly **1110** is configured to displace rib **964** into disposable housing assembly **804**, resulting in a 0.5 mL reduction in the 3.00 mL capacity of disposable housing assembly **804**. Further, assume that button assembly **1112** is configured to displace rib

966 into disposable housing assembly 804, also resulting in a 0.5 mL reduction in the 3.00 mL capacity of disposable housing assembly 804. Further, assume that button assembly 1114 is configured to displace rib 968 into disposable housing assembly 804, also resulting in a 0.50 mL reduction in the 3.00 mL capacity of disposable housing assembly 804. Therefore, if the user wishes to fill reservoir 908 within disposable housing assembly 804 with 2.00 mL of infusible fluid, the user may depress button assemblies 1112 and 1114 (resulting in the displacement of ribs 966 and 968 into disposable housing assembly 804), effectively reducing the 3.00 mL capacity of reservoir 908 within disposable housing assembly 804 to 2.0 mL.

(319) Vial fill adapter 1100 may further include vial filling aid assembly 1116 that may be configured to fluidly couple a vial of infusible fluid to reservoir 908 of disposable housing assembly 804 via a septum. With particular reference to FIG. 71, vial filling aid assembly may include double ended needle assembly 1118. Double ended needle assembly 1118 may include first needle end 1120 configured to penetrate the septum of a vial (not shown) and second needle end 1122 configured to penetrate the septum of disposable housing assembly 804. As such, the vial and reservoir 908 may be fluidly coupled allowing infusible fluid to be transferred from the vial to reservoir 908. Double ended needle assembly 1118 may include vial engagement portion 1124 adjacent first end 1120. Vial engagement arms 1124, 1126 may be configured to releasably engage, e.g., a vial cap, to assist in maintaining the fluid connection between double ended needle assembly 1118 and the vial. Additionally, double ended needle assembly 1118 may include body 1128 that may be slidably received in opening 1130 of vial filling aid body 1132. Vial filling aid body 1132 may include stabilizer arms 1134, 1136, e.g., which may be configured to stabilize the vial during filling of disposable housing assembly 804. In one embodiment, the vial may be engaged with double ended needle assembly 1118 e.g., such that first end 1120 may penetrate the septum of the vial and the cap of the vial may be engaged by engagement arms 1124, 1126. Body 1128 may be slidably inserted into opening 1130 such that second end 1122 of double ended needle assembly 1118 may penetrate the septum of disposable body assembly 804.

(320) Similar to fill adapter 1000, vial filling aid assembly 1116 may be configured to be pivotally coupled to vial fill adapter base plate 1138. For example, vial filling aid 1116 may include pivot members 1140, 1142 that may be configured to be received in pivot supports 1144, 1146 (e.g., shown in FIG. 71), thereby allowing vial filling aid 1116 to pivot between an open position (e.g., as shown in FIGS. 66-70) and a closed position (e.g., as shown in FIGS. 72-74). The closed position may be suitable, e.g., for packaging vial fill adapter 1100, storage of vial fill adapter 1100, or the like. In order to ensure that vial filling aid 1116 is properly oriented for filling reservoir 908, vial fill adapter 1100 may include support member 1148. To properly orient vial filling aid 1116, a user may pivot vial filling aid 1116 to a fully open position, wherein vial filling aid 1116 may contact support member 1148. Additionally, vial fill adapter base plate 1138 may include one or more locking features (e.g., locking tabs 1150, 1152) that may engage vial filling aid 1116, and may maintain vial filling aid 1116 in the closed position. Vial fill adapter base plate 1138 may also include features (e.g., tabs 1154, 1156) that may be configured to assist in retaining double ended needle assembly 1118, e.g., by preventing slidable separation of double ended needle assembly 1118 from vial filling aid body 1132.

(321) As shown in FIGS. 72-74, filling aid assembly 1116 is in a closed position. In this configuration, support member 1148 may additionally function as a needle guard. When removing filling aid assembly 1116 from disposable housing assembly 804, support member 1148 may function to safely allow a user to squeeze the ends and rotate filling aid assembly 1116 for removal. As shown in FIG. 70, in the open position, support member 1148 may function as a stop to maintain proper orientation.

(322) Referring again to FIGS. 57-73, the exemplary embodiments of the fill adapter include a grip feature (e.g., 1166 in FIG. 72). Grip feature 1166 may provide a grip interface for removal of the fill adapter from disposable housing assembly 804. Although shown in one configuration in these figures, in other embodiments, the configuration may vary. In still other embodiments, a grip feature may not be included.

(323) According to one embodiment, fill adapter base plate 1020 and vial fill adapter base plate 1138 may be interchangeable components. Accordingly, a single base plate (e.g., either fill adapter base plate 1020 or vial fill adapter base plate 1138) may be used with either filling aid 1010 or vial filling aid 1116. Accordingly, the number of distinct components that are required for both filling adapters may be reduced, and a user may have the ability to select the filling adapter that may be the most suitable for a given filling scenario.

(324) The various embodiments of the fill adapters may provide many safely benefits, including but not limited to: providing a system for filling the reservoir without handling a needle; protecting the reservoir from unintentional contact with the needle, i.e., destruction of the integrity of the reservoir through unintentional puncture; designed to be ambidextrous; in some embodiments, may provide a system for maintaining air in the reservoir.

(325) As discussed above, reusable housing assembly 802 may include battery 832, e.g., which may include a rechargeable battery. Referring also to FIGS. 75-80, battery charger 1200 may be configured to recharge battery 832. Battery charger 1200 may include housing 1202 having top plate 1204. Top plate 1204 may include one or more electrical contacts 1206, generally, configured to be electrically coupled to electrical contacts 834 of reusable housing assembly 802. Electrical contacts 1206 may include, but are not limited to, electrical contact pads, spring biased electrical contact members, or the like. Additionally, top plate 1204 may include alignment tabs 1208, 1210, which may be configured to mate with openings 836, 838 in base plate 818 of reusable housing assembly 802 (e.g., as shown in FIG. 35C). The cooperation of alignment tabs 1208, 1210 and openings 836, 838 may ensure that reusable housing assembly 802 is aligned with battery charger 1200 such that electrical contacts 1206 of battery charger 1200 may electrically couple with electrical contacts 834 of reusable housing assembly 802.

(326) With reference also to FIGS. 77 and 78, battery charger 1200 may be configured to releasably engage reusable housing assembly 802. For example, in a similar manner as disposable housing assembly 804, battery charger 1200 may include one or more locking tabs (e.g., locking tabs 1212, 1214 shown in FIG. 76). The locking tabs (e.g., locking tabs 1212, 1214) may be engaged by tabs 942, 944, 946, 948 of locking ring assembly 806. As such, reusable housing assembly 802 may be aligned with battery charger 1200 (via alignment tabs 1208, 1210) with locking ring 806 in a first, unlocked position, as shown in FIG. 77. Locking ring 806 may be rotated relative to battery charger 1200 in the direction of arrow 1216 to releasably engage tabs 942, 944, 946, 948 of locking ring 806 with the locking tabs (e.g., locking tabs 1212, 1214) of battery charger 1200, as shown in FIG. 78.

(327) In an embodiment, battery charger **1200** may include recessed region **1218**, e.g., which may, in the exemplary embodiments, provide clearance to accommodate reusable housing assembly **802** pumping and valving components. Referring also to FIGS. **79** & **80**, battery charger **1200** may provide electrical current to electrical contacts **1206** (and thereby to reusable housing assembly **802** via electrical contacts **834**) for recharging battery **832** of reusable housing assembly **802**. In some embodiments, when a signal indicative of a fully engaged reusable housing is not provided, current may not be provided to electrical contacts **1206**. According to such an embodiment, the risk associated with an electrical short circuit (e.g., resulting from foreign objects contacting electrical contacts **1206**) and damage to reusable housing assembly **802** (e.g., resulting from improper initial alignment between electrical contacts **1206** and electrical contacts **834**) may be reduced. Additionally, battery charger **1200** may not unnecessarily draw current when battery charger is not charging reusable housing assembly **802**.

(328) Still referring to FIGS. **79** and **80**, battery charger **1200** may include a lower housing portion **1224** and top plate **1204**. Printed circuit board **1222** (e.g., which may include electrical contacts **1206**) may be disposed within a cavity included between top plate **1204** and lower housing portion **1224**.

(329) Referring also to FIGS. **81-89B**, various embodiments of battery charger/docking stations are shown. FIGS. **81** and **82** depicts desktop charger **1250** including recess **1252** configured to mate with and recharge a reusable housing assembly (e.g., reusable housing assembly **802**). The reusable housing assembly may rest in recess **1252** and or may be releasably engaged in recess **1252**, in a similar manner as discussed above. Additionally, desktop charger **1250** may include recess **1254** configured to mate with a remote control assembly (e.g., remote control assembly **300**). Recess **1254** may include a USB plug **1256**, e.g., which may be configured to couple with the remote control assembly when the remote control assembly is disposed within recess **1254**. USB plug **1256** may allow for data transfer to/from the remote control assembly, as well as charging of remote control assembly. Desktop charger **1250** may also include USB port **1258** (e.g., which may include a mini-USB port), allowing desktop charger to receive power (e.g., for charging the reusable housing assembly and/or the remote control assembly). Additionally/alternatively USB port **1258** may be configured for data transfer to/from remote control assembly and/or reusable housing assembly, e.g., by connection to a computer (not shown).

(330) Referring to FIGS. **83A-83B**, similar to the previous embodiment, desktop charger **1260** may include recess **1262** for mating with a reusable housing assembly (e.g., reusable housing assembly **1264**). Desktop charger may also include recess **1266** configured to receive a remote control assembly (e.g., remote control assembly **1268**). One or more of recess **1262**, **1266** may include electrical and/or data connections configured to charge and/or transfer data to/from reusable housing assembly **1262** and/or remote control assembly **1268**, respectively.

(331) Referring to FIGS. **84A-84B**, another embodiment of a desktop charger is shown. Similar to desktop charger **1260**, desktop charger **1270** may include recesses (not shown) for respectively mating with reusable housing assembly **1272** and remote control assembly **1274**. As shown, desktop charger **1270** may hold reusable housing assembly **1272** and remote control assembly **1274** in a side-by-side configuration. Desktop charger **1270** may include various electrical and data connection configured to charge and/or transfer data to/from reusable housing assembly **1272** and/or remote control assembly **1274**, as described in various embodiments above.

(332) Referring to FIG. **85A-85D**, collapsible charger **1280** may include recess **1282** for receiving reusable housing assembly **1284** and remote control assembly **1286**. Collapsible charger **1280** may include various electrical and data connection configured to charge and/or transfer data to/from reusable housing assembly **1284** and/or remote control assembly **1286**, as described in various embodiments above. Additionally, as shown in FIGS. **85B-85D**, collapsible charger **1280** may include pivotable cover **1288**. Pivotable cover **1288** may be configured to pivot between an open position (e.g., as shown in FIG. **85B**), in which reusable housing assembly **1284** and remote control assembly **1286** may be docked in collapsible charger **1280**, and a closed position (e.g., as shown in FIG. **85D**), in which recess **1282** may be covered by pivotable cover **1288**. In the closed position, recess **1282**, as well as any electrical and/or data connections disposed therein, may be protected from damage.

(333) Referring to FIG. **86**, wall charger **1290** may include recess **1292** configured to receive reusable housing assembly **1294**. Additionally, wall charger **1290** may include recess **1296** configured to receive remote control assembly **1298**. Reusable housing assembly **1294** and remote control assembly **1298** may be positioned in a stacked configuration, e.g., thereby providing a relatively slim profile. A rear portion of wall charger **1290** may include an electrical plug, configured to allow wall charger to be plugged into an electrical receptacle. As such, wall charger **1290**, while plugged into the electrical receptacle, may achieve a wall mounted configuration. Additionally, while plugged into the electrical receptacle, wall charger **1290** may be provided with power for charging reusable housing assembly **1294** and/or remote control assembly **1298**.

(334) Referring to FIG. **87**, wall charger **1300** may include recess **1302** configured to receive remote control assembly **1304**. Additionally, wall charger may include a recess (not shown) configured to receive reusable housing assembly **1306**. Wall charger **1300** may be configured to position remote control assembly **1304** and reusable housing assembly **1306** in a back-to-back configuration, which may provide a relatively thin profile. Additionally, wall charger **1300** may include an electrical plug **1308** configured to be plugged into an electrical receptacle. Electrical plug **1308** may include a stowable configuration, in which electrical plug **1308** may be pivotable between a deployed position (e.g., as shown), and a stowed position. In the deployed position, electrical plug **1308** may be oriented to be plugged into an electrical receptacle. In the stowed position electrical plug **1308** may be disposed within recess **1310**, which may protect electrical plug **1308** from damage and/or from damaging other items.

(335) Referring to FIG. **88**, charger **1320** may include recess **1322** configured to receive reusable housing assembly **1324**. Charger **1320** may additionally include a recess (not shown) configured to receive remote control assembly **1326**. Charger **1320** may additionally include cover **1328**. Cover **1328** may be configured to pivot between an open position (as shown) and a closed position. When cover **1328** is in the open position, reusable housing assembly **1324** and remote control assembly **1326** may be accessible (e.g., allowing a user to remove/install reusable housing assembly **1324** and/or remote control assembly **1326** from/into charger **1320**. When cover **1324** is in the closed position, cover **1328** and charger body **1330** may substantially enclose reusable housing assembly **1324** and/or remote control assembly **1326** and/or recess **1322** and the recess configured to receive remote

control assembly **1326**, thereby providing damage and/or tamper protection for reusable housing assembly **1324**, remote control assembly **1326** and/or any electrical and/or data connection associated with charger **1320**.

(336) Referring to FIGS. **89A-89B**, wall charger **1350** may include recess **1352** configured to receive remote control assembly **1354**. Wall charger **1350** may also include recess **1356** configured to receive reusable housing assembly **1358**. Wall charger **1350** may be configured to position remote control assembly **1354** and reusable housing assembly **1358** in a generally side-by-side configuration, thereby providing a relatively slim profile. Charger **1350** may additionally include electrical plug **1360**, e.g., which may be configured to be plugged into an electrical receptacle. Electrical plug **1360** may include a stowable configuration, in which electrical plug **1360** may be pivotable between a deployed position (e.g., as shown), and a stowed position. In the deployed position, electrical plug **1360** may be oriented to be plugged into an electrical receptacle. In the stowed position electrical plug **1360** may be disposed within recess **1362**, which may protect electrical plug **1308** from damage and/or from damaging other items.

(337) Infusion pump therapy may include volume and time specifications. The amount of fluid dispensed together with the dispense timing may be two critical factors of infusion pump therapy. As discussed in detail below, the infusion pump apparatus and systems described herein may provide for a method of dispensing fluid together with a device, system and method for measuring the amount of fluid dispensed. However, in a circumstance where the calibration and precision of the measurement device calibration is critical, there may be advantages to determining any compromise in the precision of the measurement device as soon as possible. Thus, there are advantages to off-board verification of volume and pumping.

(338) As discussed above, infusion pump assembly **100** may include volume sensor assembly **148** configured to monitor the amount of fluid infused by infusion pump assembly **100**. Further and as discussed above, infusion pump assembly **100** may be configured so that the volume measurements produced by volume sensor assembly **148** may be used to control, through a feedback loop, the amount of infusible fluid that is infused into the user.

(339) Referring also to FIGS. **90A-90C**, there is shown one diagrammatic view and two cross-sectional views of volume sensor assembly **148**. Referring also to FIGS. **91A-91I**, there is shown various isometric and diagrammatic views of volume sensor assembly **148** (which is shown to include upper housing **1400**). Referring also to FIGS. **92A-92I**, there is shown various isometric and diagrammatic views of volume sensor assembly **148** (with upper housing **1400** removed), exposing speaker assembly **622**, reference microphone **626**, and printed circuit board assembly **830**. Referring also to FIGS. **93A-93I**, there is shown various isometric and diagrammatic views of volume sensor assembly **148** (with printed circuit board assembly **830** removed), exposing port assembly **624**. Referring also to FIGS. **94A-94F**, there is shown various isometric and diagrammatic cross-sectional views of volume sensor assembly **148** (with printed circuit board assembly **830** removed), exposing port assembly **624**. Referring also to FIG. **95**, there are shown an exploded view of volume sensor assembly **148**, exposing upper housing **1400**, speaker assembly **622**, reference microphone **626**, seal assembly **1404**, lower housing **1402**, port assembly **624**, spring diaphragm **628**, and retaining ring assembly **1406**.

(340) The following discussion concerns the design and operation of volume sensor assembly **148** (which is shown in a simplified form in FIG. **96**). For the following discussion, the following nomenclature may be used:

(341) TABLE-US-00009 Symbols P Pressure p Pressure Perturbation V Volume v Volume Perturbation γ Specific Heat Ratio R Gas Constant ρ Density Z Impedance f Flow friction A Cross sectional Area L Length ω Frequency ξ Damping ratio α Volume Ratio Subscripts 0 Speaker Volume 1 Reference Volume 2 Variable Volume k Speaker r Resonant Port z Zero p Pole Derivation of the Equations for Volume Sensor Assembly **148**:

Modeling the Acoustic Volumes

(342) The pressure and volume of an ideal adiabatic gas may be related by:

$PV_{\text{sup}}\gamma = K$ [EQ #1] where K is a constant defined by the initial conditions of the system.

(343) EQ #1 may be written in terms of a mean pressure, P, and volume, V, and a small time-dependent perturbation on top of those pressures, p(t), v(t) as follows:

$(P + p(t))(V + v(t))_{\text{sup}}\gamma = K$ [EQ #2]

(344) Differentiating this equation may result in:

$\{ \dot{p} \over (P + p(t)) \} (V + v(t))_{\text{sup}}\gamma + \gamma (V + v(t))_{\text{sup}}\gamma - 1 (P + p(t)) \{ \dot{v} \over (V + v(t)) \} (t) = 0$ [EQ #3] which may simplify to:

(345) $\dot{p}(t) + \frac{P + p(t)}{V + v(t)} \dot{v}(t) = 0$ [EQ#4]

(346) If the acoustic pressure levels are much less than the ambient pressure, the equation may be further simplified to:

(347) $\dot{p}(t) + \frac{P}{V} \dot{v}(t) = 0$ [EQ#5]

(348) How good is this assumption? Using the adiabatic relation it may be shown that:

(349) $\frac{P}{V} = \left(\frac{P + p(t)}{V + v(t)} \right) \left(\frac{P + p(t)}{P} \right)^{\frac{1}{\gamma} + 1}$ [EQ#6]

(350) Accordingly, the error in the assumption would be:

(351) $\text{error} = 1 - \left(\frac{P + p(t)}{P} \right)^{\frac{1}{\gamma} + 1}$ [EQ#7]

(352) A very loud acoustic signal (120 dB) may correspond to pressure sine wave with amplitude of roughly 20 Pascal. Assuming air at atmospheric conditions ($\gamma=1.4$, $P=101325$ Pa), the resulting error is 0.03%. The conversion from dB to Pa is as follows:

(353) $= 20 \log_{10} \left(\frac{P_{\text{rms}}}{P_{\text{ref}}} \right)$ or $P_{\text{rms}} = P_{\text{ref}} 10^{\frac{\text{dB}}{20}}$ [EQ#8] where $p_{\text{sub.ref}}=20 \text{ Math.}\mu\text{Pa}$.

(354) Applying the ideal gas law, $P=\rho RT$, and substituting in for pressure may result in the following:

(355) $\dot{p}(t) + \frac{RT}{V} \dot{v}(t) = 0$ [EQ#9]

(356) EQ #9 may be written in terms of the speed of sound, $a=\sqrt{\gamma RT}$ as follows:

(357) $p(t) + \frac{a^2}{V} v(t) = 0$ [EQ#10]

(358) Acoustic impedance for a volume may be defined as follows:

$$(359) \quad Z_v = \frac{p(t)}{v(t)} = -\frac{1}{(-\frac{1}{a})s} \quad [\text{EQ\#11}]$$

Modeling the Acoustic Port

(360) The acoustic port may be modeled assuming that all of the fluid in the port essentially moves as a rigid cylinder reciprocating in the axial direction. All of the fluid in the channel is assumed to travel at the same velocity, the channel is assumed to be of constant cross section, and the “end effects” resulting from the fluid entering and leaving the channel are neglected.

(361) If we assume laminar flow friction of the form $\Delta p = f \rho \{ \dot{v} \}$, the friction force acting on the mass of fluid in the channel may be written as follows:

$$F = f \rho A \cdot 2 \{ \dot{x} \} \quad [\text{EQ \#12}]$$

(362) A second order differential equation may then be written for the dynamics of the fluid in the channel:

$$\mu L A \{ \ddot{x} \} = \Delta p A - f \rho A \cdot 2 \{ \dot{x} \} \quad [\text{EQ \#13}] \text{ or, in terms of volume flow rate:}$$

$$(363) \quad \overset{\text{Math.}}{\dot{V}} = -\frac{fA}{L} \dot{V} + p \frac{A}{L} \quad [\text{EQ\#14}]$$

(364) The acoustic impedance of the channel may then be written as follows:

$$(365) \quad 0 \quad Z_p = \frac{p}{v} = \frac{L}{A} (s + \frac{fA}{L}) \quad [\text{EQ\#15}]$$

System Transfer Functions

(366) Using the volume and port dynamics defined above, volume sensor assembly **148** may be described by the following system of equations: (k=speaker, r=resonator)

$$\dot{p}_0 - \frac{a^2}{V_0} \dot{v}_k = 0 \quad [\text{EQ\#16}]$$

$$(367) \quad \dot{p}_1 + \frac{a^2}{V_1} (\dot{v}_k - \dot{v}_r) = 0 \quad [\text{EQ\#17}]$$

$$\dot{p}_2 + \frac{a^2}{V_2} \dot{v}_r = 0 \quad [\text{EQ\#18}]$$

$$\overset{\text{Math.}}{\dot{V}}_r = -\frac{fA}{L} \dot{V}_r + \frac{A}{L} (p_2 - p_1) \quad [\text{EQ\#19}]$$

(368) One equation may be eliminated if p.sub.0 is treated as the input substituting in

$$(369) \quad \dot{v}_k = \frac{V_0}{a^2} \dot{p}_0.$$

$$\dot{p}_1 + \frac{V_0}{V_1} \dot{p}_0 - \frac{a^2}{V_1} \dot{v}_r = 0 \quad [\text{EQ\#20}]$$

$$(370) \quad \dot{p}_2 + \frac{a^2}{V_2} \dot{v}_r = 0 \quad [\text{EQ\#21}]$$

$$\dot{v}_r = -\frac{fA}{L} \dot{V}_r + \frac{A}{L} p_2 - \frac{A}{L} p_1 \quad [\text{EQ\#22}]$$

Cross System Transfer Function

(371) The relationship between the speaker volume and the variable volume may be referred to as the Cross System transfer function. This transfer function may be derived from the above equations and is as follows:

$$(372) \quad \frac{p_2}{p_0} = \frac{V_0}{V_1 s^2 + 2 \frac{a^2}{V_1} s + \frac{a^2}{V_1}} \text{ where} \quad [\text{EQ\#23}]$$

$$\frac{a^2}{V_1} = \frac{a^2 A}{L V_1}, \quad \frac{a^2}{V_2} = \frac{fA}{L} \quad \text{and} \quad \frac{V_0}{V_1} = (1 + \frac{V_2}{V_1}) \quad [\text{EQ\#24}]$$

(373) Referring also to FIG. 97, a bode plot of EQ #23 is shown.

(374) The difficulty of this relationship is that the complex poles depend on both the variable volume, V.sub.2, and the reference volume, V.sub.1. Any change in the mean position of the speaker may result in an error in the estimated volume.

(375) Cross Port Transfer Function

(376) The relationship between the two volumes on each side of the acoustic port may be referred to as the Cross Port transfer function. This relationship is as follows:

$$(377) \quad \frac{p_2}{p_1} = \frac{\frac{a^2}{V_1} s^2 + 2 \frac{a^2}{V_1} s + \frac{a^2}{V_1}}{s^2 + 2 \frac{a^2}{V_1} s + \frac{a^2}{V_1}} \quad [\text{EQ\#25}] \text{ which is shown graphically in FIG. 98.}$$

(378) This relationship has the advantage that the poles are only dependent on the variable volume and not on the reference volume. It does, however, have the difficulty that the resonant peak is actually due to the inversion of the zero in the response of the reference volume pressure. Accordingly, the pressure measurement in the reference chamber will have a low amplitude in the vicinity of the resonance, potentially increasing the noise in the measurement.

(379) Cross Speaker Transfer Function

(380) The pressures may also be measured on each side of the speaker. This is referred to as the cross speaker transfer function:

$$(381) \quad \frac{p_1}{p_0} = \frac{V_0}{V_1} \frac{s^2 + 2 \zeta \omega_n s + \omega_n^2}{s^2 + 2 \zeta \omega_n s + \omega_n^2} \quad [\text{EQ\#26}] \text{ which is shown graphically in FIG. 99.}$$

(382) This transfer function has a set of complex zeros in addition to the set of complex poles.

(383) Looking at the limits of this transfer function: as

$$(384) \quad s \rightarrow 0, \frac{p_1}{p_0} \rightarrow \frac{V_0}{V_1 + V_2};$$

and as

$$(385) \quad s \rightarrow \infty, \frac{p_1}{p_0} \rightarrow \frac{V_0}{V_1}.$$

Resonance Q Factor and Peak Response

(386) The quality of the resonance is the ratio of the energy stored to the power loss multiplied by the resonant frequency. For a pure second-order system, the quality factor may be expressed as a function of the damping ratio:

$$(387) \quad Q = \frac{1}{2\zeta} \quad [\text{EQ\#27}]$$

(388) The ratio of the peak response to the low-frequency response may also be written as a function of the damping ratio:

$$(389) \quad 0 \leq |G|_d = \frac{1}{\sqrt{5-4}} \quad [\text{EQ\#28}]$$

(390) This may occur at the damped natural frequency:

$$\omega_{\text{sub.d}} = \omega_{\text{sub.n}} \sqrt{1-\zeta^2} \quad [\text{EQ \#29}]$$

Volume Estimation

Volume Estimation Using Cross-Port Phase

(391) The variable volume (i.e., within volume sensor chamber **620**) may also be estimated using the cross-port phase. The transfer function for the pressure ratio across the resonant port may be as follows:

$$(392) \quad \frac{p_2}{p_1} = \frac{\frac{2}{s^2 + bs + \frac{2}{n}}}{\frac{2}{n}} \quad [\text{EQ\#30}]$$

(393) At the 90° phase point, $\omega = \omega_{\text{sub.n}}$; where

$$(394) \quad \frac{2}{n} = \frac{1}{V_2} \frac{a^2 A}{L}$$

(395) The resonant frequency may be found on the physical system using a number of methods. A phase-lock loop may be employed to find the 90° phase point—this frequency may correspond to the natural frequency of the system. Alternatively, the resonant frequency may be calculated using the phase at any two frequencies:

(396) The phase, ϕ , at any given frequency will satisfy the following relation:

$$(397) \quad \tan \phi = \frac{b}{\frac{2}{n}} \text{ where } b = \frac{fA}{L} \quad [\text{EQ\#31}]$$

(398) Solving for $V_{\text{sub.2}}$ results in:

$$(399) \quad V_2 = \frac{\frac{a^2 A}{L}}{-f \cot \phi} \quad [\text{EQ\#32}]$$

(400) Accordingly, the ratio of the phases at two different frequencies $\omega_{\text{sub.1}}$ and $\omega_{\text{sub.2}}$ can be used to compute the natural frequency of the system:

$$(401) \quad \frac{2}{n} = \frac{1}{2} \frac{\left(\frac{\tan \phi_1}{\tan \phi_2} - \frac{2}{1} \right)}{\left(\frac{\tan \phi_1}{\tan \phi_2} - \frac{1}{1} \right)} \quad [\text{EQ\#33}]$$

(402) For computational efficiency, the actual phase does not need to be calculated. All that is needed is the ratio of the real and imaginary parts of the response ($\tan \phi$).

(403) Re-writing EQ #33 in terms of the variable volume results in:

$$(404) \quad \frac{1}{V_2} = \frac{1}{a^2 A} \frac{1}{2} \frac{\left(\frac{\tan \phi_1}{\tan \phi_2} - \frac{2}{1} \right)}{\left(\frac{\tan \phi_1}{\tan \phi_2} - \frac{1}{1} \right)} \quad [\text{EQ\#34}]$$

Volume Estimation Using Swept Sine

(405) The resonant frequency of the system may be estimated using swept-sine system identification. In this method, the response of the system to a sinusoidal pressure variation may be found at a number of different frequencies. This frequency response data may then be used to estimate the system transfer function using linear regression.

(406) The transfer function for the system may be expressed as a rational function of s . The general case is expressed below for a transfer function with an n .sup.th order numerator and an m .sup.th order denominator. N and D are the coefficients for the numerator and denominator respectively. The equation has been normalized such that the leading coefficient in the denominator is 1.

$$G(s) = \frac{N_n s^n + N_{n-1} s^{n-1} + \dots + N_0}{s^m + D_{m-1} s^{m-1} + D_{m-2} s^{m-2} + \dots + D_0} \quad [\text{EQ\#35}]$$

$$(407) \quad G(s) = \frac{\sum_{k=0}^n \text{Math. } N_k s^k}{s^m + \sum_{k=0}^{m-1} \text{Math. } D_k s^k} \quad [\text{EQ\#36}]$$

(408) This equation may be re-written as follows:

$$(409) \quad G s^m = \sum_{k=0}^n \text{Math. } N_k s^k - G \sum_{k=0}^{m-1} \text{Math. } D_k s^k \quad [\text{EQ\#37}]$$

(410) Representing this summation in matrix notation resulting in the following:

$$(411) \quad \begin{bmatrix} G_1 s_1^m & s_1^n & \text{Math.} & s_1^0 & -G_1 s_1^{m-1} & \text{Math.} & -G_1 s_1^0 \\ \text{Math.} & & & & & & \end{bmatrix} = \begin{bmatrix} \text{Math.} & & & & & & \\ \text{Math.} & & & & & & \\ \text{Math.} & & & & & & \\ \text{Math.} & & & & & & \\ \text{Math.} & & & & & & \\ \text{Math.} & & & & & & \\ \text{Math.} & & & & & & \end{bmatrix} \begin{bmatrix} N_n \\ N_0 \\ D_{m-1} \\ D_0 \end{bmatrix} \quad [\text{EQ\#38}] \quad \text{where } k \text{ is the number of data points}$$

points collected in the swept sine. To simplify the notation, this equation may be summarized using the vectors:

$y = Xc$ [EQ #39] where y is k by 1, x is k by $(m+n-1)$ and c is $(m+n-1)$ by 1. The coefficients may then be found using a least square approach. The error function may be written as follows:

$$e = y - Xc \quad [\text{EQ \#40}]$$

(412) The function to be minimized is the weighted square of the error function; W is a $k \times k$ diagonal matrix.

$$e_{\text{sup.TW}} = (y - Xc)_{\text{sup.TW}} (y - Xc) \quad [\text{EQ \#41}]$$

$$e_{\text{sup.TW}} = y_{\text{sup.TW}} y - (y_{\text{sup.TW}} Xc)_{\text{sup.T}} - y_{\text{sup.TW}} Xc + c_{\text{sup.Tx}}_{\text{sup.TW}} Xc \quad [\text{EQ \#42}]$$

(413) As the center two terms are scalars, the transpose may be neglected.

$$e^T W e = y^T W y - 2y^T W X c + c^T X^T W X c \quad [\text{EQ\#43}]$$

$$(414) \quad 0 \quad \frac{\partial e^T W e}{\partial c} = -2X^T W y + 2X^T W X c = 0 \quad [\text{EQ\#44}]$$

$$c = (X^T W X)^{-1} X^T W y \quad [\text{EQ\#45}]$$

(415) It may be necessary to use the complex transpose in all of these cases. This approach may result in complex coefficients, but the process may be modified to ensure that all the coefficients are real. The least-square minimization may be modified to give only real coefficients if the error function is changed to be

$$e.\text{sup.}TW e = \text{Re}(y - Xc).\text{sup.}TW \text{Re}(y - Xc) + \text{Im}(y - Xc).\text{sup.}TW \text{Im}(y - Xc) \quad [\text{EQ \#46}]$$

(416) Accordingly, the coefficients may be found with the relation:

$$c = (\text{Re}(X).\text{sup.}TW \text{Re}(X) + \text{Im}(X).\text{sup.}TW \text{Im}(X))(\text{Re}(X).\text{sup.}TW \text{Re}(y) + \text{Im}(X).\text{sup.}TW \text{Im}(y)) \quad [\text{EQ \#47}]$$

Solution for a 2nd Order System

(417) For a system with a 0.sup.th order numerator and a second order denominator as shown in the transfer function:

$$(418) \quad G(s) = \frac{N_0}{s^2 + D_1 s + D_0} \quad [\text{EQ\#48}]$$

(419) The coefficients in this transfer function may be found based on the expression found in the previous section:

$$c = (\text{Re}(X).\text{sup.}TW \text{Re}(X) + \text{Im}(X).\text{sup.}TW \text{Im}(X))(\text{Re}(X).\text{sup.}TW \text{Re}(y) + \text{Im}(X).\text{sup.}TW \text{Im}(y)) \quad [\text{EQ \#49}] \text{ where:}$$

$$(420) \quad y = \begin{bmatrix} G_1 s_1^2 \\ G_k s_k^2 \end{bmatrix}, X = \begin{bmatrix} 1 & -G_1 s_1 & -G_1 \\ 1 & -G_k s_k & -G_k \end{bmatrix}, \text{ and } c = \begin{bmatrix} N_0 \\ D_1 \\ D_0 \end{bmatrix} \quad [\text{EQ\#50}]$$

(421) To simplify the algorithm, we may combine some of terms:

$$c = D.\text{sup.}TW y \quad [\text{EQ \#51}]$$

where:

$$D = \text{Re}(X).\text{sup.}TW \text{Re}(X) + \text{Im}(X).\text{sup.}TW \text{Im}(X) \quad [\text{EQ \#52}]$$

$$b = \text{Re}(X).\text{sup.}TW \text{Re}(y) + \text{Im}(X).\text{sup.}TW \text{Im}(y) \quad [\text{EQ \#53}]$$

(422) To find an expression for D in terms of the complex response vector G and the natural frequency $s = j\omega$, X may be split into its real and imaginary parts:

$$(423) \quad \text{Re}(X) = \begin{bmatrix} 1 & \text{Im}(G_1) & -\text{Re}(G_1) \\ \vdots & \vdots & \vdots \\ 1 & \text{Im}(G_k) & -\text{Re}(G_k) \end{bmatrix}, \text{Im}(X) = \begin{bmatrix} 0 & -\text{Re}(G_1) & -\text{Im}(G_1) \\ \vdots & \vdots & \vdots \\ 0 & -\text{Re}(G_k) & -\text{Im}(G_k) \end{bmatrix} \quad [\text{EQ\#54}]$$

(424) The real and imaginary portions of the expression for D above may then become

$$\text{Re}(X)^T W \text{Re}(X) = \begin{bmatrix} \sum_{i=1}^k w_i \text{Im}(G_i) & \sum_{i=1}^k w_i \text{Im}(G_i) \text{Im}(G_i) & -\sum_{i=1}^k w_i \text{Re}(G_i) \\ \sum_{i=1}^k w_i \text{Im}(G_i) \text{Im}(G_i) & \sum_{i=1}^k w_i \text{Im}(G_i)^2 & -\sum_{i=1}^k w_i \text{Im}(G_i) \text{Re}(G_i) \\ -\sum_{i=1}^k w_i \text{Re}(G_i) & -\sum_{i=1}^k w_i \text{Im}(G_i) \text{Re}(G_i) & \sum_{i=1}^k w_i \text{Re}(G_i)^2 \end{bmatrix} \quad [\text{EQ\#55}]$$

$$(425) \quad \text{Im}(X)^T W \text{Im}(X) = \begin{bmatrix} 0 & 0 & 0 \\ 0 & \sum_{i=1}^k w_i \text{Re}(G_i)^2 & \sum_{i=1}^k w_i \text{Im}(G_i) \text{Re}(G_i) \\ 0 & \sum_{i=1}^k w_i \text{Im}(G_i) \text{Re}(G_i) & \sum_{i=1}^k w_i \text{Im}(G_i)^2 \end{bmatrix} \quad [\text{EQ\#56}]$$

(426) Combining these terms results in the final expression for the D matrix, which may contain only real values.

$$(427) \quad D = \begin{bmatrix} \sum_{i=1}^k w_i \text{Im}(G_i) & \sum_{i=1}^k w_i \text{Im}(G_i) \text{Im}(G_i) & -\sum_{i=1}^k w_i \text{Re}(G_i) \\ \sum_{i=1}^k w_i \text{Im}(G_i) \text{Im}(G_i) & \sum_{i=1}^k w_i (\text{Re}(G_i)^2 + \text{Im}(G_i)^2) & 0 \\ -\sum_{i=1}^k w_i \text{Re}(G_i) & 0 & \sum_{i=1}^k w_i (\text{Re}(G_i)^2 + \text{Im}(G_i)^2) \end{bmatrix} \quad [\text{EQ\#57}]$$

(428) The same approach may be taken to find an expression for the b vector in terms of G and co. The real and imaginary parts of y are as follows:

$$(429) \quad \text{Re}(y) = \begin{bmatrix} -\text{Re}(G_1) \\ \vdots \\ -\text{Re}(G_k) \end{bmatrix}, \text{Im}(y) = \begin{bmatrix} -\text{Im}(G_1) \\ \vdots \\ -\text{Im}(G_k) \end{bmatrix} \quad [\text{EQ\#58}]$$

(430) Combining the real and imaginary parts results in the expression for the b vector as follows:

$$(431) \quad b = \text{Re}(X)^T W \text{Re}(y) + \text{Im}(X)^T W \text{Im}(y) = \begin{bmatrix} -\sum_{i=1}^k \text{Math. } w_i \text{Re}(G_i)^2 \\ 0 \end{bmatrix} \quad [\text{EQ\#59}]$$

(432) The next step is to invert the D matrix. The matrix is symmetric and positive-definite so the number of computations needed to find the inverse will be reduced from the general 3×3 case. The general expression for a matrix inverse is:

$$(433) \quad D^{-1} = \frac{1}{\det(D)} \text{adj}(D) \quad [\text{EQ\#60}]$$

(434) If D is expressed as follows:

$$(435) \quad D = \begin{bmatrix} d_{11} & d_{12} & d_{13} \\ d_{12} & d_{22} & 0 \\ d_{13} & 0 & d_{33} \end{bmatrix} \quad [\text{EQ\#61}] \quad \text{then the adjugate matrix may be written as follows:}$$

(436) 0

$$\text{adj}(D) = \begin{bmatrix} \text{Math. } d_{22} & 0 & \text{Math. } -d_{12} & 0 & \text{Math. } d_{12} & d_{22} & \text{Math. } \\ 0 & d_{33} & d_{13} & d_{33} & d_{13} & 0 & \\ -\text{Math. } d_{12} & d_{13} & \text{Math. } d_{11} & d_{13} & \text{Math. } -d_{11} & d_{12} & \text{Math. } \\ 0 & d_{33} & d_{13} & d_{33} & d_{13} & 0 & \\ \text{Math. } d_{12} & d_{13} & \text{Math. } -d_{11} & d_{13} & \text{Math. } d_{11} & d_{12} & \text{Math. } \\ d_{22} & 0 & d_{12} & 0 & d_{12} & d_{22} & \end{bmatrix} = \begin{bmatrix} a_{11} & a_{12} & a_{13} \\ a_{12} & a_{22} & a_{23} \\ a_{13} & a_{32} & a_{33} \end{bmatrix} \quad [\text{EQ\#62}]$$

(437) Due to symmetry, only the upper diagonal matrix may need to be calculated.

(438) The Determinant may then be computed in terms of the adjugate matrix values, taking advantage of the zero elements in the original array:

$$\det(D) = a_{11}d_{22}d_{33} + a_{12}d_{23}d_{31} + a_{13}d_{21}d_{32} \quad [\text{EQ \#63}]$$

(439) Finally, the inverse of D may be written as follows:

$$(440) \quad D^{-1} = \frac{1}{\det(D)} \text{adj}(D) \quad [\text{EQ\#64}]$$

(441) Since we are trying to solve:

$$c = D^{-1} b = \frac{1}{\det(D)} \text{adj}(D) b \quad [\text{EQ\#65}]$$

then:

$$(442) \quad c = \frac{1}{\det(D)} \begin{bmatrix} a_{11} & a_{12} & a_{13} \\ a_{12} & a_{22} & a_{23} \\ a_{13} & a_{32} & a_{33} \end{bmatrix} \begin{bmatrix} b_1 \\ 0 \\ b_3 \end{bmatrix} = \frac{1}{\det(D)} \begin{bmatrix} a_{11}b_1 + a_{13}b_3 \\ a_{12}b_1 + a_{23}b_3 \\ a_{13}b_1 + a_{33}b_3 \end{bmatrix} \quad [\text{EQ\#66}]$$

(443) The final step is to get a quantitative assessment of how well the data fits the model. Accordingly, the original expression for the error is as follows:

$$e_{\text{sup}} = \text{Re}(y - Xc)_{\text{sup}} + \text{Im}(y - Xc)_{\text{sup}} \quad [\text{EQ \#67}]$$

(444) This may be expressed in terms of the D matrix and the b and c vectors as follows:

$$e^T W e = h - 2c^T b + c^T D c \quad [\text{EQ\#68}]$$

where

$$(445) \quad h = \text{Re}(y^T) W \text{Re}(y) + \text{Im}(y^T) W \text{Im}(y) \quad [\text{EQ\#69}]$$

$$h = \sum_{i=1}^k \text{Math. } w_i (\text{Re}(G_i)^2 + \text{Im}(G_i)^2) \quad [\text{EQ\#70}]$$

(446) The model fit error may also be used to detect sensor failures.

(447) Alternate Solution for a 2nd Order System

$$G(s) = \frac{N_n s^n + N_{n-1} s^{n-1} + \text{Math. } + N_0}{s^m + D_{m-1} s^{m-1} + D_{m-2} s^{m-2} + \text{Math. } + D_0} \quad \text{or} \quad [\text{EQ\#71}]$$

$$(448) \quad G(s) = \frac{\sum_{k=0}^n \text{Math. } N_k s^k}{s^m + \sum_{k=0}^{m-1} \text{Math. } D_k s^k} \quad [\text{EQ\#72}]$$

(449) This equation may be re-written as follows:

$$(450) \quad G = \sum_{k=0}^n \text{Math. } N_k s^{k-m} - G \sum_{k=0}^{m-1} \text{Math. } D_k s^{k-m} \quad [\text{EQ\#73}]$$

(451) Putting this summation into matrix notation results in the following:

$$(452) \quad \begin{bmatrix} G_1 & s_1^n & \text{.Math.} & s_1^{-m} & -G_1 s_1^{-1} & \text{.Math.} & -G_1 s_1^{-m} & \text{.Math.} \\ \text{.Math.} & & & \text{.Math.} & \text{.Math.} & & \text{.Math.} & \end{bmatrix} \begin{bmatrix} N_n \\ N_0 \\ D_{m-1} \\ D_0 \end{bmatrix} \quad [\text{EQ\#74}]$$

(453) For a system with a 0.sup.th order numerator and a second order denominator as shown in the transfer function:

$$(454) \quad G(s) = \frac{N_0}{s^2 + D_1 s + D_0} \quad [\text{EQ\#75}]$$

(455) The coefficients in this transfer function may be found based on the expression found in the previous section:

$$c = (\text{Re}(X)^T W \text{Re}(X) + \text{Im}(X)^T W \text{Im}(X))^{-1} (\text{Re}(X)^T W \text{Re}(y) + \text{Im}(X)^T W \text{Im}(y)) \quad [\text{EQ\#76}]$$

(456) where

$$y = \begin{bmatrix} G_1 & s_1^{-2} & -G_1 s_1^{-1} & -G_1 s_1^{-2} \\ \text{.Math.} & \text{.Math.} & \text{.Math.} & \text{.Math.} \end{bmatrix}, \text{ and } c = \begin{bmatrix} N_0 \\ D_1 \\ D_0 \end{bmatrix} \quad [\text{EQ\#77}]$$

(457) To simplify the algorithm, some terms may be combined:

$$c = D \cdot \text{sup.} - 1b \quad [\text{EQ \#78}]$$

where:

$$D = \text{Re}(X) \cdot \text{sup.} T W \text{Re}(X) + \text{Im}(X) \cdot \text{sup.} T W \text{Im}(X) \quad [\text{EQ \#79}]$$

$$b = \text{Re}(X) \cdot \text{sup.} T W \text{Re}(y) + \text{Im}(X) \cdot \text{sup.} T W \text{Im}(y) \quad [\text{EQ \#80}]$$

(458) To find an expression for D in terms of the complex response vector G and the natural frequency $s = j\omega$, split X may be split into its real and imaginary parts:

$$\text{Re}(X) = \begin{bmatrix} -\frac{1}{s_1^2} & -w_1^{-1} \text{Im}(G_1) & \frac{1}{s_1^2} \text{Re}(G_1) \\ \text{.Math.} & \text{.Math.} & \text{.Math.} \end{bmatrix} \quad [\text{EQ\#81}]$$

$$(459) \quad \text{Im}(X) = \begin{bmatrix} -\frac{1}{s_k^2} & -\frac{1}{s_k} \text{Im}(G_k) & \frac{1}{s_k^2} \text{Re}(G_k) \\ \text{.Math.} & \text{.Math.} & \text{.Math.} \\ 0 & -\frac{1}{s_1} \text{Re}(G_1) & \frac{1}{s_1^2} \text{Im}(G_1) \\ \text{.Math.} & \text{.Math.} & \text{.Math.} \\ 0 & -\frac{1}{s_k} \text{Re}(G_k) & \frac{1}{s_k^2} \text{Im}(G_k) \end{bmatrix} \quad [\text{EQ\#82}]$$

(460) The real and imaginary portions of the expression for D above may then become:

$$(461) \quad \begin{aligned} \text{Re}(X)^T W \text{Re}(X) &= \begin{bmatrix} \sum_{i=1}^k w_i^{-4} & \sum_{i=1}^k w_i \text{Im}(G_i)^{-3} & -\sum_{i=1}^k w_i \text{Re}(G_i)^{-4} \\ \sum_{i=1}^k w_i \text{Im}(G_i)^{-3} & \sum_{i=1}^k w_i \text{Im}(G_i)^2 i^{-2} & -\sum_{i=1}^k w_i \text{Im}(G_i) \text{Re}(G_i)^{-3} \\ -\sum_{i=1}^k w_i \text{Re}(G_i)^{-4} & -\sum_{i=1}^k w_i \text{Im}(G_i) \text{Re}(G_i)^{-3} & \sum_{i=1}^k w_i \text{Re}(G_i)^2 i^{-4} \end{bmatrix} \quad [\text{EQ\#83}] \\ \text{Im}(X)^T W \text{Im}(X) &= \begin{bmatrix} 0 & 0 & 0 \\ 0 & \sum_{i=1}^k w_i (G_i)^2 i^{-4} & -\sum_{j=1}^k w_j \text{Im}(G_i) \text{Re}(G_i)^{-3} \\ 0 & -\sum_{i=1}^k w_i \text{Im}(G_i) \text{Re}(G_i)^{-3} & \sum_{i=1}^k w_i \text{Im}(G_i)^2 i^{-4} \end{bmatrix} \quad [\text{EQ\#84}] \end{aligned}$$

(462) Combining these terms results in the final expression for the D matrix, which may contain only real values.

$$(463) \quad D = \begin{bmatrix} \sum_{i=1}^k w_i^{-4} & \sum_{i=1}^k w_i \text{Im}(G_i)^{-3} & -\sum_{i=1}^k w_i \text{Re}(G_i)^{-4} \\ \sum_{i=1}^k w_i \text{Im}(G_i)^{-3} & \sum_{i=1}^k w_i (\text{Re}(G_i)^2 + \text{Im}(G_i)^2) i^{-2} & -2 \sum_{i=1}^k w_i \text{Im}(G_i) \text{Re}(G_i)^{-3} \\ -\sum_{i=1}^k w_i \text{Re}(G_i)^{-4} & -2 \sum_{i=1}^k w_i \text{Im}(G_i) \text{Re}(G_i)^{-3} & \sum_{i=1}^k w_i (\text{Re}(G_i)^2 + \text{Im}(G_i)^2) i^{-4} \end{bmatrix} \quad [\text{EQ\#85}]$$

(464) The same approach may be taken to find an expression for the b vector in terms of G and ω . The real and imaginary parts of y areas follows:

$$(465) \quad \text{Re}(y) = \begin{bmatrix} -\text{Re}(G_1) \\ \text{.Math.} \\ -\text{Re}(G_k) \end{bmatrix}, \text{Im}(y) = \begin{bmatrix} -\text{Im}(G_1) \\ \text{.Math.} \\ -\text{Im}(G_k) \end{bmatrix} \quad [\text{EQ\#86}]$$

(466) Combining the real and imaginary parts results in the expression for the b vector as follows:

$$- \sum_{i=1}^k \text{Math. } w_i \text{Re}(G_i) \quad i^{-2}$$

$$(467) \quad b = \text{Re}(X)^T W \text{Re}(y) + \text{Im}(X)^T W \text{Im}(y) = \left[- \sum_{i=1}^k \text{Math. } w_i (\text{Im}(G_i) + \text{Re}(G_i) \quad i^{-1} \right] \text{ [EQ\#87]}$$

$$\sum_{i=1}^k \text{Math. } w_i (\text{Re}(G_i)^2 + \text{Im}(G_i)^2) \quad i^{-2}$$

Implementing Acoustic Volume Sensing

Collecting the Frequency Response Data and Computing the Complex Response

(468) To implement volume sensor assembly **148**, volume sensor assembly **148** should determine the relative response of reference microphone **626** and invariable volume microphone **630** to the acoustic wave set up by speaker assembly **622**. This may be accomplished by driving speaker assembly **622** with a sinusoidal output at a known frequency; the complex response of microphones **626**, **630** may then be found at that driving frequency. Finally, the relative response of microphones **626**, **630** may be found and corrected for alternating sampling by e.g., an analog-to-digital convertor (i.e., ADC).

(469) Additionally, the total signal variance may be computed and compared to the variance of pure tone extracted using the discrete Fourier transform (i.e., DFT). This may result in a measure of how much of the signal power comes from noise sources or distortion. This value may then be used to reject and repeat bad measurements.

(470) Computing the Discrete Fourier Transform

(471) The signal from the microphone may be sampled synchronously with the output to speaker assembly **622** such that a fixed number of points, N, are taken per wavelength. The measured signal at each point in the wavelength may be summed over an integer number of wavelengths, M, and stored in an array x by the ISR for processing after all the data for that frequency has been collected.

(472) A DFT may be performed on the data at the integer value corresponding to the driven frequency of the speaker. The general expression for the first harmonic of a DFT is as follows:

$$(473) \quad x_k = \frac{2}{MN} \sum_{n=0}^{N-1} \text{Math. } x_n e^{-\frac{2}{N} i k n} \quad \text{[EQ\#88]}$$

(474) The product MN may be the total number of points and the factor of two may be added such that the resulting real and imaginary portions of the answer match the amplitude of the sine wave:

$$(475) \quad x_n = \text{re}(x_k) \cos(\frac{2}{N} k n) + \text{im}(x_k) \sin(\frac{2}{N} k n) \quad \text{[EQ\#89]}$$

(476) This real part of this expression may be as follows:

$$(477) \quad \text{re}(x) = \frac{2}{MN} \sum_{n=0}^{N-1} \text{Math. } x_n \cos(\frac{2}{N} n) \quad \text{[EQ\#90]}$$

(478) We may take advantage of the symmetry of the cosine function to reduce the number of computations needed to compute the DFT. The expression above may be equivalent to:

$$(479) \quad \text{re}(x) = \frac{2}{MN} [(x_0 - x_{\frac{1}{2}N}) + \sum_{n=1}^{\frac{1}{2}N-1} \text{Math. } \sin(\frac{2}{N} n) [(x_n - x_{\frac{1}{2}N+n}) - (x_{\frac{1}{2}N-n} - x_{N-n})]] \quad \text{[EQ\#91]}$$

(480) Similarly, for the imaginary portion of the equation:

$$(481) \quad \text{im}(x) = -\frac{2}{MN} \sum_{n=0}^{N-1} \text{Math. } x_n \sin(\frac{2}{N} n) \quad \text{[EQ\#92]}$$

(482) which may be expressed as follows:

$$(483) \quad \text{im}(x) = -\frac{2}{MN} [(x_{\frac{1}{4}N} - x_{\frac{3}{4}N}) + \sum_{n=1}^{\frac{1}{4}N-1} \text{Math. } \sin(\frac{2}{N} n) [(x_n - x_{\frac{1}{2}N+n}) + (x_{\frac{1}{2}N-n} - x_{N-n})]] \quad \text{[EQ\#93]}$$

(484) The variance of this signal may be calculated as follows:

$$\sigma_{\text{sup.2}} = \frac{1}{2} (\text{re}(x)_{\text{sup.2}} + \text{im}(x)_{\text{sup.2}}) \quad \text{[EQ \#94]}$$

(485) The maximum possible value of the real and imaginary portions of x may be 2.sup.11; which corresponds to half the AD range. The maximum value of the tone variance may be 2.sup.21; half the square of the AD range.

(486) Computing the Signal Variance

(487) The pseudo-variance of the signal may be calculated using the following relation:

$$(488) \quad 0^2 = \frac{1}{NM^2} \sum_{n=0}^{N-1} \text{Math. } x_n^2 - \frac{1}{N^2 M^2} (\sum_{n=0}^{N-1} \text{Math. } x_n)^2 \quad \text{[EQ\#95]}$$

(489) The result may be in the units of AD counts squared. It may only be the “pseudo-variance” because the signal has been averaged over M periods before the variance is calculated over the N samples in the “averaged” period. This may be a useful metric, however, for finding if the “averaged” signal looks like a sinusoid at the expected frequency. This may be done by comparing the total signal variance to that of the sinusoid found in the discrete Fourier transform.

(490) The summation may be on the order of

$$(491) \quad \sum_{n=0}^{N-1} \text{Math. } x_n^2 = O(NM^2 2^{24})$$

for a 12-bit ADC. If N<2.sup.7=128 and M<2.sup.6=64, then the summation will be less than 2.sup.43 and may be stored in a 64-bit integer. The maximum possible value of the variance may result if the ADC oscillated between a value of 0 and 2.sup.12 on each consecutive sample. This may result in a peak variance of ¼(2.sup.12).sup.2=2.sup.22 so the result may be stored at a maximum of a ½.sup.9 resolution in a signed 32-bit integer.

Computing the Relative Microphone Response

(492) The relative response (G) of microphones **626**, **630** may be computed from the complex response of the individual microphones:

$$G = \frac{X_{\text{var}}}{X_{\text{ref}}} = \frac{X_{\text{var}}^*}{X_{\text{ref}}^*} \quad [\text{EQ\#96}]$$

$$(493) \quad \text{Re}(G) = \frac{\text{Re}(X_{\text{var}})\text{Re}(X_{\text{ref}}) + \text{Im}(X_{\text{var}})\text{Im}(X_{\text{ref}})}{\text{Re}(X_{\text{ref}})^2 + \text{Im}(X_{\text{ref}})^2} \quad [\text{EQ\#97}]$$

$$\text{Im}(G) = \frac{\text{Re}(X_{\text{ref}})\text{Im}(X_{\text{var}}) - \text{Re}(X_{\text{var}})\text{Im}(X_{\text{ref}})}{\text{Re}(X_{\text{ref}})^2 + \text{Im}(X_{\text{ref}})^2} \quad [\text{EQ\#98}]$$

(494) The denominator of either expression may be expressed in terms of the reference tone variance computed in the previous section as follows:

$$\text{Re}(x.\text{sub.ref}).\text{sup.2} + \text{Im}(x.\text{sub.ref}).\text{sup.2} = 2\sigma.\text{sub.ref.}\text{sup.2} \quad [\text{EQ \#99}]$$

Correcting for A/D Skew

(495) The signals from microphones **626**, **630** may not be sampled simultaneously; the A/D ISR alternates between microphones **626**, **630**, taking a total of N samples per wavelength for each of microphones **626**, **630**. The result may be a phase offset between two microphones **626**, **630** of π/N . To correct for this phase offset, a complex rotation may be applied to the relative frequency response computed in the previous section:

$$(496) \quad G_{\text{rotated}} = G \cdot \text{Math.}(\cos(\frac{\pi}{N}) + i \sin(\frac{\pi}{N})) \quad [\text{EQ\#100}]$$

Reference Models

Second and Higher Order Models

(497) Leakage through the seals (e.g., seal assembly **1404**) of volume sensor chamber **620** may be modeled as a second resonant port (e.g., port **1504**, FIG. **100**) connected to an external volume (e.g., external volume **1506**, FIG. **100**).

(498) The system of equations describing the three-chamber configuration may be as follows:

$$\dot{p}_1 + \frac{a^2}{V_1}(\dot{v}_k - \dot{v}_{r12}) = 0 \quad [\text{EQ\#101}]$$

$$\dot{p}_2 + \frac{a^2}{V_2}(\dot{v}_{r12} - \dot{v}_{r23}) = 0 \quad [\text{EQ\#102}]$$

$$(499) \quad \text{Math.} \dot{V}_{r12} = \frac{f_{12}A_{12}}{L_{12}}\dot{v}_{r12} + \frac{A_{12}}{L_{12}}(p_2 - p_1) \quad [\text{EQ\#103}]$$

$$\dot{p}_3 + \frac{a^2}{V_3}\dot{v}_{r23} = 0 \quad [\text{EQ\#104}]$$

$$\text{Math.} \dot{V}_{r23} = \frac{f_{23}A_{23}}{L_{23}}\dot{v}_{r23} + \frac{A_{23}}{L_{23}}(p_3 - p_2) \quad [\text{EQ\#105}]$$

(500) Putting these equations into state-space results in the following:

$$(501) \quad \begin{bmatrix} \dot{p}_1 \\ \dot{p}_2 \\ \dot{p}_3 \\ \text{Math.} \dot{V}_{12} \\ \text{Math.} \dot{V}_{23} \end{bmatrix} = \begin{bmatrix} 0 & 0 & 0 & -\frac{a^2}{V_1} & 0 \\ 0 & 0 & 0 & -\frac{a^2}{V_2} & \frac{a^2}{V_2} \\ 0 & 0 & 0 & 0 & -\frac{a^2}{V_3} \\ -\frac{A_{12}}{L_{12}} & \frac{A_{23}}{L_{23}} & 0 & -b_{12} & 0 \\ 0 & -\frac{A_{23}}{L_{23}} & \frac{A_{23}}{L_{23}} & 0 & -b_{23} \end{bmatrix} \begin{bmatrix} p_1 \\ p_2 \\ p_3 \\ v_{12} \\ v_{23} \end{bmatrix} + \begin{bmatrix} -\frac{a^2}{V_1} \\ 0 \\ 0 \\ 0 \\ 0 \end{bmatrix} [\dot{v}_k] \quad [\text{EQ\#106}]$$

(502) the frequency response of which may be represented graphically in the Bode diagram shown in FIG. **101** and which may also be written in transfer function form:

$$(503) \quad \frac{p_2}{p_1} = \frac{\frac{1}{12}(s^2 + b_{23}s + \frac{2}{23})}{(s^2 + b_{12}s + \frac{2}{12})(s^2 + b_{23}s + \frac{2}{23}) + \frac{V_1}{V_2}\frac{2}{23}(s + b_{12})s} \quad [\text{EQ\#107}]$$

(504) Expanding the denominator results in the following:

$$(505) \quad \frac{p_2}{p_1} = \frac{\frac{1}{12}(s^2 + b_{23}s + \frac{2}{23})}{s^4 + (b_{12} + b_{23})s^3 + (b_{12}b_{23} + \frac{2}{12} + \frac{2}{23}(1 + \frac{V_1}{V_2}))s^2 + (b_{23}\frac{2}{12} + b_{12}\frac{2}{23}(1 + \frac{V_1}{V_2}))s + \frac{2}{12}\frac{2}{23}} \quad [\text{EQ\#108}]$$

(506) A bubble underneath the diaphragm material in the variable volume will follow the same dynamic equations as a leakage path. In this case, the diaphragm material may act as the resonant mass rather than the leakage port. Accordingly, the equation may be as follows:

$m\{\text{umlaut over } (x)\} = \Delta pA - b.\text{sub.m}\{\dot{x}\}$ [EQ #109] wherein m is the mass of the diaphragm, A is the cross sectional area of the diaphragm that can resonate, and b.sub.m is the mechanical damping. EQ #106 may be written in terms of the volume flow rate:

(507) $\text{Math.} \dot{V} = -\frac{b}{m}\dot{v} + p\frac{A^2}{m}$ [EQ\#110] wherein the volume of the air bubble is V.sub.3. If the bubble volume is substantially smaller than the acoustic volume V.sub.3 << V.sub.2 than the transfer function may be simplified to:

$$(508) \quad \frac{p_2}{p_1} = \frac{\frac{1}{12}(s^2 + b_{23}s + \frac{2}{23})}{(s^2 + b_{12}s + \frac{2}{12})(s^2 + b_{23}s + \frac{2}{23}(1 + \frac{V_1}{V_2}))} \quad [\text{EQ\#111}]$$

Second Order with Time Delay

(509) The volume sensor assembly **148** equations derived above assume that the pressure is the same everywhere in the acoustic volume. This is only an approximation, as there are time delays associated with the propagation of the sound waves through the volume. This situation may look like a time delay or a time advance based on the relative position of the microphone and speakers.

(510) A time delay may be expressed in the Laplace domain as:

$G(s) = e.\text{sup.} - \Delta Ts$ [EQ #112] which makes for a non-linear set of equations. However, a first-order Pade approximation of the time delay may be used as follows:

(511) $0 \quad G(s) = -\frac{s + \frac{2}{T}}{s - \frac{2}{T}}$ [EQ#113] which is shown graphically in FIG. 102.

Three Chamber Volume Estimation

(512) Volume sensor assembly **148** may also be configured using a third reference volume (e.g., reference volume **1508**; FIG. 103) connected with a separate resonant port (e.g., port **1510**; FIG. 103). This configuration may allow for temperature-independent volume estimation.

(513) The system of equations describing the three-chamber configuration are as follows:

$$\dot{p}_1 + \frac{a^2}{V_1}(\dot{v}_k - \dot{v}_{r12} - \dot{v}_{r13}) = 0 \quad [\text{EQ\#114}]$$

$$\dot{p}_2 + \frac{a^2}{V_2}\dot{v}_{r12} = 0 \quad [\text{EQ\#115}]$$

$$\text{Math.} \quad \dot{V}_{r12} = -\frac{f_{12}A_{12}}{L_{12}}\dot{v}_{r12} + \frac{A_{12}}{L_{12}}(p_2 - p_1) \quad [\text{EQ\#116}]$$

$$\dot{p}_3 + \frac{a^2}{V_3}\dot{v}_{r13} = 0 \quad [\text{EQ\#117}]$$

$$\text{Math.} \quad \dot{V}_{r13} = -\frac{f_{13}A_{13}}{L_{13}}\dot{v}_{r13} + \frac{A_{13}}{L_{13}}(p_2 - p_1) \quad [\text{EQ\#118}]$$

(516) Using these equations and solving for the transfer function across each of the resonant ports results in the following:

$$\frac{P_2}{P_1} = \frac{\frac{2}{n_{12}}}{s^2 + 2 \frac{2}{n_{12}}s + \frac{2}{n_{12}}} \text{where} \quad [\text{EQ\#119}]$$

$$\text{Math.} \quad n_{12} = \frac{1}{V_2} \frac{a^2 A_{12}}{L_{12}} \text{and} \quad = \frac{f_{12} A_{12}}{2L_{12} n_{12}} \quad [\text{EQ\#120}]$$

$$\frac{P_3}{P_1} = \frac{\frac{2}{n_{13}}}{s^2 + 2 \frac{2}{n_{13}}s + \frac{2}{n_{13}}} \text{where} \quad [\text{EQ\#121}]$$

$$n_{13} = \frac{1}{V_2} \frac{a^2 A_{13}}{L_{13}} \text{and} \quad = \frac{f_{13} A_{13}}{2L_{13} n_{13}} \quad [\text{EQ\#122}]$$

(518) The volume of volume sensor chamber **620** may be estimated using the ratio of the natural frequency of the two resonant ports as follows:

$$\frac{2}{n_{13}} = \frac{V_2 A_{13} L_{12}}{V_3 A_{12} L_{13}} \quad [\text{EQ\#123}]$$

(520) EQ #120 illustrates that the volume of volume sensor chamber **620** may be proportional to reference volume **1508**. The ratio of these two volumes (in the ideal model) may only depend on the geometry of the resonant port (e.g., port **1510**; FIG. 103) and has no dependence upon temperature.

(521) Exponential Volume Model

(522) Assume the flow out through the flow resistance has the following form:

$$\dot{V}_{\text{out}} = \frac{V_{\text{avs}}}{T} \quad [\text{EQ\#124}]$$

(524) Assuming a fixed input flow rate from the pump chamber, the volume of volume sensor chamber **620** is based upon the following differential equation:

$$\dot{V}_{\text{avs}} = \dot{V}_{\text{in}} - \dot{V}_{\text{out}} = \dot{V}_{\text{in}} - \frac{V_{\text{avs}}}{T} \quad [\text{EQ\#125}] \text{ which gives the following solution assuming a zero initial volume:}$$

$$V_{\text{avs}} = \dot{V}_{\text{in}} (1 - e^{-\frac{t}{T}}) \quad [\text{EQ\#126}]$$

(527) Accordingly, the output flow rate flows:

$$\dot{V}_{\text{out}} = \dot{V}_{\text{in}} (1 - e^{-\frac{t}{T}}) \quad [\text{EQ\#127}]$$

(529) The volume delivered during the pump phase may be written:

$$V_{\text{out}} = \dot{V}_{\text{in}} [t - (1 - e^{-\frac{t}{T}})] \quad [\text{EQ\#128}]$$

Device Calibration

(531) The model fit allows the resonant frequency of the port to be extracted from the sine sweep data. The next step is to relate this value to the delivered volume. The ideal relationship between the resonant frequency and the delivered volume to be expressed as follows:

$$\frac{2}{n} = \frac{a^2 A}{L V_2} \quad [\text{EQ\#129}]$$

(533) The speed of sound will vary with temperature, so it may be useful to split out the temperature effects.

$$\frac{2}{n} = \frac{RA}{L V_2} \quad [\text{EQ\#130}]$$

(535) The volume may then be expressed as a function of the measured resonant frequency and the temperature:

$$V_2 = C \frac{T}{n} \quad [\text{EQ\#131}] \text{ Where } c \text{ is the calibration constant}$$

$$C = \frac{RA}{L}$$

Implementation Details

End Effects

(538) The air resonating in the port (e.g., port assembly **624**) may extend out into the acoustic volumes at the end of each oscillation. The distance the air extends may be estimated based on the fundamental volume sensor assembly equations. For any given acoustic volume, the distance the air extends into the volume may be expressed as a function of the pressure and port cross-sectional area:

$$x = \frac{V}{a^2 A} p \quad [\text{EQ\#132}]$$

(540) If we assume the following values:

$$V = 28.8 \times 10^{-6} L \quad [\text{EQ\#133}]$$

$$= 1.292 \frac{\text{kg}}{\text{m}^3} \quad [\text{EQ\#134}]$$

$$(541) \quad a = 340 \frac{\text{m}}{\text{s}} \quad [\text{EQ\#135}]$$

$$d = 0.5 \text{ .Math. mm} \quad [\text{EQ\#136}]$$

$$p = 1 \text{ .Math. Pa (Approximately 100 dB)} \quad [\text{EQ\#137}]$$

(542) Accordingly, the air will extend roughly 1.9 mm in to the acoustic chamber.

(543) Sizing V.sub.1 (i.e., the Fixed Volume) Relative to V.sub.2 (i.e., the Variable Volume)

(544) Sizing V.sub.1 (e.g., fixed volume **1500**) may require trading off acoustic volume with the relative position of the poles and zeros in the transfer function. The transfer function for both V.sub.1 and V.sub.2 (e.g., variable volume **1502**) are shown below relative to the volume displacement of speaker assembly **622**.

$$\frac{P_2}{V_k} = -\frac{a^2}{V_1} \frac{\frac{2}{n}}{s^2 + 2\zeta\omega_n s + \alpha\omega_n^2} \quad [\text{EQ\#138}]$$

$$(545) \quad \frac{P_1}{V_k} = -\frac{a^2 s^2 + 2\zeta\omega_n s + \alpha\omega_n^2}{V_1} \text{ where} \quad [\text{EQ\#139}]$$

$$\frac{2}{n} = \frac{a^2 A}{L} \frac{1}{V_2}, \quad = \frac{fA}{2L} \text{ and} \quad = (1 + \frac{V_2}{V_1}) \quad [\text{EQ\#140}]$$

(546) As V.sub.1 is increased the gain may decrease and the speaker may be driven at a higher amplitude to get the same sound pressure level. However, increasing V.sub.1 may also have the benefit of moving the complex zeros in the p.sub.1 transfer function toward the complex poles. In the limiting case where V.sub.1.fwdarw.∞, α.fwdarw.1 and you have pole-zero cancellation and a flat response. Increasing V.sub.1, therefore, may have the benefit of reducing both the resonance and the notch in the p.sub.1 transfer function, and moving the p.sub.2 poles toward ω.sub.n; resulting in a lower sensitivity to measurement error when calculating the p.sub.2/p.sub.1 transfer function.

(547) FIG. **104** is a graphical representation of:

$$(548) \quad \frac{P_1}{V_k} \quad [\text{EQ\#141}]$$

(549) FIG. **105** is a graphical representation of

$$(550) \quad \frac{P_2}{V_k} \quad [\text{EQ\#141}]$$

Aliasing

(551) Higher frequencies may alias down to the frequency of interest, wherein the aliased frequency may be expressed as follows: $f = |f_{\text{sub.n}} - n f_{\text{sub.s}}|$ [EQ #143] where f.sub.s is the sampling frequency, f.sub.n is the frequency of the noise source, n is a positive integer, and f is the aliased frequency of the noise source.

(552) The demodulation routine may effectively filter out noise except at the specific frequency of the demodulation. If the sample frequency is set dynamically to be a fixed multiple of the demodulation frequency, then the frequency of the noise that can alias down to the demodulation frequency may be a fixed set of harmonics of that fundamental frequency.

(553) For example, if the sampling frequency is eight times the demodulation frequency, then the noise frequencies that can alias down to that frequency are as follows:

$$(554) \quad \frac{f_n}{f} = \left\{ \frac{1}{n+1}, \frac{1}{n-1} \right\} = \left\{ \frac{1}{7}, \frac{1}{9}, \frac{1}{15}, \frac{1}{17}, \frac{1}{23}, \frac{1}{25}, \text{ .Math. } \right\} \quad [\text{EQ\#144}] \quad \text{where}$$

$$(555) \quad 0 = \frac{f_s}{f} = 8.$$

For β=16, the following series would result:

$$(556) \quad \frac{f_n}{f} = \left\{ \frac{1}{15}, \frac{1}{17}, \frac{1}{31}, \frac{1}{33}, \text{ .Math. } \right\} \quad [\text{EQ\#145}]$$

Performance

Sensitivity to Temperature

(557) The sensitivity to temperature may be split into a gain change and a noise change. If the temperature is off by a factor of dT, the resulting gain error may be:

$$(558) \quad V_2 = c \left(\frac{T_2}{2} - \frac{T_1}{1} \right) \quad [\text{EQ\#147}]$$

(559) Accordingly, if the same temperature is used for both sine sweeps, any error in the temperature measurement may look like a gain change to the system.

$$(560) \quad e_{\text{gain}} = 1 - \frac{T_{\text{measured}}}{T_{\text{actual}}} \quad [\text{EQ\#148}]$$

(561) Therefore, for a 1° K temperature error, the resulting volume error may be 0.3% at 298° K. This error may include both the error in the temperature sensor and the difference between the sensor temperature and the temperature of the air within volume sensor assembly **148**.

(562) The measurement, however, may be more susceptible to noise in the temperature measurement. A temperature change during the differential sine sweeps may result in an error that looks more like an offset rather than a gain change:

$$(563) \quad V_{\text{error}} = \frac{c}{T} \quad [\text{EQ\#149}]$$

(564) Accordingly, if the measurement varies by 0.1 K during the two measurement sine sweeps, the difference may be 0.012 uL. Therefore, it may be better to use a consistent temperature estimate for each delivery rather than taking a separate temperature measurement for each sine sweep (as shown in FIG. **107**).

(565) The LM73 temperature sensor has a published accuracy of +/−1° C. and a resolution of 0.03 C. Further, the LM73 temperature sensor seems to consistently have a startup transient of about 0.3° C. that takes about five sine sweeps to level out (as shown in FIG. **108**).

(566) Since the above-described infusion pump assemblies (e.g., infusion pump assembly **100**, **100'**, **400**, **500**) provides discrete

deliveries of infusible fluid, the above-described pump assemblies may be modeled entirely in the discrete domain (in the manner shown in FIG. 109), which may be reduced to the following:

$$(567) \quad G_p(z) = \frac{Kz}{z-1} \quad [\text{EQ\#150}]$$

(568) A discrete-time PI regulator may perform according to the following:

$$(569) \quad G_c(z) = K_p \left(1 + \frac{T_s}{T_i} \frac{z}{z-1}\right) \quad [\text{EQ\#151}]$$

(570) The AVS system described above works by comparing the acoustic response in fixed volume 1500 and variable volume 1502 to a speaker driven input and extracting the volume of the variable volume 1502. As such, there is a microphone in contact with each of these separate volumes (e.g., microphones 626, 630). The response of variable volume microphone 630 may also be used in a more gross manner to detect the presence or absence of disposable housing assembly 114. Specifically, if disposable housing assembly 114 is not attached to (i.e., positioned proximate) variable volume 1502, essentially no acoustic response to the speaker driven input should be sensed. The response of fixed volume 1500, however, should remain tied to the speaker input. Thus, the microphone data may be used to determine whether disposable housing assembly 114 by simply ensuring that both microphones exhibit an acoustic response. In the event that microphone 626 (i.e., the microphone positioned proximate fixed volume 1500) exhibits an acoustic response and microphone 630 (i.e., the microphone positioned proximate variable volume 1502) does not exhibit an acoustic response, it may be reasonably concluded that disposable housing assembly 114 is not attached to reusable housing assembly 102. It should be noted that a failure of variable volume microphone 630 may also appear to be indicative of disposable housing assembly 114 not being attached, as the failure of variable volume microphone 630 may result in a mid-range reading that is nearly indistinguishable from the microphone response expected when disposable housing assembly 114 is not attached.

(571) For the following discussion, the following nomenclature may be used:

(572) TABLE-US-00010 Symbols α .sub.max(f) maximum read at a given frequency α .sub.min(f) minimum read at a given frequency δ difference between max and min sums f individual frequency F set of sine sweep frequencies N number of frequencies in each sine sweep, $F \phi$ boolean disposable attached flag σ max sum of maximum ADC reads σ min sum of minimum ADC reads T max/min ADC difference threshold Subscripts i sweep number ref reference volume var variable volume

(573) As part of the demodulation routine employed in each frequency response calculation, the minimum and maximum readings of both fixed volume microphone 626 and variable volume microphone 630 may be calculated. The sum of these maximum and minimum values may be calculated over the entire sine-sweep (as discussed above) for both microphone 626 and microphone 630 as follows.

$$(574) \quad \sigma_{max} = \sum_{f \in F} \max(f) \quad [\text{EQ\#152}]$$

$$\sigma_{min} = \sum_{f \in F} \min(f) \quad [\text{EQ\#153}]$$

(575) and the difference between these two summations may be simplified as follows:

$$\delta = \sigma_{max} - \sigma_{min} \quad [\text{EQ \#154}]$$

(576) While δ may be divided by the number of sine sweeps to get the average minimum/maximum difference for the sine sweep (which is then compared to a threshold), the threshold may equivalently be multiplied by N for computational efficiency. Accordingly, the basic disposable detection algorithm may be defined as follows:

$$(577) \quad i = \begin{cases} 1 & \text{if } var > N * T \\ 0 & \text{if } var < N * T \& ref > N * T \end{cases} \quad [\text{EQ\#155}]$$

(578) The additional condition that the maximum/minimum difference be greater than the threshold is a check performed to ensure that a failed speaker is not the cause of the acoustic response received. This algorithm may be repeated for any sine-sweep, thus allowing a detachment of disposable housing assembly 114 to be sensed within e.g., at most two consecutive sweeps (i.e., in the worst case scenario in which disposable housing assembly 114 is removed during the second half of an in-progress sine sweep).

(579) Thresholding for the above-described algorithm may be based entirely on numerical evidence. For example, examination of typical minimum/maximum response differences may show that no individual difference is ever less than five hundred ADC counts. Accordingly, all data examined while disposable housing assembly 114 is detached from reusable housing assembly 102 may show that all minimum/maximum response differences as being well under five hundred ADC counts. Thus, the threshold for δ may be set at $T=500$.

(580) While volume sensor assembly 148 is described above as being utilized within an infusion pump assembly (e.g., infusion pump assembly 100), this is for illustrative purposes only and is not intended to be a limitation of this disclosure, as other configurations are possible and are considered to be within the scope of this disclosure. For example, volume sensor assembly 148 may be used within a process control environment for e.g., controlling the quantity of chemicals mixed together. Alternatively, volume sensor assembly 148 may be used within a beverage dispensing system to control e.g., the quantity of ingredients mixed together.

(581) While volume sensor assembly 148 is described above as utilizing a port (e.g., port assembly 624) as a resonator, this is for illustrative purposes only, as other configurations are possible and are considered to be within the scope of this disclosure. For example, a solid mass (not shown) may be suspended within port assembly 624 and may function as a resonator for volume sensor assembly 148. Specifically, the mass (not shown) for the resonator may be suspended on a diaphragm (not shown) spanning port assembly 624. Alternatively, the diaphragm itself (not shown) may act as the mass for the resonator. The natural frequency of volume sensor assembly 148 may be a function of the volume of variable volume 1502. Accordingly, if the natural frequency of volume sensor assembly 148 can be measured, the volume of variable volume 1502 may be calculated.

(582) The natural frequency of volume sensor assembly 148 may be measured in a number of different ways. For example, a time-varying force may be applied to the diaphragm (not shown) and the relationship between that force and the motion of the

diaphragm (not shown) may be used to estimate the natural frequency of volume sensor assembly **148**. Alternately the mass (not shown) may be perturbed and then allowed to oscillate. The unforced motion of the mass (not shown) may then be used to calculate the natural frequency of volume sensor assembly **148**.

(583) The force applied to the resonant mass (not shown) may be accomplished in various ways, examples of which may include but are not limited to: speaker assembly **622** may create a time-varying pressure within fixed volume **1500**; the resonant mass (not shown) may be a piezoelectric material responding to a time-varying voltage/current; and the resonant mass (not shown) may be a voice coil responding to a time-varying voltage/current

(584) The force applied to the resonant mass may be measured in various ways, examples of which may include but are not limited to: measuring the pressure in the fixed volume; the resonant mass (not shown) may be a piezoelectric material; and a strain gauge may be connected to the diaphragm (not shown) or other structural member supporting the resonant mass (not shown).

(585) Similarly, the displacement of the resonant mass (not shown) may be estimated by measuring the pressure in the variable volume, or measured directly in various ways, examples of which may include but are not limited to: via piezoelectric sensor; via capacitive sensor; via optical sensor; via Hall-effect sensor; via a potentiometer (time varying impedance) sensor; via an inductive type sensor; and via a linear variable differential transformer (LVDT)

(586) Further, the resonant mass (not shown) may be integral to either the force or displacement type sensor (i.e. the resonant mass (not shown) may be made of piezoelectric material).

(587) The application of force and measurement of displacement may be accomplished by a single device. For example, a piezoelectric material may be used for the resonant mass (not shown) and a time-varying voltage/current may be applied to the piezoelectric material to create a time-varying force. The resulting voltage/current applied to the piezoelectric material may be measured and the transfer function between the two used to estimate the natural frequency of volume sensor assembly **148**.

(588) As discussed above, the resonant frequency of volume sensor assembly **148** may be estimated using swept-sine system identification. Specifically, the above-described model fit may allow the resonant frequency of the port assembly to be extracted from the sine sweep data, which may then be used to determine the delivered volume. The ideal relationship between the resonant frequency and the delivered volume may be expressed as follows:

$$(589) \quad \frac{2}{n} = \frac{a^2 A}{L} \frac{1}{V_2} \quad [\text{EQ\#126}]$$

(590) The speed of sound will vary with temperature, so it may be useful to split out the temperature effects.

$$(591) \quad 00 \quad \frac{2}{n} = -\frac{RA}{L} \frac{T}{V_2} \quad [\text{EQ\#126}]$$

(592) The volume may then be expressed as a function of the measured resonant frequency and the temperature:

$$(593) \quad 01 \quad V_2 = C \frac{T}{n} \quad [\text{EQ\#127}] \quad \text{Where } c \text{ is the calibration constant}$$

$$(594) \quad 02C = -\frac{RA}{L}.$$

(595) Infusion pump assembly **100** may then compare this calculated volume V.sub.2 (i.e., representative of the actual volume of infusible fluid delivered to the user) to the target volume (i.e., representative of the quantity of fluid that was supposed to be delivered to the user). For example, assume that infusion pump assembly **100** was to deliver a 0.100 unit basal dose of infusible fluid to the user every thirty minutes. Further, assume that upon effectuating such a delivery, volume sensor assembly **148** indicates a calculated volume V.sub.2 (i.e., representative of the actual volume of infusible fluid delivered to the user) of 0.095 units of infusible fluid.

(596) When calculating volume V.sub.2, infusion pump assembly **100** may first determine the volume of fluid within volume sensor chamber **620** prior to the administration of the dose of infusible fluid and may subsequently determine the volume of fluid within volume sensor chamber **620** after the administration of the dose of infusible fluid, wherein the difference of those two measurements is indicative of V.sub.2 (i.e., the actual volume of infusible fluid delivered to the user). Accordingly, V.sub.2 is a differential measurement.

(597) V.sub.2 may be the total air space over the diaphragm in the variable volume chamber. The actual fluid delivery to the patient may be the difference in V.sub.2 from when the chamber was full to after the measurement valve was opened and the chamber was emptied. V.sub.2 may not directly be the delivered volume. For example, the air volume may be measured and a series of differential measurements may be taken. For occlusion, an empty measurement may be taken, the chamber may be filed, a full measurement may be taken, and then a final measurement may be taken after the exit valve is open. Accordingly, the difference between the first and second measurement may be the amount pumped and the difference between the second and third is the amount delivered to the patient.

(598) Accordingly, electrical control assembly **110** may determine that the infusible fluid delivered is 0.005 units under what was called for. In response to this determination, electrical control assembly **110** may provide the appropriate signal to mechanical control assembly **104** so that any additional necessary dosage may be pumped. Alternatively, electrical control assembly **110** may provide the appropriate signal to mechanical control assembly **104** so that the additional dosage may be dispensed with the next dosage. Accordingly, during administration of the next 0.100 unit dose of the infusible fluid, the output command for the pump may be modified based on the difference between the target and amount delivered.

(599) Referring also to FIG. **110**, there is shown one particular implementation of a control system for controlling the quantity of infusible fluid currently being infused based, at least in part, on the quantity of infusible fluid previously administered.

Specifically and continuing with the above-stated example, assume for illustrative purposes that electrical control assembly **110** calls for the delivery of a 0.100 unit dose of the infusible fluid to the user. Accordingly, electrical control assembly **110** may provide a target differential volume signal **1600** (which identifies a partial basal dose of 0.010 units of infusible fluid per cycle of shape memory actuator **112**) to volume controller **1602**. Accordingly and in this particular example, shape memory actuator **112** may need to be cycled ten times in order to achieve the desired basal dose of 0.100 units of infusible fluid (i.e., 10 cycles×0.010 units per cycle=0.100 units). Volume controller **1602** in turn may provide “on-time” signal **1606** to SMA (i.e., shape memory actuator) controller **1608**. Also provided to SMA controller **1608** is battery voltage signal **1610**.

(600) Specifically, shape-memory actuator **112** may be controlled by varying the amount of thermal energy (e.g., joules) applied to

shape-memory actuator **112**. Accordingly, if the voltage level of battery **606** is reduced, the quantity of joules applied to shape-memory actuator **112** may also be reduced for a defined period of time. Conversely, if the voltage level of battery **606** is increased, the quantity of joules applied to shape memory actuator **112** may also be increased for a defined period of time. Therefore, by monitoring the voltage level of battery **606** (via battery voltage signal **1610**), the type of signal applied to shape-memory actuator **112** may be varied to ensure that the appropriate quantity of thermal energy is applied to shape-memory actuator **112** regardless of the battery voltage level.

(601) SMA controller **1608** may process “on-time” signal **1606** and battery voltage signal **1610** to determine the appropriate SMA drive signal **1612** to apply to shape-memory actuator **112**. One example of SMA drive signal **1612** may be a series of binary pulses in which the amplitude of SMA drive signal **1612** essentially controls the stroke length of shape-memory actuator **112** (and therefore pump assembly **106**) and the duty cycle of SMA drive signal **1612** essentially controls the stroke rate of shape-memory actuator **112** (and therefore pump assembly **106**). Further, since SMA drive signal **1612** is indicative of a differential volume (i.e., the volume infused during each cycle of shape memory actuator **112**), SMA drive signal **1612** may be integrated by discrete time integrator **1614** to generate volume signal **1616** which may be indicative of the total quantity of infusible fluid infused during a plurality of cycles of shape memory actuator **112**. For example, since (as discussed above) it may take ten cycles of shape memory actuator **112** (at 0.010 units per cycle) to infuse 0.100 units of infusible fluid, discrete time integrator **1614** may integrate SMA drive signal **1612** over these ten cycles to determine the total quantity infused of infusible fluid (as represented by volume signal **1616**).

(602) SMA drive signal **1612** may actuate pump assembly **106** for e.g. one cycle, resulting in the filling of volume sensor chamber **620** included within volume sensor assembly **148**. Infusion pump assembly **100** may then make a first measurement of the quantity of fluid included within volume sensor chamber **620** (as discussed above). Further and as discussed above, measurement valve assembly **610** may be subsequently energized, resulting in all or a portion of the fluid within volume sensor chamber **620** being delivered to the user. Infusion pump assembly **100** may then make a measurement of the quantity of fluid included within volume sensor chamber **620** (as described above) and use those two measurements to determine V.sub.2 (i.e., the actual volume of infusible fluid delivered to the user during the current cycle of shape memory actuator **112**). Once determined, V.sub.2 (i.e., as represented by signal **1618**) may be provided (i.e., fed back) to volume controller **1602** for comparison to the earlier-received target differential volume.

(603) Continuing with the above-stated example in which the differential target volume was 0.010 units of infusible fluid, assume that V.sub.2 (i.e., as represented by signal **1618**) identifies 0.009 units of infusible fluid as having been delivered to the user. Accordingly, infusion pump assembly **100** may increase the next differential target volume to 0.011 units to offset the earlier 0.001 unit shortage. Accordingly and as discussed above, the amplitude and/or duty cycle of SMA drive signal **1612** may be increased when delivering the next basal dose of the infusible fluid to the user. This process may be repeated for the remaining nine cycles of shape memory actuator **112** (as discussed above) and discrete time integrator **1614** may continue to integrate SMA drive signal **1612** (to generate volume signal **1616**) which may define the total quantity of infusible fluid delivered to the user.

(604) Referring also to FIG. **111**, there is shown one possible embodiment of volume controller **1602**. In this particular implementation, volume controller **1602** may include PI (proportional-integrator) controller **1650**. Volume controller **1602** may include feed forward controller **1652** for setting an initial “guess” concerning “on-time” signal **1606**. For example, for the situation described above in which target differential volume signal **1600** identifies a partial basal dose of 0.010 units of infusible fluid per cycle of shape memory actuator **112**, feed forward controller **1652** may define an initial “on-time” of e.g., one millisecond. Feed forward controller **1652** may include e.g., a lookup table that define an initial “on-time” that is based, at least in part, upon target differential volume signal **1600**. Volume controller **1602** may further include discrete time integrator **1654** for integrating target differential volume signal **1600** and discrete time integrator **1656** for integrating V.sub.2 (i.e., as represented by signal **1618**).

(605) Referring also to FIG. **112**, there is shown one possible embodiment of feed forward controller **1652**. In this particular implementation, feed forward controller **1652** may define a constant value signal **1658** and may include amplifier **1660** (e.g., a unity gain amplifier), the output of which may be summed with constant value signal **1658** at summing node **1662**. The resulting summed signal (i.e., signal **1664**) may be provided to as an input signal to e.g., lookup table **1666**, which may be processed to generate the output signal of feed forward controller **1652**.

(606) As discussed above, pump assembly **106** may be controlled by shape memory actuator **112**. Further and as discussed above, SMA controller **1608** may process “on-time” signal **1606** and battery voltage signal **1610** to determine the appropriate SMA drive signal **1612** to apply to shape-memory actuator **112**.

(607) Referring also to FIGS. **113-114**, there is shown one particular implementation of SMA controller **1608**. As discussed above, SMA controller **1608** may be responsive to “on-time” signal **1606** and battery voltage signal **1610** and may provide SMA drive signal **1612** to shape-memory actuator **112**. SMA controller **1608** may include a feedback loop (including unit delay **1700**), the output of which may be multiplied with battery voltage signal **1610** at multiplier **1702**. The output of multiplier **1702** may be amplified with e.g., unity gain amplifier **1704**. The output of amplifier **1704** may be applied to the negative input of summing node **1706** (to which “on-time” signal **1606** is applied). The output of summing node **1706** may be amplified (via e.g., unity gain amplifier **1708**). SMA controller may also include feed forward controller **1710** to provide an initial value for SMA drive signal **1612** (in a fashion similar to feed forward controller **1652** of volume controller **1602**; See FIG. **112**). The output of feed forward controller **1710** may be summed at summing node **1712** with the output of amplifier **1708** and an integrated representation (i.e., signal **1714**) of the output of amplifier **1708** to form SMA drive signal **1612**.

(608) SMA drive signal **1612** may be provided to control circuitry that effectuates the application of power to shape-memory actuator **112**. For example, SMA drive signal **1612** may be applied to switching assembly **1716** that may selectively apply current signal **1718** (supplied from battery **606**) and/or fixed signal **1720** to shape-memory actuator. For example, SMA drive signal **1612** may effectuate the application of energy (supplied from battery **606** via current signal **1718**) via switching assembly **1716** in a manner that achieves the duty cycle defined by SMA drive signal **1612**. Unit delay **1722** may generate a delayed version of the

signal applied to shape-memory actuator **112** to form battery voltage signal **1610** (which may be applied to SMA controller **1608**). (609) When applying power to shape-memory actuator **112**, voltage may be applied for a fixed amount of time and: a) at a fixed duty cycle with an unregulated voltage; b) at a fixed duty cycle with a regulated voltage; c) at a variable duty cycle based upon a measured current value; d) at a variable duty cycle based upon a measured voltage value; and e) at a variable duty cycle based upon the square of a measured voltage value. Alternatively, voltage may be applied to shape-memory actuator **112** for a variable amount of time based upon a measured impedance.

(610) When applying an unregulated voltage for a fixed amount of time at a fixed duty cycle, inner loop feedback may not be used and shape memory actuator may be driven at a fixed duty cycle and with an on-time determined by the outer volume loop.

(611) When applying a regulated voltage for a fixed amount of time at a fixed duty cycle, inner loop feedback may not be used and shape memory actuator **112** may be driven at a fixed duty cycle and with an on-time determined by the outer volume loop.

(612) When applying an unregulated voltage at a variable duty cycle based upon a measured current value, the actual current applied to shape-memory actuator **112** may be measured and the duty cycle may be adjusted during the actuation of shape-memory actuator **112** to maintain the correct mean current.

(613) When applying an unregulated voltage at a variable duty cycle based upon a measured voltage value, the actual voltage applied to shape-memory actuator **112** may be measured and the duty cycle may be adjusted during the actuation of shape-memory actuator **112** to maintain the correct mean voltage.

(614) When applying an unregulated voltage at a variable duty cycle based upon the square of a measured voltage value, the actual voltage applied to shape-memory actuator **112** may be measured and the duty cycle may be adjusted during the actuation of shape-memory actuator **112** to maintain the square of the voltage at a level required to provide the desired level of power to shape-memory actuator **112** (based upon the impedance of shape-memory actuator **112**).

(615) Referring also to FIG. **114A-114B**, there is shown other implementations of SMA controller **1608**. Specifically, FIG. **114A** is an electrical schematic that includes a microprocessor and various control loops that may be configured to provide a PWM signal that may open and close the switch assembly. The switch assembly may control the current that is allowed to flow through the shape memory actuator. The battery may provide the current to the shape memory actuator. Further, **114B** discloses a volume controller and an inner shape memory actuator controller. The shape memory actuator controller may provide a PWM signal to the pump, which may be modified based on the battery voltage. This may occur for a fixed ontime, the result being a volume that may be measured by volume sensor assembly **148** and fed back into the volume controller.

(616) In our preferred embodiment, we vary the duty cycle based on the measured battery voltage to give you approximately consistent power. We adjust the duty cycle to compensate for a lower battery voltage. Battery voltage may change for two reasons: 1) as batteries are discharged, the voltage slowly decreases; and 2) when you apply a load to a battery it has an internal impedance so its voltage dips. This is something that happens in any type of system, and we compensate for that by adjusting the duty cycle, thus mitigating the lower or varying battery voltage. Battery voltage may be measured by the microprocessor. In other systems: 1) voltage may be regulated (put a regulator to maintain the voltage at a steady voltage); 2) feedback based on something else (i.e., speed or position of a motor, not necessarily measuring the battery voltage).

(617) Other configurations may be utilized to control the shape memory actuator. For example: A) the shape memory actuator may be controlled at fixed duty cycle with unregulated voltage. As voltage varies, the repeatability of heating the shape memory actuator is reduced. B) a fixed duty cycle, regulated voltage may be utilized which compensate for changes in battery voltage. However, regulate the voltage down is less efficient due to energy of energy. C) the duty cycle may be varied based on changes in current (which may required more complicated measurement circuitry. D) The duty cycle may be varied based on measured voltage. E) The duty cycle may be varied based upon the square of the current. or the square of the voltage divided by resistance. F) the voltage may be applied for a variable amount of time based on the measured impedance (e.g., may measure impedance using Wheatstone gauge (not shown)). The impedance of the shape memory actuator may be correlated to strain (i.e., may correlate how much the SMA moves based on its impedance).

(618) Referring also to FIG. **115** and as discussed above, to enhance the safety of infusion pump assembly **100**, electrical control assembly **110** may include two separate and distinct microprocessors, namely supervisor processor **1800** and command processor **1802**. Specifically, command processor **1802** may perform the functions discussed above (e.g., generating SMA drive signal **1612**) and may control relay/switch assemblies **1804**, **1806** that control the functionality of (in this example) shape memory actuators **112**, **632** (respectively). Command processor **1802** may receive feedback from signal conditioner **1808** concerning the condition (e.g., voltage level) of the voltage signal applied to shape memory actuators **112**, **632**. Command processor **1800** may control relay/switch assembly **1810** independently of relay/switch assemblies **1804**, **1806**. Accordingly, when an infusion event is desired, both of supervisor processor **1800** and command processor **1802** must agree that the infusion event is proper and must both actuate their respective relays/switches. In the event that either of supervisor processor **1800** and command processor **1802** fails to actuate their respective relays/switches, the infusion event will not occur. Accordingly through the use of supervisor processor **1800** and command processor **1802** and the cooperation and concurrence that must occur, the safety of infusion pump assembly **100** is enhanced.

(619) The supervisor processor may prevent the command processor from delivering when it is not supposed and also may alarm if the command processor does not deliver when it should be delivering. The supervisor processor may deactivate the relay/switch assembly if the command processor actuates the wrong switch, or if the command processor it tries to apply power for too long.

(620) The supervisor processor may redundantly doing calculations for how much insulin should be delivered (i.e., double checking the calculations of the command processor). Command processor may decide the delivery schedule, and the supervisor processor may redundantly check those calculations.

(621) Supervisor also redundantly holds the profiles (delivery profiles) in RAM, so the command processor may be doing the correct calculations, but if it has bad RAM, would cause the command to come up with the wrong result. The Supervisor uses its local copy of the basal profile, etc., to double check.

(622) Supervisor can double check AVS measurements, looks at the AVS calculations and applies safety checks. Every time AVS

measurement is taken, it double checks.

(623) Referring also to FIG. **116**, one or more of supervisor processor **1800** and command processor **1802** may perform diagnostics on various portions of infusion pump assembly **100**. For example, voltage dividers **1812**, **1814** may be configured to monitor the voltages (V1 & V2 respectively) sensed at distal ends of e.g., shape memory actuator **112**. The value of voltages V1 & V2 in combination with the knowledge of the signals applied to relay/switch assemblies **1804**, **1810** may allow for diagnostics to be performed on various components of the circuit shown in FIG. **116** (in a manner similar to that shown in illustrative diagnostic table **1816**).

(624) As discussed above and as illustrated in FIGS. **115-116**, to enhance the safety of infusion pump assembly **100**, electrical control assembly **110** may include a plurality of microprocessors (e.g., supervisor processor **1800** and command processor **1802**), each of which may be required to interact and concur in order to effectuate the delivery of a dose of the infusible fluid. In the event that the microprocessors fail to interact/concur, the delivery of the dose of infusible fluid may fail and one or more alarms may be triggered, thus enhancing the safety and reliability of infusion pump assembly **100**.

(625) A master alarm may be utilized that tracks the volume error over time. Accordingly, if the sum of the errors becomes too large, the master alarm may be initiated, indicating that something may be wrong with the system. Accordingly, the master alarm may be indicative of a total volume comparison being performed and a discrepancy being noticed. A typical value of the discrepancy required to initiate the master alarm may be 1.00 milliliters. The master alarm may monitor the sum in a leaky fashion (i.e., Inaccuracies have a time horizon).

(626) Referring also to FIGS. **117A-117B**, there is shown one such illustrative example of such interaction amongst multiple microprocessors during the delivery of a dose of the infusible fluid. Specifically, command processor **1802** may first determine **1900** the initial volume of infusible fluid within volume sensor chamber **620**. Command processor **1802** may then provide **1902** a “pump power request” message to supervisor processor **1800**. Upon receiving **1904** the “pump power request” message, supervisor processor **1800** may e.g., energize **1906** relay/switch **1810** (thus energizing shape memory actuator **112**) and may send **1908** a “pump power on” message to command processor **1802**. Upon receiving **1910** the “pump power on” message, command processor **1802** may actuate **1912** e.g., pump assembly **106** (by energizing relay/switch **1804**), during which time supervisor processor **1800** may monitor **1914** the actuation of e.g., pump assembly **106**.

(627) Once actuation of pump assembly **106** is complete, command processor **1802** may provide **1914** a “pump power off” message to supervisor processor **1800**. Upon receiving **1916** the “pump power off” message, supervisor processor **1800** may deenergize **1918** relay/switch **1810** and provide **1920** a “pump power off” message to command processor **1802**. Upon receiving **1922** the “pump power off” message, command processor **1802** may measure **1924** the quantity of infusible fluid pumped by pump assembly **106**. This may be accomplished by measuring the current quantity of fluid within volume sensor chamber **620** and comparing it with the quantity determined above (in step **1900**). Once determined **1924**, command processor **1802** may provide **1926** a “valve open power request” message to supervisor processor **1800**. Upon receiving **1928** the “valve open power request” message, supervisor processor **1800** may energize **1930** relay/switch **1810** (thus energizing shape memory actuator **632**) and may send **1932** a “valve open power on” message to command processor **1802**. Upon receiving **1934** the “valve open power on” message, command processor **1802** may actuate **1936** e.g., measurement valve assembly **610** (by energizing relay/switch **1806**), during which time supervisor processor **1800** may monitor **1938** the actuation of e.g., measurement valve assembly **610**.

(628) Once actuation of measurement valve assembly **610** is complete, command processor **1802** may provide **1940** a “valve power off” message to supervisor processor **1800**. Upon receiving **1942** the “valve power off” message, supervisor processor **1800** may deenergize **1944** relay/switch **1810** and provide **1946** a “valve power off” message to command processor **1802**.

(629) Upon receiving **1948** the “valve power off” message, command processor **1802** may provide **1950** a “valve close power request” message to supervisor processor **1800**. Upon receiving **1952** the “valve close power request” message, supervisor processor **1800** may energize **1954** relay/switch **1810** (thus energizing shape memory actuator **652**) and may send **1956** a “power on” message to command processor **1802**. Upon receiving **1958** the “power on” message, command processor **1802** may actuate **1960** an energizing relay/switch (not shown) that is configured to energize shape memory actuator **652**, during which time supervisor processor **1800** may monitor **1962** the actuation of e.g., shape memory actuator **652**.

(630) As discussed above (and referring temporarily to FIGS. **26A**, **26B**, **27A**, **27B** & **28**), shape memory actuator **652** may be anchored on a first end using electrical contact **654**. The other end of shape memory actuator **652** may be connected to bracket assembly **656**. When shape memory actuator **652** is activated, shape memory actuator **652** may pull bracket assembly **656** forward and release valve assembly **634**. As such, measurement valve assembly **610** may be activated via shape memory actuator **632**. Once measurement valve assembly **610** has been activated, bracket assembly **656** may automatically latch valve assembly **610** in the activated position. Actuating shape memory actuator **652** may pull bracket assembly **656** forward and release valve assembly **634**. Assuming shape memory actuator **632** is no longer activated, measurement valve assembly **610** may move to a de-activated state once bracket assembly **656** has released valve assembly **634**. Accordingly, by actuating shape memory actuator **652**, measurement valve assembly **610** may be deactivated.

(631) Once actuation of shape memory actuator **652** is complete, command processor **1802** may provide **1964** a “power off” message to supervisor processor **1800**. Upon receiving **1966** the “power off” message, supervisor processor **1800** may deenergize **1968** relay/switch **1810** and may provide **1970** a “power off” message to command processor **1802**. Upon receiving **1972** the “power off” message, command processor **1802** may determine the quantity of infusible fluid within volume sensor chamber **620**, thus allowing command processor **1802** to compare this measured quantity to the quantity determined above (in step **1924**) to determine **1974** the quantity of infusible fluid delivered to the user.

(632) In the event that the quantity of infusible fluid delivered **1974** to the user is less than the quantity of infusible fluid specified for the basal/bolus infusion event, the above-described procedure may be repeated (via loop **1976**).

(633) Referring also to FIG. **118**, there is shown another illustrative example of the interaction amongst processors **1800**, **1802**, this time during the scheduling of a dose of infusible fluid. Command processor **1802** may monitor **2000**, **2002** for the receipt of a basal scheduling message or a bolus request message (respectively). Upon receipt **2000**, **2002** of either of these messages,

command processor **1802** may set **2004** the desired delivery volume and may provide **2006** a “delivery request” message to supervisor processor **1800**. Upon receiving **2008** the “delivery request” message, supervisor processor **1800** may verify **2010** the volume defined **2004** by command processor **1802**. Once verified **2010**, supervisor processor **1800** may provide **2012** a “delivery accepted” message to command processor **1802**. Upon receipt **2014** of the “delivery accepted” message, command processor **1802** may update **2016** the controller (e.g., the controller discussed above and illustrated in FIG. **110**) and execute **2018** delivery of the basal/bolus dose of infusible fluid. Command processor **1808** may monitor and update **2022** the total quantity of infusible fluid delivered to the user (as discussed above and illustrated in FIGS. **117A-117B**). Once the appropriate quantity of infusible fluid is delivered to the user, command processor **1802** may provide **2024** a “delivery done” message to supervisor processor **1800**. Upon receipt **2026** of the “delivery done” message, supervisor processor **1800** may update **2028** the total quantity of infusible fluid delivered to the user. In the event that the total quantity of infusible fluid delivered **2018** to the user is less than the quantity defined above (in step **2004**), the infusion process discussed above may be repeated (via loop **2030**).

(634) Referring also to FIG. **119**, there is shown an example of the manner in which supervisor processor **1800** and command processor **1802** may interact while effectuating a volume measurements via volume sensor assembly **148** (as described above).

(635) Specifically, command processor **1802** may initialize **2050** volume sensor assembly **148** and begin collecting **2052** data from volume sensor assembly **148**, the process of which may be repeated for each frequency utilized in the above-described sine sweep. Each time that data is collected for a particular sweep frequency, a data point message may be provided **2054** from command processor **1802**, which may be received **2056** by supervisor processor **1800**.

(636) Once data collection **2052** is completed for the entire sine sweep, command processor **1802** may estimate **2058** the volume of infusible fluid delivered by infusion pump assembly **100**. Command processor **1802** may provide **2060** a volume estimate message to supervisor processor **1800**. Upon receiving **2062** this volume estimate message, supervisor processor **1800** may check (i.e., confirm) **2064** the volume estimate message. Once checked (i.e., confirmed), supervisor processor **1800** may provide **2066** a verification message to command processor **1802**. Once received **2068** from supervisor processor **1800**, command processor **1802** may set the measurement status for the dose of infusible fluid delivered by volume sensor assembly **148**.

(637) As discussed above and referring temporarily to FIG. **11**, the various embodiments of the infusion pump assembly (e.g., infusion pump assembly **100**, **100'**, **400**, **500**) discussed above may be configured via a remote control assembly **300**. When configurable via remote control assembly **300**, the infusion pump assembly may include telemetry circuitry (not shown) that allows for communication (e.g., wired or wireless) between the infusion pump assembly and e.g., remote control assembly **300**, thus allowing remote control assembly **300** to remotely control the infusion pump assembly. Remote control assembly **300** (which may also include telemetry circuitry (not shown) and may be capable of communicating with the infusion pump assembly) may include display assembly **302** and input assembly **304**. Input assembly **304** may include slider assembly **306** and switch assemblies **308**, **310**. In other embodiments, the input assembly may include a jog wheel, a plurality of switch assemblies, or the like. Remote control assembly **300** may allow the user to program basal and bolus delivery events.

(638) Remote control assembly **300** may include two processors, one processor (e.g., which may include, but is not limited to a CC2510 microcontroller/RF transceiver, available from Chipcon AS, of Oslo, Norway) may be dedicated to radio communication, e.g., for communicating with infusion pump assembly **100**, **100'**, **400**, **500**. The second processor included within remote control assembly (which may include but are not limited to an ARM920T and an ARM922T manufactured by ARM Holdings PLC of the United Kingdom) may be a command processor and may perform data processing tasks associated with e.g., configuring infusion pump assembly **100**, **100'**, **400**, **500**.

(639) Further and as discussed above, one embodiment of electrical control assembly **816** may include three microprocessors. One processor (e.g., which may include, but is not limited to a CC2510 microcontroller/RF transceiver, available from Chipcon AS, of Oslo, Norway) may be dedicated to radio communication, e.g., for communicating with a remote control assembly **300**. Two additional microprocessors (e.g., supervisor processor **1800** and command processor **1802**) may effectuate the delivery of the infusible fluid (as discussed above). Examples of supervisor processor **1800** and command processor **1802** may include, but is not limited to an MSP430 microcontroller, available from Texas Instruments Inc. of Dallas, Texas.

(640) The OS may be a non-preemptive scheduling system, in that all tasks may run to completion before the next task is allowed to run regardless of priority. Additionally, context switches may not be performed. When a task completes executing, the highest priority task that is currently scheduled to run may then be executed. If no tasks are scheduled to execute, the OS may place the processor (e.g., supervisor processor **1800** and/or command processor **1802**) into a low power sleep mode and may wake when the next task is scheduled. The OS may only be used to manage main loop code and may leave interrupt-based functionality unaffected.

(641) The OS may be written to take advantage of the C++ language. Inheritance as well as virtual functions may be key elements of the design, allowing for easy creation, scheduling and managing of tasks.

(642) At the base of the OS infrastructure may be the ability to keep track of system time and controlling the ability to place the processor in Low Power Mode (LPM; also known as sleep mode). This functionality along with the control and configuration of all system clocks may be encapsulated by the SysClocks class.

(643) The SysClocks class may contain the functionality to place the processor (e.g., supervisor processor **1800** and/or command processor **1802**) into LPM to reduce energy consumption. While in LPM, the slow real time clock may continue to run while the fast system clock that runs the CPU core and most peripherals may be disabled.

(644) Placing the processor into LPM may always be done by the provided SysClocks function. This function may contain all required power down and power up sequences resulting in consistency whenever entering or exiting LPM. Waking from LPM may be initiated by any interrupts based on the slow clock.

(645) The OS may keep track of three aspects of time: seconds, milliseconds and the time of day. Concerning seconds, SysClocks may count seconds starting when the processor comes out of reset. The second counter may be based on the slow system clocks and, therefore, may increment regardless of whether the processor is in LPM or at full power. As a result, it is the boundary at which the processor may wake from sleep to execute previously scheduled tasks. If a task is scheduled to run immediately from an

interrupt service routine (ISR), the ISR may wake the processor from LPM on exit and the task may be executed immediately. Concerning milliseconds, in addition to counting the seconds since power on, SysClocks may also count milliseconds while the processor is in full power mode. Since the fast clock is stopped during LPM, the millisecond counter may not increment. Accordingly, whenever a task is scheduled to execute based on milliseconds, the processor may not enter LPM. Concerning time of day, the time of day may be represented within SysClocks as seconds since a particular point time (e.g., seconds since 1 Jan. 2004).

(646) The SysClocks class may provide useful functionality to be used throughout the Command and Supervisor project code base. The code delays may be necessary to allow hardware to settle or actions to be completed. SysClocks may provide two forms of delays, a delay based on seconds or a delay based on milliseconds. When a delay is used, the processor may simply wait until the desired time has passed before continue with its current code path. Only ISRs may be executed during this time. SysClocks may provide all of the required functionality to set or retrieve the current time of day.

(647) The word “task” may be associated with more complex scheduling systems; therefore within the OS, task may be represented by and referred to as Managed Functions. The ManagedFunc class may be an abstract base class that provides all the necessary control members and functionality to manage and schedule the desired functionality.

(648) The ManagedFunc base class may have five control members, two scheduling manipulation member functions, and one pure virtual execute function that may contain the managed functionality. All of the ManagedFunc control members may be hidden from the derived class and may only be directly set by the derived class during creation, thus simplifying the use and enhancing the safety of infusion pump assembly **100, 100', 400, 500**.

(649) The Function ID may be set at the time of creation and may never be changed. All Function IDs may be defined within a single .h file, and the base ManagedFunc constructor may strongly enforce that the same ID may not be used for more than one managed function. The ID may also define the priority of a function (with respect to other functions) based upon the function ID assigned, wherein higher priority functions are assigned lower function IDs. The highest priority task that is currently scheduled to execute may execute before lower priority tasks.

(650) All other control members may be used to represent the function's current scheduled state, when it should be executed, and if (upon execution) the function should be rescheduled to execute in a previously set amount of time. Manipulation of these controls and states may be allowed but only through the public member functions (thus enforcing safety controls on all settings).

(651) To control the scheduling of a managed function, the set start and set repeat functions may be used. Each of these member functions may be a simple interface allowing the ability to configure or disable repeat settings as well as control whether a managed function is inactive, scheduled by seconds, milliseconds, or time of day.

(652) Through inheritance, creating a Managed Function may be done by creating a derived class and defining the pure virtual ‘execute’ function containing the code that needs to be under scheduling control. The ManagedFunc base class constructor may be based upon the unique ID of a function, but may also be used to set default control values to be used at start up.

(653) For example to create a function that runs thirty seconds after start up and every 15 seconds thereafter, the desired code is placed into the virtual execute function and the function ID, scheduled by second state, thirty second start time, and repeat setting of fifteen seconds is provided to the constructor.

(654) The following is an illustrative code example concerning the creation of a managed function. In this particular example, a “heartbeat” function is created that is scheduled to execute for the first time one second after startup of infusion pump assembly **100, 100', 400, 500** and execute every ten seconds thereafter:

```
(655) TABLE-US-00011 #include "ManagedFunc.h" // The SendGoodFunc is a “heartbeat” status message class SendGoodFunc :
public ManagedFunc { public: // Initialize the managed func to run 2 seconds after start up // and repeat every second.
SendGoodFunc( ) : ManagedFunc(IPC_SEND_GOOD, SCHEDULED_SEC, 1, true, 10) { }; ~SendGoodFunc( ) { };
protected: void execute(void); }; void SendGoodFunc::execute(void) { // << code to send the heartbeat >> }
SendGoodFunc g_sendGoodFunc; // to manipulate the heartbeat timing simply call: // g_sendGoodFunc.setFuncStart(...) or
g_sendGoodFunc.setRepeat( ... )
```

(656) The actual execution of the Managed Functions may be controlled and performed by the SleepManager class. The SleepManager may contain the actual prioritized list of managed functions. This prioritized list of functions may automatically be populated by the managed function creation process and may ensure that each function is created properly and has a unique ID.

(657) The main role of the SleepManager class may be to have its ‘manage’ function called repeatedly from the processors main loop and/or from a endless while loop. Upon each call of manage, the SleepManager may execute all functions that are scheduled to run until the SleepManager has exhausted all scheduled functions; at which time the SleepManager may place the processor in LPM. Once the processor wakes from LPM, the manage function may be reentered until the processor is again ready to enter LPM (this process may be repeated until stopped, e.g., by a user or by the system).

(658) If the processor has to be kept in full power mode for an extended period of time (e.g., while an analog-to-digital conversion is being sampled), the SleepManager may provide functionality to disable entering LPM. While LPM is disabled, the manage function may continuously search for a scheduled task.

(659) The SleepManager may also provide an interface to manipulate the scheduling and repeat settings of any managed function through the use of the unique ID of the function, which may allow any section of code to perform any required scheduling without having direct access to or unnecessary knowledge of the desired ManagedFunc object.

(660) Radio circuitry included within each of infusion pump assembly **100, 100', 400, 500** and remote control assembly **300** may effectuate wireless communication between remote control assembly **300** and infusion pump assembly **100, 100', 400, 500**. A 2.4 GHz radio communications chip (e.g., a Texas Instruments CC2510 radio transceiver) with an internal 8051 microcontroller may be used for radio communications.

(661) The radio link may balance the following three objectives: link availability; latency; and energy.

(662) Concerning link availability, remote control assembly **300** may provide the primary means for controlling the infusion pump assembly **100, 100', 400, 500** and may provide detailed feedback to the user via the graphical user interface (GUI) of remote

control assembly **300**. Concerning latency, the communications system may be designed to provide for low latency to deliver data from remote control assembly **300** to the infusion pump assembly **100, 100', 400, 500** (and vice versa). Concerning energy, both remote control assembly **300** and infusion pump assembly **100, 100', 400, 500** may have a maximum energy expenditure for radio communications.

(663) The radio link may support half-duplex communications. Remote control assembly **300** may be the master of the radio link, initiating all communications. Infusion pump assembly **100, 100', 400, 500** may only respond to communications and may never initiate communications. The use of such a radio communication system may provide various benefits, such as: increased security; a simplified design (e.g., for airplane use); and coordinated control of the radio link.

(664) Referring also to FIG. **120A**, there is shown one illustrative example of the various software layers of the radio communication system discussed above.

(665) The radio processors included within remote control assembly **300** and infusion pump assembly **100, 100', 400, 500** may transfer messaging packets between an SPI port and a 2.4 GHz radio link (and vice versa). The radio may always be the SPI slave. On infusion pump assembly **100, 100', 400, 500**, radio processor (PRP) **1818** (See FIGS. **115-116**) may service two additional nodes over the SPI port that are upstream (namely command processor **1800** and supervisor processor **1802**. In some embodiments, on remote control assembly **300**, the radio processor (CRP) may service at least one additional node over the SPI port that may be either upstream or down stream, for example, in some embodiments, the above-described remote control processor (UI) and the Continuous Glucose Engine (CGE).

(666) A messaging system may allow for communication of messages between various nodes in the network. The UI processor of remote control assembly **300** and e.g., supervisor processor **1800** may use the messaging system to configure and initiate some of the mode switching on the two system radios. It may be also used by the radios to convey radio and link status information to other nodes in the network.

(667) When the radio of remote control assembly **300** wishes to gather channel statistics from the infusion pump assembly **100, 100', 400, 500** or update the master channel list of the radio of infusion pump assembly **100, 100', 400, 500**, the radio of remote control assembly **300** may use system messages. Synchronization for putting the new updated list into effect may use flags in the heartbeat messages to remove timing uncertainty.

(668) The radio communication system may be written in C++ to be compatible with the messaging software. A four byte radio serial number may be used to address each radio node. A hash table may be used to provide a one-to-one translation between the device “readable” serial number string and the radio serial number. The hash table may provide a more randomized 8-bit logical address so that pumps (e.g., infusion pump assembly **100, 100', 400, 500**) or controllers with similar readable serial numbers are more likely to have unique logical addresses. Radio serial numbers may not have to be unique between pumps (e.g., infusion pump assembly **100, 100', 400, 500**) and controllers due to the unique roles each has in the radio protocol.

(669) The radio serial number of remote control assembly **300** and the radio serial number of infusion pump assembly **100, 100', 400, 500** may be included in all radio packets except for the RF Pairing Request message that may only include the radio serial number of remote control assembly **300**, thus ensuring that only occur with the remote control assembly/infusion pump assembly to which it is paired. The CC2510 may support a one byte logical node address and it may be advantageous to use one byte of the radio serial number as the logical node address to provide a level of filtering for incoming packets.

(670) The Quiet_Radio signal may be used by the UI processor of remote control assembly **300** to prevent noise interference on the board of remote control assembly **300** by other systems on the board. When Quiet_Radio is asserted, the radio application of remote control assembly **300** may send a message to the radio of infusion pump assembly **100, 100', 400, 500** asserting Radio Quiet Mode for a pre-determined period of time. The Quiet_Radio feature may not be required based on noise interference levels measured on the PC board of remote control assembly **300**. During this period of time, the radio of remote control assembly **300** may stay in Sleep Mode 2 for up to a maximum of 100 ms. The radio of remote control assembly **300** may come out of Sleep Mode 2 when the Quiet_Radio signal is de-asserted or the maximum time period has expired. The UI processor of remote control assembly **300** may assert Quiet_Radio at least one radio communication's interval before the event needs to be asserted. The radio of remote control assembly **300** may inform the radio of infusion pump assembly **100, 100', 400, 500** that communications will be shutdown during this quiet period. The periodic radio link protocol may have status bits/bytes that accommodate the Quiet_Radio feature unless Quiet_Radio is not required.

(671) The radio software may integrate with the messaging system and radio bootloader on the same processor, and may be verified using a throughput test. The radio software may integrate with the messaging system, SPI Driver using DMA, and radio bootloader, all on the same processor (e.g., the TI CC2510).

(672) The radio of remote control assembly **300** may be configured to consume no more than 32 mAh in three days (assuming one hundred minutes of fast heartbeat mode communications per day). The radio of infusion pump assembly **100, 100', 400, 500** may be configured to consume no more than 25 mAh in three days (assuming one hundred minutes of fast heartbeat mode communications per day).

(673) The maximum time to reacquire communications may be <6.1 seconds including connection request mode and acquisition mode. The radio of remote control assembly **300** may use the fast heartbeat mode or slow heartbeat mode setting to its advantage in order to conserve power and minimize latency to the user. The difference between the infusion pump assembly **100, 100', 400, 500** and remote control assembly **300** entering acquisition mode may be that the infusion pump assembly **100, 100', 400, 500** needs to enter acquisition mode often enough to ensure communications may be restored within the maximum latency period. However, the remote control assembly **300** may change how often to enter acquisition mode with the infusion pump assembly **100, 100', 400, 500** when in slow heartbeat mode and heartbeats are lost. The radio of remote control assembly **300** may have knowledge of the user GUI interaction, but the infusion pump assembly **100, 100', 400, 500** may not.

(674) The radio of remote control assembly **300** may set the heartbeat period for both radios. The period may be selectable in order to optimize power and link latency depending on activity. The desired heartbeat period may be communicated in each heartbeat from the radio of remote control assembly **300** to the radio of infusion pump assembly **100, 100', 400, 500**. This may not

exclusively establish the heartbeat rate of infusion pump assembly **100, 100', 400, 500** due to other conditions that determine what mode to be in. When in fast heartbeat mode, the radio of remote control assembly **300** may set the heartbeat period to 20 ms if data packets are available to send or receive, thus providing low link latency communications when data is actively being exchanged.

(675) When in fast heartbeat mode, the radio of remote control assembly **300** may set the heartbeat period to 60 ms four heartbeats after a data packet was last exchanged in either direction on the radio. Keeping the radio heartbeat period short after a data packet has been sent or received may assure that any data response packet may be also serviced using a low link latency. When in slow heartbeat mode, the heartbeat rate may be 2.00 seconds or 6.00 second, depending upon online or offline status respectively.

(676) The infusion pump assembly **100, 100', 400, 500** may use the heartbeat rate set by the radio of remote control assembly **300**. The radio of remote control assembly **300** may support the following mode requests via the messaging system: Pairing Mode Connection Mode Acquisition Mode (includes the desired paired infusion pump assembly **100, 100', 400, 500** radio serial number) Sync Mode—Fast Heartbeat Sync Mode—Slow Heartbeat RF Off Mode

(677) The radio of infusion pump assembly **100, 100', 400, 500** may support the following mode requests via the messaging system: Pairing Mode Acquisition Mode RF Off Mode

(678) The radio may use a system message to obtain the local radio serial number. On remote control assembly **300**, the radio may get the serial number from the UI processor of remote control assembly **300**. The radio may use a system message to store the paired radio serial number.

(679) Remote control assembly **300** and the radio of infusion pump assembly **100, 100', 400, 500** may issue a status message using the messaging system to the UI processor of remote control assembly **300** and command processor **1802** whenever the following status changes: Online Fast: Successful connection Online Fast: Change from Acquisition Mode to Fast Heartbeat Mode Online Slow: Successful request change from Fast Heartbeat to Slow Heartbeat Offline: Automatic change to Search Sync mode due to lack of heartbeat exchanges. Online Fast: Successful request change from Slow Heartbeat to Fast Heartbeat Offline: Bandwidth falls below 10% in Sync Mode Online: Bandwidth rises above 10% in Search Sync mode Offline: Successful request change to RF Off Mode

(680) The radio configuration message may be used to configure the number of radio retries. This message may be sent over the messaging system. The UI processor of remote control assembly **300** will send this command to both the radio of remote control assembly **300** and the radio of infusion pump assembly **100, 100', 400, 500** to configure these radio settings.

(681) There may be two parameters in the radio configuration message: namely the number of RF retries (e.g., the value may be from 0 to 10); and the radio offline parameters (e.g., the value may be from 1 to 100 in percent of bandwidth).

(682) The radio application on both the remote control assembly **300** and infusion pump assembly **100, 100', 400, 500** may have an API that allows the messaging system to configure the number of RF retries and radio offline parameters.

(683) The following parameters may be recommended for the radio hardware configuration: Base Radio Specifications MSK 250 kbps over air baud rate Up to 84 channels Channel spacing 1000 kHz Filter bandwidth 812 kHz No Manchester encoding Data whitening 4 byte preamble 4 byte sync (word) CRC appended to packet LQI (Link Quality Indicator) appended to packet Automatic CRC filtering enabled

(684) Forward Error Correction (FEC) may or may not be utilized. Although Forward Error Correction (FEC) may be used to increase the effective signal dynamic range by approximately 3 dB, FEC requires fixed packet sizes and doubles the number of over the air bits for the same fixed size message.

(685) The radio may function within 1.83 meters distance under nominal operating conditions (except in pairing mode). It may be a goal that the radio function within 7.32 meters distance under nominal operating conditions. The transmit power level may be 0 dBm (except in pairing mode) and the transmit power level in pairing mode may be -22 dBm. Since the desired radio node address of infusion pump assembly **100, 100', 400, 500** may be not known by the remote control assembly **300** in pairing mode, both infusion pump assembly **100, 100', 400, 500** and remote control assembly **300** may use a lower transmit power to reduce the likelihood of inadvertently pairing with another infusion pump assembly.

(686) AES Encryption may be used for all packets but may not be required, as the Texas Instruments CC2510 radio transceiver includes this functionality. If AES encryption is used, fixed keys may be utilized, as fixed keys provide a quick way to enable encryption without passing keys. However, key exchange may be provided for in future versions of infusion pump assembly **100, 100', 400, 500**. The fixed keys may be contained in one separate header source file with no other variables but the fixed keys data, thus allowing for easier management of read access of the file.

(687) The radio software may support the following eight modes: Pairing Mode RF Off Mode Connection Mode Acquisition Mode Fast Heartbeat Mode Slow Heartbeat Mode Search Sync Mode Sync'ed Acquisition Mode which are graphically depicted in FIGS. **120B-120C**.

(688) Pairing may be the process of exchanging radio serial numbers between remote control assembly **300** and infusion pump assembly **100, 100', 400, 500**. Remote control assembly **300** may be “paired” with infusion pump assembly **100, 100', 400, 500** when infusion pump assembly **100, 100', 400, 500** knows its serial number. Infusion pump assembly **100, 100', 400, 500** may be “paired” with remote control assembly **300** when remote control assembly **300** knows its serial number.

(689) Pairing mode (which is graphically depicted in FIG. **120D**) may require that four messages to be exchanged over the RF link: RF Pairing Request (broadcast from Remote control assembly **300** to any Infusion pump assembly **100, 100', 400, 500**) RF Pairing Acknowledge (from Infusion pump assembly **100, 100', 400, 500** to Remote control assembly **300**) RF Pairing Confirm Request (from Remote control assembly **300** to Infusion pump assembly **100, 100', 400, 500**) RF Pairing Confirm Acknowledge (from Infusion pump assembly **100, 100', 400, 500** to Remote control assembly **300**)

(690) Additionally, remote control assembly **300** may cancel the pairing process at any time via the RF pairing abort message (from remote control assembly **300** to infusion pump assembly **100, 100', 400, 500**. Pairing mode may not support messaging system data transfers.

(691) The radio of infusion pump assembly **100, 100', 400, 500** may enter pairing mode upon receiving a pairing mode request

message. It may be the responsibility of supervisor processor **1800** on infusion pump assembly **100, 100', 400, 500** to request the radio to enter pairing mode if there is no disposable attached to infusion pump assembly **100, 100', 400, 500** and the user has pressed the button of infusion pump assembly **100, 100', 400, 500** for six seconds. The radio of infusion pump assembly **100, 100', 400, 500** may set the appropriate transmit power level for pairing mode. Infusion pump assembly **100, 100', 400, 500** may only be paired with one remote control assembly **300** at a time.

(692) Upon receiving the first valid RF pairing request message while in pairing mode, the radio of infusion pump assembly **100, 100', 400, 500** may use the serial number of remote control assembly **300** for the duration of pairing mode and respond with an RF pairing acknowledge message containing the radio serial number infusion pump assembly **100, 100', 400, 500**.

(693) The radio of infusion pump assembly **100, 100', 400, 500** may timeout of pairing mode automatically after 2.0 ± 0.2 seconds if no RF pairing request is received. The radio of infusion pump assembly **100, 100', 400, 500** may issue a pairing request received message after transmitting the RF pairing acknowledge. This message to supervisor processors will allow feedback to the user during the pairing confirm process. The radio of infusion pump assembly **100, 100', 400, 500** may automatically timeout of pairing mode in 1.0 ± 0.1 minutes after sending an RF pairing acknowledge unless an RF pairing confirm request is received. The radio of infusion pump assembly **100, 100', 400, 500** may issue a store paired radio serial number message if an RF pairing confirm request message is received after receiving a RF pairing request message. This action may store the radio serial number of remote control assembly **300** in the non-volatile memory of infusion pump assembly **100, 100', 400, 500** and may overwrite the existing pairing data for the infusion pump assembly **100, 100', 400, 500**.

(694) The radio of infusion pump assembly **100, 100', 400, 500** may transmit an RF pairing confirm acknowledge and exit pairing mode after the acknowledgment from the store paired radio serial number message is received. This may be the normal exit of pairing mode on infusion pump assembly **100, 100', 400, 500** and may result in infusion pump assembly **100, 100', 400, 500** powering down until connection mode or pairing mode entered by the user.

(695) If the radio of infusion pump assembly **100, 100', 400, 500** exits pairing mode upon successfully receiving a pairing confirm request message, then the radio of infusion pump assembly **100, 100', 400, 500** may revert to the newly paired remote control assembly **300** and may send a pairing completion success message to command processor **1802**. The radio of infusion pump assembly **100, 100', 400, 500** may exit pairing mode upon receiving an RF pairing abort message. The radio of infusion pump assembly **100, 100', 400, 500** may exit pairing mode upon receiving a pairing abort request message addressed to it. This may allow command processor **1802** or supervisor processor **1800** to abort the pairing process locally on the infusion pump assembly **100, 100', 400, 500**.

(696) The radio of remote control assembly **300** may enter pairing mode upon receiving a pairing mode request message. It may be the responsibility of the UI processor of remote control assembly **300** to request that the radio enter pairing mode under the appropriate conditions. The radio of remote control assembly **300** may set the appropriate transmit power level for pairing mode. The radio of remote control assembly **300** may transmit RF pairing requests until an RF pairing acknowledge is received or pairing is aborted.

(697) The radio of remote control assembly **300** may automatically abort pairing mode if the RF pairing acknowledge message is not received within 30.0 ± 1.0 seconds after entering pairing mode. Upon receiving the first valid RF pairing acknowledge message while in pairing mode, the radio of remote control assembly **300** may send a pairing success message to the UI processor of remote control assembly **300** that includes the serial number of infusion pump assembly **100, 100', 400, 500** and may use that serial number for the duration of pairing mode. This message may provide a means for the UI processor of remote control assembly **300** to have the user confirm the serial number of the desired infusion pump assembly **100, 100', 400, 500**. If the radio of remote control assembly **300** receives multiple responses (concerning a single pairing request) from infusion pump assembly **100, 100', 400, 500**, the first valid one may be used.

(698) The Radio of remote control assembly **300** may only accept an RF pairing confirm acknowledge messages after an RF pairing acknowledge is received while in pairing mode. The radio of remote control assembly **300** may transmit the RF pairing confirm message upon receiving a pair confirm request message from the UI processor of remote control assembly **300**.

(699) The radio of remote control assembly **300** may check that infusion pump assembly **100, 100', 400, 500** confirms the pairing before adding infusion pump assembly **100, 100', 400, 500** to the pairing list. The radio of remote control assembly **300** may issue a store paired radio serial number message if an RF pairing complete message is received. This action may allow the UI processor of remote control assembly **300** to store the new serial number of infusion pump assembly **100, 100', 400, 500** and provide user feedback of a successful pairing. It may be the responsibility of the UI processor of remote control assembly **300** to manage the list of paired infusion pump assemblies.

(700) The radio of remote control assembly **300** may send an RF pairing abort message and exit pairing mode upon receiving a pairing abort request message. This may allow the UI processor of the remote control assembly **300** to abort the pairing process on both the remote control assembly **300** and acknowledged infusion pump assembly **100, 100', 400, 500**.

(701) In connection request mode, the radio of remote control assembly **300** may attempt to acquire each infusion pump assembly **100, 100', 400, 500** in its paired infusion pump assembly list and retrieve its "connection ready" status. The "connection" process (which is graphically depicted in FIG. 120E) may allow remote control assembly **300** to quickly identify one of its paired infusion pump assemblies that may be ready to be used. The radio of remote control assembly **300** may be capable of performing the connection request mode with up to six paired infusion pump assemblies. Connection request mode may be only supported on remote control assembly **300** and may be a special form of acquisition mode. In connection request mode, remote control assembly **300** may connect with the first infusion pump assembly to respond. However, each message may be directed to a specific infusion pump assembly serial number.

(702) The radio of remote control assembly **300** may obtain the latest paired infusion pump assembly serial number list upon entering connection mode. The radio of remote control assembly **300** may enter connection mode upon receiving a connection mode request message. It may be the responsibility of the UI processor of remote control assembly **300** to request that the radio enter connection mode when it desires communications with a paired infusion pump assembly. The radio of remote control

assembly **300** may issue a connection assessment message to the UI processor of remote control assembly **300** containing the radio serial number of the first infusion pump assembly, if any, that is “connection ready”. The radio of remote control assembly **300** may generate the connection assessment message within thirty seconds of entering connection request mode. The radio of remote control assembly **300** may exit connection request mode upon receipt of the connection assessment acknowledgement and transition to fast heartbeat mode. The radio of remote control assembly **300** may exit connection request mode upon receipt of a connection request abort message from the UI processor of remote control assembly **300**.

(703) On remote control assembly **300**, acquisition mode may be used to find a particular paired infusion pump assembly. The radio of remote control assembly **300** may send RF RUT (aRe yoU There) packets to the desired paired infusion pump assembly. If the infusion pump assembly receives the RF RUT message, it may respond to the radio of remote control assembly **300**. Multiple channels may be used in the acquisition mode algorithm to improve the opportunity for the radio of remote control assembly **300** to find the paired infusion pump assembly.

(704) The radio of remote control assembly **300** may enter acquisition mode upon receiving an acquisition mode request or fast heartbeat mode request message while in RF Off Mode. The radio of remote control assembly **300** may enter sync'ed acquisition mode upon receiving an acquisition mode request or fast heartbeat mode request message while in search sync mode. It may be the responsibility of the UI processor of remote control assembly **300** to request that the radio enter acquisition mode when the RF link is off-line and remote control assembly **300** desires communications with infusion pump assembly **100, 100', 400, 500**.

(705) The radio of remote control assembly **300** may only communicate with one paired infusion pump assembly **100, 100', 400, 500** (except in pairing and connection modes). When communications are lost, the UI processor of remote control assembly **300** may use acquisition mode (at some periodic rate limited by the power budget) to attempt to restore communications.

(706) Infusion pump assembly **100, 100', 400, 500** may enter acquisition mode under the following conditions: When in Radio Off Mode and Acquisition Mode may be requested When Search Sync Mode times out due to lack of heartbeats

(707) Upon entering acquisition mode, the radio of infusion pump assembly **100, 100', 400, 500** may obtain the serial number of the last stored paired remote control assembly **300**. The radio of infusion pump assembly **100, 100', 400, 500** may only communicate with the remote control assembly to which it has been “paired” (except while in the “pairing request” mode). The radio of infusion pump assembly **100, 100', 400, 500** may transition from acquisition mode to fast heartbeat mode upon successfully acquiring synchronization with the remote control assembly **300**. The acquisition mode of infusion pump assembly **100, 100', 400, 500** may be capable of acquiring synchronization within 6.1 seconds, which may implies that the infusion pump assembly **100, 100', 400, 500** may always be listening at least every ~6 seconds when in acquisition mode.

(708) Data packets may be sent between two paired devices when the two devices are in sync mode and online. The two devices may sync via a heartbeat packet before data packets are exchanged. Each radio may send data packets at known time intervals after the heartbeat exchange. The infusion pump assembly **100, 100', 400, 500** may adjust its timing to anticipate reception of a packet. The radio may support one data packet in each direction on each heartbeat. The radio may provide a negative response to a fast heartbeat mode request if the radio is offline. The radio of remote control assembly **300** may change to fast heartbeat mode if a system request for fast heartbeat mode is received while in slow heartbeat mode and the radio is online.

(709) Upon transitioning to fast heartbeat mode from acquisition mode, the radio of remote control assembly **300** may send the master channel list message. The master channel list may be built by the radio of remote control assembly **300** and sent to the radio of infusion pump assembly **100, 100', 400, 500** to allow a selection of frequency hopping channels based on historical performance. When in fast heartbeat mode or slow heartbeat mode, periodic heartbeat messages may be exchanged between the radio of remote control assembly **300** and the radio of infusion pump assembly **100, 100', 400, 500**. The periodicity of these messages may be at the heartbeat rate. The heartbeat messages may allow data packet transfers to take place and may also exchange status information. The two radios may exchange the following status information: Quiet Mode, data availability, buffer availability, heartbeat rate, and prior channel performance. It may be a goal to keep the packet size of the heartbeat messages small in order to conserve power. The radio may provide for a maximum data packet size of eighty-two bytes when in Sync Mode. The messaging system may be designed to support packet payload sizes up to sixty-four bytes. This maximum size was selected as an optimal trade-off between minimum messages types and non-fragmented messages. The eighty-two bytes may be the maximum packet size of the messaging system including packet overhead.

(710) The messaging system has an API that may allow the radio protocol to send an incoming radio packet to it. The messaging system may also have an API that allows the radio protocol to get a packet for transmission over the radio network. The messaging system may be responsible for packet routing between the radio protocol and the SPI port. Data packets may be given to the messaging system for processing. The messaging system may have an API that allows the radio protocol to obtain a count of the number of data packets waiting to be sent over the radio network. The radio protocol may query the messaging system on each heartbeat to determine if data packets are available to send over the radio network. It may be desirable for the software to check the availability of a message just before the heartbeat is sent to minimize round trip message latency.

(711) The radio protocol may be capable of buffering one incoming radio data packet and passing the packet to the messaging system. The radio protocol may send the data packet to the messaging system upon receipt of the data packet. The message system may be responsible for routing radio data packets to the proper destination node. The radio protocol may be capable of buffering one packet from the messaging system.

(712) The radio protocol may be responsible for acknowledging receipt of valid data packets over the RF link via an RF ACK reply packet to the sending radio. The RF ACK packet may contain the source and destination radio serial numbers, RF ACK command identification, and sequence number of the data packet being acknowledged.

(713) The radio transmitting a radio data packet may retransmit that radio data packet on the next heartbeat with the same sequence number if an RF ACK is not received and the retry count is within the maximum RF retries allowed. It may be expected that, from time to time, interference will corrupt a transmission on a particular frequency. An RF retry allows the same packet to be retransmitted at the next opportunity at a different frequency. The sequence number provides a means of uniquely identifying the packet over a short time window. The number of radio packet retries may be configurable using the radio configuration

command. Allowing more retries may increase the probability of a packet being exchanged but introduces more latency for a round trip messages. The default number of radio retries at power up may be ten (i.e., the maximum transmission attempts before dropping the message).

(714) A one byte (modulo 256) radio sequence number may be included in all radio data packets over the RF link. Since the radio may be responsible for retrying data packet transmission if not acknowledged, the sequence number may provide a way for the two radios to know if a data packet is a duplicate. The transmitted sequence number may be incremented for each new radio data packet and may be allowed to rollover. When a data packet is successfully received with the same sequence number as the previous successfully received data packet (and in the same direction), the data packet may be ACK'd and the received data packet discarded. This may remove duplicate packets generated by the RF protocol before they are introduced into the network. Note that it may be possible that multiple data packets in a row may need to be dropped with the same sequence number under extreme situations.

(715) If a heartbeat is missed, the radio of remote control assembly **300** and the radio of infusion pump assembly **100, 100', 400, 500** may attempt to send and listen respectively for subsequent heartbeats. The radio of remote control assembly **300** and the radio of infusion pump assembly **100, 100', 400, 500** may automatically change from fast heartbeat mode or slow heartbeat mode to search sync mode if heartbeats are missed for two seconds. This may minimize power consumption when the link is lost by allowing the radios to continue to use their synchronization information, as two seconds allows sufficient time to hop through all channels.

(716) The radio may be considered online while in the following modes: Fast Heartbeat mode Slow Heartbeat mode

(717) as these are the only conditions where messaging system traffic may be exchanged. All other conditions may be considered offline.

(718) The radio may initialize to radio off mode at the start of code execution from reset. When code first executes on the radio processor, the initial state may be the radio off mode to allow other processors to perform self-tests before requesting the radio to be active. This requirement does not intend to define the mode when waking from sleep mode. The radio may cease RF communications when set to radio off mode. On remote control assembly **300**, this mode may be intended for use on an airplane to suppress RF emissions. Since infusion pump assembly **100, 100', 400, 500** only responds to transmissions from remote control assembly **300** (which will have ceased transmitting in airplane mode), radio off mode may only be used on infusion pump assembly **100, 100', 400, 500** when charging.

(719) Command processor **1802** may be informed of airplane mode and that, therefore, the RF was intentionally turned off on remote control assembly **300** so that it does not generate walk-away alerts. However, this may be completely hidden from the radio of infusion pump assembly **100, 100', 400, 500**.

(720) The radio of remote control assembly **300** and the radio of infusion pump assembly **100, 100', 400, 500** may periodically attempt to exchange heartbeats in order to reestablish data bandwidth while in search sync mode. The radio of remote control assembly **300** may transition to radio off mode after twenty minutes of search sync mode with no heartbeats successfully exchanged.

(721) The radio of infusion pump assembly **100, 100', 400, 500** may transition to acquisition mode after twenty minutes of search sync mode with no heartbeats successfully exchanged. Listening during pre-agreed time slots may be the most efficient use of power for infusion pump assembly **100, 100', 400, 500** to re-establish the RF link. After a loss of communications, the crystal tolerance and temperature drift may make it necessary to expand the receive window of infusion pump assembly **100, 100', 400, 500** over time. Staying in search sync mode for extended periods (e.g., 5-20 minutes) after communications loss may cause the instantaneous power consumed to exceed the average power budgeted for the radio of infusion pump assembly **100, 100', 400, 500**. The radio of remote control assembly **300** may not be forced to expand its window, so staying in search sync mode may be very power efficient. Acquisition mode may consume more power for remote control assembly **300**. Twenty minutes may be used as a compromise to balance power consumption on both the radio of remote control assembly **300** and the radio of infusion pump assembly **100, 100', 400, 500**.

(722) The radio of remote control assembly **300** and the radio of infusion pump assembly **100, 100', 400, 500** may transition to slow heartbeat mode if they successfully exchange three of the last five heartbeats. Approximately every six seconds, a burst of five heartbeats may be attempted. If three of these are successful, the bandwidth may be assumed to be sufficient to transition to slow heartbeat mode. The radio of infusion pump assembly **100, 100', 400, 500** may be acquirable while in search sync mode with a latency of 6.1 seconds. This may imply that the infusion pump assembly **100, 100', 400, 500** may always be listening at least every ~6 seconds when in search sync mode.

(723) Radio protocol performance statistics may be necessary to promote troubleshooting of the radio and to assess radio performance. The following radio performance statistics may be maintained by the radio protocol in a data structure:

(724) TABLE-US-00012 NAME SIZE DESCRIPTION TX Heartbeat Count 32 Bits Total transmitted heartbeats RX Heartbeat Count 32 bits Total valid received heartbeats CRC Errors 16 bits Total packets received over the RF link which were dropped due to bad CRC. This may be a subset of RX Packets Nacked. First Retry Count 32 bits Total number of packets which were successfully acknowledged after 1 retry Second Retry Count 32 bits Total number of packets which were successfully acknowledged after 2 retries Third Retry Count 32 bits Total number of packets which were successfully acknowledged after 3 retries Fourth Retry Count 32 bits Total number of packets which were successfully acknowledged after 4 retries Fifth Retry Count 16 bits Total number of packets which were successfully acknowledged after 5 retries Sixth Retry Count 16 bits Total number of packets which were successfully acknowledged after 6 retries Seventh Retry Count 16 bits Total number of packets which were successfully acknowledged after 7 retries Eighth Retry Count 16 bits Total number of packets which were successfully acknowledged after 8 retries Ninth Retry Count 16 bits Total number of packets which were successfully acknowledged after 9 retries Tenth Retry Count 16 bits Total number of packets which were successfully acknowledged after 10 retries Dropped Retry Count 16 bits Total number of packets which were dropped after maximum retries attempts Duplicate Packet Count 16 bits Total number of received packets dropped due to duplicate packet 1 to 5 Missed Fast Mode 16 bits Count of

1 to 5 consecutive Hops missed hops in Fast mode (i.e. not received) 6 to 16 Missed Fast Mode 16 bits Count of 6 to 16 consecutive Hops missed hops in Fast mode. 17 to 33 Missed Fast Mode 16 bits Count of 17 to 33 consecutive Hops missed hops in Fast mode 34+ Missed Fast Mode Hops 16 bits Count of 34 or more consecutive missed hops in Fast mode 1 to 2 Missed Slow Mode 16 bits Count of 1 to 2 consecutive Hops missed hops in Slow mode (i.e. not received) 3 to 5 Missed Slow Mode 16 bits Count of 3 to 5 consecutive Hops missed hops in Slow mode 5 to 7 Missed Slow Mode 16 bits Count of 5 to 7 consecutive Hops missed hops in Slow mode 8+ Missed Slow Mode Hops 16 bits Count of 8 or more consecutive missed hops in Slow mode Destination Radio Serial 16 bits Count of received packets in Number Mismatch which the destination made it past the hardware filtering but does not match this radio's serial number. This may be not an error but indicates that the radio may be waking up and receiving (but not processing) packets intended for other radios Total Walkaway Time 16 bits (minutes) Total Walkaway Events 16 bits Together with total walkaway time provides an average walkaway time Number of Pairing Attempts 16 bits Total Time in Acquisition 16 bits Mode (Infusion pump assembly 100, 100', 400, 500 Only) Total Acquisition Mode 16 bits Successful Acquisition Count Attempts (Remote control 16 bits Count of transitions assembly 300 Only) from Connect or Acquisition Mode to Fast Heartbeat Mode Requested Slow Heartbeat 16 bits Mode Transitions Automatic Slow Heartbeat 16 bits Mode Transitions Radio offline messages sent 16 bits Radio online messages sent 16 bits

(725) A #define DEBUG option (compiler option may be use to gather the following additional radio performance statistics per each channel (16 bit numbers): Number of missed hops CCA good count CCA bad count Average RSSI (accumulated for good RX packets only) Dropped from Frequency Hop List count Acquisition Mode count (found pair on this channel)

(726) The debug option may be used to gather engineering only statistics. If processor performance, power, and memory allow, it may be desirable to keep this information at runtime. The radio statistics may be made available to the messaging system.

(727) Link quality may be intended to be used on remote control assembly **300** to provide a bar indicator, similar to a cell phone, of the radio link quality. Link quality may be made available to both remote control assembly **300** and infusion pump assembly **100, 100', 400, 500**. It may be anticipated that the link quality status will consist of a one byte indicator of the quality of the radio link.

(728) The radio may change frequency for each heartbeat. An adaptive pseudo random frequency hopping algorithm may be used for sync mode and heartbeat attempts in search sync mode. It may be a goal to use sixty-four channels for frequency hopping. An algorithm may be developed to adaptively generate a channel list on remote control assembly **300** for frequency hopping. The radio of remote control assembly **300** may build, maintain, and distribute the master channel list. Prior channel statistics and historical performance information may be obtained from the radio of infusion pump assembly **100, 100', 400, 500** by the radio of remote control assembly **300** using the messaging system as needed to meet performance requirements. By building the channel list from the perspective of both units, the radio interference environment of both units may be considered. The radios may adaptively select hopping channels to meet the round trip message latency, while operating in a desirable RF environment.

(729) Occlusions and/or leaks may occur anywhere along the fluid delivery path of infusion pump assembly **100**. For example and referring to FIG. **121**, occlusions/leaks may occur: in the fluid path between reservoir **118** and reservoir valve assembly **614**; in the fluid path between reservoir valve assembly **614** and pump assembly **106**; in the fluid path between pump assembly **106** and volume sensor valve assembly **612**; in the fluid path between volume sensor valve assembly **612** and volume sensor chamber **620**; in the fluid path between volume sensor chamber **620** and measurement valve assembly **610**; and in the fluid path between measurement valve assembly **610** and the tip of disposable cannula **138**. Infusion pump assembly **100** may be configured to execute one or more occlusion/leak detection algorithms that detect and locate such occlusions/leaks and enhance the safety/reliability of infusion pump assembly **100**.

(730) As discussed above, when administering the infusible fluid, infusion pump assembly **100** may first determine the volume of infusible fluid within volume sensor chamber **620** prior to the administration of the dose of infusible fluid and may subsequently determine the volume of infusible fluid within volume sensor chamber **620** after the administration of the dose of infusible fluid. By monitoring these values, the occurrence of occlusions/leaks may be detected.

(731) Occlusion Type—Total: When a total occlusion is occurring, the difference between the initial measurement prior to the administration of the dose of infusible fluid and the final measurement after the administration of the dose of infusible fluid will be zero (or essentially zero), indicating a large residual quantity of infusible fluid within volume sensor chamber **620**.

Accordingly, no fluid may be leaving volume sensor chamber **620**.

(732) Specifically, if the tip of disposable cannula is occluded, the fluid path down stream of volume sensor chamber **620** will fill with fluid and eventually become pressurized to a level equivalent to the mechanical pressure exerted by spring diaphragm **628**.

Accordingly, upon measurement valve assembly **610** opening, zero (or essentially zero) fluid will be dispensed and, therefore, the value of the initial and final measurements (as made by volume sensor assembly **148**) will essentially be equal.

(733) Upon detecting the occurrence of such a condition, a total occlusion flag may be set and infusion pump assembly **100** may e.g., trigger an alarm, thus indicating that the user needs to seek alternative means for receiving their therapy.

(734) Occlusion Type—Partial: When a partial occlusion is occurring, the difference between the initial measurement prior to the administration of the dose of infusible fluid and the final measurement after the administration of the dose of infusible fluid will indicate that less than a complete dose of infusible fluid was delivered. For example, assume that at the end of a particular pumping cycle, volume sensor assembly **148** indicated that 0.10 microliters of infusible fluid were present in volume sensor chamber **620**. Further, assume that measurement valve assembly **610** is subsequently closed and pump assembly **106** is subsequently actuated, resulting in volume sensor chamber **620** being filled with the infusible fluid. Further assume that volume sensor assembly **148** determines that volume sensor chamber **620** is now filled with 1.00 microliters of infusible fluid (indicating a pumped volume of 0.90 microliters).

(735) Accordingly, upon the opening of measurement valve assembly **610**, the quantity of infusible fluid included within volume sensor chamber would be expected to drop to 0.10 microliters (or reasonably close thereto). However, in the event of a partial occlusion, due to a slower-than-normal flow rate from volume sensor chamber **620**, the quantity of infusible fluid within volume sensor chamber **620** may only be reduced to 0.40 microliters (indicating a delivered volume of 0.60 microliters). Accordingly, by

monitoring the difference between the pumped volume (0.90 microliters) and the delivered volume (0.60 microliters), the residual volume may be defined and the occurrence of a partial occlusion may be detected.

(736) Upon detecting the occurrence of such a condition, a partial occlusion flag may be set and infusion pump assembly **100** may e.g., trigger an alarm, thus indicating that the user needs to seek alternative means for receiving their therapy. However, as this is indicative of a partial occlusion (as opposed to a complete occlusion), the issuance of an alarm may be delayed, as the partial occlusion may clear itself.

(737) Alternatively, infusion pump assembly **100** may: calculate a pump ontime to volume delivered ratio; track it through time; and track by using a fast moving and a slow moving exponential average of the pump ontime. The exponential average may be tracked, in a fashion similar to the leaky sum integrator. The infusion pump assembly **100** may filter signal and look for a fast change. The rate of fluid outflow and/or residual volume may be monitored. If the residual volume does not change, then there may be a total occlusion. If the residual volume changed, they may be a partial occlusion. Alternatively still, the residual values may be summed. If the number of valve actuations or the latch time is being varied, the fluid flow rate may be examined, even if you build up pressure in volume sensor assembly **148**.

(738) Total/Partial Empty Reservoir: When reservoir **118** is becoming empty, it will become more difficult to fill volume sensor chamber **620** to the desired level. Typically, pump assembly **106** is capable of pumping 1.0 microliters per millisecond. For example, assume that an “empty” condition for volume sensor chamber **620** is 0.10 microliters and a “full” condition for volume sensor chamber **620** is 1.00 microliters. However, as reservoir **118** begins to empty, it may become harder for pump assembly **106** to fill volume sensor chamber **620** to the “full” condition and may consistently miss the goal. Accordingly, during normal operations, it may take one second for pump assembly **106** to fill volume sensor chamber **620** to the “full” condition and, as reservoir **118** empties, it may take three seconds to fill volume sensor chamber **620** to the “full” condition. Eventually, if reservoir **118** completely empties, volume sensor chamber **620** may never be able to achieve a “full condition”. Accordingly, the inability of pump assembly **106** to fill volume sensor chamber **620** to a “full” condition may be indicative of reservoir **118** being empty. Alternatively, the occurrence of such a condition may be indicative of other situations (e.g., the failure of pump assembly **106** or an occlusion in the fluid path prior to volume sensor chamber **620**). Infusion pump assembly **100** may determine the difference between the “full” condition and the amount actually pumped. These differences may be summed and the made up for once the reservoir condition is addressed.

(739) Upon detecting the occurrence of such a condition, an empty flag may be set and infusion pump assembly **100** may e.g., trigger an alarm, thus indicating that the user needs to e.g., replace disposable housing assembly **114**.

(740) Additionally, as reservoir **118** empties, reservoir **118** will eventually result in a “vacuum” condition and the ability of pump assembly **106** to deliver fluid to volume sensor chamber **620** may be compromised. As discussed above, volume controller **1602** may include feed forward controller **1652** for setting an initial “guess” concerning “on-time” signal **1606**, wherein this initial guess is based upon a pump calibration curve. For example, in order for pump assembly **106** to deliver 0.010 units of infusible fluid, feed forward controller **1652** may define an initial “on-time” of e.g., one millisecond. However, as reservoir **118** begins to empty, due to compromised pumping conditions, it may take two milliseconds to deliver 0.010 units of infusible fluid. Further, as reservoir **118** approaches a fully empty condition, it may take ten milliseconds to deliver 0.010 units of infusible fluid. Accordingly, the occurrence of reservoir **118** approaching an empty condition may be detected by monitoring the level at which the actual operation of pump assembly **106** (e.g., two milliseconds to deliver 0.010 units of infusible fluid) differs from the anticipated operation of pump assembly **106** (e.g., one millisecond to deliver 0.010 units of infusible fluid).

(741) Upon detecting the occurrence of such a condition, a reserve flag may be set and infusion pump assembly **100** may e.g., trigger an alarm, thus indicating that the user will need to e.g., replace disposable housing assembly **114** shortly.

(742) Leak Detection: In the event of a leak (e.g., a leaky valve or a rupture/perforation) within the fluid path, the ability of the fluid path to retain fluid pressure may be compromised. Accordingly, in order to check for leaks within the fluid path, a bleed down test may be performed in which pump assembly **106** is used to pressurize volume sensor chamber **620**. Volume sensor assembly **148** may then perform a first volume measurement (as described above) to determine the volume of infusible fluid within volume sensor chamber **620**. Infusion pump assembly **100** may then wait a defined period of time to allow for bleed down in the event of a leak. For example, after a sixty second bleed down period, volume sensor assembly **148** may perform a second volume measurement (as described above) to determine the volume of infusible fluid within volume sensor chamber **620**. If there are no leaks, the two volume measurements should be essentially the same. However, in the event of a leak, the second measurement may be less than the first measurement. Additionally, depending on the severity of the leak, pump assembly **106** may be incapable of filling volume sensor chamber **620**. Typically, a leak check may be performed as part of a delivery of infusible fluid.

(743) In the event that the difference between the first volume measurement and the second volume measurement exceeds an acceptable threshold, a leak flag may be set and infusion pump assembly **100** may e.g., trigger an alarm, thus indicating that the user needs to seek alternative means for receiving their therapy

(744) As discussed above, infusion pump assembly **100** may include supervisor processor **1800**, command processor **1802**, and radio processor **1818**. Unfortunately, once assembled, access to electrical control assembly **110** within infusion pump assembly **100** very limited. Accordingly, the only means to access electrical control assembly **110** (e.g., for upgrading flash memories) may be through the communication channel established between infusion pump assembly **100**, **100'**, **400**, **500** and remote control assembly **300**, or via electrical contacts **834** used by battery charger **1200**.

(745) Electrical contacts **834** may be directly coupled to radio processor **1818** and may be configured to provide I2C communication capability for erasing/programming any flash memory (not shown) included within radio processor **1818**. The process of loading a program into radio processor **1818** may provide a means for erasing/programming of the flash memories in both the supervisor processor **1800** and command processor **1802**.

(746) When programming supervisor processor **1800** or command processor **1802**, the program (i.e., data) to be loaded into flash memory accessible by supervisor processor **1800** or command processor **1802** may be provided in a plurality of data blocks. This

is because the radio processor **1818** may not have enough memory to hold the entire flash image of the software as one block. (747) Referring also to FIG. **122**, there is shown one illustrative example of the manner in which the various systems within infusion pump assembly **100, 100', 400, 500** may be interconnected. For example, battery charger **1200** may be coupled to computing device **2100** (e.g., a personal computer) via bus translator **2102**, which converts e.g., RS232 formatted data to e.g., I2C formatted data. Bus translator **2102** may execute a pass-through program that effectuates the above-described translation. Battery charger **1200** may be coupled to radio processor **181** via electrical contacts **834** (described above). Radio processor **1818** may then be coupled to supervisor processor **1800** and command processor **1802** via e.g., an RS232 bus. Radio processor **1818** may execute an update program that allows radio processor **1818** to control/orchestrate the updating of the flash memories accessible by supervisor processor **1800** and command processor **1802**. Accordingly, through the use of the above-described coupling, software updates obtained by computing device **2100** may be uploaded to flash memory (not shown) accessible by supervisor processor **1800** and command processor **1802**. The above-described software updates may be command line program that may be automatically invoked by a script process.

(748) As discussed above, infusion pump assembly **100, 100' 400, 500** may be configured to deliver an infusible fluid to a user. Further and as discussed above, infusion pump assembly **100, 100' 400, 500** may deliver the infusible fluid via sequential, multi-part, infusion events (that may include a plurality of discrete infusion events) and/or one-time infusion events. However, in some embodiments, infusion pump assembly **100, 100' 400, 500** may deliver stacking bolus infusion events. For example, a user may request the delivery of a bolus, e.g., 6 units. While the 6 units are in the process of being delivered to the user, the user may request a second bolus, e.g., 3 units. In some embodiments of infusion pump assembly **100, 100' 400, 500** may deliver the second bolus at the completion of the first bolus.

(749) Examples of other such sequential, multi-part, infusion events may include but are not limited to a basal infusion event and an extended-bolus infusion event. As is known in the art, a basal infusion event refers to the repeated injection of small (e.g. 0.05 unit) quantities of infusible fluid at a predefined interval (e.g. every three minutes) that may be repeated until stopped, e.g., by a user or by the system. Further, the basal infusion rates may be pre-programmed and may include specified rates for pre-programmed time-frames, e.g., a rate of 0.50 units per hour from 6:00 am-3:00 pm; a rate of 0.40 units per hour from 3:00 pm-10:00 pm; and a rate of 0.35 units per hour from 10:00 pm-6:00 am. However, the basal rate may be 0.025 units per hour, and may not change according to pre-programmed time-frames. The basal rates may be repeated regularly/daily until otherwise changed.

(750) Further and as is known in the art, an extended-bolus infusion event may refer to the repeated injection of small (e.g. 0.05 unit) quantities of infusible fluid at a predefined interval (e.g. every three minutes) that is repeated for a defined number of intervals (e.g., three intervals) or for a defined period of time (e.g., nine minutes). An extended-bolus infusion event may occur simultaneously with a basal infusion event.

(751) If multiple infusion events conflict with each other, infusion pump assembly **100, 100' 400, 500** may prioritize the infusion event in the follow manner.

(752) Referring also to FIG. **123**, assume for illustrative purposes only that the user configures infusion pump assembly **100, 100' 400, 500** to administer a basal dose (e.g. 0.05 units) of infusible fluid every three minutes. The user may utilize remote control assembly **300** to define a basal infusion event for the infusible fluid (e.g., 1.00 units per hour).

(753) Infusion pump assembly **100, 100' 400, 500** may then determine an infusion schedule based upon the basal infusion event defined. Once determined, infusion pump assembly **100, 100' 400, 500** may administer the sequential, multi-part, infusion event (e.g., 0.05 units of infusible fluid every three minutes). Accordingly, while administering the sequential, multi-part, infusion event, infusion pump assembly **100, 100' 400, 500**: may infuse a first 0.05 unit dose **2200** of the infusible fluid at t=0:00 (i.e., a first discrete infusion event), may infuse a second 0.05 unit dose **2202** of the infusible fluid at t=3:00 (i.e., a second discrete infusion event); may infuse a third 0.05 unit dose **2204** of the infusible fluid at t=6:00 (i.e., a third discrete infusion event); may infuse a fourth 0.05 unit dose **2206** of the infusible fluid at t=9:00 (i.e., a fourth discrete infusion event); and may infuse a fifth 0.05 unit dose **2208** of the infusible fluid at t=12:00 (i.e., a fifth discrete infusion event). As discussed above, this pattern of infusing 0.05 unit doses of the infusible fluid every three minutes may be repeated until stopped, e.g., by a user or by the system, in this example, as this is an illustrative example of a basal infusion event.

(754) Further, assume for illustrative purposes that the infusible fluid is insulin and sometime after the first 0.05 unit dose **2200** of infusible fluid is administered (but before the second 0.05 unit dose **2202** of infusible fluid is administered), the user checks their blood glucose level and realizes that their blood glucose level is running a little higher than normal. Accordingly, the user may define an extended bolus infusion event via remote control assembly **300**. An extended bolus infusion event may refer to the continuous infusion of a defined quantity of infusible fluid over a finite period of time. However, as such an infusion methodology is impractical/undesirable for an infusion pump assembly, when administered by such an infusion pump assembly, an extended bolus infusion event may refer to the infusion of additional small doses of infusible fluid over a finite period of time.

(755) Accordingly, the user may utilize remote control assembly **300** to define an extended bolus infusion event for the infusible fluid (e.g., 0.20 units over the next six minutes), which may be confirmed in a manner discussed above. While, in this example, the extended bolus infusion event is described as 0.20 units over the next six minutes, this is for illustrative purposes only and is not intended to be a limitation of this disclosure, as either or both of the unit quantity and total time interval may be adjusted upward or downward. Once defined and/or confirmed, infusion pump assembly **100, 100' 400, 500** may determine an infusion schedule based upon the extended bolus infusion event defined; and may administer the infusible fluid. For example, infusion pump assembly **100, 100' 400, 500** may deliver 0.10 units of infusible fluid every three minutes for the next two interval cycles (or six minutes), resulting in the delivery of the extended bolus dose of infusible fluid defined by the user (i.e., 0.20 units over the next six minutes).

(756) Accordingly, while administering the second, sequential, multi-part, infusion event, infusion pump assembly **100, 100' 400, 500** may infuse a first 0.10 unit dose **2210** of the infusible fluid at t=3:00 (e.g., after administering the second 0.05 unit dose **2202** of infusible fluid). Infusion pump assembly **100, 100' 400, 500** may also infuse a second 0.10 unit dose **2212** of the infusible fluid at t=6:00 (e.g., after administering the third 0.05 unit dose **2204** of infusible fluid).

(757) Assume for illustrative purposes only that after the user programs infusion pump assembly **100, 100' 400, 500** via remote control assembly **300** to administer the first sequential, multi-part, infusion event (i.e., 0.05 units infused every three minute interval repeated continuously) and administer the second sequential, multi-part, infusion event (i.e., 0.10 units infused every three minute interval for two intervals), the user decides to eat a very large meal. Predicting that their blood glucose level might increase considerably, the user may program infusion pump assembly **100, 100' 400, 500** (via remote control assembly **300**) to administer a one-time infusion event. An example of such a one-time infusion event may include but is not limited to a normal bolus infusion event. As is known in the art, a normal bolus infusion event refers to a one-time infusion of the infusible fluid.

(758) For illustrative purposes only, assume that the user wishes to have infusion pump assembly **100, 100' 400, 500** administer a bolus dose of thirty-six units of the infusible fluid. Infusion pump assembly **100, 100' 400, 500** may monitor the various infusion events being administered to determine whether a one-time infusion event is available to be administered. If a one-time infusion event is available for administration, infusion pump assembly **100, 100' 400, 500** may delay the administration of at least a portion of the sequential, multi-part, infusion event.

(759) Continuing with the above-stated example, once the user completes the programming of infusion pump assembly **100, 100' 400, 500** to deliver one-time infusion event **2214** (i.e., the thirty-six unit bolus dose of the infusible fluid), upon infusion pump assembly **100, 100' 400, 500** determining that the one-time infusion event is available for administration, infusion pump assembly **100, 100' 400, 500** may delay the administration of each sequential, multi-part infusion event and administer the available one-time infusion event.

(760) Specifically and as discussed above, prior to the user programming infusion pump assembly **100, 100' 400, 500** to deliver one-time infusion event **2214**, infusion pump assembly **100, 100' 400, 500** was administering a first sequential, multi-part, infusion event (i.e., 0.05 units infused every three minute interval repeated continuously) and administering a second sequential, multi-part, infusion event (i.e., 0.10 units infused every three minute interval for two intervals).

(761) For illustrative purposes only, the first sequential, multi-part, infusion event may be represented within FIG. 123 as 0.05 unit dose **2200** @ t=0:00, 0.05 unit dose **2202** @ t=3:00, 0.05 unit dose **2204** @ t=6:00, 0.05 unit dose **2206** @ t=9:00, and 0.05 unit dose **2208** @ t=12:00. As the first sequential, multi-part, infusion event as described above is a basal infusion event, infusion pump assembly **100, 100' 400, 500** may continue to infuse 0.05 unit doses of the infusible fluid at three minute intervals indefinitely (i.e., until the procedure is cancelled by the user).

(762) Further and for illustrative purposes only, the second sequential, multi-part, infusion event may be represented within FIG. 123 as 0.10 unit dose **2210** @ t=3:00 and 0.10 unit dose **2212** @ t=6:00. As the second sequential, multi-part, infusion event is described above as an extended bolus infusion event, infusion pump assembly **100, 100' 400, 500** may continue to infuse 0.10 unit doses of the infusible fluid at three minute intervals for exactly two intervals (i.e., the number of intervals defined by the user).

(763) Continuing with the above-stated example, upon infusion pump assembly **100, 100' 400, 500** determining that the thirty-six unit normal bolus dose of the infusible fluid (i.e., one-time infusion event **2214**) is available for administration, infusion pump assembly **100, 100' 400, 500** may delay the administration of each sequential, multi-part infusion event and may start administering one-time infusion event **2214** that is available for administration.

(764) Accordingly and for illustrative purposes only, assume that upon completion of the programming of infusion pump assembly **100, 100' 400, 500** to deliver the thirty-six unit normal bolus dose of the infusible fluid (i.e., the one-time infusion event), infusion pump assembly **100, 100' 400, 500** begins administering one-time infusion event **2214**. Being that one-time infusion event **2214** is comparatively large, it may take longer than three minutes (i.e., the time interval between individual infused doses of the sequential, multi-part, infusion events) and one or more of the individual infused doses of the sequential, multi-part, infusion events may need to be delayed.

(765) Specifically, assume that it will take infusion pump assembly **100, 100' 400, 500** greater than six minutes to infuse thirty-six units of the infusible fluid. Accordingly, infusion pump assembly **100, 100' 400, 500** may delay 0.05 unit dose **2202** (i.e., scheduled to be infused @ t=3:00), 0.05 unit dose **2204** (i.e., scheduled to be infused @ t=6:00), and 0.05 unit dose **2206** (i.e., scheduled to be infused @ t=9:00) until after one-time infusion event **2214** (i.e., the thirty-six unit normal bolus dose of the infusible fluid) is completely administered. Further, infusion pump assembly **100, 100' 400, 500** may delay 0.10 unit dose **2210** (i.e., scheduled to be infused @ t=3:00 and 0.10 unit dose **2212** (i.e., scheduled to be infused @ t=6:00) until after one-time infusion event **2214**.

(766) Once administration of one-time infusion event **2214** is completed by infusion pump assembly **100, 100' 400, 500**, any discrete infusion events included within the sequential, multi-part, infusion event that were delayed may be administered by infusion pump assembly **100, 100' 400, 500**. Accordingly, once one-time infusion event **2214** (i.e., the thirty-six unit normal bolus dose of the infusible fluid) is completely administered, infusion pump assembly **100, 100' 400, 500** may administer 0.05 unit dose **2202**, 0.05 unit dose **2204**, 0.05 unit dose **2206**, 0.10 unit dose **2210**, and 0.10 unit dose **2212**.

(767) While infusion pump assembly **100, 100' 400, 500** is shown to administer 0.05 unit dose **2202**, then 0.10 unit dose **2210**, then 0.05 unit dose **2204**, then 0.10 unit dose **2212**, and then 0.05 unit dose **2206**, this is for illustrative purposes only and is not intended to be a limitation of this disclosure, as other configurations are possible and are considered to be within the scope of this disclosure. For example, upon infusion pump assembly **100, 100' 400, 500** completing the administration of one-time infusion event **2214** (i.e., the thirty-six unit normal bolus dose of the infusible fluid), infusion pump assembly **100, 100' 400, 500** may administer all of the delayed discrete infusion events associated with the first sequential, multi-part infusion event (i.e., namely 0.05 unit dose **2202**, 0.05 unit dose **2204**, and 0.05 unit dose **2206**). Infusion pump assembly **100, 100' 400, 500** may then administer all of the delayed discrete infusion events associated with the second sequential, multi-part infusion event (i.e., 0.10 unit dose **2210**, and 0.10 unit dose **2212**).

(768) While one-time infusion event **2214** (i.e., the thirty-six unit normal bolus dose of the infusible fluid) is shown as being infused beginning at t=3:00, this is for illustrative purposes only and is not intended to be a limitation of this disclosure. Specifically, infusion pump assembly **100, 100' 400, 500** may not need to begin infusing one-time infusion event **2214** at one of the three-minute intervals (e.g., t=0:00, t=3:00, t=6:00, t=9:00, or t=12:00) and may begin administering one-time infusion event

2214 at any time.

(769) While each discrete infusion event (e.g., 0.05 unit dose **2202**, 0.05 unit dose **2204**, 0.05 unit dose **2206**, 0.10 unit dose **2210**, and 0.10 unit dose **2212**) and one-time infusion event **2214** are shown as being a single event, this is for illustrative purposes only and is not intended to be a limitation of this disclosure. Specifically, at least one of the plurality of discrete infusion events e.g., 0.05 unit dose **2202**, 0.05 unit dose **2204**, 0.05 unit dose **2206**, 0.10 unit dose **2210**, and 0.10 unit dose **2212**) may include a plurality of discrete infusion sub-events. Further, one-time infusion event **2214** may include a plurality of one-time infusion sub-events.

(770) Referring also to FIG. **124** and for illustrative purposes, 0.05 unit dose **2202** is shown to include ten discrete infusion sub-events (e.g., infusion sub-events **2216.sub.1-10**), wherein a 0.005 unit dose of the infusible fluid is infused during each of the ten discrete infusion sub-events. Additionally, 0.10 unit dose **2210** is shown to include ten discrete infusion sub-events (e.g., infusion sub-events **2218.sub.1-10**), wherein a 0.01 unit dose of the infusible fluid is delivered during each of the ten discrete infusion sub-events. Further, one-time infusion event **2214** may include e.g., three-hundred-sixty one-time infusion sub-events (not shown), wherein a 0.1 unit dose of the infusible fluid is delivered during each of the three-hundred-sixty one-time infusion sub-events. The number of sub-events defined above and the quantity of the infusible fluid delivered during each sub-event is solely for illustrative purposes only and is not intended to be a limitation of this disclosure, as the number of sub-events and/or the quantity of the infusible fluid delivered during each sub-event may be increased or decreased depending upon e.g., the design criteria of infusion pump assembly **100**, **100'** **400**, **500**.

(771) Before, after, or in between the above-described infusion sub-events, infusion pump assembly **100**, **100'** **400**, **500** may confirm the proper operation of infusion pump assembly **100**, **100'** **400**, **500** through the use of any of the above-described safety features (e.g., occlusion detection methodologies and/or failure detection methodologies).

(772) In the exemplary embodiments, the infusion pump assembly may be wirelessly controlled by a remote control device. In the exemplary embodiments, a split ring resonator antenna may be used for wireless communication between the infusion pump assembly and the remote control device (or other remote device). The term “wirelessly controlled” refers to any device that may receive input, instructions, data, or other, wirelessly. Further, a wirelessly controlled insulin pump refers to any insulin pump that may wirelessly transmit and/or receive data from another device. Thus, for example, an insulin pump may both receive instructions via direct input by a user and may receive instructions wirelessly from a remote controller.

(773) Referring to FIG. **127** and FIG. **131**, an exemplary embodiment of a split ring resonator antenna adapted for use in a wirelessly controlled medical device, and is used in the exemplary embodiment of the infusion pump assembly, includes at least one split ring resonator antenna (hereinafter “SRR antenna”) **2508**, a wearable electric circuit, such as a wirelessly controlled medical infusion apparatus (hereinafter “infusion apparatus”) **2514**, capable of powering the antenna, and a control unit **2522**.

(774) In various embodiments, a SRR antenna **2508** may reside on the surface of a non-conducting substrate base **2500**, allowing a metallic layer (or layers) to resonate at a predetermined frequency. The substrate base **2500** may be composed of standard printed circuit board material such as Flame Retardant 2 (FR-2), FR-3, FR-4, FR-5, FR-6, G-10, CEM-1, CEM-2, CEM-3, CEM-4, CEM-5, Polyimide, Teflon, ceramics, or flexible Mylar. The metallic resonating bodies comprising a SRR antenna **2508** may be made of two rectangular metallic layers **2502**, **2504**, made of, for example, platinum, iridium, copper, nickel, stainless steel, silver or other conducting materials. In other various embodiments, a SRR antenna **2508** may contain only one metallic resonating body.

(775) In the exemplary embodiment, a gold-plated copper outer layer **2502**, surrounds, without physically contacting, a gold-plated copper inner ring **2504**. That is, the inner ring **2504** resides in the cavity **2510** (or aperture) formed by the outer layer **2502**. The inner ring **2504** may contain a gap, or split **2506**, along its surface completely severing the material to form an incomplete ring shape. Both metallic resonating bodies **2502**, **2504** may reside on the same planar surface of the substrate base **2500**. In such a configuration, the outer layer **2502** may be driven via a transmission line **2512** coupled to the outer layer **2502**, for example. Additionally, in various other embodiments, a transmission line **2512** may be coupled to the inner ring **2504**.

(776) Antenna design software, such as AWR Microwave Office, capable of simulating electromagnetic geometries, such as, antenna performance, may significantly decrease the time required to produce satisfactory dimensions compared to physically fabricating and testing antennas. Accordingly, with aid of such software, the SRR antenna **2508** may be designed such that the geometric dimensions of the resonant bodies **2502**, **2504** facilitate an operational frequency of 2.4 GHz. FIG. **132** depicts the exemplary dimensions of the inner ring **2504** and outer layer **2502**, and the positioning of the cavity **2510** in which the inner ring **2504** resides. The distance in between the outer layer **2502** and the inner ring **2504** is a constant 0.005 inches along the perimeter of the cavity **2510**. However, in other embodiments, the distance between the outer layer and the inner ring may vary and in some embodiments, the operational frequency may vary.

(777) In various embodiments, a SRR antenna **2508** may have dimensions such that it could be categorized as electrically small, that is, the greatest dimension of the antenna being far less than one wavelength at operational frequency.

(778) In various other embodiments, a SRR antenna **2508** may be composed of one or more alternatively-shaped metallic outer layers, such as circular, pentagonal, octagonal, or hexagonal, surrounding one or more metallic inner layers of similar shape. Further, in various other embodiments, one or more metallic layers of a SRR antenna **2508** may contain gaps in the material, forming incomplete shapes.

(779) Referring to FIG. **130**, a SRR antenna **2508** having the exemplary geometry exhibits acceptable return loss and frequency values when placed in contact with human skin. As shown in FIG. **130**, focusing on the band of interest denoted by markers **1** and **2** on the graph, return loss prior to contact with human skin is near -15 dB while monitoring a frequency band centered around 2.44 GHz. Return loss during contact with human skin, as shown in FIG. **130A**, remains a suitable value near -25 dB at the same frequency, yielding approximately 97% transmission power.

(780) These results are favorable especially as compared with a non-split ring resonator antenna type, such as the Inverted-F. Return loss of an Inverted-F antenna may exhibit a difference when the antenna contacts human skin, resulting in a low percentage of power transmitted outward from the antenna. By way of example, as shown in FIG. **133**, and again focusing on the band of interest denoted by markers **1** and **2** on the graph, return loss of an Inverted-F antenna prior to contact with human skin is

near -25 dB at a frequency centered around 2.44 GHz. Return loss during contact with human skin is nearly -2 dB at the same frequency, yielding approximately 37% power transmission.

(781) Integration with a Wireless Medical Device

(782) In the exemplary embodiment, referring to FIG. 132 and FIG. 128, one application of a SRR antenna 2508 may be integration into a wearable infusion apparatus 2514 capable of delivering fluid medication to a user/patient 2524. In such an application, the safety of the user/patient is dependent on fluid operation between these electrical components, thus reliable wireless transmission to and from a control unit 2522 is of great importance.

(783) An infusion apparatus 2514 may be worn directly on the human body. By way of example, such a device may be attached on or above the hip joint in direct contact with human skin, placing the SRR antenna 2508 at risk of unintended dielectric loading causing a frequency shift in electrical operation. However, in such an application, electrical characteristics of the SRR antenna 2508 which allow it to be less sensitive to nearby parasitic objects are beneficial in reducing or eliminating degradation to the performance. A controlling component, such as a control unit 2522 (generally shown in FIG. 131), may be paired with an infusion apparatus 2514, and may be designed to transmit and receive wireless signals to and from the infusion apparatus 2514 at a predetermined frequency, such as 2.4 GHz. In the exemplary embodiment, the control unit 2522 serves as the main user interface through which a patient or third party may manage insulin delivery. In other embodiments, infusion apparatus 2514 may utilize a SRR antenna 2508 to communicate with one or more control units 2522.

(784) In various embodiments, a number of different wireless communication protocols may be used in conjunction with the SRR antenna 2508, as the protocol and data types to be transferred are independent of the electrical characteristics of the antenna. However, in the exemplary embodiment, a bi-directional master/slave means of communication organizes the data transfer through the SRR antenna 2508. The control unit 2522 may act as the master by periodically polling the infusion apparatus 2514, or slave, for information. In the exemplary embodiment, only when the slave is polled, the slave may send signals to the control unit 2522 only when the slave is polled. However, in other embodiments, the slave may send signals before being polled. Signals sent by way of this system may include, but are not limited to, control, alarm, status, patient treatment profile, treatment logs, channel selection and negotiation, handshaking, encryption, and check-sum. In some embodiments, transmission through the SRR antenna 2508 may also be halted during certain infusion operations as an added precaution against electrical disruption of administration of insulin to the patient.

(785) In the exemplary embodiment, the SRR antenna 2508 may be coupled to electrical source circuitry via one or more pins 2516 on a transmission line 2512. In various other embodiments a transmission line may comprise a wire, pairs of wire, or other controlled impedance methods providing a channel by which the SRR antenna 2508 is able to resonate at a certain frequency. The transmission line 2512 may reside on the surface of the substrate base 2500 and may be composed of the same material as the SRR antenna 2508, such as gold-plated copper. Additionally, a ground plane may be attached to the surface of the substrate base opposite the transmission line 2512.

(786) The electrical circuitry coupled to the SRR antenna 2508 may apply an RF signal to the end of the transmission line 2512 nearest the circuitry, creating an electromagnetic field throughout, and propagating from, the SRR antenna 2508. The electrical circuitry coupled to the SRR antenna 2508 facilitates resonance at a predetermined frequency, such as 2.4 GHz. Preferably, transmission line 2512 and SRR antenna 2508 both have impedances of 50 Ohms to simplify circuit simulation and characterization. However, in other various embodiments, the transmission line and split ring resonator antenna may have other impedance values, or a different resonating frequency.

(787) Referring to FIG. 129, a signal processing component(s) 2518, such as, a filter, amplifier, or switch, may be integrated into the transmission line 2512, or at some point between the signal source connection pins 2516 and the SRR antenna 2508. In the exemplary embodiment, the signal processing component 2518 is a band-pass filter to facilitate desired signal processing, such as, allowing only the exemplary frequency to be transmitted to the antenna, and rejecting frequencies outside that range. In the exemplary embodiment, a Comblane band-pass filter 2518 may be included in the transmission line 2512 between the antenna and the signal source. However in other embodiments, any other signal processing device, for example, but not limited to, filters, amplifiers, or any other signal processing devices known in the art.

(788) In various embodiments, a SRR antenna 2508 may be composed of metallic bodies capable of resonating on a flexible or rigid substrate. As shown in FIG. 128 and FIG. 3, the exemplary embodiment incorporates a curved SRR antenna on a flexible Polyimide substrate 2520. Polyimide may be the exemplary material because it tends to be more flexible than alternative substrates. This configuration may allow for simplified integration into circular-shaped devices (such as a wirelessly controlled medical infusion apparatus 2514), devices with irregular-shaped external housing, or devices in which saving space is paramount.

(789) In various embodiments, both control unit 2522 and base unit 2514 may incorporate a split SRR antenna 2508. This configuration may prove beneficial where the control unit is meant to be handheld, in close proximity to human skin, or is likely to be in close proximity to a varying number of materials with varying dielectric constants.

(790) In various other embodiments, a SRR antenna 2508 may be integrated into a human or animal limb replacement. As prosthetic limbs are becoming more sophisticated the electrical systems developed to control and simulate muscle movements require much more wiring and data transfer among subsystems. Wireless data transfer within a prosthetic limb may reduce weight through reduced physical wiring, conserve space, and allow greater freedom of movement. However, common antennas in such a system may be susceptible to dielectric loading. Similar to the previously mentioned benefits of integrating a SRR antenna 2508 into a wirelessly controlled medical infusion apparatus, a prosthetic limb, such as a robotic arm, may also come into contact with human skin or other dielectric materials and benefit from the reduction of electrical disturbances associated with such an antenna. In other various embodiments, the SRR antenna 2508 may be integrated into any device comprised of the electrical components capable of powering and transmitting/receiving data to an antenna and susceptible to electrical disturbances associated with proximity to dielectric materials.

(791) In various embodiments, a SRR antenna 2508 may be integrated into a configuration of medical components in which one or more implantable medical devices, operating within the human body, communicate wirelessly to a handheld, body-mounted, or

remote control unit. In certain embodiments, both body-mounted and in-body wireless devices may utilize a SRR antenna **2508** for wireless communication. Additionally, one or more of the components utilizing a SRR antenna **2508** may be completely surrounded by human skin, tissue or other dielectric material. By way of example, such a configuration may be used in conjunction with a heart monitoring/control system where stability and consistency of wireless data transmission are of fundamental concern.

(792) In various other embodiments, a SRR antenna **2508** may be integrated into the embodiments of the infusion pump assembly. configuration of medical components in which one or more electrical sensors positioned on, or attached to, the human body wirelessly communicate to a remote transceiving unit. By way of example, a plurality of electrodes positioned on the body may be coupled to a wireless unit employing a SRR antenna **2508** for wireless transmission to a remotely located electrocardiogram machine. By way of further example, a wireless temperature sensor in contact with human skin may employ SRR antenna **2508** for wireless communication to a controller unit for temperature regulation of the room in which the sensor resides.

(793) A number of embodiments have been described. Nevertheless, it will be understood that various modifications may be made. Accordingly, other embodiments are within the scope of the following claims.

Claims

1. A wearable infusion pump assembly comprising: a reusable housing assembly; a disposable housing assembly including a reservoir for receiving an infusible fluid; a releasable engagement assembly configured to allow the reusable housing assembly to releasably engage the disposable housing assembly; a bolus switch assembly configured to effectuate a bolus infusion event; at least one processor; and a computer readable medium coupled to the at least one processor, the computer readable medium including a plurality of instructions stored thereon which, when executed by the at least one processor, cause the at least one processor to perform operations comprising: receiving an initiation signal from the bolus switch assembly indicative of a bolus infusion event; receiving a dose signal from the bolus switch assembly indicative of at least a portion of a bolus quantity of the infusible fluid; rendering an audible quantity signal in response to the dose signal; and receiving an approval signal from the bolus switch assembly indicative of a concurrence with the audible quantity signal.
 2. The wearable infusion pump assembly of claim 1 wherein the computer readable medium further includes instructions for: administering the bolus quantity of the infusible fluid.
 3. The wearable infusion pump assembly of claim 1 wherein the bolus switch assembly is configured to check a battery life of a battery of the reusable housing assembly.
 4. The wearable infusion pump assembly of claim 3 wherein the bolus switch assembly is configured to check the battery life of the battery of the reusable housing assembly when the reusable housing assembly is disconnected from the disposable housing assembly and the bolus switch assembly is depressed for a defined period of time.
 5. The wearable infusion pump assembly of claim 4 wherein the wearable infusion pump assembly renders a battery pass tone when the check of the battery life of the battery is determined to have a charge above a desired threshold.
 6. The wearable infusion pump assembly of claim 4 wherein the wearable infusion pump assembly renders a battery fail tone when the check of the battery life of the battery is determined to have a charge below a desired threshold.
 7. The wearable infusion pump assembly of claim 1 wherein the bolus switch assembly is configured to cause pairing of the reusable housing assembly with a remote control assembly.
 8. The wearable infusion pump assembly of claim 7 wherein the wearable infusion pump assembly is configured such that the reusable housing assembly is required to be uncoupled from the disposable housing assembly in order for the bolus switch assembly to cause the pairing of the reusable housing assembly with the remote control assembly.
 9. The wearable infusion pump assembly of claim 1 wherein the bolus switch assembly is configured to cause aborting of administration of a bolus dose of the infusible fluid.
-