

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250279360

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

Chiang; Kuo-Chang et al.

VERTICAL BACK END OF LINE TRANSISTOR AND INTEGRATION WITH MEMORY CELL

Abstract

A back-end-of-line (BEOL) transistor includes a source electrode vertically stacked over a drain electrode and spaced apart from the drain electrode by a dielectric spacer between the first and second horizontal conductive layers. A semiconductor layer extends vertically between the source electrode and the drain electrode along a sidewall of the dielectric spacer. The drain electrode provides a channel for the transistor. A gate dielectric layer and a gate electrode are disposed over the gate dielectric layer. This structure allows the transistor to be manufactured without an etch process that can introduce defects into the semiconductor layer. The source electrode may be extended laterally to provide the bottom electrode of a memory cell that is integrated with the BEOL transistor.

Inventors: Chiang; Kuo-Chang (Hsinchu City, TW), Lai; Hsin-Yu (Hsinchu, TW), Chang; Chih-Yu (New Taipei City, TW), Chiang; Katherine H. (New Taipei City, TW)

Applicant: Taiwan Semiconductor Manufacturing Company, Ltd. (Hsinchu, TW)

Family ID: 96156379

Appl. No.: 18/773963

Filed: July 16, 2024

Related U.S. Application Data

us-provisional-application US 63560797 20240304

Publication Classification

Int. Cl.: H01L23/528 (20060101); H01L21/28 (20250101); H01L29/51 (20060101); H01L29/66 (20060101); H01L29/78 (20060101); H10B51/10 (20230101); H10B51/20 (20230101); H10B53/10 (20230101); H10B53/20 (20230101)

U.S. Cl.:

CPC **H01L23/5283** (20130101); **H01L23/528** (20130101); **H10B51/10** (20230201);
H10B51/20 (20230201); **H10B53/10** (20230201); **H10B53/20** (20230201);
H10D30/0415 (20250101); **H10D30/701** (20250101); **H10D64/033** (20250101);
H10D64/689 (20250101);

Background/Summary

REFERENCE TO RELATED APPLICATIONS [0001] This Application claims the benefit of U.S. Provisional Application No. 63/560,797, filed on Mar. 4, 2024, which is hereby incorporated by reference in its entirety.

BACKGROUND

[0002] Integrated circuit devices may include millions or billions of transistors. The transistors are configured to act as switches and or to produce power gains so as to enable logical functionality for an integrated chip (e.g., form a processor configured to perform logic functions). Integrated chips may also include large numbers of passive devices, such as capacitors, resistors, inductors, varactors, and the like. Passive devices are widely used to control integrated chip characteristics, such as gains, time constants, etc. Active and passive devices may be used to provide memory in large scale arrays.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0003] Aspects of the present disclosure are best understood from the following detailed description when read with the accompanying figures. It is noted that, in accordance with the standard practice in the industry, various features are not drawn to scale. In fact, the dimensions of the various features may be arbitrarily increased or reduced for clarity of discussion.

[0004] FIGS. **1-3** illustrate cross-sectional views of integrated circuit (IC) devices according to various embodiments of the present disclosure.

[0005] FIG. **4A-4C** illustrate patterns for pits in the bottom electrode of a memory cell in accordance with various embodiments.

[0006] FIG. **5A** illustrates a cross-sectional view and FIG. **5B** illustrates a plan view of an IC device according to another embodiment.

[0007] FIGS. **6-17** are a series of cross-sectional views illustrating an embodiment of a method of forming IC device of the present disclosure.

[0008] FIGS. **18-22** illustrate a variation on the method of FIGS. **6-17**, the variation providing an embodiment of another method of forming IC device of the present disclosure.

[0009] FIGS. **23-41B** are a series of views illustrating an embodiment of a method of forming IC device of the present disclosure. Where the figures have no letter suffix or the suffix “A”, they are cross-sectional view. Where the figures have the suffix “B”, they are plan views.

[0010] FIG. **42-44** provide flow charts for various embodiments of methods of forming IC devices in accordance with the present disclosure.

DETAILED DESCRIPTION

[0011] The present disclosure provides many different embodiments, or examples, for implementing different features of this disclosure. Specific examples of components and arrangements are described below to simplify the present disclosure. These are, of course, merely examples and are not intended to be limiting. For example, the formation of a first feature over or

on a second feature in the description that follows may include embodiments in which the first and second features are formed in direct contact and may also include embodiments in which additional features may be formed between the first and second features, such that the first and second features may not be in direct contact. In addition, the present disclosure may repeat reference numerals and or letters in the various examples. This repetition is for the purpose of simplicity and clarity and does not in itself dictate a relationship between the various embodiments and or configurations discussed.

[0012] Further, spatially relative terms, such as “beneath,” “below,” “lower,” “above,” “upper” and the like, may be used herein for ease of description to describe one element or feature's relationship to another element(s) or feature(s) as illustrated in the figures. The spatially relative terms are intended to encompass different orientations of the device in use or operation in addition to the orientation depicted in the figures. The apparatus may be otherwise oriented (rotated 90 degrees or at other orientations) and the spatially relative descriptors used herein may likewise be interpreted accordingly.

[0013] Front-end-of-line (FEOL) transistors may be a bottleneck in the drive toward higher density non-volatile memories (NVMs). High density random access memory may dictate a write current greater than 200 $\mu\text{A}/\mu\text{m}$. Larger transistors or multiple transistors operated in parallel may be needed to support a current of that magnitude. For example, some designs suggest the use of two or more transistors for each memory cell to provide sufficient drive current. Those approaches pose a large FEOL area penalty.

[0014] To avoid that penalty, back-end-of-line (BEOL) transistors may be used as access control devices for memory cells. The BEOL transistors and the memory cells are disposed in the metal interconnect structure over a semiconductor substrate. Placing the access control devices within the metal interconnect structure frees up space at the semiconductor substrate surface and thereby provides added flexibility for device integration.

[0015] A BEOL transistor within a metal interconnect typically has a channel provided by a layer of oxide semiconductor. A gate for the BEOL transistor may be below the oxide semiconductor and may be separated from the oxide semiconductor by a gate dielectric. Source and drain electrodes vias contact an upper surface of the oxide semiconductor layer. The source electrode via may connect to the bottom electrode of a memory cell above the BEOL transistor.

[0016] The inventors have found that the oxide semiconductor layer may be damaged and the reliability of the BEOL transistor may be reduced by a damascene process used to form the source and drain electrode vias. In particular, the damascene process includes etching via openings for the source and drain electrode vias. The oxide semiconductor layer is exposed through the via openings. Potential issues may arise from etch chemical residues on the oxide semiconductor layer, damage due to over etching, or from hydrogen/water absorption through the via openings. These issues may lead to oxygen defect generation, additional donor states, or other phenomena that manifest in deviation of a threshold voltage of the BEOL transistor from design targets or variability in the threshold voltage among a group of BEOL transistors.

[0017] The present disclosure provides a BEOL transistor that can be easily manufactured without the problematic etch process discussed above. The BEOL transistor includes a source electrode vertically stacked over a drain electrode and spaced apart from the drain electrode by a dielectric spacer. The channel is provided by a semiconductor layer that extends vertically between the source electrode and the drain electrode along a sidewall of the dielectric spacer. A gate dielectric layer is disposed over the semiconductor layer and a gate electrode is over the gate dielectric layer. This approach results improves the quality of the oxide semiconductor layer in the BEOL transistors in a memory array, reduces source/drain contact resistances, and provides memory devices with higher reliability. Additional benefits have been realized, including the avoidance of film stacking stresses that occurred with the old approach.

[0018] In some embodiments, the drain electrode juts out from under the dielectric spacer, and the

semiconductor layer has a lower horizontal portion on the jutting portion of the drain electrode. In some embodiments, the drain electrode juts out on all sides of the dielectric spacer. The semiconductor layer may have an upper horizontal portion over the source electrode. With this structure, the semiconductor layer may have no cut edges or etched surfaces in proximity to the channel. In some embodiments, some or all of the cut edges of the semiconductor layer are covered by high κ dielectric. The high κ dielectric on the cut edges may reduce leakage between the oxide semiconductor layer and the drain electrode. While the terms “source electrode” and “drain electrode” are used in this description, it will be appreciated that the structure described as the “source electrode” may be configured as the drain electrode and the structure described as the “drain electrode” may be configured as the source electrode.

[0019] In some embodiments, a memory cell is integrated with the BEOL transistor. In particular, the source electrode may extend laterally to provide a bottom electrode for the memory cell. In some embodiments, the memory cell and the BEOL transistor are disposed between an adjacent pair of metallization layers in the metal interconnect structure. In some embodiments, a dielectric layer or a data storage structure of the memory cell is in direct contact with the bottom electrode. In some embodiments, the source electrode is pitted in the area where it provides the bottom electrode so that the memory cell has a three-dimensional structure. The pits may be circular as in holes, linear as in trenches, or of any other suitable shape.

[0020] The memory cell can be any type of memory cell having a top electrode and a bottom electrode. In some embodiments, the memory cell is a dynamic random access memory (DRAM) cell and the internal structure of the memory cell, which is the portion of the memory cell between the bottom electrode and the top electrode, is provided by a dielectric so that the memory cell is a capacitor. In some embodiments, the dielectric is a high κ dielectric. In some embodiments, the memory cell is a ferroelectric random access memory (FeRAM) cell and the internal structure comprises a ferroelectric layer. In some embodiments, the memory cell is a resistive random access memory (ReRAM) cell and the internal structure comprises a resistance switching material. In some embodiments, the memory cell is a magnetoresistive random access memory (MRAM) cell and the internal structure comprises a magnetic tunnel junction (MTJ). In some embodiments, the memory cell is a phase change memory (PCM) cell and the internal structure comprises a phase changing material. The internal structures of these memory cells are data storage structures except for the case of the capacitor in which the internal structure is simply a dielectric.

[0021] In some embodiments in which the memory cell is a capacitor, the capacitor dielectric is formed simultaneously with the gate dielectric layer so that the capacitor dielectric and the gate dielectric layer have the same composition and thickness. In some embodiments, the top electrode of the memory cell is formed simultaneously with the gate electrode of the BEOL transistor. In some embodiments, the top electrode and the gate electrode have the same composition and thickness. In some embodiments, the top electrode and the gate electrode are planarized so that an upper surface of the top electrode is coplanar with an upper surface of the gate electrode.

[0022] In some embodiments, the BEOL transistor is one of a pair that share a gate electrode. The pair may be symmetrical about the gate electrode. In some embodiments, the dielectric spacer sidewall of the first of the pair faces the dielectric spacer sidewall of the second of the pair. The pair may be operated in parallel as one transistor equivalent to two transistors having twice the width or may be operated as two distinct transistors.

[0023] FIG. 1 illustrates an IC device **100** that includes a metal interconnect structure **161** over a substrate **177**. Semiconductor devices **179** may be disposed on the substrate **177**. The metal interconnect structure **161** comprises a plurality of stacked metallization layers including the metallization layers M.sub.1, M.sub.X-2, M.sub.X, and M.sub.X+1. The metal interconnect structure **161** may have a greater or lesser number of metallization layers than those illustrated. The metallization layers M.sub.1, M.sub.X-2, M.sub.X, and M.sub.X+1 include wires **123**. A via layer **102** and an etch stop layer **156** are disposed between each adjacent pair of the M.sub.1, M.sub.X-2,

M.sub.X, and M.sub.X+1. The wires **123** in adjacent metallization layers may be connected by vias **127** in via layers **102**.

[0024] A BEOL transistor **107** is disposed between the adjacent metallization layers M.sub.X-1 and M.sub.X. The BEOL transistor **107** is formed by a semiconductor layer **114** and a gate stack **106** over a sidewall **110** of an electrode stack **119**. The electrode stack **119** includes a first horizontal conductive layer **155**, a spacer dielectric **151**, and a second horizontal conductive layer **147** in a vertical stack. The gate stack **106** includes a gate dielectric layer **112** and a gate electrode **111**. The BEOL transistor **107** includes a source electrode **116** provided by the second horizontal conductive layer **147**, a drain electrode **118** provided by the first horizontal conductive layer **155**, and a channel **109** provided by a vertical portion **114B** of the semiconductor layer **114**. The BEOL transistor **107** has an effective channel length that is approximately equal to a thickness T.sub.1 of the spacer dielectric **151**. In some embodiments, the thickness T.sub.1 is in the range from about 10 nm to about 100 nm. In some embodiments, the thickness T.sub.1 is in the range from about 10 nm to about 30 nm. These thickness provide channel lengths suitable for transistors that provide access control for memory cells. The BEOL transistor **107** may be scaled down by reducing its horizontal dimensions while maintaining a channel length of 10 nm or more so as to avoid short channel effects.

[0025] The sidewall **110** comprises the spacer dielectric **151** and the source electrode **116**. The drain electrode **118** juts out from the sidewall **110**. The semiconductor layer **114** includes a lower horizontal portion **114C** that is over the jutting portion **117** of the drain electrode **118**, a vertical portion **114B** that is on the sidewall **110**, and an upper horizontal portion **114A** that is on top of the source electrode **116**. The semiconductor layer **114** has cut edges **115**. The cut edges **115** are distal from the channel **109**.

[0026] A memory cell **137A** is integrated with the BEOL transistor **107**. In particular, the memory cell **137A** is formed directly over the electrode stack **119** so that the second horizontal conductive layer **147** provides both the source electrode **116** and a bottom electrode **149** for the memory cell **137A**. The source electrode **116** and the bottom electrode **149** are essentially a single structure. The memory cell **137A** is a capacitor having a top electrode **139** and a dielectric layer **143** between the bottom electrode **149** and the top electrode **139**. In accordance with some embodiments, the dielectric layer **143** has the same composition and thickness as the gate dielectric layer **112** and the top electrode **139** has the same composition and thickness as the gate electrode **111**.

[0027] The memory cell **137A** may be one in an array (not shown) of memory cells **137A** for which BEOL transistors **107** provide access control. A bitline **173** for the array may be disposed in the metallization layer M.sub.X-1 and connected to the first horizontal conductive layer **155** by a via **120**. An etch stop layer **165** and or an oxide layer **169** may be disposed between the bitline **173** and the first horizontal conductive layer **155**. A word line **101** may run perpendicular to the bitline **173**, may be disposed over the gate electrode **111**, and may be connected to the gate electrode **111** by a via **105**. The top electrode **139** may be connected to a ground rail **131** by a via **135**. One or more dielectrics such as an interlevel dielectric **159** may surround and insulate these wires and vias.

[0028] FIG. 2 illustrates an IC device **200** that is like the IC device **100** of FIG. 1 except that it includes the memory cell **137B** in place of the memory cell **137A**. The memory cell **137B** has a top electrode **139** that may be thicker than the gate electrode **111**. The top electrode **139** may have an upper surface **205** that is coplanar with an upper surface **203** of the gate electrode **111**. The memory cell **137B** has an internal structure **201** that may be either a dielectric layer or a data storage structure. In either case, the internal structure **201** may be in direct contact with the bottom electrode **149**. A data storage structure may be a ferroelectric layer, a resistive switching material layer, a magnetic tunnel junction (MTJ), a phase changing material layer, the like, or any other type data storage structure. If the memory cell **137B** is a capacitor and the internal structure **201** is a dielectric layer, the dielectric layer may have a different thickness and or composition from the gate dielectric layer **112**. In some embodiments, the internal structure **201** continues onto sidewalls **207**

of the top electrode **139**.

[0029] FIG. **3** illustrates an IC device **300** that is like the IC device **200** of FIG. **2** except that it includes the memory cell **137C** in place of the memory cell **137B**, and in the IC device **300** the bottom electrode **149** has internal sidewalls **303** that define pits **301**. In the memory cell **137C**, the internal structure **201** and the top electrode **139** extend into the pits **301** so that the memory cell **137C** has a three-dimensional structure.

[0030] FIG. **4A** provide a plan view **400** illustrating the bottom electrode **149** in accordance with a first embodiment. In the first embodiments, the pits **301** have elliptical cross-sections and form an array have n rows and m columns. Each of m and n may be separately selected and may be in the range from about 1 to about 500. In some embodiments, m and n are in the range from 2 to about 100. The depth of the pits **301** may be, for example, in the range from about 1 nm to about 100 nm. In some embodiments, the pits **301** have depths in the range from about 1 nm to about 20 nm. In some embodiments, the pits **301** have depths in the range from about 20 nm to about 100 nm. In some embodiments, the pits **301** have depths that are less than a thickness of the second horizontal conductive layer **147** (see FIG. **3**).

[0031] The pits **301** may be circular with a diameter $D_{sub.1}$ and a spacing S_1 . The diameter $D_{sub.1}$ may be, for example, in the range from about 1 nm to about 100 nm. In some embodiments, the diameter $D_{sub.1}$ is in the range from about 1 nm to about 20 nm. In some embodiments, the diameter $D_{sub.1}$ is in the range from about 20 nm to about 100 nm. The spacing $S_{sub.1}$ may be less than the diameter $D_{sub.1}$. In some embodiments, the spacing $S_{sub.1}$ is half or less the diameter $D_{sub.1}$. In some embodiments, the pits **301** are non-circular. If the pits **301** are elliptical but non-circular, they may have a major access to minor access ratio in the range from about 1:1 to about 2:1.

[0032] FIG. **4B** provide a plan view **410** illustrating the bottom electrode **149** in accordance with a second embodiment. The second embodiment of FIG. **4B** is like the first embodiment of FIG. **4A** except that in the embodiment of FIG. **4B** the rows of pits **301** are staggered to provide narrower spacing. FIG. **4C** provide a plan view **420** illustrating the bottom electrode **149** in accordance with a third embodiment. In the third embodiment, the pits **301** take the form of trenches.

[0033] FIG. **5A** provides a cross-sectional view and FIG. **5B** provides a plan view of an IC device **500**. The cross-sectional view of FIG. **5A** illustrates a unit cell **502**, which is one in an array of like cells. The cross-sectional view of FIG. **5A** corresponds to the line A-A' in the plan view of FIG. **5B**. The plan view of FIG. **5B** shows three of the unit cells **502**. The unit cell **502** includes two BEOL transistors **107** and two memory cells **137C** symmetrically arranged around a shared gate electrode **111**. A high κ dielectric layer **503** covers edges **507** of the of the semiconductor layers **114** and edges **509** of the drain electrodes **118** so as to reduce leakage currents. A space between the edges **507** may be filled by an oxide layer **505**. The BEOL transistors **107** in each pair may be connected in parallel to operate as one transistor.

[0034] With reference to the plan view of FIG. **5B**, the drain electrodes **118** may be wider than the bitlines **173** so that they have side edges offset by a distance $D_{sub.2}$, which is approximately half the difference in width. The distance $D_{sub.2}$ may be in the range from about 1 nm to about 100 nm. In some embodiments, the distance $D_{sub.2}$ is in the range from about 1 nm to about 20 nm. In some embodiments, the distance $D_{sub.2}$ is in the range from about 20 nm to about 100 nm. The offset allows greater areas for the BEOL transistors **107** and the memory cells **137C** while maintaining a spacing between the bitlines **173**. If the offset is too large, the drain electrodes **118** will be too close together. If the offset is too small, either the BEOL transistors **107** will be too small or the spacing between the bitlines **173** will need to be increased so that the device density is compromised.

[0035] The source electrodes **116** may be narrower than the drain electrodes **118** so that they have side edges offset by a distance $D_{sub.3}$, which is approximately half the difference in width. The distance $D_{sub.3}$ may be in the range from about 1 nm to about 100 nm. In some embodiments, the

distance D.sub.3 is in the range from about 1 nm to about 20 nm. In some embodiments, the distance D.sub.3 is in the range from about 20 nm to about 100 nm. If the offset is too large, either the BEOL transistors **107** will be too small or the spacing between the bitlines **173** will need to be increased so that the device density is compromised. If the offset is too small, the manufacturing process will be difficult to execute.

[0036] FIGS. **6-17** provide a series of cross-sectional views exemplifying a method of forming an IC device in accordance with some embodiments. While FIGS. **6-17** are described with reference to various embodiments of a method, it will be appreciated that the structures shown in FIGS. **6-17** are not limited to the method but rather may stand alone separate from the method. While FIGS. **6-17** are described as a series of acts, it will be appreciated that the order of the acts may be altered in other embodiments. While FIGS. **6-17** illustrate and describe a specific set of acts, some acts that are illustrated and or described may be omitted in some embodiments. Further, acts that are not illustrated and or described may be included. The method of FIGS. **6-17** may provide the IC device **100** of FIG. **1** or some other IC device.

[0037] As shown by the cross-sectional view **600** of FIG. **6**, the method begins after provision of the substrate **177**, front end of line (FEOL) processing, and formation of a first group of metallization layers M.sub.1 to M.sub.X-1 of the metal interconnect structure **161**. The bitline **173** is disposed in one of these metallization layers. As shown in FIG. **6**, the method may begin with formation of the oxide layer **169** and the etch stop layer **165** over the metallization layer M.sub.X-1. It will be appreciated that the oxide layer **169** and the etch stop layer **165** are examples, and that a different dielectric structure may be used in place of the oxide layer **169** and the etch stop layer **165**.

[0038] The substrate **177** may be a semiconductor substrate. A semiconductor substrate may be a bulk semiconductor substrate or a semiconductor on insulator (SOI) substrate. At least an upper portion of a semiconductor substrate is a semiconductor. The semiconductor may be silicon (Si), a group III-V semiconductor (e.g., GaAs) or some other binary semiconductor, a tertiary semiconductor (e.g., AlGaAs), a higher order semiconductor, the like, or any other suitable semiconductor. In some embodiments, the semiconductor is silicon (Si) or the like. Semiconductor devices **179** may be formed on the substrate **177** during FEOL processing. The semiconductor devices **179** may be transistors, diodes, capacitors, memory cells, thyristors, resistors, the like, or any combination thereof.

[0039] The metal interconnect structure **161** may be formed using damascene or dual damascene processes. The bitline **173** and other wires **123** and vias **127** (see FIG. **1**) in the metal interconnect structure **161** may include one or more layers of copper (Cu), tungsten (W), ruthenium (Ru), palladium (Pd), platinum (Pt), cobalt (Co), nickel (Ni), zirconium (Zr), titanium (Ti), tantalum (Ta), aluminum (Al), conductive carbides, oxides, alloys of these metals, the like, or any other suitable conductive materials. One of the layers may be a diffusion barrier layer such as titanium (Ti), tantalum (Ta), titanium nitride (TiN), tantalum nitride (TaN), or the like. The interlevel dielectric **159** may include one or more layers of silicon dioxide (SiO.sub.2), a low K dielectric, or an extremely low K dielectric. A low K dielectric is one having a smaller dielectric constant than silicon dioxide (SiO.sub.2). Examples of low K dielectrics include borosilicate glass (BSG), phosphorus silicate glass (PSG), borophosphosilicate glass (BPSG), fluorosilicate glass (FSG), undoped silicate glass (USG), and the like. An extremely low K dielectric is a material having a dielectric constant of about 2.1 or less. An extremely low K dielectric may be a low K dielectric with porosity that lowers its effective dielectric constant.

[0040] Adjacent metallization layer M.sub.1-M.sub.X-1 may be separated by etch stop layers **156**. The etch stop layers **156** may include one or more layers of aluminum oxide (AlOx), silicon nitride (SiN), silicon carbide (SiC), silicon carbonitride (SiCN), silicon oxycarbide (SiOC), silicon oxycarbonitride (SiOCN), combinations thereof, or the like.

[0041] The oxide layer **169** may be, for example, silicon dioxide (SiO.sub.2), a low K dielectric, or

an extremely low K dielectric. The oxide layer **169** may be deposited by ALD, CVD, PVD, the like, or any other suitable processes. The etch stop layer **165** may be, for example, aluminum oxide (AlOx), silicon nitride (SiN), silicon carbide (SiC), silicon carbonitride (SiCN), silicon oxycarbide (SiOC), silicon oxycarbonitride (SiOCN), combinations thereof, or the like. These layers may be deposited by physical vapor deposition (PVD), chemical vapor deposition (CVD), atomic layer deposition (ALD), the like, or another suitable process(es).

[0042] As shown by the cross-sectional view **700** of FIG. 7, the method may continue with formation of a mask **701** and using it to etch a via opening **703** through the etch stop layer **165** and the oxide layer **169**. The mask **701** and other masks used in processes of this disclosure may be or comprise a photoresist, a hard mask, or the like and may be patterned by photolithography, ion beam lithography, the like, or some other suitable process. The etch process may be a dry etch such as a plasma etch, the like, or some other suitable etch process. After the etch process, the mask **701** may be stripped.

[0043] As shown by the cross-sectional view **800** of FIG. 8, the electrode stack **119** may be deposited over the structure shown by the cross-sectional view **700** of FIG. 7. The electrode stack **119** includes the first horizontal conductive layer **155**, the spacer dielectric **151**, and the second horizontal conductive layer **147**. The first horizontal conductive layer **155** may deposit in the opening **703** to provide the via **120**. The second horizontal conductive layer **147** and the first horizontal conductive layer **155** may have thicknesses in the range from about 5 nm to about 100 nm. In some embodiments, these layers have thicknesses in the range from about 5 nm to about 25 nm. In some embodiments, these layers have thicknesses in the range from about 25 nm to about 100 nm. Each of these layers may comprise one or more layers of molybdenum (Mo), titanium (Ti), tungsten (W), copper (Cu), ruthenium (Ru), chromium (Cr), nickel (Ni), titanium nitride (TiN), tantalum nitride (TaN), or the like, a conductive oxide such as indium oxide (InO), indium tin oxide (InSnO), or the like, a combination of the foregoing, or any other suitable conductive materials. In some embodiments, the second horizontal conductive layer **147** includes a top metal layer of titanium nitride (TiN), tantalum nitride (TaN), or the like. The top metal layer may have thicknesses in the range from about 5 nm to about 50 nm. The conductive layers may be deposited by PVD, CVD, ALD, electroplating, electroless plating, the like, or any other suitable process(es).

[0044] The spacer dielectric **151** may be silicon dioxide (SiO₂), silicon oxynitride (SiON), the like, or any other suitable dielectric(s). The spacer dielectric **151** may have a thickness in the range from about 10 nm to about 100 nm. In some embodiments, the spacer dielectric **151** has a thickness in the range from about 10 nm to about 30 nm. In some embodiments, the spacer dielectric **151** has a thickness in the range from about 30 nm to about 100 nm. The spacer dielectric **151** may be deposited by PVD, CVD, ALD, the like, or any other suitable process.

[0045] As shown by the cross-sectional view **900** of FIG. 9, a mask **901** may be formed and used to pattern the electrode stack **119**. This patterning process defines the drain electrode **118** from the first horizontal conductive layer **155**. The patterning process may be a dry etch such as a plasma etch, the like, or some other suitable etch process.

[0046] As shown by the cross-sectional view **1000** of FIG. 10, a mask **1001** may be formed and used to further pattern an upper portion of the electrode stack **119** that includes the second horizontal conductive layer **147** and the spacer dielectric **151**. Optionally, the mask **1001** is formed by trimming the mask **901**. This patterning process creates the sidewall **110**, which includes the second horizontal conductive layer **147** and the spacer dielectric **151**. The sidewall **110** is in alignment with an edge **1003** of the mask **1001**. This patterning process also shapes the source electrode **116**, which also provides the bottom electrode **149**, from the second horizontal conductive layer **147**. A difference in the shape of the mask **1001** from the shape of the mask **901** (see FIG. 9) exposes the jutting portion **117** of the drain electrode **118**. The patterning process may be a dry etch such as a plasma etch, the like, or some other suitable etch process. After the etch process, the mask **1001** may be stripped.

[0047] As shown by the cross-sectional view **1100** of FIG. **11**, the semiconductor layer **114** may be formed over the structure shown by the cross-sectional view **1000** of FIG. **10** so that the semiconductor layer **114** is brought into contact with source electrode **116** and the drain electrode **118** without causing etch damage to the semiconductor layer **114**. As shown by the cross-sectional view **1200** of FIG. **12**, a mask **1201** may be formed and used to pattern the semiconductor layer **114**. Patterning removes the semiconductor layer **114** from a second region **185** while leaving a portion of the semiconductor layer **114** in a first region **181**. The semiconductor layer **114** may be deposited by PVD, CVD, ALD, the like, or any other suitable process. Alternatively, the semiconductor layer **114** be selectively grown in areas where the semiconductor layer **114** is desired.

[0048] The semiconductor layer **114** may be an oxide semiconductor or the like. In some embodiments, the oxide semiconductor has the formula $\text{In}_{\text{sub.x}}\text{Ga}_{\text{sub.y}}\text{Zn}_{\text{sub.z}}\text{MO}$, where M is titanium (Ti), aluminum (Al), silver (Ag), tungsten (W), cerium (Ce), or tin (Sn) and x is in the range from 0 to 1, y is in the range from 0 to 1, and z is in the range from 0 to 1. Examples include indium gallium oxide (IGO), indium zinc oxide (IZO), indium tungsten oxide (IWO), indium gallium zinc oxide (IGZO), zinc oxide (ZnO), aluminum zinc tin oxide (AZTO), indium titanium oxide (InTiO), gallium zinc oxide (GZO), indium oxide ($\text{InO}_{\text{sub.2}}$), gallium oxide ($\text{Ga}_{\text{sub.2}}\text{O}_{\text{sub.3}}$), and the like, with or without tin (Sn) or other dopants. The semiconductor layer **114** may have a thickness in the range from about 3 nm to about 50 nm. In some embodiments, the thickness is in the range from about 3 nm to about 10 nm. In some embodiments, the thickness is in the range from about 10 nm to about 50 nm.

[0049] As shown by the cross-sectional view **1300** of FIG. **13**, the gate stack **106** may be formed over the structure shown by the cross-sectional view **1200** of FIG. **12**. The gate stack **106** includes a gate dielectric layer **1301** and a gate electrode layer **1303**. In some embodiments, the gate dielectric layer **1301** is a high κ dielectric. Examples of high κ dielectrics include zirconium oxide ($\text{ZrO}_{\text{sub.2}}$), hafnium oxide ($\text{HfO}_{\text{sub.2}}$), hafnium silicon oxide (HfSiO), hafnium titanium oxide (HfTiO), hafnium lanthanum oxide (HfLaO), hafnium silicon oxide (HfSiO), hafnium tantalum oxide (HfTaO), hafnium zirconium oxide (HfZrO), and the like. Some additional examples include hafnium titanium oxide (HfTiO), hafnium oxide aluminum oxide ($\text{HfO}_{\text{sub.2}}\text{-Al}_{\text{sub.2}}\text{O}_{\text{sub.3}}$) alloy, tantalum oxide ($\text{Ta}_{\text{sub.2}}\text{O}_{\text{sub.5}}$), aluminum oxide ($\text{Al}_{\text{sub.2}}\text{O}_{\text{sub.3}}$), yttrium oxide ($\text{Y}_{\text{sub.2}}\text{O}_{\text{sub.3}}$), lanthanum oxide ($\text{La}_{\text{sub.2}}\text{O}_{\text{sub.3}}$), strontium titanium oxide ($\text{SrTiO}_{\text{sub.3}}$), and the like. In some embodiments, the high K dielectric has a dielectric constant of about 6 or more. The gate dielectric layer **1301** may have a thickness in the range from about 3 nm to about 50 nm. In some embodiments, the thickness is in the range from about 3 nm to about 10 nm. In some embodiments, the thickness is in the range from about 10 nm to about 50 nm. The gate dielectric layer **1301** may be deposited by ALD, CVD, PVD, the like, or any suitable process.

[0050] The gate electrode layer **1303** may be or comprise one or more layers of conductors. The conductors may be metals such as tungsten (W), titanium nitride (TiN), tantalum nitride (TaN), ruthenium (Ru), nickel (Ni), and the like or conductive oxides such as indium oxide (InO), indium tin oxide (InSnO), or the like, or any other suitable conductive material(s). The gate electrode layer **1303** may have a thickness in the range from about 5 nm to about 100 nm. In some embodiments, the gate electrode layer **1303** has a thickness in the range from about 5 nm to about 25 nm. In some embodiments, the gate electrode layer **1303** has a thickness in the range from about 25 nm to about 100 nm. The gate electrode layer **1303** may be deposited by PVD, CVD, ALD, electroplating, electroless plating, the like, or any other suitable process(es).

[0051] As shown by the cross-sectional view **1400** of FIG. **14**, a mask **1401** may be formed and an etch process carried out to pattern the gate stack **106**. Etching separates the gate electrode **111** from the top electrode **139**, both of which are patterned from the gate electrode layer **1303** (see FIG. **13**). A first portion of the gate dielectric layer **1301** that is in the first region **181** provides the gate dielectric layer **112** of the BEOL transistor **107** and a second portion of the gate dielectric layer

1301 that is in the second region **185** provides the dielectric layer **143** of the memory cell **137A**. The second horizontal conductive layer **147** provides both the source electrode **116** of the BEOL transistor **107** and the bottom electrode **149** of the memory cell **137A**. Etching stops in or before the second horizontal conductive layer **147** so that the source electrode **116** and the bottom electrode **149** remain a single undivided structure. After etching, the mask **1401** may be stripped. [0052] As shown by the cross-sectional view **1500** of FIG. **15**, a layer of the interlevel dielectric **159** may be formed over the structure shown by the cross-sectional view **1400** of FIG. **14**. The interlevel dielectric **159** may be one or more layer of dielectrics such as silicon oxide, a low K dielectric (dielectric constant less than 3.9), or an extremely low K dielectric (dielectric constant 2.1 or less). The interlevel dielectric **159** may be deposited by PVD, CVD, the like, or any other suitable process. A planarization process such as chemical mechanical polishing (CMP) may be carried out after the deposition.

[0053] As shown by the cross-sectional view **1600** of FIG. **16**, the interlevel dielectric **159** may be patterned with opening **1601**. As shown by the cross-sectional view **1700** of FIG. **17**, the openings **1601** may be filled with metal to provide vias **105** and **135**, the word line **101**, and the ground rail **131**. The metal may be copper (Cu), tungsten (W), aluminum (Al), titanium (Ti) tantalum (Ta), the like, or any other suitable metal. The metal may be deposited by CVD, PVD, electroplating, electroless plating, or the like. After deposition, excess metal may be removed by a planarization process such as CVD or the like.

[0054] FIGS. **18-22** provide a series of cross-sectional views exemplifying a variation on the method illustrated by the cross-sectional views of FIGS. **6-17**. This variation may provide the IC device **200** of FIG. **2** or some other IC device in which the internal structure **201** of the memory cell has a distinct composition from the gate dielectric layer **112** (see FIG. **2**).

[0055] The variation may begin from where the gate stack **106** has been deposited as shown by the cross-sectional view **1300** of FIG. **13**. As shown by the cross-sectional view **1800** of FIG. **18**, in this variation the gate stack **106** is patterned with a mask **1801** so that the gate stack **106** is removed from the second region **185**. The gate stack **106** may be patterned to the footprint of the semiconductor layer **114**. Optionally, the semiconductor layer **114** is patterned together with the gate stack **106**.

[0056] As shown by the cross-sectional view **1900** of FIG. **19**, a layer of the interlevel dielectric **159** is formed over the structure shown by the cross-sectional view **1800** of FIG. **18**. As shown by the cross-sectional view **2000** of FIG. **20**, a mask **2001** may be formed and used to etch an opening through the interlevel dielectric **159** over the bottom electrode **149** in the second region **185**.

[0057] As shown by the cross-sectional view **2100** of FIG. **21**. The internal structure **201** and top electrode metal layer **2005** may be deposited so as to fill the opening **2003**. The bottom electrode **149**, the internal structure **201**, top electrode metal layer **2005** together form a memory cell stack **2007**. Examples of materials suitable for the top electrode metal layer **2005** include materials suitable for the second horizontal conductive layer **147** and materials suitable for the gate electrode **111**. The composition and thickness of the internal structure **201** depend on the type of memory cell to be formed. If the memory cell is a DRAM memory cell, the internal structure **201** is a dielectric such as a high κ dielectric.

[0058] If the memory cell is an FeRAM memory cell, the internal structure **201** comprises a ferroelectric material. The ferroelectric material may be, for example, a binary oxide, a ternary oxide, or a quaternary oxide. In some embodiments the ferroelectric material is a binary oxide such as hafnium oxide (HfO.sub.x) or the like. In some embodiments the ferroelectric material is a ternary oxide such as hafnium silicate (HfSiO.sub.x), hafnium zirconate (HfZrO.sub.x), barium titanate (BaTiO.sub.3), lead titanate (PbTiO.sub.3), strontium titanate (SrTiO.sub.3), calcium manganite (CaMnO.sub.3), bismuth ferrite (BiFeO.sub.3), aluminum scandium nitride (AlScN), aluminum gallium nitride (AlGaN), aluminum yttrium nitrate, silicon doped hafnium oxide, zirconium doped hafnium oxide, yttrium doped hafnium oxide, aluminum doped hafnium oxide,

gadolinium doped hafnium oxide, strontium doped hafnium oxide, lanthanum doped hafnium oxide, scandium doped hafnium oxide, germanium doped hafnium oxide, a combination thereof, or the like. In some embodiments the ferroelectric material is a quaternary oxide such as lead zirconate, barium strontium titanate (BaSrTiO.sub.x), strontium bismuth tantalate or the like.

[0059] If the memory cell is an ReRAM memory cell, the internal structure **201** comprises a resistive switching material. Examples of resistive switching materials include binary transition metal oxides such as nickel oxide (NiO), titanium dioxide (TiO.sub.2), copper oxide (CuOx) and the like, transition metal sulfides such as copper sulfide (CuS) and the like, perovskites such as strontium titanate (SrTiO), praseodymium calcium manganite (PCMO), and the like, organic charge transfer complexes such as copper-tetracyanoquinodimethane (CuTCNQ) and the like, organic donor—acceptor systems such as Ag-I-dicyanovinylidene (AIDCN) and the like.

[0060] If the memory cell is a conductive bridging (CBRAM) memory cell, the internal structure **201** comprises a solid-state electrolyte. Example of solid-state electrolytes include germanium selenium (GeSe), silver oxide (AgO), and the like.

[0061] If the memory cell a PCRAM memory cell, the internal structure **201** comprises a phase change material. Examples of phase change materials include chalcogenides such as germanium antimony tellurium (GeSbTe) silver indium antimony tellurium (AgInSbTe), and the like

[0062] If the memory cell is a MRAM memory cell, is to be formed cell the internal structure **201** comprises an MTJ. An MTJ comprises two ferromagnetic layers separated by a tunnel barrier layer. The ferromagnetic layers include a pinned layer and a free layer. Example of materials that may be suitable for the pinned layer include cobalt (Co), iron (Fe), boron (B), nickel (Ni), ruthenium (Ru), iridium (Ir), platinum (Pt), and the like. Example of materials that may be suitable for the tunnel barrier layer include magnesium oxide (MgO), aluminum oxide (AlO), nickel oxide (NiO), gadolinium oxide (GdO), tantalum oxide (TaO), molybdenum oxide (MoO), titanium oxide (TiO), tungsten oxide (WO), and the like. Example of materials that may be suitable for the free layer include cobalt (Co), iron (Fe), boron (B), iron cobalt (FeCo), nickel cobalt (NiCo), cobalt iron boride (CoFeB), iron boride (FeB), iron platinum (FePt), iron palladium (FePd), and the like.

[0063] As shown by the cross-sectional view **2200** of FIG. **22**, a planarization process may be carried out to remove portions of the top electrode metal layer **2005** that deposited outside the opening **2003**. The portion of the top electrode metal layer **2005** that remains in the opening **2003** provide the top electrode **139**. The planarization process may be CMP or the like. Planarization may leave the upper surface **205** of the top electrode **139** coplanar with the upper surface **203** of the gate electrode **111**.

[0064] FIGS. **23-25** provide a series of cross-sectional views exemplifying a variation on the method illustrated by the cross-sectional views of FIGS. **18-22**. This variation may provide the IC device **300** of FIG. **3** or some other IC device in which the memory cell **137C** has a three-dimensional structure.

[0065] The variation may begin after etching the opening **2003**, which is shown by the cross-sectional view **2000** of FIG. **20**. As shown by the cross-sectional view **2300** of FIG. **23**, in the present variation another mask **2301** is formed and used to etch pits **2303** in the second horizontal conductive layer **147**. The pits **2303** may go part way through or entirely through the second horizontal conductive layer **147**. As shown by the cross-sectional view **2400** of FIG. **24**, when the internal structure **201** and the top electrode metal layer **2005** are deposited in the opening **2003**, the internal structure **201** lines the pits **2303** and the top electrode metal layer **2005** extends into the pits **2303**. The process may continue with planarization as shown by the cross-sectional view **2500** of FIG. **25**.

[0066] FIGS. **26-41** provide a series of views exemplifying a method of forming an IC device in accordance with some embodiments. While FIGS. **26-41** are described with reference to various embodiments of a method, it will be appreciated that the structures shown in FIGS. **26-41** are not limited to the method but rather may stand alone separate from the method. While FIGS. **26-41** are

described as a series of acts, it will be appreciated that the order of the acts may be altered in other embodiments. While FIGS. **26-41** illustrate and describe a specific set of acts, some acts that are illustrated and or described may be omitted in some embodiments. Further, acts that are not illustrated and or described may be included. The method of FIGS. **26-41** may provide the IC device **500** of FIG. **5A** or some other IC device.

[0067] As shown by the cross-sectional view **2600** of FIG. **26**, the method may begin with formation of the vias **120** through the oxide layer **169** and the etch stop layer **165** (or other dielectric structure) to make connections to the bitline **173**. The vias **120** may be formed by a damascene process or some other suitable process.

[0068] As shown by the cross-sectional view **2700** of FIG. **27**, the method may continue with formation of the electrode stack **119**. The electrode stack **119** includes the first horizontal conductive layer **155**, the spacer dielectric **151**, and the second horizontal conductive layer **147**. In this example, the second horizontal conductive layer **147** includes a top metal layer **501**.

[0069] As shown by the cross-sectional view **2800** of FIG. **28A** and the plan view **2810** of FIG. **28B**, a mask **2801** may be formed and an etch process carried out to pattern the electrode stack **119**. This patterning process may shape the drain electrodes **118**.

[0070] As shown by the cross-sectional view **2900** of FIG. **29**, the mask **2801** may be trimmed. Trimming may include exposing and developing a photoresist. As shown by the cross-sectional view **3000** of FIG. **30A** and the plan view **3010** of FIG. **30B**, after trimming another etch process may be carried out with the mask **2801**. This etch process may stop on the first horizontal conductive layer **155**, may shape the source electrode **116**, and may create sidewalls **110**.

[0071] As shown by the cross-sectional view **3100** of FIG. **3100**, the semiconductor layer **114** and the gate dielectric layer **112** may be formed over the structure shown by the cross-sectional view **3000** of FIG. **30A**. As shown by the cross-sectional view **3200** of FIG. **32**, a layer of the interlevel dielectric **159** may then be deposited and planarized to provide a level surface.

[0072] As shown by the cross-sectional view **3300** of FIG. **33A** and the plan view **3310** of FIG. **33B**, a mask **3301** may be formed and an etch process carried out that patterns the semiconductor layer **114**. The etch may stop on the etch stop layer **165** so that the patterning process creates edges **509** of the drain electrodes **118** in addition to edges **507** of the semiconductor layers **114**. The etch may form the gap **3305** and separate the drain electrode **118** on the right from the drain electrode **118** on the left. Alternatively, this separation may be achieved with the etch illustrated by the cross-sectional view **2800** of FIG. **28A** and the plan view **2810** of FIG. **28B**, however, in that alternative process the semiconductor layer **114** deposits in gap **3305**. The present etch may then remove the semiconductor layer **114** from the gap **3305**. But the illustrated process sequence in which the present etch separates the drain electrodes **118** allows for less etching of the semiconductor layer **114** and may provide a device that has lower leakage.

[0073] As shown by the cross-sectional view **3400** of FIG. **34**, the high κ dielectric layer **503** and an additional layer of the interlevel dielectric **159** may be deposited over the structure shown by the cross-sectional view **3300** of FIG. **33A**. The high κ dielectric layer **503** coats the edges **507** of the semiconductor layers **114** and edges **509** of the drain electrodes **118**. The high K dielectric layer **503** may be as thin or thinner than the gate dielectric layer **112**.

[0074] As shown by the cross-sectional view **3500** of FIG. **35**, a planarization process such as CMP or the like may be carried out to provide a level surface **3501**. As shown by the cross-sectional view **3600** of FIG. **36A** and the plan view **3610** of FIG. **36B**, a mask **3601** may be formed and an etch process carried out to form openings **3603**. This etch may stop on the top metal layer **501**.

[0075] As shown by the cross-sectional view **3700** of FIG. **37**, a mask **3701** may be formed and an etch process may be carried out to form pits **3703** in the source electrodes **116**. This etch may also form the gap **3705** between the source electrodes **116**. The etch may be a dry etch such as a plasma etch or the like.

[0076] As shown by the cross-sectional view **3800** of FIG. **38**, another etch may be carried out to

expose the gate dielectric layer **112** over the channels **109**. This etch process is selective for removing the interlevel dielectric **159** without damaging the gate dielectric layer **112**. In some embodiments, this is a wet etch. The top metal layer **501** may protect the source electrodes **116** during this etch process.

[0077] As shown by the cross-sectional view **3900** of FIG. **39**, the internal structure **201** and the top electrode metal layer **2005** are deposited over the structure shown by the cross-sectional view **3800** of FIG. **38**. The internal structure **201** and the top electrode metal layer **2005** fill the pits **3703** in the source electrodes **116**. As shown by the cross-sectional view **4000** of FIG. **40A** and the plan view **4010** of FIG. **40B**, a planarization process such as CMP or the like may be carried out. After planarization, a first remaining portion of the top electrode metal layer **2005** provides the gate electrode **111** and a second remaining portion of the top electrode metal layer **2005** provides the top electrodes **139**.

[0078] As shown by the cross-sectional view **4100** of FIG. **41A** and the plan view **4110** of FIG. **41B**, an additional layer of the interlevel dielectric **159** may be deposited and a dual damascene process carried out to form the vias **105** and **135**, the word lines **101**, and the ground rails **131**. Alternatively, the word lines **101** and or the ground rails **131** may be disposed in a subsequently formed metallization layer.

[0079] FIGS. **42-44** present flow chart for some processes that may be used to form an integrated circuit device according to the present disclosure. While the processes of FIG. **42-44** are illustrated and described herein as series of acts or events, it will be appreciated that the illustrated ordering of such acts or events is not to be interpreted in a limiting sense. For example, some acts may occur in different orders and or concurrently with other acts or events apart from those illustrated and or described herein. Further, not all illustrated acts are required to implement some aspects of the present disclosure or the embodiments thereof, and one or more of the acts depicted may be carried out in one or more separate acts and or phases.

[0080] The process **4200** of FIG. **42** may begin with act **4201**, forming a metal interconnect structure including a bitline. The cross-sectional views **600** of FIGS. **6** and **2600** of FIG. **26** provide examples.

[0081] Act **4203** is depositing an electrode stack. The electrode stack includes two electrode layers separated by a spacer layer. The cross-sectional views **800** of FIGS. **8** and **2700** of FIG. **27** provide examples.

[0082] Act **4205** is patterning the electrode stack to provide a sidewall that includes the spacer layer. The cross-sectional views **1000** of FIGS. **10** and **300** of FIG. **30A** provide examples.

[0083] Act **4207** is forming a semiconductor layer on the sidewall. The cross-sectional views **1100** of FIGS. **11** and **3100** of FIG. **31** provide examples.

[0084] Act **4209** is removing the semiconductor layer from a memory cell region. The memory cell region is a region where memory cells will be formed. The cross-sectional views **1200** of FIG. **12**, **1800** of FIGS. **18**, and **3600** of FIG. **36A** provide examples. This step may be avoided if the semiconductor layer is provided by a selective growth process so that the semiconductor layer is not formed in the memory cell region.

[0085] Act **4211** is an optional step of etching pits in the electrode stack within the memory cell region. The depth of the pits may be limited to the uppermost electrode of the electrode stack. The cross-sectional views **2300** of FIGS. **23** and **3700** of FIG. **37** provide examples.

[0086] Act **4213** is depositing a gate dielectric layer. The cross-sectional views **1300** of FIG. **13**, **3100** of FIG. **31** provide examples.

[0087] Act **4215** is depositing a gate electrode layer. The cross-sectional views **1300** of FIGS. **13** and **3900** of FIG. **39** provide examples.

[0088] Act **4217** is etching that separates the gate electrode layer from the top capacitor plate. The cross-sectional view **1400** of FIG. **14** provides an example.

[0089] The process **4300** of FIG. **43** contains many of the same steps as the process **4200** of FIG.

42. The process **4300** differs beginning with act **4301**, etching to remove the gate dielectric layer and the gate electrode layer from the memory region. The cross-sectional view **1800** of FIG. **18** provides an example of this alternative processing. Optional the semiconductor layer is removed from the memory cell region at this stage of processing rather than at an earlier stage.

[0090] Act **4303** is depositing a dielectric fill material and planarizing. The dielectric fill may be an interlevel dielectric. The cross-sectional views **1900** of FIGS. **19** and **3200** of FIG. **32** provide examples.

[0091] Act **4305** is etching to expose the electrode stack in the memory cell region. The cross-sectional views **2000** of FIGS. **20** and **3600** of FIG. **36A** provide examples. Optionally, act **4211** is then carried out to form pits in the electrode stack.

[0092] Act **4307** is depositing the internal structure of a memory cell, which may be either a dielectric layer or a data storage structure. The cross-sectional views **2100** of FIG. **21**, **2400** of FIGS. **24**, and **3900** of FIG. **39** provide examples.

[0093] Act **4309** is forming the top electrode layer. The cross-sectional views **2100-2200** of FIG. **21-22** provide one example. The cross-sectional views **2400-2500** of FIG. **24-25** provide another example. The cross-sectional views **4000-4100** of FIG. **40A-41A** provide a third example.

[0094] The process **4400** of FIG. **44** contains many of the same steps as the processes **4200** and **4300** of FIGS. **42** and **43**. The process **4400** may differ beginning with act **4401**, forming a mask and patterning the electrode stack. This patterning may define edges of the drain electrode. The cross-sectional view **2800** of FIG. **28A** and the plan view **2810** of FIG. **28B** provide an example.

[0095] Act **4403** is trimming the mask. The cross-sectional view **2900** of FIG. **29** provides an example. Act **4405** is using the trimmed mask to shape the source electrodes and to define sidewalls that include the spacer layer. The cross-sectional view **3000** of FIG. **30A** and the plan view **3010** of FIG. **30B** provide an example.

[0096] Act **4407** is forming a mask and carrying out an etch to divide two adjacent drain electrodes. The cross-sectional view **3300** of FIG. **33A** and the plan view **3310** of FIG. **33B** provide an example.

[0097] Act **4409** is coating exposed sidewalls of the semiconductor layer and the drain electrode with high κ dielectric. Act **4411** is depositing another dielectric layer and planarizing. The cross-sectional view **3400** of FIG. **34** provides an example.

[0098] With act **4305**, the electrode stack is exposed in the memory cell regions. With act **4307**, the internal structure of the memory cells is deposited.

[0099] Act **4413** is etching to expose the gate dielectric over the channels. The cross-sectional views **3700** of FIGS. **37** and **3800** of FIG. **38** provide an example.

[0100] The top electrode layer is deposited with act **4309**. This deposition may also provide metal for the gate electrode. Act **4415** is planarizing the top electrode layer, which defines the gate electrode from this metal. The cross-sectional views **3900** of FIGS. **39** and **4000** of FIG. **40A** provide an example of this processing.

[0101] Some aspects of the present disclosure relate to an integrated circuit device that include a metal interconnect structure over the semiconductor substrate. A first transistor disposed within the metal interconnect structure include a first source/drain electrode, a second source/drain electrode, a channel, a gate dielectric, and a gate electrode. The second source/drain electrode is vertically stacked over the first source/drain electrode and is separated from the first source/drain electrode by a dielectric spacer. The dielectric spacer has a sidewall extending from the second source/drain electrode to the first source/drain electrode. The channel is provided by a semiconductor layer that forms a coating on the sidewall. The gate dielectric is between the gate electrode and the channel.

[0102] In some embodiments, the semiconductor layer comprises an oxide semiconductor and the gate dielectric comprises a high κ dielectric. In some embodiments, the semiconductor layer extends above the second source/drain electrode. In some embodiments, the integrated circuit device further includes a second transistor. The second transistor shares the gate electrode with the

first transistor, and the first transistor and the second transistor are symmetrical about the gate electrode.

[0103] In some embodiments, the integrated circuit device further includes a memory cell, wherein the second source/drain electrode extends laterally to provide a bottom electrode for the memory cell. In some embodiments, the dielectric spacer and the first source/drain electrode extend directly beneath the memory cell. In some embodiments, the memory cell is a capacitor. In some embodiments, the memory cell includes a distinct layer of material that has a composition and thickness equivalent to the gate dielectric. In some embodiments, the memory cell has a top electrode with a composition and thickness equivalent to the gate electrode. In some embodiments, the memory cell has a top electrode, and the top electrode and the gate electrode have coplanar upper surfaces. In some embodiments, the semiconductor layer extends to a height above the bottom electrode for the memory cell. In some embodiments, the metal interconnect structure comprises two adjacent metallization layers, and the first transistor and the memory cell are between the two adjacent metallization layers.

[0104] In some embodiments, the bottom electrode is pitted so that the memory cell has a three-dimensional structure. In some embodiments, the bottom electrode has internal sidewalls that define pits having elliptical horizontal cross-sections. In some embodiments, the bottom electrode has internal sidewalls that define pits having circular horizontal cross-sections. In some embodiments, the bottom electrode has internal sidewalls that define trenches.

[0105] Some aspects of the present disclosure relate to an integrated circuit device that include a metal interconnect structure over the semiconductor substrate. An electrode stack within the metal interconnect structure includes a second electrode layer over a dielectric spacer over a first electrode layer. The electrode stack has a sidewall comprising the second electrode layer and the dielectric spacer. An oxide semiconductor layer is over the sidewall. A gate stack is disposed over the oxide semiconductor layer. The gate stack includes a high κ dielectric layer, and a gate electrode. The electrode stack and the gate stack form a transistor for which the second electrode layer and the first electrode layer provide a source electrode and a drain electrode.

[0106] In some embodiments, the integrated circuit device further includes a memory cell having a data storage structure in direct contact with the second electrode layer. In some embodiments, the integrated circuit device further includes a memory cell having a dielectric layer in direct contact with the second electrode layer.

[0107] Some aspects of the present disclosure relate to a method of manufacturing an integrated circuit device that includes forming a metallization layer over a semiconductor, forming a first source/drain electrode layer over the metallization layer, forming a spacer layer over the first source/drain electrode layer, forming a second source/drain electrode layer over the spacer layer, and etching through the second source/drain electrode layer and the spacer layer. The etching forms a sidewall comprising the second source/drain electrode layer and the spacer layer. The method further includes forming a semiconductor layer that coats the sidewall, forming a gate dielectric layer over the semiconductor layer, and depositing a gate electrode layer over the gate dielectric layer.

[0108] In some embodiments, the method further includes masking the semiconductor layer in a first region while etching to remove the semiconductor layer from a second region prior to forming the gate dielectric layer. In some embodiments, forming the semiconductor layer includes a selective growth process so that the semiconductor layer forms in the first region but does not form in the second region. In some embodiments, the method further includes etching to pattern a stack comprising the first source/drain electrode layer, the spacer layer, and the second source/drain electrode layer using a first mask, trimming the first mask, and using the trimmed mask to form the sidewall.

[0109] In some embodiments, etching through the second source/drain electrode layer and the spacer layer forms a first source electrode and a second source electrode, and the method further

includes depositing a first dielectric over the first source electrode and the second source electrode, etching a first opening between the first source electrode and the second source electrode, wherein the first opening extends through the first dielectric, the gate dielectric layer, and the semiconductor layer, etching the first opening forms a semiconductor layer sidewall, and etching the first opening exposes a first source/drain electrode layer sidewall, lining the first opening with a high κ dielectric layer, wherein the high κ dielectric layer covers the semiconductor layer sidewall and the first source/drain electrode layer sidewall, and filling the first opening with a second dielectric.

[0110] In some embodiments, etching the first opening divides a first portion of the first source/drain electrode layer into a first drain electrode and a second drain electrode. In some embodiments, the method further includes etching a second opening between the first source electrode and the second source electrode, wherein etching exposes the gate dielectric layer and the gate electrode layer deposits within the second opening. In some embodiments, etching the second opening comprises an etch process that is selective for etching the first dielectric compared to the high κ dielectric layer. In some embodiments, etching through the second source/drain electrode layer and the spacer layer forms a first source electrode and a second source electrode, and the method further includes depositing a first dielectric over the first source electrode and the second source electrode, and etching a first opening between the first source electrode and the second source electrode, wherein the first opening extends through the first dielectric, the gate dielectric layer, the semiconductor layer, and the first source/drain electrode layer, etching forms a semiconductor layer sidewall and a source/drain electrode layer sidewall, and the first opening divides a first portion of the first source/drain electrode layer beneath the first source electrode from a second portion of the second source/drain electrode layer beneath the second source electrode.

[0111] In some embodiments, the second source/drain electrode layer provides a bottom electrode for a memory cell in the second region. In some embodiments, the gate electrode layer provides a top electrode for the memory cell. In some embodiments, the memory cell is a capacitor, and the gate dielectric layer provides an insulating layer for the capacitor. In some embodiments, the method further includes etching a pit in the second source/drain electrode layer within the second region, wherein a top electrode of the memory cell extends into the pit. In some embodiments, depositing the gate electrode layer forms the top electrode.

[0112] In some embodiments, the method further includes etching to remove the gate electrode layer and the gate dielectric layer from the second region and forming a memory cell stack in the second region, wherein the second source/drain electrode layer provides a bottom electrode layer for the memory cell stack. In some embodiments, the method further includes etching a pit in the second source/drain electrode layer within the second region, wherein portions of the memory cell stack deposit within the pit.

[0113] The foregoing outlines features of several embodiments so that those skilled in the art may better understand the aspects of the present disclosure. Those skilled in the art should appreciate that they may readily use the present disclosure as a basis for designing or modifying other processes and structures for carrying out the same purposes and or achieving the same advantages of the embodiments introduced herein. Those skilled in the art should also realize that such equivalent constructions do not depart from the spirit and scope of the present disclosure, and that they may make various changes, substitutions, and alterations herein without departing from the spirit and scope of the present disclosure.

Claims

1. An integrated circuit device, comprising: a semiconductor substrate; a metal interconnect structure over the semiconductor substrate; and a first transistor within the metal interconnect structure; wherein the first transistor comprises a first source/drain electrode, a second source/drain

electrode, a channel, a gate dielectric, and a gate electrode; the second source/drain electrode is vertically stacked over the first source/drain electrode, and is separated from the first source/drain electrode by a dielectric spacer; the dielectric spacer has a sidewall extending from the second source/drain electrode to the first source/drain electrode; the channel is provided by a semiconductor layer that forms a coating on the sidewall; and the gate dielectric is between the gate electrode and the channel.

2. The integrated circuit device of claim 1, wherein the semiconductor layer extends above the second source/drain electrode.
3. The integrated circuit device of claim 1, further comprising a second transistor, wherein the second transistor shares the gate electrode with the first transistor, and the first transistor and the second transistor are symmetrical about the gate electrode.
4. The integrated circuit device of claim 1, further comprising a memory cell, wherein the second source/drain electrode extends laterally to provide a bottom electrode for the memory cell.
5. The integrated circuit device of claim 4, wherein the dielectric spacer and the first source/drain electrode extend directly beneath the memory cell.
6. The integrated circuit device of claim 4, wherein the memory cell is a capacitor.
7. The integrated circuit device of claim 4, wherein the memory cell comprises a distinct layer that has a composition and thickness equivalent to the gate dielectric.
8. The integrated circuit device of claim 4, wherein the memory cell comprises a top electrode that has a composition and thickness equivalent to the gate electrode.
9. The integrated circuit device of claim 4, wherein the memory cell comprises a top electrode, and the top electrode and the gate electrode have coplanar upper surfaces.
10. The integrated circuit device of claim 4, wherein the semiconductor layer extends to a height above the bottom electrode for the memory cell.
11. The integrated circuit device of claim 4, wherein the metal interconnect structure comprises two adjacent metallization layers, and the first transistor and the memory cell are between the two adjacent metallization layers.
12. The integrated circuit device of claim 4, wherein the bottom electrode is pitted so that the memory cell has a three-dimensional structure.
13. An integrated circuit device, comprising: a semiconductor substrate; a metal interconnect structure over the semiconductor substrate; an electrode stack comprising a second electrode layer over a dielectric spacer over a first electrode layer, wherein the electrode stack is within the metal interconnect structure and has a sidewall comprising the second electrode layer and the dielectric spacer; an oxide semiconductor layer over the sidewall; and a gate stack comprising, a high κ dielectric layer, and a gate electrode, wherein the gate stack is disposed over the oxide semiconductor layer; wherein the electrode stack and the gate stack form a transistor for which the second electrode layer and the first electrode layer provide a source electrode and a drain electrode.
14. The integrated circuit device of claim 13, further comprising a memory cell having a data storage structure in direct contact with the second electrode layer.
15. A method of manufacturing an integrated circuit device, the method comprising: forming a metallization layer over a semiconductor substrate that comprises a first region and a second region; forming a first source/drain electrode layer over the metallization layer; forming a spacer layer over the first source/drain electrode layer; forming a second source/drain electrode layer over the spacer layer; forming a first mask; etching through the second source/drain electrode layer and the spacer layer, wherein the etching forms a sidewall aligned to an edge of the first mask, the sidewall comprises the second source/drain electrode layer and the spacer layer, and the sidewall is in the first region; forming a semiconductor layer that coats the sidewall; forming a gate dielectric layer over the semiconductor layer; and depositing a gate electrode layer over the gate dielectric layer.
16. The method of claim 15, further comprising masking the semiconductor layer in the first region

while etching to remove the semiconductor layer from the second region prior to forming the gate dielectric layer.

17. The method of claim 15, wherein forming the semiconductor layer comprises a selective growth process so that the semiconductor layer forms in the first region but does not form in the second region.

18. The method of claim 15, wherein the second source/drain electrode layer provides a bottom electrode for a memory cell in the second region.

19. The method of claim 18, wherein the gate electrode layer provides a top electrode for the memory cell.

20. The method of claim 18, wherein the memory cell is a capacitor, and the gate dielectric layer provides an insulating layer for the capacitor.
