

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250279398

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

Yang; Tzu-Hsien et al.

VERTICAL INTERCONNECT STRUCTURES IN THREE-DIMENSIONAL INTEGRATED CIRCUITS

Abstract

A 3D IC structure includes multiple die layers, such as a top die layer and a bottom die layer. The top die layer and/or the bottom die layer each includes devices such as computing units, Analog-to-Digital converters, analog circuits, RF circuits, logic circuits, sensors, Input/Output devices, and/or memory devices. The devices on the first and the second die layers are laterally surrounded by, or adjacent, vertical interconnect structures (VIS).

Inventors: Yang; Tzu-Hsien (Hsinchu City, TW), Noguchi; Hiroki (Hsinchu City, TW), Fujiwara; Hidehiro (Hsinchu, TW), Wang; Yih (Hsinchu City, TW)

Applicant: Taiwan Semiconductor Manufacturing Company, Ltd. (Hsinchu, TW)

Family ID: 82460354

Appl. No.: 19/088623

Filed: March 24, 2025

Related U.S. Application Data

parent US continuation 18620591 20240328 parent-grant-document US 12261152 child US 19088623

parent US division 17538029 20211130 parent-grant-document US 11978723 child US 18620591 us-provisional-application US 63168462 20210331

Publication Classification

Int. Cl.: H01L25/065 (20230101); H01L25/00 (20060101)

U.S. Cl.:

Background/Summary

PRIORITY CLAIM AND CROSS-REFERENCE [0001] The present application is a continuation of U.S. patent application Ser. No. 18/620,591, which is a divisional of U.S. patent application Ser. No. 17/538,029 and claims the benefit of U.S. Provisional Patent Application No. 63/168,462 titled “Through-Silicon Vias In Three-Dimensional Integrated Circuits” and filed on Mar. 31, 2021, of which the entire disclosures are hereby incorporated by reference in their entireties.

BACKGROUND

[0002] Three-dimensional (3D) stacked chips or integrated circuits (IC) are an integration technology that can be used in modern computing and electronic systems. Through-silicon vias (TSVs) are used to electrically connect two or more stacked dies. For example, a TSV can enable a heterogeneous integration of a computation die and a memory die to reduce the footprint of the stacked dies.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0003] Aspects of the present disclosure are best understood from the following detailed description when read with the accompanying figures. It is noted that, in accordance with the standard practice in the industry, various features are not drawn to scale. In fact, the dimensions of the various features may be arbitrarily increased or reduced for clarity of discussion.

[0004] FIG. 1 illustrates a 3D IC package in accordance with some embodiments;

[0005] FIG. 2 illustrates a first example 3D IC structure in accordance with some embodiments;

[0006] FIG. 3 illustrates connections between vertical interconnect structures on different die layers in the 3D IC in accordance with some embodiments;

[0007] FIG. 4 illustrates a first example of a layout of vertical interconnect structure cells in accordance with some embodiments;

[0008] FIG. 5 illustrates a second example of a layout of vertical interconnect structure cells in accordance with some embodiments;

[0009] FIG. 6 illustrates a block diagram of a first example of a die layer in accordance with some embodiments;

[0010] FIG. 7 illustrates a block diagram of a second example of a die layer in accordance with some embodiments;

[0011] FIG. 8 illustrates a second example of a 3D IC structure in accordance with some embodiments;

[0012] FIG. 9 illustrates a third example of a die layer in accordance with some embodiments;

[0013] FIG. 10 illustrates a fourth example of a die layer in accordance with some embodiments;

[0014] FIG. 11 illustrates a fifth example of a die layer in accordance with some embodiments;

[0015] FIG. 12 illustrates a flowchart of an example method of fabricating an IC layer in accordance with some embodiments;

[0016] FIG. 13 illustrates a flowchart of an example method of fabricating a 3D IC structure in accordance with some embodiments;

[0017] FIG. 14 illustrates an example system that is suitable for designing a 3D IC structure in accordance with some embodiments; and

[0018] FIG. 15 illustrates a block diagram of an example integrated circuit manufacturing system

and manufacturing flow in accordance with some embodiments.

DETAILED DESCRIPTION

[0019] The following disclosure provides many different embodiments, or examples, for implementing different features of the provided subject matter. Specific examples of components and arrangements are described below to simplify the present disclosure. These are, of course, merely examples and are not intended to be limiting. For example, the formation of a first feature over or on a second feature in the description that follows may include embodiments in which the first and second features are formed in direct contact, and may also include embodiments in which additional features may be formed between the first and second features, such that the first and second features may not be in direct contact. In addition, the present disclosure may repeat reference numerals and/or letters in the various examples. This repetition is for the purpose of simplicity and clarity and does not in itself dictate a relationship between the various embodiments and/or configurations discussed.

[0020] Further, spatially relative terms, such as “beneath,” “below,” “lower,” “above,” “upper” and the like, may be used herein for ease of description to describe one element or feature's relationship to another element(s) or feature(s) as illustrated in the figures. The spatially relative terms are intended to encompass different orientations of the device in use or operation in addition to the orientation depicted in the figures. The apparatus may be otherwise oriented (rotated 90 degrees or at other orientations) and the spatially relative descriptors used herein may likewise be interpreted accordingly.

[0021] Embodiments disclosed herein provide 3D IC structures that include multiple die layers, such as a top die layer and a bottom die layer. The top die layer and/or the bottom die layer includes devices such as computing units, Analog-to-Digital converters (ADCs), analog circuits, RF circuits, logic circuits, sensors, Input/Output (I/O) devices, and/or memory devices. Example memory devices include Static Random Access Memory (SRAM), Resistive Random Access Memory (RRAM), Dynamic Random Access Memory (DRAM), cache, and/or Flash Memory. Example computing units are microprocessors, field-programmable gate arrays, graphics processing unit, and the like.

[0022] Vertical interconnect structures (VIS) are formed in the die layers of a 3D IC structure. The VISs can be any suitable type of vertical interconnect structures, such as through-silicon vias (TSVs), through-glass vias (TGVs), and through-dielectric vias (TDVs). As will be described in more detail later, in one embodiment, the floorplan of the devices and the VISs in at least one die layer in a 3D IC differs from the floorplan of the devices and the VISs in another die layer in the 3D IC.

[0023] The VISs can be used to transmit power signals, data signals, and bias voltage signals (e.g., analog bias signals). The VISs in each die layer are arranged in a grid layout on the die layer. The VISs in a die layer may be arranged in a grid layout around the device or devices on the die layer. The grid layouts of the VISs can improve the fabrication process that is used to manufacture the die layer, which in turn may increase the yield of the VISs. Additionally or alternatively, when the density of the VISs is uniform on a die layer, the uniform density reduces the resistance between the VISs and the devices, and the IR drop in the power signals can be reduced.

[0024] FIG. 1 illustrates a 3D IC package in accordance with some embodiments. The 3D IC package **100** includes a substrate **102**. The substrate **102** may be any suitable type of substrate, such as a silicon-based substrate or a printed circuit board. Electrical connectors **104** are disposed between the substrate **102** and an interposer **106**. In the illustrated embodiment, the electrical connectors **104** are solder bumps, but other embodiments are not limited to this implementation. The electrical connectors **104** can be any suitable electrical connector, such as wire bonds or a ball grid array.

[0025] The electrical connectors **104** transmit power signals, data signals, and/or bias signals between the substrate **102** and the interposer **106**. The interposer **106** is configured to route the

signals between the electrical connectors **104** and the 3D IC **108**. The 3D IC **108** includes two or more die layers stacked vertically and one or more VIS in each die layer to electrically connect the die layers to each other. In some embodiments, the 3D IC **108** is a heterogeneous 3D IC where the types of devices on one die layer differ from the types of devices on another die layer. For example, the types of devices on a bottom die layer can be memory devices and the types of devices on a top die layer may be computing units. In other embodiments, the 3D IC **108** is a homogeneous 3D IC where the same type of devices is formed in and/or on the die layers.

[0026] As will be described in more detail later, the VISs in one die layer in the 3D IC **108** are arranged in a layout that can differ from the arrangement of the VISs in another die layer. The different layouts can vary to meet improved or optimum area usage and/or routing requirements. For example, an electronic design application (EDA) can be used to determine the best or optimum layout for the VISs in a die layer based on the power requirements of the devices on that die layer as well as the power requirements of the devices on any die layers disposed above the die layer.

[0027] Additionally or alternatively, the diameter, the pitch, and the density of the VISs are the same on one die layer but the diameter, the pitch, and/or the density of the VISs can differ on another die layer. The VIS layout, the diameter, the pitch, and the density of the VIS in each die layer are based on, for example, the power requirements of the devices on a die layer, the power requirements of the devices on an upper die layer(s), and/or the IR drop experienced by the power signals, data signals, and/or analog bias signals at the upper die layer(s). For example, when a 3D IC is formed with two die layers, the layout of the VISs in the bottom die layer is based on the power requirements of the devices on the bottom die layer, the power requirements of the devices on the top die layer, and/or the IR drop experienced by the power signals, data signals, and/or analog bias signals at the top die layer. The layout of the VISs in the top die layer is based on the power requirements of the devices on the top die layer. When the power signals are input into the 3D IC at the bottom die layer, the density of the VISs in the bottom die layer is typically greater than the density of the VISs in the top die layer because the VISs in the bottom die layer have to provide a sufficient or minimum amount of power to the devices on the top die layer to maintain the integrity of the operations of the devices on the top die layer.

[0028] FIG. 2 depicts an example 3D IC structure in accordance with some embodiments. The 3D IC structure **200** includes multiple die layers. For illustration purposes, FIG. 2 includes select portions of a 3D IC structure. Other portions that are not shown may be included in a 3D IC structure. For example, micro-bumps, molding regions, dummy regions, adhesion layers, a heat sink, interconnects, ball grid array (BGA) connectors, silicon interposers, and other components or structural elements may be included.

[0029] In the illustrated embodiment, the 3D IC structure **200** includes a die layer **200A** and a die layer **200B** disposed over the die layer **200A**. Other embodiments of a 3D IC structure can include additional die layers (e.g., 3, 5, or 8). In some embodiments, peripheral structures **202** can provide mechanical support and/or provide thermal conduction for heat dissipation.

[0030] The die layer **200A** includes devices **204**. Example devices **204** include, but are not limited to, memory devices and I/O devices. The die layer **200B** includes devices **206**. The devices **206** on the die layer **200B** may be the same type of devices or a variety of different devices. In a non-limiting embodiment, the devices **206** are computing units. In other embodiments, when the 3D IC structure is a heterogeneous 3D IC structure, the die layer **200A** can include one or more computing units and the die layer **200B** may include RF and analog circuits. In another example embodiment of a heterogeneous 3D IC, the die layer **200A** can include logic circuits and memory devices, and the die layer **200B** may include sensors, input/output (I/O) devices, and one or more computing units.

[0031] The die layer **200B** is electrically connected to the die layer **200A** through the VISs **208** on the die layer **200A** and the VISs **210** on the die layer **200B**. One or more devices **204** are electrically connected to one or more respective devices **206** through VISs **208**, **210**. As discussed

earlier, the VISs **208**, **210** include TSVs, TDVs, or other types of vertical interconnect structures. In the illustrated embodiment, the VISs **208**, **210** are TSVs. The TSVs can be power TSVs, data signal TSVs, and bias TSVs. For example, the VISs **208a** positioned around the periphery of the bottom die layer **200A** may be data signal TSVs and the VISs **208b** disposed between the devices **204** can be power TSVs.

[0032] The VISs **208** in the die layer **200A** are arranged in a first layout, while the VISs **210** on the die layer **200B** are arranged in a different second layout. As described earlier, the layout of the VISs **208** on the die layer **200A** is based at least on factors such as the power requirements of the devices **204** on the die layer **200A**, the power requirements of the devices **206** on the die layer **200B**, and/or the IR drop experienced by the power signals, data signals, and/or analog bias signals. The layout of the VISs **210** on the die layer **200B** is at least based on the power requirements of the devices **206** on the die layer **200B**. In some instances, the layouts of the VISs **208**, **210** can also be based on an improved or optimized consumption of the die area on the die layers **200A**, **200B**.

[0033] In the illustrated embodiment, a power supply **212** is electrically connected to the 3D IC structure **200** through electrical connectors, such as the electrical connectors **104** shown in FIG. **1**. The power supply **212** provides power to the devices **204**, **206** on the die layers **200A**, **200B**. The power is supplied to the die layers **200A**, **200B** through at least some of the VISs **208**, **210**.

[0034] As shown in FIG. **2**, the floorplan of the devices **204** and the VISs **208** on the die layer **200A** differs from the floorplan of the devices **206** and the VISs **210** on the die layer **200B**. The number of devices **204**, the number of VISs **208**, and the layout of the VISs **208** in the die layer **200A** is different from the number of devices **206**, the number of VISs **210**, and the layout of the VISs **210** in the die layer **200B**. Accordingly, the design and the fabrication of each die layer **200A**, **200B** can be optimized or selected based on the requirements of the respective die layers **200A**, **200B**. For example, when the device **206** is a processing unit, a more expensive fabrication process may be used to manufacture the die layer **200B** due to the high-speed requirements for the processing unit. Alternatively, when the devices **204** on the die layer **200A** include memory devices, analog devices, and/or a logic devices, a less expensive fabrication process can be used to manufacture the die layer **200A** due to the slower speed requirements of these types of devices.

[0035] FIG. **3** illustrates connections between VISs in different die layers in a 3D IC in accordance with some embodiments. The 3D IC **300** includes a die layer **302** positioned under a die layer **304**. The VISs **306a-306e** on the die layer **302** are arranged in a first layout **308**. The VISs **310a-310c** on the die layer **304** are arranged in a second layout **312**. As discussed earlier, the first and the second layouts **308**, **312** can differ based on improved die area consumption and/or the power requirements of the die layers **302**, **304**.

[0036] For example, the distance **314** between the VISs **306a-306e** (the “pitch” of the VISs **306a-306e**) is typically the same for the die layer **302**, and the pitch **316** for the VISs **310a-310c** in the die layer **304**. However, the pitch **314** differs from the pitch **316** in the illustrated embodiment. The pitch for the VISs in a particular die layer can be based on several factors. For example, the pitch **314**, **316** is defined by one or more design rules for a 3D IC. Additionally, in some embodiments, the minimum distance of the pitch **314**, **316** is limited by the fabrication process that is used to manufacture the respective die layer **302**, **304**. Each die layer in a 3D IC can be fabricated using a particular fabrication process for that die layer. For example, when a processing unit is formed on a die layer, a more expensive fabrication process may be used to manufacture the die layer due to the high-speed requirements for the processing unit. Alternatively, when a die layer includes memory devices, analog devices, and/or a logic devices a less expensive fabrication process can be used to manufacture the die layer due to the slower speed requirements of these types of devices.

[0037] Additionally or alternatively, the density of the VISs **306a-306e** and the density of the VISs **310a-310c** are based on one or more factors. The type of devices on a die layer (e.g., devices **204** on the die layer **200A**), the power requirements of the devices on the die layer (e.g., the devices **204** on the die layer **200A**), the power requirements of the devices on any die layers positioned over and

above of the die layer (e.g., the devices **206** on the die layer **200B**), and/or the IR drop experienced by the signals at any die layers positioned over and above the die layer are factors that are considered when determining the density of the VISs in a die layer. Additionally, the density of the VISs can vary across a die layer based on the factors. For example, the density of the VISs in one part of a die layer can differ from the density of the VISs in another part of the die layer based on the type of devices in each section of the die layer, the power requirements of the devices in each section on the die layer, the power requirements of the devices on any die layers positioned over and above of the die layer, and/or the IR drop experienced by the signals at any die layers positioned over and above the die layer.

[0038] Positioned between the die layers **302**, **304** is an intermediate conductive layer **318** (e.g., a redistribution layer). The electrical connections between the die layers **302**, **304** are implemented through the intermediate conductive layer **318**. The intermediate conductive layer **318** is patterned to produce one or more contacts (collectively contact **320**) and one or more signal lines (collectively signal line **322**). The contact **320** is used to electrically connect a VIS in the die layer **302** (e.g., VIS **306a**) to a VIS in the die layer **304** (e.g., VIS **310a**). The electrical connection between the VIS **306a** and the VIS **310a** is represented by the dashed line **324**.

[0039] Since the second layout **312** of the VISs **310a-310c** in the die layer **304** differs from the first layout **308** of the VISs **306a-306e** in the die layer **302**, the signal line **322** is used to route a signal from a VIS in one die layer to a respective VIS in another die layer. For example, as shown in FIG. **3**, the signal line **322** electrically connects the VIS **306b** on the die layer **302** to the VIS **310b** on the die layer **304**. The electrical connection between the VIS **306b** and the VIS **310b** is represented by the dashed lines **326**.

[0040] Although only one contact **320** and only one signal line **322** are shown in FIG. **3**, other embodiments can include any suitable number of contacts and signal lines in the intermediate conductive layer **318**. Additionally, although not shown in FIG. **3**, an insulating material is disposed around the contact **320** and the signal line **322** to electrically isolate the contact **320** and the signal line **322** from each other and from other contacts and/or signal lines in the intermediate conductive layer **318**.

[0041] FIG. **4** illustrates a first example of a layout of VIS cells in accordance with some embodiments. Lines **400**, **402**, **404**, **406** of VIS cells **408** are disposed adjacent the edges **410**, **412**, **416**, **414**, respectively, of a device **418**. A VIS cell **408** includes a VIS **420** and unused die area **422**. The size of the unused die area **422** can be based on one or more design rules and/or the requirements of the fabrication process that is used to manufacture the die layer.

[0042] The VIS cells **408** form a grid around the device **418**. When the device **418** is one of multiple devices on a die layer, the VIS cells **408** that are adjacent another device can be part of the grid of VIS cells around the other device (see e.g., FIGS. **6** and **7**). The device **418** can be a device on a bottom die layer (e.g., die layer **200A** in FIG. **2**), a device on a top die layer (e.g., die layer **200B** in FIG. **2**), or a device in an intermediate die layer (between a bottom die layer and a top die layer) in a 3D IC structure. The VISs **420** are formed in the VIS cells **408**. Although the device **418**, the VIS cells **408**, and the VISs **420** are shown as having a rectangular shape, other embodiments are not limited to this implementation.

[0043] In the illustrated embodiment, the VIS cells **408** surround the device **418** to form a grid and the lines **400**, **402**, **404**, **406** about the edges **410**, **412**, **416**, **414** of the device **418**. As described earlier, the pitch of the VISs **420** is typically the same for the VISs in a respective die layer due to one or more design rules and/or requirements of a fabrication process that is used to manufacture the die layer. In other embodiments, the number of lines **400**, **402**, **404**, **406** of VIS cells **408** can be fewer or greater.

[0044] FIG. **5** depicts a second example of a layout of VIS cells in accordance with some embodiments. Like FIG. **4**, lines **400**, **402**, **404**, **406** of VIS cells **408** are disposed adjacent each edge **410**, **412**, **416**, **414**, respectively, of a device **418**. The VIS cells **408** in the lines **400**, **402**, **404**,

406 form a grid around the device **418**.

[0045] A second line **500** of VIS cells **408** is adjacent and abuts the line **400**, and a second line **502** of VIS cells **408** is adjacent and abuts the line **402**. The number of VIS cells **408** in each line **400**, **402**, **404**, **406**, **500**, **502** can be the same number or the number of VIS cells **408** in one line may differ from the number of VIS cells **408** in another line. As noted earlier, the pitch of the VISs **420** is the same for the VISs **420** on the die layer.

[0046] In embodiments, the number of lines **400**, **402**, **404**, **406**, **500**, **502** that are adjacent to the device **418** can be fewer or greater. As shown in FIG. 5, the number of lines **400**, **500** adjacent the edge **410** is N, where $N=2$. The number of lines **402**, **502** adjacent the edge **412** is M, where $M=2$. The number of lines **404**, **406** adjacent the respective edges **416**, **414** is P and O, where $O=P=1$. In other embodiments, M, N, O, and P can each be any suitable number. For example, M, N, O, and P can each equal one (1), as shown in FIG. 4. Alternatively, M can equal one (1), N may equal one (1), O can equal one (1), and P may equal three (3).

[0047] The number of lines **400**, **402**, **404**, **406**, **500**, **502** of VIS cells **408** is based on the density of the VISs **420** on a die layer. As described earlier, the density of the VISs **420** is based on one or more factors. The type of devices on a die layer, the power requirements of the devices on the die layer, the power requirements of the devices on any die layers positioned over and above of the die layer, and/or the IR drop experienced by the signals at any die layers positioned over and above the die layer are factors that are considered when determining the density of the VISs **420** in a die layer. Additionally, the density of the VISs **420** can vary across a die layer based on one or more factors. For example, the density of the VISs **420** in one part of a die layer can differ from the density of the VISs **420** in another part of the die layer based on the type of devices in each section of the die layer, the power requirements of the devices in each section on the die layer, the power requirements of the devices on any die layers positioned over and above of the die layer, and/or the IR drop experienced by the signals at any die layers positioned over and above the die layer.

[0048] FIG. 6 depicts a block diagram of a first example of a die layer in accordance with some embodiments. In a non-limiting example, the die layer **600** is the bottom die layer **200A** in FIG. 2. Multiple devices **602** are disposed within or on the die layer **600**. As discussed earlier, example devices **602** include, but are not limited to, SRAM, RRAM, DRAM, and Flash memory devices, ADCs, I/O devices, and/or computing units.

[0049] In FIG. 6, the devices **602** can be the same type of devices (e.g., memory) or at least one type of device **602** (e.g., memory) may differ from another type of device **602** (e.g., logic circuit). In the example embodiment, a first grid **604** of VISs is formed on the die layer **600** such that each device **602** is laterally surrounded by a second grid **605** of VISs. FIG. 6 depicts first lines **606** of VISs (e.g., vertical or perpendicular lines with respect to the edge **608**) and second lines **610** of VISs (e.g., horizontal or parallel lines with respect to the edge **608**), and a center line **612** of VISs. The number and the arrangement of the VISs are for illustration purposes and other embodiments can have a fewer or a greater number of VISs that are positioned in any given layout.

[0050] The VISs can be power VISs that are configured to transmit power signals to the devices **602** and to the devices on one or more additional die layers attached to the die layer **600**. In one embodiment, the VISs positioned in the center line **612** of the grid **604** may be data signal VISs that transmit data signals between die layers in the 3D IC structure. Thus, the center line **612** is a signal trunk. In other embodiments, the data signal VISs can be positioned at other locations in a die layer. For example, the data signal VISs can be disposed at one or more of the first lines **606** that are located around the periphery of the die layer **600** (e.g., first lines **606'**).

[0051] In some embodiments, one or more signal lines electrically connects VISs to respective devices. For example, as shown in FIG. 6, the signal line **614** electrically connects the device **602'** to a VIS in the center line **612** of VISs. Although only one signal line **614** is depicted in FIG. 6, other embodiments can use any suitable number of signal lines to connect VISs to respective devices.

[0052] FIG. 7 illustrates a block diagram of a second example of a die layer in accordance with some embodiments. FIG. 7 shows that at least one device can consume a larger amount of area on a die layer **700** compared to other devices. Additionally, the area of one or more unused die areas can differ from the area of other unused die areas. Thus, the die areas used by the devices and/or the die areas used by the unused die areas can vary in some embodiments.

[0053] In a non-limiting example, the die layer **700** is the bottom IC layer **200A** in FIG. 2. Multiple devices **602** are disposed within and/or on the die layer **700**. As shown in FIG. 7, each of the devices **702**, **704** uses a greater amount of area on the die layer **700** compared to the amount of area used by each of the other device **602**. Additionally, the amount of area used by the unused die area **706** around a VIS (e.g., unused die area **422** in FIG. 4) that is adjacent the edges of the device **704** is greater than the amounts of area used by the unused die areas **708** around a VIS that is adjacent the device **702**. In some embodiments, the size or area of an unused die area is based on the type of device that is adjacent the VIS cells and/or a size of the device **602**, **702**, **704**.

[0054] Additionally or alternatively, one or more VISs can be removed (see area **710**) to provide additional die area for a larger device **602'** and/or to route signal lines. The determination of which VISs to remove is based on the power requirements of the device **602'**, the power requirements of the devices **602** around the device **602'**, and/or the power requirements of the devices on any die layers that are positioned over and above the die layer **700**.

[0055] FIG. 8 illustrates a second example of a 3D IC structure in accordance with some embodiments. The 3D IC structure **800** includes a top die layer **802**, a bottom die layer **804**, and intermediate die layers **806**, **808**. The top die layer **802** includes devices **206** and each of the die layers **804**, **806**, **808** includes one or more devices **204**.

[0056] In one embodiment, the lines **810** of VIS cells **408** are disposed in a grid on each die layer **802**, **804**, **806**, **808**. The VISs (e.g., VIS **420** in FIG. 4) in the VIS cells **408** are configured to transmit power signals, data signals, and/or analog bias signals between the die layers **802**, **804**, **806**, **808**. A center line **812** of VIS cells **408** on the top die layer **802**, the bottom die layer **804**, and on the intermediate die layers **806**, **808** can be configured to transmit data signals between the die layers **802**, **804**, **806**, **808**. Other embodiments can transmit data signals, power signals, and/or analog bias signals using any suitable grid layout of VIS cells **408** on each die layer **802**, **804**, **806**, **808**.

[0057] In one embodiment, a power supply **814** is operably connected to the bottom die layer **804** to provide power signals to the 3D IC **800**. In such embodiments, the density of the VISs in the bottom die layer **804** is greater than the density of the VISs in the intermediate die layer **808**. The density of the VISs in the intermediate die layer **808** is greater than the density of the VISs in the intermediate die layer **806**. The density of the VISs in the intermediate die layer **806** is greater than the density of the VISs in the top die layer **802**. The VIS densities on each die layer **802**, **804**, **806**, **808** increase from the top die layer **802** to the bottom die layer **804**. The density of the VISs in the bottom die layer **804** is greatest due to the power requirements of the devices **204**, **206** on all of the die layers **802**, **804**, **806**, **808**. Since the VISs in the bottom die layer **804** supply power signals to all of the die layers **802**, **804**, **806**, **808**, the density of the VISs in the bottom die layer **804** is based on the power requirements of the devices **204** on the bottom die layer **804**, the power requirements of the devices **204** on the intermediate die layer **808**, the power requirements of the devices **204** on the intermediate die layer **806**, the power requirements of the devices **206** on the top die layer **802**, and/or the IR drops produced as the power signals transmit from the bottom die layer **804** to the intermediate die layer **808**, from the intermediate die layer **808** to the intermediate die layer **806**, and from the intermediate die layer **806** to the top die layer **802**.

[0058] The density of the VISs in the intermediate die layer **808** is based on the power requirements of the devices **204** on the intermediate die layer **808**, the power requirements of the devices **204** on the intermediate die layer **806**, the power requirements of the devices **206** on the top die layer **802**, and/or the IR drops produced as the power signals transmit from the intermediate die

layer **808** to the intermediate die layer **806**, and from the intermediate die layer **806** to the top die layer **802**. Similarly, the density of the VISs in the intermediate die layer **806** is based on the power requirements of the devices **204** on the intermediate die layer **806**, the power requirements of the devices **206** on the top die layer **802**, and/or the IR drops produced as the power signals transmit from the intermediate die layer **806** to the top die layer **802**. The density of the VISs in the top die layer **802** is based on the power requirements of the devices **206** on the top die layer **802**.

[0059] Additionally, as discussed earlier, the pitch and the diameters of the VISs in a respective die layer **802**, **804**, **806**, **808** are the same but the pitch and the diameter of the VISs in one die layer can differ from the pitch and the diameter of the VISs in another die layer. In some embodiments, the density, the pitch, and the diameter of the VISs in each die layer differs from the pitch, the density, and the diameter of the VISs in all of the other die layers.

[0060] In other embodiments, a power supply is operably connected to a top die layer. In such embodiments, the densities of the VISs is greatest at the top die layer and decreases with each die layer below the top die layer. FIGS. **9-11** illustrate the die layers in a 3D IC where the density of the VISs is greatest at the top die layer and the densities of the VISs decrease with each die layer below the top die layer. FIG. **9** depicts a third example of a die layer in accordance with some embodiments. The die layer **900** is a bottom die layer in the 3D IC structure formed by the die layers **900**, **1000**, **1100** and includes a device **902**. One example of a device **902** is a computing unit. The VISs in the die layer **900** have a first density and are arranged in a grid layout around the device **902**.

[0061] FIG. **10** illustrates a fourth example of a die layer in accordance with some embodiments. The die layer **1000** is an intermediate die layer in the 3D IC structure formed by the die layers **900**, **1000**, **1100** and includes an array of four (4) devices **1002**. The devices **1002** may be the same type of devices or different types of devices. Example devices **1002** include RF devices, logic devices, analog devices, memory devices, computing units, or combinations thereof. The VISs in the die layer **1000** have a second density, are arranged in a grid layout on the die layer **1000**, and are arranged in a grid layout around each device **1002**. The second density of the VISs in the die layer **1000** is greater than the first density of the VISs in the die layer **900**.

[0062] FIG. **11** depicts a fifth example of a die layer in accordance with some embodiments. The die layer **1100** is a top die layer of the 3D IC structure formed by the die layers **900**, **1000**, and **1100** and includes an array of sixteen (16) devices **1102**. As discussed previously, the devices **1102** may be the same type of devices or different types of devices. Example devices **1102** include, but are not limited to, ADCs, analog circuits, RF circuits, logic circuits, I/O device, memory devices, or combinations thereof.

[0063] The VISs in the die layer **1100** have a third density, are arranged in a grid layout on the die layer **1100**, and are arranged in a grid layout around each device **1102**. A power supply **1104** is operably connected to the die layer **1100**. Thus, the VISs in the die layer **1100** support the power requirements of all of the devices **902**, **1002**, and **1102** in the 3D IC structure. Accordingly, the density of the VISs in the die layer **1100** is greater than the densities of the VISs in the die layers **900**, **1000**.

[0064] FIG. **12** illustrates a flowchart of an example method of fabricating a die layer in accordance with some embodiments. Initially, as shown in block **1200**, a substrate is provided. The substrate can be any suitable type of substrate. Example substrates include, but are not limited to, a silicon substrate, a silicon on insulator (SOI) substrate, a Sapphire substrate, or a compound substrate (e.g., a gallium arsenide substrate, a gallium nitride substrate).

[0065] Next, as shown in block **1202**, the locations for the devices and the locations for the VISs are determined. In one embodiment, the locations for the devices and the locations for the VISs are determined based on a device specification and a layout diagram. Additionally, the locations can be determined using an EDA. In some embodiments, some or all of the locations are established manually.

[0066] The VISs are formed at block **1204**. The VISs can be TSVs, TDVs, and other types of vertical interconnect structures. Any suitable process can be used to construct the VISs. For example, one technique for forming TSVs includes forming a first mask layer over the substrate and patterning the first mask layer to include openings where the VISs will be formed.

[0067] A conductive material is formed (e.g., deposited) in the openings. In a non-limiting example, the conductive material is deposited using a PVD process or a CVD process. The conductive material can be made of any suitable conductive material, such as copper, cobalt, aluminum, tungsten, doped polysilicon, other suitable conductive material, and/or combinations thereof.

[0068] The first mask layer is then removed, and a second mask layer is formed over the substrate. The second mask layer is patterned to include openings where insulating material will be formed around the conductive material. An insulating material is formed in the openings around the conductive material to electrically isolate the TSVs. The second mask layer is then removed.

[0069] The devices are formed within and/or on the substrate at block **1206**. Any suitable process can be used to construct the devices. One or more signal lines are formed at block **1208** to connect a device or devices to a select VIS in the die layer. The signal line(s) electrically connect a device or devices to a respective VIS.

[0070] FIG. **13** illustrates a flowchart of an example method of fabricating a 3D IC structure in accordance with some embodiments. Initially, as shown in block **1300**, a first die layer is processed. The processing of the first die layer includes forming the devices the VISs, and signal lines within and/or on the first die layer. Any suitable fabrication process can be used to construct the devices, the VISs, and the signal lines.

[0071] An intermediate conductive layer is formed on a surface of the first die layer and patterned to produce one or more contacts and/or one or more signal lines (block **1302**). In an example process, a conductive material (e.g., copper) is deposited on the surface of the first die layer. A mask layer is formed over the conductive material and patterned to define the locations of the contact(s) and/or signal line(s). The conductive material exposed in the patterned mask layer is removed (etched) to produce the one or more contacts and/or the one or more signal lines. An insulating material is then formed between the contact(s) and/or the signal line(s). As described earlier, the intermediate conductive layer is used to route signals between the first die layer and a second die layer positioned over the first die layer.

[0072] A second die layer is processed at block **1304**. Similar to the processing of the first die layer, the processing of the second die layer includes forming the devices and the VISs within and/or on the second die layer. The second die layer is processed to align with the first die layer.

[0073] Next, as shown in block **1306**, the second die layer is attached to the intermediate conductive layer and the first die layer to produce a 3D IC structure. In one embodiment, at least one of the pitch, the density, and or the diameter of the VISs in the first die layer is different from at least one of the pitch, the density, and or the diameter of the VISs in the second die layer. Additionally or alternatively, the VISs in the first die layer are arranged in a first grid layout on the first die and the VISs in the second die layer are arranged in a second grid layout on the second die. The arrangement of the VISs in the first grid layout differs from the arrangement of the VISs in the second grid layout.

[0074] In other embodiments, the operations noted in the blocks may occur out of the order as shown in FIGS. **12** and **13**. For example, two blocks shown in succession may in fact be executed substantially concurrently. Additionally or alternatively, blocks may be executed in the reverse order, depending upon the functionality/acts involved.

[0075] FIG. **14** depicts an example system that is suitable for designing a 3D IC structure in accordance with some embodiments. The design process may be implemented by a computer system, such as an ECAD system. Some or all of the operations for design (e.g., layout) methods disclosed herein are capable of being performed as part of a design procedure performed in a

design house, such as the design house **1502** discussed below in conjunction with FIG. **15**. [0076] In some embodiments, the system **1400** includes an automated place and route (APR) system. In some embodiments, the system **1400** includes a processing device **1402** and a non-transitory, computer-readable storage medium **1404** (“storage device”). The processing device **1402** is any suitable processing device or processing devices. Example processing devices include, but are not limited to, a central processing unit, a microprocessor, a distributed processing system, an application specific integrated circuit, a graphics processing unit, a field programmable gate array, or combinations thereof.

[0077] The storage device **1404** may be encoded with or store, for example, computer program code (e.g., a set of executable instructions **1406**). Execution of the executable instructions **1406** by the processing device **1402** represents (at least in part) an ECAD tool that implements a portion or all of, the methods described herein to produce the designs for the structures and the ICs disclosed herein. Further, the fabrication tools **1408** may be included for layout and physical implementation of the ICs. In one or more embodiments, the storage device **1404** is an electronic, magnetic, optical, electromagnetic, infrared, and/or a semiconductor system (or apparatus or device). For example, the storage device **1404** includes a semiconductor or solid-state memory, a magnetic tape, a removable computer diskette, a random access memory (RAM), a read-only memory (ROM), a rigid magnetic disk, and/or an optical disk. In one or more embodiments using optical disks, the storage device **1404** includes a compact disk-read only memory (CD-ROM), a compact disk-read/write (CD-R/W), and/or a digital video disc (DVD).

[0078] The processing device **1402** is operably connected to the storage device **1404** via a bus **1410**. The processing device **1402** is also operably connected to an input/output (I/O) interface **1412** and a network interface **1414** by the bus **1410**. The network interface **1414** is operably connected to a network **1416** so that the processing device **1402** and the storage device **1404** are capable of connecting to external elements via the network **1416**. In one or more embodiments, the network **1416** is illustrative of any type of wired and/or wireless network, such as an intranet and/or a distributed computing network (e.g., the Internet).

[0079] The network interface **1414** allows the system **1400** to communicate with other computing or electronic devices (not shown) via the network **1416**. The network interface **1414** includes wireless network interfaces and/or wired network interfaces. Example wireless network interfaces include BLUETOOTH, WIFI, WIMAX, GPRS, or WCDMA. Example wired network interfaces include ETHERNET, USB, or IEEE-1364. In one or more embodiments, some or all of the processes and/or methods disclosed herein are implemented in a distributed system via the network **1416**.

[0080] The processing device **1402** is configured to execute the executable instructions **1406** encoded in the storage device **1404** to cause the system **1400** to be usable for performing some or all of the processes and/or methods. For example, an electronic design application (e.g., in an ECAD system or as a standalone application) can be configured to perform the methods and techniques shown in FIGS. **1-13**.

[0081] In one or more embodiments, the storage device **1404** stores the executable instructions **1406** configured to cause the system **1400** to be usable for performing some or all of the processes and/or methods. In one or more embodiments, the storage device **1404** also stores information that facilitates execution of a portion of or all of the processes and/or methods. In one or more embodiments, the storage device **1404** stores a cell library **1418** that includes (at least in part) standard and/or previously designed cells.

[0082] The I/O interface **1412** is operably connected to I/O devices **1420**. In one or more embodiments, the I/O devices **1420** include one or more of an image capture device, a microphone, a scanner, a keyboard, a keypad, a mouse, a trackpad, a touchscreen, and/or cursor direction keys for communicating information and commands to the processing device **1402**. The I/O devices **1420** may also include one or more displays, one or more speakers, a printer, headphones, a haptic

or tactile feedback device, and the like.

[0083] The system **1400** is configured to receive information through the I/O interface **1412**. The information received through the I/O interface **1412** includes one or more of instructions, data, design rules, cell libraries, and/or other parameters for processing by the processing device **1402**. The information is transferred to the processing device **1402** via the bus **1410**. The system **1400** is configured to receive information related to a user interface (UI) through the I/O interface **1412**. The information is stored in the storage device **1404** as a UI **1422** or for presentation in the UI **1422**.

[0084] In some embodiments, a portion or all of the processes and/or methods is implemented as a standalone software application (e.g., an EDA) for execution by a processing device (e.g., processing device **1402**). In some embodiments, a portion or all of the processes and/or methods is implemented as a software application that is a part of an additional software application. In some embodiments, a portion or all of the processes and/or methods is implemented as a plug-in to a software application. In some embodiments, at least one of the processes and/or methods is implemented as a software application that is a portion of an EDA tool. In some embodiments, a portion or all of the processes and/or methods is implemented as a software application that is used by the system **1400**. In some embodiments, a layout diagram which includes standard and/or previously designed cells is generated using a tool such as VIRTUOSO available from CADENCE DESIGN SYSTEMS, Inc., or another suitable layout generating tool.

[0085] In some embodiments, the processes are realized as functions of a program stored in a non-transitory computer readable recording medium (e.g., the storage device **1404**). Examples of a non-transitory computer readable recording medium include, but are not limited to, external/removable and/or internal/built-in storage or memory unit, e.g., one or more of an optical disk, such as a DVD, a magnetic disk, such as a hard disk, a semiconductor memory, such as a ROM, a RAM, a memory card, and the like.

[0086] As noted above, embodiments of the system **1400** may include the fabrication tools **1408** for implementing the processes and/or methods stored in the storage device **1404**. For instance, a synthesis may be performed on a design in which the behavior and/or functions desired from the design are transformed to a functionally equivalent logic gate-level circuit description by matching the design to cells selected from the cell library **1418**. The synthesis results in a functionally equivalent logic gate-level circuit description, such as a gate-level netlist. Based on the gate-level netlist, a photolithographic mask may be generated that is used to fabricate the IC by the fabrication tools **1408**. Further aspects of device fabrication are disclosed in conjunction with FIG. **15**, which is a block diagram of an integrated circuit manufacturing system, and a manufacturing flow associated therewith, in accordance with some embodiments. In some embodiments, based on a layout diagram, at least one of: (a) one or more semiconductor masks; or (b) at least one component in a layer of a semiconductor IC is fabricated using the manufacturing system **1500**.

[0087] FIG. **15** illustrates a block diagram of an example integrated circuit manufacturing system and manufacturing flow in accordance with some embodiments. In the illustrated embodiment, the IC manufacturing system **1500** includes entities, such as a design house **1502**, a mask house **1504**, and an IC manufacturer/fabricator ("fab") **1506**, that interact with one another in the design, development, and manufacturing cycles and/or services related to manufacturing an IC **1508**, such as the ICs disclosed herein. The entities in the system **1500** are operably connected by a communication network (not shown). In some embodiments, the communication network is a single network. In some embodiments, the communication network is a variety of different networks, such as an intranet and the Internet. The communication network includes wired and/or wireless communication channels.

[0088] Each entity interacts with one or more of the other entities and provides services to and/or receives services from one or more of the other entities. In some embodiments, two or more of the design house **1502**, the mask house **1504**, and the IC fab **1506** is owned by a single company. In

some embodiments, two or more of the design house **1502**, the mask house **1504**, and the IC fab **1506** coexist in a common facility and use common resources.

[0089] The design house (or design team) **1502** generates an IC design layout diagram **1510**. The IC design layout diagram **1510** includes various geometrical patterns, or IC layout diagrams designed for the IC **1508** to be fabricated. The geometrical patterns correspond to patterns of metal, oxide, or semiconductor layers that make up the various components of the IC **1508** to be fabricated. The various layers combine to form various IC features. For example, a portion of the IC design layout diagram **1510** includes various IC features, such as active diffusion regions, gate electrodes, source and drain, metal lines or local vias, and openings for bonding pads, to be formed in a semiconductor substrate (such as a silicon wafer) and various material layers disposed on the semiconductor substrate.

[0090] The design house **1502** implements a design procedure to form the IC design layout diagram **1510**. The design procedure includes one or more of logic design, physical design or place and route. The IC design layout diagram **1510** is presented in one or more data files having information of the geometrical patterns. For example, the IC design layout diagram **1510** can be expressed in a GDS file format, a GDSII file format, or a DFII file format.

[0091] The mask house **1504** includes mask data preparation **1512** and mask fabrication **1514**. The mask house **1504** uses the IC design layout diagram **1510** to manufacture one or more masks **1516** to be used for fabricating the various layers of the IC **1508** according to the IC design layout diagram **1510**. The mask house **1504** performs mask data preparation **1512**, where the IC design layout diagram **1510** is translated into a representative data file (“RDF”). The mask data preparation **1512** provides the RDF to the mask fabrication **1514**. The mask fabrication **1514** includes a mask writer (not shown) that converts the RDF to an image on a substrate, such as a mask (reticle) **1516** on a semiconductor wafer. The IC design layout diagram **1510** is manipulated by the mask data preparation **1512** to comply with particular characteristics of the mask writer and/or requirements of the IC fab **1506**. In FIG. 15, the mask data preparation **1512** and the mask fabrication **1514** are illustrated as separate elements. In some embodiments, the mask data preparation **1512** and the mask fabrication **1514** can be collectively referred to as a mask data preparation.

[0092] In some embodiments, the mask data preparation **1512** includes an optical proximity correction (OPC) that uses lithography enhancement techniques to compensate for image errors, such as those that can arise from diffraction, interference, other process effects and the like. The OPC adjusts the IC design layout diagram **1510**. In some embodiments, the mask data preparation **1512** includes further resolution enhancement techniques (RET), such as off-axis illumination, sub-resolution assist features, phase-shifting masks, other suitable techniques, and the like or combinations thereof. In some embodiments, inverse lithography technology (ILT) is also used, which treats OPC as an inverse imaging problem.

[0093] In some embodiments, the mask data preparation **1512** includes a mask rule checker (MRC) (not shown) that checks the IC design layout diagram **1510** that has undergone processes in OPC with a set of mask creation rules that contain certain geometric and/or connectivity restrictions to ensure sufficient margins, to account for variability in semiconductor manufacturing processes, and the like. In some embodiments, the MRC modifies the IC design layout diagram **1510** to compensate for limitations during the mask fabrication, which may undo part of the modifications performed by OPC in order to meet mask creation rules.

[0094] In some embodiments, the mask data preparation **1512** includes lithography process checking (LPC) (not shown) that simulates processing that will be implemented by the IC fab **1506** to fabricate the IC **1508**. LPC simulates this processing based on the IC design layout diagram **1510** to create a simulated manufactured device, such as the IC **1508**. The processing parameters in LPC simulation can include parameters associated with various processes of the IC manufacturing cycle, parameters associated with tools used for manufacturing the IC, and/or other aspects of the

manufacturing process. LPC takes into account various factors, such as aerial image contrast, depth of focus (“DOF”), mask error enhancement factor (“MEEF”), other suitable factors, and the like or combinations thereof. In some embodiments, after a simulated manufactured device has been created by LPC, and if the simulated device is not sufficiently close in shape to satisfy design rules, OPC and/or MRC are repeated to further refine the IC design layout diagram **1510**.

[0095] It should be understood that the above description of the mask data preparation **1512** has been simplified for the purposes of clarity. In some embodiments, the mask data preparation **1512** includes additional features such as a logic operation (LOP) to modify the IC design layout diagram **1510** according to manufacturing rules. Additionally, the processes applied to the IC design layout diagram **1510** during the mask data preparation **1512** may be executed in a variety of different orders.

[0096] After the mask data preparation **1512** and during the mask fabrication **1514**, a mask **1516** or a group of masks **1516** are fabricated based on the IC design layout diagram **1510**. In some embodiments, the mask fabrication **1514** includes performing one or more lithographic exposures based on the IC design layout diagram **1510**. In some embodiments, an electron-beam (e-beam) or a mechanism of multiple e-beams is used to form a pattern on a mask(s) **1516** (photomask or reticle) based on the IC design layout diagram **1510**. The mask(s) **1516** can be formed in various technologies. For example, in some embodiments, the mask(s) **1516** is formed using binary technology. In some embodiments, a mask pattern includes opaque regions and transparent regions. A radiation beam, such as an ultraviolet (UV) beam, used to expose the image sensitive material layer (e.g., photoresist) which has been coated on a wafer, is blocked by the opaque region and transmits through the transparent regions. In one example, a binary mask version of the mask(s) **1516** includes a transparent substrate (e.g., fused quartz) and an opaque material (e.g., chromium) coated in the opaque regions of the binary mask.

[0097] In another example, the mask(s) **1516** is formed using a phase shift technology. In a phase shift mask (PSM) version of the mask(s) **1516**, various features in the pattern formed on the phase shift mask are configured to have a proper phase difference to enhance the resolution and imaging quality. In various examples, the phase shift mask can be attenuated PSM or alternating PSM. The mask(s) **1516** generated by the mask fabrication **1514** is used in a variety of processes. For example, a mask(s) **1516** is used in an ion implantation process to form various doped regions in the semiconductor wafer, in an etching process to form various etching regions in the semiconductor wafer, and/or in other suitable processes.

[0098] The IC fab **1506** includes wafer fabrication **1518**. The IC fab **1506** is an IC fabrication business that includes one or more manufacturing facilities for the fabrication of a variety of different IC products. In some embodiments, the IC fab **1506** is a semiconductor foundry. For example, there may be a manufacturing facility for the front end fabrication of a plurality of IC products (FEOL fabrication), while a second manufacturing facility may provide the back end fabrication for the interconnection and packaging of the IC products (BEOL fabrication), and a third manufacturing facility may provide other services for the foundry business.

[0099] The IC fab **1506** uses the mask(s) **1516** fabricated by the mask house **1504** to fabricate the IC **1508**. Thus, the IC fab **1506** at least indirectly uses the IC design layout diagram **1510** to fabricate the IC **1508**. In some embodiments, a semiconductor wafer **1520** is fabricated by the IC fab **1506** using the mask(s) **1516** to form the IC **1508**. In some embodiments, the IC fab **1506** includes performing one or more lithographic exposures based at least indirectly on the IC design layout diagram **1510**. The semiconductor wafer **1520** includes a silicon substrate or other proper substrate having material layers formed thereon. The semiconductor wafer **1520** further includes one or more of various doped regions, dielectric features, multilevel interconnects, and the like (formed at subsequent manufacturing steps).

[0100] In one aspect, a 3D integrated circuit structure includes a first die layer and a second die layer disposed vertically above the first die layer. The first die layer includes one or more first

devices and VISs formed in the first die layer and arranged around the one or more first devices in a first grid layout. The second die layer includes multiple second devices and multiple VISs formed in the second die layer and arranged around the second devices in a second grid layout. The first grid layout is different from the second grid layout. A density of the VISs in the second die layer is greater than a density of the VISs in the first die layer.

[0101] In another aspect, a system includes a 3D integrated circuit structure and a power supply operably connected to the 3D integrated circuit structure. The 3D integrated circuit structure includes a first die layer and a second die layer. The first die layer includes devices and vertical interconnect structures (VIS) formed in the first die layer and arranged in a first grid layout. The second die layer is attached vertically to the first die layer and includes devices and VISs formed in the second die layer and arranged in a second grid layout. The arrangement of the VISs in the first grid layout is different from the arrangement of the VISs in the second grid layout. A first density of the VISs in the first die layer is different from a second density of the VISs in the second die layer.

[0102] In yet another aspect, a method for fabricating a 3D integrated circuit structure includes processing a first die layer to produce a device and a first plurality of vertical interconnect structures (VISs) arranged in a first grid layout on the first die layer. An intermediate conductive layer is processed on the first die layer. A second die layer is processed to produce a plurality of devices and a second plurality of VISs arranged in a second grid layout on the second die layer. The signal line in the intermediate conductive layer electrically connects a respective VIS in the first plurality of VISs to a respective VIS in the second plurality of VISs. The first grid layout on the first die layer is different from the second grid layout on the second die layer.

[0103] The foregoing outlines features of several embodiments so that those skilled in the art may better understand the aspects of the present disclosure. Those skilled in the art should appreciate that they may readily use the present disclosure as a basis for designing or modifying other processes and structures for carrying out the same purposes and/or achieving the same advantages of the embodiments introduced herein. Those skilled in the art should also realize that such equivalent constructions do not depart from the spirit and scope of the present disclosure, and that they may make various changes, substitutions, and alterations herein without departing from the spirit and scope of the present disclosure.

Claims

1-20. (canceled)

21. A method for fabricating a 3D integrated circuit structure, the method comprising: processing a first die layer to produce one or more first devices and a first plurality of vertical interconnect structures (VISs) arranged in a first layout on the first die layer based on any one of (i) power requirements of the one or more first devices, (ii) IR drops of signals at the first die layer, or (iii) both (i) and (ii); processing a second die layer vertically above the first die layer to produce one or more second devices and a second plurality of VISs arranged in a second layout on the second die layer based on any one of (i) power requirements of the one or more second devices, (ii) IR drops of signals at the second die layer, or (iii) both (i) and (ii); and wherein a density of the first plurality of VISs is greater than a density of the second plurality of VISs.

22. The method of claim 21, further comprising processing an intermediate conductive layer between the first die layer and the second die layer, wherein the intermediate conductive layer is configured to electrically connect one or more VISs of the first plurality of VISs to one or more VISs of the second plurality of VISs.

23. The method of claim 21, further comprising electrically connecting a power supply to the first die layer.

24. The method of claim 21, wherein: processing the first die layer comprises disposing at least a

portion of the first plurality of VISs adjacent to edges of the one or more first devices; and processing the second die layer comprises disposing at least a portion of the second plurality of VISs adjacent to edges of the one or more second devices.

25. The method of claim 21, wherein processing the first die layer comprises: determining locations of the one or more first devices and the first plurality of VISs; forming the one or more first devices and the first plurality of VISs at the locations; and forming one or more first die signal lines, wherein the one or more first die signal lines electrically connect the one or more first devices to one or more VISs of the first plurality of VISs.

26. The method of claim 21, wherein processing the second die layer comprises: determining locations of the one or more second devices and the second plurality of VISs; forming the one or more second devices and the second plurality of VISs at the locations; and forming one or more second die signal lines, wherein the one or more second die signal lines electrically connect the one or more second devices to one or more VISs of the second plurality of VISs.

27. The method of claim 21, wherein processing the second die layer vertically above the first die layer comprises attaching the second die layer to the first die layer.

28. A 3D integrated circuit structure, comprising: a first die layer comprising: one or more first devices, and a first plurality of vertical interconnect structures (VISs) arranged in a first layout on the first die layer based on any one of (i) power requirements of the one or more first devices, (ii) IR drops of signals at the first die layer, or (iii) both (i) and (ii); and a second die layer comprising: one or more second devices, and a second plurality of VISs arranged in a second layout on the second die layer based on any one of (i) power requirements of the one or more second devices, (ii) IR drops of signals at the second die layer, or (iii) both (i) and (ii); wherein: the second die layer is disposed vertically above the first die layer, and a density of the first plurality of VISs is greater than a density of the second plurality of VISs.

29. The 3D integrated circuit structure of claim 28, further comprising an intermediate conductive layer between the first die layer and the second die layer, wherein the intermediate conductive layer is configured to electrically connect one or more VISs of the first plurality of VISs to one or more VISs of the second plurality of VISs.

30. The 3D integrated circuit structure of claim 29, wherein the intermediate conductive layer comprises any one of (i) one or more contacts, (ii) one or more signal lines, or (iii) both (i) and (ii).

31. The 3D integrated circuit structure of claim 28, wherein the density of the first plurality of VISs is variable based on any one of (i) one or more types of the one or more first devices, (ii) the power requirements of the one or more first devices, (iii) the power requirements of the one or more second devices, (iv) the IR drops of the signals at the second die layer, or (v) any combination of (i)-(iv).

32. The 3D integrated circuit structure of claim 28, wherein the density of the second plurality of VISs is variable based on any one of (i) one or more types of the one or more second devices, (ii) the power requirements of the one or more second devices, or (iii) both (i) and (ii).

33. The 3D integrated circuit structure of claim 28, wherein the first plurality of VISs and the second plurality of VISs comprises any one of (i) through-silicon vias (TSVs), (ii) through-glass vias (TGVs), (iii) through-dielectric vias (TDVs), or (iv) any combination of (i)-(iii).

34. The 3D integrated circuit structure of claim 28, wherein: the first die layer further comprises one or more first die signal lines, wherein the one or more first die signal lines electrically connect the one or more first devices to one or more VISs of the first plurality of VISs; and the second die layer further comprises one or more second die signal lines, wherein the one or more second die signal lines electrically connect the one or more second devices to one or more VISs of the second plurality of VISs.

35. The 3D integrated circuit structure of claim 28, wherein: at least a portion of the first plurality of VISs are disposed adjacent to edges of the one or more first devices; and at least a portion of the second plurality of VISs are disposed adjacent to edges of the one or more second devices.

- 36.** A system, comprising: a 3D integrated circuit structure; and a power supply operably connected to the 3D integrated circuit structure, wherein the 3D integrated circuit structure comprises: a first die layer comprising: one or more first devices, and a first plurality of vertical interconnect structures (VISs) arranged in a first layout on the first die layer based on any one of (i) power requirements of the one or more first devices, (ii) IR drops of signals at the first die layer, or (iii) both (i) and (ii); and a second die layer comprising: one or more second devices, and a second plurality of VISs arranged in a second layout on the second die layer based on any one of (i) power requirements of the one or more second devices, (ii) IR drops of signals at the second die layer, or (iii) both (i) and (ii); wherein: the second die layer is disposed vertically above the first die layer, and a density of the first plurality of VISs is greater than a density of the second plurality of VISs.
- 37.** The system of claim 36, wherein the 3D integrated circuit structure further comprises an intermediate conductive layer between the first die layer and the second die layer, wherein the intermediate conductive layer is configured to electrically connect one or more VISs of the first plurality of VISs to one or more VISs of the second plurality of VISs.
- 38.** The system of claim 36, wherein the density of the first plurality of VISs is variable based on any one of (i) one or more types of the one or more first devices, (ii) the power requirements of the one or more first devices, (iii) the power requirements of the one or more second devices, (iv) the IR drops of the signals at the second die layer, or (v) any combination of (i)-(iv).
- 39.** The system of claim 36, wherein the density of the second plurality of VISs is variable based on any one of (i) one or more types of the one or more second devices, (ii) the power requirements of the one or more second devices, or (iii) both (i) and (ii).
- 40.** The system of claim 36, wherein: the first die layer further comprises one or more first die signal lines, wherein the one or more first die signal lines electrically connect the one or more first devices to one or more VISs of the first plurality of VISs; and the second die layer further comprises one or more second die signal lines, wherein the one or more second die signal lines electrically connect the one or more second devices to one or more VISs of the second plurality of VISs.
-