

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12416838
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Kimura; Hajime et al.

Display device

Abstract

An object is to provide a display device that performs accurate display. A circuit is formed using a transistor that includes an oxide semiconductor and has a low off-state current. A precharge circuit or an inspection circuit is formed in addition to a pixel circuit. The off-state current is low because the oxide semiconductor is used. Thus, it is not likely that a signal or voltage is leaked in the precharge circuit or the inspection circuit to cause defective display. As a result, a display device that performs accurate display can be provided.

Inventors:	Kimura; Hajime (Atsugi, JP), Umezaki; Atsushi (Isehara, JP)
Applicant:	Semiconductor Energy Laboratory Co., Ltd. (Atsugi, JP)
Family ID:	1000008818871
Assignee:	Semiconductor Energy Laboratory Co., Ltd. (Atsugi, JP)
Appl. No.:	18/663356
Filed:	May 14, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240302699 A1	Sep. 12, 2024

Foreign Application Priority Data

JP	2010-028285	Feb. 11, 2010
----	-------------	---------------

Related U.S. Application Data

continuation parent-doc US 17980674 20221104 US 12007656 child-doc US 18663356
continuation parent-doc US 17488398 20210929 US 11500254 20221115 child-doc US 17980674
continuation parent-doc US 16925535 20200710 US 11143925 20211012 child-doc US 17488398

continuation parent-doc US 15991170 20180529 US 10718986 20200721 child-doc US 16925535
continuation parent-doc US 15711029 20170921 US 10007160 20180626 child-doc US 15991170
continuation parent-doc US 14602876 20150122 US 9465271 20161011 child-doc US 15262611
continuation parent-doc US 13021955 20110207 US 8947337 20150203 child-doc US 14602876
division parent-doc US 15262611 20160912 US 9798211 20171024 child-doc US 15711029

Publication Classification

Int. Cl.: **G02F1/1362** (20060101); **G02F1/1368** (20060101); **G09G3/00** (20060101); **G09G3/36** (20060101); **H10D30/67** (20250101); **H10D86/40** (20250101); **H10D86/60** (20250101); G02F1/1333 (20060101); G02F1/1339 (20060101); G02F1/1343 (20060101); G02F1/167 (20190101)

U.S. Cl.:

CPC **G02F1/13624** (20130101); **G02F1/136259** (20130101); **G02F1/136286** (20130101); **G02F1/1368** (20130101); **G09G3/006** (20130101); **G09G3/3648** (20130101); **H10D30/6755** (20250101); **H10D86/423** (20250101); **H10D86/441** (20250101); **H10D86/481** (20250101); **H10D86/60** (20250101); G02F1/133302 (20210101); G02F1/133345 (20130101); G02F1/1339 (20130101); G02F1/134309 (20130101); G02F1/13439 (20130101); G02F1/136254 (20210101); G02F1/167 (20130101); G09G2230/00 (20130101); G09G2310/0251 (20130101); H10D30/673 (20250101)

Field of Classification Search

CPC: G02F (1/133345); G02F (1/1339); G02F (1/134309); G02F (1/13439); G02F (1/13624); G02F (1/136259); G02F (1/136286); G02F (1/1368); G02F (1/167); G02F (2001/133302); G02F (2001/136254); G09G (2230/00); G09G (2310/0251); G09G (3/006); G09G (3/3648); H01L (27/1225); H01L (27/124); H01L (27/1255); H01L (29/42384); H01L (29/7869)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5337172	12/1993	Lehureau	N/A	N/A
5348898	12/1993	Yatsuda	257/E27.081	H10B 69/00
5731856	12/1997	Kim et al.	N/A	N/A
5744864	12/1997	Cillessen et al.	N/A	N/A
6281700	12/2000	Matsueda	N/A	N/A
6294274	12/2000	Kawazoe et al.	N/A	N/A
6330044	12/2000	Murade	349/110	G02F 1/136209
6404414	12/2001	Ishii	N/A	N/A
6493047	12/2001	Ha	349/40	G02F 1/136204
6525556	12/2002	Matsueda	N/A	N/A
6563174	12/2002	Kawasaki et al.	N/A	N/A
6624857	12/2002	Nagata et al.	N/A	N/A

6670944	12/2002	Ishii	345/87	G09G 3/3688
6704068	12/2003	Murade	349/44	H01L 29/78633
6727522	12/2003	Kawasaki et al.	N/A	N/A
6784862	12/2003	Kodate et al.	N/A	N/A
6794892	12/2003	Matsueda	N/A	N/A
6853364	12/2004	Kai	438/30	G09G 3/3688
6882378	12/2004	Nagata et al.	N/A	N/A
7049190	12/2005	Takeda et al.	N/A	N/A
7061014	12/2005	Hosono et al.	N/A	N/A
7064346	12/2005	Kawasaki et al.	N/A	N/A
7105868	12/2005	Nause et al.	N/A	N/A
7211825	12/2006	Shih et al.	N/A	N/A
7282782	12/2006	Hoffman et al.	N/A	N/A
7297977	12/2006	Hoffman et al.	N/A	N/A
7312624	12/2006	Ishii	324/760.02	G09G 3/006
7323356	12/2007	Hosono et al.	N/A	N/A
7385224	12/2007	Ishii et al.	N/A	N/A
7402506	12/2007	Levy et al.	N/A	N/A
7411209	12/2007	Endo et al.	N/A	N/A
7453065	12/2007	Saito et al.	N/A	N/A
7453087	12/2007	Iwasaki	N/A	N/A
7462862	12/2007	Hoffman et al.	N/A	N/A
7468304	12/2007	Kaji et al.	N/A	N/A
7501293	12/2008	Ito et al.	N/A	N/A
7505020	12/2008	Yamamoto et al.	N/A	N/A
7570072	12/2008	Hata et al.	N/A	N/A
7674650	12/2009	Akimoto et al.	N/A	N/A
7732819	12/2009	Akimoto et al.	N/A	N/A
7863611	12/2010	Abe et al.	N/A	N/A
7910490	12/2010	Akimoto et al.	N/A	N/A
7932521	12/2010	Akimoto et al.	N/A	N/A
7932886	12/2010	Higashi	345/100	G09G 3/3611
7940244	12/2010	Higashi	345/100	G09G 3/3611
7968383	12/2010	Honda et al.	N/A	N/A
7994500	12/2010	Kim et al.	N/A	N/A
7998372	12/2010	Yano et al.	N/A	N/A
8017513	12/2010	Jeong et al.	N/A	N/A
8242986	12/2011	Kimura	N/A	N/A
8274077	12/2011	Akimoto et al.	N/A	N/A
8324920	12/2011	Hata et al.	N/A	N/A
8330691	12/2011	Tanimoto et al.	N/A	N/A
8455371	12/2012	Yano et al.	N/A	N/A
8466463	12/2012	Akimoto et al.	N/A	N/A
8502217	12/2012	Sato et al.	N/A	N/A
8513662	12/2012	Yabuta et al.	N/A	N/A

8541258	12/2012	Kim et al.	N/A	N/A
8629069	12/2013	Akimoto et al.	N/A	N/A
8659016	12/2013	Kim et al.	N/A	N/A
8669550	12/2013	Akimoto et al.	N/A	N/A
8785240	12/2013	Watanabe	N/A	N/A
8790959	12/2013	Akimoto et al.	N/A	N/A
8796069	12/2013	Akimoto et al.	N/A	N/A
8796679	12/2013	Jeong et al.	N/A	N/A
8947337	12/2014	Kimura	345/100	G09G 3/344
8962457	12/2014	Watanabe	N/A	N/A
9099562	12/2014	Akimoto et al.	N/A	N/A
9136338	12/2014	Yano et al.	N/A	N/A
9465271	12/2015	Kimura	N/A	G09G 3/3648
9798211	12/2016	Kimura	N/A	G02F 1/13624
10007160	12/2017	Kimura	N/A	H01L 27/1255
10718986	12/2019	Kimura	N/A	G02F 1/1368
11143925	12/2020	Kimura	N/A	G02F 1/13624
11201394	12/2020	Jia	N/A	N/A
2001/0019384	12/2000	Murade	349/110	H01L 29/78633
2001/0030635	12/2000	Kodate	345/87	G09G 3/3648
2001/0030722	12/2000	Murade	349/110	G02F 1/133512
2001/0046027	12/2000	Tai et al.	N/A	N/A
2002/0018152	12/2001	Nagata	349/38	G02F 1/136227
2002/0056838	12/2001	Ogawa	N/A	N/A
2002/0057251	12/2001	Higashi	345/100	G09G 3/3688
2002/0132454	12/2001	Ohtsu et al.	N/A	N/A
2003/0098708	12/2002	Matsueda	324/760.01	G09G 3/3648
2003/0151587	12/2002	Yamashita	345/102	G09G 3/006
2003/0189401	12/2002	Kido et al.	N/A	N/A
2003/0218222	12/2002	Wager, III et al.	N/A	N/A
2003/0218594	12/2002	Ishii	345/96	G09G 3/3688
2004/0038446	12/2003	Takeda et al.	N/A	N/A
2004/0046920	12/2003	Hayata	349/149	G02F 1/1345
2004/0127038	12/2003	Carcia et al.	N/A	N/A
2005/0017302	12/2004	Hoffman	N/A	N/A
2005/0024081	12/2004	Kuo et al.	N/A	N/A
2005/0068310	12/2004	Ishii	345/204	G09G 3/3688
2005/0146349	12/2004	Lai et al.	N/A	N/A

2005/0156830	12/2004	Tobita	345/76	G09G 3/32
2005/0199959	12/2004	Chiang et al.	N/A	N/A
2005/0258427	12/2004	Chan et al.	N/A	N/A
2005/0285825	12/2004	Eom	345/76	G09G 3/3233
2006/0035452	12/2005	Carcia et al.	N/A	N/A
2006/0043377	12/2005	Hoffman et al.	N/A	N/A
2006/0091793	12/2005	Baude et al.	N/A	N/A
2006/0108529	12/2005	Saito et al.	N/A	N/A
2006/0108636	12/2005	Sano et al.	N/A	N/A
2006/0110867	12/2005	Yabuta et al.	N/A	N/A
2006/0113536	12/2005	Kumomi et al.	N/A	N/A
2006/0113539	12/2005	Sano et al.	N/A	N/A
2006/0113549	12/2005	Den et al.	N/A	N/A
2006/0113565	12/2005	Abe et al.	N/A	N/A
2006/0169973	12/2005	Isa et al.	N/A	N/A
2006/0170111	12/2005	Isa et al.	N/A	N/A
2006/0197092	12/2005	Hoffman et al.	N/A	N/A
2006/0208977	12/2005	Kimura	N/A	N/A
2006/0228974	12/2005	Thelss et al.	N/A	N/A
2006/0231882	12/2005	Kim et al.	N/A	N/A
2006/0238135	12/2005	Kimura	N/A	N/A
2006/0244107	12/2005	Sugihara et al.	N/A	N/A
2006/0262075	12/2005	Higashi	345/100	G09G 3/2011
2006/0279510	12/2005	Lai	345/100	G09G 3/006
2006/0279515	12/2005	Higashi	345/100	G09G 3/2011
2006/0284171	12/2005	Levy et al.	N/A	N/A
2006/0284172	12/2005	Ishii	N/A	N/A
2006/0292777	12/2005	Dunbar	N/A	N/A
2007/0001205	12/2006	Kimura	257/296	H01L 27/1255
2007/0024187	12/2006	Shin et al.	N/A	N/A
2007/0046191	12/2006	Saito	N/A	N/A
2007/0052025	12/2006	Yabuta	N/A	N/A
2007/0054507	12/2006	Kaji et al.	N/A	N/A
2007/0090365	12/2006	Hayashi et al.	N/A	N/A
2007/0108446	12/2006	Akimoto	N/A	N/A
2007/0109243	12/2006	Higashi	345/92	G09G 3/3648
2007/0152217	12/2006	Lai et al.	N/A	N/A
2007/0172591	12/2006	Seo et al.	N/A	N/A
2007/0187678	12/2006	Hirao et al.	N/A	N/A
2007/0187760	12/2006	Furuta et al.	N/A	N/A
2007/0194379	12/2006	Hosono et al.	N/A	N/A
2007/0252928	12/2006	Ito et al.	N/A	N/A
2007/0272922	12/2006	Kim et al.	N/A	N/A
2007/0287296	12/2006	Chang	N/A	N/A

2008/0006877	12/2007	Mardilovich et al.	N/A	N/A
2008/0038882	12/2007	Takechi et al.	N/A	N/A
2008/0038929	12/2007	Chang	N/A	N/A
2008/0050595	12/2007	Nakagawara et al.	N/A	N/A
2008/0073653	12/2007	Iwasaki	N/A	N/A
2008/0083950	12/2007	Pan et al.	N/A	N/A
2008/0106191	12/2007	Kawase	N/A	N/A
2008/0128689	12/2007	Lee et al.	N/A	N/A
2008/0129195	12/2007	Ishizaki et al.	N/A	N/A
2008/0143653	12/2007	Shishido	345/78	G09G 3/3233
2008/0166834	12/2007	Kim et al.	N/A	N/A
2008/0182358	12/2007	Cowdery-Corvan et al.	N/A	N/A
2008/0197344	12/2007	Yano	257/E51.001	H10K 10/466
2008/0224133	12/2007	Park et al.	N/A	N/A
2008/0254569	12/2007	Hoffman et al.	N/A	N/A
2008/0258139	12/2007	Ito et al.	N/A	N/A
2008/0258140	12/2007	Lee et al.	N/A	N/A
2008/0258141	12/2007	Park et al.	N/A	N/A
2008/0258143	12/2007	Kim et al.	N/A	N/A
2008/0278410	12/2007	Yamashita	345/55	H10K 71/621
2008/0296568	12/2007	Ryu et al.	N/A	N/A
2008/0308805	12/2007	Akimoto et al.	N/A	N/A
2009/0068773	12/2008	Lai et al.	N/A	N/A
2009/0073325	12/2008	Kuwabara et al.	N/A	N/A
2009/0114910	12/2008	Chang	N/A	N/A
2009/0121998	12/2008	Ohkawa	345/100	G09G 3/3688
2009/0134399	12/2008	Sakakura et al.	N/A	N/A
2009/0152506	12/2008	Umeda et al.	N/A	N/A
2009/0152541	12/2008	Maekawa et al.	N/A	N/A
2009/0256827	12/2008	Tanikame	345/204	G09G 3/3291
2009/0267873	12/2008	Ishii	345/76	G09G 3/3648
2009/0278122	12/2008	Hosono et al.	N/A	N/A
2009/0280600	12/2008	Hosono et al.	N/A	N/A
2009/0295690	12/2008	Seo	257/E33.001	G09G 3/3233
2009/0295839	12/2008	Furukawa	345/88	G09G 3/3413
2009/0303155	12/2008	Takasaki	345/98	G09G 3/3648
2009/0303166	12/2008	Tsubata	345/87	G09G 3/342
2009/0305461	12/2008	Akimoto et al.	N/A	N/A

2010/0025678	12/2009	Yamazaki et al.	N/A	N/A
2010/0065844	12/2009	Tokunaga	N/A	N/A
2010/0092800	12/2009	Itagaki et al.	N/A	N/A
2010/0109002	12/2009	Itagaki et al.	N/A	N/A
2010/0193784	12/2009	Morosawa	257/E29.296	H01L 29/7869
2011/0062435	12/2010	Yamazaki	257/43	H01L 29/7869
2011/0068388	12/2010	Yamazaki	257/E21.414	H01L 29/04
2011/0104851	12/2010	Akimoto et al.	N/A	N/A
2011/0121290	12/2010	Akimoto et al.	N/A	N/A
2011/0133180	12/2010	Yamazaki	257/43	H01L 29/7869
2011/0193846	12/2010	Kimura	345/92	H01L 29/7869
2015/0131021	12/2014	Kimura	349/46	G09G 3/006
2015/0340513	12/2014	Akimoto et al.	N/A	N/A
2016/0377897	12/2015	Kimura	349/46	H01L 27/1225
2018/0017819	12/2017	Kimura	N/A	G09G 3/344
2020/0341309	12/2019	Kimura	N/A	G09G 3/006

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
0895220	12/1998	EP	N/A
1209748	12/2001	EP	N/A
1548699	12/2004	EP	N/A
1737044	12/2005	EP	N/A
1770788	12/2006	EP	N/A
1995787	12/2007	EP	N/A
1998373	12/2007	EP	N/A
1998374	12/2007	EP	N/A
1998375	12/2007	EP	N/A
2017881	12/2008	EP	N/A
2058697	12/2008	EP	N/A
2141744	12/2009	EP	N/A
2226847	12/2009	EP	N/A
60-198861	12/1984	JP	N/A
63-210022	12/1987	JP	N/A
63-210023	12/1987	JP	N/A
63-210024	12/1987	JP	N/A
63-215519	12/1987	JP	N/A
63-239117	12/1987	JP	N/A
63-265818	12/1987	JP	N/A
05-134273	12/1992	JP	N/A
05-251705	12/1992	JP	N/A
05-307167	12/1992	JP	N/A
08-264794	12/1995	JP	N/A
10-214065	12/1997	JP	N/A

11-505377	12/1998	JP	N/A
11-338376	12/1998	JP	N/A
2000-044236	12/1999	JP	N/A
2000-150900	12/1999	JP	N/A
2001-265248	12/2000	JP	N/A
2002-076356	12/2001	JP	N/A
2002-116423	12/2001	JP	N/A
2002-289859	12/2001	JP	N/A
2003-050405	12/2002	JP	N/A
2003-086000	12/2002	JP	N/A
2003-086808	12/2002	JP	N/A
2004-004536	12/2003	JP	N/A
2004-103957	12/2003	JP	N/A
2004-273614	12/2003	JP	N/A
2004-273732	12/2003	JP	N/A
2005-099740	12/2004	JP	N/A
2005-208611	12/2004	JP	N/A
2006-165532	12/2005	JP	N/A
2007-073614	12/2006	JP	N/A
2007-123861	12/2006	JP	N/A
2007-142195	12/2006	JP	N/A
2007-233353	12/2006	JP	N/A
2008-281988	12/2007	JP	N/A
2008-283046	12/2007	JP	N/A
2009-021536	12/2008	JP	N/A
2009-085925	12/2008	JP	N/A
2009-093023	12/2008	JP	N/A
2009-141002	12/2008	JP	N/A
2009-260378	12/2008	JP	N/A
2009-276387	12/2008	JP	N/A
2009-295997	12/2008	JP	N/A
2010-016347	12/2009	JP	N/A
2011-186450	12/2010	JP	N/A
WO-2004/114391	12/2003	WO	N/A
WO-2008/026344	12/2007	WO	N/A
WO-2008/126879	12/2007	WO	N/A
WO-2008/143021	12/2007	WO	N/A
WO-2009/072532	12/2008	WO	N/A
WO-2009/081796	12/2008	WO	N/A
WO-2009/139483	12/2008	WO	N/A
WO-2009/142289	12/2008	WO	N/A

OTHER PUBLICATIONS

Coates.D et al., “Optical Studies of the Amorphous Liquid-Cholesteric Liquid Crystal Transition: the “Blue Phase””, Physics Letters, Sep. 10, 1973, vol. 45A, No. 2, pp. 115-116. cited by applicant

Meiboom.S et al., “Theory of the Blue Phase of Cholesteric Liquid Crystals”, Phys. Rev. Lett. (Physical Review Letters), May 4, 1981, vol. 46, No. 18, pp. 1216-1219. cited by applicant

Costello.M et al., “Electron Microscopy of a Cholesteric Liquid Crystal and Its Blue Phase”, Phys. Rev. a (Physical Review. A), May 1, 1984, vol. 29, No. 5, pp. 2957-2959. cited by applicant

Kimizuka.N et al., “Spinel, YBFE204, and YB2FE307 Types of Structures for Compounds in the

IN2O3 and SC2O3-A2O3-BO Systems [A; Fe, Ga, or Al; B: Mg, Mn, Fe, Ni, Cu, or Zn] At Temperatures Over 1000°C”, Journal of Solid State Chemistry, 1985, vol. 60, pp. 382-384, ELSEVIER. cited by applicant

Nakamura.M et al., “The phase relations in the In2O3-Ga2ZnO4-ZnO system at 1350°C”, Journal of Solid State Chemistry, Aug. 1, 1991, vol. 93, No. 2, pp. 298-315, ELSEVIER. cited by applicant

Kitzerow.H et al., “Observation of Blue Phases in Chiral Networks”, Liquid Crystals, 1993, vol. 14, No. 3, pp. 911-916. cited by applicant

Kimizuka.N et al., “Syntheses and Single-Crystal Data of Homologous Compounds, In2O3(ZnO)m (m = 3, 4, and 5), InGaO3(ZnO)3, and Ga2O3(ZnO)m (m = 7, 8, 9, and 16) in the In2O3-ZnGa2O4-ZnO System”, Journal of Solid State Chemistry, Apr. 1, 1995, vol. 116, No. 1, pp. 170-178, ELSEVIER. cited by applicant

Chern.H et al., “An Analytical Model for the Above-Threshold Characteristics of Polysilicon Thin-Film Transistors”, IEEE Transactions on Electron Devices, Jul. 1, 1995, vol. 42, No. 7, pp. 1240-1246. cited by applicant

Prins.M et al., “A Ferroelectric Transparent Thin-Film Transistor”, Appl. Phys. Lett. (Applied Physics Letters) , Jun. 17, 1996, vol. 68, No. 25, pp. 3650-3652. cited by applicant

Li.C et al., “Modulated Structures of Homologous Compounds InMO3(ZnO)m (M=In,Ga; m=Integer) Described by Four-Dimensional Superspace Group”, Journal of Solid State Chemistry, 1998, vol. 139, pp. 347-355, ELSEVIER. cited by applicant

Kikuchi.H et al., “Polymer-Stabilized Liquid Crystal Blue Phases”, Nature Materials, Sep. 2, 2002, vol. 1, pp. 64-68. cited by applicant

Tsuda.K et al., “Ultra Low Power Consumption Technologies for Mobile TFT-LCDs”, IDW '02 : Proceedings of the 9th International Display Workshops, Dec. 4, 2002, pp. 295-298. cited by applicant

Nomura.K et al., “Thin-Film Transistor Fabricated in Single-Crystalline Transparent Oxide Semiconductor”, Science, May 23, 2003, vol. 300, No. 5623, pp. 1269-1272. cited by applicant

Ikeda.T et al., “Full-Functional System Liquid Crystal Display Using CG-Silicon Technology”, SID Digest '04 : SID International Symposium Digest of Technical Papers, 2004, vol. 35, pp. 860-863. cited by applicant

Nomura.K et al., “Room-Temperature Fabrication of Transparent Flexible Thin-Film Transistors Using Amorphous Oxide Semiconductors”, Nature, Nov. 25, 2004, vol. 432, pp. 488-492. cited by applicant

Dembo.H et al., “RFCPUS On Glass and Plastic Substrates Fabricated By TFT Transfer Technology”, IEDM 05: Technical Digest of International Electron Devices Meeting, Dec. 5, 2005, pp. 1067-1069. cited by applicant

Kanno.H et al., “White Stacked Electrophosphorescent Organic Light-Emitting Devices Employing MOO3 as a Charge-Generation Layer”, Adv. Mater. (Advanced Materials), 2006, vol. 18, No. 3, pp. 339-342. cited by applicant

Lee.H et al., “Current Status of, Challenges to, and Perspective View of AM-OLED”, IDW '06 : Proceedings of the 13th International Display Workshops, Dec. 7, 2006, pp. 663-666. cited by applicant

Hosono.H, “68.3:Invited Paper:Transparent Amorphous Oxide Semiconductors for High Performance TFT”, SID Digest '07 : SID International Symposium Digest of Technical Papers, 2007, vol. 38, pp. 1830-1833. cited by applicant

Hirao.T et al., “Novel Top-Gate Zinc Oxide Thin-Film Transistors (ZNO TFTS) for AMLCDS”, J. Soc. Inf. Display (Journal of the Society for Information Display), 2007, vol. 15, No. 1, pp. 17-22. cited by applicant

Park.S et al., “Challenge to Future Displays: Transparent AM-OLED Driven By Peald Grown ZNO TFT”, IMID '07 DIGEST, 2007, pp. 1249-1252. cited by applicant

Kikuchi.H et al., “62.2:INVITED Paper:Fast Electro-Optical Switching in Polymer-Stabilized

Liquid Crystalline Blue Phases for Display Application”, SID Digest '07 : SID International Symposium Digest of Technical Papers, 2007, vol. 38, pp. 1737-1740. cited by applicant

Miyasaka.M, “Suftla Flexible Microelectronics on Their Way to Business”, SID Digest '07 : SID International Symposium Digest of Technical Papers, 2007, vol. 38, pp. 1673-1676. cited by applicant

Kurokawa.Y et al., “UHF RFCPUS on Flexible and Glass Substrates for Secure RFID Systems”, Journal of Solid-State Circuits , 2008, vol. 43, No. 1, pp. 292-299. cited by applicant

Jeong.J et al., “3.1: Distinguished Paper: 12.1-Inch WXGA AMOLED Display Driven by Indium-Gallium-Zinc Oxide TFTs Array”, SID Digest '08 : SID International Symposium Digest of Technical Papers, May 20, 2008, vol. 39, No. 1, pp. 1-4. cited by applicant

Lee.J et al., “World's Largest (15-INCH) XGA AMLCD Panel Using Igzo Oxide TFT”, SID Digest '08 : SID International Symposium Digest of Technical Papers, May 20, 2008, vol. 39, pp. 625-628. cited by applicant

Park.J et al., “Amorphous Indium-Gallium-Zinc Oxide TFTS and Their Application for Large Size AMOLED”, AM-FPD '08 Digest of Technical Papers, Jul. 2, 2008, pp. 275-278. cited by applicant

Takahashi.M et al., “Theoretical Analysis of IGZO Transparent Amorphous Oxide Semiconductor”, IDW '08 : Proceedings of the 15th International Display Workshops, Dec. 3, 2008, pp. 1637-1640. cited by applicant

Sakata.J et al., “Development of 4.0-IN. AMOLED Display With Driver Circuit Using Amorphous In—Ga—Zn—Oxide TFTS”, IDW '09 : Proceedings of the 16th International Display Workshops, 2009, pp. 689-692. cited by applicant

Asaoka.Y et al., “29.1:Polarizer-Free Reflective LCD Combined With Ultra Low-Power Driving Technology”, SID Digest '09 : SID International Symposium Digest of Technical Papers, May 31, 2009, pp. 395-398. cited by applicant

Nowatari.H et al., “60.2: Intermediate Connector With Suppressed Voltage Loss for White Tandem OLEDs”, SID Digest '09 : SID International Symposium Digest of Technical Papers, May 31, 2009, vol. 40, pp. 899-902. cited by applicant

Jin.D et al., “65.2: Distinguished Paper: World-Largest (6.5”) Flexible Full Color Top Emission AMOLED Display on Plastic Film and Its Bending Properties”, SID Digest '09 : SID International Symposium Digest of Technical Papers, May 31, 2009, pp. 983-985. cited by applicant

Lee.M et al., “15.4:Excellent Performance of Indium-Oxide-Based Thin-Film Transistors by DC Sputtering”, SID Digest '09 : SID International Symposium Digest of Technical Papers, May 31, 2009, pp. 191-193. cited by applicant

Cho.D et al., “21.2:Al and Sn-Doped Zinc Indium Oxide Thin Film Transistors for AMOLED Back-Plane”, SID Digest '09 : SID International Symposium Digest of Technical Papers, May 31, 2009, pp. 280-283. cited by applicant

Kikuchi.H et al., “39.1:Invited Paper:Optically Isotropic Nano-Structured Liquid Crystal Composites for Display Applications”, SID Digest '09 : SID International Symposium Digest of Technical Papers, May 31, 2009, pp. 578-581. cited by applicant

Osada.T et al., “15.2: Development of Driver-Integrated Panel using Amorphous In—Ga—Zn—Oxide TFT”, SID Digest '09 : SID International Symposium Digest of Technical Papers, May 31, 2009, vol. 40, pp. 184-187. cited by applicant

Ohara.H et al., “21.3:4.0 In. QVGA AMOLED Display Using In—Ga—Zn—Oxide TFTS With a Novel Passivation Layer”, SID Digest '09 : SID International Symposium Digest of Technical Papers, May 31, 2009, pp. 284-287. cited by applicant

Godo.H et al., “P-9:Numerical Analysis on Temperature Dependence of Characteristics of Amorphous In—Ga—Zn—Oxide TFT”, SID Digest '09 : SID International Symposium Digest of Technical Papers, May 31, 2009, pp. 1110-1112. cited by applicant

Osada.T et al., “Development of Driver-Integrated Panel Using Amorphous In—Ga—Zn—Oxide TFT”, AM-FPD '09 Digest of Technical Papers, Jul. 1, 2009, pp. 33-36. cited by applicant

Godou.H et al., "Temperature Dependence of Characteristics and Electronic Structure for Amorphous In—Ga—Zn—Oxide TFT", AM-FPD '09 Digest of Technical Papers, Jul. 1, 2009, pp. 41-44. cited by applicant

Ohara.H et al., "Amorphous In—Ga—Zn—Oxide TFTs with Suppressed Variation for 4.0 inch QVGA AMOLED Display", AM-FPD '09 Digest of Technical Papers, Jul. 1, 2009, pp. 227-230, The Japan Society of Applied Physics. cited by applicant

Park.J et al., "High performance amorphous oxide thin film transistors with self-aligned top-gate structure", IEDM 09: Technical Digest of International Electron Devices Meeting, Dec. 7, 2009, pp. 191-194. cited by applicant

Nakamura.M, "Synthesis of Homologous Compound with New Long-Period Structure", NIRIM Newsletter, Mar. 1, 1995, vol. 150, pp. 1-4. cited by applicant

Hosono.H et al., "Working hypothesis to explore novel wide band gap electrically conducting amorphous oxides and examples", J. Non-Cryst. Solids (Journal of Non-Crystalline Solids), 1996, vol. 198-200, pp. 165-169. cited by applicant

Orita.M et al., "Mechanism of Electrical Conductivity of Transparent InGaZnO₄", Phys. Rev. B (Physical Review. B), Jan. 15, 2000, vol. 61, No. 3, pp. 1811-1816. cited by applicant

Van de Walle.C, "Hydrogen as a Cause of Doping in Zinc Oxide", Phys. Rev. Lett. (Physical Review Letters), Jul. 31, 2000, vol. 85, No. 5, pp. 1012-1015. cited by applicant

Orita.M et al., "Amorphous transparent conductive oxide InGaO₃(ZnO)_m (m < 4): a Zn4s conductor", Philosophical Magazine, 2001, vol. 81, No. 5, pp. 501-515. cited by applicant

Janotti.A et al., "Oxygen Vacancies In ZnO", Appl. Phys. Lett. (Applied Physics Letters) , 2005, vol. 87, pp. 122102-1-122102-3. cited by applicant

Clark.S et al., "First Principles Methods Using Castep", Zeitschrift fur Kristallographie, 2005, vol. 220, pp. 567-570. cited by applicant

Nomura.K et al., "Amorphous Oxide Semiconductors for High-Performance Flexible Thin-Film Transistors", Jpn. J. Appl. Phys. (Japanese Journal of Applied Physics) , 2006, vol. 45, No. 5B, pp. 4303-4308. cited by applicant

Janotti.A et al., "Native Point Defects In ZnO", Phys. Rev. B (Physical Review. B), Oct. 4, 2007, vol. 76, No. 16, pp. 165202-1-165202-22. cited by applicant

Lany.S et al., "Dopability, Intrinsic Conductivity, and Nonstoichiometry of Transparent Conducting Oxides", Phys. Rev. Lett. (Physical Review Letters), Jan. 26, 2007, vol. 98, pp. 045501-1-045501-4. cited by applicant

Park.J et al., "Improvements in the Device Characteristics of Amorphous Indium Gallium Zinc Oxide Thin-Film Transistors By Ar Plasma Treatment", Appl. Phys. Lett. (Applied Physics Letters) , Jun. 26, 2007, vol. 90, No. 26, pp. 262106-1-262106-3. cited by applicant

Park.J et al., "Electronic Transport Properties of Amorphous Indium-Gallium-Zinc Oxide Semiconductor Upon Exposure to Water", Appl. Phys. Lett. (Applied Physics Letters) , 2008, vol. 92, pp. 072104-1-072104-3. cited by applicant

Hsieh.H et al., "P-29: Modeling of Amorphous Oxide Semiconductor Thin Film Transistors and Subgap Density of States", SID Digest '08 : SID International Symposium Digest of Technical Papers, May 20, 2008, vol. 39, pp. 1277-1280. cited by applicant

Oba.F et al., "Defect energetics in ZnO: A hybrid Hartree-Fock density functional study", Phys. Rev. B (Physical Review. B), 2008, vol. 77, pp. 245202-1-245202-6. cited by applicant

Kim.S et al., "High-Performance oxide thin film transistors passivated by various gas plasmas", 214th ECS Meeting, 2008, No. 2317, ECS. cited by applicant

Hayashi.R et al., "42.1: Invited Paper: Improved Amorphous In—Ga—Zn—O TFTs", SID Digest '08 : SID International Symposium Digest of Technical Papers, May 20, 2008, vol. 39, pp. 621-624. cited by applicant

Son.K et al., "42.4L: Late-News Paper: 4 Inch QVGA AMOLED Driven by the Threshold Voltage Controlled Amorphous GIZO (Ga₂O₃-In₂O₃-ZnO) TFT", SID Digest '08 : SID International

Symposium Digest of Technical Papers, May 20, 2008, vol. 39, pp. 633-636. cited by applicant

Park.S et al., "42.3: Transparent ZnO Thin Film Transistor for the Application of High Aperture Ratio Bottom Emission AM-OLED Display", SID Digest '08 : SID International Symposium Digest of Technical Papers, May 20, 2008, vol. 39, pp. 629-632. cited by applicant

Fung.T et al., "2-D Numerical Simulation of High Performance Amorphous In—Ga—Zn—O TFTs for Flat Panel Displays", AM-FPD '08 Digest of Technical Papers, Jul. 2, 2008, pp. 251-252, The Japan Society of Applied Physics. cited by applicant

Mo.Y et al., "Amorphous Oxide TFT Backplanes for Large Size AMOLED Displays", IDW '08 : Proceedings of the 6th International Display Workshops, Dec. 3, 2008, pp. 581-584. cited by applicant

Asakuma.N et al., "Crystallization and Reduction of Sol-Gel-Derived Zinc Oxide Films By Irradiation With Ultraviolet Lamp", Journal of Sol-Gel Science and Technology, 2003, vol. 26, pp. 181-184. cited by applicant

Fortunato.E et al., "Wide-Bandgap High-Mobility ZNO Thin-Film Transistors Produced At Room Temperature", Appl. Phys. Lett. (Applied Physics Letters) , Sep. 27, 2004, vol. 85, No. 13, pp. 2541-2543. cited by applicant

Masuda.S et al., "Transparent thin film transistors using ZnO as an active channel layer and their electrical properties", J. Appl. Phys. (Journal of Applied Physics) , Feb. 1, 2003, vol. 93, No. 3, pp. 1624-1630. cited by applicant

Oh.M et al., "Improving the Gate Stability of ZNO Thin-Film Transistors With Aluminum Oxide Dielectric Layers", J. Electrochem. Soc. (Journal of the Electrochemical Society), 2008, vol. 155, No. 12, pp. H1009-H1014. cited by applicant

Park.J et al., "Dry etching of ZnO films and plasma-induced damage to optical properties", J. Vac. Sci. Technol. B (Journal of Vacuum Science & Technology B), Mar. 1, 2003, vol. 21, No. 2, pp. 800-803. cited by applicant

Ueno.K et al., "Field-Effect Transistor on SrTiO₃ With Sputtered Al₂O₃ Gate Insulator", Appl. Phys. Lett. (Applied Physics Letters) , Sep. 1, 2003, vol. 83, No. 9, pp. 1755-1757. cited by applicant

Nomura.K et al., "Carrier transport in transparent oxide semiconductor with intrinsic structural randomness probed using single-crystalline InGaO₃(ZnO)₅ films", Appl. Phys. Lett. (Applied Physics Letters) , Sep. 13, 2004, vol. 85, No. 11, pp. 1993-1995. cited by applicant

Primary Examiner: Bolotin; Dmitriy

Attorney, Agent or Firm: Robinson Intellectual Property Law Office, P.C.

Background/Summary

BACKGROUND OF THE INVENTION

1. Field of the Invention

(1) The present invention relates to a semiconductor device, a display device, a liquid crystal display device, and a light-emitting device and a method for manufacturing these devices. In particular, the present invention relates to a semiconductor device, a display device, a liquid crystal display device, and a light-emitting device each of which includes a circuit having a transistor including an oxide semiconductor film, and a method for manufacturing these devices.

2. Description of the Related Art

(2) Thin film transistors (TFTs) in which silicon layers formed using amorphous silicon or the like are used for channel layers have been widely used as switching elements in display devices typified

by liquid crystal display devices. Although thin film transistors formed using amorphous silicon have low field-effect mobility, they have an advantage that larger glass substrates can be used.

(3) Moreover, attention has been recently drawn to a technique by which a transistor is manufactured using a metal oxide with semiconductor properties and such a transistor is applied to an electronic device or an optical device. For example, it is known that some metal oxides such as tungsten oxide, tin oxide, indium oxide, and zinc oxide have semiconductor properties. Patent Document 1 discloses a transistor in which a transparent semiconductor layer formed using such a metal oxide is used as a channel formation region.

REFERENCE

(4) Patent Document 1: Japanese Published Patent Application No. 2006-165532

SUMMARY OF THE INVENTION

(5) An object of one embodiment of the present invention is to provide a semiconductor device or the like with less noise, to provide a semiconductor device or the like with high withstand voltage, to provide a semiconductor device or the like with low power consumption, or to provide a display device or the like that can perform accurate display. Note that the description of these objects does not exclude another object. In addition, one embodiment of the present invention does not necessarily achieve all the objects listed above.

(6) In order to achieve any of the above objects, a circuit is formed using a transistor including an oxide semiconductor (OS), particularly a MOS transistor including an oxide semiconductor. The oxide semiconductor is a substantially intrinsic semiconductor. For that reason, the off-state current is extremely low.

(7) According to one embodiment of the present invention, a liquid crystal display device includes a pixel portion including a plurality of pixels, and a precharge circuit. The precharge circuit includes a plurality of first transistors. Each of the plurality of pixels includes a second transistor and a liquid crystal element. Each of the first transistors and the second transistors includes an oxide semiconductor.

(8) According to one embodiment of the present invention, a liquid crystal display device includes a pixel portion including a plurality of pixels, and an inspection circuit. The inspection circuit includes a plurality of first transistors. Each of the plurality of pixels includes a second transistor and a liquid crystal element. Each of the first transistors and the second transistors includes an oxide semiconductor.

(9) According to one embodiment of the present invention, a liquid crystal display device includes a pixel portion including a plurality of pixels, and a circuit. The circuit includes a plurality of first transistors. Each of the plurality of pixels includes a second transistor and a liquid crystal element. Gates of the plurality of first transistors are electrically connected to each other. First terminals of the plurality of first transistors are electrically connected to each other. All of second terminals of the plurality of first transistors are electrically connected to the pixel portion. The gates of the plurality of first transistors are in a floating state. Each of the first transistors and the second transistors includes an oxide semiconductor.

(10) According to one embodiment of the present invention, a liquid crystal display device includes a pixel portion including a plurality of pixels, and a circuit. The circuit includes a plurality of first transistors. Each of the plurality of pixels includes a second transistor and a liquid crystal element. Gates of the plurality of first transistors are electrically connected to each other. First terminals of the plurality of first transistors are electrically connected to each other. All of second terminals of the plurality of first transistors are electrically connected to the pixel portion. The first terminals of the plurality of first transistors are in a floating state. Each of the first transistors and the second transistors includes an oxide semiconductor.

(11) In any of the above liquid crystal display devices, the oxide semiconductor included in the first transistors and the second transistors may be an intrinsic semiconductor.

(12) In the invention disclosed herein, a circuit is formed using a transistor that includes an oxide

semiconductor and has a low off-state current; thus unnecessary current can be prevented from being leaked into the circuit. For that reason, the circuit is more likely to operate normally. As a result, accurate display can be performed in a display device that includes a circuit having a transistor including an oxide semiconductor.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) In the accompanying drawings:

- (2) FIG. 1 is a circuit diagram illustrating a semiconductor device;
- (3) FIG. 2 is a circuit diagram illustrating a semiconductor device;
- (4) FIG. 3 is a circuit diagram illustrating a semiconductor device;
- (5) FIG. 4 is a circuit diagram illustrating a semiconductor device;
- (6) FIG. 5 is a circuit diagram illustrating a semiconductor device;
- (7) FIGS. 6A and 6B are timing charts each illustrating a waveform of a signal in a semiconductor device;
- (8) FIG. 7 is a timing chart illustrating waveforms of signals in a semiconductor device;
- (9) FIGS. 8A and 8B are circuit diagrams each illustrating a semiconductor device;
- (10) FIGS. 9A and 9B are circuit diagrams each illustrating a semiconductor device;
- (11) FIGS. 10A and 10B are circuit diagrams each illustrating a semiconductor device;
- (12) FIGS. 11A and 11B are circuit diagrams each illustrating a semiconductor device;
- (13) FIGS. 12A to 12D are cross-sectional views each illustrating a semiconductor device;
- (14) FIG. 13A is a circuit diagram illustrating a display device, and FIG. 13B is a cross-sectional view illustrating a display device;
- (15) FIGS. 14A to 14C are cross-sectional views each illustrating a display device;
- (16) FIGS. 15A to 15C are timing charts each illustrating a waveform in a display device;
- (17) FIGS. 16A to 16H each illustrate an electronic device; and
- (18) FIGS. 17A to 17H each illustrate an electronic device.

DETAILED DESCRIPTION OF THE INVENTION

(19) Embodiments will be described below with reference to the accompanying drawings. Note that in structures described below, the same portions or portions having similar functions are denoted by the same reference numerals, and description thereof is not repeated.

Embodiment 1

(20) In this embodiment, an example of a device (a semiconductor device, a display device, or a light-emitting device) having a transistor including an oxide semiconductor, particularly a transistor including an oxide semiconductor in an active layer will be described with reference to drawings. The off-state current of a transistor including an oxide semiconductor is low; therefore, defects caused due to off-state current can be reduced in a semiconductor device or the like including an oxide semiconductor. Moreover, a transistor including an oxide semiconductor has high withstand voltage. For that reason, even when high voltage is applied to the transistor, the transistor can operate normally and the off-state current can be low; thus, defects caused due to off-state current can be reduced.

(21) FIG. 1 illustrates an example of a structure of a device in this embodiment. The device according to one example of this embodiment includes a pixel portion **101** and a circuit **111**.

(22) A plurality of pixels are arranged in matrix in the pixel portion **101**. Here, the expression “pixels are arranged (provided) in matrix” also includes the case where the pixels are arranged in a straight line and the case where the pixels are arranged in a jagged line, in the longitudinal direction or the lateral direction. For example, a pixel **102a** and a pixel **102b** are aligned in the lateral direction. Similarly, a pixel **102c** and a pixel **102d** are aligned in the lateral direction. Moreover, the

pixel **102a** and the pixel **102c** are aligned in the longitudinal direction. Similarly, the pixel **102b** and the pixel **102d** are aligned in the longitudinal direction. The pixels are connected to each other with wirings. Pixels arranged in the longitudinal direction are connected with a wiring extended in the vertical direction. Pixels arranged in the lateral direction are connected with a wiring extended in the horizontal direction. For example, the pixel **102a** and the pixel **102b** are connected with a wiring **104a**. Similarly, the pixel **102c** and the pixel **102d** are connected with a wiring **104b**. Furthermore, the pixel **102a** and the pixel **102c** are connected with a wiring **103a**. Similarly, the pixel **102b** and the pixel **102d** are connected with a wiring **103b**. Note that pixels can be connected with another wiring, for example, a wiring to which all the pixels are connected (e.g., a common wiring or a power supply line). Further, pixels other than the pixels **102a** to **102d** are arranged and connected in a similar manner.

(23) Here, the wirings provided in the horizontal direction, such as the wirings **104a** and **104b**, are sometimes connected to gates of transistors included in pixels and thus can have a function of a gate signal line (a gate wiring, a gate line, or the like). Alternatively, the wirings provided in the horizontal direction, such as the wirings **104a** and **104b**, are supplied with a selection signal per row and the signal is scanned in some cases. Thus, the wirings provided in the horizontal direction, such as the wirings **104a** and **104b**, can have a function of a scan signal line (a scan wiring, a scan line, or the like).

(24) The wirings provided in the vertical direction, such as the wiring **103a**, the wiring **103b**, a wiring **103c**, a wiring **103d**, a wiring **103e**, a wiring **103f**, a wiring **103g**, a wiring **103h**, a wiring **103i**, a wiring **103j**, a wiring **103k**, and a wiring **103L** (the wirings **103a** to **103L**), are sometimes connected to sources or drains of transistors included in pixels and thus can have a function of a source signal line (a source wiring, a source line, or the like). Alternatively, the wirings provided in the vertical direction, such as the wirings **103a** to **103L**, are sometimes supplied with a data signal, a video signal, a source signal, or the like and thus can have a function of a data signal line (a data wiring, a data line, or the like).

(25) The circuit **111** is connected to the pixel portion **101** or the pixels through the wirings provided in the vertical direction, such as the wirings **103a** to **103L**. The circuit **111** can have a variety of functions.

(26) FIG. 2 illustrates an example of a circuit configuration showing the details of the circuit **111**. For example, the circuit **111** can have a function of a precharge circuit or a function of an inspection circuit. Alternatively, the circuit **111** can have both a function of a precharge circuit and a function of an inspection circuit. Note that one embodiment of the present invention is not limited to these examples.

(27) The circuit **111** includes a transistor **201a**, a transistor **201b**, a transistor **201c**, a transistor **201d**, a transistor **201e**, a transistor **201f**, a transistor **201g**, a transistor **201h**, a transistor **201i**, a transistor **201j**, a transistor **201k**, and a transistor **201L** (the transistors **201a** to **201L**). The wirings **103a** to **103L** are connected to a wiring **202** through the transistors **201a** to **201L**, respectively. Therefore, either sources or drains of the transistors **201a** to **201L** are connected to the wiring **202**, and the rest of the sources and drains of the transistors **201a** to **201L** are connected to the respective wirings **103a** to **103L**. A wiring **203** is connected to gates of the transistors **201a** to **201L**. That is, the gates of the transistors **201a** to **201L** are connected to each other.

(28) Note that in this specification and the like, a transistor is an element having at least three terminals of a gate, a drain, and a source. The transistor has a channel region between the drain (a drain terminal, a drain region, or a drain electrode) and the source (a source terminal, a source region, or a source electrode), and current can flow through the drain, the channel region, and the source.

(29) Note that in this specification and the like, a transistor with a multi-gate structure having two or more gate electrodes can be used, for example. With the multi-gate structure, a structure where a plurality of transistors are connected in series is provided because channel regions are connected in

series. Thus, with the multi-gate structure, the amount of off-state current can be reduced and the withstand voltage of the transistor can be increased (the reliability can be improved). Alternatively, with the multi-gate structure, drain-source current does not change much even if drain-source voltage changes when the transistor operates in a saturation region, so that a flat slope of voltage-current characteristics can be obtained. By utilizing the flat slope of the voltage-current characteristics, an ideal current source circuit or an active load having an extremely large resistance can be realized. Accordingly, a differential circuit, a current mirror circuit, or the like having excellent properties can be realized.

(30) Note that a transistor with a structure where gate electrodes are formed above and below a channel can be used, for example. With the structure where the gate electrodes are formed above and below the channel, a circuit structure where a plurality of transistors are connected in parallel is provided. Thus, a channel region is increased, so that the amount of current can be increased.

Alternatively, with the structure where the gate electrodes are formed above and below the channel, a depletion layer is easily formed; thus, the subthreshold swing value (S value) can be improved.

(31) The circuit **111** is not limited to having the configuration in FIG. 2 and can have a variety of configuration. FIG. 3 illustrates another example of the circuit **111**. The description of FIG. 1 and FIG. 2 can be applied to FIG. 3.

(32) FIG. 3 illustrates an example of the case where a plurality of wirings **202** are provided in FIG. 2. FIG. 3 shows the case where three wirings **202** are provided; however, one embodiment of the present invention is not limited to this example, and two wirings **202** or four or more wirings **202** can be provided. The wirings **103a** to **103L** are connected to one of a wiring **202a**, a wiring **202b**, and a wiring **202c** through the respective transistors **201a** to **201L**. Therefore, either sources or drains of the transistors **201a** to **201L** are connected to one of the wirings **202a**, **202b**, and **202c**, and the rest of the sources and drains of the transistors **201a** to **201L** are connected to the respective wirings **103a** to **103L**. The wiring **203** is connected to gates of the transistors **201a** to **201L**. That is, the gates of the transistors **201a** to **201L** are connected to each other.

(33) In the case of performing color display, each color of pixels performing display can correspond to one of the wirings **202a**, **202b**, and **202c**. For example, a wiring that is connected to the wiring **202a** through a transistor is connected to red pixels. Therefore, the wiring **202a** is connected to the wirings **103a**, **103d**, **103g**, and **103j** through the respective transistors. Similarly, a wiring that is connected to the wiring **202b** through a transistor is connected to blue pixels. Therefore, the wiring **202b** is connected to the wirings **103b**, **103e**, **103h**, and **103k** through the respective transistors. Similarly, a wiring that is connected to the wiring **202c** through a transistor is connected to green pixels. Therefore, the wiring **202c** is connected to the wirings **103c**, **103f**, **103i**, and **103L** through the respective transistors. Note that the colors are not limited to red, blue, and green; for example, four colors (RGB and white) can be used or a plurality of slightly different reds (or blues or greens) can be used. Accordingly, colors can be controlled.

(34) Next, FIG. 4 illustrates another example of the configuration of the circuit **111**. The description of FIG. 1, FIG. 2, and FIG. 3 can be applied to FIG. 4.

(35) FIG. 4 illustrates an example of the case where a plurality of wirings **203** are provided in FIG. 2. FIG. 4 shows the case where three wirings **203** are provided; however, one embodiment of the present invention is not limited to this example, and two wirings **203** or four or more wirings **203** can be provided. The wirings **103a** to **103L** are connected to the wiring **202** through the transistors **201a** to **201L**, respectively. Therefore, either sources or drains of the transistors **201a** to **201L** are connected to the wiring **202**, and the rest of the sources and drains of the transistors **201a** to **201L** are connected to the respective wirings **103a** to **103L**. Gates of the transistors **201a** to **201L** are connected to one of a wiring **203a**, a wiring **203b**, and a wiring **203c**. That is, the gates of some of the transistors **201a** to **201L** (e.g., the transistors **201a**, **201d**, **201g**, and **201j**) are connected to each other and to the wiring **203a**. Similarly, the gates of some of the transistors **201a** to **201L** (e.g., the transistors **201b**, **201e**, **201h**, and **201k**) are connected to each other and to the wiring **203b**.

Similarly, the gates of the others (e.g., the transistors **201c**, **201f**, **201i**, and **201L**) are connected to each other and to the wiring **203c**.

(36) In the case of performing color display, each color of pixels performing display can correspond to one of the wirings **203a**, **203b**, and **203c**. For example, a wiring that is connected to the wiring **202** through a transistor whose gate is connected to the wiring **203a** is connected to red pixels. Therefore, the wiring **202** is connected to the wirings **103a**, **103d**, **103g**, and **103j** through the respective transistors each having the gate connected to the wiring **203a**. Similarly, a wiring that is connected to the wiring **202** through a transistor whose gate is connected to the wiring **203b** is connected to blue pixels. Therefore, the wiring **202** is connected to the wirings **103b**, **103e**, **103h**, and **103k** through the respective transistors each having the gate connected to the wiring **203b**. Similarly, a wiring that is connected to the wiring **202** through a transistor whose gate is connected to the wiring **203c** is connected to green pixels. Therefore, the wiring **202** is connected to the wirings **103c**, **103f**, **103i**, and **103L** through the respective transistors each having the gate connected to the wiring **203c**. Note that the colors are not limited to red, blue, and green; for example, four colors (RGB and white) can be used or a plurality of slightly different reds (or blues or greens) can be used. Accordingly, colors can be controlled.

(37) Next, FIG. 5 illustrates another example of the configuration of the circuit **111**. The description of FIG. 1, FIG. 2, FIG. 3, and FIG. 4 can be applied to FIG. 5.

(38) FIG. 5 illustrates an example of the case where a plurality of wirings **202** and a plurality of wirings **203** are provided in FIG. 2. That is, FIG. 5 corresponds to the case where a plurality of wirings **203** are provided in FIG. 3 and the case where a plurality of wirings **202** are provided in FIG. 4. FIG. 5 shows the case where three wirings **202** and three wirings **203** are provided; however, one embodiment of the present invention is not limited to this example, and the number of the wiring **202** and/or the wiring **203** can be two or four or more. The wirings **103a** to **103L** are connected to one of the wirings **202a**, **202b**, and **202c** through the respective transistors **201a** to **201L**. Therefore, either sources or drains of the transistors **201a** to **201L** are connected to one of the wirings **202a**, **202b**, and **202c**, and the rest of the sources and drains of the transistors **201a** to **201L** are connected to the respective wirings **103a** to **103L**. Gates of the transistors **201a** to **201L** are connected to one of the wirings **203a**, **203b**, and **203c**. That is, the gates of some of the transistors **201a** to **201L** (e.g., the transistors **201a**, **201d**, **201g**, and **201j**) are connected to each other and to the wiring **203a**. Similarly, the gates of some of the transistors **201a** to **201L** (e.g., the transistors **201b**, **201e**, **201h**, and **201k**) are connected to each other and to the wiring **203b**. Similarly, the gates of the others (e.g., the transistors **201c**, **201f**, **201i**, and **201L**) are connected to each other and to the wiring **203c**.

(39) In the case of performing color display, as in FIG. 2, FIG. 3, and FIG. 4, each color of pixels performing display can correspond to one of the wirings **203a**, **203b**, and **203c** or one of the wirings **202a**, **202b**, and **202c**. Accordingly, colors can be controlled.

Embodiment 2

(40) In this embodiment, an example of the operation of the circuit **111** illustrated in FIG. 2, FIG. 3, FIG. 4, and FIG. 5 will be described.

(41) The circuit **111** can have a variety of functions depending on an operation method. For example, the circuit **111** can have a function of an inspection circuit and/or a function of a precharge circuit. Note that one embodiment of the present invention is not limited to this example, and the circuit **111** can have another function.

(42) First, an operation method in the case where the circuit **111** is operated as a precharge circuit will be described. FIGS. 6A and 6B show waveforms in the case where precharge is performed. FIG. 6A shows a waveform of a signal supplied to a wiring in a given row, for example, the wiring **104a**. A signal **901** has a waveform with a cycle **902**. The cycle **902** often corresponds to one frame period or one subframe period, for example. In the cycle **902**, the signal **901** is at H level only in a period **903** and is at L level in the other periods. The period **903** often corresponds to one gate

selection period or 1H period, for example. FIG. 6B shows detailed waveforms in one gate selection period. One gate selection period can be considered to be divided into a former period **904** and a latter period **905**. In the former period **904**, a predetermined voltage can be supplied to the wirings **103a** to **103L** in advance. Such an operation for supplying a predetermined voltage in advance corresponds to precharge. That is, the former period **904** can be referred to as a precharge period. In the latter period **905**, a video signal is supplied. That is, the latter period **905** can be referred to as a signal input period. As an example, a signal **908** represents a signal supplied to any one of the wirings **103a** to **103L**. The potential of the signal **908** becomes approximately equal to a potential **906** in the former period **904**. Here, the potential **906** can be a reference potential, for example, a potential that is approximately equal to a common potential or a counter potential supplied to a display element (e.g., a liquid crystal element). Alternatively, the potential **906** preferably lies nearly in the middle of the amplitude of the potential of a video signal. In the latter period **905**, the potential of the signal **908** becomes a potential corresponding to a video signal. Accordingly, the potential of the signal **908** in the latter period **905** varies as appropriate depending on the polarity of a video signal or a signal supplied to a liquid crystal element, for example. By thus supplying a predetermined voltage to the wirings **103a** to **103L** in advance, a signal can be supplied rapidly. Thus, the speed of writing signals is increased, leading to a reduction in the time for writing signals.

(43) In the circuit in FIG. 2, a signal like a signal **907** is supplied to the wiring **203**. In the former period **904**, the signal **907** is a voltage with which the transistors **201a** to **201L** are turned on. Moreover, the potential **906** is supplied to the wiring **202**. Thus, the wirings **103a** to **103L** can be precharged in the former period **904**.

(44) In this case, when the potential of each wiring is controlled by a transistor including an oxide semiconductor, adverse effects of the off-state current of the transistor can be reduced; thus, leakage of voltage and noise can be reduced, and accurate voltages can be supplied to wirings. Therefore, the use of the transistor including an oxide semiconductor can realize accurate display.

(45) As described above, the transistors **201a** to **201L** have a function of being turned on or off, controlled with a gate signal. Accordingly, the transistors **201a** to **201L** can have a switch function.

(46) The circuit in FIG. 3 includes a plurality of wirings **202a** to **202c**. For that reason, in the former period **904**, different potentials can be supplied to the wirings **103a** to **103L**. Therefore, for example, potentials different depending on colors can be supplied to the wirings **103a** to **103L** in the former period **904**. Accordingly, the circuit can operate optimally to express various colors.

(47) The circuit in FIG. 4 includes a plurality of wirings **203a** to **203c**. For that reason, when the former period **904** is further divided into a plurality of periods, only one of the transistors **201a** to **201L** can be turned on. FIG. 7 shows waveforms of signals supplied to the wirings **203a** to **203c** in that case. A signal **907a** represents a signal supplied to the wiring **203a**. A signal **907b** represents a signal supplied to the wiring **203b**. A signal **907c** represents a signal supplied to the wiring **203c**. The signal **907a** is at H level only in the first third of the former period **904**. The signal **907b** is at H level only in the middle third of the former period **904**. The signal **907c** is at H level only in the final third of the former period **904**. By thus dividing the former period **904** into a plurality of periods so that potentials supplied to the wiring **202** are made different in the plurality of periods, potentials supplied to the wirings **103a** to **103L** can be made to vary. Therefore, in the former period **904**, potentials different depending on colors can be supplied to the wirings **103a** to **103L**. Accordingly, the circuit can operate optimally in accordance with colors.

(48) The circuit in FIG. 5 includes a plurality of wirings **202a** to **202c**. For that reason, in the former period **904**, different potentials can be supplied to the wirings **103a** to **103L**. Furthermore, the circuit in FIG. 5 includes a plurality of wirings **203a** to **203c**. For that reason, when the former period **904** is divided into a plurality of periods as illustrated in FIG. 7, only one of the transistors **201a** to **201L** can be turned on. By thus dividing the former period **904** into a plurality of periods so that potentials supplied to the wirings **202a** to **202c** are made different in the plurality of periods,

potentials supplied to the wirings **103a** to **103L** can be made to vary. Therefore, in the former period **904**, potentials different depending on colors can be supplied to the wirings **103a** to **103L**. Accordingly, the circuit can operate optimally in accordance with colors.

(49) Next, an operation method in the case where the circuit **111** is operated as an inspection circuit will be described. First, the case of the circuit **111** in FIG. 2 is described.

(50) First, a signal is supplied to a pixel by a given means. For example, a signal is supplied to the wirings **103a** to **103L** from a signal line driver circuit connected to the wirings **103a** to **103L**. Preferably, a signal is supplied to one of the wirings **103a** to **103L**. Alternatively, the transistors **201a** to **201L** are turned on to supply a signal to the wirings **103a** to **103L**, preferably one of the wirings **103a** to **103L**, through the wiring **202**. Further alternatively, a probe for supplying a signal comes into contact with the wirings **103a** to **103L**, preferably one of the wirings **103a** to **103L**, to supply a signal. Then, an H-level signal is supplied to any one of gate lines such as the wirings **104a** and **104b**. Thus, the signal is supplied into a pixel when a transistor in the pixel operates normally. After that, an L-level signal is supplied to that gate line. As a result, the signal is held in the pixel.

(51) Next, an H-level signal is supplied to the gate line, so that the signal held in the pixel is supplied to the wirings **103a** to **103L**. At this time, an H-level signal is supplied to the wiring **203** to turn on the transistors **201a** to **201L**. Thus, the signal held in the pixel can be read through the wiring **202**.

(52) In this case, if the transistor in the pixel is defective, the signal cannot be properly read. Therefore, whether the transistor normally operates or not can be inspected depending on whether the signal is properly read.

(53) In the case where a signal is supplied to one of the wirings **103a** to **103L**, a signal is then supplied to another one of the wirings **103a** to **103L** and a similar operation is repeated. Further, this operation is performed on all the gate lines. Thus, all the pixels can be inspected. In the case where one gate line is being selected, when a signal is supplied to only one of a plurality of pixels connected to the gate line and reading is performed on the pixel, inspection can be accurately performed on a pixel-by-pixel basis. On the other hand, when a signal is supplied to some or all of a plurality of pixels and reading is performed on the pixels, the pixels can be roughly inspected.

(54) In FIG. 3, a plurality of wirings **202a** to **202c** are provided. For that reason, signals held in a plurality of pixels can be read at the same time through the wirings **202a** to **202c**. Three wirings are provided in the case of FIG. 3; therefore, signals can be supplied to three pixels at the same time, and the signals in three pixels can be read at the same time. Thus, rapid inspection can be realized. As a result, the duration of a manufacturing process of a semiconductor device or the like can be reduced, and costs can be reduced.

(55) In FIG. 4, a plurality of wirings **203a** to **203c** are provided. For that reason, signals held in pixels can be sequentially read through the wiring **202** in such a manner that signals supplied to the wirings **203a** to **203c** are sequentially set at H level. Accordingly, signals can be supplied to a plurality of pixels at the same time and sequentially read on a pixel-by-pixel basis. Thus, rapid inspection can be realized. As a result, the duration of a manufacturing process of a semiconductor device or the like can be reduced, and costs can be reduced.

(56) In FIG. 5, a plurality of wirings **202a** to **202c** are provided. For that reason, signals held in a plurality of pixels can be read at the same time through the wirings **202a** to **202c**. Moreover, a plurality of wirings **203a** to **203c** are provided. For that reason, signals held in pixels can be sequentially read through the wiring **202** in such a manner that signals supplied to the wirings **203a** to **203c** are sequentially set at H level. Thus, rapid inspection can be realized. As a result, the duration of a manufacturing process of a semiconductor device or the like can be reduced, and costs can be reduced.

(57) Such inspection is performed as part of a process for manufacturing a semiconductor device or the like. Therefore, an inspection circuit is not operated after the semiconductor device or the like is

assembled and shipped.

(58) If the off-state current of the transistors **201a** to **201L** is large, current is leaked, so that noise enters the wirings **103a** to **103L**. In view of the above, by using a transistor including an oxide semiconductor as the transistors **201a** to **201L**, the off-state current can be reduced and noise can be reduced.

(59) As described above, by changing an operation method, the circuit **111** can realize a variety of functions. Accordingly, the circuit **111** can have both a function of a precharge circuit and a function of an inspection circuit. When the circuit **111** has both of the functions, a larger number of functions can be realized with a smaller number of circuits, resulting in lower cost, lower power consumption, and the like.

Embodiment 3

(60) In this embodiment, examples of peripheral circuits of the circuit **111** will be described.

(61) FIGS. **8A** and **8B** each illustrate the circuit **111**, the pixel portion **101**, and an example of peripheral circuits. The circuit **111** and the pixel portion **101** are placed over a substrate **511**. In other words, a transistor and a wiring included in the circuit **111** are formed, etched, and patterned at the same time as a transistor and a wiring included in the pixel portion **101**. That is, the circuit **111** and the pixel portion **101** are formed at the same time over one substrate through the same process. Thus, materials of the transistor and the wiring in the circuit **111** are the same as those of the transistor and the wiring in the pixel portion **101**. For that reason, when the transistor in the pixel portion **101** includes an oxide semiconductor, the transistor in the circuit **111** also includes the oxide semiconductor.

(62) Note that in this specification and the like, a transistor can be formed using a variety of substrates. There is no particular limitation on the kind of a substrate. Examples of the substrate are a semiconductor substrate (e.g., a single crystal substrate and a silicon substrate), an SOI substrate, a glass substrate, a quartz substrate, and a flexible substrate. For a flexible substrate, a flexible synthetic resin such as plastics typified by polyethylene terephthalate (PET) and polyethylene naphthalate (PEN), or acrylic can be used, for example.

(63) Note that a transistor may be formed using one substrate, and then the transistor may be transferred to another substrate.

(64) Note that all the circuits that are necessary to realize a desired function can be formed using one substrate. Thus, costs can be reduced by reduction in the number of components, or the reliability can be improved by reduction in the number of connections to circuit components.

(65) In FIG. **8A**, a circuit **501**, a circuit **502**, a circuit **503**, and a circuit **504** are formed over substrates different from the substrate **511**. For example, the circuit **501**, the circuit **502**, the circuit **503**, or the circuit **504** includes an IC chip formed using a single crystal substrate or an SOI substrate. Note that the circuit **501**, the circuit **502**, the circuit **503**, and/or the circuit **504** may be provided over the substrate **511** by COG (chip on glass).

(66) Here, the circuit **501** has a function of controlling the circuit **111**, supplying a signal and a voltage to the circuit **111**, or reading a signal from the circuit **111**, for example. The **501** has a function corresponding to the function of the circuit **111**. For example, when the circuit **111** has a function of a precharge circuit, the circuit **501** has a function of controlling a precharge operation. Similarly, when the circuit **111** has a function of an inspection circuit, the circuit **501** has a function of controlling an inspection operation. Similarly, when the circuit **111** has a function of a precharge circuit and a function of an inspection circuit, the circuit **501** has a function of controlling a precharge operation and a function of controlling an inspection operation.

(67) The circuit **502** has a function of supplying a signal to the wirings **104a** and **104b** and the like; therefore, the circuit **502** can have a function of a gate line driver circuit (a scan driver). The circuit **503** has a function of supplying a signal to the wirings **103a** to **103L**; therefore, the circuit **503** can have a function of a signal line driver circuit (a data driver). The circuit **504** has a function of controlling the circuit **502** or the circuit **503**. Therefore, the circuit **504** can have a function of a

controller, a pulse generator circuit, a clock signal generator circuit, a common voltage generator circuit, a timing generator circuit, an image processing circuit, a power supply circuit, or the like. (68) FIG. 8B illustrates the case where the circuit 501 is not provided in the structure of FIG. 8A. In the case where the circuit 111 functions as an inspection circuit, the circuit 501 is necessary when the circuit 111 performs inspection but not necessary after the inspection. Therefore, the circuit 501 can be provided as illustrated in FIG. 8A at the time of inspection, and the circuit 501 can be removed after the inspection is finished. When the circuit 501 is removed as shown in FIG. 8B, the wiring 202 and the wiring 203 are each in a floating state.

(69) Note that the circuits 501, 502, 503, and 504 are provided over substrates different from the substrate 511 in FIGS. 8A and 8B; however, one embodiment of the present invention is not limited to these examples. For example, some of these circuits can be provided over the substrate 511. As an example, FIGS. 9A and 9B each illustrate an example of the case where the circuit 502 is provided over the substrate 511. Like FIG. 8A, FIG. 9A illustrates a structure including the circuit 501. Like FIG. 8B, FIG. 9B illustrates a structure without the circuit 501. That is, in FIGS. 9A and 9B, the circuit 111, the pixel portion 101, and the circuit 502 are formed over one substrate through the same process. For that reason, when the transistor in the pixel portion 101 includes an oxide semiconductor, transistors in the circuits 111 and 502 also include the oxide semiconductor. When the circuit 501 is removed as shown in FIG. 8B, the wiring 202 and the wiring 203 are each in a floating state.

(70) By thus forming the circuit 502 over the same substrate as the pixel portion 101, costs can be reduced.

(71) As an example different from FIGS. 9A and 9B, the circuit 503 or part of the circuit 503 can be provided over the substrate 511. As an example of part of the circuit 503, an analog switch (a transfer gate) can be connected to the wirings 103a to 103L. Similarly, the circuit 504 or part of the circuit 504 can be provided over the substrate 511.

Embodiment 4

(72) In this embodiment, examples of a pixel included in the pixel portion 101 will be described.

(73) FIG. 10A illustrates an example of a circuit of the pixel 102a. A gate of a transistor 801 is connected to the wiring 104a. A first terminal of the transistor 801 is connected to the wiring 103a. A second terminal of the transistor 801 is connected to a first terminal of a display element 802. A second terminal of the display element 802 is connected to a wiring 803. A first terminal of a capacitor 804 is connected to the second terminal of the transistor 801. A second terminal of the capacitor 804 is connected to a wiring 805.

(74) Here, the wirings 803 can be connected to each other in all the pixels. Moreover, a predetermined voltage is supplied to the wiring 803. For that reason, the wiring 803 can have a function of a common wiring, a counter electrode, or the like.

(75) The wirings 805 can be connected to each other in other pixels, for example, horizontal pixels. Moreover, a predetermined voltage is supplied to the wiring 805. For that reason, the wiring 805 can have a function of a common wiring, a capacitor wiring, or the like.

(76) The transistor 801 can have a function of selecting whether or not to supply a signal to the display element 802 or the capacitor 804. Accordingly, the transistor 801 can have a switch function. Alternatively, the transistor 801 can have a function of a switching transistor (a transistor for switching) or a selection transistor.

(77) Note that the capacitor 804 can be omitted so that the aperture ratio is increased. FIG. 10B illustrates a circuit diagram in that case. By using a transistor with low off-state current, for example, a transistor including an oxide semiconductor as the transistor 801, a voltage applied to the display element 802 can be retained even when the capacitor 804 is omitted.

(78) Note that examples of the pixel circuit are not limited to the circuits illustrated in FIGS. 10A and 10B. FIG. 11A illustrates another example of a pixel circuit. A gate of a transistor 1301 is connected to the wiring 104a. A first terminal of the transistor 1301 is connected to the wiring

103a. A second terminal of the transistor **1301** is connected to a gate of a transistor **1311**. A first terminal of the transistor **1311** is connected to a wiring **1305**. A second terminal of the transistor **1311** is connected to a first terminal of the display element **802**. A second terminal of the display element **802** is connected to a wiring **1303**. A first terminal of a capacitor **1304** is connected to the second terminal of the transistor **1301**. A second terminal of the capacitor **1304** is connected to the second terminal of the transistor **1311**.

(79) Note that a wiring or a terminal to which the second terminal of the capacitor **1304** is connected is not limited to the example in FIG. **11A**; the second terminal of the capacitor **1304** can be connected to another wiring, for example, the wiring **1305**.

(80) Here, the wirings **1303** can be connected to each other in all the pixels. Moreover, a predetermined voltage is supplied to the wiring **1303**. For that reason, the wiring **1303** can have a function of a common wiring, a counter electrode, a cathode wiring, a cathode line, or the like.

(81) The wirings **1305** can be connected to each other in other pixels, for example, horizontal pixels or vertical pixels. Moreover, a predetermined voltage is supplied to the wiring **1305**. For that reason, the wiring **1305** can have a function of a common wiring, a capacitor wiring, a power supply line, a current supply line, an anode line, or the like.

(82) The transistor **1301** can have a function of selecting whether or not to supply a signal to the transistor **1311** or the capacitor **1304**. Accordingly, the transistor **1301** can have a switch function. Alternatively, the transistor **1301** can have a function of a switching transistor or a selection transistor.

(83) The transistor **1311** can have a switch function of selecting whether or not to supply a signal, a voltage, or a current to the display element **802**; and a function of a current source for controlling the magnitude of the signal, voltage, or current. Alternatively, the transistor **1311** can have a function of a driving transistor.

(84) Note that the capacitor **1304** can be omitted so that the aperture ratio is increased. FIG. **11B** illustrates a circuit diagram in that case. By using a transistor with low off-state current, for example, a transistor including an oxide semiconductor as the transistors **1301** and **1311**, a voltage applied to the display element **802** can be retained even when the capacitor **1304** is omitted.

(85) A variety of elements can be used as the display element **802**, and the display element **802** can function as a light-emitting element in some cases. FIG. **11B** illustrates a circuit diagram in the case where a light-emitting element **802a** is used as a display element.

(86) Examples of display elements are elements including a display medium whose contrast, luminance, reflectance, transmittance, or the like changes by electromagnetic action, such as an EL (electroluminescence) element (e.g., an EL element containing organic and inorganic materials, an organic EL element, and an inorganic EL element), an LED (e.g., a white LED, a red LED, a green LED, and a blue LED), a liquid crystal element, electronic ink, an electrophoretic element, and a carbon nanotube. An example of a display device including liquid crystal elements is a liquid crystal display. An example of a display device including electronic ink or electrophoretic elements is electronic paper.

(87) An example of an EL element is an element including an anode, a cathode, and an EL layer placed between the anode and the cathode. Examples of an EL layer are a layer utilizing light emission (fluorescence) from a singlet exciton, a layer utilizing light emission (phosphorescence) from a triplet exciton, a layer utilizing light emission (fluorescence) from a singlet exciton and light emission (phosphorescence) from a triplet exciton, a layer formed using an organic material, a layer formed using an inorganic material, a layer formed using an organic material and an inorganic material, a layer including a high-molecular material, a layer including a low-molecular material, and a layer including a high-molecular material and a low-molecular material. Note that various types of EL elements can be used without limitation to the above.

(88) An example of a liquid crystal element is an element that controls transmission and non-transmission of light by optical modulation action of liquid crystals. The element can include a pair

of electrodes and a liquid crystal layer. The optical modulation action of liquid crystals is controlled by an electric field applied to the liquid crystals (including a lateral electric field, a vertical electric field, and a diagonal electric field). Moreover, the following methods can be used for driving the liquid crystals, for example: a TN (twisted nematic) mode, an STN (super twisted nematic) mode, an IPS (in-plane-switching) mode, an FFS (fringe field switching) mode, an MVA (multi-domain vertical alignment) mode, a PVA (patterned vertical alignment) mode, an ASV (advanced super view) mode, an ASM (axially symmetric aligned microcell) mode, an OCB (optically compensated birefringence) mode, an ECB (electrically controlled birefringence) mode, an FLC (ferroelectric liquid crystal) mode, an AFLC (anti-ferroelectric liquid crystal) mode, a PDLC (polymer dispersed liquid crystal) mode, a PNLC (polymer network liquid crystal) mode, a guest-host mode, and a blue phase mode. Note that various liquid crystal elements and driving methods can be used without limitation to the above.

(89) Since there are few limitations on the layout of the transistors included in the circuit **111**, the channel width (or the gate width) W of the transistors included in the circuit **111** (e.g., the transistors **201a** to **201L**) can be larger than the channel width (or the gate width) W of the transistor included in the pixel (e.g., the transistors **801**, **1301**, and **1311**). In particular, a transistor including an oxide semiconductor has a low off-state current; therefore, an increase in the channel width (or the gate width) W causes fewer adverse effects. Further, when the channel width (or the gate width) W of the transistors included in the circuit **111** is increased, precharge and inspection can be rapidly performed. Similarly, the channel length (or the gate length) L of the transistors included in the circuit **111** (e.g., the transistors **201a** to **201L**) can be larger than the channel length (or the gate length) L of the transistor included in the pixel (e.g., the transistors **801**, **1301**, and **1311**).

Embodiment 5

(90) In this embodiment, a transistor in which a channel formation region is formed using an oxide semiconductor is used as each of the transistors **201a** to **201L**, the transistor **801**, the transistor **1301**, the transistor **1311**, and the like.

(91) Examples of oxide semiconductors are an In—Sn—Ga—Zn—O-based oxide semiconductor which is an oxide of four metal elements; an In—Ga—Zn—O-based oxide semiconductor, an In—Sn—Zn—O-based oxide semiconductor, an In—Al—Zn—O-based oxide semiconductor, a Sn—Ga—Zn—O-based oxide semiconductor, an Al—Ga—Zn—O-based oxide semiconductor, and a Sn—Al—Zn—O-based oxide semiconductor which are oxides of three metal elements; an In—Zn—O-based oxide semiconductor, a Sn—Zn—O-based oxide semiconductor, an Al—Zn—O-based oxide semiconductor, a Zn—Mg—O-based oxide semiconductor, a Sn—Mg—O-based oxide semiconductor, and an In—Mg—O-based oxide semiconductor which are oxides of two metal elements; an In—O-based oxide semiconductor, a Sn—O-based oxide semiconductor, and a Zn—O-based oxide semiconductor. Further, the above-described metal oxide semiconductor may contain SiO.sub.2.

(92) As the oxide semiconductor, a material expressed by $\text{InMO}_{3-m}(\text{ZnO})_m$ ($m > 0$) can be used. Here, M represents one or more metal elements selected from Ga, Al, Mn, and Co. For example, M can be Ga, Ga and Al, Ga and Mn, or Ga and Co. An oxide semiconductor whose composition formula is represented by $\text{InMO}_{3-m}(\text{ZnO})_m$ ($m > 0$) where Ga is included as M is referred to as an In—Ga—Zn—O oxide semiconductor, and a thin film thereof is also referred to as an In—Ga—Zn—O-based film.

(93) One embodiment of a method for manufacturing a transistor in which a channel formation region is formed using an oxide semiconductor will be described with reference to FIGS. **12A** to **12D**.

(94) FIGS. **12A** to **12D** illustrates an example of a cross-sectional structure of a transistor. A transistor **410** illustrated in FIGS. **12A** to **12D** has a bottom-gate structure called a channel-etched structure.

(95) Although a single-gate transistor is illustrated in FIGS. 12A to 12D, a multi-gate transistor including a plurality of channel formation regions can be formed as needed.

(96) Steps for manufacturing the transistor **410** over a substrate **400** will be described below with reference to FIGS. 12A to 12D.

(97) First, a conductive film is formed over the substrate **400** having an insulating surface, and then, a gate electrode layer **411** is formed through a first photolithography process.

(98) Although there is no particular limitation on a substrate that can be used as the substrate **400** having an insulating surface, the substrate needs to have heat resistance high enough to at least withstand heat treatment to be performed later. For example, a glass substrate made of barium borosilicate glass, aluminoborosilicate glass, or the like can be used. A glass substrate whose strain point is 730° C. or more is preferably used when the temperature of the heat treatment performed later is high.

(99) An insulating film serving as a base film may be provided between the substrate **400** and the gate electrode layer **411**. The base film has a function of preventing diffusion of an impurity element from the substrate **400**, and can be formed with a single-layer structure or a layered structure using one or more of a silicon nitride film, a silicon oxide film, a silicon nitride oxide film, and a silicon oxynitride film.

(100) The gate electrode layer **411** can be formed with a single-layer structure or a layered structure using a metal material such as molybdenum, titanium, chromium, tantalum, tungsten, aluminum, copper, neodymium, or scandium or an alloy material containing any of these materials as its main component.

(101) Then, a gate insulating layer **402** is formed over the gate electrode layer **411**.

(102) The gate insulating layer **402** can be formed with a single-layer structure or a layered structure using a silicon oxide layer, a silicon nitride layer, a silicon oxynitride layer, a silicon nitride oxide layer, or an aluminum oxide layer by a plasma CVD method, a sputtering method, or the like. Furthermore, a high-k material such as hafnium oxide (HfOx) or tantalum oxide (TaOx) can be used as the gate insulating layer. The thickness of the gate insulating layer **402** is 100 nm to 500 nm. In the case of employing a layered structure, the gate insulating layer **402** is a stack, for example, of a first gate insulating layer with a thickness of 50 nm to 200 nm and a second gate insulating layer with a thickness of 5 nm to 300 nm over the first gate insulating layer.

(103) In this embodiment, a silicon oxynitride layer having a thickness of 100 nm or less is formed by plasma CVD as the gate insulating layer **402**.

(104) Further, as the gate insulating layer **402**, a silicon oxynitride film may be formed using a high-density plasma apparatus. Here, a high-density plasma apparatus refers to an apparatus that can realize a plasma density of $1 \times 10^{11} / \text{cm}^3$ or higher. For example, plasma is generated by applying a microwave power of 3 kW to 6 kW, and the insulating film is formed. The insulating film formed by the high-density plasma apparatus can have a uniform thickness, and thus has excellent step coverage. Moreover, the thickness of a thin insulating film formed using the high-density plasma apparatus can be precisely controlled.

(105) The insulating film obtained with the high-density plasma apparatus is greatly different from an insulating film obtained with a conventional parallel plate PCVD apparatus. The etching rate of the insulating film obtained with the high-density plasma apparatus is lower than that of the insulating film obtained with a parallel plate PCVD apparatus by 10% or more or 20% or more in the case where the etching rates with the same etchant are compared to each other. Thus, it can be said that the insulating film obtained with the high-density plasma apparatus is a dense film.

(106) The oxide semiconductor that becomes an i-type or substantially i-type oxide semiconductor (a purified oxide semiconductor) in a later step is extremely sensitive to the interface state or interface electric charge; therefore, the interface with the gate insulating layer is important. For that reason, the gate insulating layer (GI) that is in contact with the purified oxide semiconductor needs to have high quality. Therefore, high-density plasma CVD with use of microwaves (2.45 GHz) is

preferably employed since a dense and high-quality insulating film having high withstand voltage can be formed. When the purified oxide semiconductor and the high-quality gate insulating layer are in close contact with each other, the interface state density can be reduced and favorable interface characteristics can be obtained. It is important that the gate insulating layer have lower interface state density with an oxide semiconductor and a favorable interface as well as having favorable film quality as a gate insulating layer.

(107) Then, an oxide semiconductor film **430** is formed to a thickness of 2 nm to 200 nm over the gate insulating layer **402**. As the oxide semiconductor film **430**, an In—Ga—Zn—O-based oxide semiconductor film, an In—Zn—O-based oxide semiconductor film, or the like is used. In this embodiment, the oxide semiconductor film **430** is formed by a sputtering method with the use of an In—Ga—Zn—O-based oxide semiconductor target. A cross-sectional view at this stage is illustrated in FIG. **12A**. Alternatively, the oxide semiconductor film **430** can be formed by a sputtering method in a rare gas (typically argon) atmosphere, an oxygen atmosphere, or a mixed atmosphere containing a rare gas (typically argon) and oxygen.

(108) Here, film deposition is performed using a metal oxide target containing In, Ga, and Zn (In.sub.2O.sub.3:Ga.sub.2O.sub.3:ZnO=1:1:1 [molar ratio]). The deposition conditions are set as follows: the distance between the substrate **400** and the target is 100 mm; the pressure is 0.2 Pa; the direct current (DC) power supply is 0.5 kW; and the atmosphere is a mixed atmosphere of argon and oxygen (argon:oxygen=30 sccm:20 sccm and the flow rate ratio of oxygen is 40%). Note that a pulse direct current (DC) power supply is preferably used because powder substances generated at the time of deposition can be reduced and the film thickness can be made uniform. The In—Ga—Zn—O-based film is formed to a thickness of 5 nm to 200 nm. In this embodiment, as the oxide semiconductor film, a 20-nm-thick In—Ga—Zn—O-based film is formed by a sputtering method with the use of an In—Ga—Zn—O-based metal oxide target. Then, the oxide semiconductor film **430** is processed into an island-shaped oxide semiconductor layer through a second photolithography process.

(109) Next, dehydration or dehydrogenation of the oxide semiconductor layers is performed. The temperature of first heat treatment for dehydration or dehydrogenation is higher than or equal to 400° C. and lower than or equal to 750° C., preferably higher than or equal to 400° C. and lower than the strain point of the substrate. Here, the substrate is introduced into an electric furnace which is one of heat treatment apparatuses, heat treatment is performed on the oxide semiconductor layer at 450° C. for one hour in a nitrogen atmosphere, and then, the oxide semiconductor layer is not exposed to the air so that entry of water and hydrogen into the oxide semiconductor layer is prevented; thus, an oxide semiconductor layer **431** is obtained (see FIG. **12B**).

(110) Note that a heat treatment apparatus is not limited to an electric furnace, and may include a device for heating an object to be processed by heat conduction or heat radiation from a heating element such as a resistance heating element. For example, an RTA (rapid thermal anneal) apparatus such as a GRTA (gas rapid thermal anneal) apparatus or an LRTA (lamp rapid thermal anneal) apparatus can be used. An LRTA apparatus is an apparatus for heating an object to be processed by radiation of light (an electromagnetic wave) emitted from a lamp such as a halogen lamp, a metal halide lamp, a xenon arc lamp, a carbon arc lamp, a high pressure sodium lamp, or a high pressure mercury lamp. A GRTA apparatus is an apparatus for heat treatment using a high-temperature gas. As the gas, an inert gas that does not react with an object to be processed by heat treatment, for example, nitrogen or a rare gas such as argon is used.

(111) For example, as the first heat treatment, GRTA by which the substrate is moved into an inert gas heated to a high temperature as high as 650° C. to 700° C., heated for several minutes, and moved out of the inert gas heated to the high temperature may be performed. With GRTA, high-temperature heat treatment for a short period of time can be achieved.

(112) Note that in the first heat treatment, it is preferable that water, hydrogen, and the like be not included in the atmosphere of nitrogen, a rare gas such as helium, neon, or argon, or dry air. For

example, the purity of nitrogen or a rare gas such as helium, neon, or argon, which is introduced into the heat treatment apparatus, is preferably 6N (99.9999%) or more, more preferably 7N (99.99999%) or more (i.e., impurity concentration is preferably 1 ppm or lower, more preferably 0.1 ppm or lower).

(113) The first heat treatment for the oxide semiconductor layer may be performed on the oxide semiconductor film **430** before being processed into the island-shaped oxide semiconductor layer. In that case, after the first heat treatment, the substrate is taken out of the heat treatment apparatus, and then the second photolithography process is performed.

(114) In the case where an opening portion is formed in the gate insulating layer **402**, the step of forming the opening portion may be performed before or after the oxide semiconductor film **430** is subjected to dehydration or dehydrogenation treatment.

(115) Note that the etching of the oxide semiconductor film **430** is not limited to wet etching and dry etching may also be used.

(116) As an etching gas used for dry etching of the oxide semiconductor film **430**, a gas containing chlorine (e.g., chlorine (Cl.sub.2) or boron chloride (BCl.sub.3)) is preferably used.

(117) As an etchant used for wet etching of the oxide semiconductor film **430**, a mixed solution of phosphoric acid, acetic acid, and nitric acid; ITO07N (produced by Kanto Chemical Co., Inc.); or the like can be used.

(118) Next, a metal conductive film is formed over the gate insulating layer **402** and the oxide semiconductor layer **431**. The metal conductive film may be formed by a sputtering method or a vacuum evaporation method. Examples of a material for the metal conductive film are an element selected from aluminum (Al), chromium (Cr), copper (Cu), tantalum (Ta), titanium (Ti), molybdenum (Mo), tungsten (W), neodymium (Nd), and scandium (Sc); an alloy containing any of these elements as a component; and an alloy containing any of these elements in combination. A nitride film of any of these elements may be used. Alternatively, one or more materials selected from manganese (Mn), magnesium (Mg), zirconium (Zr), beryllium (Be), and yttrium (Y) may be used. The metal conductive film may have a single-layer structure or a layered structure of two or more layers. For example, the metal conductive film can have a single-layer structure of an aluminum film containing silicon; a two-layer structure of an aluminum film and a titanium film stacked thereover; or a three-layer structure in which a titanium film, an aluminum film, and a titanium film are stacked in this order.

(119) When heat treatment is performed after formation of the metal conductive film, the metal conductive film preferably has heat resistance high enough to withstand the heat treatment.

(120) Through a third photolithography process, a resist mask is formed over the metal conductive film and etching is selectively performed, so that a source electrode layer **415a** and a drain electrode layer **415b** are formed. Then, the resist mask is removed (see FIG. 12C).

(121) In this embodiment, a titanium film is used as the metal conductive film, an In—Ga—Zn—O-based oxide is used for the oxide semiconductor layer **431**, and an ammonia peroxide mixture (31 wt % hydrogen peroxide solution:28 wt % ammonia water:water=5:2:2) is used as the etchant for the titanium film.

(122) Note that through the third photolithography process, only part of the oxide semiconductor layer **431** is sometimes etched so that a groove (a recessed portion) is formed in the oxide semiconductor layer.

(123) In order to reduce the number of photomasks used in the photolithography processes and reduce the number of photolithography processes, an etching step may be performed with the use of a multi-tone mask which is a light-exposure mask through which light is transmitted to have a plurality of intensities. Since a resist mask formed using a multi-tone mask has a plurality of thicknesses and can be further changed in shape by performing ashing, the resist mask can be used in a plurality of etching steps to provide different patterns. Therefore, a resist mask corresponding to at least two kinds of different patterns can be formed by one multi-tone mask. Thus, the number

of light-exposure masks can be reduced and the number of corresponding photolithography processes can be also reduced, so that the manufacturing process can be simplified.

(124) Next, plasma treatment using a gas such as nitrous oxide (N.sub.2O), nitrogen (N.sub.2), or argon (Ar) is performed. By this plasma treatment, absorbed water and the like attached to an exposed surface of the oxide semiconductor layer are removed. Plasma treatment may be performed using a mixture gas of oxygen and argon.

(125) After the plasma treatment, an oxide insulating layer **416** that is in contact with part of the oxide semiconductor layer and serves as a protective insulating film is formed without exposure to the air.

(126) The oxide insulating layer **416** has a thickness of at least 1 nm and can be formed as appropriate by a sputtering method or the like with which impurities such as water and hydrogen are not mixed into the oxide insulating layer **416**. When hydrogen is contained in the oxide insulating layer **416**, entry of the hydrogen to the oxide semiconductor layer is caused, thereby making a backchannel of the oxide semiconductor layer **431** have a lower resistance (have n-type conductivity) and forming parasitic channels. Therefore, it is important that a formation method in which hydrogen is not used is employed in order to form the oxide insulating layer **416** containing as little hydrogen as possible.

(127) In this embodiment, a 200-nm-thick silicon oxide film is deposited as the oxide insulating layer **416** by a sputtering method. The substrate temperature in film formation is higher than or equal to room temperature and lower than or equal to 300° C. and is 100° C. in this embodiment. The silicon oxide film can be formed by a sputtering method in a rare gas (typically argon) atmosphere, an oxygen atmosphere, or an atmosphere of a rare gas (typically argon) and oxygen. As a target, a silicon oxide target or a silicon target can be used. For example, the silicon oxide film can be formed using a silicon target by a sputtering method in an atmosphere including oxygen and nitrogen.

(128) Next, second heat treatment (preferably at 200° C. to 400° C., for example, at 250° C. to 350° C.) is performed in an inert gas atmosphere, a dry air atmosphere, or an oxygen gas atmosphere. For example, the second heat treatment is performed at 250° C. for one hour in a nitrogen atmosphere. Through the second heat treatment, part of the oxide semiconductor layer (a channel formation region) is heated while being in contact with the oxide insulating layer **416**. Thus, oxygen is supplied to part of the oxide semiconductor layer (the channel formation region). Moreover, in the vicinity of the interface between the source electrode layer **415a** or the drain electrode layer **415b** and the oxide semiconductor layer, oxygen is diffused into the source electrode layer **415a** or the drain electrode layer **415b**. Accordingly, a source region **414a** and a drain region **414b** are formed.

(129) Through the above steps, the oxide semiconductor layer is subjected to the heat treatment for dehydration or dehydrogenation, and then, part of the oxide semiconductor layer (the channel formation region) is selectively made to be in an oxygen excess state. Note that the part of the oxide semiconductor layer in an oxygen excess state is shown as a region **413** in FIG. 12D. Through the above-described process, the transistor **410** is formed.

(130) Further, heat treatment may be performed at 100° C. to 200° C. for 1 hour to 30 hours in the air. In this embodiment, the heat treatment is performed at 150° C. for 10 hours. This heat treatment may be performed at a fixed heating temperature. Alternatively, the following change in the heating temperature may be conducted plural times repeatedly: the heating temperature is increased from a room temperature to a temperature of 100° C. to 200° C. and then decreased to a room temperature.

(131) A protective insulating layer may be further formed over the oxide insulating layer **416**. For example, a silicon nitride film is formed by an RF sputtering method. Since an RF sputtering method has high productivity, it is preferably used as a method for forming the protective insulating layer. As the protective insulating layer, an inorganic insulating film that does not include impurities such as moisture, a hydrogen ion, and OH.sup.- and blocks entry of these from the

outside is used. For example, a silicon nitride film, an aluminum nitride film, a silicon nitride oxide film, or an aluminum oxynitride film is used. In this embodiment, a protective insulating layer **403** is formed using a silicon nitride film as the protective insulating layer (see FIG. **12D**).

(132) The oxide semiconductor layer in the transistor **410** in this embodiment is an intrinsic (i-type) or substantially intrinsic oxide semiconductor layer obtained by removal of hydrogen, which is an n-type impurity, for purification so that the oxide semiconductor layer contains impurities other than the main component as little as possible. In other words, the oxide semiconductor layer in this embodiment is a purified i-type (intrinsic) semiconductor or a substantially intrinsic semiconductor obtained by removing impurities such as hydrogen and water as much as possible, not by adding an impurity. This enables the Fermi level (E_f) to be at the same level as the intrinsic Fermi level (E_i).

(133) It is said that an oxide semiconductor has a band gap (E_g) of 3.15 eV and an electron affinity (χ) of 4.3 eV. The work function of titanium (Ti) contained in the source electrode layer and the drain electrode layer is substantially equal to the electron affinity (χ) of an oxide semiconductor. In that case, a Schottky barrier for electrons is not formed at an interface between the metal and the oxide semiconductor.

(134) For example, even when a transistor has a channel width W of $1 \times 10^{.4} \mu\text{m}$ and a channel length L of $3 \mu\text{m}$, the off-state current can be $10^{.-13} \text{ A}$ or less and the subthreshold swing value (S value) can be 0.1 V/decade at room temperature (with a 100-nm-thick gate insulating layer).

(135) As described above, the oxide semiconductor is purified so as to contain impurities which are not its main components as little as possible; thus, the transistor **410** can operate in a favorable manner.

(136) The above-described oxide semiconductor is a purified and electrically intrinsic (i-type) oxide semiconductor made by the following manner: in order to suppress variations in electrical characteristics, impurities that cause variations, such as hydrogen, moisture, a hydroxyl group, and hydride (also referred to as hydrogen compound), are removed intentionally; and oxygen which is a main component of the oxide semiconductor and is reduced in the step of removing impurities is supplied.

(137) Therefore, it is preferable that the oxide semiconductor contain as little hydrogen as possible. Further, the purified oxide semiconductor has very few carriers (close to zero) and the carrier density is less than $1 \times 10^{.12} / \text{cm}^{.3}$, preferably less than $1 \times 10^{.11} / \text{cm}^{.3}$. In other words, the carrier concentration of the oxide semiconductor layer is made as close to zero as possible. Since the oxide semiconductor layer includes extremely few carriers, the off-state current of the transistor can be reduced. It is preferable that off-state current be as low as possible. The off-state current per channel width (W) of $1 \mu\text{m}$ of the transistor is $100 \text{ aA}/\mu\text{m}$ or less, preferably $10 \text{ zA}/\mu\text{m}$ or less (zA: zeptoampere), further preferably $1 \text{ zA}/\mu\text{m}$ or less. Further, since there is no pn junction and no hot carrier degradation, electric characteristics of the transistor are not adversely affected by them.

(138) As described above, the off-state current can be extremely low in a transistor in which an oxide semiconductor that is purified by drastically removing hydrogen contained therein is used for a channel formation region. In other words, in circuit design, the oxide semiconductor layer can be regarded as an insulator when the transistor is off. On the other hand, when the transistor is on, the current supply capability of the oxide semiconductor layer is expected to be higher than that of a semiconductor layer formed of amorphous silicon.

(139) Design is performed assuming that the off-state current of a thin film transistor formed using low-temperature polysilicon is approximately 10000 times as high as that of a transistor formed using an oxide semiconductor. Thus, a period for holding voltage of the transistor formed using an oxide semiconductor can be approximately 10000 times as long as that of the thin film transistor formed using low-temperature polysilicon, when these transistors have an equivalent storage capacitance (of about 0.1 pF). For example, when moving images are displayed at 60 frames per second, a holding period for one signal writing can be approximately 160 seconds, which is 10000

times as long as that of the thin film transistor formed using low-temperature polysilicon. In this manner, a still image can be displayed on a display portion even by less frequent writing of image signals.

Embodiment 6

(140) In this embodiment, an example of a pixel and a method for driving the pixel will be described. Specifically, an example of a pixel that includes a display element with memory properties and an example of a method for driving the pixel will be described.

(141) FIG. 13A illustrates an example of a circuit diagram of a pixel. A pixel **5450** includes a transistor **5451**, a capacitor **5452**, and a display element **5453**. A first terminal of the transistor **5451** is connected to a wiring **5461**. A second terminal of the transistor **5451** is connected to one electrode of the capacitor **5452** and one electrode of the display element **5453** (also referred to as a pixel electrode). A gate of the transistor **5451** is connected to a wiring **5462**. The other electrode of the capacitor **5452** is connected to a wiring **5463**. The other electrode of the display element **5453** is connected to an electrode **5454** (e.g., a common electrode, a counter electrode, or a cathode electrode).

(142) Note that an electrode **5455** refers to one electrode of the display element **5453**.

(143) When FIG. 13A is compared to FIG. 10A, the transistor **5451** corresponds to the transistor **801**; the display element **5453**, the display element **802**; the capacitor **5452**, the capacitor **804**; the wiring **5462**, the wiring **104a**; and the wiring **5461**, the wiring **103a**.

(144) The display element **5453** preferably has memory properties. Examples of the display element **5453** and a method for driving the display element **5453** are microcapsule electrophoresis, microcup electrophoresis, horizontal electrophoresis, vertical electrophoresis, twisting ball, liquid powder display, electronic liquid powder (registered trademark), a cholesteric liquid crystal element, a chiral nematic liquid crystal, an anti-ferroelectric liquid crystal, and a polymer dispersed liquid crystal.

(145) Since a voltage applied to the display element **5453** is very high, a transistor for driving the display element **5453** needs to have high withstand voltage. Moreover, the off-state current of the transistor needs to be low even when such a high voltage is applied. By using a transistor including an oxide semiconductor as the transistor, the transistor can have high withstand voltage and low off-state current.

(146) FIG. 13B is a cross-sectional view of a pixel using microcapsule electrophoresis. A plurality of microcapsules **5480** are placed between an electrode **5454** and an electrode **5455**. The plurality of microcapsules **5480** are fixed by a resin **5481**. The resin **5481** functions as a binder. The resin **5481** preferably has light-transmitting properties. A space formed by the electrode **5454**, the electrode **5455**, and the microcapsule **5480** can be filled with a gas such as air or an inert gas. In such a case, a layer including a glue, an adhesive, or the like is preferably formed on one or both of the electrodes **5454** and **5455** to fix the microcapsules **5480**.

(147) The microcapsule **5480** includes a film **5482**, a liquid **5483**, particles **5484**, and particles **5485**. The liquid **5483**, the particles **5484**, and the particles **5485** are sealed in the film **5482**. The film **5482** has light-transmitting properties. The liquid **5483** functions as a dispersion liquid. The particles **5484** and the particles **5485** can be dispersed in the film **5482** by the liquid **5483**. It is preferable that the liquid **5483** have light-transmitting properties and be not colored. The particle **5484** and the particle **5485** have different colors. For example, it is preferable that one of the particle **5484** and the particle **5485** be black and the other of the particle **5484** and the particle **5485** be white. Note that the particle **5484** and the particle **5485** are charged so that their electric charge densities or polarities are different from each other. For example, one of the particle **5484** and the particle **5485** is positively charged and the other of the particle **5484** and the particle **5485** is negatively charged. Thus, when a potential difference occurs between the electrode **5454** and the electrode **5455**, the particle **5484** and the particle **5485** move in accordance with the direction of electric fields. Accordingly, the reflectance of the display element **5453** is changed, so that the gray

level can be controlled. Note that the structure of the microcapsule **5480** is not limited to the above-described structure. For example, the liquid **5483** can be colored. As another example, as particles sealed in the film **5482**, one kind of particles or three kinds or more of particles can be used. As another example, colors of the particle **5484** and the particle **5485** can be selected from red, green, blue, cyan, magenta, yellow emerald green, vermillion, and the like in addition to white and black. (148) The film **5482** is formed using a light-transmitting material (e.g., a polymer resin such as an acrylic resin (e.g., poly(methyl methacrylate) and poly(ethyl methacrylate)), a urea resin, or gum arabic), for example. Note that the film **5482** is preferably gelatinous. By using such a film **5482**, the plasticity, bending strength, mechanical strength, and the like can be improved, leading to improvement in flexibility. Alternatively, the microcapsules **5480** can be uniformly arranged with no gap therebetween over a substrate such as film.

(149) A light-transmitting oily liquid is preferably used as the liquid **5483**. Specific examples of the liquid **5483** are an alcohol-based solvent (e.g., methanol and ethanol), ester (e.g., ethyl acetate and butyl acetate), aliphatic hydrocarbon (e.g., ketone such as acetone, methyl ethyl ketone, and methyl isobutyl ketone; pentane, hexane, and octane), alicyclic hydrocarbon (e.g., cyclohexane and methylcyclohexane), aromatic hydrocarbon such as benzene having a long-chain alkyl group (e.g., benzene, toluene, and xylene), halogenated hydrocarbon (e.g., methylene chloride and chloroform), carboxylate salt, water, and other kinds of oils. Other examples of the liquid **5483** are a mixture of two or more of the above-described materials, a combination of a surface active agent or the like and one of the above materials, and a combination of a surface active agent or the like and a mixture of two or more of the above materials.

(150) Each of the particle **5484** and the particle **5485** is formed using a pigment. The pigments included in the particle **5484** and the particle **5485** preferably have different colors. For example, it is preferable that the particle **5484** be formed using a black pigment and the particle **5485** be formed using a white pigment. Examples of the black pigment are aniline black and carbon black. Examples of the white pigment are titanium dioxide, zinc white (zinc oxide), and antimony trioxide. Note that it is possible to add, to the above-described pigment, a charge controlling agent (e.g., electrolyte, a surface active agent, metallic soap, resin, rubber, oil, varnish, or a compound), a dispersing agent (e.g., a titanium-based coupling agent, an aluminum-based coupling agent, or a silane-based coupling agent), a lubricant agent, a stabilizing agent, or the like.

(151) FIG. **14A** is a cross-sectional view of a pixel in the case where a twisting ball display method is used for the display element **5453**. In the twisting ball display method, the reflectance is changed by rotation of a display element in order to control the gray level. The difference from FIG. **13B** is that instead of the microcapsule **5480**, a twisting ball **5486** is placed between the electrode **5454** and the electrode **5455**. The twisting ball **5486** includes a particle **5487** and a cavity **5488** formed around the particle **5487**. The particle **5487** is a spherical particle in which a surface of one hemisphere is colored in a given color and a surface of the other hemisphere is colored in a different color. Here, the particle **5487** has a white hemisphere and a black hemisphere. Note that there is a difference in electric charge density or polarity between the two hemispheres. For that reason, by generating a potential difference between the electrode **5454** and the electrode **5455**, the particle **5487** can be rotated in accordance with the direction of electric fields. The cavity **5488** is filled with a liquid. As the liquid, a liquid similar to the liquid **5483** can be used. Note that the structure of the twisting ball **5486** is not limited to the structure illustrated in FIG. **14A**. For example, the twisting ball **5486** can be a cylinder, an ellipse, or the like.

(152) FIG. **14B** is a cross-sectional view of a pixel in the case where a microcup electrophoresis method is used for the display element **5453**. A microcup array can be formed in the following manner: a microcup **5491** that is formed using a UV curable resin or the like and has a plurality of recessed portions is filled with charged pigment particles **5493** dispersed in a dielectric solvent **5492**, and sealing is performed with a sealing layer **5494**. An adhesive layer **5495** is preferably formed between the sealing layer **5494** and the electrode **5455**. As the dielectric solvent **5492**, a

colorless solvent can be used or a colored solvent of red, blue, or the like can be used. This embodiment shows the case where one kind of charged pigment particles is used; alternatively, two or more kinds of charged pigment particles may be used. The microcup has a wall by which cells are separated, and thus has sufficiently high resistance to shock and pressure. Moreover, since the components of the microcup are tightly sealed, adverse effects due to change in environment can be reduced.

(153) FIG. 14C is a cross-sectional view of a pixel in the case where an electronic liquid powder (registered trademark) display method is used for the display element 5453. The electronic liquid powder has fluidity and is a substance having properties of fluid and properties of a particle. In this method, cells are separated by partitions 5504, and electronic liquid powders 5502 and electronic liquid powders 5503 are placed in the cell. As the electronic liquid powder 5502 and the electronic liquid powder 5503, a white particle and a black particle are preferably used. Note that the kinds of the electronic liquid powders 5502 and 5503 are not limited thereto. For example, colored particles of two colors which are not white and black can be used as the electronic liquid powders 5502 and 5503. As another example, one of the electronic liquid powder 5502 and the electronic liquid powder 5503 can be omitted.

(154) As illustrated in FIG. 13A, a signal is input to the wiring 5461. Specifically, a signal for controlling the gray level of the display element 5453 (e.g., a video signal) is input to the wiring 5461. Accordingly, the wiring 5461 has a function of a signal line or a source signal line (also referred to as a video signal line or a source line). A signal is input to the wiring 5462. Specifically, a signal for controlling a conduction state of the transistor 5451 (e.g., a gate signal, a scan signal, or a selection signal) is input to the wiring 5462. Accordingly, the wiring 5462 has a function of a signal line or a gate signal line (also referred to as a scan signal line or a gate line). A predetermined voltage is supplied to the wiring 5463. The wiring 5463 is connected to the capacitor 5452. Accordingly, the wiring 5463 has a function of a power supply line or a capacitor line. A predetermined voltage is supplied to the electrode 5454. The electrode 5454 is often shared with a plurality of pixels or all the pixels. Accordingly, the electrode 5454 has a function of a common electrode (such as a counter electrode or a cathode electrode).

(155) Note that the signals or voltages input to the wirings 5461 to 5463 and the electrode 5454 are not limited to the above, and various other signals or voltages can be input. For example, a signal can be input to the wiring 5463. Thus, the potential of the electrode 5455 can be controlled, so that the amplitude voltage of a signal input to the wiring 5461 can be reduced. Accordingly, the wiring 5463 can have a function of a signal line. As another example, by changing a voltage supplied to the electrode 5454, a voltage applied to the display element 5453 can be adjusted. Thus, the amplitude voltage of a signal input to the wiring 5461 can be reduced.

(156) The transistor 5451 has a function of controlling electrical continuity between the wiring 5461 and the electrode 5455, a function of controlling the timing of supplying the potential of the wiring 5461 to the electrode 5455, and/or a function of controlling the timing of selecting the pixel 5450. In such a manner, the transistor 5451 has a function of a switch or a selection transistor. The transistor 5451 is an n-channel transistor. For that reason, the transistor 5451 is turned on when an H-level signal is input to the wiring 5462, and is turned off when an L-level signal is input to the wiring 5462. Note that transistor 5451 is not limited to an n-channel transistor and can be a p-channel transistor. In that case, the transistor 5451 is turned on when an L-level signal is input to the wiring 5462, and is turned off when an H-level signal is input to the wiring 5462. The capacitor 5452 has a function of holding the potential difference between the electrode 5455 and the wiring 5463, and/or a function of keeping the potential of the electrode 5455 at a predetermined value. Thus, a voltage can continue to be applied to the display element 5453 even when the transistor 5451 is off. In such a manner, the capacitor 5452 has a function of a storage capacitor. Note that functions of the transistor 5451 and the capacitor 5452 are not limited to the above, and the transistor 5451 and the capacitor 5452 can have various other functions.

(157) Next, the operation of the pixel in this embodiment will be roughly described. The gray level of the display element **5453** is controlled by applying a voltage to the display element **5453** so that an electric field is generated in the display element **5453**. A voltage applied to the display element **5453** is controlled by controlling the potential of the electrode **5454** and the potential of the electrode **5455**. Specifically, the potential of the electrode **5454** is controlled by controlling a voltage applied to the electrode **5454**. The potential of the electrode **5455** is controlled by controlling a signal input to the wiring **5461**. The signal input to the wiring **5461** is supplied to the electrode **5455** when the transistor **5451** is turned on.

(158) Note that the gray level of the display element **5453** can be controlled by controlling at least one of the intensity of electric fields applied to the display element **5453**, the direction of electric fields applied to the display element **5453**, the time during which electric fields are applied to the display element **5453**, and the like. Note that the gray level of the display element **5453** can be maintained by not generating a potential difference between the electrode **5454** and the electrode **5455**.

(159) Next, an example of the operation of the pixel in this embodiment will be described. The timing chart in FIG. **15A** shows a period T including a selection period and a non-selection period. The period T is a period from the start of a selection period until the start of the next selection period.

(160) In the selection period, an H-level signal is input to the wiring **5462**, so that the potential of the wiring **5462** (shown as a potential V_{5462}) is at H level. For that reason, the transistor **5451** is turned on, so that electrical continuity is established between the wiring **5461** and the electrode **5455**. Thus, a signal input to the wiring **5461** is supplied to the electrode **5455** through the transistor **5451**, and the potential of the electrode **5455** (shown as a potential V_{5455}) becomes a value equal to the signal input to the wiring **5461**. At this time, the capacitor **5452** holds a potential difference between the electrode **5455** and the wiring **5463**. In the non-selection period, an L-level signal is input to the wiring **5462**, so that the potential of the wiring **5462** is at L level. For that reason, the transistor **5451** is turned off, and electrical continuity between the wiring **5461** and the electrode **5455** is broken. Then, the electrode **5455** is set in a floating state. At this time, the capacitor **5452** holds the potential difference between the electrode **5455** and the wiring **5463** in the selection period. For that reason, the potential of the electrode **5455** remains equal to the signal input to the wiring **5461** in the selection period. In such a manner, in the non-selection period, a voltage can continue to be applied to the display element **5453** even when the transistor **5451** is off. As described above, by controlling a signal input to the wiring **5461** in the selection period, a voltage applied to the display element **5453** can be controlled. That is, the gray level of the display element **5453** can be controlled by controlling a signal input to the wiring **5461** in the selection period.

(161) The potential of the electrode **5455** in the non-selection period may be different from the signal input to the wiring **5461** in the selection period because of adverse effects of at least one of the off-state current of the transistor **5451**, feedthrough of the transistor **5451**, charge injection of the transistor **5451**, and the like.

(162) As illustrated in FIG. **15B**, the potential of the electrode **5455** can be equal to that of the electrode **5454** in part of the selection period. Accordingly, even if the same signal continues to be input to the pixel **5450** every time the pixel **5450** is selected, the intensity of electric fields applied to the display element **5453** can be changed by changing the potential of the electrode **5455** in part of the selection period. Therefore, afterimages can be reduced; the response speed can be increased; or variations in response speed between pixels can be reduced so that unevenness or afterimages can be prevented. In order to realize such a driving method, the selection period is preferably divided into a period T1 and a period T2. In the period T1, the potential of the signal input to the wiring **5461** is preferably equal to that of the electrode **5454**. In the period T2, the signal input to the wiring **5461** preferably has various values in order to control the gray level of the display

element **5453**. Note that when the period **T1** is too long, the time during which a signal for controlling the gray level of the display element **5453** is written into the pixel **5450** becomes short. Therefore, the period **T1** is preferably shorter than the period **T2**. Specifically, the period **T1** accounts for preferably 1 to 20%, more preferably 3 to 15%, further preferably 5 to 10% of the selection period.

(163) Next described is an example of the operation of the pixel in this embodiment, in which the gray level of the display element **5453** is controlled by the time during which a voltage is applied to the display element **5453**. The timing chart in FIG. 15C shows a period **Ta** and a period **Tb**. The period **Ta** includes **N** periods **T** (**N** is a natural number). The **N** periods **T** are similar to the period **T** illustrated in FIG. 15A or FIG. 15B. The period **Ta** is a period for changing the gray level of the display element **5453** (e.g., an address period, a writing period, or an image rewriting period). The period **Tb** is a period during which the gray level of the display element **5453** in the period **Ta** is held (i.e., a holding period).

(164) A voltage **V0** is supplied to the electrode **5454**, so that the electrode **5454** is at a potential **V0**. A signal having at least three values is input to the wiring **5461**. Three potentials of the signal are a potential **VH** ($VH > V0$), the potential **V0**, and a potential **VL** ($VL < V0$). Accordingly, the potential **VH**, the potential **V0**, and the potential **VL** are applied to the electrode **5455**.

(165) In each of the **N** periods **T** in the period **Ta**, by controlling a potential applied to the electrode **5455**, a voltage applied to the display element **5453** can be controlled. For example, when the potential **VH** is applied to the electrode **5455**, the potential difference between the electrode **5454** and the electrode **5455** becomes $VH - VL$. Thus, a positive voltage can be applied to the display element **5453**. When the potential **V0** is applied to the electrode **5455**, the potential difference between the electrode **5454** and the electrode **5455** becomes zero. Thus, zero voltage can be applied to the display element **5453**. When the potential **VL** is applied to the electrode **5455**, the potential difference between the electrode **5454** and the electrode **5455** becomes $VL - VH$. Thus, a negative voltage can be applied to the display element **5453**. As described above, in the period **Ta**, the positive voltage ($VH - VL$), the negative voltage ($VL - VH$), and zero voltage can be applied to the display element **5453** in a variety of orders. Thus, the gray level of the display element **5453** can be minutely controlled; afterimages can be reduced; or the response speed can be increased.

(166) Note that in this embodiment, when a positive voltage is applied to the display element **5453**, the gray level of the display element **5453** is close to black (also referred to as a first gray level).

When a negative voltage is applied to the display element **5453**, the gray level of the display element **5453** is close to white (also referred to as a second gray level). When zero voltage is applied to the display element **5453**, the gray level of the display element **5453** is maintained.

(167) In the period **Tb**, a signal input to the wiring **5461** is not written into the pixel **5450**.

Therefore, a potential applied to the electrode **5455** in the **N**th period **T** in the period **Ta** continues to be applied in the period **Tb**. Specifically, in the period **Tb**, the gray level of the display element **5453** is preferably maintained by not generating electric fields in the display element **5453**. For that reason, in the **N**th period **T** in the period **Ta**, the potential **V0** is preferably applied to the electrode **5455**. Thus, the potential **V0** is applied to the electrode **5455** also in the period **Tb**, so that zero voltage is applied to the display element **5453**. In such a manner, the gray level of the display element **5453** can be maintained.

(168) Note that as the gray level to be subsequently expressed by the display element **5453** is closer to the first gray level, the time during which the potential **VH** is applied to the electrode **5455** is preferably longer in the period **Ta**. Alternatively, the frequency of application of the potential **VH** to the electrode **5455** is preferably higher in the **N** periods **T**. Alternatively, in the period **Ta**, it is preferable to increase a time obtained by subtracting the time during which the potential **VL** is applied to the electrode **5455** from the time during which the potential **VH** is applied to the electrode **5455**. Further alternatively, in the **N** periods **T**, it is preferable to increase a frequency obtained by subtracting the frequency of application of the potential **VL** to the electrode **5455** from

the frequency of application of the potential VH to the electrode 5455.

(169) In addition, as the gray level to be subsequently expressed by the display element 5453 is closer to the second gray level, the time during which the potential VL is applied to the electrode 5455 is preferably longer in the period Ta. Alternatively, the frequency of application of the potential VL to the electrode 5455 is preferably higher in the N periods T. Alternatively, in the period Ta, it is preferable to increase a time obtained by subtracting the time during which the potential VH is applied to the electrode 5455 from the time during which the potential VL is applied to the electrode 5455. Further alternatively, in the N periods T, it is preferable to increase a frequency obtained by subtracting the frequency of application of the potential VH to the electrode 5455 from the frequency of application of the potential VL to the electrode 5455.

(170) In the period Ta, a combination of potentials (the potential VH, the potential V0, and the potential VL) applied to the electrode 5455 can depend not only on the gray level to be subsequently expressed by the display element 5453, but also on the gray level that has been expressed by the display element 5453. For that reason, if a different gray level has been expressed by the display element 5453, a combination of potentials applied to the electrode 5455 may vary even when the gray level to be subsequently expressed by the display element 5453 is the same.

(171) For example, in the period Ta for expressing the gray level that has been expressed by the display element 5453, the time during which the potential VL is applied to the electrode 5455 is preferably longer in the period Ta in any of the following cases: the case where the time during which the potential VH is applied to the electrode 5455 is longer; the case where a time obtained by subtracting the time during which the potential VL is applied to the electrode 5455 from the time during which the potential VH is applied to the electrode 5455 is longer; the case where the frequency of application of the potential VH to the electrode 5455 is higher in the N periods T; or the case where a frequency obtained by subtracting the frequency of application of the potential VL to the electrode 5455 from the frequency of application of the potential VH to the electrode 5455 is higher in the N periods T. Alternatively, the frequency of application of the potential VL to the electrode 5455 is preferably higher in the N periods T. Alternatively, in the period Ta, it is preferable to increase a time obtained by subtracting the time during which the potential VH is applied to the electrode 5455 from the time during which the potential VL is applied to the electrode 5455. Further alternatively, in the N periods T, it is preferable to increase a frequency obtained by subtracting the frequency of application of the potential VH to the electrode 5455 from the frequency of application of the potential VL to the electrode 5455. In such a manner, afterimages can be reduced.

(172) As another example, in the period Ta for expressing the gray level that has been expressed by the display element 5453, the time during which the potential VH is applied to the electrode 5455 is preferably longer in the period Ta in any of the following cases: the case where the time during which the potential VL is applied to the electrode 5455 is longer; the case where a time obtained by subtracting the time during which the potential VH is applied to the electrode 5455 from the time during which the potential VL is applied to the electrode 5455 is longer; the case where the frequency of application of the potential VL to the electrode 5455 is higher in the N periods T; or the case where a frequency obtained by subtracting the frequency of application of the potential VH to the electrode 5455 from the frequency of application of the potential VL to the electrode 5455 is higher in the N periods T. Alternatively, the frequency of application of the potential VH to the electrode 5455 is preferably higher in the N periods T. Alternatively, in the period Ta, it is preferable to increase a time obtained by subtracting the time during which the potential VL is applied to the electrode 5455 from the time during which the potential VH is applied to the electrode 5455. Further alternatively, in the N periods T, it is preferable to increase a frequency obtained by subtracting the frequency of application of the potential VL to the electrode 5455 from the frequency of application of the potential VH to the electrode 5455. In such a manner, afterimages can be reduced.

(173) The N periods T have the same length; however, the length of the N periods T is not limited thereto and the lengths of at least two of the N periods T can be different from each other. It is particularly preferable that the length of the N periods T be weighted. For example, in the case where N is 4 and the length of the first period T is denoted by a time h, the length of the second period T is preferably a time $h \times 2$, the length of the third period T is preferably a time $h \times 4$, and the length of the fourth period T is preferably a time $h \times 8$. When the length of the N periods T is weighted in such a manner, the frequency of selection of the pixels **5450** can be reduced and the time during which a voltage is applied to the display element **5453** can be minutely controlled. Thus, power consumption can be reduced.

(174) The potential VH and the potential VL can be selectively applied to the electrode **5454**. In this case, it is preferable that the potential VH and the potential VL be selectively applied also to the electrode **5455**. For example, in the case where the potential VH is applied to the electrode **5454**, zero voltage is applied to the display element **5453** when the potential VH is applied to the electrode **5455**, whereas a negative voltage is applied to the display element **5453** when the potential VL is applied to the electrode **5455**. On the other hand, in the case where the potential VL is applied to the electrode **5454**, a positive voltage is applied to the display element **5453** when the potential VH is applied to the electrode **5455**, whereas zero voltage is applied to the display element **5453** when the potential VL is applied to the electrode **5455**. In such a manner, the signal input to the wiring **5461** can have two values (i.e., the signal can be a digital signal). For that reason, it is possible to simplify a circuit that outputs a signal to the wiring **5461**.

(175) In the period Tb or part of the period Tb, it is possible not to input a signal to the wiring **5461** and the wiring **5462**. That is, the wiring **5461** and the wiring **5462** can be set in a floating state. Moreover, in the period Tb or part of the period Tb, it is possible not to input a signal to the wiring **5463**. That is, the wiring **5463** can be set in a floating state. Furthermore, in the period Tb or part of the period Tb, it is possible not to supply a voltage to the electrode **5454**. That is, the electrode **5454** can be set in a floating state.

Embodiment 7

(176) In this embodiment, examples of electronic devices will be described.

(177) FIGS. **16A** to **16H** and FIGS. **17A** to **17D** each illustrate an electronic device. These electronic devices can include a housing **5000**, a display portion **5001**, a speaker **5003**, an LED lamp **5004**, operation keys **5005** (including a power switch or an operation switch), a connection terminal **5006**, a sensor **5007** (a sensor having a function of measuring force, displacement, position, speed, acceleration, angular velocity, rotational frequency, distance, light, liquid, magnetism, temperature, chemical substance, sound, time, hardness, electric field, current, voltage, electric power, radiation, flow rate, humidity, gradient, oscillation, odor, or infrared ray), a microphone **5008**, and the like.

(178) FIG. **16A** illustrates a mobile computer that can include a switch **5009**, an infrared port **5010**, and the like in addition to the above-described components. FIG. **16B** illustrates a portable image reproducing device (e.g., a DVD reproducing device) provided with a memory medium, and the image reproducing device can include a second display portion **5002**, a memory medium reading portion **5011**, and the like in addition to the above components. FIG. **16C** illustrates a goggle-type display that can include second display portion **5002**, a support portion **5012**, an earphone **5013**, and the like in addition to the above components. FIG. **16D** illustrates a portable game machine that can include the memory medium reading portion **5011** and the like in addition to the above components. FIG. **16E** illustrates a projector that can include a light source **5033**, a projector lens **5034**, and the like in addition to the above components. FIG. **16F** illustrates a portable game machine that can include the second display portion **5002**, the memory medium reading portion **5011**, and the like in addition to the above components. FIG. **16G** illustrates a television set that can include a tuner, an image processing portion, and the like in addition to the above components. FIG. **16H** illustrates a portable television receiver that can include a charger **5017** capable of

transmitting and receiving signals and the like in addition to the above components. FIG. 17A illustrates a display that can include a support base **5018** and the like in addition to the above-described components. FIG. 17B illustrates a camera that can include an external connection port **5019**, a shutter button **5015**, an image receiving portion **5016**, and the like in addition to the above components. FIG. 17C illustrates a computer that can include a pointing device **5020**, the external connection port **5019**, a reader/writer **5021**, and the like in addition to the above components. FIG. 17D illustrates a mobile phone that can include an antenna **5014**, a tuner of one-segment (1 seg digital TV broadcasts) partial reception service for mobile phones and mobile terminals, and the like in addition to the above components.

(179) The electronic devices illustrated in FIGS. 16A to 16H and FIGS. 17A to 17D can have a variety of functions.

(180) The electronic device described in this embodiment includes a display portion for displaying some kind of information.

(181) Next, applications of a semiconductor device will be described.

(182) FIG. 17E illustrates an example in which a semiconductor device is incorporated in a building structure. FIG. 17E illustrates a housing **5022**, a display portion **5023**, a remote controller **5024** which is an operation portion, a speaker **5025**, and the like. The semiconductor device is incorporated in the building as a wall-hanging type and can be provided without requiring a large space.

(183) FIG. 17F illustrates another example in which a semiconductor device is incorporated in a building. A display panel **5026** is integrated with a prefabricated bath **5027**, so that a person who takes a bath can watch the display panel **5026**.

(184) Note that although the wall and the prefabricated bath are given as examples of the building, this embodiment is not limited to these examples and the semiconductor device can be provided in a variety of buildings.

(185) Next, examples in which a semiconductor device is incorporated with a moving object will be described.

(186) FIG. 17G illustrates an example in which a semiconductor device is provided in a car. A display panel **5028** is provided in a body **5029** of the car and can display information related to the operation of the car or information input from inside or outside of the car on demand. Note that a navigation function may be provided.

(187) FIG. 17H illustrates an example in which a semiconductor device is incorporated in a passenger airplane. FIG. 17H shows a usage pattern when a display panel **5031** is provided for a ceiling **5030** above a seat of the airplane. The display panel **5031** is integrated with the ceiling **5030** through a hinge portion **5032**, and a passenger can watch the display panel **5031** by extending and contracting the hinge portion **5032**. The display panel **5031** has a function of displaying information when operated by the passenger.

(188) Note that although the body of the car and the body of the plane are given as examples of the moving body, this embodiment is not limited to these examples. The display device can be provided for a variety of moving bodies such as a two-wheel motor vehicle, a four-wheel vehicle (including a car, bus, and the like), a train (including a monorail, a railway, and the like), and a ship.

(189) In such an electronic device, the formation of a circuit with the use of a transistor that includes an oxide semiconductor and has a low off-state current can prevent unnecessary current from being leaked into the circuit. For that reason, the circuit is likely to operate normally. As a result, accurate display can be performed.

(190) This application is based on Japanese Patent Application serial no. 2010-028285 filed with Japan Patent Office on Feb. 11, 2010, the entire contents of which are hereby incorporated by reference.

Claims

1. A display device comprising a pixel, the pixel comprising: a first transistor including a first oxide semiconductor in a first channel formation region; a second transistor including a second oxide semiconductor in a second channel formation region; a capacitor; and a light-emitting element, wherein one of a source and a drain of the first transistor is electrically connected to a data signal line, wherein the other of the source and the drain of the first transistor is electrically connected to a gate of the second transistor, and to one electrode of the capacitor, wherein one of a source and a drain of the second transistor is electrically connected to a power supply line, wherein the other of the source and the drain of the second transistor is electrically connected to the light-emitting element, and to the other electrode of the capacitor, and wherein each of the first oxide semiconductor and the second oxide semiconductor has an off-state current of 100 aA/ μm or less.
 2. The display device according to claim 1, wherein each of the first oxide semiconductor and the second oxide semiconductor includes indium, gallium, and zinc.
 3. The display device according to claim 1, wherein the light-emitting element is an EL (electroluminescence) element.
 4. A display device comprising a pixel, the pixel comprising: a first transistor including a first oxide semiconductor in a first channel formation region; a second transistor including a second oxide semiconductor in a second channel formation region; a capacitor; and a light-emitting element, wherein one of a source and a drain of the first transistor is electrically connected to a data signal line, wherein the other of the source and the drain of the first transistor is electrically connected to a gate of the second transistor, and to one electrode of the capacitor, wherein a gate of the first transistor is electrically connected to a gate signal line, wherein one of a source and a drain of the second transistor is electrically connected to a power supply line, wherein the other of the source and the drain of the second transistor is electrically connected to the light-emitting element, and to the other electrode of the capacitor, and wherein each of the first oxide semiconductor and the second oxide semiconductor has an off-state current of 100 aA/ μm or less.
 5. The display device according to claim 4, wherein each of the first oxide semiconductor and the second oxide semiconductor includes indium, gallium, and zinc.
 6. The display device according to claim 4, wherein the light-emitting element is an EL (electroluminescence) element.
-