

# US Patent & Trademark Office

## Patent Public Search | Text View

---

United States Patent Application Publication

20250280393

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

YANG; Wei et al.

---

### GRADUAL SENSING FOR USER EQUIPMENT POWER SAVING IN SIDELINK OPERATION

---

#### Abstract

Methods, systems, and devices for wireless communication are described. In some cases, a sidelink user equipment (UE) operating in a power saving mode may identify a resource reservation configuration for communicating within a resource pool allocated for sidelink communications. The UE may operate in a first power state of the power saving mode during a sensing window. The sensing window may correspond to a resource selection window of the resource pool. The UE may transition, after the sensing window, from the first power state to a second power state that may consume more power than the first power state. The UE may identify a subset of resources of the resource pool in the resource selection window that are available for sidelink transmission by the UE based on transitioning between the first power state and the second power state.

---

**Inventors:** YANG; Wei (San Diego, CA), HOSSEINI; Seyedkianoush (San Diego, CA), CHEN; Wanshi (San Diego, CA), KWON; Hwan Joon (San Diego, CA)

**Applicant:** QUALCOMM Incorporated (San Diego, CA)

**Family ID:** 79425344

**Appl. No.:** 19/086090

**Filed:** March 20, 2025

#### Related U.S. Application Data

parent US continuation 18617414 20240326 parent-grant-document US 12279235 child US 19086090

parent US continuation 17148876 20210114 parent-grant-document US 11963136 child US 18617414

---

#### Publication Classification

**Int. Cl.: H04W72/02 (20090101); H04W72/0446 (20230101); H04W72/0453 (20230101); H04W76/28 (20180101); H04W92/18 (20090101)**

**U.S. Cl.:**

**CPC H04W72/02 (20130101); H04W72/0446 (20130101); H04W72/0453 (20130101); H04W76/28 (20180201); H04W92/18 (20130101)**

---

## **Background/Summary**

CROSS REFERENCE [0001] The present application for patent is a continuation of U.S. patent application Ser. No. 18/617,414 by YANG et al., entitled “GRADUAL SENSING FOR USER EQUIPMENT POWER SAVING IN SIDELINK OPERATION,” filed Mar. 26, 2024, which is a continuation of U.S. patent application Ser. No. 17/148,876 by YANG et al., entitled “GRADUAL SENSING FOR USER EQUIPMENT POWER SAVING IN SIDELINK OPERATION,” filed Jan. 14, 2021, now U.S. Pat. No. 11,963,136, issued Apr. 16, 2024, assigned to the assignee hereof, and expressly incorporated by reference herein.

### **FIELD OF TECHNOLOGY**

[0002] The following relates to wireless communication, including gradual sensing for user equipment (UE) power saving in sidelink operation.

### **BACKGROUND**

[0003] Wireless communications systems are widely deployed to provide various types of communication content such as voice, video, packet data, messaging, broadcast, and so on. These systems may be capable of supporting communication with multiple users by sharing the available system resources (e.g., time, frequency, and power). Examples of such multiple-access systems include fourth generation (4G) systems such as Long Term Evolution (LTE) systems, LTE-Advanced (LTE-A) systems, or LTE-A Pro systems, and fifth generation (5G) systems which may be referred to as New Radio (NR) systems. These systems may employ technologies such as code division multiple access (CDMA), time division multiple access (TDMA), frequency division multiple access (FDMA), orthogonal frequency division multiple access (OFDMA), or discrete Fourier transform spread orthogonal frequency division multiplexing (DFT-S-OFDM). A wireless multiple-access communications system may include one or more base stations or one or more network access nodes, each simultaneously supporting communication for multiple communication devices, which may be otherwise known as user equipment (UE).

[0004] A sidelink UE may communicate with one or more other UEs via resources selected from a sidelink resource pool. A UE may operate in a power saving mode and may not monitor resources in the sidelink resource pool while operating in a low power state of the power saving mode. The UE may be unable to transmit sidelink data in corresponding resources in the sidelink resource pool that the UE did not monitor, which may increase latency associated with sidelink communications by the UE during power saving operations.

### **SUMMARY**

[0005] The described techniques relate to improved methods, systems, devices, and apparatuses that support gradual sensing for user equipment (UE) power saving in sidelink operation. Generally, the described techniques provide for a sidelink UE to transmit sidelink messages in resources that were not monitored by the UE due to the UE operating in a power saving mode (e.g., a low power state during a power saving mode). The UE may identify a resource reservation configuration for communicating within a resource pool (e.g., a set of time and frequency resources) allocated for sidelink communication. In some examples, the UE may operate in a low

power state during a sensing window, where the UE may refrain from monitoring the resource pool (e.g., performing channel sensing) during the sensing window due to operating in the low power state. The sensing window may be a set of time and frequency resources of the resource pool that the UE monitors for determining availability of one or more resources in an upcoming resource selection window. In some examples, the UE may receive a resource selection trigger that may indicate the UE has sidelink data to communicate, causing the UE to transition from the low power state to a high power state. The resource reservation configuration may permit the UE to select a first resource in the resource selection window for sidelink transmission even though the UE did not monitor a corresponding resource in the sensing window to determine that the first resource is available for sidelink transmission. The UE may transmit a sidelink message in the first resource, which may permit the UE to operate in the low power state during the sensing window without incurring significant latency in selecting a resource in the resource selection window for sidelink transmission.

[0006] A method for wireless communication at a UE is described. The method may include identifying a resource reservation configuration for communicating within a resource pool allocated for sidelink communications, transitioning from a first power state to a second power state that consumes more power than the first power state after a first sensing window occurs, the first sensing window corresponding to a first resource selection window of the resource pool of the resource reservation configuration, and determining that a first subset of resources of the resource pool in the first resource selection window are available for sidelink data transmission based on the transitioning from the first power state to the second power state.

[0007] An apparatus for wireless communication at a UE is described. The apparatus may include a processor, memory in electronic communication with the processor, and instructions stored in the memory. The instructions may be executable by the processor to cause the apparatus to identify a resource reservation configuration for communicating within a resource pool allocated for sidelink communications, transition from a first power state to a second power state that consumes more power than the first power state after a first sensing window occurs, the first sensing window corresponding to a first resource selection window of the resource pool of the resource reservation configuration, and determine that a first subset of resources of the resource pool in the first resource selection window are available for sidelink data transmission based on the transitioning from the first power state to the second power state.

[0008] Another apparatus for wireless communication at a UE is described. The apparatus may include means for identifying a resource reservation configuration for communicating within a resource pool allocated for sidelink communications, means for transitioning from a first power state to a second power state that consumes more power than the first power state after a first sensing window occurs, the first sensing window corresponding to a first resource selection window of the resource pool of the resource reservation configuration, and means for determining that a first subset of resources of the resource pool in the first resource selection window are available for sidelink data transmission based on the transitioning from the first power state to the second power state.

[0009] A non-transitory computer-readable medium storing code for wireless communication at a UE is described. The code may include instructions executable by a processor to identify a resource reservation configuration for communicating within a resource pool allocated for sidelink communications, transition from a first power state to a second power state that consumes more power than the first power state after a first sensing window occurs, the first sensing window corresponding to a first resource selection window of the resource pool of the resource reservation configuration, and determine that a first subset of resources of the resource pool in the first resource selection window are available for sidelink data transmission based on the transitioning from the first power state to the second power state.

[0010] Some examples of the method, apparatuses, and non-transitory computer-readable medium

described herein may further include operations, features, means, or instructions for selecting a resource from the first subset of resources and transmitting a sidelink data message within the resource.

[0011] Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for determining that the first subset of resources of the first resource selection window may be available for sidelink data transmission based on the UE operating in the first power state during a sensing resource in the first sensing window that corresponds to the first subset of resources.

[0012] Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for transmitting a sidelink data message within a second subset of resources in a second sensing window corresponding to a second resource selection window of the resource pool and determining that a third subset of resources in the second resource selection window corresponding to the second subset of resources may be available for sidelink data transmission based on the transmitting.

[0013] Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for transmitting a sidelink data message within a second subset of resources in a second sensing window corresponding to a second resource selection window of the resource pool and determining that a resource of the second resource selection window may be not available for sidelink transmission based on transmitting the sidelink data message within the second subset of resources in the second sensing window.

[0014] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, determining that the first subset of resources of the first resource selection window may be available may include operations, features, means, or instructions for determining that the first subset of resources of the first resource selection window may be available for data transmission based on the first subset of resources being assigned a defined signal metric level.

[0015] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, determining that the first subset of resources of the first resource selection window may be available may include operations, features, means, or instructions for comparing a signal metric value assigned for a priority level of a sidelink data message to be transmitted in the first resource selection window with the defined signal metric level and determining that the first subset of resources of the first resource selection window may be available for sidelink data transmission based on the comparing.

[0016] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the first subset of resources may be assigned the defined signal metric level based on the first subset of resources corresponding to a transmission time interval (TTI) within the first sensing window within which the UE operated in the first power state.

[0017] Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for identifying a second resource in the first resource selection window that may be available for sidelink data transmission based on the second resource having a measured signal metric level that may be lower than the defined signal metric level.

[0018] Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for transmitting a sidelink data message in the second resource in the first resource selection window based on identifying that the measured signal metric level may be lower than the defined signal metric level.

[0019] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the defined signal metric level may be a reference signal receive power (RSRP) level.

[0020] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the resource reservation configuration may include operations, features, means, or instructions for identifying the resource reservation configuration that indicates a first resource reservation periodicity that may be shorter than a second resource reservation periodicity and determining that the first subset of resources of the first resource selection window may be available based on monitoring a slot in the first sensing window that corresponds to the first resource reservation periodicity.

[0021] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, determining that the first subset of resources may be available may include operations, features, means, or instructions for determining that the first subset of resources of the first resource selection window may be available based on an instance of the second resource reservation periodicity corresponding to the first sensing window occurring when the UE may be operating in the first power state.

[0022] Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for transmitting, within the first subset of resources, a first sidelink control message that includes sidelink control information that includes a grant scheduling a first sidelink data message within the resource pool and transmitting the first sidelink data message based on the grant.

[0023] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the transitioning from the first power state to the second power state may include operations, features, means, or instructions for receiving a resource selection trigger and transitioning from the first power state to the second power state based on receiving the resource selection trigger.

[0024] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the first power state corresponds to a first bandwidth part (BWP) and the second power state corresponds to a second BWP that may be wider than the first BWP.

[0025] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the first power state corresponds to a sleep duration of a discontinuous reception (DRX) cycle and the second power state corresponds to an on duration of the DRX.

---

## Description

### BRIEF DESCRIPTION OF THE DRAWINGS

[0026] FIG. 1 illustrates an example of a wireless communications system that supports gradual sensing for user equipment (UE) power saving in sidelink operation in accordance with aspects of the present disclosure.

[0027] FIG. 2 illustrates an example of a wireless communications system in accordance with aspects of the present disclosure.

[0028] FIG. 3 illustrates an example of a resource selection scheme in accordance with aspects of the present disclosure.

[0029] FIG. 4 illustrates an example of a discontinuous reception (DRX) timeline in accordance with aspects of the present disclosure.

[0030] FIG. 5 illustrates an example of a bandwidth adaptation timeline in accordance with aspects of the present disclosure.

[0031] FIG. 6 illustrates an example of a resource pool activation timeline in accordance with aspects of the present disclosure.

[0032] FIG. 7 illustrates an example of a bandwidth adaptation timeline in accordance with aspects of the present disclosure.

[0033] FIG. 8 illustrates an example of a process flow in accordance with aspects of the present

disclosure.

[0034] FIGS. **9** and **10** show block diagrams of devices that support gradual sensing for UE power saving in sidelink operation in accordance with aspects of the present disclosure.

[0035] FIG. **11** shows a block diagram of a communications manager in accordance with aspects of the present disclosure.

[0036] FIG. **12** shows a diagram of a system including a device in accordance with aspects of the present disclosure.

[0037] FIGS. **13** through **16** show flowcharts illustrating methods in accordance with aspects of the present disclosure.

#### DETAILED DESCRIPTION

[0038] A sidelink communications system may support an autonomous resource allocation mode (e.g., sidelink mode 2 resource allocation), in which sidelink user equipments (UEs) may autonomously select or reserve sidelink resources from a resource pool (e.g., without base station scheduling of the resources). In such cases, a UE may perform channel sensing in a sensing window to determine available sidelink resources for selection from the resource pool. The UE may select sidelink resources autonomously (e.g., perform sidelink resource selection) and may transmit a sidelink message in the selected resources in a resource selection window. Additionally or alternatively, the UE may identify sidelink resources to reserve (e.g., perform sidelink resource reservation) and may signal other UEs indicating the resource reservation. In some cases, a UE may operate in a power saving mode, such as a discontinuous reception (DRX) mode or a bandwidth adaptation mode, during which the UE may transition between low power states (e.g., sleep modes or narrow bandwidth modes) and high power states (e.g., active modes or wide bandwidth modes). In some cases, the low power state and the high power state may also be referred to herein as a first power state and a second power state, respectively (e.g., see below). During low power states, the UE may not perform channel sensing. In some cases, sidelink UEs may be precluded from performing resource selection until after the UE has performed channel sensing, which may result in the UE identifying relatively few, or no available sidelink resources to use for communications, or may result in transmission latency until after the UE performs channel sensing.

[0039] To permit sidelink UEs to implement a power saving mode without excessive latency, a UE may transmit a sidelink message in a resource that was not monitored by the UE during a preceding sensing window due to the UE operating in a low power mode (e.g., a sleep mode or a narrow bandwidth mode) for some or all of the preceding sensing window. If the UE is in a low power mode during a sensing window and switches to a second power mode (e.g., an active state) for a resource selection window, the UE may transmit a sidelink control message during the resource selection window, even though the UE did not perform sensing during the preceding sensing window corresponding to the resource selection window. As such, the UE may fail to perform sensing in a transmission time interval (TTI) of the sensing window while operating in a low power mode, and the UE may be permitted to transmit in corresponding resources in a resource selection window due to the low power mode. Additionally or alternatively, the UE may fail to perform sensing in a TTI of the sensing window due to one or more transmissions by the UE in the TTI (e.g., during half-duplex communications), interference in the TTI, or a combination thereof. In some examples, a half-duplex UE may be permitted to transmit in a resource of the resource selection window if the UE failed to perform sensing due to the UE transmitting, instead of sensing, during the sensing window. In other examples, the UE may not transmit sidelink messages in one or more resources that the UE did not sense for any reason other than operating in a low power mode during the corresponding sensing window.

[0040] Accordingly, a sidelink UE may transition between a low power state and a high power state to reduce power consumption at the UE, and the sidelink UE may identify available resources for sidelink transmission during the high power state without incurring significant latency.

[0041] Aspects of the disclosure are initially described in the context of wireless communications systems. Aspects of the disclosure are described with reference to resource selection schemes, DRX timelines, bandwidth adaptation timelines, resource pool activation timelines, and process flows. Aspects of the disclosure are further illustrated by and described with reference to apparatus diagrams, system diagrams, and flowcharts that relate to gradual sensing for UE power saving in sidelink operation.

[0042] FIG. 1 illustrates an example of a wireless communications system **100** in accordance with aspects of the present disclosure. The wireless communications system **100** may include one or more base stations **105**, one or more UEs **115**, and a core network **130**. In some examples, the wireless communications system **100** may be a Long Term Evolution (LTE) network, an LTE-Advanced (LTE-A) network, an LTE-A Pro network, or a New Radio (NR) network. In some examples, the wireless communications system **100** may support enhanced broadband communications, ultra-reliable (e.g., mission critical) communications, low latency communications, communications with low-cost and low-complexity devices, or any combination thereof.

[0043] The base stations **105** may be dispersed throughout a geographic area to form the wireless communications system **100** and may be devices in different forms or having different capabilities. The base stations **105** and the UEs **115** may wirelessly communicate via one or more communication links **125**. Each base station **105** may provide a coverage area **110** over which the UEs **115** and the base station **105** may establish one or more communication links **125**. The coverage area **110** may be an example of a geographic area over which a base station **105** and a UE **115** may support the communication of signals according to one or more radio access technologies.

[0044] The UEs **115** may be dispersed throughout a coverage area **110** of the wireless communications system **100**, and each UE **115** may be stationary, or mobile, or both at different times. The UEs **115** may be devices in different forms or having different capabilities. Some example UEs **115** are illustrated in FIG. 1. The UEs **115** described herein may be able to communicate with various types of devices, such as other UEs **115**, the base stations **105**, or network equipment (e.g., core network nodes, relay devices, integrated access and backhaul (IAB) nodes, or other network equipment), as shown in FIG. 1.

[0045] The base stations **105** may communicate with the core network **130**, or with one another, or both. For example, the base stations **105** may interface with the core network **130** through one or more backhaul links **120** (e.g., via an S1, N2, N3, or other interface). The base stations **105** may communicate with one another over the backhaul links **120** (e.g., via an X2, Xn, or other interface) either directly (e.g., directly between base stations **105**), or indirectly (e.g., via core network **130**), or both. In some examples, the backhaul links **120** may be or include one or more wireless links.

[0046] One or more of the base stations **105** described herein may include or may be referred to by a person having ordinary skill in the art as a base transceiver station, a radio base station, an access point, a radio transceiver, a NodeB, an eNodeB (eNB), a next-generation NodeB or a giga-NodeB (either of which may be referred to as a gNB), a Home NodeB, a Home eNodeB, or other suitable terminology.

[0047] A UE **115** may include or may be referred to as a mobile device, a wireless device, a remote device, a handheld device, or a subscriber device, or some other suitable terminology, where the “device” may also be referred to as a unit, a station, a terminal, or a client, among other examples. A UE **115** may also include or may be referred to as a personal electronic device such as a cellular phone, a personal digital assistant (PDA), a tablet computer, a laptop computer, or a personal computer. In some examples, a UE **115** may include or be referred to as a wireless local loop (WLL) station, an Internet of Things (IoT) device, an Internet of Everything (IoE) device, or a machine type communications (MTC) device, among other examples, which may be implemented in various objects such as appliances, or vehicles, meters, among other examples.

[0048] The UEs **115** described herein may be able to communicate with various types of devices,

such as other UEs **115** that may sometimes act as relays as well as the base stations **105** and the network equipment including macro eNBs or gNBs, small cell eNBs or gNBs, or relay base stations, among other examples, as shown in FIG. **1**.

[0049] The UEs **115** and the base stations **105** may wirelessly communicate with one another via one or more communication links **125** over one or more carriers. The term “carrier” may refer to a set of radio frequency spectrum resources having a defined physical layer structure for supporting the communication links **125**. For example, a carrier used for a communication link **125** may include a portion of a radio frequency spectrum band (e.g., a bandwidth part (BWP)) that is operated according to one or more physical layer channels for a given radio access technology (e.g., LTE, LTE-A, LTE-A Pro, NR). Each physical layer channel may carry acquisition signaling (e.g., synchronization signals, system information), control signaling that coordinates operation for the carrier, user data, or other signaling. The wireless communications system **100** may support communication with a UE **115** using carrier aggregation or multi-carrier operation. A UE **115** may be configured with multiple downlink component carriers and one or more uplink component carriers according to a carrier aggregation configuration. Carrier aggregation may be used with both frequency division duplexing (FDD) and time division duplexing (TDD) component carriers. [0050] In some examples (e.g., in a carrier aggregation configuration), a carrier may also have acquisition signaling or control signaling that coordinates operations for other carriers. A carrier may be associated with a frequency channel (e.g., an evolved universal mobile telecommunication system terrestrial radio access (E-UTRA) absolute radio frequency channel number (EARFCN)) and may be positioned according to a channel raster for discovery by the UEs **115**. A carrier may be operated in a standalone mode where initial acquisition and connection may be conducted by the UEs **115** via the carrier, or the carrier may be operated in a non-standalone mode where a connection is anchored using a different carrier (e.g., of the same or a different radio access technology).

[0051] The communication links **125** shown in the wireless communications system **100** may include uplink transmissions from a UE **115** to a base station **105**, or downlink transmissions from a base station **105** to a UE **115**. Carriers may carry downlink or uplink communications (e.g., in an FDD mode) or may be configured to carry downlink and uplink communications (e.g., in a TDD mode).

[0052] A carrier may be associated with a particular bandwidth of the radio frequency spectrum, and in some examples the carrier bandwidth may be referred to as a “system bandwidth” of the carrier or the wireless communications system **100**. For example, the carrier bandwidth may be one of a number of determined bandwidths for carriers of a particular radio access technology (e.g., 1.4, 3, 5, 10, 15, 20, 40, or 80 megahertz (MHz)). Devices of the wireless communications system **100** (e.g., the base stations **105**, the UEs **115**, or both) may have hardware configurations that support communications over a particular carrier bandwidth or may be configurable to support communications over one of a set of carrier bandwidths. In some examples, the wireless communications system **100** may include base stations **105** or UEs **115** that support simultaneous communications via carriers associated with multiple carrier bandwidths. In some examples, each served UE **115** may be configured for operating over portions (e.g., a sub-band, a BWP) or all of a carrier bandwidth.

[0053] Signal waveforms transmitted over a carrier may be made up of multiple subcarriers (e.g., using multi-carrier modulation (MCM) techniques such as orthogonal frequency division multiplexing (OFDM) or discrete Fourier transform spread OFDM (DFT-S-OFDM)). In a system employing MCM techniques, a resource element may consist of one symbol period (e.g., a duration of one modulation symbol) and one subcarrier, where the symbol period and subcarrier spacing are inversely related. The number of bits carried by each resource element may depend on the modulation scheme (e.g., the order of the modulation scheme, the coding rate of the modulation scheme, or both). Thus, the more resource elements that a UE **115** receives and the higher the order

of the modulation scheme, the higher the data rate may be for the UE 115. A wireless communications resource may refer to a combination of a radio frequency spectrum resource, a time resource, and a spatial resource (e.g., spatial layers or beams), and the use of multiple spatial layers may further increase the data rate or data integrity for communications with a UE 115.

[0054] One or more numerologies for a carrier may be supported, where a numerology may include a subcarrier spacing ( $\Delta f$ ) and a cyclic prefix. A carrier may be divided into one or more BWPs having the same or different numerologies. In some examples, a UE 115 may be configured with multiple BWPs. In some examples, a single BWP for a carrier may be active at a given time and communications for the UE 115 may be restricted to one or more active BWPs.

[0055] The time intervals for the base stations 105 or the UEs 115 may be expressed in multiples of a basic time unit which may, for example, refer to a sampling period of  $T_s = 1/(\Delta f_{\text{sub.max}} - N_{\text{sub.f}})$  seconds, where  $\Delta f_{\text{sub.max}}$  may represent the maximum supported subcarrier spacing, and  $N_{\text{sub.f}}$  may represent the maximum supported discrete Fourier transform (DFT) size. Time intervals of a communications resource may be organized according to radio frames each having a specified duration (e.g., 10 milliseconds (ms)). Each radio frame may be identified by a system frame number (SFN) (e.g., ranging from 0 to 1023).

[0056] Each frame may include multiple consecutively numbered subframes or slots, and each subframe or slot may have the same duration. In some examples, a frame may be divided (e.g., in the time domain) into subframes, and each subframe may be further divided into a number of slots. Alternatively, each frame may include a variable number of slots, and the number of slots may depend on subcarrier spacing. Each slot may include a number of symbol periods (e.g., depending on the length of the cyclic prefix prepended to each symbol period). In some wireless communications systems 100, a slot may further be divided into multiple mini-slots containing one or more symbols. Excluding the cyclic prefix, each symbol period may contain one or more (e.g.,  $N_{\text{sub.f}}$ ) sampling periods. The duration of a symbol period may depend on the subcarrier spacing or frequency band of operation.

[0057] A subframe, a slot, a mini-slot, or a symbol may be the smallest scheduling unit (e.g., in the time domain) of the wireless communications system 100 and may be referred to as a transmission time interval (TTI). In some examples, the TTI duration (e.g., the number of symbol periods in a TTI) may be variable. Additionally or alternatively, the smallest scheduling unit of the wireless communications system 100 may be dynamically selected (e.g., in bursts of shortened TTIs (STTIs)).

[0058] Physical channels may be multiplexed on a carrier according to various techniques. A physical control channel and a physical data channel may be multiplexed on a downlink carrier, for example, using one or more of time division multiplexing (TDM) techniques, frequency division multiplexing (FDM) techniques, or hybrid TDM-FDM techniques. A control region (e.g., a control resource set (CORESET)) for a physical control channel may be defined by a number of symbol periods and may extend across the system bandwidth or a subset of the system bandwidth of the carrier. One or more control regions (e.g., CORESETs) may be configured for a set of the UEs 115. For example, one or more of the UEs 115 may monitor or search control regions for control information according to one or more search space sets, and each search space set may include one or multiple control channel candidates in one or more aggregation levels arranged in a cascaded manner. An aggregation level for a control channel candidate may refer to a number of control channel resources (e.g., control channel elements (CCEs)) associated with encoded information for a control information format having a given payload size. Search space sets may include common search space sets configured for sending control information to multiple UEs 115 and UE-specific search space sets for sending control information to a specific UE 115.

[0059] Each base station 105 may provide communication coverage via one or more cells, for example a macro cell, a small cell, a hot spot, or other types of cells, or any combination thereof. The term “cell” may refer to a logical communication entity used for communication with a base

station **105** (e.g., over a carrier) and may be associated with an identifier for distinguishing neighboring cells (e.g., a physical cell identifier (PCID), a virtual cell identifier (VCID), or others). In some examples, a cell may also refer to a geographic coverage area **110** or a portion of a geographic coverage area **110** (e.g., a sector) over which the logical communication entity operates. Such cells may range from smaller areas (e.g., a structure, a subset of structure) to larger areas depending on various factors such as the capabilities of the base station **105**. For example, a cell may be or include a building, a subset of a building, or exterior spaces between or overlapping with geographic coverage areas **110**, among other examples.

[0060] A macro cell generally covers a relatively large geographic area (e.g., several kilometers in radius) and may allow unrestricted access by the UEs **115** with service subscriptions with the network provider supporting the macro cell. A small cell may be associated with a lower-powered base station **105**, as compared with a macro cell, and a small cell may operate in the same or different (e.g., licensed, unlicensed) frequency bands as macro cells. Small cells may provide unrestricted access to the UEs **115** with service subscriptions with the network provider or may provide restricted access to the UEs **115** having an association with the small cell (e.g., the UEs **115** in a closed subscriber group (CSG), the UEs **115** associated with users in a home or office). A base station **105** may support one or multiple cells and may also support communications over the one or more cells using one or multiple component carriers.

[0061] In some examples, a carrier may support multiple cells, and different cells may be configured according to different protocol types (e.g., MTC, narrowband IoT (NB-IoT), enhanced mobile broadband (cMBB)) that may provide access for different types of devices.

[0062] In some examples, a base station **105** may be movable and therefore provide communication coverage for a moving geographic coverage area **110**. In some examples, different geographic coverage areas **110** associated with different technologies may overlap, but the different geographic coverage areas **110** may be supported by the same base station **105**. In other examples, the overlapping geographic coverage areas **110** associated with different technologies may be supported by different base stations **105**. The wireless communications system **100** may include, for example, a heterogeneous network in which different types of the base stations **105** provide coverage for various geographic coverage areas **110** using the same or different radio access technologies.

[0063] The wireless communications system **100** may support synchronous or asynchronous operation. For synchronous operation, the base stations **105** may have similar frame timings, and transmissions from different base stations **105** may be approximately aligned in time. For asynchronous operation, the base stations **105** may have different frame timings, and transmissions from different base stations **105** may, in some examples, not be aligned in time. The techniques described herein may be used for either synchronous or asynchronous operations.

[0064] Some UEs **115**, such as MTC or IoT devices, may be low cost or low complexity devices and may provide for automated communication between machines (e.g., via Machine-to-Machine (M2M) communication). M2M communication or MTC may refer to data communication technologies that allow devices to communicate with one another or a base station **105** without human intervention. In some examples, M2M communication or MTC may include communications from devices that integrate sensors or meters to measure or capture information and relay such information to a central server or application program that makes use of the information or presents the information to humans interacting with the application program. Some UEs **115** may be designed to collect information or enable automated behavior of machines or other devices. Examples of applications for MTC devices include smart metering, inventory monitoring, water level monitoring, equipment monitoring, healthcare monitoring, wildlife monitoring, weather and geological event monitoring, fleet management and tracking, remote security sensing, physical access control, and transaction-based business charging.

[0065] Some UEs **115** may be configured to employ operating modes that reduce power

consumption, such as half-duplex communications (e.g., a mode that supports one-way communication via transmission or reception, but not transmission and reception simultaneously). In some examples, half-duplex communications may be performed at a reduced peak rate. Other power conservation techniques for the UEs **115** include entering a power saving deep sleep mode when not engaging in active communications, operating over a limited bandwidth (e.g., according to narrowband communications), or a combination of these techniques. For example, some UEs **115** may be configured for operation using a narrowband protocol type that is associated with a defined portion or range (e.g., set of subcarriers or resource blocks (RBs)) within a carrier, within a guard-band of a carrier, or outside of a carrier.

[0066] The wireless communications system **100** may be configured to support ultra-reliable communications or low-latency communications, or various combinations thereof. For example, the wireless communications system **100** may be configured to support ultra-reliable low-latency communications (URLLC) or mission critical communications. The UEs **115** may be designed to support ultra-reliable, low-latency, or critical functions (e.g., mission critical functions). Ultra-reliable communications may include private communication or group communication and may be supported by one or more mission critical services such as mission critical push-to-talk (MCPTT), mission critical video (MCVideo), or mission critical data (MCData). Support for mission critical functions may include prioritization of services, and mission critical services may be used for public safety or general commercial applications. The terms ultra-reliable, low-latency, mission critical, and ultra-reliable low-latency may be used interchangeably herein.

[0067] In some examples, a UE **115** may also be able to communicate directly with other UEs **115** over a device-to-device (D2D) communication link **135** (e.g., using a peer-to-peer (P2P) or D2D protocol). One or more UEs **115** utilizing D2D communications may be within the geographic coverage area **110** of a base station **105**. Other UEs **115** in such a group may be outside the geographic coverage area **110** of a base station **105** or be otherwise unable to receive transmissions from a base station **105**. In some examples, groups of the UEs **115** communicating via D2D communications may utilize a one-to-many (1:M) system in which each UE **115** transmits to every other UE **115** in the group. In some examples, a base station **105** facilitates the scheduling of resources for D2D communications. In other cases, D2D communications are carried out between the UEs **115** without the involvement of a base station **105**.

[0068] In some systems, the D2D communication link **135** may be an example of a communication channel, such as a sidelink communication channel, between vehicles (e.g., UEs **115**). In some examples, vehicles may communicate using vehicle-to-everything (V2X) communications, vehicle-to-vehicle (V2V) communications, or some combination of these. A vehicle may signal information related to traffic conditions, signal scheduling, weather, safety, emergencies, or any other information relevant to a V2X system. In some examples, vehicles in a V2X system may communicate with roadside infrastructure, such as roadside units, or with the network via one or more network nodes (e.g., base stations **105**) using vehicle-to-network (V2N) communications, or with both.

[0069] The core network **130** may provide user authentication, access authorization, tracking, Internet Protocol (IP) connectivity, and other access, routing, or mobility functions. The core network **130** may be an evolved packet core (EPC) or 5G core (5GC), which may include at least one control plane entity that manages access and mobility (e.g., a mobility management entity (MME), an access and mobility management function (AMF)) and at least one user plane entity that routes packets or interconnects to external networks (e.g., a serving gateway (S-GW), a Packet Data Network (PDN) gateway (P-GW), or a user plane function (UPF)). The control plane entity may manage non-access stratum (NAS) functions such as mobility, authentication, and bearer management for the UEs **115** served by the base stations **105** associated with the core network **130**. User IP packets may be transferred through the user plane entity, which may provide IP address allocation as well as other functions. The user plane entity may be connected to IP services **150** for

one or more network operators. The IP services **150** may include access to the Internet, Intranet(s), an IP Multimedia Subsystem (IMS), or a Packet-Switched Streaming Service.

[0070] Some of the network devices, such as a base station **105**, may include subcomponents such as an access network entity **140**, which may be an example of an access node controller (ANC). Each access network entity **140** may communicate with the UEs **115** through one or more other access network transmission entities **145**, which may be referred to as radio heads, smart radio heads, or transmission/reception points (TRPs). Each access network transmission entity **145** may include one or more antenna panels. In some configurations, various functions of each access network entity **140** or base station **105** may be distributed across various network devices (e.g., radio heads and ANCs) or consolidated into a single network device (e.g., a base station **105**).

[0071] The wireless communications system **100** may operate using one or more frequency bands, typically in the range of 300 megahertz (MHz) to 300 gigahertz (GHz). Generally, the region from 300 MHz to 3 GHz is known as the ultra-high frequency (UHF) region or decimeter band because the wavelengths range from approximately one decimeter to one meter in length. The UHF waves may be blocked or redirected by buildings and environmental features, but the waves may penetrate structures sufficiently for a macro cell to provide service to the UEs **115** located indoors. The transmission of UHF waves may be associated with smaller antennas and shorter ranges (e.g., less than 100 kilometers) compared to transmission using the smaller frequencies and longer waves of the high frequency (HF) or very high frequency (VHF) portion of the spectrum below 300 MHz.

[0072] The wireless communications system **100** may also operate in a super high frequency (SHF) region using frequency bands from 3 GHz to 30 GHz, also known as the centimeter band, or in an extremely high frequency (EHF) region of the spectrum (e.g., from 30 GHz to 300 GHz), also known as the millimeter band. In some examples, the wireless communications system **100** may support millimeter wave (mmW) communications between the UEs **115** and the base stations **105**, and EHF antennas of the respective devices may be smaller and more closely spaced than UHF antennas. In some examples, this may facilitate use of antenna arrays within a device. The propagation of EHF transmissions, however, may be subject to even greater atmospheric attenuation and shorter range than SHF or UHF transmissions. The techniques disclosed herein may be employed across transmissions that use one or more different frequency regions, and designated use of bands across these frequency regions may differ by country or regulating body.

[0073] The wireless communications system **100** may utilize both licensed and unlicensed radio frequency spectrum bands. For example, the wireless communications system **100** may employ License Assisted Access (LAA), LTE-Unlicensed (LTE-U) radio access technology, or NR technology in an unlicensed band such as the 5 GHz industrial, scientific, and medical (ISM) band. When operating in unlicensed radio frequency spectrum bands, devices such as the base stations **105** and the UEs **115** may employ carrier sensing for collision detection and avoidance. In some examples, operations in unlicensed bands may be based on a carrier aggregation configuration in conjunction with component carriers operating in a licensed band (e.g., LAA). Operations in unlicensed spectrum may include downlink transmissions, uplink transmissions, P2P transmissions, or D2D transmissions, among other examples.

[0074] A base station **105** or a UE **115** may be equipped with multiple antennas, which may be used to employ techniques such as transmit diversity, receive diversity, multiple-input multiple-output (MIMO) communications, or beamforming. The antennas of a base station **105** or a UE **115** may be located within one or more antenna arrays or antenna panels, which may support MIMO operations or transmit or receive beamforming. For example, one or more base station antennas or antenna arrays may be co-located at an antenna assembly, such as an antenna tower. In some examples, antennas or antenna arrays associated with a base station **105** may be located in diverse geographic locations. A base station **105** may have an antenna array with a number of rows and columns of antenna ports that the base station **105** may use to support beamforming of communications with a UE **115**. Likewise, a UE **115** may have one or more antenna arrays that may support various MIMO

or beamforming operations. Additionally or alternatively, an antenna panel may support radio frequency beamforming for a signal transmitted via an antenna port.

[0075] The base stations **105** or the UEs **115** may use MIMO communications to exploit multipath signal propagation and increase the spectral efficiency by transmitting or receiving multiple signals via different spatial layers. Such techniques may be referred to as spatial multiplexing. The multiple signals may, for example, be transmitted by the transmitting device via different antennas or different combinations of antennas. Likewise, the multiple signals may be received by the receiving device via different antennas or different combinations of antennas. Each of the multiple signals may be referred to as a separate spatial stream and may carry bits associated with the same data stream (e.g., the same codeword) or different data streams (e.g., different codewords). Different spatial layers may be associated with different antenna ports used for channel measurement and reporting. MIMO techniques include single-user MIMO (SU-MIMO), where multiple spatial layers are transmitted to the same receiving device, and multiple-user MIMO (MU-MIMO), where multiple spatial layers are transmitted to multiple devices.

[0076] Beamforming, which may also be referred to as spatial filtering, directional transmission, or directional reception, is a signal processing technique that may be used at a transmitting device or a receiving device (e.g., a base station **105**, a UE **115**) to shape or steer an antenna beam (e.g., a transmit beam, a receive beam) along a spatial path between the transmitting device and the receiving device. Beamforming may be achieved by combining the signals communicated via antenna elements of an antenna array such that some signals propagating at particular orientations with respect to an antenna array experience constructive interference while others experience destructive interference. The adjustment of signals communicated via the antenna elements may include a transmitting device or a receiving device applying amplitude offsets, phase offsets, or both to signals carried via the antenna elements associated with the device. The adjustments associated with each of the antenna elements may be defined by a beamforming weight set associated with a particular orientation (e.g., with respect to the antenna array of the transmitting device or receiving device, or with respect to some other orientation).

[0077] A base station **105** or a UE **115** may use beam sweeping techniques as part of beam forming operations. For example, a base station **105** may use multiple antennas or antenna arrays (e.g., antenna panels) to conduct beamforming operations for directional communications with a UE **115**. Some signals (e.g., synchronization signals, reference signals, beam selection signals, or other control signals) may be transmitted by a base station **105** multiple times in different directions. For example, the base station **105** may transmit a signal according to different beamforming weight sets associated with different directions of transmission. Transmissions in different beam directions may be used to identify (e.g., by a transmitting device, such as a base station **105**, or by a receiving device, such as a UE **115**) a beam direction for later transmission or reception by the base station **105**.

[0078] Some signals, such as data signals associated with a particular receiving device, may be transmitted by a base station **105** in a single beam direction (e.g., a direction associated with the receiving device, such as a UE **115**). In some examples, the beam direction associated with transmissions along a single beam direction may be determined based on a signal that was transmitted in one or more beam directions. For example, a UE **115** may receive one or more of the signals transmitted by the base station **105** in different directions and may report to the base station **105** an indication of the signal that the UE **115** received with a highest signal quality or an otherwise acceptable signal quality.

[0079] In some examples, transmissions by a device (e.g., by a base station **105** or a UE **115**) may be performed using multiple beam directions, and the device may use a combination of digital precoding or radio frequency beamforming to generate a combined beam for transmission (e.g., from a base station **105** to a UE **115**). The UE **115** may report feedback that indicates precoding weights for one or more beam directions, and the feedback may correspond to a configured number

of beams across a system bandwidth or one or more sub-bands. The base station **105** may transmit a reference signal (e.g., a cell-specific reference signal (CRS), a channel state information reference signal (CSI-RS)), which may be precoded or unprecoded. The UE **115** may provide feedback for beam selection, which may be a precoding matrix indicator (PMI) or codebook-based feedback (e.g., a multi-panel type codebook, a linear combination type codebook, a port selection type codebook). Although these techniques are described with reference to signals transmitted in one or more directions by a base station **105**, a UE **115** may employ similar techniques for transmitting signals multiple times in different directions (e.g., for identifying a beam direction for subsequent transmission or reception by the UE **115**) or for transmitting a signal in a single direction (e.g., for transmitting data to a receiving device).

[0080] A receiving device (e.g., a UE **115**) may try multiple receive configurations (e.g., directional listening) when receiving various signals from the base station **105**, such as synchronization signals, reference signals, beam selection signals, or other control signals. For example, a receiving device may try multiple receive directions by receiving via different antenna subarrays, by processing received signals according to different antenna subarrays, by receiving according to different receive beamforming weight sets (e.g., different directional listening weight sets) applied to signals received at multiple antenna elements of an antenna array, or by processing received signals according to different receive beamforming weight sets applied to signals received at multiple antenna elements of an antenna array, any of which may be referred to as “listening” according to different receive configurations or receive directions. In some examples, a receiving device may use a single receive configuration to receive along a single beam direction (e.g., when receiving a data signal). The single receive configuration may be aligned in a beam direction determined based on listening according to different receive configuration directions (e.g., a beam direction determined to have a highest signal strength, highest signal-to-noise ratio (SNR), or otherwise acceptable signal quality based on listening according to multiple beam directions).

[0081] The wireless communications system **100** may be a packet-based network that operates according to a layered protocol stack. In the user plane, communications at the bearer or Packet Data Convergence Protocol (PDCP) layer may be IP-based. A Radio Link Control (RLC) layer may perform packet segmentation and reassembly to communicate over logical channels. A Medium Access Control (MAC) layer may perform priority handling and multiplexing of logical channels into transport channels. The MAC layer may also use error detection techniques, error correction techniques, or both to support retransmissions at the MAC layer to improve link efficiency. In the control plane, the Radio Resource Control (RRC) protocol layer may provide establishment, configuration, and maintenance of an RRC connection between a UE **115** and a base station **105** or a core network **130** supporting radio bearers for user plane data. At the physical layer, transport channels may be mapped to physical channels.

[0082] The UEs **115** and the base stations **105** may support retransmissions of data to increase the likelihood that data is received successfully. Hybrid automatic repeat request (HARQ) feedback is one technique for increasing the likelihood that data is received correctly over a communication link **125**. HARQ may include a combination of error detection (e.g., using a cyclic redundancy check (CRC)), forward error correction (FEC), and retransmission (e.g., automatic repeat request (ARQ)). HARQ may improve throughput at the MAC layer in poor radio conditions (e.g., low signal-to-noise conditions). In some examples, a device may support same-slot HARQ feedback, where the device may provide HARQ feedback in a specific slot for data received in a previous symbol in the slot. In other cases, the device may provide HARQ feedback in a subsequent slot, or according to some other time interval.

[0083] In some examples, a sidelink UE **115** may be configured to transmit sidelink messages in one or more resources of a resource selection window that were not monitored by the UE **115** due to the UE **115** operating in a power saving mode (e.g., a low power mode) during a preceding sensing window. The sidelink UE **115** may identify a resource reservation configuration for

communicating within a resource pool (e.g., a set of time and frequency resources) allocated for sidelink communications. In some examples, the UE **115** may operate in a low power state during a sensing window, and the UE **115** may refrain from monitoring a sidelink channel (e.g., performing channel sensing) during the sensing window due to the low power state. The UE **115** may receive a resource selection trigger that may indicate that the UE **115** is to transmit a sidelink message. The UE **115** may transition from the low power state to a high power state to select a resource for performing the sidelink transmission in a resource selection window corresponding to the sensing window that the UE **115** did not monitor. The resource reservation configuration may permit the UE **115** to identify one or more available resources in the resource selection window for sidelink transmission even though the UE **115** did not monitor the corresponding one or more resources in the sensing window due to the UE **115** operating in the low power state.

[0084] FIG. 2 illustrates an example of a wireless communications system **200** in accordance with aspects of the present disclosure. The wireless communications system **200** may include UEs **115-a** and **115-b** (e.g., among other UEs **115**), which may each represent an example of a UE **115** described with reference to FIG. 1. UEs **115-a** and **115-b** may communicate with each other or with one or more other UEs **115** in a geographic coverage area **110-a** via sidelink communication links **215**. UE **115-a**, UE **115-b**, or both, may be configured with a resource reservation configuration **210** for selecting resources from a resource pool **205** to use for sidelink communications.

[0085] Sidelink communications (e.g., cellular V2X) over a sidelink communication link **215** (e.g., a physical sidelink shared channel (PSSCH), or another sidelink channel) may operate in a distributed manner (e.g., using autonomous resource allocation, such as sidelink mode 2 resource allocation). For example, UEs **115-a** and **115-b** may communicate on their own, without any central nodes (e.g., base stations **105**) scheduling or assisting with the sidelink communications. For such sidelink communications, a UE **115** may perform channel sensing to determine whether a resource may be used for sidelink communications. The UE **115** may monitor (e.g., and decode) sidelink communications (e.g., sidelink control information (SCI) and/or other transmissions) from other UEs **115**. For example, UE **115-a** may monitor sidelink communications from UE **115-b** via the sidelink communication link **215** (e.g., among other sidelink communications). UE **115-a** may monitor sidelink communications when UE **115-a** does not transmit, for example, such that UE **115-a** may not miss sidelink messages from other UEs **115** (e.g., UE **115-a** may support half-duplex communications). In some cases, a UE **115** (e.g., a UE **115** operating in V2X mode 2 resource allocation) that wants to transmit in a resource pool may perform sensing to determine whether a resource can be used. The UE **115** may not select a resource that the UE **115** did not monitor. As such, to identify all available resources, a UE **115** may stay on and continuously monitor a channel for available sidelink resources regardless of whether the UE **115** has data to transmit, which may increase latency and power consumption by the UE **115**.

[0086] The wireless communications system **200** may support power saving UEs **115**. For example, UEs **115-a** and **115-b** may be configured with one or more power saving enhancements, such as DRX operations (e.g., in a time domain), wakeup signal indication, bandwidth adaptation via BWP switching or via resource pool **205** activation and deactivation (e.g., discontinuous reception in a frequency domain), or the like. While operating in a power saving mode, the UEs **115** may transition between a low power state and a high power state, which may be referred to as a sleep duration and an on duration, or a narrow BWP and a wide BWP, respectively. A UE **115** may transition between the high power state and the low power state periodically, or based on the UE **115** determining it does not have data to receive or transmit. The UE **115** may transition from the low power state to the high power state based on receiving a resource selection trigger indicating that the UE **115** has sidelink data to transmit.

[0087] During a low power state, a UE **115** may be unable to monitor a sidelink channel. For example, if UE **115-a** enters a low power state, UE **115-a** may not monitor one or more resources within the sidelink communication link **215**. UE **115-a** may receive a resource selection trigger

indicating that UE **115-a** has sidelink data to transmit (e.g., a packet may arrive for transmission by UE **115-a**). UE **115-a** may transition to the high power state based on receiving the resource selection trigger to select a resource for performing the sidelink data transmission. UE **115-a** may not know which resources of the resource pool **205** are available for the sidelink data transmission in the resource selection window because UE **115-a** operated in the low power state, and did not monitor the sidelink channel, during the respective sensing window. In such cases, UE **115-a** may be unable to use the resources in the resource selection window for sidelink communications until after UE **115-a** performs channel sensing, which may reduce throughput and increase latency associated with sidelink communications at UE **115-a**.

[0088] To permit sidelink UEs **115**, such as UE **115-a**, to operate in a power saving mode without incurring increased latency, a sidelink UE **115** may be permitted to transmit sidelink messages in one or more resources of a resource selection window that were not monitored by the UE **115** in a corresponding sensing window due to the UE **115** operating in a low power mode (e.g., a sleep mode or a narrow bandwidth mode). For example, UE **115-a** may be configured with a resource reservation configuration **210** for selecting a resource from the resource pool **205** for communicating via the sidelink communication link **215**. The resource reservation configuration **210** may permit UE **115-a** to select resources of the resource pool **205** that UE **115-a** did not monitor while operating in a low power mode during a preceding sensing window (e.g., the resource reservation configuration **210** may configure resource selection exemptions). UE **115-a** may select a resource from a subset of the available resources in a resource selection window and transmit a sidelink message in the resource via the sidelink communication link **215**.

[0089] In some examples, the resource reservation configuration **210** may permit UE **115-a** (e.g., a half-duplex UE **115**) to transmit a sidelink message in a resource of the resource selection window where the UE **115-a** did not monitor a corresponding resource of a preceding sensing window due to transmission of the sidelink message by UE **115-a** in the resource of the resource selection window. For example, UE **115-a** may transmit a sidelink message during a set of resources in a sensing window of a sidelink channel, and thus the half-duplex UE **115-a** did not monitor that set of resources because the UE **115-a** instead was transmitting the sidelink message in that set of resources. The resource reservation configuration **210** may permit UE **115-a** to transmit sidelink messages in a corresponding resource of a resource selection window of the resource pool **205**, even though the half-duplex UE **115-a** did not monitor a corresponding resource in the sensing window because the UE **115-a** instead was transmitting the sidelink message.

[0090] The resource reservation configuration **210** may thereby permit UE **115-a** to communicate using resources that UE **115-a** did not monitor due to operating in a low power state, or due to transmission by UE **115-a**, or both. The techniques for selecting sidelink resources described herein provide for sidelink UEs **115** to operate in a power saving mode without incurring significant latency during sidelink communications.

[0091] FIG. **3** illustrates an example of a resource selection scheme **300** that supports gradual sensing for UE power saving in sidelink operation in accordance with aspects of the present disclosure. In some examples, the resource selection scheme **300** may represent a selection scheme used by a first UE **115** (e.g., a transmitting UE **115**) to select sidelink resources for transmitting a sidelink message. The first UE **115** may communicate with one or more second UEs **115** using resource elements **330** (e.g., time and frequency resources) in a resource pool **305** over a sidelink channel. The first UE **115** and the one or more second UEs **115** may be examples of the UEs **115** described with reference to FIGS. **1** and **2**. In some examples, the first UE **115** may be configured with a resource reservation configuration that permits the first UE **115** to transmit in resources that were not monitored by the first UE **115**.

[0092] Some sidelink communications (e.g., V2X communications, or other device-to-device communications) may support autonomous resource allocation by a UE **115** (e.g., a mode 2 resource allocation). In such cases, a UE **115** (e.g., the first UE **115**) may access a channel based on

sensing outcomes. For example, the first UE **115** may identify available resources (e.g., time and frequency resources, such as resource elements **330** in slots and subchannels) of a resource pool **305** for a sidelink transmission, which may be referred to as candidate resources. The first UE **115** may select one or more resources for the sidelink transmission from the available resources in the resource pool **305** (e.g., a pool of time and frequency resources).

[0093] In the example of the resource selection scheme **300**, the first UE **115** may monitor each resource element **330** within the resource pool **305** during a sensing window **310** to identify available resources of the resource pool **305** within a corresponding resource selection window **315** to select for sidelink transmission. All of the resources within slots 0 through 7 and subchannels 0 through 3 of the resource selection window **315** may be included in a candidate set of resources for the first UE **115** to select from. The first UE **115** may exclude one or more resources from the candidate set of resources in the resource selection window **315** based on sensing outcomes from monitoring the sensing window **310**. For example, the first UE **115** may monitor for SCI from one or more other sidelink UEs **115** and perform channel sensing to determine a measured signal metric level associated with each resource element **330** in the sensing window **310**. The SCI may indicate one or more resources in a resource selection window **315** that may be reserved for a future transmission by another sidelink UE **115**. The first UE **115** may exclude the one or more reserved resources from the candidate set, and the first UE **115** may determine that the remaining resources in the resource selection window **315** are available resources of the candidate set based on the SCI grants. The first UE **115** may select a resource from the available resources for transmission of a sidelink message.

[0094] The first UE **115** may be configured with a resource selection procedure indicating one or more rules for identifying available resources. A first rule (e.g., in a Step 0 indicated in the one or more rules) may instruct the first UE **115** to initialize the set, S.sub.A, of candidate resources (e.g., single-slot resources) in the resource selection window **315**. For example, the set of candidate resources may include all of the time and frequency resources within subchannels 0 through 3 and slots 0 through 7 of the resource selection window **315**. In some examples, the first UE may project measurement and/or decoding outcomes from the sensing window **310** to the resource selection window **315**.

[0095] The first UE **115** may subsequently (e.g., in a Step 1 indicated in the one or more rules) exclude one or more resources from the candidate set, S.sub.A, if the first UE **115** did not monitor the corresponding resources in the sensing window **310** due to a transmission by the first UE **115**, instead of monitoring, in the one or more resources (e.g., the first UE **115** may exclude any resource that may potentially be reserved by a SCI grant). For example, the first UE **115** may transmit a sidelink message in resources within slot 2 and subchannels 0 through 3 of the sensing window **310**. Because the first UE **115** transmitted within the resources, and did not monitor the resources, the first UE **115** may exclude the corresponding resources in slot 2 and subchannels 0 through 3 of the resource selection window **315** from the candidate set.

[0096] The first UE **115** may exclude all resources that may potentially be reserved by an SCI grant by taking into account a set of configured (e.g., pre-configured) resource reservation periods. For example, the first UE **115** may exclude the resources in slot 7 and subchannels 0 through 3 of the resource selection window **315** from the candidate set based on a period that links the respective resources (e.g., a pre-configured periodicity that may be allowed by a higher layer parameter, such as sl-ResourceReservPeriodList-r16). For example, although the first UE **115** did not monitor the resources in slot 2 of the sensing window **310**, a hypothetical SCI grant transmitted by another UE **115** in slot 2 of the sensing window **310** may indicate that resources within slot 2 and slot 7 of the resource selection window **315** may be reserved (e.g., the SCI may include a “Resource reservation period” field set to the identified periodicity value). In this step (e.g., Step 1), if the first UE **115** does not monitor the resources in slot 2 of the sensing window **310**, the first UE **115** will not exclude resources in other slots (e.g., resources in slots 0, 1, 3, 4, 5, and 6) of the resource selection

window **315** because a potential SCI transmitted in slot 2 of the sensing window **310** cannot reserve any resources in these other slots.

[0097] For the remaining resources in the candidate set (e.g., resources  $R.sub.XY \in S.sub.A$ ), the first UE **115** may identify whether an SCI detected in the sensing window **310** reserves a resource that is overlapping with any of the remaining resources or any future candidate resources (e.g., in a Step 2 indicated by the one or more rules). The first UE **115** may exclude the reserved resources from the candidate set accordingly. For example, the first UE **115** may detect an SCI in resources within slot 4 and subchannels 2 and 3 of the sensing window **310** that may reserve corresponding resources in slot 4 and subchannels 2 and 3 of the resource selection window **315**. The first UE **115** may exclude the resources in slot 4 and subchannels 2 and 3 of the resource selection window **315** from the candidate set accordingly.

[0098] The first UE **115** may determine whether any SCI that was detected in the sensing window reserves future candidate resources associated with the remaining resources (e.g., the first UE **115** may identify future resources linked to the remaining resources within the candidate set by a period,  $P.sub.TX$ , such as  $R.sub.XY + jP.sub.TX$ ). The future candidate resources may be associated with the remaining resources based on a configured period, and the first UE **115** may determine whether any SCI received during the sensing window **310** includes a “resource reservation period” field set to the configured period value. If the SCI indicates future reserved resources based on the configured period, the first UE **115** may exclude the future reserved resources from the candidate set.

[0099] If the first UE **115** measures a reference signal receive power (RSRP) level of an SCI received during the sensing window **310**, and the measured RSRP is below an RSRP threshold (e.g., a configured RSRP threshold), the first UE **115** may not exclude resources that are reserved by the SCI from the candidate resource set,  $S.sub.A$ . The first UE **115** may include a resource in the candidate set even if the SCI indicates that the resource will be used by another UE **115**. If the measured RSRP is below the RSRP threshold, the first UE **115** determines that a transmission in the one or more resources scheduled by the SCI are unlikely to cause significant interference with a transmission by the first UE **115** in the resource (e.g., the other sidelink UE **115** that transmits in the resources may be relatively far away from the first UE **115**, and may be unlikely to interfere with communications by the first UE **115**). As such, a resource is excluded from the candidate set if the received RSRP of the SCI scheduling the resource exceeds the RSRP threshold (e.g., depending on a priority of the SCI reservation and a priority of the packet to be transmitted by the first UE **115**).

[0100] The RSRP threshold may be configured at the first UE **115**. In some examples, the RSRP threshold may be a dynamic threshold. For example, the first UE **115** may gradually increase the RSRP threshold until the first UE **115** identifies available resources for performing sidelink communications (e.g., until the first UE **115** identifies an SCI with a measured RSRP level below the RSRP threshold).

[0101] After identifying available resources of the resource pool **305** within the resource selection window **315**, the first UE **115** may select a resource for transmission of a sidelink message (e.g., a sidelink data message or an SCI to reserve resources for future sidelink data transmission by the first UE **115**). The first UE **115** may perform random resource selection from the candidate set of available resources.

[0102] When the first UE **115** receives a resource selection trigger **320** (e.g., a packet arrives for transmission from the first UE **115**), the first UE **115** may identify the sensing window **310** (e.g., a window in the past) and the resource selection window **315** (e.g., a window in the future), and the first UE **115** may perform resource selection according to the one or more resource selection rules as previously discussed. For example, the first UE **115** may determine a set of available resources in the resource selection window **315** based on SCI decoding and/or RSRP measurement in the sensing window **310** (e.g., the first UE **115** may look back at corresponding resources the first UE

**115** monitored in the sensing window **310**). The first UE **115** may select a resource from the available resources for transmitting the sidelink data indicated by the resource selection trigger **320**. The resource selection trigger **320** may be triggered by a higher layer of the first UE **115**. The higher layer may trigger a lower layer of the first UE **115** to transmit a packet.

[0103] Accordingly, to perform autonomous resource allocation (e.g., mode 2 allocation), the first UE **115** may monitor one or more sidelink transmissions, perform RSRP measurements, and perform resource selection when such selection is triggered by the resource selection trigger **320** (e.g., resource selection may be triggered by a packet arrival). Because the first UE **115** may not know when a resource selection trigger **320** will arrive, the first UE **115** may continuously monitor a resource pool **305** to determine available resources in the future for potential sidelink transmission by the first UE **115**, which may result in relatively high power consumption at the first UE **115**. If the first UE **115** refrains from monitoring one or more resources in the resource pool **305** and the first UE **115** subsequently receives a resource selection trigger **320**, the first UE **115** cannot transmit sidelink data in corresponding resources in a resource selection window **315**, which may increase latency and reduce throughput associated with sidelink communications by the first UE **115**.

[0104] Some sidelink UEs **115**, such as the first UE **115**, may operate in a power saving mode, which may include switching between low power states and high power states. During a low power state, the first UE **115** may not monitor resources in the resource pool **305** or perform channel sensing. If the first UE **115** receives the resource selection trigger **320**, the first UE **115** transitions from the low power state to the high power state to perform transmission of the sidelink data within a resource selection window **315**. But, the first UE **115** may not have monitored resources in the corresponding sensing window **310** during the low power state. As such, after transitioning to the high power state the first UE **115** may monitor resources within the resource selection window **315** to identify available resources prior to selecting a resource for transmission within the resource selection window **315**, which may increase latency.

[0105] As described herein, the first UE **115** may be configured with exemptions to the one or more rules for identifying available resources such that the first UE **115** may operate in a power saving mode without incurring significant latency. The one or more rules may be conveyed to the first UE **115** via a resource reservation configuration, such as the resource reservation configuration **210** described with reference to FIG. 2. The resource reservation configuration may configure the first UE **115** to operate in a power saving mode without incurring significant latency by permitting the first UE **115** to transmit in resources in the resource selection window **315** that the first UE **115** did not monitor due to the first UE **115** operating in a low power state during the corresponding sensing window **310**. In other words, for resource determination in sidelink resource allocation mode 2, if the first UE **115** has not monitored a slot in the sensing window **310** for the resource pool **305** due to power saving (e.g., during a DRX off duration or due to bandwidth adaptation), the first UE **115** may not exclude resources in corresponding slots in the resource selection window **315** that could be reserved by a hypothetical SCI grant during the slot in the sensing window **310** (e.g., the first UE **115** may be provided with an exemption to use a resource without sensing during a power saving period). In one example, Step 1 of the resource selection procedure may be modified to permit such an exemption for resource selection. For example, if the first UE **115** operates in a low power state during the sensing window **310** and subsequently receives the resource selection trigger **320**, the first UE **115** may transition to a high power state and select a resource in the resource selection window **315** for sidelink transmission even though the first UE **115** did not monitor a corresponding resource in the sensing window **310** due to the low power state. Such techniques for resource selection may provide for the power saving first UE **115** to use a resource without sensing during a power saving period.

[0106] In some examples, the resource reservation configuration may permit the first UE **115** to select a resource in the resource selection window **315** for transmission that the first UE **115** did not

monitor due to transmission by the first UE **115** in that resource during the sensing window **310** (e.g., the first UE **115** may not exclude all resources in the resource selection window **315** that could potentially be reserved by a hypothetical SCI grant). For example, if the first UE **115** (e.g., a half-duplex UE **115**) transmits in resources within slot 2 and subchannels 0 through 3 of the sensing window **310**, instead of monitoring the resources, the first UE **115** may be permitted to include corresponding resources in slot 2 and subchannels 0 through 3 within the resource selection window **315** in the set of candidate resources (e.g., and corresponding resources in slot 7 and subchannels 0 through 3 of the resource selection window **315** that may be linked by a configured period). In some examples, whether the first UE **115** is permitted to select resources the first UE **115** did not monitor due to transmission may be based on a type of power saving mode the first UE **115** operates in. In one example, the first UE **115** may be permitted to select resources the first UE **115** did not monitor due to transmission during a DRX mode, but the first UE **115** may not select such resources during a bandwidth adaptation mode.

[0107] In some examples, a sidelink control message (e.g., SCI) may be transmitted by another UE **115** in the resources of slot 2 and subchannels 0 through 3 or the resources in slot 4 and subchannels 2 and 3 of the sensing window **310**, and the sidelink control message may indicate that the corresponding resources in the resource selection window **315** are reserved (e.g., by a hypothetical SCI grant). If the first UE **115** did not receive the SCI due to operating in a low power state or transmission by the first UE **115**, the first UE **115** may be permitted to transmit in the reserved resources in the resource selection window **315**, which may result in interference between transmissions by the first UE **115** and the second UE **115** in the resources. The resource reservation exemption described herein may thereby allow for some risk of increased interference in the network to provide for reduced power consumption at the first UE **115**.

[0108] Accordingly, the first UE **115** may perform autonomous resource allocation (e.g., mode 2 allocation) while operating in a power saving mode by selecting a resource when such selection is triggered by the resource selection trigger **320** based on one or more resource reservation exemption rules to reduce power consumption at the first UE **115**, improve throughput, and improve the quality of sidelink communications.

[0109] FIG. **4** illustrates an example of a DRX timeline **400** in accordance with aspects of the present disclosure. In some examples, the DRX timeline **400** may implement aspects of the wireless communications systems **100** and **200**, as described with reference to FIGS. **1** and **2** and the resource selection scheme **300**, as described with reference to FIG. **3**. For example, the DRX timeline **400** may illustrate operations for resource selection from a resource pool **405** (e.g., a pool of time and frequency resources) by a sidelink UE **115** (e.g., a first UE **115**) in a power saving mode. The DRX timeline **400** may be applicable to implementations or instances when the first UE **115** is configured to support resource selection during power saving operations in the temporal domain (e.g., DRX operations).

[0110] The DRX timeline **400** may include one or more DRX cycles **440**, which may correspond to a set of time resources (e.g., a symbol duration, a slot duration, a subframe duration, a frame duration), as well as a set of frequency resources (e.g., subcarriers, carriers). Each DRX cycle **440** may include an inactive duration **430** (also referred to as a DRX sleep duration) and an active duration **435** (also referred to as a DRX ON duration), which may correspond to time and frequency resources. The first UE **115** may operate in the high power state during each active duration **435** for monitoring a sidelink channel, transmitting data, or both. The first UE **115** may enter a sleep mode (e.g., a low power mode), and may refrain from transmitting or monitoring during each inactive duration **430** to reduce power consumption.

[0111] The DRX timeline **400** illustrates three active durations **435** (e.g., active durations **435-a**, **435-b**, and **435-c**), and two inactive durations **430** (e.g., inactive durations **430-a** and **430-b**) for the first UE **115** that are located periodically in the time domain. Active duration **435-a** and inactive duration **430-a** may correspond to a first DRX cycle **440** for the first UE **115**. Active duration **435-**

*b* and inactive duration **430-b** may correspond to a second DRX cycle **440** for the first UE **115**. Active duration **435-c** may correspond to a beginning of a third DRX cycle **440** for the first UE **115**.

[0112] The first UE **115** may transition between the inactive durations **430** and the active durations **435** periodically or based on signaling. In one example, each inactive duration **430** and active duration **435** may be configured according to respective periods within a DRX cycle **440**, and the first UE **115** may transition between states according to the configured periods. In some examples, the first UE **115** may transition between the active durations **435** and the inactive durations **430** periodically regardless of whether the first UE **115** has data to transmit.

[0113] In another example, the first UE **115** may receive a wakeup signal indicating the first UE **115** is to transition from the inactive duration **430** to the active duration **435** to transmit data, perform channel sensing, or the like. The wakeup signal may carry an indication of an active duration **435** of the DRX cycle **440** for the first UE **115**. The wakeup signal may be transmitted in a pre-wakeup window (not pictured) that may occur before each respective active duration **435** (e.g., the wakeup signal may be configured in addition to DRX) and may include a wakeup signal monitoring period. In some examples, the pre-wakeup window may be part of the DRX cycle **440** to preserve resources (for example, time and frequency resources) or a battery life of the first UE **115**, among other advantages. For example, the pre-wakeup window may facilitate power saving advantages of the first UE **115** by reducing unnecessary wakeup occasions for the first UE **115**. The first UE **115** may monitor for a wakeup signal during the wakeup signal monitoring occasion in the pre-wakeup window. If the first UE **115** detects a wakeup signal during the pre-wakeup window, the first UE **115** will transition from a low power state to a high power state. If the first UE **115** does not detect a wakeup signal in the pre-wakeup window, the first UE **115** will remain in the low power state or will transition from a high power state to the low power state.

[0114] The wakeup signal may be an example of the resource selection trigger **320** described with reference to FIG. 3. The first UE **115** may receive signaling (e.g., a wakeup signal, a resource selection trigger, or some other signaling) indicating that the first UE **115** is to transmit data, and the first UE **115** may transition from a low power state to a high power state to perform resource selection accordingly. It is understood that a UE **115** may transition between any number of active durations **435** and inactive durations **430** that are not illustrated. For instance, the first UE **115** may transition between DRX cycles **440** according to any DRX periods or any signaling received at the UE **115**.

[0115] A sensing window **445** for the first UE **115** may occur during an inactive duration **430**, and a corresponding resource selection window **450** for the first UE **115** may occur during an active duration **435** (e.g., after the first UE **115** receives a resource selection trigger). The resource selection windows **450** (e.g., resource selection windows **450-a**, **450-b**, and **450-c**) and the sensing windows **445** (e.g., sensing windows **445-a** and **445-b**) may be examples of the sensing window **310** and the resource selection window **315**, as described with reference to FIG. 3.

[0116] When operating in the DRX power saving mode, the first UE **115** may refrain from monitoring the resource pool **405** in a sensing window **445** during each inactive duration **430**. The first UE **115** may thereby be unable to identify available resources for sidelink transmission in a corresponding resource selection window **450** when the first UE **115** transitions to an active duration **435**. When the first UE **115** transitions to a high power state, the first UE **115** may monitor the resource pool **405** within the active duration **435** before performing sidelink transmission, which may increase latency. For example, the first UE **115** may refrain from monitoring resources within TTI **415-a** in sensing window **445-a** due to a low power state of the first UE **115** during inactive duration **430-a**. As such, the first UE **115** may not obtain sensing information for the resources, and may be unable to select corresponding resources in TTI **415-b** in resource selection window **450-b** for transmission. The first UE **115** may perform channel sensing during resource selection window **450-b** before identifying available resources, which may result in increased

latency associated with sidelink communications.

[0117] As described herein, the first UE **115** may be configured (e.g., via a resource reservation configuration) with one or more resource reservation exemptions for the first UE **115** when the first UE **115** operates in a power saving mode, such as a DRX mode. The resource reservation configuration may permit the first UE **115** to select one or more resources in a resource selection window **450** that were not monitored by the first UE **115** during a corresponding sensing window **445** due to the UE **115** operating in a low power state, as described with reference to FIGS. **2** and **3**. For example, the first UE **115** may not monitor resources in TTI **415-a** (e.g., a slot, a symbol, or some other quantity of time and frequency resources) due to the first UE **115** operating in a low power state (e.g., a DRX off state) during sensing window **445-a** within inactive duration **430-a**. But, the first UE **115** may be permitted to include the corresponding resources in TTI **415-b** in a candidate set of available resources for sidelink transmission in resource selection window **450-b** within active duration **435-b** based on the first UE **115** operating in the low power state.

[0118] In some examples, the resource reservation configuration may permit the first UE **115** to transmit sidelink data in resources that the first UE **115** did not monitor due to a transmission by the first UE **115**. For example, the first UE **115** may transmit sidelink data in TTI **410-a** during active duration **435-a**. The first UE **115** may support half-duplex operations and may not monitor the resources in TTI **410-a** due to the transmission by the first UE **115**. If the resource reservation configuration indicates that resources that were not monitored due to transmission by the UE **115** are exempt from sensing, the first UE **115** may determine that the resources in TTI **410-b** in a subsequent active duration **435-b** are available for sidelink transmission by the first UE **115**. The resource selection exemptions for transmission may be based on a type of power saving mode that the first UE **115** operates in. For example, the resources in TTI **410-a** that the first UE **115** transmitted in, instead of monitoring, may be identified as available resources (e.g., exempt resources) for the first UE **115** if the first UE **115** operates in a DRX power saving mode, as illustrated in FIG. **4**. In some examples, the resources in TTI **410-a**, or another TTI that the first UE **115** transmitted in in active duration **435-a** or inactive duration **430-a**, may not be identified as available resources if the first UE **115** operates in a bandwidth adaption power saving mode, or some other power saving mode.

[0119] If the first UE **115** receives a sidelink control message (e.g., SCI) from another UE **115** that reserves resources, such as resources in TTIs **410-b** or **415-b**, in a resource selection window **450-b**, the first UE **115** will continue to exclude the reserved resources from the candidate set (e.g., regardless of the resource reservation configuration).

[0120] In some examples, the resource reservation configuration for the first UE **115** may indicate that the resource reservation exemption for a power saving UE **115** is applicable to a subset of resource reservation periodicities **425**. For example, the first UE **115** may be configured with a set of resource reservation periodicities **425** (e.g., periodicities with durations of 10 ms, 100 ms, 1 second, or some other duration). The first UE **115** may be exempted to exclude resources in a TTI from a candidate resource set for a subset of resource reservation periodicities **425** (e.g., 100 ms and 1 second, or some other subset of periodicities) of the set of configured resource reservation periodicities **425**, but may not be exempted from excluding resources in the TTI from the candidate resource set for remaining periodicities in the set (e.g., a 10 ms periodicity). The resource reservation periodicities **425** may be indicated to the UE via signaling from a base station **105** (e.g., during network-controlled sidelink operations, such as Mode 1 sidelink communication), or the resource reservation periodicities **425** may be configured at the first UE **115** (e.g., the periodicities may be pre-loaded to the UE **115** during manufacturing).

[0121] In the example of the DRX timeline **400**, the first UE **115** may be configured with resource reservation periodicities **425-a**, **425-b**, and one or more other resource reservation periodicities **425**. The time and frequency resources in TTIs **420-a**, **420-b**, and **420-c** may be linked according to the respective resource reservation periodicities **425**. Resource reservation periodicity **425-a** may be

included in the subset of exempted resource reservation periodicities **425** indicated by the reservation configuration and resource reservation periodicity **425-b** may not be included in the subset. Accordingly, the first UE **115** may be exempted to exclude resources in TTI **420-c** for resource reservation periodicity **425-a**, but the first UE **115** may not be exempted to exclude resources in TTI **420-c** for resource reservation periodicity **425-b**. If the first UE **115** does not monitor TTI **420-a** during sensing window **445-b** (e.g., due to a low power state of the first UE **115** during inactive duration **430-b**), the first UE **115** may determine that resources in TTI **420-c** are available for sidelink transmission in resource selection window **450-c** (e.g., the first UE **115** may be allowed to use the resources in TTI **420-c**). However, if the first UE **115** does not monitor resources in TTI **420-b** during active duration **435-c** (e.g., or during another sensing window **445** (not pictured)), the first UE **115** may not include resources in TTI **420-c** in the set of available resources for sidelink transmission in resource selection window **450-c** (e.g., because the first UE **115** did not monitor within resource reservation periodicity **425-b**).

[0122] In other words, if a subset of resource reservation periodicities **425** are indicated in the resource reservation configuration, the first UE **115** can refrain from monitoring resources during the indicated subset of resource reservation periodicities **425**, but the first UE **115** monitors resources in the resource pool **405** during the resource reservation periodicities **425** that were not indicated in the subset in order to transmit in corresponding resources in a resource selection window **450**. In some examples, the resource reservation periodicities **425** that are identified in the subset may be longer than the remaining resource reservation periodicities **425**. As such, by including or exempting resources from a candidate set of available resources according to the indicated subset of resource reservation periodicities **425**, the first UE **115** may perform channel sensing for at least a configured duration before using resources in the resource selection window **450** (e.g., the first UE **115** may perform channel sensing for at least 10 ms, or some other periodicity, before using resources in the resource pool **405**). Such techniques may provide for gradual sensing by the first UE **115**. For example, the first UE **115** may perform no sensing and random resource selection in the beginning of the resource selection window **450**, and the first UE **115** may perform full sensing of the resource pool **405** by the end of the resource selection window **450**.

[0123] In some examples, the first UE **115** may be permitted to use resources in the resource selection window **450** based on a defined signal metric level (e.g., RSRP level). Instead of including all of the resources that the first UE **115** did not monitor during an inactive duration **430** (e.g., a low power state), the first UE **115** may assume that each of the resources in the sensing window **445** that the first UE **115** did not monitor have a received RSRP value corresponding to a configured signal metric level. The first UE **115** may apply the defined RSRP level (e.g., X decibel milliwatts (dBm)) to all resources in the sensing window **445** that the first UE **115** did not monitor during the low power state. For example, the first UE **115** may assume that a measured RSRP level for the resources in sensing window **445-a** that the first UE **115** did not monitor during inactive duration **430-a** is the same as the defined RSRP level. As described with reference to FIG. 3, the first UE **115** may compare an RSRP measurement for each resource in sensing window **445-a** (e.g., a measured RSRP level for one or more SCI grants received in sensing window **445-a**) with a RSRP threshold to identify resources that are available for sidelink transmission in a corresponding resource selection window **450-b**. In some examples, the RSRP threshold may be lower than the defined signal metric level. In such cases, if the first UE **115** identifies one or more resources in sensing window **445-a** that are associated with a measured RSRP value that is lower than the threshold (e.g., the first UE **115** may have performed channel sensing on the one or more resources), the first UE **115** will prioritize those resources, and the first UE **115** may determine that those resources are available.

[0124] Additionally or alternatively, the first UE **115** may determine that no resources are available due to the defined RSRP value that was applied to each resource the first UE **115** did not monitor in

sensing window **445-a** during inactive duration **430-a** being higher than the RSRP threshold. The first UE **115** may gradually raise the RSRP threshold until the first UE **115** identifies available resources. In some examples, the first UE **115** may raise the RSRP threshold above the defined RSRP value, and the first UE **115** may determine that each of the resources that the first UE **115** did not monitor during sensing window **445-a** are available for sidelink data transmission in resource selection window **450-b**. By starting with a small RSRP threshold and increasing the RSRP threshold gradually, the first UE **115** may prioritize the use of resources that the first UE **115** has performed sensing for over resources that the first UE **115** has not performed sensing for.

[0125] In some examples, the RSRP threshold may be determined based on a priority of the data traffic the first UE **115** is to transmit. If the first UE **115** has high priority data to transmit in resource selection window **450-a**, the RSRP threshold may be relatively high, such that the first UE **115** may select an arbitrary resource from the resource set in resource selection window **450-a** (e.g., a relatively large number of resources, or all of the resources, in resource selection window **450-a** may be associated with a measured RSRP level that is smaller than the RSRP threshold). If the data to be transmitted by the first UE **115** is low priority data traffic, the RSRP threshold may be decreased (e.g., a low RSRP threshold), which may limit the resources that can be selected by the first UE **115** (e.g., fewer resources in resource selection window **450-a** may meet the RSRP threshold). Accordingly, the first UE **115** may prioritize transmission of high priority traffic over low priority traffic.

[0126] The first UE **115** may be permitted to use a resource if the first UE **115** has higher priority data to transmit than the priority of the data traffic in the resource. For example, if data traffic to be transmitted within TTI **415-b** is associated with a first priority level, and the first UE **115** is preparing to transmit a packet with a second priority that is lower than the first priority level, the first UE **115** may not use the resources in TTI **415-b** for transmitting the packet. If the first UE **115** is preparing to transmit a packet with a third priority that is higher than the first priority level, the first UE **115** may transmit the packet using the resources in TTI **415-b**.

[0127] A sidelink UE **115** may thereby be configured with a resource reservation configuration that permits the sidelink UE **115** to transmit in resources that the UE **115** did not monitor during a low power state to provide for reduced power consumption by the UE **115** without incurring significant latency.

[0128] FIG. 5 illustrates an example of a bandwidth adaptation timeline **500** in accordance with aspects of the present disclosure. In some examples, the bandwidth adaptation timeline **500** may implement aspects of the wireless communications systems **100** and **200**, as described with reference to FIGS. 1 and 2 and the resource selection scheme **300**, as described with reference to FIG. 3. For example, the bandwidth adaptation timeline **500** may illustrate operations for resource selection from a resource pool **505** by a sidelink UE **115** (e.g., a first UE **115**) in a power saving mode. The bandwidth adaptation timeline **500** may be applicable to implementations or instances when the first UE **115** is configured to support resource selection during power saving operations in the frequency domain, which may be referred to as bandwidth adaptation.

[0129] The bandwidth adaptation timeline **500** may illustrate operations by the first UE **115** in a bandwidth adaptation mode (e.g., a mechanism for reducing power consumption at the first UE **115**). The first UE **115** may operate in a low power state (e.g., a narrow bandwidth mode) and may transition to a high power state (e.g., a wide bandwidth mode). The low power state may correspond to the first UE **115** communicating using a first resource pool **505-a** (e.g., resource pool 0) associated with a first BWP (e.g., BWP0), and the high power state may correspond to the UE **115** communicating using a second resource pool **505-b** (e.g., resource pool 1) associated with a second BWP (e.g., BWP1) that may be wider than the first BWP in the frequency domain (e.g., the second BWP may include more carriers, subcarriers, or the like, than the first BWP). In some examples, the first UE **115** may operate in the low power state and monitor time and frequency resources in the first resource pool **505-a** until the first UE **115** has large data **515** to transmit. The

first UE **115** may transmit relatively small data traffic, such as the small data **510** in a number of time and frequency resources within resource pool **505-a** and the corresponding first BWP.

[0130] The first UE **115** may operate in the high power state when the first UE **115** has data packets to transmit that are relatively large, such as the large data **515**. The large data **515** may occupy a number of time and frequency resources within resource pool **505-b** that may be greater than the number of time and frequency resources occupied by the small data **510** (e.g., resource pool **505-b** may occupy a total number of time and frequency resources in a channel or subchannel, and resource pool **505-a** may occupy a subset of the total number of resources). The first UE **115** may save power by using fewer time and frequency resources for communications in the first resource pool **505-a** associated with the first BWP than the time and frequency resources in the second resource pool **505-b** associated with the second BWP.

[0131] The BWP sizes may be configured at the first UE **115**, and the first UE **115** may transition between BWPs periodically or based on signaling received at the first UE **115**, such as a resource selection trigger **320**, as described with reference to FIG. 3. The bandwidth adaptation timeline **500** may include a sensing window **525** and a resource selection window **530**, which may be examples of the sensing windows and resource selection windows described with reference to FIGS. 3 and 4. The first UE **115** may operate in the low power state during the sensing window **525** and transition to operating in the high power state during the resource selection window **530**. At **520**, the first UE **115** may receive a resource selection trigger indicating that the first UE **115** has a relatively large data packet to transmit (e.g., indicating that the large data **515** arrives). The first UE **115** may switch BWPs based on the resource selection trigger to operate in the high power state within the second BWP. The first UE **115** may perform the BWP switch within a time duration (e.g., a gap or offset time) between the sensing window **525** and the resource selection window **530**.

[0132] In some cases, the first UE **115** may identify available resources in the resource selection window **530** for transmitting the large data **515** (e.g., sidelink data) based on a channel sensing procedure, as described with reference to FIG. 3. However, the first UE **115** may not have performed channel sensing in the sensing window **525** prior to the resource selection window **530** due to the first UE **115** operating in the low power state (e.g., the narrow bandwidth mode). Additionally or alternatively, the first UE **115** may not have performed channel sensing for all of the resources in resource pool **505-b** due to operating in the low power state within resource pool **505-a** (e.g., the first UE **115** may not have monitored all of the time and frequency resources that are included in resource pool **505-b**). Accordingly, the first UE **115** may be unable to identify available resources for transmitting the large data **515** in resource pool **505-b** until the first UE **115** performs channel sensing in the resource selection window **530**, which may increase latency associated with communications by the first UE **115**.

[0133] As described with reference to FIGS. 2 through 4, the first UE **115** may be permitted to transmit sidelink data in resources that the first UE **115** did not monitor while operating in a low power state. The first UE **115** may identify a set of available resources in the resource selection window **530** that correspond to one or more resources that the first UE **115** did not monitor in the sensing window **525** (e.g., resources that may occupy the second BWP in the frequency domain). The first UE **115** may select one or more available resources for transmission of the large data **515** in the resource selection window **530**. The first UE **115** may transition back to the low power state by switching from the second BWP to the first BWP after the first UE **115** transmits the large data **515**.

[0134] Accordingly, the first UE **115** may reduce power consumption by operating within a small resource pool **505-a** corresponding to a small BWP (e.g., BWP0) until the first UE **115** has large data **515** to transmit. By transmitting the large data **515** in a resource that the first UE **115** did not monitor while operating in a low power state within resource pool **505-a**, the first UE **115** may reduce power consumption and increase throughput without incurring significant latency during sidelink communications by the first UE **115**.

[0135] FIG. 6 illustrates an example of a resource pool activation timeline 600 in accordance with aspects of the present disclosure. In some examples, the resource pool activation timeline 600 may implement aspects of the wireless communications systems 100 and 200, as described with reference to FIGS. 1 and 2. For example, the resource pool activation timeline 600 may illustrate operations for resource selection from one or more resource pools 605 by a sidelink UE 115 (e.g., a first UE 115) in a power saving mode, as described with reference to FIGS. 1 through 5. The resource pool activation timeline 600 may be applicable to implementations or instances when the first UE 115 is configured to support resource selection during power saving operations that include switching between resource pools 605.

[0136] The first UE 115 may operate according to the resource pool activation timeline 600 by activating or deactivating a resource pool 605 based on data traffic. The first UE 115 may be configured with one or more resource pools 605, such as a primary resource pool 605-a (e.g., resource pool 0) and a secondary resource pool 605-b (e.g., resource pool 1). Each resource pool 605 may include a number of resources in the time and frequency domain. The primary resource pool 605-a and the secondary resource pool 605-b may include a same quantity of time and frequency resources or a different quantity of time and frequency resources (e.g., a different quantity of subchannels, channels, BWPs, slots, symbols, or the like). The first UE 115 may activate or deactivate secondary resource pool 605-b periodically or based on signaling received at the first UE 115, such as a resource selection trigger indicating the first UE 115 has data to transmit, as described with reference to FIGS. 3 through 5.

[0137] The first UE 115 may continuously monitor the primary resource pool 605-a. The first UE 115 may not monitor the secondary resource pool 605-b continuously to reduce power consumption. The resource pool activation timeline 600 may include a sensing window 620 and a resource selection window 625, which may be examples of a sensing window and resource selection windows described with reference to FIGS. 3-5. The first UE 115 may monitor the primary resource pool 605-a during the sensing window 620, and the first UE 115 may concurrently monitor both the primary resource pool 605-a and the secondary resource pool 605-b during the resource selection window 625. The concurrent monitoring or use of the resource pools 605 may correspond to a high power state of the first UE 115.

[0138] If the first UE 115 receives a resource selection trigger indicating that the first UE 115 has large data to transmit (e.g., data that may occupy more time and frequency resources than are available in the primary resource pool 605-a), the first UE 115 may activate the secondary resource pool 605-b. For example, the first UE 115 may activate the secondary resource pool 605-b at another sidelink UE 115 that may receive the data transmission from the first UE 115. The first UE 115 may transmit an indication of the resource pool activation via SCI 610-a or a PSSCH 615-a. In some cases, the first UE 115 may be unable to identify available resources in the secondary resource pool 605-b during the resource selection window 625 because the first UE 115 did not monitor corresponding resources in secondary resource pool 605-b during the sensing window 620 (e.g., while operating in the low power state), which may increase latency associated with the sidelink communications.

[0139] As described with reference to FIGS. 2 through 5, the first UE 115 may be permitted to transmit in a set of resources in secondary resource pool 605-b that the first UE 115 did not monitor in the sensing window 620 while operating in the low power state (e.g., while secondary resource pool 605-b is deactivated). Accordingly, the first UE 115 may refrain from monitoring secondary resource pool 605-b during the sensing window 620 to reduce power consumption, and the first UE 115 may subsequently activate secondary resource pool 605-b at another receiving UE 115 and transmit data to the receiving UE 115 using one or more resources in secondary resource pool 605-b (e.g., even though the first UE 115 did not perform channel sensing on the one or more resources).

[0140] The first UE 115 may deactivate secondary resource pool 605-b after transmitting the

sidelink data and return to the low power state. The first UE **115** may transmit an indication of the deactivation of the secondary resource pool **605-b** via SCI **610-b** or PSSCH **615-b** in primary resource pool **605-a**.

[0141] Accordingly, the described techniques provide for a sidelink UE **115** to reduce power consumption by activating and deactivating one or more secondary resource pools **605** based on whether the UE **115** has data to transmit. The UE **115** may perform efficient sidelink communication during the power saving mode by transmitting in resources in the secondary resource pools **605** that the UE **115** did not monitor while operating in a low power state (e.g., while monitoring a single resource pool **605**).

[0142] FIG. 7 illustrates an example of a bandwidth adaptation timeline **700** in accordance with aspects of the present disclosure. In some examples, the bandwidth adaptation timeline **700** may implement aspects of the wireless communications systems **100** and **200**, as described with reference to FIGS. 1 and 2. For example, the bandwidth adaptation timeline **700** may implement aspects of resource selection by a sidelink UE **115** operating in a power saving mode, as described with reference to FIGS. 1 through 6. The bandwidth adaptation timeline **700** may be an example of the bandwidth adaptation timeline **500**, as described with reference to FIG. 5, and the bandwidth adaptation timeline **700** may be applicable to implementations or instances when the first UE **115** is configured to support resource selection during power saving operations in the frequency domain, which may be referred to as bandwidth adaptation.

[0143] As described with reference to FIG. 5, a first UE **115** operating in a bandwidth adaptation mode may transition between a first resource pool **705-a** (e.g., resource pool 0 and a corresponding first BWP 0) and a second resource pool **705-b** (e.g., resource pool 1 and a corresponding second BWP 1) that may include more time and frequency resources than the first resource pool **705-a**. The first UE **115** may operate in a low power state by using and monitoring a first quantity of time and frequency resources within resource pool **705-a** during a sensing window **720**. The first UE **115** may transition to a high power state by using and monitoring a greater quantity of time and frequency resources in resource pool **705-b** during a resource selection window **725**.

[0144] As described with further reference to FIG. 5, the first UE **115** may receive a resource selection trigger indicating arrival of a data packet to be transmitted by the first UE **115**. The data packet may occupy more resources than are available in resource pool **705-a**, and the first UE **115** may switch BWP (or a resource pool **705**) based on the resource selection trigger to transmit the large data in the greater quantity of time and frequency resources within resource pool **705-b**. As described with reference to FIGS. 2 through 6, to reduce power consumption without incurring increased latency during sidelink communications, the first UE **115** may be permitted to transmit sidelink data during the resource selection window **725** using one or more resources in resource pool **705-b** that the first UE **115** did not monitor due to operating in the low power state.

[0145] In the example of the bandwidth adaptation timeline **700**, the first UE **115** may refrain from monitoring all of the time and frequency resources in TTI **710-a** during the sensing window **720**. For example, the first UE **115** may not monitor any resources (e.g., frequency resources) in the second BWP (e.g., BWP 0 in resource pool **705-b**) during TTI **710-a**, but the first UE **115** may monitor resources in the first BWP (e.g., BWP 1 in resource pool **705-a**) during TTI **710-a** (e.g., TTI **710-a** may represent an interval of resources in the time domain). The resources in TTI **710-a** may correspond to the resources in TTI **710-b** during the resource selection window **725**. One or more of the resources in TTI **710-b** may be located outside of resource pool **705-a** (e.g., frequency resources in TTI **710-b** may be located outside of the narrow BWP 0 and may occupy more BWPs, subchannels, channels, or the like, than resource pool **705-a**). During the low power state, the first UE **115** may monitor resources within resource pool **705-a**, and may not obtain sensing information for each of the resources in TTI **710-a** that are outside of resource pool **705-a** (e.g., the first UE **115** may not monitor for SCI transmitted in one or more of the frequency resources outside of the narrow BWP 0 during TTI **710-a**). In some examples, the first UE **115** may not monitor any of the

resources in TTI **710-a** during the sensing window **720**, and the first UE **115** may be permitted to transmit in corresponding resources in TTI **710-b** during the resource selection window **725** due to the low power state. Additionally or alternatively, the first UE **115** may monitor some of the resources within TTI **710-a** that are within resource pool **705-a** (e.g., resources in frequency ranges that are within the narrow BWP of resource pool 0), but the first UE **115** may not monitor the resources in TTI **710-a** that are outside of resource pool **705-a** (e.g., resources in frequency ranges that are outside of the narrow BWP, but within the wide BWP of resource pool 1). The first UE **115** may be permitted to perform resource selection within the monitored resources of TTI **710-b** that are within resource pool **705-a** as well as the unmonitored resources of TTI **710-b** that are within frequency ranges outside of resource pool **705-a** and within resource pool **705-b** due to the low power state of the first UE **115** during the corresponding TTI **710-a** within the sensing window **720**.

[0146] As the first UE **115** operates in the high power state during the resource selection window **725**, the first UE **115** may gradually transition from no sensing to full channel sensing. For example, the first UE **115** may not measure sensing information for resources located near the beginning (e.g., in the temporal domain) of the resource selection window **725** due to operating in a low power state prior to the resource selection window **725**. Because the first UE **115** operates in the high power state during the resource selection window, the first UE **115** may begin monitoring one or more resources within the resource selection window **725**. The first UE **115** may thereby perform full channel sensing to obtain sensing information for one or more of the resources in a later portion of the resource selection window **725**. The resource selection exemption provided for the first UE **115** by the resource reservation configuration may apply for the beginning portion of the resource selection window **725** in which the first UE **115** performs random resource selection (e.g., the exemption may not apply once the first UE **115** transitions to full sensing in the resource selection window **725**).

[0147] For example, the first UE **115** may operate in the high power state during TTI **715-a**, and the first UE **115** may be capable of monitoring the resources in TTI **715-a**. The first UE **115** may perform channel sensing for the resources in TTI **715-a** to determine whether the corresponding resources in TTI **715-b** of the resource selection window **725** are available resources. If the first UE **115** does not monitor the resources in TTI **715-a** due to a transmitting, instead of sensing, in TTI **715-a**, the resource selection exemption may not apply, and the first UE **115** may be unable to transmit sidelink messages in TTI **715-b** (e.g., the resources may be unavailable for sidelink data transmission by the first UE **115**).

[0148] In some examples, the first UE **115** (e.g., a half-duplex UE **115**) may be permitted to perform resource selection in resources that the first UE **115** did not monitor due to a transmission by the first UE **115**, instead of monitoring, in the resources. In some examples, the first UE **115** may be configured with a subset of resource reservation periodicities, and the resource reservation exemptions may be applicable to the subset of resource reservation periodicities, as described with reference to FIG. 4. For example, the first UE **115** operating in the bandwidth adaptation mode may perform resource selection within resources of the resource selection window **725** for a subset of configured periodicities, and the first UE **115** may not be permitted to perform resource selection within the resource selection window **725** for remaining periodicities that are not included in the subset. Additionally or alternatively, the first UE **115** operating in the bandwidth adaptation mode may be configured with a defined signal metric level, an RSRP threshold, or a combination thereof, and the first UE **115** may select one or more available resources in the resource selection window **725** based on the signal metric level and the RSRP threshold, as described with reference to FIG. 4. In some examples, the first UE **115** may select a resource in the resource selection window **725** based on a priority of traffic to be transmitted by the first UE **115**.

[0149] A sidelink UE **115** may thereby be configured to support gradual sensing within a resource selection window **725** while operating in a power saving mode to improve throughput of sidelink

communications without incurring latency.

[0150] FIG. 8 illustrates an example of a process flow **800** in accordance with aspects of the present disclosure. The process flow **800** may implement or be implemented by aspects of the wireless communications systems **100** or **200**. For example, process flow **800** may be implemented by UEs **115-c** and **115-d**, which may each represent an example of a UE **115** described with reference to FIGS. 1 through 7. Process flow **800** may be implemented by UEs **115-c** and **115-d**, for example, to identify available resources for sidelink transmission by UE **115-c** operating in a power saving mode, as described with reference to FIGS. 2 through 7.

[0151] In the following description of the process flow **800**, the operations may be performed in a different order than the order shown, or the operations performed by UEs **115-c** and **115-d** may be performed in different orders or at different times. For example, specific operations may also be left out of the process flow **800**, or other operations may be added to the process flow **800**. Although UEs **115-c** and **115-d** are shown performing the operations of the process flow **800**, some aspects of some operations may also be performed by one or more other wireless devices.

[0152] At **805**, UE **115-c** may identify a resource reservation configuration for communicating within a resource pool allocated for sidelink communication. The resource reservation configuration may be configured at UE **115-c** (e.g., pre-loaded to UE **115-c** during manufacturing) or indicated to UE **115-c** via signaling from a base station **105**.

[0153] At **810**, UE **115-c** may transition from a first power state of a power saving mode to a second power state that consumes more power than the first power state (e.g., from a low power state to a high power state). UE **115-c** may perform the transition to the second power state after a first sensing window occurs. The first sensing window may correspond to a first resource selection window of the resource pool of the resource reservation configuration, as described with reference to FIGS. 3-7. In some examples, UE **115-c** may transition from the first power state to the second state based on receiving a resource selection trigger. The first power state may be an inactive duration (e.g., a sleep mode) of a DRX cycle, a narrow bandwidth mode of a bandwidth adaptation operation, a first resource pool monitored by UE **115-c**, or any combination thereof. The second power state may be an active duration (e.g., an ON duration) of a DRX cycle, a wide bandwidth mode of a bandwidth adaptation operation, first and second resource pools monitored by UE **115-c**, or a combination thereof.

[0154] At **815**, UE **115-c** may determine that a first subset of resources of the resource pool in the resource selection window are available for sidelink data transmission. UE **115-c** may determine that the first subset of resources are available based on transitioning from the first power state to the second power state. For example, UE **115-c** may be permitted to transmit in the first subset of resources that correspond to resources in the sensing window that UE **115-c** did not monitor while operating in the low power state.

[0155] In some examples, UE **115-c** may determine that the first subset of resources are available based on a transmission by UE **115-c**, instead of performing sensing, in one or more corresponding resources in the sensing window. Additionally or alternatively, UE **115-c** may determine that the first subset of resources are available based on monitoring one or more corresponding resources within a configured resource reservation periodicity, or based on a signal metric level associated with the first subset of resources.

[0156] At **820**, UE **115-c** may select a resource from the first subset of available resources and may transmit a sidelink data message to UE **115-d** within the resource. In some examples, UE **115-c** may transmit a sidelink control message (e.g., SCI) to UE **115-d** within the resource, and the sidelink control message may include a grant that reserves corresponding resources for one or more future sidelink data transmissions by UE **115-c** (e.g., a SCI grant scheduling a sidelink data message).

[0157] FIG. 9 shows a block diagram **900** of a device **905** in accordance with aspects of the present disclosure. The device **905** may be an example of aspects of a UE **115** as described herein. The

device **905** may include a receiver **910**, a transmitter **915**, and a communications manager **920**. The device **905** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

[0158] The receiver **910** may provide a means for receiving information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to gradual sensing for UE power saving in sidelink operation). Information may be passed on to other components of the device **905**. The receiver **910** may utilize a single antenna or a set of multiple antennas.

[0159] The transmitter **915** may provide a means for transmitting signals generated by other components of the device **905**. For example, the transmitter **915** may transmit information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to gradual sensing for UE power saving in sidelink operation). In some examples, the transmitter **915** may be co-located with a receiver **910** in a transceiver module. The transmitter **915** may utilize a single antenna or a set of multiple antennas.

[0160] The communications manager **920**, the receiver **910**, the transmitter **915**, or various combinations thereof or various components thereof may be examples of means for performing various aspects of gradual sensing for UE power saving in sidelink operation as described herein. For example, the communications manager **920**, the receiver **910**, the transmitter **915**, or various combinations or components thereof may support a method for performing one or more of the functions described herein.

[0161] In some examples, the communications manager **920**, the receiver **910**, the transmitter **915**, or various combinations or components thereof may be implemented in hardware (e.g., in communications management circuitry). The hardware may include a processor, a digital signal processor (DSP), an application-specific integrated circuit (ASIC), a field-programmable gate array (FPGA) or other programmable logic device, a discrete gate or transistor logic, discrete hardware components, or any combination thereof configured as or otherwise supporting a means for performing the functions described in the present disclosure. In some examples, a processor and memory coupled with the processor may be configured to perform one or more of the functions described herein (e.g., by executing, by the processor, instructions stored in the memory).

[0162] Additionally or alternatively, in some examples, the communications manager **920**, the receiver **910**, the transmitter **915**, or various combinations or components thereof may be implemented in code (e.g., as communications management software or firmware) executed by a processor. If implemented in code executed by a processor, the functions of the communications manager **920**, the receiver **910**, the transmitter **915**, or various combinations or components thereof may be performed by a general-purpose processor, a DSP, a central processing unit (CPU), an ASIC, an FPGA, or any combination of these or other programmable logic devices (e.g., configured as or otherwise supporting a means for performing the functions described in the present disclosure).

[0163] In some examples, the communications manager **920** may be configured to perform various operations (e.g., receiving, monitoring, transmitting) using or otherwise in cooperation with the receiver **910**, the transmitter **915**, or both. For example, the communications manager **920** may receive information from the receiver **910**, send information to the transmitter **915**, or be integrated in combination with the receiver **910**, the transmitter **915**, or both to receive information, transmit information, or perform various other operations as described herein.

[0164] The communications manager **920** may support wireless communication at a UE in accordance with examples as disclosed herein. For example, the communications manager **920** may be configured as or otherwise support a means for identifying a resource reservation configuration for communicating within a resource pool allocated for sidelink communications. The communications manager **920** may be configured as or otherwise support a means for transitioning

from a first power state to a second power state that consumes more power than the first power state after a first sensing window occurs, the first sensing window corresponding to a first resource selection window of the resource pool of the resource reservation configuration. The communications manager **920** may be configured as or otherwise support a means for determining that a first subset of resources of the resource pool in the first resource selection window are available for sidelink data transmission based on the transitioning from the first power state to the second power state.

[0165] By including or configuring the communications manager **920** in accordance with examples as described herein, the device **905** (e.g., a processor controlling or otherwise coupled to the receiver **910**, the transmitter **915**, the communications manager **920**, or a combination thereof) may support techniques for reduced processing and reduced power consumption. By operating in a low power mode until the device **905** has sidelink data to transmit, the processor may reduce power consumption. For example, the processor may refrain from performing channel sensing, may monitor a smaller bandwidth, may enter a sleep mode, or the like, during a low power state, which may result in fewer operations performed by the device **905** and correspond to reduced processing and power consumption by the processor. By identifying available resources corresponding to resources the device **905** did not monitor due to the low power state, the processor of the device **905** may refrain from processing (e.g., monitoring and performing channel measurements) on each resource in a resource pool.

[0166] FIG. **10** shows a block diagram **1000** of a device **1005** that supports gradual sensing for UE power saving in sidelink operation in accordance with aspects of the present disclosure. The device **1005** may be an example of aspects of a device **905** or a UE **115** as described herein. The device **1005** may include a receiver **1010**, a transmitter **1015**, and a communications manager **1020**. The device **1005** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

[0167] The receiver **1010** may provide a means for receiving information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to gradual sensing for UE power saving in sidelink operation). Information may be passed on to other components of the device **1005**. The receiver **1010** may utilize a single antenna or a set of multiple antennas.

[0168] The transmitter **1015** may provide a means for transmitting signals generated by other components of the device **1005**. For example, the transmitter **1015** may transmit information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to gradual sensing for UE power saving in sidelink operation). In some examples, the transmitter **1015** may be co-located with a receiver **1010** in a transceiver module. The transmitter **1015** may utilize a single antenna or a set of multiple antennas.

[0169] The device **1005**, or various components thereof, may be an example of means for performing various aspects of gradual sensing for UE power saving in sidelink operation as described herein. For example, the communications manager **1020** may include a resource reservation configuration component **1025**, a power state component **1030**, a resource selection component **1035**, or any combination thereof. The communications manager **1020** may be an example of aspects of a communications manager **920** as described herein. In some examples, the communications manager **1020**, or various components thereof, may be configured to perform various operations (e.g., receiving, monitoring, transmitting) using or otherwise in cooperation with the receiver **1010**, the transmitter **1015**, or both. For example, the communications manager **1020** may receive information from the receiver **1010**, send information to the transmitter **1015**, or be integrated in combination with the receiver **1010**, the transmitter **1015**, or both to receive information, transmit information, or perform various other operations as described herein.

[0170] The communications manager **1020** may support wireless communication at a UE in

accordance with examples as disclosed herein. The resource reservation configuration component **1025** may be configured as or otherwise support a means for identifying a resource reservation configuration for communicating within a resource pool allocated for sidelink communications. The power state component **1030** may be configured as or otherwise support a means for transitioning from a first power state to a second power state that consumes more power than the first power state after a first sensing window occurs, the first sensing window corresponding to a first resource selection window of the resource pool of the resource reservation configuration. The resource selection component **1035** may be configured as or otherwise support a means for determining that a first subset of resources of the resource pool in the first resource selection window are available for sidelink data transmission based on the transitioning from the first power state to the second power state.

[0171] FIG. **11** shows a block diagram **1100** of a communications manager **1120** in accordance with aspects of the present disclosure. The communications manager **1120** may be an example of aspects of a communications manager **920**, a communications manager **1020**, or both, as described herein. The communications manager **1120**, or various components thereof, may be an example of means for performing various aspects of gradual sensing for UE power saving in sidelink operation as described herein. For example, the communications manager **1120** may include a resource reservation configuration component **1125**, a power state component **1130**, a resource selection component **1135**, a sidelink data component **1140**, a signal metric component **1145**, a periodicity component **1150**, a sidelink grant component **1155**, a resource selection trigger component **1160**, or any combination thereof. Each of these components may communicate, directly or indirectly, with one another (e.g., via one or more buses).

[0172] The communications manager **1120** may support wireless communication at a UE in accordance with examples as disclosed herein. The resource reservation configuration component **1125** may be configured as or otherwise support a means for identifying a resource reservation configuration for communicating within a resource pool allocated for sidelink communications. The power state component **1130** may be configured as or otherwise support a means for transitioning from a first power state to a second power state that consumes more power than the first power state after a first sensing window occurs, the first sensing window corresponding to a first resource selection window of the resource pool of the resource reservation configuration. The resource selection component **1135** may be configured as or otherwise support a means for determining that a first subset of resources of the resource pool in the first resource selection window are available for sidelink data transmission based on the transitioning from the first power state to the second power state.

[0173] In some examples, the resource selection component **1135** may be configured as or otherwise support a means for selecting a resource from the first subset of resources. In some examples, the sidelink data component **1140** may be configured as or otherwise support a means for transmitting a sidelink data message within the resource.

[0174] In some examples, the resource selection component **1135** may be configured as or otherwise support a means for determining that the first subset of resources of the first resource selection window are available for sidelink data transmission based on the UE operating in the first power state during a sensing resource in the first sensing window that corresponds to the first subset of resources.

[0175] In some examples, the sidelink data component **1140** may be configured as or otherwise support a means for transmitting a sidelink data message within a second subset of resources in a second sensing window corresponding to a second resource selection window of the resource pool. In some examples, the resource selection component **1135** may be configured as or otherwise support a means for determining that a third subset of resources in the second resource selection window corresponding to the second subset of resources are available for sidelink data transmission based on the transmitting.

[0176] In some examples, the sidelink data component **1140** may be configured as or otherwise support a means for transmitting a sidelink data message within a second subset of resources in a second sensing window corresponding to a second resource selection window of the resource pool. In some examples, the resource selection component **1135** may be configured as or otherwise support a means for determining that a resource of the second resource selection window is not available for sidelink transmission based on transmitting the sidelink data message within the second subset of resources in the second sensing window.

[0177] In some examples, to support determining that the first subset of resources of the first resource selection window are available, the signal metric component **1145** may be configured as or otherwise support a means for determining that the first subset of resources of the first resource selection window are available for data transmission based on the first subset of resources being assigned a defined signal metric level. In some examples, to support determining that the first subset of resources of the first resource selection window are available, the signal metric component **1145** may be configured as or otherwise support a means for comparing a signal metric value assigned for a priority level of a sidelink data message to be transmitted in the first resource selection window with the defined signal metric level. In some examples, to support determining that the first subset of resources of the first resource selection window are available, the resource selection component **1135** may be configured as or otherwise support a means for determining that the first subset of resources of the first resource selection window are available for sidelink data transmission based on the comparing.

[0178] In some examples, the first subset of resources are assigned the defined signal metric level based on the first subset of resources corresponding to a TTI within the first sensing window within which the UE operated in the first power state.

[0179] In some examples, the signal metric component **1145** may be configured as or otherwise support a means for identifying a second resource in the first resource selection window that is available for sidelink data transmission based on the second resource having a measured signal metric level that is lower than the defined signal metric level. In some examples, the sidelink data component **1140** may be configured as or otherwise support a means for transmitting a sidelink data message in the second resource in the first resource selection window based on identifying that the measured signal metric level is lower than the defined signal metric level. In some examples, the defined signal metric level is a reference signal receive power level.

[0180] In some examples, to support identifying the resource reservation configuration, the periodicity component **1150** may be configured as or otherwise support a means for identifying the resource reservation configuration that indicates a first resource reservation periodicity that is shorter than a second resource reservation periodicity. In some examples, to support identifying the resource reservation configuration, the periodicity component **1150** may be configured as or otherwise support a means for determining that the first subset of resources of the first resource selection window are available based on monitoring a slot in the first sensing window that corresponds to the first resource reservation periodicity.

[0181] In some examples, to support determining that the first subset of resources are available, the periodicity component **1150** may be configured as or otherwise support a means for determining that the first subset of resources of the first resource selection window are available based on an instance of the second resource reservation periodicity corresponding to the first sensing window occurring when the UE is operating in the first power state.

[0182] In some examples, the sidelink grant component **1155** may be configured as or otherwise support a means for transmitting, within the first subset of resources, a first sidelink control message that includes SCI that includes a grant scheduling a first sidelink data message within the resource pool. In some examples, the sidelink data component **1140** may be configured as or otherwise support a means for transmitting the first sidelink data message based on the grant.

[0183] In some examples, to support transitioning from the first power state to the second power

state, the resource selection trigger component **1160** may be configured as or otherwise support a means for receiving a resource selection trigger. In some examples, to support transitioning from the first power state to the second power state, the power state component **1130** may be configured as or otherwise support a means for transitioning from the first power state to the second power state based on receiving the resource selection trigger.

[0184] In some examples, the first power state corresponds to a first BWP and the second power state corresponds to a second BWP that is wider than the first BWP. In some examples, the first power state corresponds to a sleep duration of a DRX cycle and the second power state corresponds to an on duration of the DRX cycle.

[0185] FIG. **12** shows a diagram of a system **1200** including a device **1205** in accordance with aspects of the present disclosure. The device **1205** may be an example of or include the components of a device **905**, a device **1005**, or a UE **115** as described herein. The device **1205** may communicate wirelessly with one or more base stations **105**, UEs **115**, or any combination thereof. The device **1205** may include components for bi-directional voice and data communications including components for transmitting and receiving communications, such as a communications manager **1220**, an input/output (I/O) controller **1210**, a transceiver **1215**, an antenna **1225**, a memory **1230**, code **1235**, and a processor **1240**. These components may be in electronic communication or otherwise coupled (e.g., operatively, communicatively, functionally, electronically, electrically) via one or more buses (e.g., a bus **1245**).

[0186] The I/O controller **1210** may manage input and output signals for the device **1205**. The I/O controller **1210** may also manage peripherals not integrated into the device **1205**. In some cases, the I/O controller **1210** may represent a physical connection or port to an external peripheral. In some cases, the I/O controller **1210** may utilize an operating system such as iOS®, ANDROID®, MS-DOS®, MS-WINDOWS®, OS/2®, UNIX®, LINUX®, or another known operating system. Additionally or alternatively, the I/O controller **1210** may represent or interact with a modem, a keyboard, a mouse, a touchscreen, or a similar device. In some cases, the I/O controller **1210** may be implemented as part of a processor, such as the processor **1240**. In some cases, a user may interact with the device **1205** via the I/O controller **1210** or via hardware components controlled by the I/O controller **1210**.

[0187] In some cases, the device **1205** may include a single antenna **1225**. However, in some other cases, the device **1205** may have more than one antenna **1225**, which may be capable of concurrently transmitting or receiving multiple wireless transmissions. The transceiver **1215** may communicate bi-directionally, via the one or more antennas **1225**, wired, or wireless links as described herein. For example, the transceiver **1215** may represent a wireless transceiver and may communicate bi-directionally with another wireless transceiver. The transceiver **1215** may also include a modem to modulate the packets, to provide the modulated packets to one or more antennas **1225** for transmission, and to demodulate packets received from the one or more antennas **1225**. The transceiver **1215**, or the transceiver **1215** and one or more antennas **1225**, may be an example of a transmitter **915**, a transmitter **1015**, a receiver **910**, a receiver **1010**, or any combination thereof or component thereof, as described herein.

[0188] The memory **1230** may include random access memory (RAM) and read-only memory (ROM). The memory **1230** may store computer-readable, computer-executable code **1235** including instructions that, when executed by the processor **1240**, cause the device **1205** to perform various functions described herein. The code **1235** may be stored in a non-transitory computer-readable medium such as system memory or another type of memory. In some cases, the code **1235** may not be directly executable by the processor **1240** but may cause a computer (e.g., when compiled and executed) to perform functions described herein. In some cases, the memory **1230** may contain, among other things, a basic I/O system (BIOS) which may control basic hardware or software operation such as the interaction with peripheral components or devices.

[0189] The processor **1240** may include an intelligent hardware device (e.g., a general-purpose

processor, a DSP, a CPU, a microcontroller, an ASIC, an FPGA, a programmable logic device, a discrete gate or transistor logic component, a discrete hardware component, or any combination thereof). In some cases, the processor **1240** may be configured to operate a memory array using a memory controller. In some other cases, a memory controller may be integrated into the processor **1240**. The processor **1240** may be configured to execute computer-readable instructions stored in a memory (e.g., the memory **1230**) to cause the device **1205** to perform various functions (e.g., functions or tasks supporting gradual sensing for UE power saving in sidelink operation). For example, the device **1205** or a component of the device **1205** may include a processor **1240** and memory **1230** coupled to the processor **1240**, the processor **1240** and memory **1230** configured to perform various functions described herein.

[0190] The communications manager **1220** may support wireless communication at a UE in accordance with examples as disclosed herein. For example, the communications manager **1220** may be configured as or otherwise support a means for identifying a resource reservation configuration for communicating within a resource pool allocated for sidelink communications. The communications manager **1220** may be configured as or otherwise support a means for transitioning from a first power state to a second power state that consumes more power than the first power state after a first sensing window occurs, the first sensing window corresponding to a first resource selection window of the resource pool of the resource reservation configuration. The communications manager **1220** may be configured as or otherwise support a means for determining that a first subset of resources of the resource pool in the first resource selection window are available for sidelink data transmission based on the transitioning from the first power state to the second power state.

[0191] By including or configuring the communications manager **1220** in accordance with examples as described herein, the device **1205** may support techniques for reduced latency, reduced power consumption, longer battery life, and improved utilization of processing capability. The device **1205** may operate in a power saving mode to reduce power consumption and improve the battery life of the device **1205**. While operating in the power saving mode, the device **1205** may avoid increased latency that may be a result of operating in a low power state by determining that resources in a resource selection window that correspond to resources the device **1205** did not monitor in a corresponding sensing window are available for sidelink transmission. The device **1205** may thereby be configured with a resource reservation configuration that may permit some potential interference to better enable the sidelink device **1205** to transition between low power states and high power states to save power without incurring significant latency.

[0192] In some examples, the communications manager **1220** may be configured to perform various operations (e.g., receiving, monitoring, transmitting) using or otherwise in cooperation with the transceiver **1215**, the one or more antennas **1225**, or any combination thereof. Although the communications manager **1220** is illustrated as a separate component, in some examples, one or more functions described with reference to the communications manager **1220** may be supported by or performed by the processor **1240**, the memory **1230**, the code **1235**, or any combination thereof. For example, the code **1235** may include instructions executable by the processor **1240** to cause the device **1205** to perform various aspects of gradual sensing for UE power saving in sidelink operation as described herein, or the processor **1240** and the memory **1230** may be otherwise configured to perform or support such operations.

[0193] FIG. **13** shows a flowchart illustrating a method **1300** in accordance with aspects of the present disclosure. The operations of the method **1300** may be implemented by a UE or its components as described herein. For example, the operations of the method **1300** may be performed by a UE **115** as described with reference to FIGS. **1** through **12**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

[0194] At **1305**, the method may include identifying a resource reservation configuration for communicating within a resource pool allocated for sidelink communications. The operations of **1305** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1305** may be performed by a resource reservation configuration component **1125** as described with reference to FIG. **11**.

[0195] At **1310**, the method may include transitioning from a first power state to a second power state that consumes more power than the first power state after a first sensing window occurs, the first sensing window corresponding to a first resource selection window of the resource pool of the resource reservation configuration. The operations of **1310** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1310** may be performed by a power state component **1130** as described with reference to FIG. **11**.

[0196] At **1315**, the method may include determining that a first subset of resources of the resource pool in the first resource selection window are available for sidelink data transmission based on the transitioning from the first power state to the second power state. The operations of **1315** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1315** may be performed by a resource selection component **1135** as described with reference to FIG. **11**.

[0197] FIG. **14** shows a flowchart illustrating a method **1400** in accordance with aspects of the present disclosure. The operations of the method **1400** may be implemented by a UE or its components as described herein. For example, the operations of the method **1400** may be performed by a UE **115** as described with reference to FIGS. **1** through **12**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

[0198] At **1405**, the method may include identifying a resource reservation configuration for communicating within a resource pool allocated for sidelink communications. The operations of **1405** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1405** may be performed by a resource reservation configuration component **1125** as described with reference to FIG. **11**.

[0199] At **1410**, the method may include transitioning from a first power state to a second power state that consumes more power than the first power state after a first sensing window occurs, the first sensing window corresponding to a first resource selection window of the resource pool of the resource reservation configuration. The operations of **1410** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1410** may be performed by a power state component **1130** as described with reference to FIG. **11**.

[0200] At **1415**, the method may include determining that a first subset of resources of the resource pool in the first resource selection window are available for sidelink data transmission based on the transitioning from the first power state to the second power state. The operations of **1415** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1415** may be performed by a resource selection component **1135** as described with reference to FIG. **11**.

[0201] At **1420**, the method may include selecting a resource from the first subset of resources. The operations of **1420** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1420** may be performed by a resource selection component **1135** as described with reference to FIG. **11**.

[0202] At **1425**, the method may include transmitting a sidelink data message within the resource. The operations of **1425** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1425** may be performed by a sidelink data component **1140** as described with reference to FIG. **11**.

[0203] FIG. **15** shows a flowchart illustrating a method **1500** in accordance with aspects of the

present disclosure. The operations of the method **1500** may be implemented by a UE or its components as described herein. For example, the operations of the method **1500** may be performed by a UE **115** as described with reference to FIGS. **1** through **12**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

[0204] At **1505**, the method may include identifying a resource reservation configuration for communicating within a resource pool allocated for sidelink communications. The operations of **1505** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1505** may be performed by a resource reservation configuration component **1125** as described with reference to FIG. **11**.

[0205] At **1510**, the method may include transitioning from a first power state to a second power state that consumes more power than the first power state after a first sensing window occurs, the first sensing window corresponding to a first resource selection window of the resource pool of the resource reservation configuration. The operations of **1510** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1510** may be performed by a power state component **1130** as described with reference to FIG. **11**.

[0206] At **1515**, the method may include determining that a first subset of resources of the resource pool in the first resource selection window are available for sidelink data transmission based on the transitioning from the first power state to the second power state. The operations of **1515** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1515** may be performed by a resource selection component **1135** as described with reference to FIG. **11**.

[0207] At **1520**, the method may include determining that the first subset of resources of the first resource selection window are available for sidelink data transmission based on the UE operating in the first power state during a sensing resource in the first sensing window that corresponds to the first subset of resources. The operations of **1520** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1520** may be performed by a resource selection component **1135** as described with reference to FIG. **11**.

[0208] FIG. **16** shows a flowchart illustrating a method **1600** in accordance with aspects of the present disclosure. The operations of the method **1600** may be implemented by a UE or its components as described herein. For example, the operations of the method **1600** may be performed by a UE **115** as described with reference to FIGS. **1** through **12**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

[0209] At **1605**, the method may include identifying a resource reservation configuration for communicating within a resource pool allocated for sidelink communications. The operations of **1605** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1605** may be performed by a resource reservation configuration component **1125** as described with reference to FIG. **11**.

[0210] At **1610**, the method may include transitioning from a first power state to a second power state that consumes more power than the first power state after a first sensing window occurs, the first sensing window corresponding to a first resource selection window of the resource pool of the resource reservation configuration. The operations of **1610** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1610** may be performed by a power state component **1130** as described with reference to FIG. **11**.

[0211] At **1615**, the method may include transmitting a sidelink data message within a second subset of resources in a second sensing window corresponding to a second resource selection window of the resource pool. The operations of **1615** may be performed in accordance with

examples as disclosed herein. In some examples, aspects of the operations of **1615** may be performed by a sidelink data component **1140** as described with reference to FIG. **11**.

[0212] At **1620**, the method may include determining that a first subset of resources of the resource pool in the first resource selection window are available for sidelink data transmission based on the transitioning from the first power state to the second power state. The operations of **1620** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1620** may be performed by a resource selection component **1135** as described with reference to FIG. **11**.

[0213] At **1625**, the method may include determining that a third subset of resources in the second resource selection window corresponding to the second subset of resources are available for sidelink data transmission based on the transmitting. The operations of **1625** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1625** may be performed by a resource selection component **1135** as described with reference to FIG. **11**.

#### SUMMARY OF ASPECTS

[0214] The following provides an overview of aspects of the present disclosure:

[0215] Aspect 1: A method for wireless communication at a UE, comprising: identifying a resource reservation configuration for communicating within a resource pool allocated for sidelink communications; transitioning from a first power state to a second power state that consumes more power than the first power state after a first sensing window occurs, the first sensing window corresponding to a first resource selection window of the resource pool of the resource reservation configuration; and determining that a first subset of resources of the resource pool in the first resource selection window are available for sidelink data transmission based at least in part on the transitioning from the first power state to the second power state.

[0216] Aspect 2: The method of aspect 1, further comprising: selecting a resource from the first subset of resources; and transmitting a sidelink data message within the resource.

[0217] Aspect 3: The method of any of aspects 1 through 2, further comprising: determining that the first subset of resources of the first resource selection window are available for sidelink data transmission based at least in part on the UE operating in the first power state during a sensing resource in the first sensing window that corresponds to the first subset of resources.

[0218] Aspect 4: The method of any of aspects 1 through 3, further comprising: transmitting a sidelink data message within a second subset of resources in a second sensing window corresponding to a second resource selection window of the resource pool; and determining that a third subset of resources in the second resource selection window corresponding to the second subset of resources are available for sidelink data transmission based at least in part on the transmitting.

[0219] Aspect 5: The method of any of aspects 1 through 3, further comprising: transmitting a sidelink data message within a second subset of resources in a second sensing window corresponding to a second resource selection window of the resource pool; and determining that a resource of the second resource selection window is not available for sidelink transmission based at least in part on transmitting the sidelink data message within the second subset of resources in the second sensing window.

[0220] Aspect 6: The method of any of aspects 1 through 3, wherein determining that the first subset of resources of the first resource selection window are available comprises: determining that the first subset of resources of the first resource selection window are available for data transmission based at least in part on the first subset of resources being assigned a defined signal metric level.

[0221] Aspect 7: The method of aspect 6, wherein determining that the first subset of resources of the first resource selection window are available comprises: comparing a signal metric value assigned for a priority level of a sidelink data message to be transmitted in the first resource selection window with the defined signal metric level; and determining that the first subset of

resources of the first resource selection window are available for sidelink data transmission based at least in part on the comparing.

[0222] Aspect 8: The method of any of aspects 6 through 7, wherein the first subset of resources are assigned the defined signal metric level based at least in part on the first subset of resources corresponding to a TTI within the first sensing window within which the UE operated in the first power state.

[0223] Aspect 9: The method of any of aspects 6 through 8, further comprising: identifying a second resource in the first resource selection window that is available for sidelink data transmission based at least in part on the second resource having a measured signal metric level that is lower than the defined signal metric level.

[0224] Aspect 10: The method of aspect 9, further comprising: transmitting a sidelink data message in the second resource in the first resource selection window based at least in part on identifying that the measured signal metric level is lower than the defined signal metric level.

[0225] Aspect 11: The method of any of aspects 6 through 10, wherein the defined signal metric level is a reference signal receive power level.

[0226] Aspect 12: The method of any of aspects 1 through 3, wherein identifying the resource reservation configuration further comprises: identifying the resource reservation configuration that indicates a first resource reservation periodicity that is shorter than a second resource reservation periodicity; determining that the first subset of resources of the first resource selection window are available based at least in part on monitoring a slot in the first sensing window that corresponds to the first resource reservation periodicity.

[0227] Aspect 13: The method of aspect 12, wherein determining that the first subset of resources are available comprises: determining that the first subset of resources of the first resource selection window are available based at least in part on an instance of the second resource reservation periodicity corresponding to the first sensing window occurring when the UE is operating in the first power state.

[0228] Aspect 14: The method of any of aspects 1 through 13, further comprising: transmitting, within the first subset of resources, a first sidelink control message that comprises sidelink control information that includes a grant scheduling a first sidelink data message within the resource pool; and transmitting the first sidelink data message based at least in part on the grant.

[0229] Aspect 15: The method of any of aspects 1 through 14, wherein the transitioning from the first power state to the second power state comprises: receiving a resource selection trigger; and transitioning from the first power state to the second power state based at least in part on receiving the resource selection trigger.

[0230] Aspect 16: The method of any of aspects 1 through 15, wherein the first power state corresponds to a first bandwidth part and the second power state corresponds to a second bandwidth part that is wider than the first bandwidth part.

[0231] Aspect 17: The method of any of aspects 1 through 16, wherein the first power state corresponds to a sleep duration of a DRX cycle and the second power state corresponds to an on duration of the DRX cycle.

[0232] Aspect 18: An apparatus for wireless communication at a UE, comprising a processor; memory coupled with the processor; and instructions stored in the memory and executable by the processor to cause the apparatus to perform a method of any of aspects 1 through 17.

[0233] Aspect 19: An apparatus for wireless communication at a UE, comprising at least one means for performing a method of any of aspects 1 through 17.

[0234] Aspect 20: A non-transitory computer-readable medium storing code for wireless communication at a UE, the code comprising instructions executable by a processor to perform a method of any of aspects 1 through 17.

[0235] It should be noted that the methods described herein describe possible implementations, and that the operations and the steps may be rearranged or otherwise modified and that other

implementations are possible. Further, aspects from two or more of the methods may be combined. [0236] Although aspects of an LTE, LTE-A, LTE-A Pro, or NR system may be described for purposes of example, and LTE, LTE-A, LTE-A Pro, or NR terminology may be used in much of the description, the techniques described herein are applicable beyond LTE, LTE-A, LTE-A Pro, or NR networks. For example, the described techniques may be applicable to various other wireless communications systems such as Ultra Mobile Broadband (UMB), Institute of Electrical and Electronics Engineers (IEEE) 802.11 (Wi-Fi), IEEE 802.16 (WiMAX), IEEE 802.20, Flash-OFDM, as well as other systems and radio technologies not explicitly mentioned herein.

[0237] Information and signals described herein may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof.

[0238] The various illustrative blocks and components described in connection with the disclosure herein may be implemented or performed with a general-purpose processor, a DSP, an ASIC, a CPU, an FPGA or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general-purpose processor may be a microprocessor, but in the alternative, the processor may be any processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices (e.g., a combination of a DSP and a microprocessor, multiple microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration).

[0239] The functions described herein may be implemented in hardware, software executed by a processor, firmware, or any combination thereof. If implemented in software executed by a processor, the functions may be stored on or transmitted over as one or more instructions or code on a computer-readable medium. Other examples and implementations are within the scope of the disclosure and appended claims. For example, due to the nature of software, functions described herein may be implemented using software executed by a processor, hardware, firmware, hardwiring, or combinations of any of these. Features implementing functions may also be physically located at various positions, including being distributed such that portions of functions are implemented at different physical locations.

[0240] Computer-readable media includes both non-transitory computer storage media and communication media including any medium that facilitates transfer of a computer program from one place to another. A non-transitory storage medium may be any available medium that may be accessed by a general-purpose or special-purpose computer. By way of example, and not limitation, non-transitory computer-readable media may include RAM, ROM, electrically erasable programmable ROM (EEPROM), flash memory, compact disk (CD) ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other non-transitory medium that may be used to carry or store desired program code means in the form of instructions or data structures and that may be accessed by a general-purpose or special-purpose computer, or a general-purpose or special-purpose processor. Also, any connection is properly termed a computer-readable medium. For example, if the software is transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, DSL, or wireless technologies such as infrared, radio, and microwave are included in the definition of computer-readable medium. Disk and disc, as used herein, include CD, laser disc, optical disc, digital versatile disc (DVD), floppy disk and Blu-ray disc where disks usually reproduce data magnetically, while discs reproduce data optically with lasers.

Combinations of the above are also included within the scope of computer-readable media.

[0241] As used herein, including in the claims, “or” as used in a list of items (e.g., a list of items

prefaced by a phrase such as “at least one of” or “one or more of”) indicates an inclusive list such that, for example, a list of at least one of A, B, or C means A or B or C or AB or AC or BC or ABC (i.e., A and B and C). Also, as used herein, the phrase “based on” shall not be construed as a reference to a closed set of conditions. For example, an example step that is described as “based on condition A” may be based on both a condition A and a condition B without departing from the scope of the present disclosure. In other words, as used herein, the phrase “based on” shall be construed in the same manner as the phrase “based at least in part on.”

[0242] In the appended figures, similar components or features may have the same reference label. Further, various components of the same type may be distinguished by following the reference label by a dash and a second label that distinguishes among the similar components. If just the first reference label is used in the specification, the description is applicable to any one of the similar components having the same first reference label irrespective of the second reference label, or other subsequent reference label.

[0243] The description set forth herein, in connection with the appended drawings, describes example configurations and does not represent all the examples that may be implemented or that are within the scope of the claims. The term “example” used herein means “serving as an example, instance, or illustration,” and not “preferred” or “advantageous over other examples.” The detailed description includes specific details for the purpose of providing an understanding of the described techniques. These techniques, however, may be practiced without these specific details. In some instances, known structures and devices are shown in block diagram form in order to avoid obscuring the concepts of the described examples.

[0244] The description herein is provided to enable a person having ordinary skill in the art to make or use the disclosure. Various modifications to the disclosure will be apparent to a person having ordinary skill in the art, and the generic principles defined herein may be applied to other variations without departing from the scope of the disclosure. Thus, the disclosure is not limited to the examples and designs described herein but is to be accorded the broadest scope consistent with the principles and novel features disclosed herein.

## Claims

1. A method for wireless communication at a user equipment (UE), comprising: identifying a resource reservation configuration for communicating within a resource pool allocated for sidelink communications; transitioning from a first power state to a second power state that consumes more power than the first power state after a first sensing window occurs, the first sensing window corresponding to a first resource selection window of the resource pool of the resource reservation configuration; and determining that a first subset of resources of the resource pool in the first resource selection window are available for sidelink data transmission based at least in part on the transitioning from the first power state to the second power state.

---