

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12412731
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Zhao; Jinrong et al.

Coil structure and plasma processing apparatus

Abstract

A coil structure includes a coil set including a first coil and a second coil. The first coil and the second coil are wound to form an annular area. A first end of the first coil and a first end of the second coil are close to an inner ring of the annular area. A second end of the first coil and a second end of the second coil are close to an outer ring of the annular area. The first end of the first coil is electrically connected to the first end of the second coil. A first projection-of the first coil on a plane perpendicular to an axial direction of the coil structure and a second projection of the second coil on the plane are mirror-symmetrical to each other.

Inventors:	Zhao; Jinrong (Beijing, CN), Zhang; Ying (Beijing, CN), Chen; Xing (Beijing, CN), Wei; Gang (Beijing, CN), Niu; Chen (Beijing, CN), Xu; Jinji (Beijing, CN), Wang; Song (Beijing, CN)
Applicant:	BEIJING NAURA MICROELECTRONICS EQUIPMENT CO., LTD. (Beijing, CN)
Family ID:	72757088
Assignee:	BEIJING NAURA MICROELECTRONICS EQUIPMENT CO., LTD. (Beijing, CN)
Appl. No.:	18/003086
Filed (or PCT Filed):	May 28, 2021
PCT No.:	PCT/CN2021/096658
PCT Pub. No.:	WO2021/258990
PCT Pub. Date:	December 30, 2021

Prior Publication Data

Document Identifier	Publication Date
----------------------------	-------------------------

Foreign Application Priority Data

CN

202010578805.X

Jun. 23, 2020

Publication Classification**Int. Cl.:** H01J37/32 (20060101); H01F5/04 (20060101)**U.S. Cl.:**

CPC H01J37/3211 (20130101); H01F5/04 (20130101); H01J2237/3343 (20130101)

Field of Classification Search**CPC:** H01J (37/321); H01J (37/3211); H01J (37/32119); H01J (37/32137); H01J (37/3222); H01J (2237/3343); H01F (5/00); H01F (5/04); C23C (16/0245); C23C (16/505); H01L (21/67063)

References Cited**U.S. PATENT DOCUMENTS**

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5716451	12/1997	Hama	118/723I	H01J 37/321
5975013	12/1998	Holland et al.	N/A	N/A
6076482	12/1999	Ding	438/758	H01J 37/32458
6534922	12/2002	Bhardwaj	315/111.21	H01J 37/321
2001/0022158	12/2000	Brcka	156/345.48	H01J 37/321
2003/0067273	12/2002	Benjamin et al.	N/A	N/A
2008/0223521	12/2007	Kim	156/345.1	H01J 37/321
2010/0066251	12/2009	Nakagami	315/111.51	H01J 37/32174
2017/0186585	12/2016	Zuo	N/A	H01J 37/3211

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
101960928	12/2010	CN	N/A
110416054	12/2018	CN	N/A
110534393	12/2018	CN	N/A
111785605	12/2019	CN	N/A
0813227	12/1996	EP	N/A
20120140084	12/2011	KR	N/A
20150122063	12/2014	KR	N/A
200833180	12/2007	TW	N/A

201405627	12/2013	TW	N/A
201833975	12/2017	TW	N/A
2007062605	12/2006	WO	N/A
WO-2011065506	12/2010	WO	C23C 16/4401
2011133562	12/2010	WO	N/A
2016201612	12/2015	WO	N/A

OTHER PUBLICATIONS

The World Intellectual Property Organization (WIPO) International Search Report for PCT/CN2021/096658 Aug. 27, 2021 6 Pages (including translation). cited by applicant

Primary Examiner: Baldwin; Gordon

Assistant Examiner: Reyes; Joshua

Attorney, Agent or Firm: ANOVA LAW GROUP, PLLC

Background/Summary

CROSS-REFERENCES TO RELATED APPLICATION APPLICATIONS

(1) This application is a national phase entry under 35 U.S.C. § 371 of International Application No. PCT/CN2021/096658, filed on May 28, 2021, which claims priority to Chinese patent application No. 202010578805.X, titled “Coil Structure and Plasma Processing Apparatus,” filed on Jun. 23, 2020 with China National Intellectual Property Administration, the entire contents of both of which is incorporated herein by reference.

TECHNICAL FIELD

(2) The present disclosure generally relates to the semiconductor technology field and, more particularly, to a coil structure and a plasma processing apparatus.

BACKGROUND

(3) With the development of integrated circuit manufacturing technology, requirements for uniformity of an etching environment are getting higher and higher. In an etching process, an upper electrode is usually configured to excite and generate plasma, and uniformity of plasma distribution determines etching uniformity. Thus, an upper electrode structure configured to generate the plasma, such as a coil structure, is very important for the uniformity of the etching process.

(4) In the existing technology, coils as shown in FIG. 1 and FIG. 2 are generally used. In FIG. 1, a coil structure includes an inner coil set and an outer coil set that are connected in parallel. The inner coil set and the outer coil set are in a planar structure. The inner coil set and the outer coil set each include two coils that are connected in parallel. A single coil is wound in involute or concentric circles. As shown in FIG. 2, the single coil is wound in an involute with 1.5 turns. As shown in FIG. 2, geometric distribution of coil winding is uneven, which causes left and right distribution of an electromagnetic field to be asymmetrical. Thus, the coil structure has different currents on the left and right. During a processing process, density distribution of free radicals and ions is caused to be asymmetrical. That is, the plasma distribution is caused to be asymmetrical. Thus, wafer etching is caused to be asymmetrical, which has negative effects on etching quality or efficiency.

SUMMARY

(5) The problem solved by the present disclosure includes that the etching quality or the etching efficiency is negatively impacted due to an uneven plasma generated by asymmetrically distributed electromagnetic field of the coil structure in left and right in the existing technology.

- (6) To solve the above problem, the present disclosure provides a coil structure applied to the plasma processing apparatus. The coil structure includes at least one coil set.
- (7) The coil set includes a first coil and a second coil. The first coil and the second coil are wound to form an annular area. A first end of the first coil and a first end of the second coil are close to an inner ring of the annular area, and a second end of the first coil and a second end of the second coil are close to an outer ring of the annular area.
- (8) The first end of the first coil is electrically connected to the first end of the second coil.
- (9) The first coil forms a first projection on a plane perpendicular to an axial direction of the coil structure. The second coil forms a second projection on a plane parallel to the axial direction of the coil structure. The first projection and the second projection are mirror-symmetrical to each other.
- (10) In some embodiments, along the axial direction of the coil structure, the first end of the first coil and the first end of the second coil are arranged at an interval in an up-down direction, and the second end of the first coil and the second end of the second coil are arranged at an interval in the up-down direction. A connection line between the first end of the first coil and the first end of the second coil is parallel to an axis of the coil structure. A connection line between the second end of the first coil and the second end of the second coil is parallel to the axis of the coil structure.
- (11) In some embodiments, the coil structure includes at least two coil sets, and first ends of first coils of the at least two coil sets are on a first plane. First ends of second coils of the at least two coil sets are on a second plane. Second ends of first coils of the at least two coil sets are on a third plane. Second ends of second coils of the at least two coil sets are on a fourth plane. A predetermined distance exists between the first plane and the second plane and between the third plane and the fourth plane.
- (12) In some embodiments, the predetermined distance is 10 mm.
- (13) In some embodiments, the first ends of the first coils of the at least two coil sets are arranged uniformly along a circumferential direction of the coil structure. The second ends of the first coils of the at least two coil sets are arranged uniformly along the circumferential direction of the coil structure.
- (14) In some embodiments, winding trajectories of the first coil and the second coil are both in an involute shape.
- (15) In some embodiments, a radial radius change amount of each turn of the first coil and/or the second coil is $a=60$ mm.
- (16) In some embodiments, a number of winding turns of the first coil and a number of winding turns of the second coil are both integer multiples of 0.5 turns.
- (17) In some embodiments, the coil structure includes an even number of coil sets.
- (18) In the coil structure of the present disclosure, the plane perpendicular to a radial direction of the coil structure is taken as the projection plane. A single coil set is taken as an example. The coil set may be formed by winding the first coil and the second coil, which are electrically connected to each other. The first projection of the first coil and the second projection of the second coil may be mirror-symmetrical to each other on the projection plane. Thus, the magnetic field and the electric field of the coil structure including at least one coil set are mirror-symmetrical. For example, the magnetic field and the electric field may be symmetrically distributed left and right. That is, a left magnetic field is same as a right magnetic field. Left and right electric fields are reversed to each other and cancel each other out. Thus, the uniform plasma is generated to effectively improve the etching quality and etching efficiency of the semiconductor process.
- (19) Moreover, the present disclosure further provides a plasma processing apparatus. The plasma processing apparatus includes the RF source, the reaction chamber, the dielectric member arranged on top of the reaction chamber, and the above coil structure. The coil structure is arranged on the dielectric member. The RF source is configured to provide RF power to the coil structure.
- (20) In some embodiments, the plasma processing apparatus further includes a connection structure. The connection structure includes a first connector and a second connector.

- (21) The second end of the first coil of each coil set is electrically connected to the first connector. The second end of the first coil of each coil set is electrically connected to the second connector; and
- (22) One of the first connector and the second connector is configured to input RF power. The other one is configured to be grounded.
- (23) In some embodiments, the first connector and the second connector are both in an annular structure. The first connector and the second connector are arranged at an interval along the axial direction of the coil structure.
- (24) In some embodiments, the connection structure further includes a third connector and a fourth connector.
- (25) The third connector is electrically connected to the first connector through a first connection bar. The fourth connector is electrically connected to the second connector through a second connection bar.
- (26) One of the third connector and the fourth connector is configured to input RF power, and the other one is configured to be grounded.
- (27) In some embodiments, the third connector and the fourth connector both have an annular structure and are arranged at an interval along the axial direction of the coil structure.
- (28) In some embodiments, a plurality of first connection bars and a plurality of second connection bars are provided. The plurality of first connection bars and the plurality of second connection bars are uniformly arranged along the circumferential direction of the coil structure.
- (29) In some embodiments, the second end of the first coil of each coil set is used as an input end. The second end of the second coil of each coil set is used as an output end. The first connector includes a first connection segment. The first connection segment is connected to the input end. Each first connection segment is connected to the input end with a number of at least one.
- (30) And/or the second connector includes a second connection segment. The second connection segment is connected to the output end. Each second connection segment is connected to the output end with a number of at least one.
- (31) In some embodiments, the coil structure includes a plurality of coil sets, the first connector includes at least two first connection segments. The at least two first connection segments are arranged at an interval along the circumferential direction to enclose to form a first contour. A number of coil sets is twice a number of first connection segments. A number of input ends connected to each first connection segment is two. The second connector includes at least two second connection segments. At least two second connection segments are arranged at an interval along the circumferential direction to enclose to form a second contour. A number of coil sets is twice a number of second connection segments. A number of output ends connected to each second connection segment is two.
- (32) In some embodiments, the first contour is annular, the second contour is annular. The first contour and the second contour are coaxial.
- (33) In some embodiments, an interval between any two neighboring first connection segments of the at least two first connection segments is same; and/or an interval between any two neighboring second connection segments of the at least two second connection segments is same.
- (34) In some embodiments, the connection structure further includes at least two first connection bars. A number of the first connection bars is same as the number of first connection segments. The first end of the first connection bar is connected to a corresponding first connection segment. The second end of the first connection bar is configured to input RF power.
- (35) And/or the connection structure further includes at least two second connection bars. A number of the second connection bars is same as the number of second connection segments. The first end of the second connection bar is connected to a corresponding second connection segment. The second end of the second connection bar is configured to be grounded. In some embodiments, second ends of the at least two first connection bars are connected to a first point, and the first point

is used as a power input end configured to input RF power; and/or second ends of the at least two second connection bars are connected to a second point, and the second point is used as a ground end configured to be grounded.

(36) In some embodiments, two ends of the first connection segment are electrically connected to the input ends, respectively. A connection position of the first connection bar and the first connection segment is located at a middle position of the first connection segment along a length direction.

(37) And/or two ends of the second connection segment are electrically connected to the output ends, respectively. A connection position of the second connection bar and the second connection segment is located at a middle position of the second connection segment along the length direction.

(38) In some embodiments, at least two coil structures are provided. The at least two coil structures are sleeved at an interval in a radial direction, or the at least two coil structures are arranged at the interval along the axial direction, and along the axial direction, radial dimensions of the at least two coil structures gradually increase or decrease.

(39) In the coil structure applied to the plasma processing apparatus of embodiments of the present disclosure, the plane perpendicular to the axial direction of the coil structure is used as a projection plane and take a single coil set as an example, the coil set is formed by winding the first coil and the second coil that are electrically connected with each other. The first projection of the first coil and the second projection of the second coil may be mirror-symmetrical to each other on the same projection. The magnetic field and electric field distribution formed by the coil structure including the coil set are mirror-symmetrical, for example, the magnetic field and the electric field are left and right symmetrically distributed. That is, the left and right magnetic fields are the same, and the left and right electric fields cancel each other in opposite directions. Thus, uniformly distributed plasma is generated to effectively improve the etching quality and etching efficiency of the semiconductor process.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) In order to describe the technical solution of embodiments of the present disclosure or in the background technology more clearly, the following briefly introduces the accompanying drawings that are used in the description of embodiments or the background technology. Obviously, the drawings described below are merely some embodiments of the present disclosure. For those of ordinary skill in the art, other drawings can also be obtained according to these drawings without any creative effort.

(2) FIG. 1 is a schematic structural diagram of a coil in the existing technology.

(3) FIG. 2 is a schematic distribution diagram of a magnetic field of a single coil in a coil structure in the existing technology.

(4) FIG. 3 is a schematic perspective diagram of a coil set of a coil structure according to some embodiments of the present disclosure.

(5) FIG. 4 is a schematic top view of FIG. 3 and schematically shows a magnetic field distribution.

(6) FIG. 5 is a schematic top view of a coil structure including six coil sets.

(7) FIG. 6 is a schematic top view of six first coils in the coil structure in FIG. 5.

(8) FIG. 7 is a schematic top view of six second coils in the coil structure in FIG. 5.

(9) FIG. 8 is a schematic top view of a coil structure including eight coil sets.

(10) FIG. 9 is a schematic top view of eight first coils in the coil structure in FIG. 8.

(11) FIG. 10 is a schematic top view of eight second coils in the coil structure in FIG. 8.

(12) FIG. 11 is a schematic top view of a coil structure including four coil sets.

- (13) FIG. 12 is a schematic top view of four first coils in the coil structure in FIG. 11.
- (14) FIG. 13 is a schematic top view of four second coils in the coil structure in FIG. 11.
- (15) FIG. 14 is a schematic diagram of another coil set of a coil structure according to some embodiments of the present disclosure.
- (16) FIG. 15 is a schematic top view of FIG. 14 and shows a magnetic distribution diagram.
- (17) FIG. 16 is a schematic top view of a coil structure including six coil sets when both a first coil and a second coil have 0.5 turns according to some embodiments of the present disclosure.
- (18) FIG. 17 is a schematic top view of six first coils in the coil structure in FIG. 16.
- (19) FIG. 18 is a schematic top view of six first coils in the coil structure in FIG. 16.
- (20) FIG. 19 is a first schematic diagram of a plasma processing apparatus provided with a connection structure and a coil structure according to some embodiments of the present disclosure.
- (21) FIG. 20 is a second schematic diagram of a plasma processing apparatus provided with two connection structures and two coil structures with the two coil structures being sleeved along a radial direction at an interval according to some embodiments of the present disclosure.
- (22) FIG. 21 is a third schematic diagram of a plasma processing apparatus being provided with two connection structures and two coil structures with the two coil structures being arranged along an axial direction at an interval according to some embodiments of the present disclosure.
- (23) FIG. 22 is a schematic perspective diagram of a coil structure when a connector of a connection structure is a closed ring according to some embodiments of the present disclosure.
- (24) FIG. 23 is a schematic top view of FIG. 22.
- (25) FIG. 24 is a schematic main view of FIG. 22.
- (26) FIG. 25 is a schematic top view of a total assembly of a coil structure adopting the connection structure of FIG. 22 according to some embodiments of the present disclosure.
- (27) FIG. 26 is a schematic diagram of a coil structure when a first connector of a connection structure is a closed ring, and a second end of a first connection bar is connected to a point according to some embodiments of the present disclosure.
- (28) FIG. 27 is a schematic diagram of magnetic field distribution of a coil of the plasma processing apparatus in FIG. 19 with a first connector and a second connector of the connection structure being closed rings.
- (29) FIG. 28 is a schematic diagram of a magnetic amplitude value distribution in the plasma processing apparatus in FIG. 27.
- (30) FIG. 29 is a schematic diagram of magnetic field distribution of the plasma processing apparatus in FIG. 20 with a first connector and a second connector of the two connection structures being closed rings.
- (31) FIG. 30 is a schematic diagram showing magnetic field amplitude value distribution in the plasma processing apparatus in FIG. 29.
- (32) FIG. 31 is a schematic top view showing the coil magnetic field distribution in FIG. 29.
- (33) FIG. 32 is a schematic perspective structural diagram of a coil structure when a connector of a connection structure is a connection segment according to some embodiments of the present disclosure.
- (34) FIG. 33 is a schematic main view of FIG. 32.
- (35) FIG. 34 is a schematic diagram of a coil structure when a first connector of a connection structure is a connection segment, and a second end of a first connection bar is connected to a point according to some embodiments of the present disclosure.
- (36) FIG. 35 is a schematic diagram showing connection between an upper layer coil in FIG. 17 and the first connector in FIG. 34.
- (37) FIG. 36 is a schematic diagram showing coil magnetic field distribution of the plasma processing apparatus in FIG. 19 when the first connector and the second connector of the connection structure are connection segments.
- (38) FIG. 37 is a schematic diagram showing the magnetic field amplitude value distribution in the

plasma processing apparatus in FIG. 36.

(39) FIG. 38 is a schematic diagram showing coil magnetic field distribution of the plasma processing apparatus in FIG. 20 when the first connector and the second connector of the connection structure are connection segments.

(40) FIG. 39 is a schematic diagram showing the magnetic field amplitude value distribution of the plasma processing apparatus in FIG. 38.

(41) FIG. 40 is a schematic top view showing the coil magnetic field distribution in FIG. 38.

(42) TABLE-US-00001 Reference numerals: 10 Coil structure; 100 Coil set; 110 First coil; 120 Second coil; 130 Vertical connection bar; 140 External coil set; 150 Internal coil set; 111 First end of first coil; 112 Second end of first coil; 121 First end of second coil; 122 Second end of second coil; 200 Connection structure; 210 First connector; 220 Second connector; 230 Third connector; 240 Fourth connector; 250 First connection bar; 260 Second connection bar; 270 Power input end; 280 Ground end; 201 External connection structure; 202 Internal connection structure; 211 First wire connector; 212 First connection segment; 213 First contour; 221 Second wire connector; 222 Second connection segment; 223 Second contour; 300 Reaction chamber; 310 Inner liner; 320 Support base; 330 Chamber edge; 340 Continuous magnetic field; 400 Dielectric member; 500 Shield cover; 600 Matcher; 700 Radio frequency source; 910 Outer ring assembly; 920 Inner ring assembly; 930 Inner ring magnetic field; 940 Outer ring magnetic field.

DETAILED DESCRIPTION OF THE EMBODIMENTS

(43) In order to make the above objects, features, and advantages of the present disclosure more clearly understood, specific embodiments of the present disclosure are described in detail below with reference to the accompanying drawings. It should be understood that the specific embodiments described herein are only used to explain the present disclosure, but not to limit the present disclosure.

(44) Embodiments of the present disclosure provide a coil structure, for example, a coil structure 10 shown in FIG. 19, which is configured in a plasma processing apparatus. The plasma processing apparatus may be configured to perform an etching process on a semiconductor workpiece such as a wafer. The coil structure 10 may be used as an upper electrode to excite and generate a plasma.

(45) The coil structure 10 includes at least one coil set 100. As shown in FIG. 3 and FIG. 4, the coil set 100 includes a first coil 110 and a second coil 120. The first coil 110 and the second coil 120 are wound to form an annular area. A first end 111 of the first coil and a first end 121 of the second coil gradually approach an inner ring of the annular area. A second end 112 of the first coil and a second end 122 of the second coil gradually approach an outer inner ring of the annular area. The first end 111 of the first coil may be electrically connected to the first end 121 of the second coil. The first coil 110 may form a first projection on a plane perpendicular to an axial direction of the coil structure 10. The second coil 120 may form a second projection on the plane perpendicular to the axial direction of the coil structure 10. The first projection and the second projection may be mirror-symmetrical to each other.

(46) The annular area, as shown in FIG. 3 and FIG. 4, is formed by winding the first coil 110 and the second coil 120 and is an area where an entire coil structure 10 including at least one coil set is located. Specifically, as shown in an area indicated by dotted lines in FIG. 5 to FIG. 13, FIG. 16 to FIG. 18, and FIG. 25, in the above coil structures, a plurality of first coils 110 and a plurality of second coils 120 are wound to form an annular area, such as areas indicated by the dotted lines in FIG. 5 (coil structure 10 including six coil sets), FIG. 8 (coil structure 10 including eight coil sets), FIG. 16 (coil structure 10 including six coil sets), and FIG. 11 (including four coil sets). The first end 111 of the first coil 110 and the first end 121 of the second coil gradually approach the inner ring of the annular area. The second end 112 of the first coil 110 and the second end 122 of the second coil 120 gradually approach the outer ring of the annular area.

(47) In the coil structure 10 used in embodiments of the present disclosure, a plane perpendicular to the axial direction of the coil structure 10 may be used as a projection plane. Take a single coil set

100 as an example, the coil set **100** may be formed by winding the first coil **110** and the second coil **120**, which are electrically connected to each other. The first projection of the first coil **110** on the projection plane and the second projection of the second coil **120** on the projection plane may be mirror-symmetrical to each other on the projection plane. Thus, distributions of a magnetic field and an electric field formed by the coil set **100** may be mirror-symmetrical. For example, the magnetic field and electric field may be distributed symmetrically to the left and right. That is, left and right magnetic fields may be the same, and left and right electric fields cancel each other in opposite directions. Thus, a uniform plasma may be generated, which reduces or eliminates negative effects on the etching quality and etching efficiency of the semiconductor caused by the uneven plasma distribution in the existing technology. Thus, the etching quality and the etching efficiency of the semiconductor may be effectively improved.

(48) FIG. 3 takes as an example that both the first coil **110** and the second coil **120** are wound with one turn. The present disclosure is not limited to this. Preferably, a number of winding turns of the first coil **110** and the second coil **120** are both integer multiples of 0.5 turns. The number of turns wound by an integer multiple of 0.5 turns may facilitate processing, cause a winding manner to be more convenient and flexible, and be more beneficial to realizing the symmetrical distribution of the magnetic field and the electric field. Specifically, as shown in FIG. 14, numbers of the winding turns of the first coil **110** and the second coil **120** are both 0.5 turns.

(49) In the present disclosure, winding trajectories of the first coil **110** and the second coil **120** may be in various ways, for example, may be both in a spiral form or an involute form as shown in FIG. 3 to FIG. 18. The annular area formed after the coil set **100** is wound can be a circular ring, an elliptical ring, a rectangular ring, a polygonal ring, etc. Due to axial position changes of the first coil **110** and the second coil **120** during the winding process, the annular area formed by winding the first coil **110** and the second coil **120** may have a certain thickness along the axial direction. The projection on a plane along the axial direction may be in an annular shape.

(50) In addition, since the two ends of the first coil **110** gradually approach the inner and outer rings of the annular area, and the two ends of the second coil **120** gradually approach the inner and outer rings of the annular area, it can be seen that the first coil **110** and the second coil **120** are variable diameter coils with an axis center of the annular area as a center. With such an arrangement, when the coil structure **10** includes a plurality of sets of coil sets **100** that are connected in parallel, interference among the coil sets can be prevented.

(51) Specifically, as shown in FIG. 4, in the coil set **100**, the winding trajectories of the first coil **110** and the second coil **120** are both in an involute shape. A radius change amount of each turn of the first coil **110** and the second coil **120** may be set to $a=60$ mm in a radial direction (i.e., radial distance between two turns), and a coil width may be set to $b=4$ mm. A cross symbol in the figure may represent a magnetic field direction and relative size and distribution at a certain time, which is distributed symmetrically in the left and right. The radial electric field distribution is shown by arrows in the figure, which cancels each other out with equal sizes and opposite directions.

(52) It should be noted that, in embodiments of the present disclosure, for an electrical connection position between the first coil **110** and the second coil **120**, besides the above electrical connection between the first end **111** of the first coil and the first end **121** of the second coil, the second end **112** of the first coil may be electrically connected to the second end **122** of the second coil.

(53) In embodiments of the present disclosure, the first coil **110** and the second coil **120** of the coil set **100** may be arranged in an up-down direction at an interval. With such an arrangement, capacitive coupling between the upper and lower layers of coils may be reduced. In addition, arranging the first coil **110** and the second coil **120** at the interval may not only facilitate the winding of a single coil set **100**, but also facilitate the winding of a plurality of coil sets **100** to avoid interference between the coil sets. Such an arrangement not only can facilitate the electrical connection between the first coil **110** and the second coil **120** but also can facilitate the setting of a frequency feeding position and a grounding position.

(54) With reference to FIG. 3 and FIG. 14, in embodiments of the present disclosure, along an axial direction of the coil structure **10**, in the coil set **100**, the first end **111** of the first coil and the first end **121** of the second coil are arranged at an interval in the up-down direction. The second end **112** of the first coil and the second end **122** of the second coil are arranged at an interval in the up-down direction. A connection line between the first end **111** of the first coil and the first end **121** of the second coil may be parallel to the axis of the coil structure **10**. A connection line between the second end **112** of the first coil and the second end **122** of the second coil may be parallel to the axis of the coil structure **10**. Specifically, in embodiments of the present disclosure, as shown in FIG. 3 and FIG. 14, a connection manner between the first coil **110** and the second coil **120** is that the first end **111** of the first coil and the first end **121** of the second coil are connected by a vertical connection bar **130**. The vertical connection bar **130** may be parallel to the axial direction of the coil structure **10**. Thus, the electrical connection between the first coil **110** and the second coil **120** may be realized, and the connection method may have advantages that the connection is simple and effective.

(55) In embodiments of the present disclosure, an axial distance between the first coil **110** and the second coil **120** in an up-down direction may be adjustable. Specifically, by changing an effective connection length of the vertical connection bar **130** between the first coil **110** and the second coil **120**, the axial distance between the first coil **110** and the second coil **120** in the up-down direction may be changed. Thus, the capacitive coupling between the upper and lower layers of the coils may be adjusted to further reduce the interference between the coil sets **100**.

(56) In embodiments of the present disclosure, the first coil **110** and the second coil **120** are both helical coils and both are wound spirally upward or downward along the axial direction of the coil set **100**. That is, the two ends of the first coil **110** may be on different planes after the first coil **110** is wound, and the two ends of the second coil **120** may be on different planes after the second coil **120** is wound. Specifically, as shown in FIG. 5 to FIG. 13, FIG. 16 to FIG. 18, and FIG. 25, the coil structure **10** includes at least two coil sets **100**. The first ends **111** of the first coils of the at least two coil sets **100** are both on a first plane. The first ends **121** of the second coils of the at least two coil sets are both on a second plane. The second ends **112** of the first coils of the at least two coil sets **100** are both on a third plane. The second ends **122** of the second coils of the at least two coil sets **100** are both on a fourth plane. A predetermined distance may exist between the first plane and the second plane (as shown in FIG. 3, h is the predetermined distance). The predetermined distance may also exist between the third plane and the fourth plane. The predetermined distance may be the distance between the first coil **110** and the second coil **120** of the coil set **100**. By setting the predetermined distance, the capacitive coupling between the two layers of coils may be reduced. Preferably, the predetermined distance may be set to 10 mm, as shown in FIG. 3, $h=10$ mm.

(57) With reference to FIG. 3, a number of winding turns of the first coil **110** and the second coil **120** of the coil set **100** is one turn. The first coil **110** descends spirally from the first end to the second end. The second coil **120** also spirally descends from the first end to the second end. The first end **111** of the first coil and the first end **121** of the second coil may be electrically connected through the vertical connection bar **130**. The vertical connection bar **130** and the connection line between the second end **112** of the first coil and the second end **122** of the second coil may be parallel to the axial direction of the coil structure **10**. The first end **111** of the first coil may be located on the first plane. The second end **112** of the first coil may be located on the third plane. The first end **121** of the second coil may be located on the second plane. The second end **122** of the second coil may be located on the fourth plane. The four planes are located at different positions. A distance (i.e., the predetermined distance) between the first plane and the third plane may be equal to a distance between the second plane and the fourth plane.

(58) With reference to FIG. 14, numbers of winding turns of the first coil **110** and the second coil **120** of the coil set **100** are both 0.5 turns. The first coil **110** spirally descends from the first end to the second end. The second coil **120** spirally ascends from the first end to the second end. The first

end **111** of the first coil and the first end **121** of the second coil may be electrically connected through the vertical connection bar **130**. The vertical connection bar **130** and the connection line between the second end **112** of the first coil and the second end **122** of the second coil may be parallel to the axial direction of the coil structure **10**. The first end **111** of the first coil is located on the first plane. The second end **112** of the first coil is located on the third plane. The first end **121** of the second coil is located on the second plane. The second end **122** of the second coil is located on the fourth plane. The first plane and the fourth plane are coplanar. The second plane and the third plane are coplanar. Thus, the predetermined distance between the first plane and the third plane is equal to the predetermined distance between the second plane and the fourth plane. FIG. **15** is a schematic top view and a magnetic field distribution diagram of the coil set **100**.

(59) In addition to the first end and the second end of different coil sets in the coil structure **10** being located on the first plane and the second plane, respectively, when the coil structure **10** includes the at least two parallelly-connected coil sets **100**, the at least two coil sets **100** may also be arranged along the axial direction of the coil structure **10** at intervals. First ends of different coil sets **100** may be located at different heights in the axial direction, and second ends may be located at different heights in the axial direction. Thus, the capacitive coupling between different coils may be reduced, and the interference formed by the winding process of different coil sets **100** may be reduced. Specifically, along the axial direction of the coil structure **10**, the axial distance between neighboring coil sets may be adjustable. A distributed capacitance may exist between the first coil and the second coil of the plurality of coil sets. A capacitance value may be related to the distance between the two layers of coils. The first coil and the second coil may be set with an adjustable distance. By adjusting the distance of the two layers, the distributed capacitance may be adjusted. Thus, a coil resonance frequency and a coil inductance value of the coil structure **10** may be adjusted. In addition, during the winding process, the axial distance of the coil sets may be adjusted according to the capacitive coupling requirements and the connection position requirements of the coil sets and the connection structure. Thus, the applicability of the coil structure **10** may be improved.

(60) In embodiments of the present disclosure, as shown in FIG. **5** to FIG. **13**, FIG. **16** to FIG. **18**, and FIG. **25**, in the at least two coil sets **100** of the coil structure **10**, the first ends **111** of the first coils of the coil sets **100** are uniformly arranged along a circumferential direction of the coil structure **10**. The second ends **112** of the first coils of the coil sets **100** are uniformly arranged along the circumferential direction of the coil structure **10**. In the coil structure **10**, the first end of the second coil **120** is connected to the first end of the first coil **110**. The first ends **121** of the second coils and the second ends **122** of the second coils are also uniformly arranged along the circumferential direction of the coil structure **10** to ensure an angular symmetry of plasma distribution generated by the coil structure **10**. The more the coil sets **100** are provided, the better the angular symmetry of the plasma distribution is, and the more uniform the plasma distribution is. Preferably, the coil structure **10** may include an even number of coil sets, specifically four sets (as shown in FIG. **11** to FIG. **13**), six sets (as shown in FIG. **5** to FIG. **7**, FIG. **16** to FIG. **18**, and FIG. **25**), or eight sets (as shown in FIGS. **8** to **10**) of coil sets **100**.

(61) The coil structure **10** may include four coil sets. As shown in FIG. **11** to FIG. **13**, the coil structure **10** is formed and wound by electrically connecting the four coil sets **100** in parallel. Four first coils **110** are included and are angularly symmetrical at 90°. Four second coils **120** are included and are angularly symmetrical at 90°. The coil structure **10** may include six coil sets. As shown in FIG. **5** to FIG. **7**, FIG. **16** to FIG. **18**, and FIG. **25**, the coil structure **10** is formed and wound by electrically connecting the six coil sets in parallel. Six first coils **110** are included and are angularly symmetrical at 60°. Six second coils **120** are provided and are angularly symmetrical at 60°. The coil structure **10** may include eight coil sets. As shown in FIG. **8** to FIG. **10**, the coil structure **10** is formed by electrically connecting eight coil sets **100** in parallel. Eight first coils **110** are provided and are angularly symmetrical at 45°. Eight second coils **120** are

provided and are angularly symmetrical at 45°. In all the above coil structures **10**, on a projection plane perpendicular to the axial direction of the coil structure **10**, the first projection of the first coil **110** is mirror-symmetrical to the second projection of the second coil **120** of the coil sets **100**. Thus, the magnetic field and electric field of the coil sets **100** may be ensured to be symmetrically distributed at left and right. Along the circumferential direction of the coil structure **10**, the six coil sets **100** may be arranged uniformly at an interval of 60°. Thus, the magnetic field and electric field of the plurality of coil sets **100** may be uniformly distributed along the circumferential direction of the coil structure **10**. Thus, the plasma generated by the coil structure **10** may be ensured to be distributed uniformly.

(62) Specifically, in embodiments of the present disclosure, longitudinal cross-sectional shapes of the first coil **110** and the second coil **120** may be selected as a rectangle. In addition, the longitudinal cross-sectional shape of the first coil **110** and the second coil **120** may also be selected as a ring or a circle, that is, a hollow coil or a solid coil, which is not limited in the present disclosure. The coil has the advantages of easy material availability and strong applicability.

(63) Embodiments of the present disclosure further provide a plasma processing apparatus. As shown in FIG. **19**, the plasma processing apparatus includes a radio frequency (RF) source **700**, a reaction chamber **300**, a dielectric member **400** arranged on the top of the reaction chamber **300**, and the coil structure **10** of the above embodiments. The coil structure **10** including at least one coil set **100** may be arranged on the dielectric member **400**. The radio frequency source **700** may be configured to provide RF power to the coil structure **10**. Since the plasma processing apparatus has the above coil structure **10**, the plasma processing apparatus may have all the beneficial effects of the above coil structure **10**, which is not repeated here.

(64) Optionally, in embodiments of the present disclosure, as shown in FIG. **19** to FIG. **25**, the plasma processing apparatus further includes a connection structure **200**. The connection structure **200** includes a first connection member **210** and a second connection member **220**. The second end **112** of the first coil **110** in each coil set **100** may be electrically connected to the first connector **210**. The second end **122** of the second coil **120** in each coil set **100** may be electrically connected to the second connector **220**. One of the first connector **210** and the second connector **220** may be configured to input RF power. The other one may be configured to be grounded. With such an arrangement, a complete circuit path may be formed to complete the plasma generation process. Specifically, the first connector **210** may be connected between the second end **112** of the first coil **110** and the RF source **700**. The second connector **220** may be connected between the second end **122** of the second coil and the ground. The RF source may be configured to provide RF energy to the coil structure **10** through the first connector **210**. A coil magnetic field (induced magnetic field formed by the coil structure **10**) may be generated in the reaction chamber by the coil structure **10** to generate the plasma.

(65) In the plasma processing apparatus of embodiments of the present disclosure, at least two coil structures **100** may be provided. A number of connection structures **200** may be equal to the number of coil structures **10**. The connection structure **200** may be electrically connected to one of the coil structures **10**. As shown in FIG. **20**, the at least two coil structures **10** may be sleeved at an interval along the radial direction. That is, all the coil sets of a single coil structure **10** may form a complete coil. Complete coils of different coil structures **10** may be approximately at a same height and are sleeved in sequence. Alternatively, as shown in FIG. **21**, the at least two coil structures **10** are arranged at an interval along the axial direction. Along the axial direction, radial dimensions of the at least two coil structures **10** gradually increase or decrease. All coil sets of the single coil structure **10** may form a complete coil. Complete coils of different coil structures **10** may be arranged approximately coaxially and are located at different heights. Along the axial direction, a radial dimension of the complete coil may increase gradually or decrease gradually to form a structure in an approximately conical shape. During the processing process, the connection structures **200** may be connected to the coil structures **10** in a one-to-one correspondence. The RF

source **700** may provide RF energy to the plurality of complete coils through the plurality of connection structures **200**. Thus, the coil magnetic fields generated by the plurality of complete coils may be coupled to obtain a coupled induction magnetic field with a higher magnetic field amplitude and a larger magnetic radial continuous distribution range. Thus, the density and distribution uniformity of the plasma generated in the reaction chamber **300** may be further improved. Correspondingly, productivity and uniformity of using the plasma to perform processing on the product may be further improved. In addition, by using the arrangement manner along the radial direction or the circumferential direction at intervals, the interference between neighboring coil structures **10** may be effectively reduced to ensure the arrangement of the plurality of coil structures **10**. Specifically, two or three coil structures **10** may be provided. A number of corresponding connection structures may be the same as the number of the coil structures **10**. The arrangement manner may be adjusted according to the shapes of the corresponding coil structures **10**. Thus, the RF may be ensured to be fed uniformly, and the plurality of coil structures **10** may be connected in parallel. The plurality of coil sets of each coil structure **10** may be connected in parallel. Thus, the uniformity of the electromagnetic field generated by the coupling of the coil structure **10** may be further improved.

(66) With reference to FIG. **22** to FIG. **25**, specifically, the first connector **210** and the second connector **220** are both annular structures with a certain thickness. The first connector **210** and the second connector **220** may be arranged at an interval along the axial direction of the coil structure **10**. With such an arrangement, the plurality of first connection member **211** may be arranged through the first connector **210**. The plurality of first connection member **211** may be connected to the second ends **112** of the first coils **110** in the plurality of coil sets **100**. The plurality of second connection member **221** may be arranged through the second connector **220**. By connecting the second ends **122** of the second coils **120** in the plurality of coil sets **100** may be connected. Thus, the plurality of coil sets **100** including the first coils **110** and the second coils **120** may be connected in parallel. In embodiments of the present disclosure, preferably, the number of the first connection members **211** provided on the first connector **210** and the number of the second connection members **221** provided on the second connector **220** may be the same as the number of the coil sets. As shown in FIG. **25**, the coil structure **10** includes six coil sets, including six first coils **110** and six second coils **120**. Correspondingly, six first connection members **211** may be provided and may be electrically connected to the second ends **112** of the six first coils **110** in a one-to-one correspondence. Six second connection members **221** may be provided and electrically connected to the second ends **122** of the six second coils **120**. The connection structure may have advantages of being simple, convenient, and effective.

(67) It should be noted that the radial dimensions of the first connector **210** and the second connector **220** may be equal or unequal. For example, the radial dimension of the first connector **210** may be larger than the radial dimension of the second connector **220**. When the radial dimensions of the first connector **210** and the second connector **220** are not equal, the first connector **210** and the second connector **220** may be located in the same plane.

(68) With reference to FIG. **22** to FIG. **25**, in the coil structure **10**, the connection structure **200** further includes a third connector **230** and a fourth connector **240**. The third connector **230** may be electrically connected to the first connector **210** through the first connection bar **250**. The fourth connector **240** may be electrically connected to the second connector **220** through the second connection bar **260**. The third connector **230** includes a power input end **270** configured to input RF power. The fourth connector **240** includes a ground end **280**, which is configured to be grounded. With such an arrangement, a complete circuit path may be formed. Thus, the plasma generation process may be completed. It should be noted that, in addition to arranging the power input end **270** on the third connector **230** and arranging the ground end **280** on the fourth connector **240**, the power input end **270** may also be arranged on the fourth connector **240**. The ground end **280** may be arranged on the third connector **230**, which is not limited herein.

(69) Specifically, as shown in FIG. 22 to FIG. 25, in embodiments of the present disclosure, the third connector **230** and the fourth connector **240** are both arranged as annular structures. The third connector **230** and the fourth connector **240** are arranged at an interval along the axial direction of the coil structure **10**. The third connector **230** and the fourth connector may be located above the first connector **210** and the second connector **220**. The third connector **230** is located above the fourth connector **240**. One end of the first connection bar **250** is electrically connected to the first connector **210**, and the other end is electrically connected to the third connector **230**. Thus, the electrical connection between the first connector **210** and the third connector **230** may be achieved. One end may be electrically connected to the second connector **220**. The other end may be electrically connected to the fourth connector **240**. Thus, the electrical connection between the second connector **220** and the fourth connector **240** may be realized. It can be seen from FIG. 22 to FIG. 25, with such an arrangement, the second connector **220**, the second connection bar **260**, and the fourth connector **240** may be covered by an area enclosed by the first connector **210**, the first connection bar **250**, and the third connector **230**. Thus, the interference between the connectors and the connection bars may be avoided without the need to perform, for example, a bending process on the connectors and connection bars.

(70) It needs to be noted that, in embodiments of the present disclosure, a plurality of first connection bars **250** and a plurality of second connection bars **260** may be provided. The plurality of first connection bars **250** and the plurality of second connection bars **260** may be uniformly arranged along the circumferential direction of the coil structure **10**. As shown in FIG. 22 to FIG. 25, three first connection bars **250** and three second connection bars **260** are provided. That is, along the circumferential direction of the first connector **210** or the second connector **220**, an angle between neighboring connection bars may be 120°. The connection bars may be in an inverted “L” shape, which can be obtained by simply bending, and has the advantages of simple structure and low production cost. The protected solution of the present disclosure is not limited to this. A connection bar of another arrangement form may also be used, as long as having the connection functions of the above connection bars, and the connection bar is within the scope of the present disclosure.

(71) Optionally, in embodiments of the present disclosure, the connection structure **200** may not be provided with the third connector **230** and the fourth connector **240**. As shown in FIG. 25 and FIG. 26, ends of the plurality of first connection bars **250** are electrically connected to the first connector **210**, and the other ends are connected to a point as a power input end **270**, which is configured to input RF power. Ends of the plurality of second connection bars **250** are electrically connected to the second connector **220**, and the other ends are connected to a point as a ground end **280**, which is configured to be grounded.

(72) In addition to the above closed ring form, the connector of the connection structure **200** may also adopt a form of a connection segment. As shown in FIG. 32 to FIG. 40, the connection structure is applied to the electrical connection of the coil set **100** with the RF source **700** and the ground in the plasma processing apparatus. The second end **112** of the first coil in each coil set **100** may be set as an input end. The second end **122** of the second coil may be set as an output end. The first connector **210** of embodiments of the present disclosure may include the first connection segment **212**. The first connection segment **212** may be connected to the input end. A number of input ends connected to each first connection segment **212** may be at least one. The second connector **220** may include a second connection segment **222**. The second connection segment **222** may be connected to the output end. A number of output ends connected to each second connection segment **222** may be at least one. The connection structure with such the connection form may be applied to the plasma processing apparatus. The first connection segment **212** of the first connector **210** may be connected between the input end of the coil set **100** and the RF source **700**. The second connection segment **222** of the second connector **220** may be connected between the output end of the coil set **100** and ground. The RF source **700** may provide RF energy to the coil structure **10**

through the first connection segment **212**. The coil structure **10** may generate the coil magnetic field. Since the first connection segment **212** and the second connection segment **222** are in a state that two ends are disconnected, the first connector **210** and the second connector **220** corresponding to the first connection segment **212** and the connection segment **222** may be in an unclosed ring shape. Thus, the first connector **210** and the second connector **220** may not be induced to generate reverse current opposite to a current direction of the coil structure **10** under the action of the coil magnetic field. Correspondingly, the first connector **210** and the second connector **220** may not generate a reverse induced magnetic field that can weaken the coil magnetic field and may not block the coil magnetic field. Thus, the radial continuous distribution range of the magnetic field amplitude value and magnetic field may be ensured to further improve the density and uniformity of the plasma generated in the reaction chamber **300**. Correspondingly, the productivity and uniformity of using the plasma to perform processing on the product may be ensured.

(73) Of course, in other embodiments of the present disclosure, only one of the first connector **210** and the second connector **220** may have the form of the connection segment. The RF source **700** may provide RF energy to the coil structure **10** through the connector. The connector may not generate a reverse current that is opposite to the current direction of the coil structure **10**, correspondingly, may not generate a reverse induced magnetic field that can weaken the coil magnetic field, and may not block the coil magnetic field. Thus, the weakening effect of the connection structure to the coil magnetic field may be effectively reduced, and correspondingly the magnetic amplitude value of the coil magnetic field may be improved to further improve the density of the plasma in the reaction chamber.

(74) Optionally, as shown in FIG. **32** and FIG. **33**, in the plasma processing apparatus of embodiments of the present disclosure, the coil structure **10** includes a plurality of coil sets **100**. The first connector **210** includes at least two first connection segments **212**. The at least two first connection segments **212** are arranged at intervals along the circumferential direction to enclose to form a first contour **213**. A number of coil sets **100** is twice a number of the first connection segments **212**. A number of input ends connected to each first connection segment **212** is two. The second connector **220** may include at least two second connection segments **222**. The at least two second connection segments **222** are arranged at intervals in the circumferential direction to form a second contour **223**. A number of coil sets **100** is twice the number of the second connection segments **222**. A number of the output ends connected to each second connection segment **222** is two. The connection structure **200** may be used in the coil structure **10** including the plurality of output ends and the plurality of input ends. When connecting, the input ends are connected to the first connection segment **212**. Each first connection segment **212** may be ensured to be connected to two input ends. The first connection segment **212** is connected to the RF source **700**. The output ends are connected to the second connection segment **222**. Each second segment **222** may be ensured to be connected to two output ends. The second connection segment **222** is electrically connected to the ground. During a processing process, the RF source **700** may apply RF energy to the coil structure **10** through the first connection segment **212**. The coil structure **10** may generate a plurality of induced magnetic fields. The plurality of induced magnetic fields may be coupled to form a coil magnetic field with a higher magnetic field amplitude value. Correspondingly, the plasma with higher density may be generated in the reaction chamber **300**, which has a higher processing capacity for the products.

(75) Further, as shown in FIG. **32**, in the connection structure **200** of the plasma processing apparatus of embodiments of the present disclosure, the first contour **213** is annular, and the second contour **223** is annular. The plurality of first connection segments **212** are arranged at intervals along the circumferential direction of the first contour **213**. The plurality of second connection segments **222** are arranged at intervals along the circumferential direction of the second contour **223**. The interference caused by connecting the plurality of input ends and the plurality of output ends to the corresponding connection segments may be reduced. Specifically, as shown in FIG. **32**

to FIG. 34, the first connector **210** includes three first connection segments **212** arranged at intervals. The second connector **220** includes three second connection segments **222** arranged at intervals.

(76) As shown in FIG. 32, embodiments of the present disclosure provide a connection structure **200** in the plasma processing apparatus. The first contour **213** and the second contour **223** are coaxial. By designing the first contour **213** and the second contour **223** to be coaxial, the connection structure **200** may uniformly feed energy into the coil structure **10** to further improve the uniformity of the coil magnetic field generated by the coupling of the coil structure **10**. Correspondingly, the uniformity of the plasma generated in the reaction chamber **300** may be higher to improve processing uniformity of the plasma to the product.

(77) In the connection structure **200** in the plasma processing apparatus of embodiments of the present disclosure, the two ends of the first connection segment **212** are electrically connected to an input end, respectively. The two ends of the second connection segment **222** are respectively electrically connected to an output end. The intervals between any two neighboring first connection segments **212** of the plurality of connection segments **212** may be equal. The intervals between any two neighboring second connection segments **222** of the plurality of second connection segments **222** may be equal. When the first connection segments **212** and the second connection segments **222** are evenly arranged along the first contour **213** and the second contour **223** at intervals, respectively, the uniformity of the RF energy fed into the coil structure **10** along the circumferential direction may be correspondingly improved. Thus, the uniformity of the magnetic field generated by the coil structure **10** may be improved. Therefore, the uniformity of the plasma in the reaction chamber **300** may be improved, and correspondingly the uniformity of the product processing by the plasma may be improved. Preferably, an arc length of the first connection segment **212** may be equal to a length of the interval between two neighboring first connection segments **212**. An arc length of the second connection segment **222** may be equal to the distance between the two neighboring second connection segments **222**. The RF energy feeding and the output positions may be arranged evenly to further improve the uniformity of the arrangement of the plasma and improve the uniformity of the product processing by the plasma.

(78) As shown in FIG. 35, the first connector **210** includes three first connection segments **212**. Second ends **112** of each two first coils are correspondingly connected to two ends of the first connection segment **212**.

(79) As shown in FIG. 32, in the plasma processing apparatus of embodiments of the present disclosure, the connection structure **200** further includes at least two first connection bars **250**. A number of the first connection bars **250** may be the same as the number of the first connection segments **212**. The first end of the first connection bar **250** is correspondingly connected to one first connection segment **212**. The second end of the first connection bar **250** is configured to be electrically connected to the RF source **700** to input RF power. The connection structure **200** may further include at least two second connection bars **260**. The number of the second connection bars **260** may be the same as the number of the second connection segments **222**. The first end of the second connection bar **260** may be correspondingly connected to one second connection **222**. The second end of the second connection bar **260** may be configured to be electrically connected to ground. Here, a specific form of electrical connection between the first connection segment **212** and the RF source **700** and between the second connection segment **222** and the ground is described. The first connection bar **250** is connected between the RF source **700** and the first connection segment **212**. Based on realizing the electrical connection between the first connection segment **212** and the RF source **700**, the first connection segment **212** may be ensured to be arranged along the circumferential direction of the first contour **213**. The effect on the position arrangement by the electrical connection between the second connection segment **222** and the RF source **700** may be reduced. Similarly, the second connection bar **260** may be connected between the ground and the second connection segment **222**. Based on realizing the electrical connection

between the second connection segment **222** and the ground, the second connection segment **222** may be ensured to be arranged along the circumferential direction of the second contour **223**. The effect on the position arrangement by the electric connection between the second connection segment **222** and the ground is reduced.

(80) In a connection structure **200** of the plasma processing apparatus of embodiments of the present disclosure, as shown in FIG. **32** and FIG. **34**, second ends of the at least two first connection bars **250** are both connected to a first point. The first point may be used as the power input end **270** and be configured to be electrically connected to the RF source **700**. The RF **700** may be electrically connected to a single power input end **270**. That is, the RF source **700** may be electrically connected to the plurality of first connection segments **212**. The connection structure may be simple, and little interference may exist between different first connection bars **250**. Similarly, the second ends of the at least two second bars **260** may be connected to the second point. The second point may be used as a ground end **280** and configured to be electrically connected to the ground. The ground may be electrically connected to a single ground end **280**. That is, the ground may be electrically connected to the plurality of second connection segments **222**. The connection structure may be simple. Little interference may exist between different second connection bars **260**. Of course, the ground end **280** may be electrically connected to the ground through the capacitor and/or inductor.

(81) Embodiments of the present disclosure provide a connection structure **200** in a plasma processing apparatus. As shown in FIG. **32** and FIG. **34**, two ends of the first connection segment **212** are electrically connected to an input end respectively. A connection position of the corresponding first connection bar **250** and the first connection segment **212** may be located at a middle position in a length direction of the first connection segment **212**. Two ends of the second connection segment **222** may be electrically connected to the output end. A connection position of the corresponding second connection bar **260** and the second connection segment **222** may be located at the middle position along the length direction of the second connection segment **222**. The RF source **700** may provide RF energy to two coil sets at two ends of the first connection segment **212** through the first connection bar **250**. Distances between the first connection bar **250** and the two ends of the first connection segment **212** may be same, and the distances between the second connection bar **260** and the two ends of the first connection segment **212** may also be same. Thus, effective lengths of the coils in the coil sets connected to the first connection segment **212** and the second connection segment **222** may be ensured to be the same to cause the coils to have the same inductance and the current value. Correspondingly, the uniformity of the magnetic field generated by the coils structure **10** may be improved. Thus, the uniformity of the coil magnetic field generated by coupling of the coil structure **10** is improved to improve the uniformity of the plasma in the reaction chamber.

(82) With reference to FIG. **27** and FIG. **28**, the plasma processing apparatus includes the coil structure **10**. The connectors of the connection structure **200** are all closed rings as shown in FIG. **26**. During the processing process, the closed rings may be used as the connection structure, which may generate a reverse current through induction in the coil magnetic field. The reverse inductance magnetic field generated by the reverse current may cancel or weaken the coil magnetic field. Thus, the magnetic field amplitude value H_r may be reduced. Correspondingly, the density of the plasma in the reaction chamber may be reduced. In addition, the reverse current generated by the first connector **210** and the second connector **220** of the connection structure **200** and the reverse induced magnetic field may block the coil magnetic field along the circumferential direction. The coil magnetic field may be distributed in the inner ring area. The magnetic field may not be distributed at an outer ring area of the connection structure **200**. Correspondingly, the density of the plasma at the inner ring area of the connection structure **200** in the reaction chamber **300** may be relatively large. The density of the plasma at the outer ring area of the connection structure **200** in the reaction chamber **300** may be relatively small. Thus, the density of the plasma in the reaction

chamber **300** may be small, and the distribution uniformity may be relatively poor. Thus, the product processing productivity and the uniformity may be poor.

(83) With reference to FIG. **36** and FIG. **37**, the difference between the plasma processing apparatus and the plasma processing apparatus in FIG. **27** and FIG. **28** includes that the first connector **210** of the connection structure **200** adopts the first connection segment **212** with a form that two ends are disconnected. The second connector **210** may also adopt the second connection segment **222** with a form that two ends are disconnected. During the processing process the first connector **210** and the second connector **220** may not generate the reverse current. Thus, the magnetic field amplitude value H_r may not be reduced, and the coil magnetic field may not be blocked. The magnetic field amplitude value H_r of the coil magnetic field generated in the reaction chamber **300** may be relatively large. The radial boundary of the coil magnetic field may be the chamber edge **330** of the reaction chamber **300**. Thus, the magnetic field amplitude value of the inner coil magnetic field in the reaction chamber **300** and the magnetic field radial continuous distribution range may be improved. Correspondingly, the reaction chamber may be filled with the plasma. The plasma may have a large density. Thus, the productivity and uniformity of the product processing using the plasma may be improved.

(84) With reference to FIG. **29** and FIG. **30**, two coil structures **10** and two connection structures **200** are arranged in the plasma processing apparatus. The first connector **210** and the second connector **220** of the two connection structures **200** are closed rings. The two coil structures **10** may be set to be the inner coil set **150** and the outer coil set **140** respectively. The connection structure **200** connected to the inner coil set **150** is an inner ring set **920**. The connection structure **200** connected to the outer coil set **140** is an outer ring set **910**. The inner coil set **150** is located at the inner ring of the outer coil set **140**. During the processing process, the inner coil set **150** and the outer coil set **140** may be coupled to form a coupling induced magnetic field. As shown in FIG. **31**, since the closed ring of the inner ring set **920** and the closed ring of the outer ring set **910** may generate the reverse current, the magnetic field amplitude value H_r of the coupling induced magnetic field may be reduced. Moreover, the inner ring set **920** and the outer ring set **910** may both block the coupling induced magnetic field. The inner ring set **920** and the outer ring set **910** may block the coupling induced magnetic field into an outer ring magnetic field **930** and an outer ring magnetic field **940**. Moreover, the inner ring magnetic field **930** may be distributed at the inner ring area of the inner ring set **920**. The outer ring magnetic field **940** may be distributed at the annular area enclosed by the inner ring set **920** and the outer ring set **910**. The magnetic field may not be distributed at an area between the outer ring set **910** and the chamber boundary **330**. Thus, the plasma in the reaction chamber **300** may correspond to the magnetic field and may be distributed at intervals at the outer ring set **910**. The radial area may be located in the inner ring of the outer ring set **910**. The density, uniformity, and radial distribution area may be relatively small. Thus, the productivity, uniformity, and processing range of the corresponding product may be poor.

(85) With reference to FIG. **32**, FIG. **33**, and FIG. **38** to FIG. **40**, the difference between this plasma processing apparatus and the plasma processing apparatus of FIG. **29** and FIG. **30** includes that the first connectors **210** of the two connection structures **200** both adopt the first connection segment **212** in the form that the two ends are disconnected, the second connectors **220** of the two connection structures **200** adopt the second connection segment **222** in the form that the two ends are disconnected, the connection structure **200** connected to the outer coil set **140** is the outer connection structure **201**, and the connection structure **200** connected to the inner coil set **150** is the inner connection structure **202**. During the processing process, neither the inner connection structure **202** nor the outer connection structure **201** may generate the reverse current. Thus, the coupled induced magnetic field generated by the inner coil group **150** and the outer coil group **140** may not be weakened correspondingly, and the coupled induced magnetic field may not be blocked. The inner coil set **150** and the outer coil set **140** may generate a continuous magnetic field **340** with a relatively large magnetic field amplitude value H_r in the reaction chamber **300**. As

shown in FIG. 40, the radial boundary of the continuous magnetic field 340 is the chamber boundary 330 of the reaction chamber 300. The continuous magnetic field 340 is continuously distributed in the reaction chamber 300. Accordingly, the reaction chamber 300 is filled with plasma. The plasma may be arranged continuously and have a high density. Thus, the productivity and the uniformity of the product may be relatively high and the processing range may be relatively large.

(86) Specifically, a dielectric member 400 in the plasma processing apparatus of embodiments of the present disclosure may include a dielectric barrel or a dielectric window.

(87) In addition, a support base 320 and a liner 310 arranged around the support base 320 may be arranged in the reaction chamber 300. The support base 320 may be configured to carry the to-be-processed workpiece (e.g., a wafer). The liner 310 may be configured to protect an inner wall of the reaction chamber 300. The dielectric member 40 may be arranged on a top of the reaction chamber 300. The plasma processing apparatus may also include an adjustment bracket configured to adjust a height of the dielectric member 400, more precisely, adjust the height of the dielectric member 400 relative to the to-be-processed workpiece.

(88) The plasma processing apparatus may further include a shield cover 500 and a matching device 600. The shield cover 500 may be arranged above the dielectric member 400. The coil structure 10 and the connection structure 200 may be both arranged in the shield cover 500. The RF source 700 may be connected to the connector of the connection structure 10, which is configured to input RF power through the matching device 600.

(89) With the connection form among the first connector 210, the second connector 220, the third connector 230, the fourth connector 240, and the connection bars, the power of the coil set in the coil structure 10 may be distributed uniformly to further realize the uniformly distributed electromagnetic field generated by the coil structure 10 of the present disclosure, which is beneficial to generate the uniform plasma in the reaction chamber 300 to ensure etching.

(90) It should be noted that, in the ground electrical connection of the present disclosure, the second connector 220 may be configured to be electrically connected to the coil set 100 and the ground. The connection manner between the second connector 220 and the ground is not limited by the present disclosure. In FIG. 19 to FIG. 21, FIG. 27 to FIG. 30, and FIG. 36 to FIG. 39 of embodiments of the present disclosure, the second connector 220 being electrically connected to the ground via the ground electrical connection end on the matching device 600 includes that the second connector 220 is grounded through a housing of the matching device, which is merely exemplarily described here. The connector of the connection structure 10 configured to be grounded may also be grounded through any manner such as the shield cover 500 or the outer wall of the reaction chamber, as long as the connector is grounded.

(91) Although the present disclosure is disclosed above, the present disclosure is not limited to this. Those skilled in the art may make various changes and modifications without departing from the spirit and scope of the present disclosure. Therefore, the protection scope of the present disclosure should be based on the scope defined by the claims.

(92) Finally, it should also be noted that in the present specification, relational terms such as first and second are used only to distinguish one entity or operation from another, and do not necessarily require or imply that there is any such actual relationship or sequence between these entities or operations. Moreover, the terms “comprising,” “including,” or any other variation thereof are intended to encompass non-exclusive inclusion such that a process, method, article, or apparatus comprising a list of elements includes not only those elements, but also includes other elements that are not explicitly listed or elements inherent to such a process, method, article, or apparatus. Without further limitation, an element associated with the phrase “comprising a . . .” does not preclude the presence of additional identical elements in a process, method, article, or apparatus that includes the element.

(93) The above description of the disclosed embodiments enables those skilled in the art to make or

use the present disclosure. Various modifications to these embodiments will be apparent to those skilled in the art, and the generic principles defined herein may be implemented in other embodiments without departing from the spirit or scope of the present disclosure. Thus, the present disclosure is not intended to be limited to the embodiments shown herein, but conforms to the widest scope consistent with the principles and novel features disclosed in the present application.

Claims

1. A coil structure applied to a plasma processing apparatus comprising: at least two coil sets, each coil set of the at least two coil sets including: a first coil; and a second coil; wherein: the first coil and the second coil are wound to form an annular area; a first end of the first coil and a first end of the second coil are close to an inner ring of the annular area; a second end of the first coil and a second end of the second coil are close to an outer ring of the annular area; the first end of the first coil is electrically connected to the first end of the second coil; a first projection of the first coil on a plane perpendicular to an axial direction of the coil structure and a second projection of the second coil on the plane are mirror-symmetrical to each other; the first end of the first coil and the first end of the second coil are arranged at an interval along the axial direction of the coil structure; the second end of the first coil and the second end of the second coil are arranged at an interval along the axial direction of the coil structure; a connection line between the first end of the first coil and the first end of the second coil is parallel to an axis of the coil structure; a connection line between the second end of the first coil and the second end of the second coil is parallel to the axis of the coil structure; first ends of first coils of the at least two coil sets are on a first plane; first ends of second coils of the at least two coil sets are on a second plane; second ends of the first coils of the at least two coil sets are on a third plane; second ends of the second coils of the at least two coil sets are on a fourth plane; and the first plane is separated from the second plane by a predetermined distance, and the third plane is separated from the fourth plane by the predetermined distance.
2. The coil structure according to claim 1, wherein the predetermined distance is 10 mm.
3. The coil structure according to claim 1, wherein: the first ends of the first coils of the at least two coil sets are arranged uniformly along a circumferential direction of the coil structure; and the second ends of the first coils of the at least two coil sets are arranged uniformly along the circumferential direction of the coil structure.
4. The coil structure according to claim 1, wherein winding trajectories of the first coil and the second coil are both in an involute shape.
5. The coil structure according to claim 4, wherein at least one of a radial radius change amount of each turn of the first coil or a radial radius change amount of each turn of the second coil equals 60 mm.
6. The coil structure according to claim 1, wherein a number of winding turns of the first coil and a number of winding turns of the second coil are both integer multiples of 0.5 turns.
7. The coil structure according to claim 1, wherein the coil set is one of a plurality of coil sets of the coil structure, and a number of the plurality of coil sets is an even number.
8. The coil structure according to claim 1, wherein: the first end of the first coil on the first projection overlaps with the first end of the second coil on the second projection; and the second end of the second coil on the first projection overlaps with the second end of the second coil on the second projection.
9. A plasma processing apparatus comprising: a radio frequency (RF) source; a reaction chamber; a dielectric member arranged on a top of the reaction chamber; and a coil structure arranged on the dielectric member and including: at least two coil sets, each coil set of the at least two coil sets including: a first coil; and a second coil; wherein: the first coil and the second coil are wound to form an annular area; a first end of the first coil and a first end of the second coil are close to an inner ring of the annular area; a second end of the first coil and a second end of the second coil are

close to an outer ring of the annular area; the first end of the first coil is electrically connected to the first end of the second coil; a first projection of the first coil on a plane perpendicular to an axial direction of the coil structure and a second projection of the second coil on the plane are mirror-symmetrical to each other; the first end of the first coil and the first end of the second coil are arranged at an interval along the axial direction of the coil structure; the second end of the first coil and the second end of the second coil are arranged at an interval along the axial direction of the coil structure; a connection line between the first end of the first coil and the first end of the second coil is parallel to an axis of the coil structure; a connection line between the second end of the first coil and the second end of the second coil is parallel to the axis of the coil structure; first ends of first coils of the at least two coil sets are on a first plane; first ends of second coils of the at least two coil sets are on a second plane; second ends of the first coils of the at least two coil sets are on a third plane; second ends of the second coils of the at least two coil sets are on a fourth plane; and the first plane is separated from the second plane by a predetermined distance, and the third plane is separated from the fourth plane by the predetermined distance.

10. The plasma processing apparatus according to claim 9, further comprising: a connection structure including: a first connector electrically connected to the second end of the first coil; and a second connector electrically connected to the second end of the second coil; wherein one of the first connector and the second connector is configured to input RF power, and another one of the first connector and the second connector is configured to be grounded.

11. The plasma processing apparatus according to claim 10, wherein: the first connector and the second connector both have an annular structure; and the first connector and the second connector are arranged at an interval along the axial direction of the coil structure.

12. The plasma processing apparatus according to claim 10, wherein: the connection structure further includes: a third connector electrically connected to the first connector through a first connection bar; and a fourth connector electrically connected to the second connector through a second connection bar; and one of the third connector and the fourth connector is configured to input RF power, and another one of the third connector and the fourth connector is configured to be grounded.

13. The plasma processing apparatus according to claim 12, wherein the third connector and the fourth connector both have an annular structure and are arranged at an interval along the axial direction of the coil structure.

14. The plasma processing apparatus according to claim 12, wherein: the first connection bar is one of a plurality of first connection bars uniformly arranged along a circumferential direction of the coil structure; and the second connection bar is one of a plurality of second connection bars uniformly arranged along the circumferential direction of the coil structure.

15. The plasma processing apparatus according to claim 10, wherein: the second end of the first coil of the coil set is configured as an input end, and the second end of the second coil of the coil set is configured as an output end; and the first connector includes a first connection segment connected to the input end, and a number of the first connection segment connected to the input end is at least one, and/or the second connector includes a second connection segment connected to the output end, a number of the second connection segment connected to the output end is at least one.

16. The plasma processing apparatus according to claim 15, comprising a plurality of coil sets wherein: the first connection segment is one of at least two first connection segments of the first connector that are arranged at an interval along a circumferential direction to enclose to form a first contour; and a number of the coil sets is twice a number of the first connection segments; a number of input ends connected to each of the first connection segments is two; the second connection segment is one of at least two second connection segments of the second connector that are arranged at an interval along the circumferential direction to enclose to form a second contour; the number of the coil sets is twice a number of the second connection segment; and a number of output ends connected to each of the second connection segments is two.

17. The plasma processing apparatus according to claim 16, wherein the first contour is annular, the second contour is annular, and the first contour and the second contour are coaxial.
18. The plasma processing apparatus according to claim 16, wherein: an interval between any two neighboring ones of the at least two first connection segments is same; and/or an interval between any two neighboring ones of the at least two second connection segments is same.
19. The plasma processing apparatus according to claim 16, wherein the connection structure further includes: at least two first connection bars, a number of the first connection bars being same as the number of the first connection segments, a first end of each of the first connection bars being connected to a corresponding one of the first connection segments, and a second end of each of the first connection bars being configured to input RF power; and/or at least two second connection bars, a number of the second connection bars being same as the number of the second connection segments, a first end of each of the second connection bars being connected to a corresponding one of the second connection segments, and a second end of each of the second connection bars being configured to be grounded.
-