

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12419075
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Tsai; Ming-Hua et al.

Transistor with embedded insulating structure set

Abstract

A transistor with an embedded insulating structure set includes a substrate. A gate is disposed on the substrate. A first lightly doped region is disposed at one side of the gate. A second lightly doped region is disposed at another side of the gate. The first lightly doped region and the second lightly doped region have the same conductive type. The first lightly doped region is symmetrical to the second lightly doped region. A first source/drain doped region is disposed within the first lightly doped region. A second source/drain doped region is disposed within the second lightly doped region. A first insulating structure set is disposed within the first lightly doped region and the first source/drain doped region. The first insulating structure set includes an insulating block embedded within the substrate. A sidewall of the insulating block contacts the gate dielectric layer.

Inventors: Tsai; Ming-Hua (Tainan, TW), Kuo; Chin-Chia (Tainan, TW), Chang; Wei-Hsuan (Tainan, TW)

Applicant: UNITED MICROELECTRONICS CORP. (Hsin-Chu, TW)

Family ID: 1000008818970

Assignee: UNITED MICROELECTRONICS CORP. (Hsin-Chu, TW)

Appl. No.: 18/120980

Filed: March 13, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240266435 A1	Aug. 08, 2024

Foreign Application Priority Data

TW	112104035	Feb. 06, 2023
----	-----------	---------------

Publication Classification

Int. Cl.: H10D30/60 (20250101); H10D30/01 (20250101); H10D62/10 (20250101)

U.S. Cl.:

CPC H10D30/603 (20250101); H10D30/0227 (20250101);

Field of Classification Search

CPC: H10D (30/0227); H10D (30/603); H10D (62/116); H10D (30/605)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
7217985	12/2006	Kim	257/500	H10D 84/83
8643101	12/2013	Kao	N/A	N/A
8836067	12/2013	Hsu	N/A	N/A
11171222	12/2020	Kim	N/A	N/A
2020/0251575	12/2019	Kim	N/A	H10D 30/0227
2022/0069081	12/2021	Lin	N/A	H10D 30/0281
2022/0336502	12/2021	Oh	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2005-150331	12/2004	JP	N/A
2010-62182	12/2009	JP	N/A

Primary Examiner: Rosario; Joshua Benitez

Assistant Examiner: Nelson; Jacob T

Background/Summary

BACKGROUND OF THE INVENTION

1. Field of the Invention

(1) The present invention relates to a metal oxide semiconductor (MOS) transistor, and more particularly to an MOS transistor which uses an embedded insulating structure set to increase breakdown voltage and decrease current leakage.

2. Description of the Prior Art

(2) Currently, the application of high voltage MOS transistor is increasing, and it can be applied to personal computers, servers, power supply, communication electronics, cell phones, consumer products and industrial application products. Power transistor plays an important role in power switches. Power transistors of different withstand voltage levels are used in different products.

(3) When the pitch between transistors is shrinking, the breakdown voltage decreases as the space between the gate and the drain getting smaller. However, conventionally, in order for the transistor to sustain higher breakdown voltage, the space between the gate and the drain needs to be

extended. The extended space leads to the increase of the transistor's area. Therefore, a transistor structure which can sustain high voltage and without increasing transistor's area is needed.

SUMMARY OF THE INVENTION

(4) In view of this, the present invention provides a transistor with an embedded insulating structure set to achieve higher breakdown voltage and lower current leakage.

(5) According to a preferred embodiment of the present invention, a transistor with an embedded insulating structure set includes a substrate with an active region thereon. A gate is disposed within the active region. A gate dielectric layer is disposed between the gate and the active region. A first lightly doped region is disposed within the active region at one side of the gate. A second lightly doped region is disposed within the active region at another side of the gate, wherein the first lightly doped region and the second lightly doped region have the same conductive type, and wherein by taking a symmetrical line of the gate as a given axis, the first lightly doped region is symmetrical to the second lightly doped region. A first source/drain doped region is disposed within the first lightly doped region. A second source/drain doped region is disposed within the second lightly doped region. A first insulating structure set is disposed within the first lightly doped region and the first source/drain doped region, wherein the first insulating structure set includes a first insulating block embedded within the substrate and a sidewall of the first insulating block contacts the gate dielectric layer.

(6) These and other objectives of the present invention will no doubt become obvious to those of ordinary skill in the art after reading the following detailed description of the preferred embodiment that is illustrated in the various figures and drawings.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 depicts a transistor with an embedded insulating structure set according to a first preferred embodiment of the present invention.

(2) FIG. 2 depicts a transistor with an embedded insulating structure set according to a second preferred embodiment of the present invention.

(3) FIG. 3 depicts a transistor with an embedded insulating structure set according to a third preferred embodiment of the present invention.

(4) FIG. 4 depicts a transistor with an embedded insulating structure set according to a fourth preferred embodiment of the present invention.

(5) FIG. 5 depicts a transistor with an embedded insulating structure set according to a fifth preferred embodiment of the present invention.

(6) FIG. 6 depicts a transistor with an embedded insulating structure set according to a sixth preferred embodiment of the present invention.

(7) FIG. 7 depicts a transistor with an embedded insulating structure set according to a seventh preferred embodiment of the present invention.

(8) FIG. 8 depicts a transistor with an embedded insulating structure set according to an eighth preferred embodiment of the present invention.

(9) FIG. 9 depicts a transistor with an embedded insulating structure set according to a ninth preferred embodiment of the present invention.

DETAILED DESCRIPTION

(10) FIG. 1 depicts a transistor with an embedded insulating structure set according to a first preferred embodiment of the present invention.

(11) As shown in FIG. 1, a transistor **100** with an embedded insulating structure set includes a substrate **10**. A first shallow trench isolation **12a** and a second shallow trench isolation **12b** are embedded within the substrate **10**. The first shallow trench isolation **12a** and the second shallow

trench **12b** define the active region A on the substrate **10**. A deep well **14** is disposed within the active region A. A well **16** is disposed within the deep well region **14**. A gate G is disposed within the active region A. Two spacers **S1/S2** are respectively disposed at two sides of the gate G. A gate dielectric layer **18** is disposed between the gate G and the active region A and the gate dielectric layer **18** is embedded within the substrate **10**. A first lightly doped region **LDD1** is disposed within the active region A at one side of the gate G. A second lightly doped region **LDD2** is disposed within the active region A at another side of the gate G. The first lightly doped region **LDD1** and the second lightly doped region **LDD2** have the same conductive type. Moreover, by taking a symmetrical line L of the gate G as a given axis, the first lightly doped region **LDD1** is symmetrical to the second lightly doped region **LDD2**. A first source/drain doped region **SD1** is disposed within the first lightly doped region **LDD1**. A second source/drain doped region **SD2** is disposed within the second lightly doped region **LDD2**. Silicide layers **20a/20b** are respectively disposed on the first source/drain doped region **SD1** and the second source/drain doped region **SD2**. The deep well **14**, the first lightly doped region **LDD1**, the second lightly doped region **LDD2**, the first source/drain doped region **SD1** and the second source/drain doped region **SD2** have a first conductive type. The well **16** has a second conductive type. In this embodiment, the first conductive type is N type. The second conductive type is P type. However, in a different embodiment, the first conductive type can be P type. The second conductive type can be N type.

(12) The first insulating structure set **22** is disposed within the first lightly doped region **LDD** and the first source/drain doped region **SD1**. The first insulating structure set **22** includes at least an insulating block **22a** embedded within the substrate **10**. A sidewall of the insulating block **22a** contacts an end of the gate dielectric layer **18**. Part of the insulating block **22a** overlaps the gate G and another part of the insulating block **22a** overlaps the spacer **S1** which is closer to the first source/drain doped region **SD1**. The number of the insulating block in the first insulating structure set **22** can be adjusted based on different requirement. The number of the insulating block can be 1 or more than 1. In the first preferred embodiment, there are three insulating blocks **22a/22b/22c** presented as an example. Among three insulating blocks **22a/22b/22c**, the insulating block **22a** is the closest to the gate G and the insulating block **22c** is the farthest from the gate G. The size and the shape of the three insulating blocks **22a/22b/22c** are the same. Moreover, the depth of each of the three insulating blocks **22a/22b/22c** is larger than the depth of the first source/drain doped region **SD1**.

(13) Furthermore, with respect to the gate G, the first shallow trench isolation **12a** is disposed at the same side of the first source/drain doped region **SD1**. The first source/drain doped region **SD1** is between the insulating blocks **22a/22b/22c**, and between the first insulating structure set **22** and the first shallow trench isolation **12a**. The first source/drain doped region **SD1** contacts the insulating blocks **22a/22b/22c** and the first shallow trench isolation **12a**. A conductive plug **26a** contacts the silicide layer **20a** on the first source/drain doped region **SD1** which is between the first insulating structure set **22** and the first shallow trench isolation **12a**.

(14) In addition, the transistor **100** with an embedded insulating structure set further includes a second insulating structure set **24** disposed within the second lightly doped region **LDD2** and the second source/drain doped region **SD2**. By taking the symmetrical line L of the gate G as the given axis, the transistor **100** with an embedded insulating structure set is in left-right symmetry. Therefore, the location of the insulating blocks of the second insulating structure set **24** are entirely the same as the location of the insulating blocks of the first insulating structure set **22**. For example, the second insulating structure set **24** includes insulating blocks **24a/24b/24c**. Furthermore, a silicide layer **20b** is disposed on the second source/drain doped region **SD2**. A conductive plug **26b** contacts the silicide layer **20b**.

(15) The advantage of making the transistor **100** with an embedded insulating structure set in left-right symmetry is that the first source/drain doped region **SD1** and the second source/drain doped region **SD2** can be source or drain selectively based on requirements. Besides, the conventional

MOS transistors are also in left-right symmetry, therefore, the fabricating steps of the transistor **100** with an embedded insulating structure set in left-right symmetry can be compatible with the fabricating steps of the conventional MOS transistor.

(16) The fabricating steps of the transistor **100** with an embedded insulating structure set includes forming the first shallow trench isolation **12a**, the second trench isolation **12b**, the first insulating structure set **22** and the second insulating structure set **24**. If the depths of the first shallow trench isolation **12a**, the second trench isolation **12b**, the first insulating structure set **22** and the second insulating structure set **24** are the same, they can be formed by forming numerous trenches simultaneously within the substrate **10** to contain the first shallow trench isolation **12a**, the second trench isolation **12b**, the first insulating structure set **22** and the second insulating structure set **24**. If the depths of the first shallow trench isolation **12a**, the second trench isolation **12b**, the first insulating structure set **22** and the second insulating structure set **24** are different, numerous trenches with different depths have to be manufactured in different steps. Then, isolating material is filled in the trenches with different depths to form the first shallow trench isolation **12a**, the second trench isolation **12b**, the first insulating structure set **22** and the second insulating structure set **24**. After the first shallow trench isolation **12a**, the second trench isolation **12b**, the first insulating structure set **22** and the second insulating structure set **24** are completed, dopants are implanted into the substrate **10** to form the deep well **14**. Thereafter, other dopants are implants into the substrate **10** to form the well **16**. Later, a photoresist (not shown) is formed to cover a predetermined position for the gate G. Next, by taking the photoresist as a mask, dopants are implanted to form the first lightly doped region LDD1 and the second lightly doped region LDD2 simultaneously. Subsequently, the photoresist is removed. Then, the gate dielectric layer **18**, the gate G and the spacers S1/S2 are formed in sequence. Finally, the first source/drain doped region SD1 and the second source/drain doped region SD2 are formed by taking the spacers S1/S2 and the gate G as a mask,

(17) In the transistor **100** with embedded insulating structure set, the withstand voltage between the gate G and the first source/drain doped region SD1 and the withstand voltage between the gate G and the second source/drain doped region SD2 can be adjusted by altering the device structures. When the withstand voltage is adjusted, the current leakage between the gate G and the first source/drain doped region SD1 or between the gate G and the second source/drain doped region SD2 can be reduced.

(18) The above-mentioned device structures includes the numbers of the insulating block of the first insulating structure set **22**, the shape of the insulating block of the first insulating structure set **22**, the relative depth of the insulating block of the first insulating structure set **22** with respective to the depth of the first source/drain doped region SD1, the position of the insulating block of the first insulating structure set **22**, the range of the first source/drain doped region SD1, the position of the gate dielectric layer **18** and whether or not the first insulating structure set **22** is symmetrical to the second insulating structure set **24**. By arranging aforesaid the device structures differently, many transistors with different withstand voltage can be accomplished. Each of transistors with different withstand voltage share the same features as follows. First, the first lightly doped region LDD1 and the second lightly doped region LDD2 have the same conductive type. Secondly, by taking the symmetrical line L of the gate G as the given axis, the first lightly doped region LDD1 is symmetrical to the second lightly doped region LDD2. Thirdly, among all insulating blocks, the insulating block which is the closest to the gate G, such as the insulating block **22a**, has a sidewall which contacts the gate dielectric layer **18**.

(19) In the following description, several embodiments will be used to illustrate the way of altering device structures. However, the present invention does not limited to the following embodiments.

(20) FIG. 2 depicts a transistor with an embedded insulating structure set according to a second preferred embodiment of the present invention, wherein elements which are substantially the same as those in the first preferred embodiment are denoted by the same reference numerals; an

accompanying explanation is therefore omitted.

(21) As shown in FIG. 2, the gate dielectric layer **18** of a transistor **200** with an embedded insulating structure set is disposed on a top surface of the substrate **10**. That is, the gate dielectric layer **18** does not embed within the substrate **10**. Therefore, the insulating block **22a** contacts the bottom of the gate dielectric layer **18**, but does not contact the end of the gate dielectric layer **18**. Other elements are the same as those of the first preferred embodiment.

(22) FIG. 3 depicts a transistor with an embedded insulating structure set according to a third preferred embodiment of the present invention, wherein elements which are substantially the same as those in the first preferred embodiment are denoted by the same reference numerals; an accompanying explanation is therefore omitted.

(23) As shown in FIG. 3, the insulating block **22a** of the transistor **300** with an embedded insulating structure set does not overlaps the gate G, and only overlaps the spacer **S1**. In this way, the transistor **300** with an embedded insulating structure set has longer channel than the transistor **100** with an embedded insulating structure set. Other elements are the same as those of the first preferred embodiment.

(24) FIG. 4 depicts a transistor with an embedded insulating structure set according to a fourth preferred embodiment of the present invention, wherein elements which are substantially the same as those in the first preferred embodiment are denoted by the same reference numerals; an accompanying explanation is therefore omitted.

(25) As shown in FIG. 4, the depths of the insulating blocks **22a/22b/22c** of the transistor **400** with an embedded insulating structure set are smaller than the depth of the first source/drain doped region **SD1**. In this embodiment, the insulating blocks **22b/22c** are entirely encompassed within the first source/drain doped region **SD1**. Other elements are the same as those of the first preferred embodiment.

(26) FIG. 5 depicts a transistor with an embedded insulating structure set according to a fifth preferred embodiment of the present invention, wherein elements which are substantially the same as those in the first preferred embodiment are denoted by the same reference numerals; an accompanying explanation is therefore omitted.

(27) As shown in FIG. 5, the first source/drain doped region **SD1** of the transistor **500** with an embedded insulating structure set is disposed outside of the first insulating structure set **22** and only between the first insulating structure set **22** and the first shallow trench isolation **12a**. There is no first source/drain doped region **SD1** within the first insulating structure set **22**. Other elements are the same as those of the first preferred embodiment.

(28) FIG. 6 depicts a transistor with an embedded insulating structure set according to a sixth preferred embodiment of the present invention, wherein elements which are substantially the same as those in the first preferred embodiment are denoted by the same reference numerals; an accompanying explanation is therefore omitted.

(29) As shown in FIG. 6, in the transistor **600** with an embedded insulating structure set, the widths of the insulating blocks **22a/22b** of the first insulating structure set **22** are different from each other. For example, the width of the insulating block **22a** is larger than the width of the insulating block **22b**. Furthermore, comparing to the first preferred embodiment, there is only two insulating blocks **22a/22b** in the first insulating structure set **22**. The number of the insulating block in the first insulating structure set **22** of the transistor **600** with an embedded insulating structure set is less than number of the insulating block in the first insulating structure set **22** of the transistor **100** with an embedded insulating structure set. Other elements are the same as those of the first preferred embodiment. In addition, the insulating block which has a larger width is disposed closer to the gate dielectric layer **18**, and the insulating block which has a smaller width is disposed farther to the gate dielectric layer **18**. The insulating block which has the larger width can separate the first source/drain doped region **SD1** from the gate dielectric layer **18** with greater distance. Therefore, current leakage between the first source/drain doped region **SD1** and the gate G can be reduced

more efficiently. However, if the width of the insulating block **22b** is widened as well, the size of the transistor will be further increased. Therefore, the present invention specially designs that the insulating block which has a larger width is disposed closer to the gate dielectric layer **18**, and the insulating block which has a smaller width is disposed farther from the gate dielectric layer **18** to take care of both the size of the transistor and the current leakage.

(30) FIG. **7** depicts a transistor with an embedded insulating structure set according to a seventh preferred embodiment of the present invention, wherein elements which are substantially the same as those in the first preferred embodiment are denoted by the same reference numerals; an accompanying explanation is therefore omitted.

(31) As shown in FIG. **7**, the depths of the insulating block **22a/22b/22c** of the transistor **700** with an embedded insulating structure set are the same as that of the first shallow trench isolation **12a**. Other elements are the same as those of the first preferred embodiment.

(32) FIG. **8** depicts a transistor with an embedded insulating structure set according to an eighth preferred embodiment of the present invention, wherein elements which are substantially the same as those in the first preferred embodiment are denoted by the same reference numerals; an accompanying explanation is therefore omitted.

(33) As shown in FIG. **8**, the transistor **800** with an embedded insulating structure set only has the first insulating structure set **22**, but there is no second insulating structure set within the second source/drain doped region **SD2**. That is, the transistor **800** with an embedded insulating structure set is an asymmetrical structure. This asymmetrical structure is because the device structure of the first source/drain doped region **SD1** and the second source/drain doped region **SD2** are adjusted according to different withstand voltage required by the drain doped region and the source doped region. Moreover, because there is no second insulating structure set, the conductive plug **26b** on the second source/drain doped region **SD2** can be located freely in horizontal direction, and does not limited by the position of the insulating block. Furthermore, the depth of the insulating block **22a** is largest, the depth of the insulating block **22c** is smallest, and the depth of the insulating block **22b** is between the depth of the insulating block **22a** and the depth of the insulating block **22c**. That is, the insulating block with larger depth is closer to the gate dielectric layer **18**, and the insulating block with smaller depth is farther from the gate dielectric layer **18**. This structure has the advantage that current has to flow more depth when passing the insulating block **22a**. In this way, the current leakage occurred at the bottom of the gate can be lower. However, if the depths of the insulating block **22b/22c** are the same as that of the insulating block **22a**, the on-resistance will be increased greatly. In order to take care of both the on-resistance of the transistor and the current leakage, the insulating block with larger depth is disposed closer to the gate dielectric layer **18**, and the insulating block with smaller depth is disposed farther from the gate dielectric layer **18**.

(34) FIG. **9** depicts a transistor with an embedded insulating structure set according to a ninth preferred embodiment of the present invention, wherein elements which are substantially the same as those in the first preferred embodiment are denoted by the same reference numerals; an accompanying explanation is therefore omitted.

(35) As shown in FIG. **9**, the transistor **900** with an embedded insulating structure set is an asymmetrical structure. The number of the insulating blocks in the first insulating structure set **22** is different from the number of the insulating blocks in the second insulating structure set **24**. Moreover, the width of the insulating block **24a** of the second insulating structure set **24** is greater than the widths of the insulating block **22a/22b**. Because the shapes of the first insulating structure set **22** and the second insulating structure set **24** are different from each other, the range of the first source/drain doped region **SD1** and the second source/drain doped region **SD2** are also different from each other. Moreover, the relative position between the conductive plug **26a** and the gate **G**, and the relative position between the conductive plug **26b** and the gate **G** are also different because the shapes of the first insulating structure set **22** and the second insulating structure set **24** are different from each other.

(36) Those skilled in the art will readily observe that numerous modifications and alterations of the device and method may be made while retaining the teachings of the invention. Accordingly, the above disclosure should be construed as limited only by the metes and bounds of the appended claims.

Claims

1. A transistor with an embedded insulating structure set, comprising: a substrate, wherein the substrate comprises an active region; a gate disposed within the active region; a gate dielectric layer disposed between the gate and the active region, wherein the gate dielectric layer is embedded within the substrate; a first lightly doped region disposed within the active region at one side of the gate; a second lightly doped region disposed within the active region at another side of the gate, wherein the first lightly doped region and the second lightly doped region have a same conductive type, and wherein by taking a symmetrical line of the gate as a given axis, the first lightly doped region is symmetrical to the second lightly doped region; a first source/drain doped region disposed within the first lightly doped region; a second source/drain doped region disposed within the second lightly doped region; and a first insulating structure set disposed within the first lightly doped region and the first source/drain doped region, wherein the first insulating structure set comprises a first insulating block embedded within the substrate and a sidewall of the first insulating block contacts the gate dielectric layer.
2. The transistor with an embedded insulating structure set of claim 1, further comprising two spacers respectively disposed at two sides of the gate, wherein part of the first insulating block overlaps the gate and another part of the first insulating block overlaps one of the two spacers.
3. The transistor with an embedded insulating structure set of claim 1, further comprising two spacers respectively disposed at two sides of the gate, wherein the first insulating block does not overlap the gate, and part of the first insulating block overlaps one of the two spacers.
4. The transistor with an embedded insulating structure set of claim 1, further comprising two shallow trench isolations embedded within the substrate, the two shallow trench isolations define the active region, wherein a depth of the first insulating block is smaller than a depth of each of the two shallow trench isolations.
5. The transistor with an embedded insulating structure set of claim 1, further comprising two shallow trench isolations embedded with the substrate, the two shallow trench isolations define the active region, wherein a depth of the first insulating block is the same as a depth of each of the two shallow trench isolations.
6. The transistor with an embedded insulating structure set of claim 1, wherein the sidewall of the first insulating block contacts an end of the gate dielectric layer.
7. The transistor with an embedded insulating structure set of claim 1, wherein part of the first insulating block overlaps the gate dielectric layer.
8. The transistor with an embedded insulating structure set of claim 1, wherein a depth of the first insulating block is larger than a depth of the first source/drain doped region, and the depth of the first insulating block is smaller than a depth of the first lightly doped region.
9. The transistor with an embedded insulating structure set of claim 1, wherein a depth of the first insulating block is smaller than a depth of the first source/drain doped region.
10. The transistor with an embedded insulating structure set of claim 1, wherein the first insulating structure set further comprises a second insulating block disposed within the first lightly doped region, and the second insulating block is farther from the gate than the first insulating block.
11. The transistor with an embedded insulating structure set of claim 10, wherein a width of the second insulating block is different from a width of the first insulating block.
12. The transistor with an embedded insulating structure set of claim 10, wherein a depth of the second insulating block is different from a depth of the first insulating block.

13. The transistor with an embedded insulating structure set of claim 10, wherein the first lightly doped region does not contact the second lightly doped region.
 14. The transistor with an embedded insulating structure set of claim 1, further comprising a second insulating structure set disposed within the second lightly doped region and the second source/drain doped region.
 15. The transistor with an embedded insulating structure set of claim 14, wherein by taking the symmetrical line of the gate as the given axis, the second insulating structure set is symmetrical to the first insulating structure set.
 16. The transistor with an embedded insulating structure set of claim 14, wherein by taking the symmetrical line of the gate as the given axis, the first source/drain doped region is symmetrical to the second source/drain doped region.
 17. The transistor with an embedded insulating structure set of claim 14, wherein by taking the symmetrical line of the gate as the given axis, the second insulating structure set is asymmetrical to the first insulating structure set.
 18. The transistor with an embedded insulating structure set of claim 1, wherein there is no insulating structure set within the second lightly doped region.
 19. The transistor with an embedded insulating structure set of claim 1, further comprising: a silicide layer contacting a top surface of the first source/drain doped region; a conductive plug contacting the silicide layer; a first shallow trench isolation and a second shallow trench isolation, wherein the first shallow trench isolation and the second shallow trench isolation are embedded within the substrate, the first shallow trench isolation and the second shallow trench define the active region, and the first shallow trench isolation contacts the first lightly doped region; wherein the conductive plug is disposed outside of the first insulating structure set and is disposed between the first insulating structure set and the first shallow trench isolation.
-