

# US Patent & Trademark Office

## Patent Public Search | Text View

---

|                      |                           |
|----------------------|---------------------------|
| United States Patent | 12401433                  |
| Kind Code            | B2                        |
| Date of Patent       | August 26, 2025           |
| Inventor(s)          | Garcia; Gabriel R. et al. |

---

### Systems and methods for spectrum analysis utilizing signal degradation data

---

#### Abstract

Methods for tracking a signal origin by a spectrum analysis and management device are disclosed. Signal characteristics of other known emitters are used for obtaining a position of an emitter of a signal of interest. In one embodiment, frequency difference of arrival technique is implemented. In another embodiment, time difference of arrival technique is implemented.

---

**Inventors:** Garcia; Gabriel R. (Severna Park, MD), Carbajal; Daniel (Severna Park, MD)

**Applicant:** Digital Global Systems, Inc. (Tysons Corner, VA)

**Family ID:** 1000008783041

**Assignee:** Digital Global Systems, Inc. (Tysons Corner, VA)

**Appl. No.:** 19/077675

**Filed:** March 12, 2025

#### Prior Publication Data

| Document Identifier | Publication Date |
|---------------------|------------------|
| US 20250211343 A1   | Jun. 26, 2025    |

#### Related U.S. Application Data

continuation parent-doc US 18955234 20241121 US 12278669 child-doc US 19077675  
continuation parent-doc US 18792113 20240801 US 12191925 20250107 child-doc US 18955234  
continuation parent-doc US 18434178 20240206 US 12095518 20240917 child-doc US 18792113  
continuation parent-doc US 18374385 20230928 US 11901963 20240213 child-doc US 18434178  
continuation parent-doc US 18137785 20230421 US 11791913 20231017 child-doc US 18374385  
continuation parent-doc US 18082210 20221215 US 11637641 20230425 child-doc US 18137785  
continuation parent-doc US 17569984 20220106 US 11588562 20230221 child-doc US 18082210

continuation parent-doc US 16751887 20200124 US 11223431 20220111 child-doc US 17569984  
continuation parent-doc US 16395987 20190426 US 10554317 20200204 child-doc US 16751887  
continuation parent-doc US 16002751 20180607 US 10284309 20190507 child-doc US 16395987  
continuation parent-doc US 15228325 20160804 US 9998243 20180612 child-doc US 16002751  
continuation parent-doc US 14743011 20150618 US 9414237 20160809 child-doc US 15228325  
continuation parent-doc US 13912893 20130607 US 9078162 20150707 child-doc US 14743011  
us-provisional-application US 61789758 20130315

---

**Publication Classification**

**Int. Cl.:** **H04B17/27** (20150101); **H04B17/23** (20150101); **H04B17/309** (20150101);  
**H04B17/318** (20150101); **H04W4/029** (20180101); **H04W16/14** (20090101);  
**H04W24/08** (20090101); **H04W24/10** (20090101); **H04W64/00** (20090101);  
**H04W72/0446** (20230101); **H04W72/0453** (20230101); **H04W72/51** (20230101);  
**H04W72/541** (20230101); H04B17/391 (20150101)

**U.S. Cl.:**

**CPC** **H04B17/27** (20150115); **H04B17/23** (20150115); **H04B17/309** (20150115);  
**H04B17/318** (20150115); **H04W4/029** (20180201); **H04W16/14** (20130101);  
**H04W24/08** (20130101); **H04W24/10** (20130101); **H04W64/006** (20130101);  
**H04W72/0446** (20130101); **H04W72/0453** (20130101); **H04W72/51** (20230101);  
**H04W72/541** (20230101); H04B17/3911 (20150115)

**Field of Classification Search**

**CPC:** H04W (24/08); H04W (24/02); H04W (72/541); H04W (16/18); H04W (84/18); H04W  
(72/542); H04W (28/0236); H04W (52/243); H04W (72/04); H04W (16/14); H04B  
(17/318); H04B (17/309); H04B (17/3911); H04B (17/26); H04B (17/336); H04B  
(1/1027); H04B (17/373); H04B (17/391)

---

**References Cited**

**U.S. PATENT DOCUMENTS**

| Patent No. | Issued Date | Patentee Name   | U.S. Cl. | CPC |
|------------|-------------|-----------------|----------|-----|
| 4215345    | 12/1979     | Frosch et al.   | N/A      | N/A |
| 4400700    | 12/1982     | Rittenbach      | N/A      | N/A |
| 4453137    | 12/1983     | Rittenbach      | N/A      | N/A |
| 4501020    | 12/1984     | Wakeman         | N/A      | N/A |
| 4581769    | 12/1985     | Grimsley et al. | N/A      | N/A |
| 4638493    | 12/1986     | Bishop et al.   | N/A      | N/A |
| 4794325    | 12/1987     | Britton et al.  | N/A      | N/A |
| 4928106    | 12/1989     | Ashjaee et al.  | N/A      | N/A |
| 5103402    | 12/1991     | Morton et al.   | N/A      | N/A |
| 5134407    | 12/1991     | Lorenz et al.   | N/A      | N/A |
| 5144642    | 12/1991     | Weinberg et al. | N/A      | N/A |
| 5166664    | 12/1991     | Fish            | N/A      | N/A |
| 5230087    | 12/1992     | Meyer et al.    | N/A      | N/A |
| 5293170    | 12/1993     | Lorenz et al.   | N/A      | N/A |

|         |         |                        |     |     |
|---------|---------|------------------------|-----|-----|
| 5343212 | 12/1993 | Rose et al.            | N/A | N/A |
| 5393713 | 12/1994 | Schwob                 | N/A | N/A |
| 5416593 | 12/1994 | Vercruysse             | N/A | N/A |
| 5448309 | 12/1994 | Won                    | N/A | N/A |
| 5506864 | 12/1995 | Schilling              | N/A | N/A |
| 5513385 | 12/1995 | Tanaka                 | N/A | N/A |
| 5548809 | 12/1995 | Lemson                 | N/A | N/A |
| 5570099 | 12/1995 | DesJardins             | N/A | N/A |
| 5589835 | 12/1995 | Gildea et al.          | N/A | N/A |
| 5612703 | 12/1996 | Mallinckrodt           | N/A | N/A |
| 5642732 | 12/1996 | Wang                   | N/A | N/A |
| 5831874 | 12/1997 | Boone et al.           | N/A | N/A |
| 5835857 | 12/1997 | Otten                  | N/A | N/A |
| 5838906 | 12/1997 | Doyle et al.           | N/A | N/A |
| 5846208 | 12/1997 | Pichlmayr et al.       | N/A | N/A |
| 5856803 | 12/1998 | Pevler                 | N/A | N/A |
| 5936575 | 12/1998 | Azzarelli et al.       | N/A | N/A |
| 6018312 | 12/1999 | Haworth                | N/A | N/A |
| 6039692 | 12/1999 | Kristoffersen          | N/A | N/A |
| 6085090 | 12/1999 | Yee et al.             | N/A | N/A |
| 6115580 | 12/1999 | Chuprun et al.         | N/A | N/A |
| 6134445 | 12/1999 | Gould et al.           | N/A | N/A |
| 6144336 | 12/1999 | Preston et al.         | N/A | N/A |
| 6157619 | 12/1999 | Ozluturk et al.        | N/A | N/A |
| 6160511 | 12/1999 | Pfeil et al.           | N/A | N/A |
| 6167277 | 12/1999 | Kawamoto               | N/A | N/A |
| 6185309 | 12/2000 | Attias                 | N/A | N/A |
| 6188715 | 12/2000 | Partyka                | N/A | N/A |
| 6191731 | 12/2000 | McBurney et al.        | N/A | N/A |
| 6198414 | 12/2000 | McPherson et al.       | N/A | N/A |
| 6249252 | 12/2000 | Dupray                 | N/A | N/A |
| 6286021 | 12/2000 | Tran et al.            | N/A | N/A |
| 6296612 | 12/2000 | Mo et al.              | N/A | N/A |
| 6304760 | 12/2000 | Thomson et al.         | N/A | N/A |
| 6314366 | 12/2000 | Farmakis et al.        | N/A | N/A |
| 6339396 | 12/2001 | Mayersak               | N/A | N/A |
| 6384776 | 12/2001 | Martin                 | N/A | N/A |
| 6400647 | 12/2001 | Huntress               | N/A | N/A |
| 6418131 | 12/2001 | Snelling et al.        | N/A | N/A |
| 6430418 | 12/2001 | Nivens et al.          | N/A | N/A |
| 6433671 | 12/2001 | Nysen                  | N/A | N/A |
| 6490318 | 12/2001 | Larsson et al.         | N/A | N/A |
| 6492945 | 12/2001 | Counselman, III et al. | N/A | N/A |
| 6512788 | 12/2002 | Kuhn et al.            | N/A | N/A |
| 6628231 | 12/2002 | Mayersak               | N/A | N/A |
| 6677895 | 12/2003 | Holt                   | N/A | N/A |
| 6697439 | 12/2003 | Trivedi et al.         | N/A | N/A |
| 6707910 | 12/2003 | Valve et al.           | N/A | N/A |
| 6711404 | 12/2003 | Arpee et al.           | N/A | N/A |
| 6741595 | 12/2003 | Maher et al.           | N/A | N/A |

|         |         |                   |           |               |
|---------|---------|-------------------|-----------|---------------|
| 6771957 | 12/2003 | Chitrapu          | N/A       | N/A           |
| 6785321 | 12/2003 | Yang et al.       | N/A       | N/A           |
| 6834180 | 12/2003 | Marshall          | 455/67.11 | H04W<br>24/00 |
| 6850557 | 12/2004 | Gronemeyer        | N/A       | N/A           |
| 6850735 | 12/2004 | Sugar et al.      | N/A       | N/A           |
| 6859831 | 12/2004 | Gelvin et al.     | N/A       | N/A           |
| 6861982 | 12/2004 | Forstrom et al.   | N/A       | N/A           |
| 6876326 | 12/2004 | Martorana         | N/A       | N/A           |
| 6898197 | 12/2004 | Lavean            | N/A       | N/A           |
| 6898235 | 12/2004 | Carlin et al.     | N/A       | N/A           |
| 6904269 | 12/2004 | Deshpande et al.  | N/A       | N/A           |
| 6985437 | 12/2005 | Vogel             | N/A       | N/A           |
| 6991514 | 12/2005 | Meloni et al.     | N/A       | N/A           |
| 7035593 | 12/2005 | Miller et al.     | N/A       | N/A           |
| 7043207 | 12/2005 | Miyazaki          | N/A       | N/A           |
| 7049965 | 12/2005 | Kelliher et al.   | N/A       | N/A           |
| 7110756 | 12/2005 | Diener            | N/A       | N/A           |
| 7116943 | 12/2005 | Sugar et al.      | N/A       | N/A           |
| 7146176 | 12/2005 | Mchenry           | N/A       | N/A           |
| 7151790 | 12/2005 | Patenaude et al.  | N/A       | N/A           |
| 7151938 | 12/2005 | Weigand           | N/A       | N/A           |
| 7152025 | 12/2005 | Lusky et al.      | N/A       | N/A           |
| 7162207 | 12/2006 | Kursula et al.    | N/A       | N/A           |
| 7171161 | 12/2006 | Miller            | N/A       | N/A           |
| 7187326 | 12/2006 | Beadle et al.     | N/A       | N/A           |
| 7206350 | 12/2006 | Korobkov et al.   | N/A       | N/A           |
| 7215716 | 12/2006 | Smith             | N/A       | N/A           |
| 7254191 | 12/2006 | Sugar et al.      | N/A       | N/A           |
| 7269151 | 12/2006 | Diener et al.     | N/A       | N/A           |
| 7289733 | 12/2006 | He                | N/A       | N/A           |
| 7292656 | 12/2006 | Kloper et al.     | N/A       | N/A           |
| 7298327 | 12/2006 | Dupray et al.     | N/A       | N/A           |
| 7340375 | 12/2007 | Patenaud et al.   | N/A       | N/A           |
| 7366463 | 12/2007 | Archer et al.     | N/A       | N/A           |
| 7408907 | 12/2007 | Diener            | N/A       | N/A           |
| 7424268 | 12/2007 | Diener et al.     | N/A       | N/A           |
| 7428270 | 12/2007 | Dubuc et al.      | N/A       | N/A           |
| 7430254 | 12/2007 | Anderson          | N/A       | N/A           |
| 7459898 | 12/2007 | Woodings          | N/A       | N/A           |
| 7466960 | 12/2007 | Sugar             | N/A       | N/A           |
| 7471683 | 12/2007 | Maher, III et al. | N/A       | N/A           |
| 7522917 | 12/2008 | Purdy, Jr. et al. | N/A       | N/A           |
| 7555262 | 12/2008 | Brenner           | N/A       | N/A           |
| 7564816 | 12/2008 | McHenry et al.    | N/A       | N/A           |
| 7595754 | 12/2008 | Mehta             | N/A       | N/A           |
| 7606335 | 12/2008 | Kloper et al.     | N/A       | N/A           |
| 7606597 | 12/2008 | Weigand           | N/A       | N/A           |
| 7620396 | 12/2008 | Floam et al.      | N/A       | N/A           |
| 7653020 | 12/2009 | Roberts           | N/A       | N/A           |

|         |         |                     |     |     |
|---------|---------|---------------------|-----|-----|
| 7676192 | 12/2009 | Wilson              | N/A | N/A |
| 7692532 | 12/2009 | Fischer et al.      | N/A | N/A |
| 7692573 | 12/2009 | Funk                | N/A | N/A |
| 7702044 | 12/2009 | Nallapureddy et al. | N/A | N/A |
| 7725110 | 12/2009 | Weigand             | N/A | N/A |
| 7728755 | 12/2009 | Jocic               | N/A | N/A |
| 7801490 | 12/2009 | Scherzer            | N/A | N/A |
| 7813742 | 12/2009 | Mitchell            | N/A | N/A |
| 7835319 | 12/2009 | Sugar               | N/A | N/A |
| 7865140 | 12/2010 | Levien et al.       | N/A | N/A |
| 7893875 | 12/2010 | Smith               | N/A | N/A |
| 7929508 | 12/2010 | Yucek et al.        | N/A | N/A |
| 7933344 | 12/2010 | Hassan et al.       | N/A | N/A |
| 7945215 | 12/2010 | Tang                | N/A | N/A |
| 7953549 | 12/2010 | Graham et al.       | N/A | N/A |
| 7965641 | 12/2010 | Ben Letaief et al.  | N/A | N/A |
| 8001901 | 12/2010 | Bass                | N/A | N/A |
| 8006195 | 12/2010 | Woodings et al.     | N/A | N/A |
| 8023957 | 12/2010 | Weigand             | N/A | N/A |
| 8026846 | 12/2010 | Mcfadden et al.     | N/A | N/A |
| 8027249 | 12/2010 | Mchenry et al.      | N/A | N/A |
| 8027690 | 12/2010 | Shellhammer         | N/A | N/A |
| 8045654 | 12/2010 | Anderson            | N/A | N/A |
| 8045660 | 12/2010 | Gupta               | N/A | N/A |
| 8055204 | 12/2010 | Livsics et al.      | N/A | N/A |
| 8059694 | 12/2010 | Junell et al.       | N/A | N/A |
| 8060017 | 12/2010 | Schlicht et al.     | N/A | N/A |
| 8060035 | 12/2010 | Haykin              | N/A | N/A |
| 8060104 | 12/2010 | Chaudhri et al.     | N/A | N/A |
| 8064840 | 12/2010 | Mchenry et al.      | N/A | N/A |
| 8077662 | 12/2010 | Srinivasan et al.   | N/A | N/A |
| RE43066 | 12/2011 | McHenry             | N/A | N/A |
| 8094610 | 12/2011 | Wang et al.         | N/A | N/A |
| 8107391 | 12/2011 | Wu et al.           | N/A | N/A |
| 8125213 | 12/2011 | Goguillon et al.    | N/A | N/A |
| 8131239 | 12/2011 | Walker et al.       | N/A | N/A |
| 8134493 | 12/2011 | Noble et al.        | N/A | N/A |
| 8151311 | 12/2011 | Huffman et al.      | N/A | N/A |
| 8155039 | 12/2011 | Wu et al.           | N/A | N/A |
| 8155649 | 12/2011 | Mchenry et al.      | N/A | N/A |
| 8160839 | 12/2011 | Woodings et al.     | N/A | N/A |
| 8170577 | 12/2011 | Singh               | N/A | N/A |
| 8175539 | 12/2011 | Diener et al.       | N/A | N/A |
| 8184653 | 12/2011 | Dain et al.         | N/A | N/A |
| 8193981 | 12/2011 | Hwang et al.        | N/A | N/A |
| 8213868 | 12/2011 | Du et al.           | N/A | N/A |
| 8224254 | 12/2011 | Haykin              | N/A | N/A |
| 8229368 | 12/2011 | Immendorf et al.    | N/A | N/A |
| 8233928 | 12/2011 | Stanforth et al.    | N/A | N/A |
| 8238247 | 12/2011 | Wu et al.           | N/A | N/A |

|         |         |                      |     |     |
|---------|---------|----------------------|-----|-----|
| 8249028 | 12/2011 | Porras et al.        | N/A | N/A |
| 8249631 | 12/2011 | Sawai                | N/A | N/A |
| 8260207 | 12/2011 | Srinivasan et al.    | N/A | N/A |
| 8265684 | 12/2011 | Sawai                | N/A | N/A |
| 8279786 | 12/2011 | Smith et al.         | N/A | N/A |
| 8280433 | 12/2011 | Quinn et al.         | N/A | N/A |
| 8289907 | 12/2011 | Seidel et al.        | N/A | N/A |
| 8290503 | 12/2011 | Sadek et al.         | N/A | N/A |
| 8295859 | 12/2011 | Yarkan et al.        | N/A | N/A |
| 8295877 | 12/2011 | Hui et al.           | N/A | N/A |
| 8301075 | 12/2011 | Sherman et al.       | N/A | N/A |
| 8305215 | 12/2011 | Markhovsky et al.    | N/A | N/A |
| 8311483 | 12/2011 | Tillman et al.       | N/A | N/A |
| 8311509 | 12/2011 | Feher                | N/A | N/A |
| 8315571 | 12/2011 | Lindoff et al.       | N/A | N/A |
| 8320910 | 12/2011 | Bobier               | N/A | N/A |
| 8326240 | 12/2011 | Kadambe et al.       | N/A | N/A |
| 8326309 | 12/2011 | Mody et al.          | N/A | N/A |
| 8326313 | 12/2011 | McHenry et al.       | N/A | N/A |
| 8335204 | 12/2011 | Samarasooriya et al. | N/A | N/A |
| 8346273 | 12/2012 | Weigand              | N/A | N/A |
| 8350970 | 12/2012 | Birkett et al.       | N/A | N/A |
| 8352223 | 12/2012 | Anthony et al.       | N/A | N/A |
| 8358723 | 12/2012 | Hamkins et al.       | N/A | N/A |
| 8364188 | 12/2012 | Srinivasan et al.    | N/A | N/A |
| 8369305 | 12/2012 | Diener et al.        | N/A | N/A |
| 8373759 | 12/2012 | Samarasooriya et al. | N/A | N/A |
| 8391794 | 12/2012 | Sawai et al.         | N/A | N/A |
| 8391796 | 12/2012 | Srinivasan et al.    | N/A | N/A |
| 8401564 | 12/2012 | Singh                | N/A | N/A |
| 8406776 | 12/2012 | Jallon               | N/A | N/A |
| 8406780 | 12/2012 | Mueck                | N/A | N/A |
| RE44142 | 12/2012 | Wilson               | N/A | N/A |
| 8421676 | 12/2012 | Moshfeghi            | N/A | N/A |
| 8422453 | 12/2012 | Abedi                | N/A | N/A |
| 8422958 | 12/2012 | Du et al.            | N/A | N/A |
| RE44237 | 12/2012 | Mchenry              | N/A | N/A |
| 8437700 | 12/2012 | Mody et al.          | N/A | N/A |
| 8442445 | 12/2012 | Mody et al.          | N/A | N/A |
| 8447237 | 12/2012 | Reial et al.         | N/A | N/A |
| 8451751 | 12/2012 | Challapali et al.    | N/A | N/A |
| 8463195 | 12/2012 | Shellhammer          | N/A | N/A |
| 8467353 | 12/2012 | Proctor              | N/A | N/A |
| 8467996 | 12/2012 | Perez et al.         | N/A | N/A |
| 8483155 | 12/2012 | Banerjea et al.      | N/A | N/A |
| 8494464 | 12/2012 | Kadambe et al.       | N/A | N/A |
| 8503955 | 12/2012 | Kang et al.          | N/A | N/A |
| 8504087 | 12/2012 | Stanforth et al.     | N/A | N/A |
| 8514729 | 12/2012 | Blackwell            | N/A | N/A |
| 8515473 | 12/2012 | Mody et al.          | N/A | N/A |

|         |         |                   |     |     |
|---------|---------|-------------------|-----|-----|
| 8520606 | 12/2012 | Cleveland         | N/A | N/A |
| RE44492 | 12/2012 | Mchenry           | N/A | N/A |
| 8526974 | 12/2012 | Olsson et al.     | N/A | N/A |
| 8532686 | 12/2012 | Schmidt et al.    | N/A | N/A |
| 8538339 | 12/2012 | Hu et al.         | N/A | N/A |
| 8548521 | 12/2012 | Hui et al.        | N/A | N/A |
| 8554264 | 12/2012 | Gibbons et al.    | N/A | N/A |
| 8559301 | 12/2012 | Mchenry et al.    | N/A | N/A |
| 8565811 | 12/2012 | Tan et al.        | N/A | N/A |
| 8599024 | 12/2012 | Bloy              | N/A | N/A |
| 8718838 | 12/2013 | Kokkeby et al.    | N/A | N/A |
| 8761051 | 12/2013 | Brisebois et al.  | N/A | N/A |
| 8773966 | 12/2013 | Petrovic et al.   | N/A | N/A |
| 8780968 | 12/2013 | Garcia et al.     | N/A | N/A |
| 8792901 | 12/2013 | Schmidt           | N/A | N/A |
| 8798548 | 12/2013 | Carbajal          | N/A | N/A |
| 8805291 | 12/2013 | Garcia et al.     | N/A | N/A |
| 8818283 | 12/2013 | McHenry et al.    | N/A | N/A |
| 8824536 | 12/2013 | Garcia et al.     | N/A | N/A |
| 8843155 | 12/2013 | Burton et al.     | N/A | N/A |
| 8886210 | 12/2013 | Sugar             | N/A | N/A |
| 8941491 | 12/2014 | Polk et al.       | N/A | N/A |
| 8977212 | 12/2014 | Carbajal          | N/A | N/A |
| 9007262 | 12/2014 | Witzgall          | N/A | N/A |
| 9008587 | 12/2014 | Carbajal          | N/A | N/A |
| 9078162 | 12/2014 | Garcia et al.     | N/A | N/A |
| 9143968 | 12/2014 | Manku et al.      | N/A | N/A |
| 9185591 | 12/2014 | Carbajal          | N/A | N/A |
| 9229102 | 12/2015 | Wright et al.     | N/A | N/A |
| 9245378 | 12/2015 | Villagomez et al. | N/A | N/A |
| 9288683 | 12/2015 | Garcia et al.     | N/A | N/A |
| 9356727 | 12/2015 | Immendorf et al.  | N/A | N/A |
| 9397619 | 12/2015 | Lozhkin           | N/A | N/A |
| 9412278 | 12/2015 | Gong et al.       | N/A | N/A |
| 9413574 | 12/2015 | Timofeev et al.   | N/A | N/A |
| 9414237 | 12/2015 | Garcia et al.     | N/A | N/A |
| 9439078 | 12/2015 | Menon et al.      | N/A | N/A |
| 9466881 | 12/2015 | Berry et al.      | N/A | N/A |
| 9529360 | 12/2015 | Melamed et al.    | N/A | N/A |
| 9537586 | 12/2016 | Carbajal          | N/A | N/A |
| 9538040 | 12/2016 | Goergen et al.    | N/A | N/A |
| 9572055 | 12/2016 | Immendorf et al.  | N/A | N/A |
| 9635669 | 12/2016 | Gormley et al.    | N/A | N/A |
| 9658341 | 12/2016 | Mathews et al.    | N/A | N/A |
| 9674684 | 12/2016 | Mendelson         | N/A | N/A |
| 9674836 | 12/2016 | Gormley et al.    | N/A | N/A |
| 9686789 | 12/2016 | Gormley et al.    | N/A | N/A |
| 9715009 | 12/2016 | Parker et al.     | N/A | N/A |
| 9749069 | 12/2016 | Garcia et al.     | N/A | N/A |
| 9755972 | 12/2016 | Mao et al.        | N/A | N/A |

|          |         |                       |     |     |
|----------|---------|-----------------------|-----|-----|
| 9767699  | 12/2016 | Borghese et al.       | N/A | N/A |
| 9769834  | 12/2016 | Immendorf et al.      | N/A | N/A |
| 9805273  | 12/2016 | Seeber et al.         | N/A | N/A |
| 9819441  | 12/2016 | Immendorf et al.      | N/A | N/A |
| 9858947  | 12/2017 | Hearing et al.        | N/A | N/A |
| 9862489  | 12/2017 | Weinstein et al.      | N/A | N/A |
| 9923700  | 12/2017 | Gormley et al.        | N/A | N/A |
| 9942775  | 12/2017 | Yun et al.            | N/A | N/A |
| 9973278  | 12/2017 | Wang et al.           | N/A | N/A |
| 9989633  | 12/2017 | Pandey et al.         | N/A | N/A |
| 9998243  | 12/2017 | Garcia et al.         | N/A | N/A |
| 10027429 | 12/2017 | Kiannejad             | N/A | N/A |
| 10104559 | 12/2017 | Immendorf et al.      | N/A | N/A |
| 10157548 | 12/2017 | Priest                | N/A | N/A |
| 10194324 | 12/2018 | Yun et al.            | N/A | N/A |
| 10198955 | 12/2018 | Boyd et al.           | N/A | N/A |
| 10227429 | 12/2018 | Watanabe et al.       | N/A | N/A |
| 10235523 | 12/2018 | Keller, III et al.    | N/A | N/A |
| 10241140 | 12/2018 | Moinuddin             | N/A | N/A |
| 10251242 | 12/2018 | Rosen et al.          | N/A | N/A |
| 10281570 | 12/2018 | Parker et al.         | N/A | N/A |
| 10389616 | 12/2018 | Ryan et al.           | N/A | N/A |
| 10393784 | 12/2018 | Logan et al.          | N/A | N/A |
| 10408936 | 12/2018 | Van Voorst            | N/A | N/A |
| 10459020 | 12/2018 | Dzierwa et al.        | N/A | N/A |
| 10540905 | 12/2019 | Bohanan et al.        | N/A | N/A |
| 10552738 | 12/2019 | Holt et al.           | N/A | N/A |
| 10587352 | 12/2019 | Kiannejad             | N/A | N/A |
| 10594034 | 12/2019 | Tran et al.           | N/A | N/A |
| 10613209 | 12/2019 | Emami et al.          | N/A | N/A |
| 10642813 | 12/2019 | Lazier et al.         | N/A | N/A |
| 10698076 | 12/2019 | Jones et al.          | N/A | N/A |
| 10700721 | 12/2019 | Ayala et al.          | N/A | N/A |
| 10701574 | 12/2019 | Gormley et al.        | N/A | N/A |
| 10764718 | 12/2019 | Boettcher et al.      | N/A | N/A |
| 10784974 | 12/2019 | Menon                 | N/A | N/A |
| 10811771 | 12/2019 | Tran et al.           | N/A | N/A |
| 10907940 | 12/2020 | Parker et al.         | N/A | N/A |
| 10916845 | 12/2020 | Tran et al.           | N/A | N/A |
| 10917797 | 12/2020 | Menon et al.          | N/A | N/A |
| 11012340 | 12/2020 | Ryan et al.           | N/A | N/A |
| 11035929 | 12/2020 | Parker et al.         | N/A | N/A |
| 11063653 | 12/2020 | Ottersten et al.      | N/A | N/A |
| 11190233 | 12/2020 | Lo et al.             | N/A | N/A |
| 11223431 | 12/2021 | Garcia et al.         | N/A | N/A |
| 11265652 | 12/2021 | Kallai et al.         | N/A | N/A |
| 11321282 | 12/2021 | Tran                  | N/A | N/A |
| 11334807 | 12/2021 | O'Shea et al.         | N/A | N/A |
| 11336011 | 12/2021 | Tran et al.           | N/A | N/A |
| 11516071 | 12/2021 | Karapantelakis et al. | N/A | N/A |



|              |         |                   |     |     |
|--------------|---------|-------------------|-----|-----|
| 11637641     | 12/2022 | Garcia et al.     | N/A | N/A |
| 11663992     | 12/2022 | Canberk et al.    | N/A | N/A |
| 11671839     | 12/2022 | Guo et al.        | N/A | N/A |
| 11700304     | 12/2022 | Brown, Jr. et al. | N/A | N/A |
| 11757185     | 12/2022 | Tran et al.       | N/A | N/A |
| 11777783     | 12/2022 | Meirosu et al.    | N/A | N/A |
| 11791913     | 12/2022 | Garcia et al.     | N/A | N/A |
| 11871103     | 12/2023 | Kleinbeck         | N/A | N/A |
| 11874674     | 12/2023 | Groden et al.     | N/A | N/A |
| 11880888     | 12/2023 | Gold et al.       | N/A | N/A |
| 11889351     | 12/2023 | Tagg              | N/A | N/A |
| 11910305     | 12/2023 | Buyukdura         | N/A | N/A |
| 12095518     | 12/2023 | Garcia et al.     | N/A | N/A |
| 12156037     | 12/2023 | Montalvo          | N/A | N/A |
| 12183213     | 12/2023 | Kleinbeck et al.  | N/A | N/A |
| 2001/0000959 | 12/2000 | Campana et al.    | N/A | N/A |
| 2001/0005423 | 12/2000 | Rhoads            | N/A | N/A |
| 2001/0016503 | 12/2000 | Kang              | N/A | N/A |
| 2001/0020220 | 12/2000 | Kurosawa          | N/A | N/A |
| 2002/0044082 | 12/2001 | Woodington et al. | N/A | N/A |
| 2002/0070889 | 12/2001 | Griffin et al.    | N/A | N/A |
| 2002/0072331 | 12/2001 | Fischer et al.    | N/A | N/A |
| 2002/0097184 | 12/2001 | Mayersak          | N/A | N/A |
| 2002/0119754 | 12/2001 | Wakutsu et al.    | N/A | N/A |
| 2002/0161775 | 12/2001 | Lasensky et al.   | N/A | N/A |
| 2002/0173341 | 12/2001 | Abdelmonem et al. | N/A | N/A |
| 2003/0013454 | 12/2002 | Hunzinger         | N/A | N/A |
| 2003/0040277 | 12/2002 | Deats             | N/A | N/A |
| 2003/0083091 | 12/2002 | Nuutinen et al.   | N/A | N/A |
| 2003/0087648 | 12/2002 | Mezhvinsky et al. | N/A | N/A |
| 2003/0104831 | 12/2002 | Razavilar et al.  | N/A | N/A |
| 2003/0144601 | 12/2002 | Prichep           | N/A | N/A |
| 2003/0145008 | 12/2002 | Burrell           | N/A | N/A |
| 2003/0145328 | 12/2002 | Rabinowitz et al. | N/A | N/A |
| 2003/0198304 | 12/2002 | Sugar et al.      | N/A | N/A |
| 2003/0206640 | 12/2002 | Malvar et al.     | N/A | N/A |
| 2003/0224801 | 12/2002 | Lovberg et al.    | N/A | N/A |
| 2003/0232612 | 12/2002 | Richards et al.   | N/A | N/A |
| 2004/0001688 | 12/2003 | Shen              | N/A | N/A |
| 2004/0023674 | 12/2003 | Miller            | N/A | N/A |
| 2004/0127214 | 12/2003 | Reddy et al.      | N/A | N/A |
| 2004/0137915 | 12/2003 | Diener et al.     | N/A | N/A |
| 2004/0147254 | 12/2003 | Reddy et al.      | N/A | N/A |
| 2004/0171390 | 12/2003 | Chitrapu          | N/A | N/A |
| 2004/0203725 | 12/2003 | Lahav et al.      | N/A | N/A |
| 2004/0203826 | 12/2003 | Sugar et al.      | N/A | N/A |
| 2004/0208238 | 12/2003 | Thomas et al.     | N/A | N/A |
| 2004/0219885 | 12/2003 | Sugar et al.      | N/A | N/A |
| 2004/0233100 | 12/2003 | Dibble et al.     | N/A | N/A |
| 2005/0003828 | 12/2004 | Sugar et al.      | N/A | N/A |

|              |         |                   |     |     |
|--------------|---------|-------------------|-----|-----|
| 2005/0096026 | 12/2004 | Chitrapu et al.   | N/A | N/A |
| 2005/0107102 | 12/2004 | Yoon et al.       | N/A | N/A |
| 2005/0114023 | 12/2004 | Williamson et al. | N/A | N/A |
| 2005/0152317 | 12/2004 | Awater et al.     | N/A | N/A |
| 2005/0159928 | 12/2004 | Moser             | N/A | N/A |
| 2005/0176401 | 12/2004 | Nanda et al.      | N/A | N/A |
| 2005/0185618 | 12/2004 | Friday et al.     | N/A | N/A |
| 2005/0192727 | 12/2004 | Shostak et al.    | N/A | N/A |
| 2005/0227625 | 12/2004 | Diener            | N/A | N/A |
| 2005/0285792 | 12/2004 | Sugar et al.      | N/A | N/A |
| 2006/0025118 | 12/2005 | Chitrapu et al.   | N/A | N/A |
| 2006/0047704 | 12/2005 | Gopalakrishnan    | N/A | N/A |
| 2006/0074558 | 12/2005 | Williamson et al. | N/A | N/A |
| 2006/0080040 | 12/2005 | Garczarek et al.  | N/A | N/A |
| 2006/0111899 | 12/2005 | Padhi et al.      | N/A | N/A |
| 2006/0128311 | 12/2005 | Tesfai            | N/A | N/A |
| 2006/0133263 | 12/2005 | Bernard et al.    | N/A | N/A |
| 2006/0199546 | 12/2005 | Durgin            | N/A | N/A |
| 2006/0235574 | 12/2005 | Lapinski et al.   | N/A | N/A |
| 2006/0238417 | 12/2005 | Jendbro et al.    | N/A | N/A |
| 2006/0258347 | 12/2005 | Chitrapu          | N/A | N/A |
| 2007/0003059 | 12/2006 | Langelaar         | N/A | N/A |
| 2007/0016412 | 12/2006 | Mehrotra et al.   | N/A | N/A |
| 2007/0041481 | 12/2006 | Malkemes et al.   | N/A | N/A |
| 2007/0049823 | 12/2006 | Li                | N/A | N/A |
| 2007/0076657 | 12/2006 | Woodings et al.   | N/A | N/A |
| 2007/0098089 | 12/2006 | Li et al.         | N/A | N/A |
| 2007/0111746 | 12/2006 | Anderson          | N/A | N/A |
| 2007/0126636 | 12/2006 | Zhang et al.      | N/A | N/A |
| 2007/0149216 | 12/2006 | Misikangas        | N/A | N/A |
| 2007/0168580 | 12/2006 | Schumacher        | N/A | N/A |
| 2007/0171889 | 12/2006 | Kwon et al.       | N/A | N/A |
| 2007/0203645 | 12/2006 | Dees et al.       | N/A | N/A |
| 2007/0223419 | 12/2006 | Ji et al.         | N/A | N/A |
| 2007/0233336 | 12/2006 | Serguei et al.    | N/A | N/A |
| 2007/0233409 | 12/2006 | Boyan et al.      | N/A | N/A |
| 2007/0273581 | 12/2006 | Garrison et al.   | N/A | N/A |
| 2007/0293171 | 12/2006 | Li et al.         | N/A | N/A |
| 2007/0296591 | 12/2006 | Frederick et al.  | N/A | N/A |
| 2007/0297541 | 12/2006 | Mcgehee           | N/A | N/A |
| 2008/0001735 | 12/2007 | Tran              | N/A | N/A |
| 2008/0010040 | 12/2007 | Mcgehee           | N/A | N/A |
| 2008/0090563 | 12/2007 | Chitrapu          | N/A | N/A |
| 2008/0113634 | 12/2007 | Gates et al.      | N/A | N/A |
| 2008/0123731 | 12/2007 | Wegener           | N/A | N/A |
| 2008/0129367 | 12/2007 | Murata et al.     | N/A | N/A |
| 2008/0130519 | 12/2007 | Bahl et al.       | N/A | N/A |
| 2008/0133190 | 12/2007 | Peretz et al.     | N/A | N/A |
| 2008/0180325 | 12/2007 | Chung et al.      | N/A | N/A |
| 2008/0186235 | 12/2007 | Struckman et al.  | N/A | N/A |

|              |         |                   |     |     |
|--------------|---------|-------------------|-----|-----|
| 2008/0195584 | 12/2007 | Nath et al.       | N/A | N/A |
| 2008/0209117 | 12/2007 | Kajigaya          | N/A | N/A |
| 2008/0211481 | 12/2007 | Chen              | N/A | N/A |
| 2008/0214903 | 12/2007 | Orbach            | N/A | N/A |
| 2008/0252516 | 12/2007 | Ho et al.         | N/A | N/A |
| 2008/0261509 | 12/2007 | Sen               | N/A | N/A |
| 2008/0293353 | 12/2007 | Mody et al.       | N/A | N/A |
| 2009/0006103 | 12/2008 | Koishida et al.   | N/A | N/A |
| 2009/0011713 | 12/2008 | Abusubaih et al.  | N/A | N/A |
| 2009/0018422 | 12/2008 | Banet et al.      | N/A | N/A |
| 2009/0021420 | 12/2008 | Sahinoglu         | N/A | N/A |
| 2009/0046003 | 12/2008 | Tung et al.       | N/A | N/A |
| 2009/0046625 | 12/2008 | Diener et al.     | N/A | N/A |
| 2009/0066578 | 12/2008 | Beadle et al.     | N/A | N/A |
| 2009/0086993 | 12/2008 | Kawaguchi et al.  | N/A | N/A |
| 2009/0103094 | 12/2008 | Hilfiker et al.   | N/A | N/A |
| 2009/0111463 | 12/2008 | Simms et al.      | N/A | N/A |
| 2009/0131067 | 12/2008 | Aaron             | N/A | N/A |
| 2009/0135046 | 12/2008 | Steele et al.     | N/A | N/A |
| 2009/0136052 | 12/2008 | Hohlfeld et al.   | N/A | N/A |
| 2009/0143019 | 12/2008 | Shellhammer       | N/A | N/A |
| 2009/0146881 | 12/2008 | Mesecher          | N/A | N/A |
| 2009/0149202 | 12/2008 | Hill et al.       | N/A | N/A |
| 2009/0190511 | 12/2008 | Li et al.         | N/A | N/A |
| 2009/0207950 | 12/2008 | Tsuruta et al.    | N/A | N/A |
| 2009/0224957 | 12/2008 | Chung et al.      | N/A | N/A |
| 2009/0245327 | 12/2008 | Michaels          | N/A | N/A |
| 2009/0278733 | 12/2008 | Haworth           | N/A | N/A |
| 2009/0280748 | 12/2008 | Shan et al.       | N/A | N/A |
| 2009/0282130 | 12/2008 | Antoniou et al.   | N/A | N/A |
| 2009/0285173 | 12/2008 | Koorapaty et al.  | N/A | N/A |
| 2009/0286563 | 12/2008 | Ji et al.         | N/A | N/A |
| 2009/0322510 | 12/2008 | Berger et al.     | N/A | N/A |
| 2010/0020707 | 12/2009 | Woodings          | N/A | N/A |
| 2010/0044122 | 12/2009 | Sleeman et al.    | N/A | N/A |
| 2010/0056200 | 12/2009 | Tolonen           | N/A | N/A |
| 2010/0075704 | 12/2009 | Mchenry et al.    | N/A | N/A |
| 2010/0109936 | 12/2009 | Levy              | N/A | N/A |
| 2010/0142454 | 12/2009 | Chang             | N/A | N/A |
| 2010/0150122 | 12/2009 | Berger et al.     | N/A | N/A |
| 2010/0172443 | 12/2009 | Shim et al.       | N/A | N/A |
| 2010/0173586 | 12/2009 | Mchenry et al.    | N/A | N/A |
| 2010/0176988 | 12/2009 | Maezawa et al.    | N/A | N/A |
| 2010/0177710 | 12/2009 | Gutkin et al.     | N/A | N/A |
| 2010/0220011 | 12/2009 | Heuser            | N/A | N/A |
| 2010/0253512 | 12/2009 | Wagner et al.     | N/A | N/A |
| 2010/0255794 | 12/2009 | Agnew             | N/A | N/A |
| 2010/0255801 | 12/2009 | Gunasekara et al. | N/A | N/A |
| 2010/0259998 | 12/2009 | Kwon et al.       | N/A | N/A |
| 2010/0279680 | 12/2009 | Reudink           | N/A | N/A |

|              |         |                      |     |     |
|--------------|---------|----------------------|-----|-----|
| 2010/0292930 | 12/2009 | Koster et al.        | N/A | N/A |
| 2010/0306249 | 12/2009 | Hill et al.          | N/A | N/A |
| 2010/0309317 | 12/2009 | Wu et al.            | N/A | N/A |
| 2010/0325621 | 12/2009 | Andrade et al.       | N/A | N/A |
| 2011/0022342 | 12/2010 | Pandharipande et al. | N/A | N/A |
| 2011/0045781 | 12/2010 | Shellhammer et al.   | N/A | N/A |
| 2011/0053604 | 12/2010 | Kim et al.           | N/A | N/A |
| 2011/0059747 | 12/2010 | Lindoff et al.       | N/A | N/A |
| 2011/0070885 | 12/2010 | Ruuska et al.        | N/A | N/A |
| 2011/0074631 | 12/2010 | Parker               | N/A | N/A |
| 2011/0077017 | 12/2010 | Yu et al.            | N/A | N/A |
| 2011/0087639 | 12/2010 | Gurney               | N/A | N/A |
| 2011/0090939 | 12/2010 | Diener et al.        | N/A | N/A |
| 2011/0096770 | 12/2010 | Henry                | N/A | N/A |
| 2011/0102258 | 12/2010 | Underbrink et al.    | N/A | N/A |
| 2011/0111751 | 12/2010 | Markhovsky et al.    | N/A | N/A |
| 2011/0116484 | 12/2010 | Henry                | N/A | N/A |
| 2011/0117869 | 12/2010 | Woodings             | N/A | N/A |
| 2011/0122855 | 12/2010 | Henry                | N/A | N/A |
| 2011/0129006 | 12/2010 | Jung et al.          | N/A | N/A |
| 2011/0131260 | 12/2010 | Mody                 | N/A | N/A |
| 2011/0134878 | 12/2010 | Geiger et al.        | N/A | N/A |
| 2011/0136478 | 12/2010 | Trigui               | N/A | N/A |
| 2011/0151876 | 12/2010 | Ishii et al.         | N/A | N/A |
| 2011/0183621 | 12/2010 | Quan et al.          | N/A | N/A |
| 2011/0183685 | 12/2010 | Burton et al.        | N/A | N/A |
| 2011/0185059 | 12/2010 | Adnani et al.        | N/A | N/A |
| 2011/0188544 | 12/2010 | Ponnuswamy           | N/A | N/A |
| 2011/0235728 | 12/2010 | Karabinis            | N/A | N/A |
| 2011/0237243 | 12/2010 | Guvenc et al.        | N/A | N/A |
| 2011/0241923 | 12/2010 | Chernukhin           | N/A | N/A |
| 2011/0273328 | 12/2010 | Parker               | N/A | N/A |
| 2011/0286555 | 12/2010 | Cho et al.           | N/A | N/A |
| 2011/0286604 | 12/2010 | Matsuo               | N/A | N/A |
| 2011/0287779 | 12/2010 | Harper               | N/A | N/A |
| 2011/0299481 | 12/2010 | Kim et al.           | N/A | N/A |
| 2011/0300849 | 12/2010 | Chan                 | N/A | N/A |
| 2011/0319120 | 12/2010 | Chen et al.          | N/A | N/A |
| 2012/0014332 | 12/2011 | Smith et al.         | N/A | N/A |
| 2012/0032854 | 12/2011 | Bull et al.          | N/A | N/A |
| 2012/0039284 | 12/2011 | Barbieri et al.      | N/A | N/A |
| 2012/0040602 | 12/2011 | Charland             | N/A | N/A |
| 2012/0047544 | 12/2011 | Bouchard             | N/A | N/A |
| 2012/0052869 | 12/2011 | Lindoff et al.       | N/A | N/A |
| 2012/0058775 | 12/2011 | Dupray et al.        | N/A | N/A |
| 2012/0063302 | 12/2011 | Damnjanovic et al.   | N/A | N/A |
| 2012/0071188 | 12/2011 | Wang et al.          | N/A | N/A |
| 2012/0072986 | 12/2011 | Livsics et al.       | N/A | N/A |
| 2012/0077510 | 12/2011 | Chen et al.          | N/A | N/A |
| 2012/0078071 | 12/2011 | Bohm et al.          | N/A | N/A |

|              |         |                           |     |     |
|--------------|---------|---------------------------|-----|-----|
| 2012/0081248 | 12/2011 | Kennedy et al.            | N/A | N/A |
| 2012/0094681 | 12/2011 | Freda et al.              | N/A | N/A |
| 2012/0100810 | 12/2011 | Oksanen et al.            | N/A | N/A |
| 2012/0105066 | 12/2011 | Marvin et al.             | N/A | N/A |
| 2012/0115522 | 12/2011 | Nama et al.               | N/A | N/A |
| 2012/0115525 | 12/2011 | Kang et al.               | N/A | N/A |
| 2012/0120892 | 12/2011 | Freda et al.              | N/A | N/A |
| 2012/0129522 | 12/2011 | Kim et al.                | N/A | N/A |
| 2012/0140236 | 12/2011 | Babbitt et al.            | N/A | N/A |
| 2012/0142386 | 12/2011 | Mody et al.               | N/A | N/A |
| 2012/0148068 | 12/2011 | Chandra et al.            | N/A | N/A |
| 2012/0148069 | 12/2011 | Bai et al.                | N/A | N/A |
| 2012/0155217 | 12/2011 | Dellinger et al.          | N/A | N/A |
| 2012/0169424 | 12/2011 | Pinarello et al.          | N/A | N/A |
| 2012/0182430 | 12/2011 | Birkett et al.            | N/A | N/A |
| 2012/0195269 | 12/2011 | Kang et al.               | N/A | N/A |
| 2012/0212628 | 12/2011 | Wu et al.                 | N/A | N/A |
| 2012/0214511 | 12/2011 | Vartanian et al.          | N/A | N/A |
| 2012/0230214 | 12/2011 | Kozisek et al.            | N/A | N/A |
| 2012/0246392 | 12/2011 | Cheon                     | N/A | N/A |
| 2012/0264388 | 12/2011 | Guo et al.                | N/A | N/A |
| 2012/0264445 | 12/2011 | Lee et al.                | N/A | N/A |
| 2012/0275354 | 12/2011 | Villain                   | N/A | N/A |
| 2012/0281000 | 12/2011 | Woodings                  | N/A | N/A |
| 2012/0282942 | 12/2011 | Uusitalo et al.           | N/A | N/A |
| 2012/0295575 | 12/2011 | Nam                       | N/A | N/A |
| 2012/0302190 | 12/2011 | Mchenry                   | N/A | N/A |
| 2012/0302263 | 12/2011 | Tinnakornsrisuphap et al. | N/A | N/A |
| 2012/0309288 | 12/2011 | Lu                        | N/A | N/A |
| 2012/0321024 | 12/2011 | Wasiewicz et al.          | N/A | N/A |
| 2012/0322487 | 12/2011 | Stanforth                 | N/A | N/A |
| 2013/0005240 | 12/2012 | Novak et al.              | N/A | N/A |
| 2013/0005374 | 12/2012 | Uusitalo et al.           | N/A | N/A |
| 2013/0012134 | 12/2012 | Jin et al.                | N/A | N/A |
| 2013/0017794 | 12/2012 | Kloper et al.             | N/A | N/A |
| 2013/0023285 | 12/2012 | Markhovsky et al.         | N/A | N/A |
| 2013/0028111 | 12/2012 | Dain et al.               | N/A | N/A |
| 2013/0035108 | 12/2012 | Joslyn et al.             | N/A | N/A |
| 2013/0035128 | 12/2012 | Chan et al.               | N/A | N/A |
| 2013/0045754 | 12/2012 | Markhovsky et al.         | N/A | N/A |
| 2013/0052939 | 12/2012 | Anniballi et al.          | N/A | N/A |
| 2013/0053054 | 12/2012 | Lovitt et al.             | N/A | N/A |
| 2013/0062334 | 12/2012 | Bilchinsky et al.         | N/A | N/A |
| 2013/0064197 | 12/2012 | Novak et al.              | N/A | N/A |
| 2013/0064328 | 12/2012 | Adnani et al.             | N/A | N/A |
| 2013/0070639 | 12/2012 | Demura et al.             | N/A | N/A |
| 2013/0090071 | 12/2012 | Abraham et al.            | N/A | N/A |
| 2013/0095843 | 12/2012 | Smith et al.              | N/A | N/A |
| 2013/0100154 | 12/2012 | Woodings et al.           | N/A | N/A |

|              |         |                      |            |               |
|--------------|---------|----------------------|------------|---------------|
| 2013/0103684 | 12/2012 | Yee et al.           | N/A        | N/A           |
| 2013/0113659 | 12/2012 | Morgan               | N/A        | N/A           |
| 2013/0165051 | 12/2012 | Li et al.            | N/A        | N/A           |
| 2013/0165134 | 12/2012 | Touag et al.         | N/A        | N/A           |
| 2013/0165170 | 12/2012 | Kang                 | N/A        | N/A           |
| 2013/0183989 | 12/2012 | Hasegawa et al.      | N/A        | N/A           |
| 2013/0183994 | 12/2012 | Ringstroem et al.    | N/A        | N/A           |
| 2013/0184022 | 12/2012 | Schmidt              | N/A        | N/A           |
| 2013/0190003 | 12/2012 | Smith et al.         | N/A        | N/A           |
| 2013/0190028 | 12/2012 | Wang et al.          | N/A        | N/A           |
| 2013/0196677 | 12/2012 | Smith et al.         | N/A        | N/A           |
| 2013/0208587 | 12/2012 | Bala et al.          | N/A        | N/A           |
| 2013/0210457 | 12/2012 | Kummetz              | N/A        | N/A           |
| 2013/0210473 | 12/2012 | Weigand              | N/A        | N/A           |
| 2013/0217406 | 12/2012 | Villardi et al.      | N/A        | N/A           |
| 2013/0217408 | 12/2012 | Difazio et al.       | N/A        | N/A           |
| 2013/0217450 | 12/2012 | Kanj et al.          | N/A        | N/A           |
| 2013/0231121 | 12/2012 | Kwak et al.          | N/A        | N/A           |
| 2013/0237212 | 12/2012 | Khayrallah et al.    | N/A        | N/A           |
| 2013/0242792 | 12/2012 | Woodings             | N/A        | N/A           |
| 2013/0242934 | 12/2012 | Ueda et al.          | N/A        | N/A           |
| 2013/0260703 | 12/2012 | Actis et al.         | N/A        | N/A           |
| 2013/0265198 | 12/2012 | Stroud               | N/A        | N/A           |
| 2013/0272436 | 12/2012 | Makhlouf et al.      | N/A        | N/A           |
| 2013/0275346 | 12/2012 | Srikanteswara et al. | N/A        | N/A           |
| 2013/0279556 | 12/2012 | Seller               | N/A        | N/A           |
| 2013/0288734 | 12/2012 | Mody et al.          | N/A        | N/A           |
| 2013/0309975 | 12/2012 | Kpodzo et al.        | N/A        | N/A           |
| 2013/0315112 | 12/2012 | Gormley et al.       | N/A        | N/A           |
| 2013/0329690 | 12/2012 | Kim et al.           | N/A        | N/A           |
| 2013/0331114 | 12/2012 | Gormley et al.       | N/A        | N/A           |
| 2014/0003547 | 12/2013 | Williams et al.      | N/A        | N/A           |
| 2014/0015796 | 12/2013 | Philipp              | N/A        | N/A           |
| 2014/0018683 | 12/2013 | Park et al.          | N/A        | N/A           |
| 2014/0024405 | 12/2013 | Qiu                  | N/A        | N/A           |
| 2014/0062781 | 12/2013 | Mathews              | 342/357.64 | G01S<br>19/11 |
| 2014/0064723 | 12/2013 | Adles et al.         | N/A        | N/A           |
| 2014/0066060 | 12/2013 | Ngai                 | N/A        | N/A           |
| 2014/0073261 | 12/2013 | Hassan et al.        | N/A        | N/A           |
| 2014/0086212 | 12/2013 | Kafle et al.         | N/A        | N/A           |
| 2014/0128032 | 12/2013 | Muthukumar et al.    | N/A        | N/A           |
| 2014/0139374 | 12/2013 | Wellman et al.       | N/A        | N/A           |
| 2014/0163309 | 12/2013 | Bernhard et al.      | N/A        | N/A           |
| 2014/0199993 | 12/2013 | Dhanda et al.        | N/A        | N/A           |
| 2014/0201367 | 12/2013 | Trummer et al.       | N/A        | N/A           |
| 2014/0204766 | 12/2013 | Immendorf et al.     | N/A        | N/A           |
| 2014/0206279 | 12/2013 | Immendorf et al.     | N/A        | N/A           |
| 2014/0206307 | 12/2013 | Maurer et al.        | N/A        | N/A           |
| 2014/0206343 | 12/2013 | Immendorf et al.     | N/A        | N/A           |

|              |         |                   |     |     |
|--------------|---------|-------------------|-----|-----|
| 2014/0207414 | 12/2013 | Bordow            | N/A | N/A |
| 2014/0225590 | 12/2013 | Jacobs            | N/A | N/A |
| 2014/0256268 | 12/2013 | Olgaard           | N/A | N/A |
| 2014/0256370 | 12/2013 | Gautier et al.    | N/A | N/A |
| 2014/0269374 | 12/2013 | Abdelmonem et al. | N/A | N/A |
| 2014/0269376 | 12/2013 | Garcia et al.     | N/A | N/A |
| 2014/0274103 | 12/2013 | Steer et al.      | N/A | N/A |
| 2014/0287100 | 12/2013 | Libman            | N/A | N/A |
| 2014/0301216 | 12/2013 | Immendorf et al.  | N/A | N/A |
| 2014/0302796 | 12/2013 | Gormley et al.    | N/A | N/A |
| 2014/0335879 | 12/2013 | Immendorf et al.  | N/A | N/A |
| 2014/0340684 | 12/2013 | Edler et al.      | N/A | N/A |
| 2014/0342675 | 12/2013 | Massarella et al. | N/A | N/A |
| 2014/0348004 | 12/2013 | Ponnuswamy        | N/A | N/A |
| 2014/0362934 | 12/2013 | Kumar             | N/A | N/A |
| 2015/0016429 | 12/2014 | Menon et al.      | N/A | N/A |
| 2015/0023329 | 12/2014 | Jiang et al.      | N/A | N/A |
| 2015/0068296 | 12/2014 | Lanza Di et al.   | N/A | N/A |
| 2015/0072633 | 12/2014 | Massarella et al. | N/A | N/A |
| 2015/0126181 | 12/2014 | Breuer et al.     | N/A | N/A |
| 2015/0133058 | 12/2014 | Livis             | N/A | N/A |
| 2015/0150753 | 12/2014 | Racette           | N/A | N/A |
| 2015/0156827 | 12/2014 | Ibragimov et al.  | N/A | N/A |
| 2015/0170145 | 12/2014 | Patel et al.      | N/A | N/A |
| 2015/0201385 | 12/2014 | Mercer et al.     | N/A | N/A |
| 2015/0208312 | 12/2014 | Fudaba            | N/A | N/A |
| 2015/0215794 | 12/2014 | Gormley et al.    | N/A | N/A |
| 2015/0215949 | 12/2014 | Gormley et al.    | N/A | N/A |
| 2015/0242384 | 12/2014 | Reiter            | N/A | N/A |
| 2015/0248047 | 12/2014 | Chakraborty       | N/A | N/A |
| 2015/0289254 | 12/2014 | Garcia et al.     | N/A | N/A |
| 2015/0289265 | 12/2014 | Gormley et al.    | N/A | N/A |
| 2015/0296386 | 12/2014 | Menon et al.      | N/A | N/A |
| 2015/0301167 | 12/2014 | Sentelle et al.   | N/A | N/A |
| 2015/0319768 | 12/2014 | Abdelmonem et al. | N/A | N/A |
| 2015/0373528 | 12/2014 | Iwai              | N/A | N/A |
| 2016/0014713 | 12/2015 | Kennedy et al.    | N/A | N/A |
| 2016/0037550 | 12/2015 | Barabell et al.   | N/A | N/A |
| 2016/0050690 | 12/2015 | Yun et al.        | N/A | N/A |
| 2016/0061583 | 12/2015 | Ryu et al.        | N/A | N/A |
| 2016/0069994 | 12/2015 | Allen et al.      | N/A | N/A |
| 2016/0072597 | 12/2015 | Carbajal          | N/A | N/A |
| 2016/0073318 | 12/2015 | Aguirre           | N/A | N/A |
| 2016/0080955 | 12/2015 | Carbajal          | N/A | N/A |
| 2016/0086621 | 12/2015 | Hearing et al.    | N/A | N/A |
| 2016/0095188 | 12/2015 | Verberkt et al.   | N/A | N/A |
| 2016/0117853 | 12/2015 | Zhong et al.      | N/A | N/A |
| 2016/0124071 | 12/2015 | Baxley et al.     | N/A | N/A |
| 2016/0126988 | 12/2015 | Mester et al.     | N/A | N/A |
| 2016/0127110 | 12/2015 | McMeekin et al.   | N/A | N/A |

|              |         |                     |     |     |
|--------------|---------|---------------------|-----|-----|
| 2016/0127392 | 12/2015 | Baxley et al.       | N/A | N/A |
| 2016/0154406 | 12/2015 | Im et al.           | N/A | N/A |
| 2016/0161578 | 12/2015 | Weissler et al.     | N/A | N/A |
| 2016/0198471 | 12/2015 | Young et al.        | N/A | N/A |
| 2016/0219506 | 12/2015 | Pratt et al.        | N/A | N/A |
| 2016/0219590 | 12/2015 | Khawer et al.       | N/A | N/A |
| 2016/0225240 | 12/2015 | Voddhi et al.       | N/A | N/A |
| 2016/0241910 | 12/2015 | Rowe                | N/A | N/A |
| 2016/0245921 | 12/2015 | Li et al.           | N/A | N/A |
| 2016/0252342 | 12/2015 | Feldmann et al.     | N/A | N/A |
| 2016/0323920 | 12/2015 | Carbajal            | N/A | N/A |
| 2016/0334527 | 12/2015 | Xu et al.           | N/A | N/A |
| 2016/0345135 | 12/2015 | Garcia et al.       | N/A | N/A |
| 2016/0364079 | 12/2015 | Qiu et al.          | N/A | N/A |
| 2016/0366685 | 12/2015 | Gormley et al.      | N/A | N/A |
| 2016/0374088 | 12/2015 | Garcia et al.       | N/A | N/A |
| 2017/0024767 | 12/2016 | Johnson, Jr. et al. | N/A | N/A |
| 2017/0025996 | 12/2016 | Cheung et al.       | N/A | N/A |
| 2017/0039413 | 12/2016 | Nadler              | N/A | N/A |
| 2017/0048838 | 12/2016 | Chrisikos et al.    | N/A | N/A |
| 2017/0061690 | 12/2016 | Laughlin et al.     | N/A | N/A |
| 2017/0064564 | 12/2016 | Yun et al.          | N/A | N/A |
| 2017/0078792 | 12/2016 | Simons              | N/A | N/A |
| 2017/0079007 | 12/2016 | Carbajal            | N/A | N/A |
| 2017/0094527 | 12/2016 | Shattil et al.      | N/A | N/A |
| 2017/0118049 | 12/2016 | Miao et al.         | N/A | N/A |
| 2017/0134631 | 12/2016 | Zhao et al.         | N/A | N/A |
| 2017/0146462 | 12/2016 | Baker et al.        | N/A | N/A |
| 2017/0148332 | 12/2016 | Ziemba et al.       | N/A | N/A |
| 2017/0148467 | 12/2016 | Franklin et al.     | N/A | N/A |
| 2017/0192089 | 12/2016 | Parker et al.       | N/A | N/A |
| 2017/0208495 | 12/2016 | Kleinbeck et al.    | N/A | N/A |
| 2017/0234979 | 12/2016 | Mathews et al.      | N/A | N/A |
| 2017/0237484 | 12/2016 | Heath et al.        | N/A | N/A |
| 2017/0238201 | 12/2016 | Gormley et al.      | N/A | N/A |
| 2017/0238203 | 12/2016 | Dzierwa et al.      | N/A | N/A |
| 2017/0243138 | 12/2016 | Dzierwa et al.      | N/A | N/A |
| 2017/0243139 | 12/2016 | Dzierwa et al.      | N/A | N/A |
| 2017/0248677 | 12/2016 | Mahmood et al.      | N/A | N/A |
| 2017/0248807 | 12/2016 | Jiang et al.        | N/A | N/A |
| 2017/0250766 | 12/2016 | Dzierwa et al.      | N/A | N/A |
| 2017/0253330 | 12/2016 | Saigh et al.        | N/A | N/A |
| 2017/0261604 | 12/2016 | Van Voorst          | N/A | N/A |
| 2017/0261613 | 12/2016 | Van Voorst          | N/A | N/A |
| 2017/0261615 | 12/2016 | Ying et al.         | N/A | N/A |
| 2017/0274992 | 12/2016 | Chretien            | N/A | N/A |
| 2017/0289840 | 12/2016 | Sung et al.         | N/A | N/A |
| 2017/0290075 | 12/2016 | Carbajal et al.     | N/A | N/A |
| 2017/0311307 | 12/2016 | Negus et al.        | N/A | N/A |
| 2017/0358103 | 12/2016 | Shao et al.         | N/A | N/A |



|              |         |                     |     |     |
|--------------|---------|---------------------|-----|-----|
| 2017/0366361 | 12/2016 | Afkhami et al.      | N/A | N/A |
| 2017/0374572 | 12/2016 | Kleinbeck et al.    | N/A | N/A |
| 2017/0374573 | 12/2016 | Kleinbeck et al.    | N/A | N/A |
| 2018/0006730 | 12/2017 | Kuo et al.          | N/A | N/A |
| 2018/0014217 | 12/2017 | Kleinbeck et al.    | N/A | N/A |
| 2018/0024220 | 12/2017 | Massarella et al.   | N/A | N/A |
| 2018/0046869 | 12/2017 | Cordell et al.      | N/A | N/A |
| 2018/0070362 | 12/2017 | Ryan et al.         | N/A | N/A |
| 2018/0074170 | 12/2017 | Ray                 | N/A | N/A |
| 2018/0074171 | 12/2017 | Ray et al.          | N/A | N/A |
| 2018/0081355 | 12/2017 | Magy et al.         | N/A | N/A |
| 2018/0083721 | 12/2017 | Wada et al.         | N/A | N/A |
| 2018/0124533 | 12/2017 | Messier et al.      | N/A | N/A |
| 2018/0129881 | 12/2017 | Seeber et al.       | N/A | N/A |
| 2018/0131445 | 12/2017 | Esman et al.        | N/A | N/A |
| 2018/0143314 | 12/2017 | Pelletier et al.    | N/A | N/A |
| 2018/0149729 | 12/2017 | Grandin et al.      | N/A | N/A |
| 2018/0211179 | 12/2017 | Dzierwa             | N/A | N/A |
| 2018/0284758 | 12/2017 | Cella et al.        | N/A | N/A |
| 2018/0288620 | 12/2017 | Jayawickrama et al. | N/A | N/A |
| 2018/0294901 | 12/2017 | Garcia et al.       | N/A | N/A |
| 2018/0313877 | 12/2017 | Brant et al.        | N/A | N/A |
| 2018/0313945 | 12/2017 | Parker et al.       | N/A | N/A |
| 2018/0324595 | 12/2017 | Shima               | N/A | N/A |
| 2018/0329020 | 12/2017 | Hafizovic et al.    | N/A | N/A |
| 2018/0331863 | 12/2017 | Carbajal            | N/A | N/A |
| 2019/0004518 | 12/2018 | Zhou et al.         | N/A | N/A |
| 2019/0011534 | 12/2018 | Trotta et al.       | N/A | N/A |
| 2019/0018103 | 12/2018 | Qian et al.         | N/A | N/A |
| 2019/0064130 | 12/2018 | Kanazawa et al.     | N/A | N/A |
| 2019/0064223 | 12/2018 | Kincaid             | N/A | N/A |
| 2019/0072601 | 12/2018 | Dzierwa et al.      | N/A | N/A |
| 2019/0074802 | 12/2018 | Geha et al.         | N/A | N/A |
| 2019/0077507 | 12/2018 | Ferris et al.       | N/A | N/A |
| 2019/0123428 | 12/2018 | Packer et al.       | N/A | N/A |
| 2019/0180630 | 12/2018 | Kleinbeck           | N/A | N/A |
| 2019/0190553 | 12/2018 | Tsuji et al.        | N/A | N/A |
| 2019/0191313 | 12/2018 | Dzierwa et al.      | N/A | N/A |
| 2019/0200303 | 12/2018 | Nakahara            | N/A | N/A |
| 2019/0208112 | 12/2018 | Kleinbeck           | N/A | N/A |
| 2019/0208491 | 12/2018 | Dzierwa et al.      | N/A | N/A |
| 2019/0215709 | 12/2018 | Kleinbeck et al.    | N/A | N/A |
| 2019/0223139 | 12/2018 | Kleinbeck et al.    | N/A | N/A |
| 2019/0230539 | 12/2018 | Dzierwa et al.      | N/A | N/A |
| 2019/0230540 | 12/2018 | Carbajal et al.     | N/A | N/A |
| 2019/0236266 | 12/2018 | Nashimoto et al.    | N/A | N/A |
| 2019/0245722 | 12/2018 | Carbajal            | N/A | N/A |
| 2019/0246304 | 12/2018 | Dzierwa et al.      | N/A | N/A |
| 2019/0253160 | 12/2018 | Garcia et al.       | N/A | N/A |
| 2019/0253905 | 12/2018 | Kleinbeck et al.    | N/A | N/A |

|              |         |                   |     |     |
|--------------|---------|-------------------|-----|-----|
| 2019/0260768 | 12/2018 | Mestha et al.     | N/A | N/A |
| 2019/0274059 | 12/2018 | Kleinbeck et al.  | N/A | N/A |
| 2019/0296910 | 12/2018 | Cheung            | N/A | N/A |
| 2019/0302249 | 12/2018 | High et al.       | N/A | N/A |
| 2019/0302275 | 12/2018 | Tao et al.        | N/A | N/A |
| 2019/0342202 | 12/2018 | Ryan et al.       | N/A | N/A |
| 2019/0346571 | 12/2018 | Furumoto          | N/A | N/A |
| 2019/0360783 | 12/2018 | Whittaker         | N/A | N/A |
| 2019/0364433 | 12/2018 | Das               | N/A | N/A |
| 2019/0364533 | 12/2018 | Kleinbeck et al.  | N/A | N/A |
| 2020/0034620 | 12/2019 | Lutterodt         | N/A | N/A |
| 2020/0036459 | 12/2019 | Menon             | N/A | N/A |
| 2020/0036487 | 12/2019 | Hammond et al.    | N/A | N/A |
| 2020/0043346 | 12/2019 | Vacek             | N/A | N/A |
| 2020/0059800 | 12/2019 | Menon et al.      | N/A | N/A |
| 2020/0066132 | 12/2019 | Kleinbeck         | N/A | N/A |
| 2020/0067752 | 12/2019 | DelMarco          | N/A | N/A |
| 2020/0068573 | 12/2019 | Drozd et al.      | N/A | N/A |
| 2020/0096548 | 12/2019 | Dzierwa et al.    | N/A | N/A |
| 2020/0107207 | 12/2019 | Kleinbeck et al.  | N/A | N/A |
| 2020/0120266 | 12/2019 | Kleinbeck         | N/A | N/A |
| 2020/0128418 | 12/2019 | Dzierwa et al.    | N/A | N/A |
| 2020/0137583 | 12/2019 | Economy et al.    | N/A | N/A |
| 2020/0142029 | 12/2019 | Brooker et al.    | N/A | N/A |
| 2020/0145032 | 12/2019 | Ayala et al.      | N/A | N/A |
| 2020/0162890 | 12/2019 | Spencer et al.    | N/A | N/A |
| 2020/0167196 | 12/2019 | Smith et al.      | N/A | N/A |
| 2020/0169892 | 12/2019 | Dzierwa et al.    | N/A | N/A |
| 2020/0184832 | 12/2019 | Kleinbeck         | N/A | N/A |
| 2020/0196269 | 12/2019 | Dzierwa et al.    | N/A | N/A |
| 2020/0196270 | 12/2019 | Kleinbeck et al.  | N/A | N/A |
| 2020/0242603 | 12/2019 | Salkintzis        | N/A | N/A |
| 2020/0245167 | 12/2019 | Kleinbeck et al.  | N/A | N/A |
| 2020/0260306 | 12/2019 | Kleinbeck et al.  | N/A | N/A |
| 2020/0294032 | 12/2019 | Cheng et al.      | N/A | N/A |
| 2020/0295855 | 12/2019 | Kleinbeck et al.  | N/A | N/A |
| 2020/0382961 | 12/2019 | Shattil et al.    | N/A | N/A |
| 2020/0388036 | 12/2019 | Skrede et al.     | N/A | N/A |
| 2021/0014696 | 12/2020 | Brookes           | N/A | N/A |
| 2021/0067974 | 12/2020 | Guo et al.        | N/A | N/A |
| 2021/0082254 | 12/2020 | Givant            | N/A | N/A |
| 2021/0084217 | 12/2020 | Kleinbeck         | N/A | N/A |
| 2021/0211911 | 12/2020 | Kleinbeck et al.  | N/A | N/A |
| 2021/0250795 | 12/2020 | Dzierwa et al.    | N/A | N/A |
| 2021/0255356 | 12/2020 | Vu et al.         | N/A | N/A |
| 2021/0280039 | 12/2020 | Kleinbeck         | N/A | N/A |
| 2021/0281510 | 12/2020 | Brown, Jr. et al. | N/A | N/A |
| 2021/0306022 | 12/2020 | Fernando et al.   | N/A | N/A |
| 2021/0360423 | 12/2020 | Dzierwa et al.    | N/A | N/A |
| 2021/0360450 | 12/2020 | Kleinbeck et al.  | N/A | N/A |

|              |         |                    |     |     |
|--------------|---------|--------------------|-----|-----|
| 2021/0360453 | 12/2020 | Kleinbeck et al.   | N/A | N/A |
| 2021/0360454 | 12/2020 | Carbajal et al.    | N/A | N/A |
| 2021/0409591 | 12/2020 | Kleinbeck          | N/A | N/A |
| 2022/0030541 | 12/2021 | Dzierwa et al.     | N/A | N/A |
| 2022/0052770 | 12/2021 | Kleinbeck et al.   | N/A | N/A |
| 2022/0128612 | 12/2021 | Dzierwa et al.     | N/A | N/A |
| 2022/0131623 | 12/2021 | Garcia et al.      | N/A | N/A |
| 2022/0150824 | 12/2021 | Kleinbeck et al.   | N/A | N/A |
| 2022/0174525 | 12/2021 | Dzierwa et al.     | N/A | N/A |
| 2022/0253407 | 12/2021 | Tran               | N/A | N/A |
| 2022/0262228 | 12/2021 | Kleinbeck          | N/A | N/A |
| 2022/0262261 | 12/2021 | Kleinbeck          | N/A | N/A |
| 2022/0286997 | 12/2021 | Kleinbeck et al.   | N/A | N/A |
| 2022/0376921 | 12/2021 | Maria              | N/A | N/A |
| 2023/0018133 | 12/2022 | Burnette et al.    | N/A | N/A |
| 2023/0087729 | 12/2022 | Goldstein et al.   | N/A | N/A |
| 2023/0098387 | 12/2022 | Hafeez et al.      | N/A | N/A |
| 2023/0105718 | 12/2022 | Carbajal           | N/A | N/A |
| 2023/0114804 | 12/2022 | Kleinbeck          | N/A | N/A |
| 2023/0116761 | 12/2022 | Barry et al.       | N/A | N/A |
| 2023/0118723 | 12/2022 | Carbajal et al.    | N/A | N/A |
| 2023/0123375 | 12/2022 | Dzierwa et al.     | N/A | N/A |
| 2023/0126223 | 12/2022 | Kleinbeck et al.   | N/A | N/A |
| 2023/0189010 | 12/2022 | Muhammad et al.    | N/A | N/A |
| 2023/0189382 | 12/2022 | Haustein et al.    | N/A | N/A |
| 2023/0206216 | 12/2022 | Lehmann et al.     | N/A | N/A |
| 2023/0209378 | 12/2022 | Kleinbeck et al.   | N/A | N/A |
| 2023/0232244 | 12/2022 | Dzierwa et al.     | N/A | N/A |
| 2023/0252744 | 12/2022 | Miller et al.      | N/A | N/A |
| 2023/0254054 | 12/2022 | Garcia et al.      | N/A | N/A |
| 2023/0254567 | 12/2022 | Kleinbeck          | N/A | N/A |
| 2023/0254702 | 12/2022 | Damnjanovic et al. | N/A | N/A |
| 2023/0275791 | 12/2022 | Carbajal           | N/A | N/A |
| 2023/0276280 | 12/2022 | Kleinbeck et al.   | N/A | N/A |
| 2023/0300256 | 12/2022 | Zhao et al.        | N/A | N/A |
| 2023/0308789 | 12/2022 | Tian et al.        | N/A | N/A |
| 2023/0308915 | 12/2022 | Carbajal et al.    | N/A | N/A |
| 2023/0326323 | 12/2022 | Kleinbeck          | N/A | N/A |
| 2023/0334472 | 12/2022 | Pene               | N/A | N/A |
| 2023/0345441 | 12/2022 | Baxley             | N/A | N/A |
| 2023/0349962 | 12/2022 | Dzierwa et al.     | N/A | N/A |
| 2023/0378645 | 12/2022 | Tran               | N/A | N/A |
| 2023/0403564 | 12/2022 | Dzierwa et al.     | N/A | N/A |
| 2024/0005409 | 12/2023 | Doney              | N/A | N/A |
| 2024/0007204 | 12/2023 | Kleinbeck et al.   | N/A | N/A |
| 2024/0007479 | 12/2023 | Doney              | N/A | N/A |
| 2024/0023054 | 12/2023 | Dzierwa et al.     | N/A | N/A |
| 2024/0029572 | 12/2023 | Kleinbeck          | N/A | N/A |
| 2024/0031042 | 12/2023 | Garcia et al.      | N/A | N/A |
| 2024/0032084 | 12/2023 | Hellwig            | N/A | N/A |

|              |         |                    |     |     |
|--------------|---------|--------------------|-----|-----|
| 2024/0089130 | 12/2023 | Wang et al.        | N/A | N/A |
| 2024/0097951 | 12/2023 | Carbajal           | N/A | N/A |
| 2024/0103059 | 12/2023 | Dzierwa et al.     | N/A | N/A |
| 2024/0114370 | 12/2023 | Kleinbeck et al.   | N/A | N/A |
| 2024/0160791 | 12/2023 | He et al.          | N/A | N/A |
| 2024/0242589 | 12/2023 | Kleinbeck          | N/A | N/A |
| 2024/0244461 | 12/2023 | Kleinbeck et al.   | N/A | N/A |
| 2024/0267268 | 12/2023 | Carbajal           | N/A | N/A |
| 2024/0267769 | 12/2023 | Dzierwa et al.     | N/A | N/A |
| 2024/0275504 | 12/2023 | Kleinbeck et al.   | N/A | N/A |
| 2024/0276261 | 12/2023 | Kleinbeck et al.   | N/A | N/A |
| 2024/0284214 | 12/2023 | Kleinbeck et al.   | N/A | N/A |
| 2024/0292248 | 12/2023 | Kleinbeck et al.   | N/A | N/A |
| 2024/0330927 | 12/2023 | Abdelrahman et al. | N/A | N/A |
| 2024/0362631 | 12/2023 | Agrawal et al.     | N/A | N/A |
| 2024/0373463 | 12/2023 | Furuichi et al.    | N/A | N/A |
| 2024/0378982 | 12/2023 | Kleinbeck          | N/A | N/A |
| 2024/0381106 | 12/2023 | Montalvo et al.    | N/A | N/A |
| 2024/0386800 | 12/2023 | Kleinbeck et al.   | N/A | N/A |
| 2024/0386801 | 12/2023 | Kleinbeck et al.   | N/A | N/A |
| 2024/0388937 | 12/2023 | Murias et al.      | N/A | N/A |
| 2024/0396648 | 12/2023 | Kleinbeck et al.   | N/A | N/A |
| 2024/0430142 | 12/2023 | Carbajal           | N/A | N/A |
| 2025/0007629 | 12/2024 | Dzierwa et al.     | N/A | N/A |
| 2025/0039711 | 12/2024 | Dzierwa et al.     | N/A | N/A |
| 2025/0063405 | 12/2024 | Carbajal et al.    | N/A | N/A |

## FOREIGN PATENT DOCUMENTS

| Patent No.  | Application Date | Country | CPC        |
|-------------|------------------|---------|------------|
| 110035440   | 12/2018          | CN      | N/A        |
| 115482071   | 12/2021          | CN      | N/A        |
| 117196617   | 12/2022          | CN      | N/A        |
| 117998368   | 12/2023          | CN      | N/A        |
| 2268857     | 12/1993          | GB      | H04W 16/14 |
| 100248671   | 12/1999          | KR      | N/A        |
| 20140041618 | 12/2013          | KR      | N/A        |
| 953557      | 12/1981          | SU      | N/A        |
| 2012129932  | 12/2011          | WO      | N/A        |
| 2018184682  | 12/2017          | WO      | N/A        |
| 2023197982  | 12/2022          | WO      | N/A        |
| 2023232010  | 12/2022          | WO      | N/A        |

## OTHER PUBLICATIONS

“A Hardware Design for Time Delay Estimation of TDOA”; Li et al.; 2013 IEEE International Conference on Signal Processing, Communication and Computing (ICSPCC 2013); Aug. 2013 (Year: 2013). cited by applicant

“A Low-Cost, Near-Real-Time Two-LIAS-Based UWB Emitter Monitoring System”; Wang et al.; IEEE A&E Systems Magazine Nov. 2015 (Year: 2015). cited by applicant

“Joint TDOA and FDOA Estimation: A Conditional Bound and Its Use for Optimally Weighted

Localization”; Yeredor et al.; IEEE Transactions On Signal Processing, vol. 59, No. 4, Apr. 2011 (Year: 2011). cited by applicant

“Multipath TDOA and FDOA Estimation Using the EM Algorithm”; Belanger; Apr. 27, 1993; 1993 IEEE International Conference on Acoustics, Speech, and Signal Processing (Year: 1993). cited by applicant

“Noise Figure”, Wikipedia, located at [https://en.wikipedia.org/wiki/Noise\\_figure](https://en.wikipedia.org/wiki/Noise_figure) (Year: 2022). cited by applicant

“Signal Models for TDOA/FDOA Estimation”; Fowler et al.; IEEE Transactions On Aerospace and Electronic Systems vol. 44, No. Oct. 4, 2008 (Year: 2008). cited by applicant

“Specific attenuation model for rain for use in prediction methods”, Recommendation ITU-R p. 838-3 (Year: 2005). cited by applicant

Bluetooth vs Zigbee-difference between Bluetooth and Zigbee (located at <https://www.rfwireless-world.com/Terminology/Bluetooth-vs-zigbee.html>) (Year: 2012). cited by applicant

Boll S.F., Suppression of Acoustic Noise in Speech Using Spectral Subtraction, Apr. 1979, IEEE Transactions On Acoustics, Speech, and Signal Processing, vol. ASSP-27, No. 2, (Year: 1979). cited by applicant

David Eppink and Wolf Kuebler, “TIREM/SEM Handbook”, Mar. 1994, IIT Research Institute, p. 1-6, located at <http://www.dtic.mil/cgi-bin/GetTRDoc?Location=U2&doc=GetTRDoc.pdf&AD=ADA296913>. cited by applicant

English translation of SU-953557-A1 (Year: 2024). cited by applicant

Gabriel Garcia and Daniel Carbajal, U.S. Appl. No. 61/789,758, Provisional Patent Application, Filed Mar. 15, 2013 (Specification, Claims, and Drawings). cited by applicant

Gary L. Sugar, System and method for locating wireless devices in an unsynchronized wireless network, U.S. Appl. No. 60/319,737, Provisional Patent Application filed on Nov. 27, 2002, Specification including the claims, abstract, and drawings. cited by applicant

IEEE 100 The Authoritative Dictionary of IEEE Standards Terms. Seventh Edition. Published by Standards Information Network IEEE Press. p. 6 (Year: 2000). cited by applicant

International Search Report and Written Opinion dated Jun. 21, 2018 issued by the International Application Division, Korean Intellectual Property Office as International Searching Authority in connection with International Application No. PCT/US2018/014504 (21 pages). cited by applicant

Mehmet Ali Aygul, Ahmed Naeem, Huseyin Arslan. “Blind Signal Analysis—Wireless Communication Signals”, located at <https://doi.org/10.1002/9781119764441.ch12> (Year: 2021). cited by applicant

Mobile Emitter Geolocation and Tracking Using TDOA and FDOA Measurements; Musicki et al.; IEEE Transactions on Signal Processing, vol. 58, No. 3, Mar. 2010 (Year: 2010). cited by applicant

RF and Digital Signal Processing for Software-Defined Radio, Chapter 4—High-Level Requirements and Link Budget Analysis (Year: 2009). cited by applicant

S. Dorner, S. Cammerer, J. Hoydis and S. t. Brink, “Deep Learning Based Communication Over the Air,” in IEEE Journal of Selected Topics in Signal Processing, vol. 12, No. 1, pp. 132-143, Feb. 2018, doi: 10.1109/JSTSP.2017.2784180. cited by applicant

Steven W. Smith, The Scientist & Engineer's Guide to Digital Signal Processing, 1999, California Technical Publishing, San Diego, California, 2nd Edition, p. 312 (located at [http://www.analog.com/media/en/technical-documentation/dsp-book/dsp\\_book\\_ch18.pdf](http://www.analog.com/media/en/technical-documentation/dsp-book/dsp_book_ch18.pdf)) (Year: 1999). cited by applicant

T. J. O'Shea, K. Karra and T. C. Clancy, “Learning to communicate: Channel auto-encoders, domain specific regularizers, and attention,” 2016 IEEE International Symposium on Signal Processing and Information Technology (ISSPIT), Limassol, Cyprus, 2016, pp. 223-228, doi: 10.1109/ISSPIT.2016.7886039. cited by applicant

T. O'Shea and J. Hoydis, “An Introduction to Deep Learning for the Physical Layer,” in IEEE

*Primary Examiner:* Tran; Mong-Thuy T

*Attorney, Agent or Firm:* NEO IP

---

## **Background/Summary**

CROSS REFERENCE TO RELATED APPLICATIONS (1) This application is related to and claims priority from the following U.S. Patent Applications: this application is a continuation of U.S. application Ser. No. 18/955,234 filed Nov. 21, 2024, which is a continuation of U.S. application Ser. No. 18/792,113 filed Aug. 1, 2024, which is a continuation of U.S. application Ser. No. 18/434,178 filed Feb. 6, 2024, which is a continuation of U.S. application Ser. No. 18/374,385 filed Sep. 28, 2023, which is a continuation of U.S. application Ser. No. 18/137,785 filed Apr. 21, 2023, which is a continuation of U.S. application Ser. No. 18/082,210 filed Dec. 15, 2022, which is a continuation of U.S. application Ser. No. 17/569,984, filed Jan. 6, 2022, which is a continuation of U.S. application Ser. No. 16/751,887 filed Jan. 24, 2020, which is a continuation of U.S. application Ser. No. 16/395,987 filed Apr. 26, 2019, which is a continuation of U.S. application Ser. No. 16/002,751 filed Jun. 7, 2018, which is a continuation of U.S. application Ser. No. 15/228,325 filed Aug. 4, 2016, which is a continuation of U.S. application Ser. No. 14/743,011 filed Jun. 18, 2015, which is a continuation of U.S. patent application Ser. No. 13/912,893 filed Jun. 7, 2013, which claims the benefit of priority to U.S. Provisional Patent Application No. 61/789,758 filed Mar. 15, 2013, each of which is hereby incorporated by reference in its entirety.

## **BACKGROUND OF THE INVENTION**

(1) A problem faced in effective spectrum management is the various numbers of devices emanating wireless signal propagations at different frequencies and across different technological standards. Coupled with the different regulations relating to spectrum usage around the globe effective spectrum management becomes difficult to obtain and at best can only be reached over a long period of time.

(2) Another problem facing effective spectrum management is the growing need for spectrum despite the finite amount of spectrum available. Wireless technologies have exponentially grown in recent years. Consequently, available spectrum has become a valuable resource that must be efficiently utilized. Therefore, systems and methods are needed to effectively manage and optimize the available spectrum that is being used.

(3) Most spectrum management devices may be categorized into two primary types. The first type is a spectral analyzer where a device is specifically fitted to run a 'scanner' type receiver that is tailored to provide spectral information for a narrow window of frequencies related to a specific and limited type of communications standard, such as cellular communication standard. Problems arise with these narrowly tailored devices as cellular standards change and/or spectrum use changes impact the spectrum space of these technologies. Changes to the software and hardware for these narrowly tailored devices become too complicated, thus necessitating the need to purchase a totally different and new device. Unfortunately, this type of device is only for a specific use and cannot be used to alleviate the entire needs of the spectrum management community.

(4) The second type of spectral management device employs a methodology that requires bulky, extremely difficult to use processes, and expensive equipment. In order to attain a broad spectrum management view and complete all the necessary tasks, the device ends up becoming a conglomerate of software and hardware devices that is both hard to use and difficult to maneuver

from one location to another.

(5) While there may be several additional problems associated with current spectrum management devices, the problems may be summed up as two major problems: 1) most devices are built to inherently only handle specific spectrum technologies such as 900 MHz cellular spectrum while not being able to mitigate other technologies that may be interfering or competing with that spectrum, and 2) the other spectrum management devices consist of large spectrum analyzers, database systems, and spectrum management software that is expensive, too bulky, and too difficult to manage for a user's basic needs.

## SUMMARY OF THE INVENTION

(6) The systems, methods, and devices of the various embodiments enable spectrum management by identifying, classifying, and cataloging signals of interest based on radio frequency measurements. In an embodiment, signals and the parameters of the signals may be identified and indications of available frequencies may be presented to a user. In another embodiment, the protocols of signals may also be identified. In a further embodiment, the modulation of signals, data types carried by the signals, and estimated signal origins may be identified.

---

## Description

### BRIEF DESCRIPTION OF THE DRAWINGS

(1) The accompanying drawings, which are incorporated herein and constitute part of this specification, illustrate exemplary embodiments of the invention, and together with the general description given above and the detailed description given below, serve to explain the features of the invention.

(2) FIG. 1 is a system block diagram of a wireless environment suitable for use with the various embodiments.

(3) FIG. 2A is a block diagram of a spectrum management device according to an embodiment.

(4) FIG. 2B is a schematic logic flow block diagram illustrating logical operations which may be performed by a spectrum management device according to an embodiment.

(5) FIG. 3 is a process flow diagram illustrating an embodiment method for identifying a signal.

(6) FIG. 4 is a process flow diagram illustrating an embodiment method for measuring sample blocks of a radio frequency scan.

(7) FIG. 5A is a process flow diagram illustrating an embodiment method for determining signal parameters.

(8) FIG. 5B is a process flow diagram illustrating an embodiment method for determining signal parameters continued from FIG. 5A.

(9) FIG. 5C is a process flow diagram illustrating an embodiment method for determining signal parameters continued from FIGS. 5A-5B.

(10) FIG. 6 is a process flow diagram illustrating an embodiment method for displaying signal identifications.

(11) FIG. 7 is a process flow diagram illustrating an embodiment method for displaying one or more open frequency.

(12) FIG. 8A is a block diagram of a spectrum management device according to another embodiment.

(13) FIG. 8B is a schematic logic flow block diagram illustrating logical operations which may be performed by a spectrum management device according to another embodiment.

(14) FIG. 9 is a process flow diagram illustrating an embodiment method for determining protocol data and symbol timing data.

(15) FIG. 10 is a process flow diagram illustrating an embodiment method for calculating signal degradation data.

- (16) FIG. 11 is a process flow diagram illustrating an embodiment method for displaying signal and protocol identification information.
- (17) FIG. 12A is a block diagram of a spectrum management device according to a further embodiment.
- (18) FIG. 12B is a schematic logic flow block diagram illustrating logical operations which may be performed by a spectrum management device according to a further embodiment.
- (19) FIG. 13 is a process flow diagram illustrating an embodiment method for estimating a signal origin based on a frequency difference of arrival.
- (20) FIG. 14 is a process flow diagram illustrating an embodiment method for displaying an indication of an identified data type within a signal.
- (21) FIG. 15 is a process flow diagram illustrating an embodiment method for determining modulation type, protocol data, and symbol timing data.
- (22) FIG. 16 is a process flow diagram illustrating an embodiment method for tracking a signal origin.

#### DETAILED DESCRIPTION OF THE PRESENT INVENTION

- (23) The various embodiments will be described in detail with reference to the accompanying drawings. Wherever possible, the same reference numbers will be used throughout the drawings to refer to the same or like parts. References made to particular examples and implementations are for illustrative purposes and are not intended to limit the scope of the invention or the claims.
- (24) The word “exemplary” is used herein to mean “serving as an example, instance, or illustration.” Any implementation described herein as “exemplary” is not necessarily to be construed as preferred or advantageous over other implementations.
- (25) The systems, methods, and devices of the various embodiments enable spectrum management by identifying, classifying, and cataloging signals of interest based on radio frequency measurements. In an embodiment, signals and the parameters of the signals may be identified and indications of available frequencies may be presented to a user. In another embodiment, the protocols of signals may also be identified. In a further embodiment, the modulation of signals, data types carried by the signals, and estimated signal origins may be identified.
- (26) Embodiments are directed to a spectrum management device that may be configurable to obtain spectrum data over a wide range of wireless communication protocols. Embodiments may also provide for the ability to acquire data from and sending data to database depositories that may be used by a plurality of spectrum management customers.
- (27) In one embodiment, a spectrum management device may include a signal spectrum analyzer that may be coupled with a database system and spectrum management interface. The device may be portable or may be a stationary installation and may be updated with data to allow the device to manage different spectrum information based on frequency, bandwidth, signal power, time, and location of signal propagation, as well as modulation type and format and to provide signal identification, classification, and geo-location. A processor may enable the device to process spectrum power density data as received and to process raw I/Q complex data that may be used for further signal processing, signal identification, and data extraction.
- (28) In an embodiment, a spectrum management device may comprise a low noise amplifier that receives a radio frequency (RF) energy from an antenna. The antenna may be any antenna structure that is capable of receiving RF energy in a spectrum of interest. The low noise amplifier may filter and amplify the RF energy. The RF energy may be provided to an RF translator. The RF translator may perform a fast Fourier transform (FFT) and either a square magnitude or a fast convolution spectral periodogram function to convert the RF measurements into a spectral representation. In an embodiment, the RF translator may also store a timestamp to facilitate calculation of a time of arrival and an angle of arrival. The In-Phase and Quadrature (I/Q) data may be provided to a spectral analysis receiver or it may be provided to a sample data store where it may be stored without being processed by a spectral analysis receiver. The input RF energy may also be directly



digital down-converted and sampled by an analog to digital converter (ADC) to generate complex I/Q data. The complex I/Q data may be equalized to remove multipath, fading, white noise and interference from other signaling systems by fast parallel adaptive filter processes. This data may then be used to calculate modulation type and baud rate. Complex sampled I/Q data may also be used to measure the signal angle of arrival and time of arrival. Such information as angle of arrival and time of arrival may be used to compute more complex and precise direction finding. In addition, they may be used to apply geo-location techniques. Data may be collected from known signals or unknown signals and time spaced in order to provide expedient information. I/Q sampled data may contain raw signal data that may be used to demodulate and translate signals by streaming them to a signal analyzer or to a real-time demodulator software defined radio that may have the newly identified signal parameters for the signal of interest. The inherent nature of the input RF allows for any type of signal to be analyzed and demodulated based on the reconfiguration of the software defined radio interfaces.

(29) A spectral analysis receiver may be configured to read raw In-Phase (I) and Quadrature (Q) data and either translate directly to spectral data or down convert to an intermediate frequency (IF) up to half the Nyquist sampling rate to analyze the incoming bandwidth of a signal. The translated spectral data may include measured values of signal energy, frequency, and time. The measured values provide attributes of the signal under review that may confirm the detection of a particular signal of interest within a spectrum of interest. In an embodiment, a spectral analysis receiver may have a referenced spectrum input of 0 Hz to 12.4 GHz with capability of fiber optic input for spectrum input up to 60 GHz.

(30) In an embodiment, the spectral analysis receiver may be configured to sample the input RF data by fast analog down-conversion of the RF signal. The down-converted signal may then be digitally converted and processed by fast convolution filters to obtain a power spectrum. This process may also provide spectrum measurements including the signal power, the bandwidth, the center frequency of the signal as well as a Time of Arrival (TOA) measurement. The TOA measurement may be used to create a timestamp of the detected signal and/or to generate a time difference of arrival iterative process for direction finding and fast triangulation of signals. In an embodiment, the sample data may be provided to a spectrum analysis module. In an embodiment, the spectrum analysis module may evaluate the sample data to obtain the spectral components of the signal.

(31) In an embodiment, the spectral components of the signal may be obtained by the spectrum analysis module from the raw I/Q data as provided by an RF translator. The I/Q data analysis performed by the spectrum analysis module may operate to extract more detailed information about the signal, including by way of example, modulation type (e.g., FM, AM, QPSK, 16QAM, etc.) and/or protocol (e.g., GSM, CDMA, OFDM, LTE, etc.). In an embodiment, the spectrum analysis module may be configured by a user to obtain specific information about a signal of interest. In an alternate embodiment, the spectral components of the signal may be obtained from power spectral component data produced by the spectral analysis receiver.

(32) In an embodiment, the spectrum analysis module may provide the spectral components of the signal to a data extraction module. The data extraction module may provide the classification and categorization of signals detected in the RF spectrum. The data extraction module may also acquire additional information regarding the signal from the spectral components of the signal. For example, the data extraction module may provide modulation type, bandwidth, and possible system in use information. In another embodiment, the data extraction module may select and organize the extracted spectral components in a format selected by a user.

(33) The information from the data extraction module may be provided to a spectrum management module. The spectrum management module may generate a query to a static database to classify a signal based on its components. For example, the information stored in static database may be used to determine the spectral density, center frequency, bandwidth, baud rate, modulation type, protocol

(e.g., GSM, CDMA, OFDM, LTE, etc.), system or carrier using licensed spectrum, location of the signal source, and a timestamp of the signal of interest. These data points may be provided to a data store for export. In an embodiment and as more fully described below, the data store may be configured to access mapping software to provide the user with information on the location of the transmission source of the signal of interest. In an embodiment, the static database includes frequency information gathered from various sources including, but not limited to, the Federal Communication Commission (FCC), the International Telecommunication Union, and data from users. As an example, the static database may be an SQL database. The data store may be updated, downloaded or merged with other devices or with its main relational database. Software API applications may be included to allow database merging with third-party spectrum databases that may only be accessed securely.

(34) In the various embodiments, the spectrum management device may be configured in different ways. In an embodiment, the front end of system may comprise various hardware receivers that may provide In-Phase and Quadrature complex data. The front end receiver may include API set commands via which the system software may be configured to interface (i.e., communicate) with a third party receiver. In an embodiment, the front end receiver may perform the spectral computations using FFT (Fast Fourier Transform) and other DSP (Digital Signal Processing) to generate a fast convolution periodogram that may be re-sampled and averaged to quickly compute the spectral density of the RF environment.

(35) In an embodiment, cyclic processes may be used to average and correlate signal information by extracting the changes inside the signal to better identify the signal of interest that is present in the RF space. A combination of amplitude and frequency changes may be measured and averaged over the bandwidth time to compute the modulation type and other internal changes, such as changes in frequency offsets, orthogonal frequency division modulation, changes in time (e.g., Time Division Multiplexing), and/or changes in I/Q phase rotation used to compute the baud rate and the modulation type. In an embodiment, the spectrum management device may have the ability to compute several processes in parallel by use of a multi-core processor and along with several embedded field programmable gate arrays (FPGA). Such multi-core processing may allow the system to quickly analyze several signal parameters in the RF environment at one time in order to reduce the amount of time it takes to process the signals. The amount of signals computed at once may be determined by their bandwidth requirements. Thus, the capability of the system may be based on a maximum frequency  $F_s/2$ . The number of signals to be processed may be allocated based on their respective bandwidths. In another embodiment, the signal spectrum may be measured to determine its power density, center frequency, bandwidth and location from which the signal is emanating and a best match may be determined based on the signal parameters based on information criteria of the frequency.

(36) In another embodiment, a GPS and direction finding location (DF) system may be incorporated into the spectrum management device and/or available to the spectrum management device. Adding GPS and DF ability may enable the user to provide a location vector using the National Marine Electronics Association's (NMEA) standard form. In an embodiment, location functionality is incorporated into a specific type of GPS unit, such as a U.S. government issued receiver. The information may be derived from the location presented by the database internal to the device, a database imported into the device, or by the user inputting geo-location parameters of longitude and latitude which may be derived as degrees, minutes and seconds, decimal minutes, or decimal form and translated to the necessary format with the default being 'decimal' form. This functionality may be incorporated into a GPS unit. The signal information and the signal classification may then be used to locate the signaling device as well as to provide a direction finding capability.

(37) A type of triangulation using three units as a group antenna configuration performs direction finding by using multilateration. Commonly used in civil and military surveillance applications,

multilateration is able to accurately locate an aircraft, vehicle, or stationary emitter by measuring the “Time Difference of Arrival” (TDOA) of a signal from the emitter at three or more receiver sites. If a pulse is emitted from a platform, it will arrive at slightly different times at two spatially separated receiver sites, the TDOA being due to the different distances of each receiver from the platform. This location information may then be supplied to a mapping process that utilizes a database of mapping images that are extracted from the database based on the latitude and longitude provided by the geo-location or direction finding device. The mapping images may be scanned in to show the points of interest where a signal is either expected to be emanating from based on the database information or from an average taken from the database information and the geo-location calculation performed prior to the mapping software being called. The user can control the map to maximize or minimize the mapping screen to get a better view which is more fit to provide information of the signal transmissions. In an embodiment, the mapping process does not rely on outside mapping software. The mapping capability has the ability to generate the map image and to populate a mapping database that may include information from third party maps to meet specific user requirements.

(38) In an embodiment, triangulation and multilateration may utilize a Bayesian type filter that may predict possible movement and future location and operation of devices based on input collected from the TDOA and geolocation processes and the variables from the static database pertaining to the specified signal of interest. The Bayesian filter takes the input changes in time difference and its inverse function (i.e., frequency difference) and takes an average change in signal variation to detect and predict the movement of the signals. The signal changes are measured within 1 ns time difference and the filter may also adapt its gradient error calculation to remove unwanted signals that may cause errors due to signal multipath, inter-symbol interference, and other signal noise.

(39) In an embodiment the changes within a 1 ns time difference for each sample for each unique signal may be recorded. The spectrum management device may then perform the inverse and compute and record the frequency difference and phase difference between each sample for each unique signal. The spectrum management device may take the same signal and calculates an error based on other input signals coming in within the 1 ns time and may average and filter out the computed error to equalize the signal. The spectrum management device may determine the time difference and frequency difference of arrival for that signal and compute the odds of where the signal is emanating from based on the frequency band parameters presented from the spectral analysis and processor computations, and determines the best position from which the signal is transmitted (i.e., origin of the signal).

(40) FIG. 1 illustrates a wireless environment **100** suitable for use with the various embodiments. The wireless environment **100** may include various sources **104**, **106**, **108**, **110**, **112**, and **114** generating various radio frequency (RF) signals **116**, **118**, **120**, **122**, **124**, **126**. As an example, mobile devices **104** may generate cellular RF signals **116**, such as CDMA, GSM, 3G signals, etc. As another example, wireless access devices **106**, such as Wi-Fi® routers, may generate RF signals **118**, such as Wi-Fi® signals. As a further example, satellites **108**, such as communication satellites or GPS satellites, may generate RF signals **120**, such as satellite radio, television, or GPS signals. As a still further example, base stations **110**, such as a cellular base station, may generate RF signals **122**, such as CDMA, GSM, 3G signals, etc. As another example, radio towers **112**, such as local AM or FM radio stations, may generate RF signals **124**, such as AM or FM radio signals. As another example, government service provides **114**, such as police units, fire fighters, military units, air traffic control towers, etc. may generate RF signals **126**, such as radio communications, tracking signals, etc. The various RF signals **116**, **118**, **120**, **122**, **124**, **126** may be generated at different frequencies, power levels, in different protocols, with different modulations, and at different times. The various sources **104**, **106**, **108**, **110**, **112**, and **114** may be assigned frequency bands, power limitations, or other restrictions, requirements, and/or licenses by a government spectrum control entity, such as the FCC. However, with so many different sources **104**, **106**, **108**,

**110**, **112**, and **114** generating so many different RF signals **116**, **118**, **120**, **122**, **124**, **126**, overlaps, interference, and/or other problems may occur. A spectrum management device **102** in the wireless environment **100** may measure the RF energy in the wireless environment **100** across a wide spectrum and identify the different RF signals **116**, **118**, **120**, **122**, **124**, **126** which may be present in the wireless environment **100**. The identification and cataloging of the different RF signals **116**, **118**, **120**, **122**, **124**, **126** which may be present in the wireless environment **100** may enable the spectrum management device **102** to determine available frequencies for use in the wireless environment **100**. In addition, the spectrum management device **102** may be able to determine if there are available frequencies for use in the wireless environment **100** under certain conditions (i.e., day of week, time of day, power level, frequency band, etc.). In this manner, the RF spectrum in the wireless environment **100** may be managed.

(41) FIG. 2A is a block diagram of a spectrum management device **202** according to an embodiment. The spectrum management device **202** may include an antenna structure **204** configured to receive RF energy expressed in a wireless environment. The antenna structure **204** may be any type of antenna, and may be configured to optimize the receipt of RF energy across a wide frequency spectrum. The antenna structure **204** may be connected to one or more optional amplifiers and/or filters **208** which may boost, smooth, and/or filter the RF energy received by antenna structure **204** before the RF energy is passed to an RF receiver **210** connected to the antenna structure **204**. In an embodiment, the RF receiver **210** may be configured to measure the RF energy received from the antenna structure **204** and/or optional amplifiers and/or filters **208**. In an embodiment, the RF receiver **210** may be configured to measure RF energy in the time domain and may convert the RF energy measurements to the frequency domain. In an embodiment, the RF receiver **210** may be configured to generate spectral representation data of the received RF energy. The RF receiver **210** may be any type RF receiver, and may be configured to generate RF energy measurements over a range of frequencies, such as 0 kHz to 24 GHz, 9 kHz to 6 GHz, etc. In an embodiment, the frequency scanned by the RF receiver **210** may be user selectable. In an embodiment, the RF receiver **210** may be connected to a signal processor **214** and may be configured to output RF energy measurements to the signal processor **214**. As an example, the RF receiver **210** may output raw In-Phase (I) and Quadrature (Q) data to the signal processor **214**. As another example, the RF receiver **210** may apply signals processing techniques to output complex In-Phase (I) and Quadrature (Q) data to the signal processor **214**. In an embodiment, the spectrum management device may also include an antenna **206** connected to a location receiver **212**, such as a GPS receiver, which may be connected to the signal processor **214**. The location receiver **212** may provide location inputs to the signal processor **214**.

(42) The signal processor **214** may include a signal detection module **216**, a comparison module **222**, a timing module **224**, and a location module **225**. Additionally, the signal processor **214** may include an optional memory module **226** which may include one or more optional buffers **228** for storing data generated by the other modules of the signal processor **214**.

(43) In an embodiment, the signal detection module **216** may operate to identify signals based on the RF energy measurements received from the RF receiver **210**. The signal detection module **216** may include a Fast Fourier Transform (FFT) module **217** which may convert the received RF energy measurements into spectral representation data. The signal detection module **216** may include an analysis module **221** which may analyze the spectral representation data to identify one or more signals above a power threshold. A power module **220** of the signal detection module **216** may control the power threshold at which signals may be identified. In an embodiment, the power threshold may be a default power setting or may be a user selectable power setting. A noise module **219** of the signal detection module **216** may control a signal threshold, such as a noise threshold, at or above which signals may be identified. The signal detection module **216** may include a parameter module **218** which may determine one or more signal parameters for any identified signals, such as center frequency, bandwidth, power, number of detected signals, frequency peak,

peak power, average power, signal duration, etc. In an embodiment, the signal processor **214** may include a timing module **224** which may record time information and provide the time information to the signal detection module **216**. Additionally, the signal processor **214** may include a location module **225** which may receive location inputs from the location receiver **212** and determine a location of the spectrum management device **202**. The location of the spectrum management device **202** may be provided to the signal detection module **216**.

(44) In an embodiment, the signal processor **214** may be connected to one or more memory **230**. The memory **230** may include multiple databases, such as a history or historical database **232** and characteristics listing **236**, and one or more buffers **240** storing data generated by signal processor **214**. While illustrated as connected to the signal processor **214** the memory **230** may also be on chip memory residing on the signal processor **214** itself. In an embodiment, the history or historical database **232** may include measured signal data **234** for signals that have been previously identified by the spectrum management device **202**. The measured signal data **234** may include the raw RF energy measurements, time stamps, location information, one or more signal parameters for any identified signals, such as center frequency, bandwidth, power, number of detected signals, frequency peak, peak power, average power, signal duration, etc., and identifying information determined from the characteristics listing **236**. In an embodiment, the history or historical database **232** may be updated as signals are identified by the spectrum management device **202**. In an embodiment, the characteristic listing **236** may be a database of static signal data **238**. The static signal data **238** may include data gathered from various sources including by way of example and not by way of limitation the Federal Communication Commission, the International Telecommunication Union, telecom providers, manufacture data, and data from spectrum management device users. Static signal data **238** may include known signal parameters of transmitting devices, such as center frequency, bandwidth, power, number of detected signals, frequency peak, peak power, average power, signal duration, geographic information for transmitting devices, and any other data that may be useful in identifying a signal. In an embodiment, the static signal data **238** and the characteristic listing **236** may correlate signal parameters and signal identifications. As an example, the static signal data **238** and characteristic listing **236** may list the parameters of the local fire and emergency communication channel correlated with a signal identification indicating that signal is the local fire and emergency communication channel.

(45) In an embodiment, the signal processor **214** may include a comparison module **222** which may match data generated by the signal detection module **216** with data in the history or historical database **232** and/or characteristic listing **236**. In an embodiment the comparison module **222** may receive signal parameters from the signal detection module **216**, such as center frequency, bandwidth, power, number of detected signals, frequency peak, peak power, average power, signal duration, and/or receive parameter from the timing module **224** and/or location module **225**. The parameter match module **223** may retrieve data from the history or historical database **232** and/or the characteristic listing **236** and compare the retrieved data to any received parameters to identify matches. Based on the matches the comparison module may identify the signal. In an embodiment, the signal processor **214** may be optionally connected to a display **242**, an input device **244**, and/or network transceiver **246**. The display **242** may be controlled by the signal processor **214** to output spectral representations of received signals, signal characteristic information, and/or indications of signal identifications on the display **242**. In an embodiment, the input device **244** may be any input device, such as a keyboard and/or knob, mouse, virtual keyboard or even voice recognition, enabling the user of the spectrum management device **202** to input information for use by the signal processor **214**. In an embodiment, the network transceiver **246** may enable the spectrum management device **202** to exchange data with wired and/or wireless networks, such as to update the characteristic listing **236** and/or upload information from the history or historical database **232**.

(46) FIG. 2B is a schematic logic flow block diagram illustrating logical operations which may be

performed by a spectrum management device **202** according to an embodiment. A receiver **210** may output RF energy measurements, such as I and Q data to a FFT module **252** which may generate a spectral representation of the RF energy measurements which may be output on a display **242**. The I and Q data may also be buffered in a buffer **256** and sent to a signal detection module **216**. The signal detection module **216** may receive location inputs from a location receiver **212** and use the received I and Q data to detect signals. Data from the signal detection module **216** may be buffered through a buffer **262** and written into a history or historical database **232**. Additionally, data from the historical database may be used to aid in the detection of signals by the signal detection module **216**. The signal parameters of the detected signals may be determined by a signal parameters module **218** using information from the history or historical database **232** and/or a static database **238** listing signal characteristics through a buffer **268**. Data from the signal parameters module **218** may be stored in the history or historical database **232** and/or sent to the signal detection module **216** and/or display **242**. In this manner, signals may be detected and indications of the signal identification may be displayed to a user of the spectrum management device.

(47) FIG. 3 illustrates a process flow of an embodiment method **300** for identifying a signal. In an embodiment the operations of method **300** may be performed by the processor **214** of a spectrum management device **202**. In block **302** the processor **214** may determine the location of the spectrum management device **202**. In an embodiment, the processor **214** may determine the location of the spectrum management device **202** based on a location input, such as GPS coordinates, received from a location receiver, such as a GPS receiver **212**. In block **304** the processor **214** may determine the time. As an example, the time may be the current clock time as determined by the processor **214** and may be a time associated with receiving RF measurements. In block **306** the processor **214** may receive RF energy measurements. In an embodiment, the processor **214** may receive RF energy measurements from an RF receiver **210**. In block **308** the processor **214** may convert the RF energy measurements to spectral representation data. As an example, the processor may apply a Fast Fourier Transform (FFT) to the RF energy measurements to convert them to spectral representation data. In optional block **310** the processor **214** may display the spectral representation data on a display **242** of the spectrum management device **202**, such as in a graph illustrating amplitudes across a frequency spectrum.

(48) In block **312** the processor **214** may identify one or more signal above a threshold. In an embodiment, the processor **214** may analyze the spectral representation data to identify a signal above a power threshold. A power threshold may be an amplitude measure selected to distinguish RF energies associated with actual signals from noise. In an embodiment, the power threshold may be a default value. In another embodiment, the power threshold may be a user selectable value. In block **314** the processor **214** may determine signal parameters of any identified signal or signals of interest. As examples, the processor **214** may determine signal parameters such as center frequency, bandwidth, power, number of detected signals, frequency peak, peak power, average power, signal duration for the identified signals. In block **316** the processor **214** may store the signal parameters of each identified signal, a location indication, and time indication for each identified signal in a history database **232**. In an embodiment, a history database **232** may be a database resident in a memory **230** of the spectrum management device **202** which may include data associated with signals actually identified by the spectrum management device.

(49) In block **318** the processor **214** may compare the signal parameters of each identified signal to signal parameters in a signal characteristic listing. In an embodiment, the signal characteristic listing may be a static database **238** stored in the memory **230** of the spectrum management device **202** which may correlate signal parameters and signal identifications. In determination block **320** the processor **214** may determine whether the signal parameters of the identified signal or signals match signal parameters in the characteristic listing **236**. In an embodiment, a match may be determined based on the signal parameters being within a specified tolerance of one another. As an

example, a center frequency match may be determined when the center frequencies are within plus or minus 1 kHz of each other. In this manner, differences between real world measured conditions of an identified signal and ideal conditions listed in a characteristics listing may be accounted for in identifying matches. If the signal parameters do not match (i.e., determination block **320**="No"), in block **326** the processor **214** may display an indication that the signal is unidentified on a display **242** of the spectrum management device **202**. In this manner, the user of the spectrum management device may be notified that a signal is detected, but has not been positively identified. If the signal parameters do match (i.e., determination block **320**="Yes"), in block **324** the processor **214** may display an indication of the signal identification on the display **242**. In an embodiment, the signal identification displayed may be the signal identification correlated to the signal parameter in the signal characteristic listing which matched the signal parameter for the identified signal. Upon displaying the indications in blocks **324** or **326** the processor **214** may return to block **302** and cyclically measure and identify further signals of interest.

(50) FIG. **4** illustrates an embodiment method **400** for measuring sample blocks of a radio frequency scan. In an embodiment the operations of method **400** may be performed by the processor **214** of a spectrum management device **202**. As discussed above, in blocks **306** and **308** the processor **214** may receive RF energy measurements and convert the RF energy measurements to spectral representation data. In block **402** the processor **214** may determine a frequency range at which to sample the RF spectrum for signals of interest. In an embodiment, a frequency range may be a frequency range of each sample block to be analyzed for potential signals. As an example, the frequency range may be 240 kHz. In an embodiment, the frequency range may be a default value. In another embodiment, the frequency range may be a user selectable value. In block **404** the processor **214** may determine a number (N) of sample blocks to measure. In an embodiment, each sample block may be sized to the determined of default frequency range, and the number of sample blocks may be determined by dividing the spectrum of the measured RF energy by the frequency range. In block **406** the processor **214** may assign each sample block a respective frequency range. As an example, if the determined frequency range is 240 kHz, the first sample block may be assigned a frequency range from 0 kHz to 240 kHz, the second sample block may be assigned a frequency range from 240 kHz to 480 kHz, etc. In block **408** the processor **214** may set the lowest frequency range sample block as the current sample block. In block **409** the processor **214** may measure the amplitude across the set frequency range for the current sample block. As an example, at each frequency interval (such as 1 Hz) within the frequency range of the sample block the processor **214** may measure the received signal amplitude. In block **410** the processor **214** may store the amplitude measurements and corresponding frequencies for the current sample block. In determination block **414** the processor **214** may determine if all sample blocks have been measured. If all sample blocks have not been measured (i.e., determination block **414**="No"), in block **416** the processor **214** may set the next highest frequency range sample block as the current sample block. As discussed above, in blocks **409**, **410**, and **414** the processor **214** may measure and store amplitudes and determine whether all blocks are sampled. If all blocks have been sampled (i.e., determination block **414**="Yes"), the processor **214** may return to block **306** and cyclically measure further sample blocks.

(51) FIGS. **5A**, **5B**, and **5C** illustrate the process flow for an embodiment method **500** for determining signal parameters. In an embodiment the operations of method **500** may be performed by the processor **214** of a spectrum management device **202**. Referring to FIG. **5A**, in block **502** the processor **214** may receive a noise floor average setting. In an embodiment, the noise floor average setting may be an average noise level for the environment in which the spectrum management device **202** is operating. In an embodiment, the noise floor average setting may be a default setting and/or may be user selectable setting. In block **504** the processor **214** may receive the signal power threshold setting. In an embodiment, the signal power threshold setting may be an amplitude measure selected to distinguish RF energies associated with actual signals from noise. In an

embodiment the signal power threshold may be a default value and/or may be a user selectable setting. In block **506** the processor **214** may load the next available sample block. In an embodiment, the sample blocks may be assembled according to the operations of method **400** described above with reference to FIG. **4**. In an embodiment, the next available sample block may be an oldest in time sample block which has not been analyzed to determine whether signals of interest are present in the sample block. In block **508** the processor **214** may average the amplitude measurements in the sample block. In determination block **510** the processor **214** may determine whether the average for the sample block is greater than or equal to the noise floor average set in block **502**. In this manner, sample blocks including potential signals may be quickly distinguished from sample blocks which may not include potential signals reducing processing time by enabling sample blocks without potential signals to be identified and ignored. If the average for the sample block is lower than the noise floor average (i.e., determination block **510**="No"), no signals of interest may be present in the current sample block. In determination block **514** the processor **214** may determine whether a cross block flag is set. If the cross block flag is not set (i.e., determination block **514**="No"), in block **506** the processor **214** may load the next available sample block and in block **508** average the sample block **508**.

(52) If the average of the sample block is equal to or greater than the noise floor average (i.e., determination block **510**="Yes"), the sample block may potentially include a signal of interest and in block **512** the processor **214** may reset a measurement counter (C) to 1. The measurement counter value indicating which sample within a sample block is under analysis. In determination block **516** the processor **214** may determine whether the RF measurement of the next frequency sample (C) is greater than the signal power threshold. In this manner, the value of the measurement counter (C) may be used to control which sample RF measurement in the sample block is compared to the signal power threshold. As an example, when the counter (C) equals 1, the first RF measurement may be checked against the signal power threshold and when the counter (C) equals 2 the second RF measurement in the sample block may be checked, etc. If the C RF measurement is less than or equal to the signal power threshold (i.e., determination block **516**="No"), in determination block **517** the processor **214** may determine whether the cross block flag is set. If the cross block flag is not set (i.e., determination block **517**="No"), in determination block **522** the processor **214** may determine whether the end of the sample block is reached. If the end of the sample block is reached (i.e., determination block **522**="Yes"), in block **506** the processor **214** may load the next available sample block and proceed in blocks **508**, **510**, **514**, and **512** as discussed above. If the end of the sample block is not reached (i.e., determination block **522**="No"), in block **524** the processor **214** may increment the measurement counter (C) so that the next sample in the sample block is analyzed.

(53) If the C RF measurement is greater than the signal power threshold (i.e., determination block **516**="Yes"), in block **518** the processor **214** may check the status of the cross block flag to determine whether the cross block flag is set. If the cross block flag is not set (i.e., determination block **518**="No"), in block **520** the processor **214** may set a sample start. As an example, the processor **214** may set a sample start by indicating a potential signal of interest may be discovered in a memory by assigning a memory location for RF measurements associated with the sample start. Referring to FIG. **5B**, in block **526** the processor **214** may store the C RF measurement in a memory location for the sample currently under analysis. In block **528** the processor **214** may increment the measurement counter (C) value.

(54) In determination block **530** the processor **214** may determine whether the C RF measurement (e.g., the next RF measurement because the value of the RF measurement counter was incremented) is greater than the signal power threshold. If the C RF measurement is greater than the signal power threshold (i.e., determination block **530**="Yes"), in determination block **532** the processor **214** may determine whether the end of the sample block is reached. If the end of the sample block is not reached (i.e., determination block **532**="No"), there may be further RF



measurements available in the sample block and in block **526** the processor **214** may store the C RF measurement in the memory location for the sample. In block **528** the processor may increment the measurement counter (C) and in determination block **530** determine whether the C RF measurement is above the signal power threshold and in block **532** determine whether the end of the sample block is reached. In this manner, successive sample RF measurements may be checked against the signal power threshold and stored until the end of the sample block is reached and/or until a sample RF measurement falls below the signal power threshold. If the end of the sample block is reached (i.e., determination block **532**="Yes"), in block **534** the processor **214** may set the cross block flag. In an embodiment, the cross block flag may be a flag in a memory available to the processor **214** indicating the signal potential spans across two or more sample blocks. In a further embodiment, prior to setting the cross block flag in block **534**, the slope of a line drawn between the last two RF measurement samples may be used to determine whether the next sample block likely contains further potential signal samples. A negative slope may indicate that the signal of interest is fading and may indicate the last sample was the final sample of the signal of interest. In another embodiment, the slope may not be computed and the next sample block may be analyzed regardless of the slope.

(55) If the end of the sample block is reached (i.e., determination block **532**="Yes") and in block **534** the cross block flag is set, referring to FIG. 5A, in block **506** the processor **214** may load the next available sample block, in block **508** may average the sample block, and in block **510** determine whether the average of the sample block is greater than or equal to the noise floor average. If the average is equal to or greater than the noise floor average (i.e., determination block **510**="Yes"), in block **512** the processor **214** may reset the measurement counter (C) to 1. In determination block **516** the processor **214** may determine whether the C RF measurement for the current sample block is greater than the signal power threshold. If the C RF measurement is greater than the signal power threshold (i.e., determination block **516**="Yes"), in determination block **518** the processor **214** may determine whether the cross block flag is set. If the cross block flag is set (i.e., determination block **518**="Yes"), referring to FIG. 5B, in block **526** the processor **214** may store the C RF measurement in the memory location for the sample and in block **528** the processor may increment the measurement counter (C). As discussed above, in blocks **530** and **532** the processor **214** may perform operations to determine whether the C RF measurement is greater than the signal power threshold and whether the end of the sample block is reached until the C RF measurement is less than or equal to the signal power threshold (i.e., determination block **530**="No") or the end of the sample block is reached (i.e., determination block **532**="Yes"). If the end of the sample block is reached (i.e., determination block **532**="Yes"), as discussed above in block **534** the cross block flag may be set (or verified and remain set if already set) and in block **535** the C RF measurement may be stored in the sample.

(56) If the end of the sample block is reached (i.e., determination block **532**="Yes") and in block **534** the cross block flag is set, referring to FIG. 5A, the processor may perform operations of blocks **506**, **508**, **510**, **512**, **516**, and **518** as discussed above. If the average of the sample block is less than the noise floor average (i.e., determination block **510**="No") and the cross block flag is set (i.e., determination block **514**="Yes"), the C RF measurement is less than or equal to the signal power threshold (i.e., determination block **516**="No") and the cross block flag is set (i.e., determination block **517**="Yes"), or the C RF measurement is less than or equal to the signal power threshold (i.e., determination block **516**="No"), referring to FIG. 5B, in block **538** the processor **214** may set the sample stop. As an example, the processor **214** may indicate that a sample end is reached in a memory and/or that a sample is complete in a memory. In block **540** the processor **214** may compute and store complex I and Q data for the stored measurements in the sample. In block **542** the processor **214** may determine a mean of the complex I and Q data. Referring to FIG. 5C, in determination block **544** the processor **214** may determine whether the mean of the complex I and Q data is greater than a signal threshold. If the mean of the complex I and Q data is less than or

equal to the signal threshold (i.e., determination block **544**="No"), in block **550** the processor **214** may indicate the sample is noise and discard data associated with the sample from memory. (57) If the mean is greater than the signal threshold (i.e., determination block **544**="Yes"), in block **546** the processor **214** may identify the sample as a signal of interest. In an embodiment, the processor **214** may identify the sample as a signal of interest by assigning a signal identifier to the signal, such as a signal number or sample number. In block **548** the processor **214** may determine and store signal parameters for the signal. As an example, the processor **214** may determine and store a frequency peak of the identified signal, a peak power of the identified signal, an average power of the identified signal, a signal bandwidth of the identified signal, and/or a signal duration of the identified signal. In block **552** the processor **214** may clear the cross block flag (or verify that the cross block flag is unset). In block **556** the processor **214** may determine whether the end of the sample block is reached. If the end of the sample block is not reached (i.e., determination block **556**="No") in block **558** the processor **214** may increment the measurement counter (C), and referring to FIG. 5A in determination block **516** may determine whether the C RF measurement is greater than the signal power threshold. Referring to FIG. 5C, if the end of the sample block is reached (i.e., determination block **556**="Yes"), referring to FIG. 5A, in block **506** the processor **214** may load the next available sample block.

(58) FIG. 6 illustrates a process flow for an embodiment method **600** for displaying signal identifications. In an embodiment, the operations of method **600** may be performed by a processor **214** of a spectrum management device **202**. In determination block **602** the processor **214** may determine whether a signal is identified. If a signal is not identified (i.e., determination block **602**="No"), in block **604** the processor **214** may wait for the next scan. If a signal is identified (i.e., determination block **602**="Yes"), in block **606** the processor **214** may compare the signal parameters of an identified signal to signal parameters in a history database **232**. In determination block **608** the processor **214** may determine whether signal parameters of the identified signal match signal parameters in the history database **232**. If there is no match (i.e., determination block **608**="No"), in block **610** the processor **214** may store the signal parameters as a new signal in the history database **232**. If there is a match (i.e., determination block **608**="Yes"), in block **612** the processor **214** may update the matching signal parameters as needed in the history database **232**.

(59) In block **614** the processor **214** may compare the signal parameters of the identified signal to signal parameters in a signal characteristic listing **236**. In an embodiment, the characteristic listing **236** may be a static database separate from the history database **232**, and the characteristic listing **236** may correlate signal parameters with signal identifications. In determination block **616** the processor **214** may determine whether the signal parameters of the identified signal match any signal parameters in the signal characteristic listing **236**. In an embodiment, the match in determination **616** may be a match based on a tolerance between the signal parameters of the identified signal and the parameters in the characteristic listing **236**. If there is a match (i.e., determination block **616**="Yes"), in block **618** the processor **214** may indicate a match in the history database **232** and in block **622** may display an indication of the signal identification on a display **242**. As an example, the indication of the signal identification may be a display of the radio call sign of an identified FM radio station signal. If there is not a match (i.e., determination block **616**="No"), in block **620** the processor **214** may display an indication that the signal is an unidentified signal. In this manner, the user may be notified a signal is present in the environment, but that the signal does not match to a signal in the characteristic listing.

(60) FIG. 7 illustrates a process flow of an embodiment method **700** for displaying one or more open frequency. In an embodiment, the operations of method **700** may be performed by the processor **214** of a spectrum management device **202**. In block **702** the processor **214** may determine a current location of the spectrum management device **202**. In an embodiment, the processor **214** may determine the current location of the spectrum management device **202** based on location inputs received from a location receiver **212**, such as GPS coordinates received from a

GPS receiver **212**. In block **704** the processor **214** may compare the current location to the stored location value in the historical database **232**. As discussed above, the historical or history database **232** may be a database storing information about signals previously actually identified by the spectrum management device **202**. In determination block **706** the processor **214** may determine whether there are any matches between the location information in the historical database **232** and the current location. If there are no matches (i.e., determination block **706**="No"), in block **710** the processor **214** may indicate incomplete data is available. In other words, the spectrum data for the current location has not previously been recorded.

(61) If there are matches (i.e., determination block **706**="Yes"), in optional block **708** the processor **214** may display a plot of one or more of the signals matching the current location. As an example, the processor **214** may compute the average frequency over frequency intervals across a given spectrum and may display a plot of the average frequency over each interval. In block **712** the processor **214** may determine one or more open frequencies at the current location. As an example, the processor **214** may determine one or more open frequencies by determining frequency ranges in which no signals fall or at which the average is below a threshold. In block **714** the processor **214** may display an indication of one or more open frequency on a display **242** of the spectrum management device **202**.

(62) FIG. **8A** is a block diagram of a spectrum management device **802** according to an embodiment. Spectrum management device **802** is similar to spectrum management device **202** described above with reference to FIG. **2A**, except that spectrum management device **802** may include symbol module **816** and protocol module **806** enabling the spectrum management device **802** to identify the protocol and symbol information associated with an identified signal as well as protocol match module **814** to match protocol information. Additionally, the characteristic listing **236** of spectrum management device **802** may include protocol data **804**, hardware data **808**, environment data **810**, and noise data **812** and an optimization module **818** may enable the signal processor **214** to provide signal optimization parameters.

(63) The protocol module **806** may identify the communication protocol (e.g., LTE, CDMA, etc.) associated with a signal of interest. In an embodiment, the protocol module **806** may use data retrieved from the characteristic listing, such as protocol data **804** to help identify the communication protocol. The symbol detector module **816** may determine symbol timing information, such as a symbol rate for a signal of interest. The protocol module **806** and/or symbol module **816** may provide data to the comparison module **222**. The comparison module **222** may include a protocol match module **814** which may attempt to match protocol information for a signal of interest to protocol data **804** in the characteristic listing to identify a signal of interest. Additionally, the protocol module **806** and/or symbol module **816** may store data in the memory module **226** and/or history database **232**. In an embodiment, the protocol module **806** and/or symbol module **816** may use protocol data **804** and/or other data from the characteristic listing **236** to help identify protocols and/or symbol information in signals of interest.

(64) The optimization module **818** may gather information from the characteristic listing, such as noise figure parameters, antenna hardware parameters, and environmental parameters correlated with an identified signal of interest to calculate a degradation value for the identified signal of interest. The optimization module **818** may further control the display **242** to output degradation data enabling a user of the spectrum management device **802** to optimize a signal of interest.

(65) FIG. **8B** is a schematic logic flow block diagram illustrating logical operations which may be performed by a spectrum management device according to an embodiment. Only those logical operations illustrated in FIG. **8B** different from those described above with reference to FIG. **2B** will be discussed. As illustrated in FIG. **8B**, as received time tracking **850** may be applied to the I and Q data from the receiver **210**. An additional buffer **851** may further store the I and Q data received and a symbol detector **852** may identify the symbols of a signal of interest and determine the symbol rate. A multiple access scheme identifier module **854** may identify whether the signal is

part of a multiple access scheme (e.g., CDMA), and a protocol identifier module **856** may attempt to identify the protocol the signal of interest is associated with. The multiple access scheme identifier module **854** and protocol identifier module **856** may retrieve data from the static database **238** to aid in the identification of the access scheme and/or protocol. The symbol detector module **852** may pass data to the signal parameter and protocol module **858** which may store protocol and symbol information in addition to signal parameter information for signals of interest.

(66) FIG. **9** illustrates a process flow of an embodiment method **900** for determining protocol data and symbol timing data. In an embodiment, the operations of method **900** may be performed by the processor **214** of a spectrum management device **802**. In determination block **902** the processor **214** may determine whether two or more signals are detected. If two or more signals are not detected (i.e., determination block **902**="No"), in determination block **902** the processor **214** may continue to determine whether two or more signals are detected. If two or more signals are detected (i.e., determination block **902**="Yes"), in determination block **904** the processor **214** may determine whether the two or more signals are interrelated. In an embodiment, a mean correlation value of the spectral decomposition of each signal may indicate the two or more signals are interrelated. As an example, a mean correlation of each signal may generate a value between 0.0 and 1, and the processor **214** may compare the mean correlation value to a threshold, such as a threshold of 0.75. In such an example, a mean correlation value at or above the threshold may indicate the signals are interrelated while a mean correlation value below the threshold may indicate the signals are not interrelated and may be different signals. In an embodiment, the mean correlation value may be generated by running a full energy bandwidth correlation of each signal, measuring the values of signal transition for each signal, and for each signal transition running a spectral correlation between signals to generate the mean correlation value. If the signals are not interrelated (i.e., determination block **904**="No"), the signals may be two or more different signals, and in block **907** processor **214** may measure the interference between the two or more signals. In an optional embodiment, in optional block **909** the processor **214** may generate a conflict alarm indicating the two or more different signals interfere. In an embodiment, the conflict alarm may be sent to the history database and/or a display. In determination block **902** the processor **214** may continue to determine whether two or more signals are detected. If the two signals are interrelated (i.e., determination block **904**="Yes"), in block **905** the processor **214** may identify the two or more signals as a single signal. In block **906** the processor **214** may combine signal data for the two or more signals into a signal single entry in the history database. In determination block **908** the processor **214** may determine whether the signals mean averages. If the mean averages (i.e., determination block **908**="Yes"), the processor **214** may identify the signal as having multiple channels in determination block **910**. If the mean does not average (i.e., determination block **908**="No") or after identifying the signal as having multiple channels in determination block **910**, in block **914** the processor **214** may determine and store protocol data for the signal. In block **916** the processor **214** may determine and store symbol timing data for the signal, and the method **900** may return to block **902**.

(67) FIG. **10** illustrates a process flow of an embodiment method **1000** for calculating signal degradation data. In an embodiment, the operations of method **1000** may be performed by the processor **214** of a spectrum management device **202**. In block **1002** the processor may detect a signal. In block **1004** the processor **214** may match the signal to a signal in a static database. In block **1006** the processor **214** may determine noise figure parameters based on data in the static database **236** associated with the signal. As an example, the processor **214** may determine the noise figure of the signal based on parameters of a transmitter outputting the signal according to the static database **236**. In block **1008** the processor **214** may determine hardware parameters associated with the signal in the static database **236**. As an example, the processor **214** may determine hardware parameters such as antenna position, power settings, antenna type, orientation, azimuth, location, gain, and equivalent isotropically radiated power (EIRP) for the transmitter associated with the

signal from the static database **236**. In block **1010** processor **214** may determine environment parameters associated with the signal in the static database **236**. As an example, the processor **214** may determine environment parameters such as rain, fog, and/or haze based on a delta correction factor table stored in the static database and a provided precipitation rate (e.g., mm/hr). In block **1012** the processor **214** may calculate and store signal degradation data for the detected signal based at least in part on the noise figure parameters, hardware parameters, and environmental parameters. As an example, based on the noise figure parameters, hardware parameters, and environmental parameters free space losses of the signal may be determined. In block **1014** the processor **214** may display the degradation data on a display **242** of the spectrum management device **202**. In a further embodiment, the degradation data may be used with measured terrain data of geographic locations stored in the static database to perform pattern distortion, generate propagation and/or next neighbor interference models, determine interference variables, and perform best fit modeling to aide in signal and/or system optimization.

(68) FIG. **11** illustrates a process flow of an embodiment method **1100** for displaying signal and protocol identification information. In an embodiment, the operations of method **1100** may be performed by a processor **214** of a spectrum management device **202**. In block **1102** the processor **214** may compare the signal parameters and protocol data of an identified signal to signal parameters and protocol data in a history database **232**. In an embodiment, a history database **232** may be a database storing signal parameters and protocol data for previously identified signals. In block **1104** the processor **214** may determine whether there is a match between the signal parameters and protocol data of the identified signal and the signal parameters and protocol data in the history database **232**. If there is not a match (i.e., determination block **1104**="No"), in block **1106** the processor **214** may store the signal parameters and protocol data as a new signal in the history database **232**. If there is a match (i.e., determination block **1104**="Yes"), in block **1108** the processor **214** may update the matching signal parameters and protocol data as needed in the history database **232**.

(69) In block **1110** the processor **214** may compare the signal parameters and protocol data of the identified signal to signal parameters and protocol data in the signal characteristic listing **236**. In determination block **1112** the processor **214** may determine whether the signal parameters and protocol data of the identified signal match any signal parameters and protocol data in the signal characteristic listing **236**. If there is a match (i.e., determination block **1112**="Yes"), in block **1114** the processor **214** may indicate a match in the history database and in block **1118** may display an indication of the signal identification and protocol on a display. If there is not a match (i.e., determination block **1112**="No"), in block **1116** the processor **214** may display an indication that the signal is an unidentified signal. In this manner, the user may be notified a signal is present in the environment, but that the signal does not match to a signal in the characteristic listing.

(70) FIG. **12A** is a block diagram of a spectrum management device **1202** according to an embodiment. Spectrum management device **1202** is similar to spectrum management device **802** described above with reference to FIG. **8A**, except that spectrum management device **1202** may include TDOA/FDOA module **1204** and modulation module **1206** enabling the spectrum management device **1202** to identify the modulation type employed by a signal of interest and calculate signal origins. The modulation module **1206** may enable the signal processor to determine the modulation applied to signal, such as frequency modulation (e.g., FSK, MSK, etc.) or phase modulation (e.g., BPSK, QPSK, QAM, etc.) as well as to demodulate the signal to identify payload data carried in the signal. The modulation module **1206** may use payload data **1221** from the characteristic listing to identify the data types carried in a signal. As examples, upon demodulating a portion of the signal the payload data may enable the processor **214** to determine whether voice data, video data, and/or text based data is present in the signal. The TDOA/FDOA module **1204** may enable the signal processor **214** to determine time difference of arrival for signals of interest and/or frequency difference of arrival for signals of interest. Using the TDOA/FDOA information

estimates of the origin of a signal may be made and passed to a mapping module **1225** which may control the display **242** to output estimates of a position and/or direction of movement of a signal.

(71) FIG. **12B** is a schematic logic flow block diagram illustrating logical operations which may be performed by a spectrum management device according to an embodiment. Only those logical operations illustrated in FIG. **12B** different from those described above with reference to FIG. **8B** will be discussed. A magnitude squared **1252** operation may be performed on data from the symbol detector **852** to identify whether frequency or phase modulation is present in the signal. Phase modulated signals may be identified by the phase modulation **1254** processes and frequency modulated signals may be identified by the frequency modulation **1256** processes. The modulation information may be passed to a signal parameters, protocols, and modulation module **1258**.

(72) FIG. **13** illustrates a process flow of an embodiment method **1300** for estimating a signal origin based on a frequency difference of arrival. In an embodiment, the operations of method **1300** may be performed by a processor **214** of a spectrum management device **1202**. In block **1302** the processor **214** may compute frequency arrivals and phase arrivals for multiple instances of an identified signal. In block **1304** the processor **214** may determine frequency difference of arrival for the identified signal based on the computed frequency difference and phase difference. In block **1306** the processor may compare the determined frequency difference of arrival for the identified signal to data associated with known emitters in the characteristic listing to estimate an identified signal origin. In block **1308** the processor **214** may indicate the estimated identified signal origin on a display of the spectrum management device. As an example, the processor **214** may overlay the estimated origin on a map displayed by the spectrum management device.

(73) FIG. **14** illustrates a process flow of an embodiment method for displaying an indication of an identified data type within a signal. In an embodiment, the operations of method **1400** may be performed by a processor **214** of a spectrum management device **1202**. In block **1402** the processor **214** may determine the signal parameters for an identified signal of interest. In block **1404** the processor **214** may determine the modulation type for the signal of interest. In block **1406** the processor **214** may determine the protocol data for the signal of interest. In block **1408** the processor **214** may determine the symbol timing for the signal of interest. In block **1410** the processor **214** may select a payload scheme based on the determined signal parameters, modulation type, protocol data, and symbol timing. As an example, the payload scheme may indicate how data is transported in a signal. For example, data in over the air television broadcasts may be transported differently than data in cellular communications and the signal parameters, modulation type, protocol data, and symbol timing may identify the applicable payload scheme to apply to the signal. In block **1412** the processor **214** may apply the selected payload scheme to identify the data type or types within the signal of interest. In this manner, the processor **214** may determine what type of data is being transported in the signal, such as voice data, video data, and/or text based data. In block **1414** the processor may store the data type or types. In block **1416** the processor **214** may display an indication of the identified data types.

(74) FIG. **15** illustrates a process flow of an embodiment method **1500** for determining modulation type, protocol data, and symbol timing data. Method **1500** is similar to method **900** described above with reference to FIG. **9**, except that modulation type may also be determined. In an embodiment, the operations of method **1500** may be performed by a processor **214** of a spectrum management device **1202**. In blocks **902**, **904**, **905**, **906**, **908**, and **910** the processor **214** may perform operations of like numbered blocks of method **900** described above with reference to FIG. **9**. In block **1502** the processor may determine and store a modulation type. As an example, a modulation type may be an indication that the signal is frequency modulated (e.g., FSK, MSK, etc.) or phase modulated (e.g., BPSK, QPSK, QAM, etc.). As discussed above, in block **914** the processor may determine and store protocol data and in block **916** the processor may determine and store timing data.

(75) In an embodiment, based on signal detection, a time tracking module, such as a TDOA/FDOA

module **1204**, may track the frequency repetition interval at which the signal is changing. The frequency repetition interval may also be tracked for a burst signal. In an embodiment, the spectrum management device may measure the signal environment and set anchors based on information stored in the historic or static database about known transmitter sources and locations. In an embodiment, the phase information about a signal be extracted using a spectral decomposition correlation equation to measure the angle of arrival (“AOA”) of the signal. In an embodiment, the processor of the spectrum management device may determine the received power as the Received Signal Strength (“RSS”) and based on the AOA and RSS may measure the frequency difference of arrival. In an embodiment, the frequency shift of the received signal may be measured and aggregated over time. In an embodiment, after an initial sample of a signal, known transmitted signals may be measured and compared to the RSS to determine frequency shift error. In an embodiment, the processor of the spectrum management device may compute a cross ambiguity function of aggregated changes in arrival time and frequency of arrival. In an additional embodiment, the processor of the spectrum management device may retrieve FFT data for a measured signal and aggregate the data to determine changes in time of arrival and frequency of arrival. In an embodiment, the signal components of change in frequency of arrival may be averaged through a Kalman filter with a weighted tap filter from 2 to 256 weights to remove measurement error such as noise, multipath interference, etc. In an embodiment, frequency difference of arrival techniques may be applied when either the emitter of the signal or the spectrum management device is moving or when then emitter of the signal and the spectrum management device are both stationary. When the emitter of the signal and the spectrum management device are both stationary the determination of the position of the emitter may be made when at least four known other known signal emitters positions are known and signal characteristics may be available. In an embodiment, a user may provide the four other known emitters and/or may use already in place known emitters, and may use the frequency, bandwidth, power, and distance values of the known emitters and their respective signals. In an embodiment, where the emitter of the signal or spectrum management device may be moving, frequency difference of arrival techniques may be performed using two known emitters.

(76) FIG. **16** illustrates an embodiment method for tracking a signal origin. In an embodiment, the operations of method **1600** may be performed by a processor **214** of a spectrum management device **1202**. In block **1602** the processor **214** may determine a time difference of arrival for a signal of interest. In block **1604** the processor **214** may determine a frequency difference of arrival for the signal interest. As an example, the processor **214** may take the inverse of the time difference of arrival to determine the frequency difference of arrival of the signal of interest. In block **1606** the processor **214** may identify the location. As an example, the processor **214** may determine the location based on coordinates provided from a GPS receiver. In determination block **1608** the processor **214** may determine whether there are at least four known emitters present in the identified location. As an example, the processor **214** may compare the geographic coordinates for the identified location to a static database and/or historical database to determine whether at least four known signals are within an area associated with the geographic coordinates. If at least four known emitters are present (i.e., determination block **1608**=“Yes”), in block **1612** the processor **214** may collect and measure the RSS of the known emitters and the signal of interest. As an example, the processor **214** may use the frequency, bandwidth, power, and distance values of the known emitters and their respective signals and the signal of interest. If less than four known emitters are present (i.e., determination block **1608**=“No”), in block **1610** the processor **214** may measure the angle of arrival for the signal of interest and the known emitter. Using the RSS or angle of arrival, in block **1614** the processor **214** may measure the frequency shift and in block **1616** the processor **214** may obtain the cross ambiguity function. In determination block **1618** the processor **214** may determine whether the cross ambiguity function converges to a solution. If the cross ambiguity function does converge to a solution (i.e., determination block **1618**=“Yes”), in block **1620** the

processor **214** may aggregate the frequency shift data. In block **1622** the processor **214** may apply one or more filter to the aggregated data, such as a Kalman filter. Additionally, the processor **214** may apply equations, such as weighted least squares equations and maximum likelihood equations, and additional filters, such as a non-line-of-sight (“NLOS”) filters to the aggregated data. In an embodiment, the cross ambiguity function may resolve the position of the emitter of the signal of interest to within 3 meters. If the cross ambiguity function does not converge to a solution (i.e., determination block **1618**=“No”), in block **1624** the processor **214** may determine the time difference of arrival for the signal and in block **1626** the processor **214** may aggregate the time shift data. Additionally, the processor may filter the data to reduce interference. Whether based on frequency difference of arrival or time difference of arrival, the aggregated and filtered data may indicate a position of the emitter of the signal of interest, and in block **1628** the processor **214** may output the tracking information for the position of the emitter of the signal of interest to a display of the spectrum management device and/or the historical database. In an additional embodiment, location of emitters, time and duration of transmission at a location may be stored in the history database such that historical information may be used to perform and predict movement of signal transmission. In a further embodiment, the environmental factors may be considered to further reduce the measured error and generate a more accurate measurement of the location of the emitter of the signal of interest.

(77) The processor **214** of spectrum management devices **202**, **802** and **1202** may be any programmable microprocessor, microcomputer or multiple processor chip or chips that can be configured by software instructions (applications) to perform a variety of functions, including the functions of the various embodiments described above. In some devices, multiple processors may be provided, such as one processor dedicated to wireless communication functions and one processor dedicated to running other applications. Typically, software applications may be stored in the internal memory **226** or **230** before they are accessed and loaded into the processor **214**. The processor **214** may include internal memory sufficient to store the application software instructions. In many devices the internal memory may be a volatile or nonvolatile memory, such as flash memory, or a mixture of both. For the purposes of this description, a general reference to memory refers to memory accessible by the processor **214** including internal memory or removable memory plugged into the device and memory within the processor **214** itself.

(78) The foregoing method descriptions and the process flow diagrams are provided merely as illustrative examples and are not intended to require or imply that the steps of the various embodiments must be performed in the order presented. As will be appreciated by one of skill in the art the order of steps in the foregoing embodiments may be performed in any order. Words such as “thereafter,” “then,” “next,” etc. are not intended to limit the order of the steps; these words are simply used to guide the reader through the description of the methods. Further, any reference to claim elements in the singular, for example, using the articles “a,” “an” or “the” is not to be construed as limiting the element to the singular.

(79) The various illustrative logical blocks, modules, circuits, and algorithm steps described in connection with the embodiments disclosed herein may be implemented as electronic hardware, computer software, or combinations of both. To clearly illustrate this interchangeability of hardware and software, various illustrative components, blocks, modules, circuits, and steps have been described above generally in terms of their functionality. Whether such functionality is implemented as hardware or software depends upon the particular application and design constraints imposed on the overall system. Skilled artisans may implement the described functionality in varying ways for each particular application, but such implementation decisions should not be interpreted as causing a departure from the scope of the present invention.

(80) The hardware used to implement the various illustrative logics, logical blocks, modules, and circuits described in connection with the aspects disclosed herein may be implemented or performed with a general purpose processor, a digital signal processor (DSP), an application



specific integrated circuit (ASIC), a field programmable gate array (FPGA) or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general-purpose processor may be a microprocessor, but, in the alternative, the processor may be any conventional processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices, e.g., a combination of a DSP and a microprocessor, a plurality of microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration. Alternatively, some steps or methods may be performed by circuitry that is specific to a given function.

(81) In one or more exemplary aspects, the functions described may be implemented in hardware, software, firmware, or any combination thereof. If implemented in software, the functions may be stored as one or more instructions or code on a non-transitory computer-readable medium or non-transitory processor-readable medium. The steps of a method or algorithm disclosed herein may be embodied in a processor-executable software module which may reside on a non-transitory computer-readable or processor-readable storage medium. Non-transitory computer-readable or processor-readable storage media may be any storage media that may be accessed by a computer or a processor. By way of example but not limitation, such non-transitory computer-readable or processor-readable media may include RAM, ROM, EEPROM, FLASH memory, CD-ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other medium that may be used to store desired program code in the form of instructions or data structures and that may be accessed by a computer. Disk and disc, as used herein, includes compact disc (CD), laser disc, optical disc, digital versatile disc (DVD), floppy disk, and Blu-ray disc where disks usually reproduce data magnetically, while discs reproduce data optically with lasers. Combinations of the above are also included within the scope of non-transitory computer-readable and processor-readable media. Additionally, the operations of a method or algorithm may reside as one or any combination or set of codes and/or instructions on a non-transitory processor-readable medium and/or computer-readable medium, which may be incorporated into a computer program product.

(82) The preceding description of the disclosed embodiments is provided to enable any person skilled in the art to make or use the present invention. Various modifications to these embodiments will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other embodiments without departing from the spirit or scope of the invention. Thus, the present invention is not intended to be limited to the embodiments shown herein but is to be accorded the widest scope consistent with the following claims and the principles and novel features disclosed herein.

## Claims

1. A spectrum analysis system comprising: a radiofrequency (RF) receiver operable to capture RF data including data relating to at least one signal; at least one device including a processor and a memory operable to receive and analyze the RF data; and a data extraction module operable to receive spectral components of the at least one signal; wherein the data extraction module is operable to organize the spectral components in a format based on user input; wherein the spectral components include modulation type and protocol; wherein the at least one device is operable to determine signal degradation data for the at least one signal; wherein the signal degradation data is used to perform pattern distortion, generate propagation models, and generate next neighbor interference models; wherein the signal degradation data is based on noise figure parameters of at least one second device emitting the at least one signal; and wherein the noise figure parameters are based on data in a static database associated with the at least one signal.
2. The system of claim 1, wherein the signal degradation data includes values for free space losses

of the at least one signal.

3. The system of claim 1, further comprising an optimization module operable to provide signal optimization parameters.

4. The system of claim 3, wherein the optimization module is operable to provide the signal optimization parameters for center frequency, bandwidth, and/or power.

5. The system of claim 1, wherein the at least one device is operable to compare the data relating to the at least one signal with stored data.

6. The system of claim 1, wherein the at least one device is operable to identify the at least one signal in real-time or near real-time.

7. The system of claim 1, wherein the signal degradation data is used with measured terrain data of geographic locations to perform the pattern distortion, generate the propagation models, and generate the next neighbor interference models.

8. A spectrum analysis apparatus comprising: at least one device including a processor and a memory operable to receive and analyze radiofrequency (RF) data; and a data extraction module operable to receive spectral components of the at least one signal; wherein the data extraction module is operable to organize the spectral components in a format based on user input; wherein the RF Data is collected from a frequency based on the user input; wherein the at least one device is operable to determine signal degradation data for at least one signal; wherein the signal degradation data is based on noise figure parameters, hardware parameters, and environmental parameters of at least one second device emitting the at least one signal; and wherein the hardware parameters comprise antenna type, orientation, azimuth, gain, and/or effective isotropic radiated power (EIRP) and/or wherein the environmental parameters comprise rain, fog, and/or haze.

9. The apparatus of claim 8, wherein the signal degradation data includes values for free space losses of the at least one signal.

10. The apparatus of claim 8, further comprising an optimization module operable to provide signal optimization parameters.

11. The apparatus of claim 10, wherein the optimization module is operable to provide the signal optimization parameters for center frequency, bandwidth, and/or power.

12. The apparatus of claim 8, wherein the at least one device is operable to compare data for the at least one signal with stored data.

13. The apparatus of claim 8, wherein the at least one device is operable to identify the at least one signal in real-time or near real-time.

14. A method for spectrum analysis, comprising: at least one device including a processor and a memory analyzing radio frequency (RF) data to identify at least one signal; receiving by a data extraction module spectral components of the at least one signal; organizing by the data extraction module the spectral components in a format based on user input; wherein the spectral components include modulation type and protocol; the at least one device determining signal degradation data for the at least one signal; and performing pattern distortion, generating propagation models, and generating next neighbor interference models using the signal degradation data; wherein the signal degradation data is based on noise figure parameters of at least one second device emitting the at least one signal; and wherein the noise figure parameters are based on data in a static database associated with the at least one signal.

15. The method of claim 14, wherein the signal degradation data includes values for free space losses of the at least one signal.

16. The method of claim 14, further comprising an optimization module providing signal optimization parameters.

17. The method of claim 16, wherein the optimization module provides the signal optimization parameters for center frequency, bandwidth, and/or power.

18. The method of claim 14, wherein the signal degradation data is further based on hardware parameters, wherein the hardware parameters comprise antenna type, orientation, azimuth, gain,

and/or effective isotropic radiated power (EIRP).

19. The method of claim 14, further comprising the at least one device comparing data relating to the at least one signal with stored data.

20. The method of claim 14, wherein the RF data includes a location from which the at least one second device is emitting the at least one signal.

---