



US012416622B2

(12) **United States Patent**
Fouda et al.

(10) **Patent No.:** **US 12,416,622 B2**
(45) **Date of Patent:** **Sep. 16, 2025**

(54) **SENSORS FOR MEASURING PROPERTIES OF MATERIALS FLOWING THROUGH A FLOWLINE**

(56) **References Cited**

U.S. PATENT DOCUMENTS

(71) Applicant: **Halliburton Energy Services, Inc.**,
Houston, TX (US)

5,677,631 A 10/1997 Reitinger et al.
6,938,470 B2 * 9/2005 DiFoggio G01N 9/002
73/152.16
7,574,898 B2 * 8/2009 Harrison G01N 29/4418
73/54.24
8,850,879 B2 * 10/2014 Swett E21B 47/017
73/152.24

(72) Inventors: **Ahmed Fouda**, Houston, TX (US);
Baris Guner, Houston, TX (US)

(Continued)

(73) Assignee: **Halliburton Energy Services, Inc.**,
Houston, TX (US)

FOREIGN PATENT DOCUMENTS

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 229 days.

EP 2104837 9/2017
WO 2016060860 4/2016

OTHER PUBLICATIONS

(21) Appl. No.: **18/081,914**

Balanis, Constantine A. "Antenna Theory Analysis and Design 3rd Edition. New Jersey: John Wiley & Sons." Inc.[Jan. 3, 2020] (2005).

(22) Filed: **Dec. 15, 2022**

(Continued)

(65) **Prior Publication Data**

US 2024/0201162 A1 Jun. 20, 2024

Primary Examiner — Jill E Culler

(74) *Attorney, Agent, or Firm* — Benjamin Ford; C. Tumey Law Group, PLLC

(51) **Int. Cl.**

G01N 33/28 (2006.01)

E21B 49/10 (2006.01)

G01N 27/08 (2006.01)

(57) **ABSTRACT**

(52) **U.S. Cl.**

CPC **G01N 33/2823** (2013.01); **E21B 49/10**
(2013.01); **G01N 27/08** (2013.01); **G01N**
33/28 (2013.01)


A method and system for downhole sampling. The system may include a downhole fluid sampling tool that may include one or more probes configured to extend into a formation, and a pump configured to collect a fluid from the formation through the one or more probes. The method may further comprise a flowline configured to transport the fluid from the formation through the one or more probes and through the downhole fluid sampling tool and a fluid analysis module comprising a resonator antenna disposed on the

(58) **Field of Classification Search**

CPC E21B 49/081; E21B 49/10; G01N 27/08;
G01N 33/28; G01N 33/2823

See application file for complete search history.

(Continued)



flowline and configured to measure at least one property of the fluid. Additionally, the method may comprise measuring at least one property of the fluid with at least one resonator antennas that are disposed on or within an outer surface of the flowline.

20 Claims, 12 Drawing Sheets

(56)

References Cited

U.S. PATENT DOCUMENTS

9,557,439 B2	1/2017	Wilson et al.	
9,562,864 B2 *	2/2017	Harrison	H01P 7/06
10,101,492 B2	10/2018	Fouda et al.	
10,227,864 B2	3/2019	Donderici et al.	
10,241,226 B2	3/2019	Donderici et al.	
10,301,935 B2	5/2019	Wang et al.	
10,422,913 B2	9/2019	Fouda et al.	
10,520,638 B1	12/2019	Lowell et al.	
10,526,885 B2	1/2020	Fouda et al.	
10,591,628 B2	3/2020	Fouda et al.	
10,684,236 B2 *	6/2020	Hurlimann	G01N 22/00
10,697,290 B2	6/2020	Wilson et al.	
11,377,946 B2	7/2022	Donderici et al.	
2014/0032116 A1	1/2014	Guner	
2014/0244175 A1	8/2014	Donderici et al.	
2014/0252250 A1	9/2014	Botto et al.	

2015/0309201 A1	10/2015	Wu et al.
2016/0266271 A1	9/2016	Fouda et al.
2017/0082770 A1	3/2017	Mandviwala et al.
2017/0115236 A1	4/2017	Renlund et al.
2017/0123096 A1	5/2017	Wilson et al.
2017/0254917 A1	9/2017	Fouda et al.
2018/0038222 A1	2/2018	Samson et al.
2018/0283170 A1	10/2018	Donderici et al.
2018/0329105 A1	11/2018	Capoglu et al.
2019/0086575 A1	3/2019	Fouda et al.
2019/0196039 A1	6/2019	Wilson et al.
2019/0203580 A1	7/2019	Guner et al.
2019/0218905 A1	7/2019	Donderici et al.
2019/0353820 A1	11/2019	Chen et al.
2020/0271817 A1	8/2020	Ewe et al.
2020/0319362 A1	10/2020	Guner et al.

OTHER PUBLICATIONS

Cheng, David Keun. Field and wave electromagnetics. Pearson New International Edition, 2014.

Fouda et al., U.S. Appl. No. 17/736,845 (unpublished), filed May 4, 2022.

Pfeiffer et al., Calibrated Formation Water Resistivity Sensor, May 2020.

Soeimani, Manuchehr, Super-sensing through industrial process tomography, Feb. 2016.

International Search Report and Written Opinion for International Patent Application No. PCT/US2023/010625 dated Sep. 5, 2023.

* cited by examiner




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7A




FIG. 7B




FIG. 7C




FIG. 7D




FIG. 8A




FIG. 8B




FIG. 9




FIG. 10




FIG. 11A




FIG. 11B




FIG. 11C




FIG. 12A




FIG. 12B




FIG. 13A




FIG. 13B




FIG. 13C

SENSORS FOR MEASURING PROPERTIES OF MATERIALS FLOWING THROUGH A FLOWLINE

BACKGROUND

Wells may be drilled at various depths to access and produce oil, gas, minerals, and other naturally-occurring deposits from subterranean geological formations. The drilling of a well is typically accomplished with a drill bit that is rotated within the well to advance the well by removing topsoil, sand, clay, limestone, calcites, dolomites, or other materials. During or after drilling operations, sampling operations may be performed to collect a representative sample of formation or reservoir fluids (e.g., hydrocarbons) to further evaluate drilling operations and production potential, or to detect the presence of certain gases or other materials in the formation that may affect well performance. Sampling operations may require the use of a downhole fluid sampling tool.

During sampling operations, a downhole fluid sampling tool may collect fluid samples from a formation. Generally, the fluid may flow through a flowline and undergo measurements. The fluid may then be removed from the fluid sampling tool into a wellbore or saved as a fluid sample within the downhole fluid sampling tool. During such sampling operations, it may be valuable to perform resistivity and permittivity measurements on the fluid flowing through the flowline. In examples, logging may be performed directly on a production flowline without the physical sampling of the fluid as well. In further examples, resistivity and permittivity measurements may be utilized to determine the properties of the fluid and/or materials within the fluid passing through the flowline and/or quantify the changes in flow over time.

Electrodes have traditionally been utilized as antennas in flowlines to determine the resistivity of the fluid passing through. However, electrodes tend to be easily coated by particles in the fluid flowing through the flowline, such as a small film of oil or dissolved minerals inside the fluid. As a result, resistivity measurements with electrodes may yield bias in the resulting resistivity measurements, affecting the accuracy of the petrophysical estimates. Furthermore, electrodes work on galvanic principles, thus requiring the continuous phase in the fluid to be conductive. Coil antennas may also be used to determine resistivity and permittivity measurements to determine the properties of the fluid and/or materials within the fluid passing through the flowline and/or quantify the changes in flow over time. However, coil antennas employ induction principles and the received signal is proportional to the conductivity of the materials in the volume of sensitivity of the tool. Thus, they do not work in the presence of conducting or magnetic flowlines. Additionally, a high-frequency flowline antenna design that is capable of measuring both the conductivity and the permittivity of the fluid requires a purpose-built flowline design. Currently, technology is not able to provide an antenna structure for traditional flowlines that does not degrade over time due to the accumulation of contaminants from the fluids and capable of making measurements in conducting flowlines.

BRIEF DESCRIPTION OF THE DRAWINGS

These drawings illustrate certain aspects of some examples of the present disclosure and should not be used to limit or define the disclosure.

FIG. 1 illustrates a schematic view of a well in which an example embodiment of a fluid sample system is deployed;

FIG. 2 illustrates a schematic view of another well in which an example embodiment of a fluid sample system is deployed;

FIG. 3 illustrates a schematic view of a chipset in an information handling system;

FIG. 4 illustrates the chipset in communication with other components of the information handling system;

FIG. 5 illustrates an example of one arrangement of resources in a computing network;

FIG. 6 illustrates a schematic view of an example embodiment of a fluid sampling tool;

FIG. 7A illustrates an electrode system;

FIG. 7B illustrates a coil antenna system;

FIG. 7C illustrates a waveguide flowline sensor;

FIG. 7D illustrates electrical impedance tomography system;

FIG. 8A illustrates a resonator antenna configured as a microstrip patch antenna;

FIG. 8B illustrates the resonator antenna configured as a cavity resonator;

FIG. 9 illustrates the fluid analysis module that comprises the resonator antenna disposed between the outer surface and the inner surface of the flowline;

FIG. 10 illustrates fluid analysis module that comprises a resonator antenna disposed between outer surface and inner surface;

FIG. 11A illustrates an alignment of slots;

FIG. 11B illustrates another alignment of slots;

FIG. 11C illustrates another example of alignment of slots;

FIG. 12A illustrates the fluid analysis module that comprises the resonator antenna as a microstrip patch antenna disposed along the outer surface of the flowline;

FIG. 12B illustrates the fluid analysis module that comprises the resonator antenna disposed within the flowline;

FIG. 13A illustrates the resonator antennas as cavity resonators located outside the flowline;

FIG. 13B illustrates the resonator antennas as microstrip patch antennas located outside the flowline; and

FIG. 13C illustrates an example of resonator antennas as cavity resonators inside the outer wall of the flowline.

DETAILED DESCRIPTION

The present disclosure relates to methods and systems for measuring resistivity and permittivity measurements to determine the properties of a fluid passing through the flowline and/or quantify the changes in flow over time. Specifically, resonator antennas may perform resistivity and permittivity measurements in flowlines of a downhole fluid sampling tool or directly in flowlines of the production tubing. Resonator antennas may not be affected by the accumulation of particles and may measure both conductive and nonconductive fluid. Furthermore, resonator antennas may be low-profile, easy to manufacture, have a high signal-to-noise ratio, and low leakage. Discussed below are methods and systems for measuring properties of material and fluids within a flowline. Although the rest of the discussion will focus on the flowlines of a downhole fluid sampling tool, same methods and systems may also be used in the flowlines of production tubing that does not perform fluid sampling without any loss of generality. Additionally, methods and systems may comprise tomography designs that may be capable of measuring the phases of the material and fluids within the downhole fluid sampling tool.

3

FIG. 1 is a schematic diagram of downhole fluid sampling tool **100** on a conveyance **102**. As illustrated, wellbore **104** may extend through subterranean formation **106**. In examples, reservoir fluid may be contaminated with well fluid (e.g., drilling fluid) from wellbore **104**. As described herein, the fluid sample may be analyzed to determine fluid contamination and other fluid properties of the reservoir fluid. As illustrated, a wellbore **104** may extend through subterranean formation **106**. While the wellbore **104** is shown extending generally vertically into the subterranean formation **106**, the principles described herein are also applicable to wellbores that extend at an angle through the subterranean formation **106**, such as horizontal and slanted wellbores. For example, although FIG. 1 shows a vertical or low inclination angle well, high inclination angle or horizontal placement of the well and equipment is also possible. It should further be noted that while FIG. 1 generally depicts a land-based operation, those skilled in the art will readily recognize that the principles described herein are equally applicable to subsea operations that employ floating or sea-based platforms and rigs, without departing from the scope of the disclosure.

As illustrated, a hoist **108** may be used to run downhole fluid sampling tool **100** into wellbore **104**. Hoist **108** may be disposed on a vehicle **110**. Hoist **108** may be used, for example, to raise and lower conveyance **102** in wellbore **104**. While hoist **108** is shown on vehicle **110**, it should be understood that conveyance **102** may alternatively be disposed from a hoist **108** that is installed at surface **112** instead of being located on vehicle **110**. Downhole fluid sampling tool **100** may be suspended in wellbore **104** on conveyance **102**. Other conveyance types may be used for conveying downhole fluid sampling tool **100** into wellbore **104**, including coiled tubing and wired drill pipe, for example. Downhole fluid sampling tool **100** may comprise a tool body **114**, which may be elongated as shown on FIG. 1. Tool body **114** may be any suitable material, including without limitation titanium, stainless steel, alloys, plastic, combinations thereof, and the like. Downhole fluid sampling tool **100** may further include one or more sensors **116** for measuring properties of the fluid sample, reservoir fluid, wellbore **104**, subterranean formation **106**, or the like. In examples, downhole fluid sampling tool **100** may also include a fluid analysis module **118**, which may be operable to process information regarding fluid sample, as described below. The downhole fluid sampling tool **100** may be used to collect fluid samples from subterranean formation **106** and may obtain and separately store different fluid samples from subterranean formation **106**. In examples, fluid analysis module **118** may comprise at least one resonator antenna **160**. Resonator antenna **160** may form more than one configuration, described in detail in FIGS. 7A, 7B, 8, 9, 10A, 10B, 10C, 11A, 11B, 13A, 13B, and 13C. Resonator antenna **160** may be configured to measure S parameters of fluids within sampling tool **100**, to be described in detail below.

Any suitable technique may be used for transmitting signals from the downhole fluid sampling tool **100** to the surface **112**. As illustrated, a communication link **120** (which may be wired or wireless, for example) may be provided that may transmit data from downhole fluid sampling tool **100** to an information handling system **122** at surface **112**. Information handling system **122** may include a processing unit **124**, a monitor **126**, an input device **128** (e.g., keyboard, mouse, etc.), and/or computer media **130** (e.g., optical disks, magnetic disks) that can store code representative of the methods described herein. Information handling system **122** may act as a data acquisition system and possibly a data

4

processing system that analyzes information from downhole fluid sampling tool **100**. For example, information handling system **122** may process the information from downhole fluid sampling tool **100** for determination of fluid contamination. The information handling system **122** may also determine additional properties of the fluid sample (or reservoir fluid), such as component concentrations, pressure-volume-temperature properties (e.g., bubble point, phase envelop prediction, etc.) based on the fluid characterization. This processing may occur at surface **112** in real-time. Alternatively, the processing may occur downhole hole or at surface **112** or another location after recovery of downhole fluid sampling tool **100** from wellbore **104**. Alternatively, the processing may be performed by an information handling system in wellbore **104**, such as fluid analysis module **118**. The resultant fluid contamination and fluid properties may then be transmitted to surface **112**, for example, in real-time. Real time may be defined within any range comprising 0.01 seconds to 0.1 seconds, 0.1 seconds to 1 second, 1 second to 1 minute, 1 minute to 1 hour, 1 hour to 4 hours, or any combination of ranges provided.

Referring now to FIG. 2, a schematic diagram of downhole fluid sampling tool **100** disposed on a drill string **200** in a drilling operation. Downhole fluid sampling tool **100** may be used to obtain a fluid sample, for example, a fluid sample of a reservoir fluid from subterranean formation **106**. The reservoir fluid may be contaminated with well fluid (e.g., drilling fluid) from wellbore **104**. As described herein, the fluid sample may be analyzed to determine fluid contamination and other fluid properties of the reservoir fluid. As illustrated, a wellbore **104** may extend through subterranean formation **106**. While the wellbore **104** is shown extending generally vertically into the subterranean formation **106**, the principles described herein are also applicable to wellbores that extend at an angle through the subterranean formation **106**, such as horizontal and slanted wellbores. For example, although FIG. 2 shows a vertical or low inclination angle well, high inclination angle or horizontal placement of the well and equipment is also possible. It should further be noted that while FIG. 2 generally depicts a land-based operation, those skilled in the art will readily recognize that the principles described herein are equally applicable to subsea operations that employ floating or sea-based platforms and rigs, without departing from the scope of the disclosure.

As illustrated, a drilling platform **202** may support a derrick **204** having a traveling block **206** for raising and lowering drill string **200**. Drill string **200** may include, but is not limited to, drill pipe and coiled tubing, as generally known to those skilled in the art. A kelly **208** may support drill string **200** as it may be lowered through a rotary table **210**. A drill bit **212** may be attached to the distal end of drill string **200** and may be driven either by a downhole motor and/or via rotation of drill string **200** from the surface **112**. Without limitation, drill bit **212** may include, roller cone bits, PDC bits, natural diamond bits, any hole openers, reamers, coring bits, and the like. As drill bit **212** rotates, it may create and extend wellbore **104** that penetrates various subterranean formations **106**. A pump **214** may circulate drilling fluid through a feed pipe **216** to kelly **208**, downhole through interior of drill string **200**, through orifices in drill bit **212**, back to surface **112** via annulus **218** surrounding drill string **200**, and into a retention pit **220**.

Drill bit **212** may be just one piece of a downhole assembly that may include one or more drill collars **222** and downhole fluid sampling tool **100**. Downhole fluid sampling tool **100**, which may be built into the drill collars **222** may

5

gather measurements and fluid samples as described herein. One or more of the drill collars **222** may form a tool body **114**, which may be elongated as shown on FIG. **2**. Tool body **114** may be any suitable material, including without limitation titanium, stainless steel, alloys, plastic, combinations thereof, and the like. Downhole fluid sampling tool **100** may be similar in configuration and operation to downhole fluid sampling tool **100** shown on FIG. **1** except that FIG. **2** shows downhole fluid sampling tool **100** disposed on drill string **200**. Alternatively downhole fluid sampling tool **100** may be lowered into the wellbore after drilling operations on a wireline.

Downhole fluid sampling tool **100** may further include one or more sensors **116** for measuring properties of the fluid sample reservoir fluid, wellbore **104**, subterranean formation **106**, or the like. The one or more sensors **116** may be disposed within fluid analysis module **118**. In examples, more than one fluid analysis module may be disposed on drill string **200**. The properties of the fluid are measured as the fluid passes from the formation through downhole fluid sampling tool **100** and into either the wellbore or a sample container. As fluid is flushed in the near wellbore region by the mechanical pump, the fluid that passes through downhole fluid sampling tool **100** generally reduces in drilling fluid filtrate content, and generally increases in formation fluid content. The downhole fluid sampling tool **100** may be used to collect a fluid sample from subterranean formation **106** when the filtrate content has been determined to be sufficiently low. Sufficiently low depends on the purpose of sampling. For some laboratory testing below 10% drilling fluid contamination is sufficiently low, and for other testing below 1% drilling fluid filtrate contamination is sufficiently low. Sufficiently low may also depend on the rate of cleanup in a cost benefit analysis since longer pumpout times required to incrementally reduce the contamination levels may have prohibitively large costs. As previously described, the fluid sample may comprise a reservoir fluid, which may be contaminated with a drilling fluid or drilling fluid filtrate. Downhole fluid sampling tool **100** may obtain and separately store different fluid samples from subterranean formation **106** with fluid analysis module **118**. Fluid analysis module **118** may operate and function in the same manner as described above. However, storing of the fluid samples in the downhole fluid sampling tool **100** may be based on the determination of the fluid contamination. For example, if the fluid contamination exceeds a tolerance, then the fluid sample may not be stored. If the fluid contamination is within a tolerance, then the fluid sample may be stored in the downhole fluid sampling tool **100**. In examples, contamination may be defined within fluid analysis module **118**.

As previously described, information from downhole fluid sampling tool **100** may be transmitted to an information handling system **122**, which may be located at surface **112**. As illustrated, communication link **120** (which may be wired or wireless, for example) may be provided that may transmit data from downhole fluid sampling tool **100** to an information handling system **111** at surface **112**. Information handling system **140** may include a processing unit **124**, a monitor **126**, an input device **128** (e.g., keyboard, mouse, etc.), and/or computer media **130** (e.g., optical disks, magnetic disks) that may store code representative of the methods described herein. In addition to, or in place of processing at surface **112**, processing may occur downhole (e.g., fluid analysis module **118**). In examples, information handling system **122** may perform computations to estimate electro-magnetic properties of a fluid sample.

6

FIG. **3** illustrates an example information handling system **122** which may be employed to perform various steps, methods, and techniques disclosed herein. As illustrated, information handling system **122** includes a processing unit (CPU or processor) **302** and a system bus **304** that couples various system components including system memory **306** such as read only memory (ROM) **308** and random-access memory (RAM) **310** to processor **302**. Processors disclosed herein may all be forms of this processor **302**. Information handling system **122** may include a cache **312** of high-speed memory connected directly with, in close proximity to, or integrated as part of processor **302**. Information handling system **122** copies data from memory **306** and/or storage device **314** to cache **312** for quick access by processor **302**. In this way, cache **312** provides a performance boost that avoids processor **302** delays while waiting for data. These and other modules may control or be configured to control processor **302** to perform various operations or actions. Other system memory **306** may be available for use as well. Memory **306** may include multiple different types of memory with different performance characteristics. It may be appreciated that the disclosure may operate on information handling system **122** with more than one processor **302** or on a group or cluster of computing devices networked together to provide greater processing capability. Processor **302** may include any general purpose processor and a hardware module or software module, such as first module **316**, second module **318**, and third module **320** stored in storage device **314**, configured to control processor **302** as well as a special-purpose processor where software instructions are incorporated into processor **302**. Processor **302** may be a self-contained computing system, containing multiple cores or processors, a bus, memory controller, cache, etc. A multi-core processor may be symmetric or asymmetric. Processor **302** may include multiple processors, such as a system having multiple, physically separate processors in different sockets, or a system having multiple processor cores on a single physical chip. Similarly, processor **302** may include multiple distributed processors located in multiple separate computing devices but working together such as via a communications network. Multiple processors or processor cores may share resources such as memory **306** or cache **312** or may operate using independent resources. Processor **302** may include one or more state machines, an application specific integrated circuit (ASIC), or a programmable gate array (PGA) including a field PGA (FPGA).

Each individual component discussed above may be coupled to system bus **304**, which may connect each and every individual component to each other. System bus **304** may be any of several types of bus structures including a memory bus or memory controller, a peripheral bus, and a local bus using any of a variety of bus architectures. A basic input/output (BIOS) stored in ROM **308** or the like, may provide the basic routine that helps to transfer information between elements within information handling system **122**, such as during start-up. Information handling system **122** further includes storage devices **314** or computer-readable storage media such as a hard disk drive, a magnetic disk drive, an optical disk drive, tape drive, solid-state drive, RAM drive, removable storage devices, a redundant array of inexpensive disks (RAID), hybrid storage device, or the like. Storage device **314** may include software modules **316**, **318**, and **320** for controlling processor **302**. Information handling system **122** may include other hardware or software modules. Storage device **314** is connected to the system bus **304** by a drive interface. The drives and the associated computer-readable storage devices provide nonvolatile storage of

computer-readable instructions, data structures, program modules and other data for information handling system 122. In one aspect, a hardware module that performs a particular function includes the software component stored in a tangible computer-readable storage device in connection with the necessary hardware components, such as processor 302, system bus 304, and so forth, to carry out a particular function. In another aspect, the system may use a processor and computer-readable storage device to store instructions which, when executed by the processor, cause the processor to perform operations, a method or other specific actions. The basic components and appropriate variations may be modified depending on the type of device, such as whether information handling system 122 is a small, handheld computing device, a desktop computer, or a computer server. When processor 302 executes instructions to perform “operations”, processor 302 may perform the operations directly and/or facilitate, direct, or cooperate with another device or component to perform the operations.

As illustrated, information handling system 122 employs storage device 314, which may be a hard disk or other types of computer-readable storage devices which may store data that are accessible by a computer, such as magnetic cassettes, flash memory cards, digital versatile disks (DVDs), cartridges, random access memories (RAMs) 310, read only memory (ROM) 308, a cable containing a bit stream and the like, may also be used in the exemplary operating environment. Tangible computer-readable storage media, computer-readable storage devices, or computer-readable memory devices, expressly exclude media such as transitory waves, energy, carrier signals, electromagnetic waves, and signals per se.

To enable user interaction with information handling system 122, an input device 322 represents any number of input mechanisms, such as a microphone for speech, a touch-sensitive screen for gesture or graphical input, keyboard, mouse, motion input, speech and so forth. Additionally, input device 322 may take in data from one or more sensors 136, discussed above. An output device 324 may also be one or more of a number of output mechanisms known to those of skill in the art. In some instances, multimodal systems enable a user to provide multiple types of input to communicate with information handling system 122. Communications interface 326 generally governs and manages the user input and system output. There is no restriction on operating on any particular hardware arrangement and therefore the basic hardware depicted may easily be substituted for improved hardware or firmware arrangements as they are developed.

As illustrated, each individual component describe above is depicted and disclosed as individual functional blocks. The functions these blocks represent may be provided through the use of either shared or dedicated hardware, including, but not limited to, hardware capable of executing software and hardware, such as a processor 302, that is purpose-built to operate as an equivalent to software executing on a general purpose processor. For example, the functions of one or more processors presented in FIG. 3 may be provided by a single shared processor or multiple processors. (Use of the term “processor” should not be construed to refer exclusively to hardware capable of executing software.) Illustrative embodiments may include microprocessor and/or digital signal processor (DSP) hardware, read-only memory (ROM) 308 for storing software performing the operations described below, and random-access memory (RAM) 310 for storing results. Very large-scale integration

(VLSI) hardware embodiments, as well as custom VLSI circuitry in combination with a general-purpose DSP circuit, may also be provided.

The logical operations of the various methods, described below, are implemented as: (1) a sequence of computer implemented steps, operations, or procedures running on a programmable circuit within a general use computer, (2) a sequence of computer implemented steps, operations, or procedures running on a specific-use programmable circuit; and/or (3) interconnected machine modules or program engines within the programmable circuits. Information handling system 122 may practice all or part of the recited methods, may be a part of the recited systems, and/or may operate according to instructions in the recited tangible computer-readable storage devices. Such logical operations may be implemented as modules configured to control processor 302 to perform particular functions according to the programming of software modules 316, 318, and 320.

In examples, one or more parts of the example information handling system 122, up to and including the entire information handling system 122, may be virtualized. For example, a virtual processor may be a software object that executes according to a particular instruction set, even when a physical processor of the same type as the virtual processor is unavailable. A virtualization layer or a virtual “host” may enable virtualized components of one or more different computing devices or device types by translating virtualized operations to actual operations. Ultimately however, virtualized hardware of every type is implemented or executed by some underlying physical hardware. Thus, a virtualization compute layer may operate on top of a physical compute layer. The virtualization compute layer may include one or more virtual machines, an overlay network, a hypervisor, virtual switching, and any other virtualization application.

FIG. 4 illustrates an example information handling system 122 having a chipset architecture that may be used in executing the described method and generating and displaying a graphical user interface (GUI). Information handling system 122 is an example of computer hardware, software, and firmware that may be used to implement the disclosed technology. Information handling system 122 may include a processor 302, representative of any number of physically and/or logically distinct resources capable of executing software, firmware, and hardware configured to perform identified computations. Processor 302 may communicate with a chipset 400 that may control input to and output from processor 302. In this example, chipset 400 outputs information to output device 324, such as a display, and may read and write information to storage device 314, which may include, for example, magnetic media, and solid-state media. Chipset 400 may also read data from and write data to RAM 310. A bridge 402 for interfacing with a variety of user interface components 404 may be provided for interfacing with chipset 400. Such user interface components 404 may include a keyboard, a microphone, touch detection and processing circuitry, a pointing device, such as a mouse, and so on. In general, inputs to information handling system 122 may come from any of a variety of sources, machine generated and/or human generated.

Chipset 400 may also interface with one or more communication interfaces 326 that may have different physical interfaces. Such communication interfaces may include interfaces for wired and wireless local area networks, for broadband wireless networks, as well as personal area networks. Some applications of the methods for generating, displaying, and using the GUI disclosed herein may include receiving ordered datasets over the physical interface or be

generated by the machine itself by processor **302** analyzing data stored in storage device **314** or RAM **310**. Further, information handling system **122** receive inputs from a user via user interface components **404** and execute appropriate functions, such as browsing functions by interpreting these inputs using processor **302**.

In examples, information handling system **122** may also include tangible and/or non-transitory computer-readable storage devices for carrying or having computer-executable instructions or data structures stored thereon. Such tangible computer-readable storage devices may be any available device that may be accessed by a general purpose or special purpose computer, including the functional design of any special purpose processor as described above. By way of example, and not limitation, such tangible computer-readable devices may include RAM, ROM, EEPROM, CD-ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other device which may be used to carry or store desired program code in the form of computer-executable instructions, data structures, or processor chip design. When information or instructions are provided via a network, or another communications connection (either hardwired, wireless, or combination thereof), to a computer, the computer properly views the connection as a computer-readable medium. Thus, any such connection is properly termed a computer-readable medium. Combinations of the above should also be included within the scope of the computer-readable storage devices.

Computer-executable instructions include, for example, instructions and data which cause a general-purpose computer, special purpose computer, or special purpose processing device to perform a certain function or group of functions. Computer-executable instructions also include program modules that are executed by computers in stand-alone or network environments. Generally, program modules include routines, programs, components, data structures, objects, and the functions inherent in the design of special-purpose processors, etc. that perform particular tasks or implement particular abstract data types. Computer-executable instructions, associated data structures, and program modules represent examples of the program code means for executing steps of the methods disclosed herein. The particular sequence of such executable instructions or associated data structures represents examples of corresponding acts for implementing the functions described in such steps.

In additional examples, methods may be practiced in network computing environments with many types of computer system configurations, including personal computers, hand-held devices, multi-processor systems, microprocessor-based or programmable consumer electronics, network PCs, minicomputers, mainframe computers, and the like. Examples may also be practiced in distributed computing environments where tasks are performed by local and remote processing devices that are linked (either by hardwired links, wireless links, or by a combination thereof) through a communications network. In a distributed computing environment, program modules may be located in both local and remote memory storage devices.

FIG. **5** illustrates an example of one arrangement of resources in a computing network **500** that may employ the processes and techniques described herein, although many others are of course possible. As noted above, an information handling system **122**, as part of their function, may utilize data, which includes files, directories, metadata (e.g., access control list (ACLS) creation/edit dates associated with the data, etc.), and other data objects. The data on the

information handling system **122** is typically a primary copy (e.g., a production copy). During a copy, backup, archive or other storage operation, information handling system **122** may send a copy of some data objects (or some components thereof) to a secondary storage computing device **504** by utilizing one or more data agents **502**.

A data agent **502** may be a desktop application, website application, or any software-based application that is run on information handling system **122**. As illustrated, information handling system **122** may be disposed at any rig site (e.g., referring to FIG. **1**) or repair and manufacturing center. Data agent **502** may communicate with a secondary storage computing device **504** using communication protocol **508** in a wired or wireless system. Communication protocol **508** may function and operate as an input to a website application. In the website application, field data related to pre- and post-operations, generated DTCs, notes, and the like may be uploaded. Additionally, information handling system **122** may utilize communication protocol **508** to access processed measurements, operations with similar DTCs, troubleshooting findings, historical run data, and/or the like. This information is accessed from secondary storage computing device **504** by data agent **502**, which is loaded on information handling system **122**.

Secondary storage computing device **504** may operate and function to create secondary copies of primary data objects (or some components thereof) in various cloud storage sites (**506A-N**). Additionally, secondary storage computing device **504** may run determinative algorithms on data uploaded from one or more information handling systems **138**, discussed further below. Communications between the secondary storage computing devices **504** and cloud storage sites **506A-N** may utilize REST protocols (Representational state transfer interfaces) that satisfy basic C/R/U/D semantics (Create/Read/Update/Delete semantics), or other hypertext transfer protocol ("HTTP")-based or file-transfer protocol ("FTP")-based protocols (e.g., Simple Object Access Protocol).

In conjunction with creating secondary copies in cloud storage sites **506A-N**, the secondary storage computing device **504** may also perform local content indexing and/or local object-level, sub-object-level or block-level deduplication when performing storage operations involving various cloud storage sites **506A-N**. Cloud storage sites **506A-N** may further record and maintain DTC code logs for each downhole operation or run, map DTC codes, store repair and maintenance data, store operational data, and/or provide outputs from determinative algorithms that are run at cloud storage sites **506A-N**. In examples, computing network **500** may be communicatively coupled to downhole fluid sampling tool **100**.

FIG. **6** illustrates a schematic of downhole fluid sampling tool **100**. As illustrated, downhole fluid sampling tool **100** may comprise probe **604**. Probe **604** may extract fluid from the reservoir and deliver it to a flowline **606** that extends from one end of downhole fluid sampling tool **100** to the other. Without limitation, probe **604** includes two probes **618**, **620** which may extend from downhole fluid sampling tool **100** and press against the inner wall of wellbore **104** (e.g., referring to FIG. **1**). Probe channels **622**, **624** may connect probes **618**, **620** to flowline **606**. The high-volume bidirectional pump **612** may be used to pump fluids from the reservoir, through probe channels **622**, **624** and to flowline **606**. Alternatively, a low volume pump **626** may be used for this purpose. Two standoffs or stabilizers **628**, **630** hold downhole fluid sampling tool **100** in place as probes **618**, **620** press against the wall of wellbore **104**. In examples,

11

probes **618**, **620** and stabilizers **628**, **630** may be retracted when downhole fluid sampling tool **100** may be in motion and probes **618**, **620** and stabilizers **628**, **630** may be extended to sample the reservoir fluids at any suitable location in wellbore **104**.

In examples, flowline **606** may be connected to other tools disposed on drill string **200** or conveyance **102** (e.g., referring to FIGS. **1** and **2**). Additionally, downhole fluid sampling tool **100** may include a flow-control pump-out section **610**, which may include a high-volume bidirectional pump **612** for pumping fluid through flowline **606**. In examples, downhole fluid sampling tool **100** may include two multi-chamber sections **614**, **616**, referred to collectively as multi-chamber sections **614**, **616** or individually as first multi-chamber section **614** and second multi-chamber section **616**, respectively.

In examples, multi-chamber sections **614**, **616** may be separated from flow-control pump-out section **610** by sensor section **632**, which may house one or more sensors **634**. Sensor **634** may be displaced within sensor section **632** in-line with flowline **606** to be a "flow through" sensor. In alternate examples, sensor **634** may be connected to flowline **606** via an offshoot of flowline **606**. Without limitation, sensor **634** may include optical sensors, acoustic sensors, electromagnetic sensors, conductivity sensors, resistivity sensors, selective electrodes, density sensors, mass sensors, thermal sensors, chromatography sensors, viscosity sensors, bubble point sensors, fluid compressibility sensors, flow rate sensors, microfluidic sensors, selective electrodes such as ion selective electrodes, and/or combinations thereof. In examples, sensor **634** may operate and/or function to measure drilling fluid filtrate.

Additionally, multi-chamber section **614**, **616** may comprise access channel **636** and chamber access channel **638**. Without limitation, access channel **636** and chamber access channel **638** may operate and function to either allow a solids-containing fluid (e.g., mud) disposed in wellbore **104** in or provide a path for removing fluid from downhole fluid sampling tool **100** into wellbore **104**. As illustrated, multi-chamber section **614**, **616** may comprise a plurality of chambers **640**. Chambers **640** may be sampling chamber that may be used to sample wellbore fluids, reservoir fluids, and/or the like during measurement operations. It should be noted that downhole fluid sampling tool **100** may also be used in pressure testing operations.

For example, during pressure testing operations, probes **618**, **620** may be pressed against the inner wall of wellbore **104** (e.g., referring to FIG. **1**). Pressure may increase at probes **618**, **620** due to formation **106** (e.g., referring to FIG. **1** or **2**) exerting pressure on probes **618**, **620**. As pressure rises and reaches a predetermined pressure, valves **642** opens so as to close equalizer valve **644**, thereby isolating fluid passageway **646** from the annulus **218**. In this manner, valve **642** ensures that equalizer valve **644** closes only after probes **618**, **620** has entered contact with mudcake (not illustrated) that is disposed against the inner wall of wellbore **104**. In examples, as probes **618**, **620** are pressed against the inner wall of wellbore **104**, the pressure rises and closes the equalizer valve in fluid passageway **646**, thereby isolating the fluid passageway **646** from the annulus **218**. In this manner, the equalizer valve in fluid passageway **646** may close before probes **618**, **620** may have entered contact with the mudcake that lines the inner wall of wellbore **104**. Fluid passageway **646**, now closed to annulus **218** (e.g., referring to FIG. **2**), is in fluid communication with low volume pump **626**.

12

As low volume pump **626** is actuated, formation fluid may thus be drawn through probe channels **622**, **624** and probes **618**, **620**. The movement of low volume pump **626** lowers the pressure in fluid passageway **646** to a pressure below the formation pressure, such that formation fluid is drawn through probe channels **622**, **624** and probes **618**, **620** and into fluid passageway **646**. The pressure of the formation fluid may be measured in fluid passageway **646** while probes **618**, **620** serves as a seal to prevent annular fluids from entering fluid passageway **646** and invalidating the formation pressure measurement.

With low volume pump **626** in its fully retracted position and formation fluid drawn into fluid passageway **646**, the pressure will stabilize and enable pressure transducers **648** to sense and measure formation fluid pressure. The measured pressure is transmitted to information handling system **122** disposed on downhole fluid sampling tool **100** and/or it may be transmitted to the surface via mud pulse telemetry or by any other conventional telemetry means to an information handling system **122** disposed on surface **112**. Additionally, flowline **606** may pass through fluid analysis module **118** which may comprise at least one resonator antenna **160**. In examples, fluid analysis module **118** may be disposed at any location within downhole sampling tool **100**. Additionally, one or more fluid analysis module **118** with at least one resonator antenna **160** to perform resistivity analysis on fluid within flowline **606**. However, further implementations to measure fluid within flowline **606** may be performed.

For example, FIG. **7A** illustrates an electrode system **700** to measure resistivity in flowline **606**. In electrode system **700**, current may be transmitted through transmitter electrode **702** and returned to return electrode **704**. As such, current may travel through the fluid inside flowline **606**. Herein, fluid inside flowline **606** may contain material of any phase but is strictly referred to as fluid inside flowline **606**. Electrode system **700** may operate with a DC Voltage Source **706**. The potential drop between transmitter electrode **702** and the return electrode **704** may be a measure of the resistivity of this material in such static conditions. In examples, if the fluid is not homogeneous (i.e., single-phase), the resulting measurement may be representative of the average resistivity of the fluid. Additionally, although the term fluid is commonly used in practice, material flowing through the flowline may include gas or solid components. In examples where an alternating current is applied between transmitter electrode **702** and return electrode **704**, a complex impedance may be measured where the measurement is influenced by the permittivity of the material (to be discussed below). However, in quasi-static conditions where the frequency is low (for example, less than 100 kHz), imaginary part of the measured impedance and effect of the permittivity may be ignored.

Electrode system **700** may operate on Galvanic principles and requires a physical contact between both transmitter and return electrodes **702** and **704** to the fluid inside flowline **606**. Thus, electrode system **700** may be invasive for both transmitter and return electrodes **702** and **704**. As such, corrosion on transmitter and return electrodes **702** and **704** may occur since they are directly exposed to the fluid inside flowline **606**. Further, electrode system **700** may also require a flowline **606** to be non-conductive such that current will not be short-circuited through the outer surface of flowline **606**. If the fluid inside flowline **606** is non-conductive, current will not readily flow thus the primary applications of such a sensor system in oil-field applications is to measure the salinity of the formation water. In a similar design, a pair

of capacitor plates may be used to determine the capacitance of the fluid inside flowline 606. As with the electrode sensors shown in FIG. 7A, if the fluid is not homogeneous and include multiple phases, measurement will represent the average capacitance of the fluid. Setup for the capacitance sensors may be the same as the one shown in **Error! Reference source not found.** FIG. 7A for the electrode sensors. The fluid in this case should have low conductivity; otherwise, a conduction current may occur, and no charge will accumulate on the capacitor plates. In addition to electrodes measuring the properties of fluid within flowline 606, coil antennas may be used as well.

FIG. 7B illustrates coil antenna system 710, a low-frequency AC current source 716 may be passed through a transmitting coil antenna 712. The frequency of the AC current source may range between 1 kHz to 1 MHz. Current within transmitting coil antenna 712 forms a magnetic field in the direction perpendicular to the plane of transmitting coil antenna 712. The alternating magnetic field creates an induced electric field inside the flowline 606. This induced electric field in turn creates a secondary magnetic field at receiving coil antenna 714. The secondary magnetic field may be measured by receiving coil antenna 714. The secondary magnetic field measured by receiving coil antenna 714 may be in proportion to the conductivities within the volume of investigation of the tool. Since the volume of investigation is not restricted to the inside of the flowline, this type of sensors will be more sensitive to conductive fluids (that is, in a given environment, more conductive the fluid, more of the measured signal would be coming from the fluid); thus, they are primarily used to measure the salinity of the formation water as well and they may not operate in conducting or magnetic flowlines. In addition to electrode and coil systems, waveguide flowline sensors may be implemented.

FIG. 7C illustrates waveguide flowline sensor 720. Waveguide flowline sensor 720 may measure fluid conductivity and permittivity. Thus, it may be used to determine the components of the fluid (e.g., oil/water ratio.) In examples, waveguide flowline sensor 720 may operate at 100 MHz. Waveguide flowline sensor 720 may comprise a coaxial conductor input 722 and a coaxial conductor output 724. Coaxial conductor input 722 may serve as a connection between waveguide flowline sensor 720 and conductor input 722. Similarly, coaxial conductor output 724 may serve as a connection between waveguide flowline sensor 720 and coaxial conductor output 724. Both the coaxial conductor input 724 and the coaxial conductor input are connected a central conductor 726 within the walls of the flowline cavity 728. As a result, central conductor 726 and the walls of the flowline cavity 728 forms a waveguide. The characteristic impedance of the waveguide is changed with the electrical properties of the fluid flowing through the flowline which enables the determination of such properties. Waveguide flowline sensor 720 may require a purpose-built flowline cavity 728 with central conductor 726. As such, waveguide flowline sensor 720 may not be adapted to work with existing flowlines. As previously discussed, multiple materials (i.e., multiphase flow) may flow through flowline 606 at the same time. For example, water, oil and gas may flow through flowline 606. In multiphase flow, measurements from waveguide flowline sensor 720, coil antenna system 710 (e.g., referring to FIG. 7B), and electrode system 700 (e.g., referring to FIG. 7A) may correspond to the average properties of the materials flowing through the flowline. Therefore, tomography may be applied to measure inconsistent fluid within flowline 606.

FIG. 7D illustrates electrical impedance tomography system 730. One or more electrodes 732 may be displaced around the inner circumference of flowline 606. Each electrode of the one or more electrodes 732 may operate as a transmitter or receiver electrode. Any number of electrodes operate as a transmitter or receiver electrode, with the exception that at least one electrode must be a transmitter and one electrode must be a receiver. A static (DC) or quasi-static (with frequencies less than 100 kHz) current may be injected into transmitter electrodes, and the potential difference between different transmitter-receiver electrode pairs may then be measured. Such measurements may then be converted into conductivity and permittivity images, to be discussed in detail below. Additionally, capacitive plates may be placed along the circumference of the flowline instead of one or more electrodes 732. In such examples, measuring the capacitance between different plates and processing the data, a cross-sectional image of the dielectric permittivity of the material flowing through the flowline may be measured. Conductivity values for materials with low inherent conductivity (i.e., insulators) may also be measured. In further examples, capacitor plates/electrodes are replaced by induction coils. As previously described in coil antenna system 710 (e.g., referring to FIG. 7B) when a coil in the transmitter mode is fired up by passing current through it, a magnetic field is created which induces an electric field. This electric field induces a secondary magnetic field inside a coil in the receiving mode. Thus, the inductance between these two coils may be measured. These measurements may then be repeated for all the remaining coil pairs and converted into conductivity and permeability images. All measurement techniques described in FIGS. 7A-7D may alternatively be replaced with a resonator antenna 160 (e.g., referring to FIG. 6) to be discussed in detail below.

FIG. 8A illustrates resonator antenna 160 configured as a microstrip patch antenna 800. In examples, resonator antenna 160 may operate between 10 MHz to 300 GHz. These high frequencies may be more suitable for imaging applications in oil-based mud environments. However, operation in water-based mud environments may also be possible. As illustrated, a microstrip patch antenna 800 may comprise a metallic ground plane 802, a dielectric substrate 804, and a conductive patch 806 on top of dielectric substrate 804. Therefore, microstrip patch antenna 800 may not be invasive within flowline 606 and as such does not experience coating, in contrast to systems and techniques described above in FIGS. 7A-7D. A reflectometry measurement may be made with microstrip patch antenna 800 by measuring one or more S-parameters (for example, S₁₁ is the reflection coefficient of the signal at the feeding port) for different formations. S-parameters is an acronym for scattering parameters and S_{ij} denote the ratio of the reflected power wave at port i to incident power wave at port j of a circuit while all the ports other than port j are terminated in matched loads. As microstrip patch antenna constitutes a dielectric cavity, they may resonate at a specific frequency (i.e., resonance frequency).

Resonance frequency of microstrip patch antenna 800 is a function of its geometry and the materials forming microstrip patch antenna 800. Resonance frequency is inversely proportional to the size of microstrip patch antenna 800 and the dielectric constant of dielectric substrate 804. Other parameters of the antenna geometry or the properties of the materials, such as the magnetic permeability of dielectric substrate 804, may also be modified in some implementations. Thus, the resonance frequency of a

15

microstrip patch antenna **800** may change by changing one or more properties of microstrip patch antenna **800**. Properties may comprise, but are not limited to, a permittivity of the substrate, a permeability of the substrate, a width, a length, and/or a thickness. The magnitude and phase of the reflection coefficient at the feeding port (referred to as S11 parameter) may be affected by the properties of the formation that the electromagnetic waves are being transmitted. As a result, measured S-parameters also vary with the electrical properties of the fluid. Thus, measured S-parameters may be used to estimate the electrical properties of the fluid through techniques such as inversion as discussed below.

In examples, slots (not illustrated) may be cut on conductive patch **806** to facilitate the transmission of electromagnetic waves into the surrounding formation. Multiple slots may be present on conductive patch **806**, which may change the operational characteristics of microstrip patch antenna **800**. If there are multiple slots, the effective measurement point of microstrip patch antenna **800** may be considered to be the geometric center of the slots. A geometric center is a location after averaging out the position of each slot. However, since characteristics of the formation (and the borehole) immediately in front of each slot may be different, this is only an approximation.

Microstrip patch antenna **800** may be connected to information handling system **122** (e.g., referring to FIG. 1) by microstrip lines, coaxial probes, aperture coupling or proximity coupling. Additionally, photoetching may be used for implementing patch and the feed lines on dielectric substrate **804**. A dielectric substrate **804** may be polyvinyl chloride (PVC), High-density polyethylene (HDPE), acrylonitrile butadiene styrene (ABS), polyetheretherketone (PEEK), or ceramic materials such as vitrified clay. While FIG. 8A illustrates resonator antenna **160** as a microstrip patch antenna **800**, resonator antennas **160** may be other antennas.

FIG. 8B illustrates resonator antenna **160** configured as a cavity resonator **820**. As illustrated, cavity resonator **820** may comprise one or more conducting walls **822** with one or more slots **824**. Slots are openings in the conducting wall that provides a path between the outside of the cavity resonator **820** and its inside. As illustrated, conducting walls **822** may further comprise a hole or iris **808**, which may feed (i.e., provide power to) cavity resonator **820** and radiating the electromagnetic energy. Cavity resonator **820** may also be referred to as cavity-backed slots. In the cavity-backed slot design, slots **824** may be the only openings on conducting walls **822** surrounding cavity resonator **820**. As a result, radiation from cavity resonator **820** may occur and/or originate from each slot **824**. Cavity resonator **820** may have a high Q-factor. Q-factor (also referred to as the quality factor) is a measure of the ratio of the energy stored to energy lost in a resonant device and a higher Q-factor represents lower losses. Therefore, cavity resonator **820**, may not be invasive within flowline **606** and as such does not experience coating, in contrast to systems and techniques that utilize electrode sensors as described above in FIGS. 7A and 7D. In the example of resonator antenna **160** in direct contact with the fluid and is subject to coating, the resulting effect on performance is negligible since the resonator antenna **160** do not require a direct conduction path as needed for the electrode sensors working based on Galvanic principles. Furthermore, resonator antennas **160** do not require non-conductive or non-magnetic flowlines in contrast to systems and techniques described above in FIG. 7B utilizing coil sensors or purpose built flowlines in contrast to systems and techniques described above in FIG. 7C utilizing waveguide

16

flowline sensor. As with the microstrip patch antenna, as the dimensions of cavity resonator **820** and the dielectric constant of the material filling the inner cavity of cavity resonator **820**) and slots **824** increases, the resonance frequency decreases. Thus, the resonance frequency of cavity resonator **820** may change by changing one or more properties of cavity resonator **820**. Properties may comprise, but are not limited to, a permittivity of the substrate, a permeability of the substrate, a width, a length, and/or a thickness. Such a resonator may also be fed through a feeding port or a waveguide **810** connected to a hole or iris **808** on the wall of slot **824**. Filling slots **824** with different material of different dielectric constants may allow for cavity resonator **820** to resonate at different frequencies. Cavity resonator **820** may be connected to information handling system **122** by microstrip lines, coaxial probes, aperture coupling or proximity coupling. Both microstrip patch antenna **800** and cavity resonator **820** are implementations of resonator antenna **160** and may be used on downhole fluid sampling tool **100** in downhole operations to take one or more measurements of a fluid moving through flowline **606** (e.g., referring to FIG. 6).

FIG. 9 illustrates fluid analysis module **118** that comprises a resonator antenna **160** disposed along an outer surface **902** of flowline **606**. As depicted in FIG. 9, resonator antenna **160** may be a cavity resonator **820** (e.g., referring to FIG. 8) as described above. An electrical connection **904** may deliver power and/or commands from information handling system **122** to resonator antenna **160**. Herein, a flowline **606** may be connected to resonator antenna **160** via coaxial cables. As such, resonator antenna **160** may comprise a slot **906** disposed on an exterior surface **908** of resonator antenna **160**. In examples, slot **906** may match with a slot cut **912** on outer surface **902** of flowline **606**. Slot **906** and cut slot **912** may be filled with a dielectric material to ensure the sealing of fluid **910** inside flowline **606**. A dielectric material as previously described, may be polyvinyl chloride (PVC), High-density polyethylene (HDPE), acrylonitrile butadiene styrene (ABS), polyetheretherketone (PEEK), or ceramic materials such as vitrified clay. In examples, flowline **606** may be formed from nonconducting material. Thus, a slot cut **912** may not be utilized on outer surface **902** of flowline **606** as nonconducting material may allow for transmission of electromagnetic waves through flowline **606**. Therefore, resonator antenna **160** may not be invasive within flowline **606** and as such does not experience coating, in contrast to systems and techniques described above in FIGS. 7A and 7D utilizing electrode sensors. Furthermore, they do not require non-conductive or non-magnetic flowlines in contrast to systems and techniques described above in FIG. 7B utilizing coil sensors or purpose-built flowlines in contrast to systems and techniques described above in FIG. 7C utilizing waveguide flowline sensor.

During measurement operations, resonator antenna **160** may transmit an electromagnetic (EM) wave into flowline **606** and receive a reflected EM wave from flowline **606**. With the transmitted EM wave and the reflected EM wave, resonator antenna **160** may calculate a S11 parameter of fluid **910** inside flowline **606**. Herein, S11 parameter is calculated as the ratio of the reflected power wave from the 1st port to an incident power wave at the 1st port. Thus, S11 measures the reflection of transmitted power back to the antenna. From a calculated S11 parameter, fluid properties may be estimated. For example, S11 parameter is a function of the reflection coefficient of the fluid, which in turn depends on electrical properties of the fluid such as the

dielectric permittivity, conductivity and permeability. In examples, resonator antenna **160** may be disposed within fluid analysis module **118** in any suitable configuration for measurement operations.

FIG. **10** illustrates fluid analysis module **118** that comprises a resonator antenna **160** disposed between outer surface **902** and inner surface **1000** of flowline **606**. If the material filling the volume between the inner surface **1000** and the outer surface **902** of flowline **606** is conductive, resonator antenna **160** may be disposed within indent **1002**. If the material filling the volume between the inner surface **1000** and the outer surface **902** of flowline **606** is nonconductive, indent **1002** may be carved out and covered with conducting material except for slot **906**, which may enable transmission of electromagnetic (EM) waves (i.e., radiation) into flowline **606**. Slot **906** may be covered with a dielectric material to prevent fluid **910** from entering indent **1002**. Therefore, resonator antenna **160** may not be invasive within flowline **606** and as such does not experience coating, in contrast to systems and techniques described above in FIGS. **7A** and **7D**. An electrical connection **904** may deliver power and/or commands from information handling system **122** to resonator antenna **160**. The S11 parameter may be measured and used to determine the properties of fluid **910** inside flowline **606**, as previously described. It should be noted that S11 parameters are discussed above, other properties and/or parameters may also be measured.

During measurement operations a complex permittivity of fluid **910** from one or more S-parameter measurements may be formed. This process may be based on a numerical forward model of resonator antenna **160** inside flowline **606**, which is created and processed on information handling system **122** (e.g., referring to FIG. **1**). Numerical forward models implemented herein may be Finite Difference Time Domain (FDTD), FEM (Finite Element Method) and MoM (Method of Moments). However additional numerical forward models may be used. S-parameter measurements taken by resonator antenna **160** may be compared with the response of the forward model for different fluid properties to determine the property whose response best matches the actual measurements. The responses of the forward model may have been computed beforehand and stored in a library. A response that produces the lowest misfit (in the least squares sense) to the actual response among the responses in the library may be selected. In other examples, an iterative inversion algorithm may be used to determine complex permittivity of fluid **910**. An iterative inversion algorithm may run the numerical forward model at each step or may use precomputed responses (i.e., an interpolation may be employed to determine the responses for points that do not exactly lie within the precomputed library).

Software packages run on information handling system **122** perform optimization/inversion tasks are commonly available in programming languages used in scientific computation. The goal of the inversion may be to minimize a misfit function as illustrated in Equation (1):

$$\arg\min_{\bar{X}} \|\bar{S}^{Meas} - \bar{S}^{Model}(\bar{X})\| \quad (1)$$

In Equation (1), $\bar{S}^{Meas}$ denotes the measurements from resonator antenna **160** while $\bar{S}^{Model}$ denotes the modelling outputs. $\bar{X}$ is the parameters of the numerical forward model (i.e., formation parameters that are desired to be found.) Overbars indicate these quantities may be vectors or matrices, which may also be represented as vectors after a

flattening operation. In examples, additional regularization terms may be added to utilize priori information to ensure smoothness of results. Generally, Equation (1) may be utilized for a single resonator antenna **160**. Additionally, there may be multiple resonance frequencies (or a band of frequencies) of a single resonator antenna **160**. However, it may not be feasible to tune multiple frequencies from a single resonator antenna **160**. Therefore, multiple nested resonator antennas **160** may be utilized to perform multi frequency measurements.

FIGS. **11A-11C** illustrate fluid analysis module **118** that comprise a plurality of resonator antennas **160** disposed along outer surface **902** of flowline **606** or between outer surface **902** and inner surface **1000** of flowline **606**. As depicted in FIGS. **11A-11C**, resonator antennas **160** may be cavity resonators **820** (e.g., referring to FIG. **8A**). In order to make multi frequency measurements at substantially similar locations at different frequencies, several different arrangements may be created. For FIGS. **11A-11C**, the face of resonator antennas **160** are shown to be circular, but they may be any other shape, such as an ellipse, rectangle or a square. Similarly, although they are shown to be concentric, their centers may not coincide. Additionally, there may be a plurality of resonator antennas **160** in proximity to one another but not nested. The resonance frequency of resonator antennas **160** may be inversely proportional to their physical sizes. Thus, smallest resonator antenna **1102** (innermost cavity) may resonate at a higher frequency f_H , second largest resonator antenna **1104** may resonate at a middle frequency f_M , and largest resonator antenna **1106** may resonate at a lower frequency f_L . Slot **906** may be opened on each resonator antenna **160** to enable the radiation of the electromagnetic waves, as discussed above. Slot **906** of each resonator antenna **160** may be located at the same axial position. Slot **906** may be located close to each other, and the measurements may be assumed to be performed at the same azimuthal position for different frequencies. There may be multiple such nested antenna structures on flowline **606**. Although there are three groups of resonator antennas **160** (operating at three different frequencies) in this example, there may be any number of nested resonator antennas **160** in other implementations which may enable measurements at different number of frequencies.

An implementation of slots **906** on the same azimuthal position is depicted in FIG. **11A**. In this alignment, there exist three resonator antenna **160** aligned perpendicular to flowline **606**. FIG. **11B** illustrates another alignment of slots **906** for resonator antennas **160** that are aligned parallel to flowline **606**. Similar to FIG. **11A**, slots **906** of each nested resonator antenna **160** arrangement may be located at close proximity to each other and may be assumed to be at the same axial position during processing. Measurements from one or more slots **906** are interpolated and aligned to the same depth. FIG. **11A** illustrates slots **1108** aligned in a horizontal direction. FIG. **11B** illustrates slots **1108** aligned in the vertical direction. In these alignments of slots **906** for FIG. **11A** and FIG. **11B**, only a single slot **1108** has been depicted for each resonator antenna **160**. It may be possible to have multiple slots **1108** in other arrangement schemes. For example, FIG. **11C** illustrates largest resonator antenna **1106** and second largest resonator antenna **1104** each having four slots **1108**.

Slots **1108** may be arranged in a symmetric manner such that their geometric center (e.g., the average of the positions of slots **1108**) lies on the same location as a single slot **1112** located in smallest resonator antenna **1102**. As a result, the measurement point of four outer sensors **1114** may be the

same as smallest resonator antenna 1102. However, the separation between one or more single slots 1112 and two outer sensors 1114 in this example may decrease the resolution of measurements taken during measurement operations. Measurements taken by resonator antennas 160 may provide S11 parameters for smallest resonator antenna 1102, second largest resonator antenna 1104, and largest resonator antenna 1106. As previously described, implementations of cavity resonators 820 (e.g., referring to FIG. 8B) configured as resonator antenna 160 may measure S11 parameters of fluid 910 inside flowline 606. In examples, smallest resonator antenna 1102 (innermost cavity) may resonate at a higher frequency f_H , second largest resonator antenna 1104 may resonate at a middle frequency f_M , and largest resonator antenna 1106 may resonate at a lower frequency f_L . Resonator antennas may be performed to measure nested S21 parameters, to be discussed below.

FIG. 12A illustrates fluid analysis module 118 that comprises a resonator antenna 160 configured to be a microstrip patch antenna 800 (e.g., referring to FIG. 8A) disposed along an outer surface 902 of flowline 606. As depicted in FIG. 12A, resonator antenna 160 may be a microstrip patch antenna, as described above. An electrical connection 904 may deliver power and/or commands from information handling system 122 (e.g., referring to FIG. 1) to resonator antenna 160. As such, resonator antenna 160 may comprise a slot 906 on its outside may be matched with a slot cut 912 on the outer surface of flowline 606, similar to a cavity resonator. Slot 906 and slot cut 912 may be filled with dielectric material, as described above to ensure the sealing of the fluid inside flowline 606. In examples, if flowline 606 is formed out of nonconducting material, there may not be a need a slot cut 912 on the outer surface of flowline 606 since nonconducting material may allow the transmission of the electromagnetic waves. Additionally, resonator antenna 160 may comprise conducting vias 1200 to reduce the radiation loss from microstrip patch antenna 800 (e.g., referring to FIG. 8A). Resonator antenna 160 may transmit an electromagnetic (EM) wave into flowline 606 and receive a reflected EM wave from flowline 606. With the transmitted EM wave and the reflected EM wave, resonator antenna 160 may calculate the S11 parameter of fluid 910 inside flowline 606. In FIG. 12A, a microstrip patch antenna 800 (e.g., referring to FIG. 8B) is disposed on the outside of flowline 606. However, further embodiments may also include a microstrip patch antenna 800 disposed within flowline 606. Microstrip patch antenna may also be located in between the outer surface and the inner surface of the flowline. As previously depicted for cavity resonators, an indent may be cut within the flowline wall in the location of the antenna. In the case of a non-conducting flowline, conducting vias may again be used to improve the radiation efficiency of this design.

FIG. 12B illustrates fluid analysis module 118 that comprises a resonator antenna 160 disposed within flowline 606. As depicted in FIG. 12B, resonator antenna 160 may be a microstrip patch antenna 800 (e.g., referring to FIG. 8A). In examples, fluids may pass through the resonator antenna 160. Thus, the fluid may act as the substrate of microstrip patch antenna 800. Thus, properties of the fluid may affect the radiation characteristics (and thus, the S parameters) of resonator antenna 160. This quantity may be measured and processed to determine electrical properties of the fluid. Additionally, conducting vias 1200 may form a measurement volume 1204. In other implementations, resonator antenna may be a cavity resonator. Cavity resonators may impede the fluid flow more than a microstrip patch antenna.

Aligning at least two of the slots with the direction of the fluid flow may alleviate this issue to an extent. Resonator antenna 160 disposed within flowline 606 may transmit an electromagnetic (EM) wave into measurement volume 1204 and receive a reflected EM wave from measurement volume 1204. With the transmitted EM wave and the reflected EM wave, resonator antenna may calculate an S11 parameter within measurement volume 1204. Although resonator antenna designs depicted in FIG. 12A and FIG. 12B are invasive and thus may be subject to coating, the effect on the performance of the antenna may be minimal since the resonator antennas do not require a direct conduction path unlike system and techniques shown in FIG. 7A and FIG. 7D utilizing electrode sensors. Furthermore, they do not require non-conductive or non-magnetic flowlines in contrast to systems and techniques described above in FIG. 7B utilizing coil sensors or purpose-built flowlines in contrast to systems and techniques described above in FIG. 7C utilizing waveguide flowline sensor. Methods and systems discussed above may calculate an S11 parameter of the resonator antenna that varies with the fluid 910 properties inside flowline 606. Additionally, methods and systems may solve for multi-phase tomography with S11 parameters.

Fluid inside flowline 606 may comprise multiple phases. Specifically, one or more fluids and gases may flow through the flowline 606 at the same time. As previously described multiple nested resonator antennas 160 implementation may transmit multiple frequencies. Measurements taken by one or more resonator antennas 160 may be used to identify different components from each other. However, calculations may be based on assumptions about the distribution of the components inside flowline 606. Therefore, resolving multiphase flow may be based on tomography. A tomography technique that utilizes resonator antennas 160 may be resistant to corrosion, operate with both conductive and nonconductive flowlines, and be low profile and easy to manufacture.

Tomography techniques may use resonator antennas 160 configured as microstrip patch antennas 800 (e.g., referring to FIG. 8A) and cavity resonator (e.g., referring to FIG. 8B). FIG. 13A illustrates resonator antennas 160 as cavity resonators 820 located outside flowline 606. Similarity, FIG. 13B illustrates resonator antennas 160 as microstrip patch antennas 800 disposed outside flowline 606. FIG. 13C illustrates cavity resonators 820 disposed inside the outer surface 902 of flowline 606 (e.g., referring to FIG. 8). Although a total of eight resonator antennas 160 have been illustrated in FIGS. 13A-13C, the actual number of resonator antennas 160 may be less or more than this number. In the tomography applications, an S21 parameter between a pair of resonator antennas 160 may be measured by using one resonator antenna 160 as a transmitter and one resonator antenna 160 as a receiver. Herein, resonator antenna 160 which transmits an electromagnetic (EM) wave may be identified as the transmitting antenna, while a receiving antenna may be the resonator antenna 160 which receives a reflected (EM) wave. The S21 parameter is dependent on the medium in between the transmitting antenna and the receiving antenna (i.e., of fluid 910 inside flowline 606). In general, the S_{ji} parameter is the element of the scattering matrix, that is calculated as the ratio of the power wave received at the j^{th} port due to an incident power wave at the i^{th} port (when the j^{th} port is terminated in a matched load). Herein, S21 is denoted as the forward voltage gain and is a measure of the transmission of the power between the two ports. It is possible to incorporate the S11 parameter in addition to the S21 parameter in an inversion for a tomog-

21

raphy application to further improve the amount of information available and thus increase the accuracy of the tomography.

An EM wave transmitted by a transmitting antenna may be received as by any resonator antenna 160 within one embodiment. Therefore, the number of measurable S21 parameter for every resonator antenna 160 may be one less than the total number of resonator antennas 160 in the embodiment. By measuring the S21 parameters between different resonator antenna 160 pairs, a tomographic image of the volume inside the flowline may be obtained. The tomographic image may be obtained by traditional methods such as the Fourier inversion theorem (e.g., the Radon transform) using at least one S21 parameter between at least one resonator antenna 160 pairs. The tomographic image (or the measurement data used in obtaining the tomographic image) may be inverted to produce resistivity and permittivity images of the flowline as described in the previous section. Furthermore, nested resonator antennas 160 may be used with different operating frequencies in a tomography application, as described above. With nested resonator antennas 160, a different tomographic image may be obtained for each frequency which may be used to resolve dispersion characteristics of the multiphase fluids.

Currently technology is not able to provide an antenna structure for traditional flowlines that does not degrade over time due to the accumulation of contaminants from the fluids and capable of making measurements in conducting flowlines. Systems and methods herein relate to resonator antennas for performing resistivity and permittivity measurements in flowlines. Resonator antennas may not be affected by the accumulation of particles and may measure both conductive and nonconductive fluid. Additionally, improvements over current technology reside in tomography measurements with a wide range of possible configurations.

Statement 1: A downhole fluid sampling tool may comprise one or more probes configured to extend into a formation, a pump configured to collect a fluid from the formation through the one or more probes, a flowline configured to transport the fluid from the formation through the one or more probes and through the downhole fluid sampling tool, and a fluid analysis module comprising a resonator antenna disposed on the flowline and configured to measure at least one property of the fluid.

Statement 2: The downhole fluid sampling tool of statement 1, wherein the resonator antenna is a cavity resonator.

Statement 3: The downhole fluid sampling tool of statement 2, wherein the cavity resonator is disposed on an outer surface of the flowline.

Statement 4: The downhole fluid sampling tool of statement 2, wherein the cavity resonator is disposed within the flowline and the fluid inside the flowline acts as a substrate of a cavity resonator.

Statement 5: The downhole fluid sampling tool of statements 2-4, wherein the cavity resonator comprises a slot.

Statement 6: The downhole fluid sampling tool of statement 5, wherein the flowline comprises a cut slot that is aligned with the slot from the cavity resonator and filled with dielectric material.

Statement 7: The downhole fluid sampling tool of statement 6, wherein the cavity resonator is configured to: transmit an electromagnetic (EM) wave through the slot and cut slot and into the flowline, and measure a reflected EM wave through the slot and cut slot from the flowline and compute an S11 parameter indicative of electrical properties of the fluid.

22

Statement 8: The downhole fluid sampling tool of statement 2, wherein the cavity resonator is disposed within at least part of a cavity carved within a wall of the flowline.

Statement 9: The downhole fluid sampling tool of statements 1-8, wherein the resonator antenna comprises two or more nested resonator antennas configured to measure a plurality of S11 parameters at more than one frequency.

Statement 10: The downhole fluid sampling tool of statement 1, wherein the resonator antenna is a microstrip patch antenna.

Statement 11: The downhole fluid sampling tool of statement 10, wherein the microstrip patch antenna comprises a slot and the flowline comprises a cut slot that is aligned with the slot from the microstrip patch antenna and filled with dielectric material.

Statement 11: The downhole fluid sampling tool of statement 10, wherein the microstrip patch antenna comprises a slot and the flowline comprises a cut slot that is aligned with the slot from the microstrip patch antenna and filled with dielectric material.

Statement 12: The downhole fluid sampling tool of statement 11, wherein the microstrip patch antenna is disposed within the flowline and the fluid inside the flowline acts as a substrate of the microstrip patch antenna.

Statement 13: The downhole fluid sampling tool of statements 11 or 12, wherein the microstrip patch antenna comprises conducting vias located around a dielectric material.

Statement 14: The downhole fluid sampling tool of statement 11, wherein the microstrip patch antenna is disposed on an outer surface of the flowline.

Statement 15: The downhole fluid sampling tool of statement 11, wherein the microstrip patch antenna is disposed between an inner surface of the flowline and an outer surface of the flowline.

Statement 16: A method may comprise disposing a downhole sampling tool into a formation, extending one or more probes from the downhole sampling tool into the formation, collecting a fluid from the formation through the one or more probes with a pump, transporting the fluid from the formation through the one or more probes and through the downhole fluid sampling tool with a flowline, and measuring at least one property of the fluid with two or more resonator antennas that are disposed on or within an outer surface of the flowline.

Statement 17: The method of statement 16, further comprising measuring at least one S21 parameter with the two or more resonator antennas.

Statement 18: The method of statement 17, wherein the two or more resonator antennas are nested and configured to measure a plurality of S21 parameters at more than one frequency.

Statement 19: The method of statement 18, further comprising forming a resistivity image and permittivity image from at least one S21 parameter.

Statement 20: The method of statement 19, wherein at least one property of the fluid is identified with at least the resistivity image and the permittivity image using tomographic techniques.

The preceding description provides various embodiments of the systems and methods of use disclosed herein which may contain different method steps and alternative combinations of components. It should be understood that, although individual embodiments may be discussed herein, the present disclosure covers all combinations of the disclosed embodiments, including, without limitation, the different component combinations, method step combinations,

23

and properties of the system. It should be understood that the compositions and methods are described in terms of “including,” “containing,” or “including” various components or steps, the compositions and methods can also “consist essentially of” or “consist of” the various components and steps. Moreover, the indefinite articles “a” or “an,” as used in the claims, are defined herein to mean one or more than one of the element that it introduces.

For the sake of brevity, only certain ranges are explicitly disclosed herein. However, ranges from any lower limit may be combined with any upper limit to recite a range not explicitly recited, as well as, ranges from any lower limit may be combined with any other lower limit to recite a range not explicitly recited, in the same way, ranges from any upper limit may be combined with any other upper limit to recite a range not explicitly recited. Additionally, whenever a numerical range with a lower limit and an upper limit is disclosed, any number and any included range falling within the range are specifically disclosed. In particular, every range of values (of the form, “from about a to about b,” or, equivalently, “from approximately a to b,” or, equivalently, “from approximately a-b”) disclosed herein is to be understood to set forth every number and range encompassed within the broader range of values even if not explicitly recited. Thus, every point or individual value may serve as its own lower or upper limit combined with any other point or individual value or any other lower or upper limit, to recite a range not explicitly recited.

Therefore, the present embodiments are well adapted to attain the ends and advantages mentioned as well as those that are inherent therein. The particular embodiments disclosed above are illustrative only, and may be modified and practiced in different but equivalent manners apparent to those skilled in the art having the benefit of the teachings herein. Although individual embodiments are discussed, the disclosure covers all combinations of all of the embodiments. Furthermore, no limitations are intended to the details of construction or design herein shown, other than as described in the claims below. Also, the terms in the claims have their plain, ordinary meaning unless otherwise explicitly and clearly defined by the patentee. It is therefore evident that the particular illustrative embodiments disclosed above may be altered or modified and all such variations are considered within the scope and spirit of those embodiments. If there is any conflict in the usages of a word or term in this specification and one or more patent(s) or other documents that may be incorporated herein by reference, the definitions that are consistent with this specification should be adopted.

What is claimed is:

1. A downhole fluid sampling tool comprising:
one or more probes configured to extend into a formation;
a pump configured to collect a fluid from the formation through the one or more probes;
a flowline configured to transport the fluid from the formation through the one or more probes and through the downhole fluid sampling tool; and
a fluid analysis module comprising two or more nested resonator antennas disposed on the flowline and configured to measure at least one property of the fluid, wherein one nested resonator antenna is disposed within the bounds of another nested resonator antenna and the boundaries of each of the two or more nested resonator antennas are different.
2. The downhole fluid sampling tool of claim 1, wherein the resonator antenna is a cavity resonator.

24

3. The downhole fluid sampling tool of claim 2, wherein the cavity resonator is disposed on an outer surface of the flowline.

4. The downhole fluid sampling tool of claim 2, wherein the cavity resonator is disposed within the flowline and the fluid inside the flowline acts as a substrate of a cavity resonator.

5. The downhole fluid sampling tool of claim 2, wherein the cavity resonator comprises a slot.

6. The downhole fluid sampling tool of claim 5, wherein the flowline comprises a cut slot that is aligned with the slot from the cavity resonator and filled with dielectric material.

7. The downhole fluid sampling tool of claim 6, wherein the cavity resonator is configured to:

transmit an electromagnetic (EM) wave through the slot and cut slot and into the flowline; and

measure a reflected EM wave through the slot and cut slot from the flowline and compute an S11 parameter, wherein the S11 parameter is a function of a reflection coefficient of the fluid.

8. The downhole fluid sampling tool of claim 2, wherein the cavity resonator is disposed within at least part of a cavity carved within a wall of the flowline.

9. The downhole fluid sampling tool of claim 1, wherein the resonator antenna comprises the two or more nested resonator antennas configured to measure a plurality of S11 parameters at more than one frequency, wherein the S11 parameters are a function of a reflection coefficient of the fluid.

10. The downhole fluid sampling tool of claim 1, wherein the resonator antenna is a microstrip patch antenna.

11. The downhole fluid sampling tool of claim 10, wherein the microstrip patch antenna comprises a slot and the flowline comprises a cut slot that is aligned with the slot from the microstrip patch antenna and filled with dielectric material.

12. The downhole fluid sampling tool of claim 11, wherein the microstrip patch antenna is disposed within the flowline and the fluid inside the flowline acts as a substrate of the microstrip patch antenna.

13. The downhole fluid sampling tool of claim 11, wherein the microstrip patch antenna comprises conducting vias located around a dielectric material.

14. The downhole fluid sampling tool of claim 11, wherein the microstrip patch antenna is disposed on an outer surface of the flowline.

15. The downhole fluid sampling tool of claim 11, wherein the microstrip patch antenna is disposed between an inner surface of the flowline and an outer surface of the flowline.

16. A method comprising:

disposing a downhole sampling tool into a formation;
extending one or more probes from the downhole sampling tool into the formation;

collecting a fluid from the formation through the one or more probes with a pump;

transporting the fluid from the formation through the one or more probes and through the downhole fluid sampling tool with a flowline; and

measuring at least one property of the fluid with two or more resonator antennas that are disposed on or within an outer surface of the flowline and the boundaries of each of the two or more nested resonator antennas are different, wherein the at least one property comprises at least one S11 parameter, wherein the S11 parameter is a function of a reflection coefficient of the fluid.

25

17. The method of claim **16**, further comprising measuring at least one S21 parameter with the two or more resonator antennas, wherein the S21 parameter is a forward voltage gain and is a measurement of power transmissions between the two resonator antennas.

5

18. The method of claim **17**, wherein the two or more resonator antennas are nested and configured to measure a plurality of S21 parameters at more than one frequency.

19. The method of claim **17**, further comprising forming a resistivity image and a permittivity image from at least one S21 parameter.

10

20. The method of claim **19**, wherein at least one property of the fluid is identified with at least the resistivity image and the permittivity image using tomographic techniques.

15

* * * * *

26