

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12397916
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Hadjidj; Djemouai

Integrated unit for transferring rotary power from an electrical chain for de-icing propeller blades and the nose cone of a turbomachine

Abstract

An integrated unit for de-icing the propeller blades and the nose of a turbomachine including: a rotary transformer including a static part and a rotary part; a DC-to-AC voltage converter connected at its output to the static part of the rotary transformer and intended to be connected at its input to a DC electrical power supply, and a power switch connected to the rotary transformer and configured to transmit electrical power to at least one pair of propeller blades and to the nose cone of the turbomachine.

Inventors:	Hadjidj; Djemouai (Moissy-Cramayel, FR)
Applicant:	SAFRAN ELECTRICAL & POWER (Blagnac, FR)
Family ID:	1000008782775
Assignee:	SAFRAN ELECTRICAL & POWER (Blagnac, FR)
Appl. No.:	18/851451
Filed (or PCT Filed):	March 28, 2023
PCT No.:	PCT/FR2023/050443
PCT Pub. No.:	WO2023/187292
PCT Pub. Date:	October 05, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20250100695 A1	Mar. 27, 2025

Foreign Application Priority Data

FR	2202967	Mar. 31, 2022
----	---------	---------------

Publication Classification

Int. Cl.: H05B3/22 (20060101); B64C27/473 (20060101); B64D15/12 (20060101)

U.S. Cl.:

CPC B64D15/12 (20130101); B64C27/473 (20130101); H05B3/22 (20130101);

Field of Classification Search

CPC: B64D (15/12); B64C (27/473); H05B (3/22)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2007/0075188	12/2006	Stoner	244/134D	F01D 25/02
2011/0290942	12/2010	Imbert et al.	N/A	N/A
2013/0307378	12/2012	Giordano	310/67R	B64C 27/32
2015/0108760	12/2014	De Wergifosse et al.	N/A	N/A

OTHER PUBLICATIONS

Search Report and Written Opinion issued in International Application No. PCT/FR2023/050443, mailed Jul. 11, 2023. cited by applicant

Primary Examiner: Landrum; Edward F

Assistant Examiner: Chen; Kuangyue

Attorney, Agent or Firm: Bookoff McAndrews, PLLC

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS

(1) This is a National Stage Application under 35 U.S.C. § 371 of International Application No. PCT/FR2023/050443, filed Mar. 28, 2023, now published as WO 2023/187292 A1, which claims priority to French Patent Application No. 2202967, filed on Mar. 31, 2022, the entireties of which are incorporated herein by reference.

TECHNICAL FIELD

(2) This invention relates to the general field of the de-icing of the propeller blades and the nose cone of a turbomachine, and more specifically to the electrical line for de-icing and for transferring power between the fixed part and the rotary part of the turbomachine.

PRIOR ART

(3) Turbomachines comprise, from upstream downward, one or more compressor modules disposed in series, which compress air taken into an air inlet. The air is then introduced into a combustion chamber where it is mixed with a fuel and burned. The combustion gases pass through one or more turbine modules which drive the compressor or compressors. The gases are then expelled either

into a nozzle to produce a propulsion force, or onto a power turbine to produce power which is taken off a transmission shaft.

(4) Current bypass turbojet engines with a high expansion ratio, or turbofans, include a fan rotor and several stages of compressor, in particular a low-pressure compressor, and a high-pressure compressor which belong to the primary spool of the engine. Upstream of the low-pressure compressor is disposed a wheel of large blades, or fan, which supplies both a primary air path with a primary flow traversing the low-pressure and high-pressure compressors, and a secondary air path with a cold flow, or secondary flow, which is guided directly onto a cool flow nozzle, the so-called secondary nozzle. The fan is driven by the rotation shaft of the low-pressure spool.

(5) The anti-frost protection of the propeller blades of the fan and of the nose cone of a turbomachine is based on electrothermal de-icing. Heated mats composed of a network of resistors are incorporated into the leading edges of the propellers and of the nose cone. In icy conditions, a layer of ice is deliberately left to form on the leading edges. Then, the resistances of the heated mats are powered for a predefined time period to heat the surface of the propellers and of the nose cone before detaching the layers of ice formed. With the rotation of the propellers and of the nose cone, these layers of ice are expelled by the effect of centrifugal force.

(6) The surfaces of the turbomachine to be de-iced are large and therefore require a good deal of electrical power to supply the resistances of the heated mats, the power dedicated to de-icing coming from the generators of the airplane. FIG. 1 shows an electric circuit **120** of a de-icing system of the prior art connected to the resistances **110** of the heated mats and to the electrical power supplies **131**, **132** and to the control system **130** of the turbomachine. The electrical circuit **120** comprises DC-to-AC voltage converters **123** which are used to supply AC voltage to the rotary transformers **122**. To limit the power supplied to the de-icing system and to the other non-propulsion systems, the resistances **110** of one pair of propeller blades are powered solely for a given time, then the resistances of the next pair and so on, a pair being formed of one blade and its opposite, the whole being connected in series with a section of the nose cone. The alternation of the powering of the resistances **110** of the blade pairs is done using the switches **121** placed between the resistances **110** and the rotary transformers **122**.

(7) To run the electrical circuit **120** of the de-icing system, ancillary power connections are needed, such as for example ancillary power connections for the low-voltage DC power supply **142**, for the high-voltage DC power supply **141** and for the communication links **143** between the parts **121**, **122**, **123** of the electrical circuit **120** and the control system **130** of the turbomachine. This requires the routing of numerous harnesses **141**, **142**, **143** in the turbomachine while observing certain restrictions on installation, such as restrictions on the radii of curvature of the harnesses or on the distances between the harnesses and/or between the components of the turbomachine. These restrictions cause an increase in the mass and volume of the turbomachine, along with a complex installation and maintenance of the de-icing system.

(8) It is therefore desirable to possess an electrical de-icing system which complies with the installation restrictions while reducing the mass, volume and complexity of integration of the de-icing system.

SUMMARY OF THE INVENTION

(9) The invention relates to an integrated unit for transferring rotary power from an electrical circuit for de-icing the propeller blades and the nose cone of a turbomachine comprising: a rotary transformer comprising a static part and a rotary part; a DC-to-AC voltage converter connected at its output to the static part of the rotary transformer and intended to be connected at its input to a DC electrical power supply, and a power switch connected to the rotary transformer and configured to transmit electrical power to at least one pair of propeller blades and to the nose cone of the turbomachine.

(10) The invention thus makes it possible to group the switch and the converter within one and the same equipment item, the rotary transformer, to form an integrated unit for transferring rotary

power. In other words, they are present locally at one and the same place in the turbomachine. The integrated unit is thus more compact and can be installed in the turbomachine in an area of small diameter, thus limiting centrifugal acceleration forces, which are very stressful and harmful to electronic components.

(11) The fact of integrating all the components into one and the same equipment item makes it possible to reduce, or even eliminate, the numerous long cables and harnesses between the equipment items of the de-icing system, and also to reduce the number and size of the electromagnetic disturbance filters (EMI or EMC filters). The mass and volume of the electrical de-icing system can thus be reduced.

(12) In addition, owing to the integrated unit, it is also possible to pool resources, such as the cooling and the low-voltage power supply between these three components. This also offers flexibility as regards the orientation of the connectors (axial orientation or circulation for example) to facilitate the routing of the power harnesses from the unit to the blade roots or the nose cone.

(13) Finally, the integrated unit offers more choice as regards the design and arrangement of the components within the unit, for example to facilitate maintenance, or improve the efficiency of the cooling or the interconnections between components.

(14) According to a particular feature of the invention, the integrated unit comprises a first electrical channel comprising the rotary transformer, the converter and the switch, and a second channel comprising a second rotary transformer comprising a static part and a rotary part, a second DC-to-AC voltage converter and a second power switch, the second converter being connected at its output to the static part of the second rotary transformer and intended to be connected at its input to a DC electrical power supply and the second switch being connected to the second rotary transformer and configured to transmit electrical power to at least one pair of propeller blades and to the nose cone of the turbomachine.

(15) The fact of having two redundant electrical channels makes it possible to always have an operational de-icing system even in the event of failure of one of the channels.

(16) According to another particular feature of the invention, the integrated unit comprises at least one DC-to-DC voltage converter associated with the DC-to-AC voltage converter and connected to the DC electrical power supply of the associated DC-to-AC voltage converter and configured to generate a low-voltage electrical power supply.

(17) The presence of a DC-to-DC voltage converter (or DC/DC converter) makes it possible to generate a local low-level voltage (for example a DC voltage of 28 V), i.e. within the integrated unit. This makes it possible, for each electrical channel, to connect the integrated unit to a single high-voltage external electrical power supply and to reduce the number of cables between the unit and its environment.

(18) According to another particular feature of the invention, the integrated unit comprises a plurality of rotary transformers in each electrical channel, and within each electrical channel, each rotary transformer is associated with a separate pair of propeller blades; the DC-to-AC voltage converter is common to the rotary transformers of the electrical channel and the switch comprises switches configured to select one of the rotary transformers of the electrical channel.

(19) Owing to this feature, each rotary transformer is powered only during the activation time of the corresponding pair of propeller blades. This makes it possible to insert the electronics of the switch between the DC/AC converter and the rotary transformers and thus to position the switch on the static part of the integrated unit, hence eliminating the centrifugal stress on the electronics.

(20) According to another particular feature of the invention, in each electrical channel, the rotary transformer and the power switch are combined.

(21) This makes it possible to have only one rotary transformer in each electrical channel capable of powering all the pairs of propeller blades, the rotary transformer comprising at least as many outputs as there are blade pairs. In addition, the electronics of the switch can also be positioned on the static part of the rotary transformer.

- (22) Another subject of the invention is a turbomachine comprising an integrated unit for transferring rotary power according to the invention and a low-pressure reduction gear, the integrated unit being secured to the low-pressure reduction gear.
- (23) The low-pressure reduction gear, also known as Reduction Gear Box, or RGB, is interposed between the fan comprising the propeller blades and the low-pressure shaft of the turbomachine.
- (24) It makes it possible to drive the propeller blades of the turbomachine fan and have a lower blade rotation speed than that of the low-pressure shaft. This reduction in speed makes it possible to increase the size of the fan.
- (25) The fact of having the integrated unit secured to the low-pressure reduction gear makes it possible to have a de-icing system close to the reduction gear and to make provision for a de-icing system that is more compact, more effective, lighter and has more accessible, and hence simplified, maintenance.
- (26) According to a particular feature of the invention, the low-pressure reduction gear comprises a rotary part and a fixed shaft, the rotary part of each of the rotary transformers of the integrated unit is secured to the rotary part of the low-pressure reduction gear, and the static part of each of the rotary transformers, the power switches and the DC-to-AC voltage converters of the integrated unit are secured to the fixed shaft of the low-pressure reduction gear.
- (27) According to another particular feature of the invention, the low-pressure reduction gear comprises a rotary part and a fixed shaft, the rotary part of each of the rotary transformers and the power switches of the integrated unit are secured to the rotary part of the low-pressure reduction gear and the static part of each of the rotary transformers and DC-to-AC voltage converters of the integrated unit are secured to the fixed shaft of the low-pressure reduction gear.
- (28) These two variants of assembly of the integrated unit to the fixed (fixed shaft) and rotary parts of the low-pressure reduction gear make it possible to eliminate the bearings on the integrated unit and thus improve its reliability and its lifetime. They also make it possible to dispense with imbalance effects and movements, by being close to the bearing hangers of the reduction gear, to have reduced mechanical play between the fixed and rotary parts of the integrated unit, to make savings on mass, particularly at the rotary transformer, to make savings on volume and improve the efficiency of the entire electrical de-icing system, and finally to have an under-wing equipment item that is accessible and replaceable without any specific tools to simplify maintenance, mounting and dismounting operations.
- (29) According to another particular feature of the invention, the turbomachine comprises fins located on an outer surface of the integrated unit and secured to the rotary part of the low-pressure reduction gear.
- (30) The fins make it possible to create a forced air flow around the integrated unit making it possible to cool the components of the integrated unit assembled on the rotary part of the reduction gear.
- (31) According to another particular feature of the invention, the turbomachine comprises a fan secured to the rotary part of the low-pressure reduction gear.
- (32) The fan makes it possible to blow air to cool the components of the integrated unit assembled on the rotary part of the reduction gear. The components assembled on the fixed part can also benefit from this air for their cooling. The fan can advantageously be combined with the fins to improve the cooling of the integrated unit.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) Other features and advantages of this invention will become apparent from the description given below, with reference to the appended drawings which illustrate exemplary embodiments

thereof without any limitation.

(2) FIG. 1 represents, schematically and partially, a de-icing system of the prior art.

(3) FIG. 2 represents, schematically and partially, an integrated unit of a de-icing system according to an embodiment of the invention.

(4) FIG. 3 represents, schematically and partially, the assembly of the rotary parts of the integrated unit on a low-pressure reduction gear according to an embodiment of the invention.

(5) FIG. 4 represents, schematically and partially, the assembly of the rotary parts of the integrated unit on a low-pressure reduction gear according to another embodiment of the invention.

(6) FIG. 5 represents, schematically and partially, an integrated unit and its assembly on a low-pressure reduction gear according to another embodiment of the invention.

DESCRIPTION OF THE EMBODIMENTS

(7) FIG. 2 represents, schematically and partially, an integrated unit **220** for transferring rotary power from a de-icing system according to an embodiment of the invention. Throughout the description, a pair of propeller blades is formed of a blade **1101** and its opposite **1102**, and the blade and its opposite are connected to a section **1121**, **1122** of the nose cone **110** of the turbomachine. In addition, the blades **1101**, **1102**, the sections **1121**, **1122** and the nose cone **110** comprise heated mats composed of a network of resistances **1111**, **1112**, **1113**, **1114**, **1115**, **1116** used to de-ice them. Although it is not shown on the figures, the propeller blades and the nose cone can also be connected to one another in parallel.

(8) The integrated unit **220** of the electrical circuit of the de-icing system comprises two redundant electrical channels. The first electrical channel comprises a rotary transformer **2221** connected to a DC-to-AC voltage converter **2231** (or DC/AC converter **2231**) at its input and to a power switch **2211** at its output. The second electrical channel also comprises a rotary transformer **2222** connected to a DC-to-AC voltage converter **2232** (or DC/AC converter **2232**) at its input and to a power switch **2212** at its output. Each rotary transformer **2221** and **2222** comprises a static part and a rotary part. These two rotary transformers **2221** and **2222** can be completely independent, or each have a winding around one and the same magnetic circuit. The power switches **2211**, **2212** of the two channels are connected to at least one pair of propeller blades **1101**, **1102** and to the nose cone **110** of the turbomachine. On this figure, for the sake of clarity, only one pair of propellers is shown. However, the switches **2211**, **2212** of the two channels can be connected to all the pairs of propeller blades of the turbomachine. The DC/AC converters **2231**, **2232** are each connected at the input to a high-voltage DC power supply **2321**, **2322** and at the output to the static part of the rotary transformer associated with their electrical circuit. In order to generate a low-voltage electrical power supply, the integrated unit **220** also comprises, in each electrical channel, a DC-to-DC voltage converter **2241**, **2242** (or DC/DC converter). The DC/DC converter **2241** of the first channel is connected at the input to the high-voltage DC electrical power supply **2321** and makes it possible to generate a low voltage in the first channel; while the DC/AC converter **2242** is connected at the input to the high-voltage DC electrical power supply **2322** and makes it possible to generate a low voltage in the second electrical channel. The two DC/DC converters **2241** and **2242** more generally make it possible to supply the low-voltage power to the control electronics of the turbomachine.

(9) The integrated unit **220** is also connected to the control system **230** of the turbomachine. Thus, the only ancillary power connections connected to the integrated unit **220** are those of the high-voltage electrical power supply **2411**, **2412** and those for communication **2431**, **2432**. It is however possible to have an additional ancillary power connection between the low-voltage electrical power supply **2311**, **2312** and the integrated unit **220**, if the unit **220** does not comprise any DC/DC converters.

(10) FIG. 3 represents, schematically and partially, the assembly of the rotary parts **3201**, **3202** of the integrated unit **320** on a low-pressure reduction gear **330** according to an embodiment of the invention.

(11) The components of the integrated unit **320** are placed in a casing of a cylindrical shape enclosed by the flanges **321** and **322**. The casing and its flanges **321** and **322** are assembled on the reduction gear **330**. Thus, the integrated unit **320** is secured to the reduction gear **330**; in particular its rotary parts **3201**, **3202** are secured to the rotary parts of the reduction gear **330**. The flanges **321** and **322** are attached to the reduction gear **330** using, for example, sets **370** of screws and nuts. The flanges **321** comprise ventilation grilles **361**, **362** to be able to evacuate the hot air from the integrated unit **320**, the ventilation grilles **362** of the flange **322** facing the ventilation grilles **360** of the reduction gear **330**. More specifically, the ventilation grille **361** of the flange **321** allows cool air to enter the integrated unit **320**, while the ventilation grilles **360** of the reduction gear **330** and **362** of the flange **322** make it possible to evacuate hot air from the integrated unit **320**. In this embodiment, the sets **370** of screws and nuts for assembling the integrated unit **320** on the reduction gear **330** are placed inside the integrated unit **320**.

(12) The reduction gear **330** comprises a fixed shaft **331** through which the ancillary power connections **3411**, **3412**, **3431**, **3432** are routed to the integrated unit **320**.

(13) FIG. 4 shows, schematically and partially, the assembly of the rotary parts **4201**, **4202** of the integrated unit **420** on a low-pressure reduction gear **430** according to another embodiment of the invention.

(14) The components of the integrated unit **420** are placed in a cylindrical casing enclosed by two flanges **421** and **422**. The casing is assembled on the reduction gear **430** via its flanges **421** and **422**. Thus, the integrated unit **420** is secured to the reduction gear **430**; in particular its rotary parts **4201**, **4202** are secured to the rotary parts of the reduction gear **430**. The flanges **421** and **422** are attached to the reduction gear **430** using, for example, sets **470** of screws and nuts. The flange **421** comprises a ventilation grille **461** to be able to expel hot air from the integrated unit **420**. More specifically, the ventilation grille **461** allows cool air to enter the integrated unit **420**. The reduction gear **430** still comprises ventilation grilles **460** used to expel hot air from the integrated unit **420**. In this embodiment, the sets **470** of screws and nuts for assembling the integrated unit **420** on the reduction gear **430** are placed outside the integrated unit **420**.

(15) As previously, the reduction gear **430** comprises a fixed shaft **431** through which the ancillary power connections **4411**, **4412**, **4431**, **4432** are routed to the integrated unit **420**.

(16) FIG. 5 shows, schematically and partially, the assembly of the integrated unit **520** on a low-pressure reduction gear **530** according to an embodiment of the invention.

(17) The fixed parts **5203**, **5204** of the integrated unit **520** are secured to the fixed shaft **531** of the low-pressure reduction gear **530**. More specifically, the integrated unit **520** comprises a rotationally immobilized hollow and sliding shaft **571**. This immobilization is for example embodied by a key. The hollow shaft **571** makes it possible to run the different ancillary power connections from the integrated unit **520** via the fixed shaft **531** of the reduction gear **530**, such as the electrical power supplies **5411**, **5412** and the communications **5431**, **5432** with the control system of the turbomachine. Then translational immobilization of the hollow shaft **571** is for example done by a slotted nut **570** mounted at the end of the shaft **571**.

(18) The rotary and fixed parts of the FIGS. 3, 4 and 5 comprise the rotary transformers, the DC/AC converters, the DC/DC converters and the power switches of the two electrical channels described in FIG. 2. The fixed part comprises the static part of each of the rotary transformers, the DC/DC converters and the DC/AC converters, while the rotary part comprises the rotary part of each of the rotary transformers. The power switches can be in the fixed part or in the rotary part. If the switches are in the fixed part of the integrated unit, they are generally placed between the DC/AC converters and the static part of each of the rotary transformers; whereas if they are in the rotary part of the integrated unit, they are generally placed between the rotary part of each of the rotary transformers and the resistances of the pairs of propeller blades and the nose cone of the turbomachine. By placing the switches in the rotary part of the integrated unit, volume can be freed up for the DC/AC converters and/or the outputs of the integrated unit can be brought closer to the

resistances of the pairs of propeller blades and the nose cone.

(19) The placement of the DC/AC converters, the DC/DC converters, the power switches and the rotary transformers within the integrated unit is suitable for meeting the restrictions on reliability and/or cooling. For example, to improve the cooling, the components most sensitive to temperature can be placed in contact with the outer surfaces of the casing of the integrated unit and close to the cool air ventilation grille. Or to limit the mechanical stress related to centrifugal forces, certain components of the rotary part of the integrated unit can be placed as close as possible to the axis of rotation.

(20) In addition, the integrated unit **320, 420, 520** may comprise one or more fans **341, 342, 441, 442, 541, 542** secured to the rotary part **3201, 3202, 4201, 4202, 5201, 5202** of the integrated unit **320, 420, 520**. These fans **341, 342, 441, 442, 541, 542** blow forced air to expel the heat from the integrated unit **320, 420, 520**.

(21) Fins **551, 552** can also be mounted on an outer and rotary surface of the integrated unit **520** (as shown in FIG. 5) to accelerate the surrounding air and create a forced air flow also used to expel heat from the integrated unit **520**, in particular from the rotary elements **5201, 5202** of the integrated unit **520**.

(22) It is also possible to place the fins **561, 562** inside the integrated unit **520**, in such a way that these fins **561, 562** are secured to the fixed parts **5203, 5204** of the integrated unit **520**. These three cooling solutions can be embodied alone or in combination on the integrated unit **520**, to adapt to different restrictions: cooling, overall dimensions, mass, etc.

(23) In addition, advantageously, the elements placed in the rotary parts of the integrated unit shown in FIGS. 3, 4 and 5 are assembled and distributed symmetrically around the reduction gear in order to ensure the balancing of the assembly and avoid creating imbalances.

(24) The integrated unit can also have its own bearings, particularly on the side of the flanges, if restrictions on integration or other restrictions require it.

(25) Whatever the embodiment of the invention, the integrated unit comprises a plurality of rotary transformers, each transformer being associated with a separate pair of propeller blades. If there are for example N pairs of propeller blades (N being greater than or equal to 1), there will be N rotary transformers in each electrical channel of the integrated unit. Within an electrical channel, each rotary transformer is powered solely during the activation time of the corresponding blade pair. To power the rotary transformers of one and the same channel, the integrated unit may comprise a single DC/AC converter per channel (and where applicable, also a single DC/DC converter) and the power switch comprises switches for activating the rotary transformer associated with the active blade pair.

(26) Within one and the same electrical channel, it is also possible to combine the rotary transformer and the power switch. Thus, the rotary transformer has as many outputs as there are pairs of propeller blades to be powered, and the switch combined with the rotary transformer acts as a selector to select the output of the rotary transformer corresponding to the active blade pair. More specifically, an electromagnetic actuator is associated with a single primary circuit of the rotary transformer and the selector is controlled to position the actuator, and therefore the primary circuit of the rotary transformer, with the secondary circuit of the rotary transformer corresponding to the blade pair active during the de-icing of this blade pair. There is always a single DC/AC converter per channel.

(27) Whatever the embodiment, the DC/AC converter can be single-phase, three-phase, or have another topology.

(28) Whatever the embodiment, the rotary transformer can be single-phase, three-phase, or have another topology.

(29) Whatever the embodiment, the switch can be direct-current or alternating-current.

Claims

1. An integrated unit for transferring rotary power from an electrical circuit for de-icing at least one pair of propeller blades and a nose of a turbomachine comprising: a rotary transformer comprising a static part and a rotary part; a DC-to-AC voltage converter connected at an output of the DC-to-AC voltage converter to the static part of the rotary transformer and connected at an input of the DC-to-AC voltage converter to a DC electrical power supply, and a power switch connected to the rotary transformer and configured to transmit electrical power to the at least one pair of propeller blades and to a nose cone of the turbomachine, wherein the integrated unit comprises a DC-to-DC voltage converter connected at an input of the DC-to-DC voltage converter to the DC electrical power supply of the DC-to-AC voltage converter and configured to decrease a voltage from the DC electrical supply and generate a low-voltage electrical power supply.
2. The integrated unit as claimed in claim 1, comprising a first electrical channel comprising the rotary transformer, the DC-to-AC voltage converter and the power switch, and a second electrical channel comprising a second rotary transformer comprising a static part and a rotary part, a second DC-to-AC voltage converter and a second power switch, the second DC-to-AC voltage converter being connected at an output of the second DC-to-AC voltage converter to the static part of the second rotary transformer and connected at an input of the second DC-to-AC voltage converter to the DC electrical power supply and the second power switch being connected to the second rotary transformer and configured to transmit electrical power to the at least one pair of propeller blades and to the nose cone of the turbomachine.
3. The integrated unit as claimed in claim 2, wherein each of the first electrical channel and the second electrical channel comprise the DC-to-DC voltage converter connected at the input of the first electrical channel and the second electrical channel to the DC electrical power supply of the DC-to-AC voltage converter of the first electrical channel and the second electrical channel and configured to generate the low-voltage electrical power supply.
4. The integrated unit as claimed in claim 2, comprising the rotary transformer and the second rotary transformer, and within each electrical channel, each rotary transformer is associated with a separate pair of propeller blades of the at least one pair of propeller blades; the DC-to-AC voltage converter is common to the rotary transformers of the electrical channel and the switch comprises switches configured to select one of the rotary transformers of the electrical channel.
5. The integrated unit as claimed in claim 2, wherein, in each of the first electrical channel and the second electrical channel, the rotary transformer and the power switch are combined.
6. The turbomachine comprising the integrated unit for transferring rotary power as claimed in claim 1, and a low-pressure reduction gear, the integrated unit being secured to the low-pressure reduction gear.
7. The turbomachine as claimed in claim 6, wherein the low-pressure reduction gear comprises a rotary part and a fixed shaft, the rotary part of the rotary transformer of the integrated unit is secured to the rotary part of the low-pressure reduction gear, and the static part of the rotary transformer, the power switch and the DC-to-AC voltage converter of the integrated unit are secured to the fixed shaft of the low-pressure reduction gear.
8. The turbomachine as claimed in claim 6, wherein the low-pressure reduction gear comprises a rotary part and a fixed shaft, the rotary part of the rotary transformer and the power switch of the integrated unit are secured to the rotary part of the low-pressure reduction gear and the static part of the rotary transformer and the DC-to-AC voltage converter of the integrated unit are secured to the fixed shaft of the low-pressure reduction gear.
9. The turbomachine as claimed in claim 6, comprising fins located on an outer surface of the integrated unit and secured to the rotary part of the low-pressure reduction gear.

10. The turbomachine as claimed in claim 6, comprising a fan secured to the rotary part of the low-pressure reduction gear.
