

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250287455

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

Ohara; Tomoya et al.

TERMINAL, BASE STATION, RADIO COMMUNICATION SYSTEM, AND RADIO COMMUNICATION METHOD

Abstract

A terminal includes a communication unit that executes intermittent communication in which communication is executed in a periodic first section, and communication is not executed in a second section other than the first section; and a control unit that executes extension of the first section or shortening of the first section when a specific condition is satisfied.

Inventors:	Ohara; Tomoya (Chiyoda-ku, Tokyo, JP), Takahashi; Yuki (Chiyoda-ku, Tokyo, JP)
Applicant:	NTT DOCOMO, INC. (Tokyo, JP)
Family ID:	1000008658712
Assignee:	NTT DOCOMO, INC. (Tokyo, JP)
Appl. No.:	18/859913
Filed (or PCT Filed):	April 28, 2022
PCT No.:	PCT/JP2022/019446

Publication Classification

Int. Cl.:	H04W76/28 (20180101)
U.S. Cl.:	
CPC	H04W76/28 (20180201);

Background/Summary

TECHNICAL FIELD

[0001] This disclosure relates to a terminal, a base station, a radio communication system and a radio communication method that execute intermittent communication.

BACKGROUND ART

[0002] The 3rd Generation Partnership Project (3GPP) has provided specifications for the 5th generation mobile communication system (which is also called 5G, New Radio (NR) or Next Generation (NG)), and is further proceeding with the next generation specifications called Beyond 5G, 5G Evolution or 6G.

[0003] In the 3GPP, supporting applications of Extended Reality (XR) has been considered, and introduction of Connected mode Discontinuous Reception (CDRX) has been considered to reduce the power consumption related to XR (for example, Non-Patent Literature 1).

CITATION LIST

Non-Patent Literature

[0004] Non-patent Literature 1: “Revised SID: Study on XR Enhancements for NR,” RP-220285, 3GPP TSG RAN Meeting #95e, 3GPP, March 2022

SUMMARY OF THE INVENTION

[0005] It is assumed that XR R traffic is periodically transmitted depending on frames per second (FPS). In such a case, if a large length of an active section of CRDX is set in order to absorb jitter of the XR traffic, power consumption of a terminal (hereinafter referred to as UE; User Equipment) increases. On the other hand, it is assumed that, if a small length of the active section of CRDX is set, the XR traffic cannot be received, resulting in a delay of the XR traffic.

[0006] An object of the present invention is to provide a terminal, a base station, a radio communication system, and a radio communication method capable of reducing power consumption while suppressing traffic delay.

[0007] An aspect of the disclosure is a terminal including: a communication unit executes that intermittent communication in which communication is executed in a periodic first section, and communication is not executed in a second section other than the first section; and a control unit that executes extension of the first section or shortening of the first section when specific condition is satisfied.

[0008] An aspect of the disclosure is a base station including: a communication unit that executes intermittent communication in which communication is executed in a periodic first section, and communication is not executed in a second section other than the first section; and a control unit that assumes that the terminal executes extension of the first section or shortening of the first section when a specific condition is satisfied.

[0009] An aspect of the disclosure is a radio communication device including a terminal and a base station, the terminal including a communication unit that executes intermittent communication in which communication is executed in a periodic first section, and communication is not executed in a second section other than the first section; and a control unit that executes extension of the first section or shortening of the first section when a specific condition is satisfied.

[0010] An aspect of the disclosure is a radio communication method including: a step of executing intermittent communication in which communication is executed in a periodic first section, and communication is not executed in a second section other than the first section; and a step of executing extension of the first section or shortening of the first section when a specific condition is satisfied.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- [0011] FIG. **1** is an overall schematic configuration diagram of a radio communication system **10**.
[0012] FIG. **2** is a diagram illustrating a frequency range used in the radio communication system **10**.
[0013] FIG. **3** is a diagram illustrating a configuration example of a radio frame, a subframe, and a slot used in the radio communication system **10**.
[0014] FIG. **4** is a functional block configuration diagram of a UE **200**.
[0015] FIG. **5** is a functional block configuration diagram of a gNB **100**.
[0016] FIG. **6** is a diagram for explaining a problem related to extension of an active section.
[0017] FIG. **7** is a diagram for explaining Operation Example 1 related to extension of the active section.
[0018] FIG. **8** is a diagram for explaining Operation Example 2 related to extension of the active section.
[0019] FIG. **9** is a diagram for explaining Operation Example 3 related to extension of the active section.
[0020] FIG. **10** is a diagram for explaining Operation Example 4 related to extension of the active section.
[0021] FIG. **11** is a diagram for explaining a problem related to shortening of the active section.
[0022] FIG. **12** is a diagram for explaining Operation Example 1 related to shortening of the active section.
[0023] FIG. **13** is a diagram for explaining Operation Example 2 related to shortening of the active section.
[0024] FIG. **14** is a diagram illustrating an example of a hardware configuration of the gNB **100** and UE the **200**.
[0025] FIG. **15** is a diagram illustrating an example of a configuration of a vehicle **2001**.

DESCRIPTION OF EMBODIMENTS

[0026] Hereinafter, embodiments will be described with reference to the drawings. It should be noted that the same functions and configurations are denoted by the same or similar reference signs, and the description thereof will be omitted, as appropriate.

Embodiments

(1) Overall Schematic Configuration of Radio Communication System

[0027] FIG. **1** is an overall schematic configuration diagram of a radio communication system **10** according to an embodiment. The radio communication system **10** is a radio communication system in accordance with 5G New Radio (NR) and includes a Next-Generation Radio Access Network **20** (hereinafter referred to as NG-RAN **20**) and a terminal **200** (hereinafter referred to as a UE (User Equipment) **200**).

[0028] The radio communication system **10** may be a radio communication system in accordance with a system called Beyond 5G, 5G Evolution or 6G.

[0029] The NG-RAN **20** includes a base station **100** (hereinafter referred to as a gNB **100**). A specific configuration of the radio communication system **10** including the number of gNBs **100** and UEs **200** is not limited to the example illustrated in FIG. **1**.

[0030] In practice, the NG-RAN **20** includes a plurality of NG-RAN Nodes, specifically gNBs (or ng-eNBs), and is connected to a core network (5GC, not illustrated) in accordance with 5G. The NG-RAN **20** and the 5GC may be simply expressed as a “network.”

[0031] The gNB **100** is a radio base station in accordance with 5G and executes radio communication with the UE **200** in accordance with 5G. The gNB **100** and the UE **200** can support Massive MIMO (Multiple-Input Multiple-Output) that generates a beam BM with a higher directivity by controlling radio signals transmitted from a plurality of antenna elements, Carrier Aggregation (CA) that uses a plurality of Component Carriers (CC) bundled together, and Dual

Connectivity (DC) that simultaneously communicates with two or more transport blocks between the UE and each of two NG-RAN nodes.

[0032] The radio communication system **10** supports a plurality of frequency ranges (FR). FIG. 2 illustrates frequency ranges used in the radio communication system **10**.

[0033] As illustrated in FIG. 2, the radio communication system **10** supports FR1 and FR2. The frequency bands of each FR are as follows. [0034] FR1: 410 MHz to 7.125 GHz [0035] FR2: 24.25 GHz to 52.6 GHz

[0036] FR1 uses Sub-Carrier Spacing (SCS) of 15, 30 or 60 kHz, and may use bandwidth (BW) of 5 to 100 MHz. FR2 has a higher frequency than FR1, and may use SCS of 60 or 120 kHz (240 kHz may be included), and may use bandwidth (BW) of 50 to 400 MHz.

[0037] SCS may be interpreted as a numerology. The numerology is defined in 3GPP TS38.300, and corresponds to one subcarrier spacing in a frequency domain.

[0038] Further, the radio communication system **10** supports a frequency band higher than the frequency band of the FR2. More specifically, the radio communication system **10** supports a frequency band exceeding 52.6 GHz and up to 71 GHz or 114.25 GHz. Such a high frequency band may be referred to as “FR2x” for convenience.

[0039] In order to solve the problem that effect of phase noise increases in a high frequency band, Cyclic Prefix-Orthogonal Frequency Division Multiplexing (CP-OFDM)/Discrete Fourier Transform-Spread (DFT-S-OFDM) with a larger Sub-Carrier Spacing (SCS) may be applied when a band exceeding 52.6 GHz is used.

[0040] FIG. 3 illustrates an example of a configuration of a radio frame, a subframe, and a slot used in the radio communication system **10**.

[0041] As illustrated in FIG. 3, one slot is configured by 14 symbols, and the larger (wider) the SCS, the shorter the symbol duration (and slot duration). The SCS is not limited to the interval (frequency) illustrated in FIG. 3. For example, 480 kHz or 960 kHz may be used.

[0042] The number of symbols that configures one slot may not necessarily be 14 symbols (for example, 28 symbols or 56 symbols). Furthermore, the number of slots per subframe may be different depending on the SCS.

[0043] Note that a time direction (t) illustrated in FIG. 3 may be called a time domain, a symbol duration, or a symbol time. A frequency direction may be called a frequency domain, a resource block, a subcarrier, or a bandwidth part (BWP).

[0044] DMRS is a type of reference signal and is prepared for various channels. Herein, unless otherwise specified, DMRS for a downlink data channel, specifically, Physical Downlink Shared Channel (PDSCH) may be interpreted as DMRS. However, DMRS for an uplink data channel, specifically, Physical Uplink Shared Channel (PUSCH) may be interpreted as DMRS for PDSCH.

[0045] DMRS may be used for channel estimation in the UE **200** as part of a device, for example, coherent demodulation. DMRS may be present only in the resource block (RB) used for PDSCH transmission.

[0046] DMRS may have multiple mapping types. Specifically, DMRS may have Mapping Type A and Mapping Type B. In Mapping Type A, first DMRS is placed in a second or third symbol of the slot. In Mapping Type A, the DMRS may be mapped with reference to slot boundaries regardless of where in the slot the actual data transmission begins. The reason for placing the first DMRS in the second or third symbol of the slot may be interpreted as placing the first DMRS after control resource sets (CORESET).

[0047] For Mapping Type B, the first DMRS may be placed in a first symbol of the data allocation. That is, the position of the DMRS is not given relative to the slot boundaries, but may be given relative to the location in which the data is located.

[0048] DMRS may also have multiple types (Type). Specifically, DMRS may have Type 1 and Type 2. Type 1 and Type 2 differ in the maximum number of mapping and orthogonal reference signals in the frequency domain. Type 1 is single-symbol DMRS that can output up to four

orthogonal signals. Type 2 is double-symbol DMRS that can output up to eight orthogonal signals.

(2) Functional Block Configuration of the Radio Communication System

[0049] Next, the functional block configuration of the radio communication system **10** will be described.

[0050] First, the functional block configuration of the UE **200** will be described.

[0051] FIG. **4** is a functional block configuration diagram of the UE **200**. As illustrated in FIG. **4**, the UE **200** includes a radio signal transmission and reception unit **210**, an amplifier unit **220**, a modulation and demodulation unit **230**, a control signal and reference signal processing unit **240**, an encoding/decoding unit **250**, a data transmission and reception unit **260**, and a control unit **270**.

[0052] The radio signal transmission and reception unit **210** transmits and receives radio signals in accordance with NR. The radio signal transmission and reception unit **210** supports the Massive MIMO, the CA that uses a plurality of the CCs bundled together, and the DC that simultaneously executes communication between the UE and each of the two NG-RAN Nodes.

[0053] The amplifier unit **220** is configured by a Power Amplifier (PA)/a Low Noise Amplifier (LNA), or the like. The amplifier unit **220** amplifies the signal output from the modulation and demodulation unit **230** to a predetermined power level. Further, the amplifier unit **220** amplifies an RF signal output from the radio signal transmission and reception unit **210**.

[0054] The modulation and demodulation unit **230** executes data modulation/demodulation, transmission power setting, resource block allocation, or the like for each predetermined communication destination (gNB **100** or another gNB). In the modulation and demodulation unit **230**, Cyclic Prefix-Orthogonal Frequency Division Multiplexing (CP-OFDM)/Discrete Fourier Transform-Spread (DFT-S-OFDM) may be applied. The DFT-S-OFDM may be used not only for the uplink (UL) but also for the downlink (DL).

[0055] The control signal and reference signal processing unit **240** executes processing related to various control signals transmitted and received by the UE **200**, and processing related to various reference signals transmitted and received by the UE **200**.

[0056] Specifically, the control signal and reference signal processing unit **240** receives various control signals transmitted from the gNB **100** via a predetermined control channel, for example, control signals of a radio resource control layer (RRC). The control signal and reference signal processing unit **240** transmits various control signals to the gNB **100** via a predetermined control channel.

[0057] The control signal and reference signal processing unit **240** executes processing using a reference signal (RS) such as a Demodulation Reference Signal (DMRS) and a Phase Tracking Reference Signal (PTRS).

[0058] The DMRS is a reference signal (pilot signal) known between the base station and the terminal for each terminal for estimating a fading channel to be used for data demodulation. The PTRS is a reference signal for each terminal for estimating phase noise, which is a problem in a high frequency band.

[0059] In addition to the DMRS and the PTRS, the reference signal may include a Channel State Information-Reference Signal (CSI-RS), a Sounding Reference Signal (SRS), and a Positioning Reference Signal (PRS) for position information.

[0060] The channel also includes a control channel and a data channel. The control channel includes Physical Downlink Control Channel (PDCCH), Physical Uplink Control Channel (PUCCH), Random Access Channel (RACH), Downlink Control Information (DCI) including Random Access Radio Network Temporary Identifier (RA-RNTI), and Physical Broadcast Channel (PBCH).

[0061] The data channel further includes Physical Downlink Shared Channel (PDSCH), Physical Uplink Shared Channel (PUSCH), or the like. The data means data transmitted via the data channel. The data channel may be read as a shared channel.

[0062] Here, the control signal and reference signal processing unit **240** may receive Downlink

Control Information (DCI). The DCI includes fields for storing DCI Formats, Carrier indicator (CI), BWP indicator, Frequency Domain Resource Assignment (FDRA), Time Domain Resource Assignment (TDRA), Modulation and Coding Scheme (MCS), HARQ Process Number (HPN), New Data Indicator (NDI), Redundancy Version (RV), or the like as existing fields.

[0063] A value stored in a DCI Format field is an information element that specifies the format of the DCI. A value stored in a CI field is an information element that specifies the CC to which the DCI is applied. A value stored in a BWP indicator field is an information element that specifies the BWP to which the DCI is applied. The BWP that can be specified by the BWP indicator is set by the information element (BandwidthPart-Config) included in a RRC message. A value stored in a FDRA field is an information element that specifies a frequency domain resource to which the DCI is applied. The frequency domain resource is specified by the value stored in the FDRA field and the information element (RA Type) included in the RRC message. A value stored in a TDRA field is an information element that specifies a time domain resource to which the DCI is applied. The time domain resource is specified by a value stored in the TDRA field and an information element (pdsch-TimeDomainAllocationList, pusch-TimeDomainAllocationList) included in the RRC message. The time domain resource may be specified by a value stored in the TDRA field and a default table. A value stored in an MCS field is an information element that specifies the MCS to which the DCI is applied. The MCS is specified by the value stored in the MCS and an MCS table. The MCS table may be specified by an RRC message or by RNTI scrambling. A value stored in an HPN field is an information element that specifies a HARQ Process to which the DCI is applied. A value stored in the NDI is an information element that specifies whether the data to which the DCI is applied is initial transmission data. A value stored in an RV field is an information element that specifies the redundancy of the data to which the DCI is applied.

[0064] The encoding/decoding unit **250** executes data division/concatenation, channel coding/decoding, and the like for each predetermined communication destination (gNB **100** or another gNB).

[0065] Specifically, the encoding/decoding unit **250** divides the data output from the data transmission and reception unit **260** into predetermined sizes, and executes channel coding on the divided data. The encoding/decoding unit **250** decodes the data output from the modulation and demodulation unit **230** and concatenates the decoded data.

[0066] The data transmission and reception unit **260** transmits and receives Protocol Data Units (PDUs) and Service Data Units (SDUs). Specifically, the data transmission and reception unit **260** assembles/disassembles PDUs/SDUs in a plurality of layers (such as media access control layer (MAC), radio link control layer (RLC), and packet data convergence protocol layer (PDCP)). The data transmission and reception unit **260** executes data error correction and retransmission control based on Hybrid Automatic Repeat Request (HARQ).

[0067] In the embodiment, the data transmission and reception unit **260** may configure a communication unit that executes intermittent communication in which communication is executed in a periodic first section, and communication is not executed in a second section other than the first section. The communication unit may include a control signal and reference signal processing unit **240**.

[0068] The intermittent communication may be referred to as Connected mode Discontinuous Reception (CDRX). The CDRX may include an existing CDRX or a CDRX introduced for Extended Reality (XR). The first section may be called an active section, and the second section may be called a sleep section. The first section may be called an on-duration, and the second section may be called an off-duration. The first section may be a section in which an on-duration timer is running, and the second section may be a section in which the on-duration timer is running.

[0069] The control unit **270** controls the functional blocks that configure the UE **200**. In the embodiment, the control unit **270** configures a control unit that executes extension of the first section or shortening of the first section when a specific condition is satisfied.

[0070] For example, the control unit **270** may execute extension of the first section when a first condition including at least one of a condition that first communication is not executed in the first section and a condition that a notification instructing extension of the first section is received is satisfied. The control unit **270** may execute shortening of the first section when a second condition including at least one of a condition that second communication is executed in the first section and a condition that a notification instructing shortening of the first section is received is satisfied. Details of the first section and the second section will be described later.

[0071] Second, the functional block configuration of the gNB **100** will be described.

[0072] FIG. **5** is a functional block configuration diagram of the gNB **100**. As illustrated in FIG. **5**, the gNB **100** includes a receiving unit **110**, a transmitting unit **120**, and a controlling unit **130**.

[0073] The receiving unit **110** receives various signals from the UE **200**. The receiving unit **110** may receive UL signals via PUCCH or PUSCH.

[0074] The transmitting unit **120** transmits various signals to the UE **200**. The transmitting unit **120** may transmit DL signals via PDCCH or PDSCH.

[0075] In the embodiment, the receiving unit **110** and the transmitting unit **120** configure a communication unit that executes intermittent communication in which communication is executed in a periodic first section, and communication is not executed in a second section other than the first section.

[0076] The control unit **130** controls the gNB **100**. In the embodiment, the control unit **130** configures a control unit that assumes that the UE **200** executes extension of the first section or shortening of the first section when a specific condition is satisfied.

(3) Operation Examples

[0077] Next, operation examples of the embodiment will be described. Hereinafter, the first section will be referred to as the active section, and the second section will be referred to as the sleep section. Hereinafter, extension of the active section and shortening of the active section are described separately.

(3.1) Extension of the Active Section

(3.1.1) Problems related to Extension of the Active Section

[0078] Here, description will be made by taking traffic related to Extended Reality (XR) as an example. As illustrated in FIG. **6**, it is assumed that XR traffic is periodically transmitted depending on frames per second (FPS).

[0079] On the other hand, depending on the jitter of the XR traffic, there is a possibility that the XR traffic arrives in the sleep section that is outside the active section, and there is a possibility that the XR traffic cannot be received, causing a delay in the XR traffic. Such a delay can also be caused by a difference between the period of the active section (for example, such as 10 ms and 20 ms) and the period of the XR traffic (for example, 16.67 ms, 8.33 ms).

[0080] Under such a background, the inventors, as a result of careful study, have found that by introducing an operation of extending the active section, the delay in the traffic can be suppressed without making the length of the active section longer than necessary.

(3.1.2) Operation Example 1 Related to Extension of the Active Section

[0081] Operation Example 1 related to extension of the active section will be described below. As illustrated in FIG. **7**, the UE **200** continuously extends the active section when the first condition is satisfied. In other words, the UE **200** extends the active section (on-duration timer) set in the UE **200**. That is, an extended portion of the active section may be set without a sleep section after the active section that is set in the UE **200**. The first condition is an example of a specific condition. The first condition may include a condition (hereinafter referred to as Condition 1A) that the first communication is not executed in the active section. The first communication may include one or more communications selected from the following communications.

[0082] Example 1. Reception of DCI (PDCCH)

[0083] Example 2. Reception of scheduling information addressed to the UE **200** (itself)

[0084] Example 3. Reception of scheduling information on XR traffic addressed to the UE **200** (itself)

[0085] Example 4. Reception of data addressed to the UE **200** (itself), which may include reception of data via Semi-Persistent Scheduling (SPS) or dynamic scheduling

[0086] Example 5. Reception of data regarding XR traffic addressed to the UE **200** (itself), which may include receiving data via SPS or dynamic scheduling

[0087] Example 6. Transmission of UL (such as PUSCH and PUCCH) from the UE **200** (itself)

[0088] Example 7. Transmission of a PUSCH with a configured grant

[0089] Example 8. Transmission of an ACK for data addressed for the UE **200** (itself)

[0090] Example 9. Transmission of an ACK for data about XR traffic addressed for the UE **200** (itself)

[0091] Further, Condition 1A may include the following options.

[0092] In Option 1, Condition 1A may include a condition that the first communication is not executed a specific number of times (for example, X times) in the active section. That is, the UE **200** may extend the active section if the number of times of the first communications in the active section is less than X times. The UE **200** may not extend the active section if the number of times of first communications in the active section is X times or more.

[0093] The specified number of times (X times) may be notified from the gNB **100**, or may be defined in advance in the radio communication system **10**. The specified number of times (X times) may be determined separately for DL reception and UL transmission, may be determined for each type of the first communication, or may be determined for the first communication as a whole.

[0094] In Option 2, Condition 1A may include a condition that the first communication of a specific data size (for example, Y bytes) is not executed in the active section. That is, the UE **200** may extend the active section when the data size of the first communication is less than Y bytes in the active section. The UE **200** may not extend the active section when the data size of the first communication is more than or equal to Y bytes in the active section.

[0095] The specific data size (Y bytes) may be notified from the gNB **100** or may be predefined in the radio communication system **10**. The specific data size (Y bytes) may be separately determined for DL reception and UL transmission, may be determined for each type of the first communication, or may be determined for the first communication as a whole.

[0096] In Option 3, Options 1 and 2 may be combined. For example, Condition 1A may include a condition that the first communication is not executed a specific number of times (X times) in the active section and that the first communication of a specific data size (Y bytes) is not executed in the active section.

[0097] When the first communication is the reception of data related to XR traffic, information indicating whether the data is XR traffic may be notified. Such information may be a flag. Such information may be included in scheduling information related to XR traffic or in data related to XR traffic.

[0098] In Operation Example 1, extension of the active section may be executed by the following options.

[0099] In Option 1, the length of the active section after extension may be notified from the gNB **100** to the UE **200**. The length of the active section after extension may be determined by a relative value to the length of the active section set in the UE **200**. The relative value represents the length of the extended portion of the active section, and may be determined in slots (XX slots) or milliseconds (YY ms). The length of the active section after extension may be determined by an absolute value of a total length of the active section after extension. The absolute value may be determined in slots (XX slots) or milliseconds (YY ms).

[0100] In Option 2, the UE **200** may extend the active section until the first communication described above is executed. In other words, the UE **200** may extend the active section until Condition 1A described above is no longer satisfied.

(3.1.3) Operation Example 2 related to Extension of the Active Section

[0101] Operation Example 2 related to extension of the active section will be described below. As illustrated in FIG. 8, the UE 200 extends the active section discontinuously when the first condition is satisfied. In other words, the UE 200 sets a discontinuous active section (extended portion) separately from the active section (on-duration timer) set in the UE 200. The first condition is an example of a specific condition. That is, an extended portion of the active section may be set after the active section set in the UE 200 with a sleep section in between. The first condition may include Condition A as in the operation example.

[0102] In Operation Example 2, a length of the sleep section between the active section that is set in the UE 200 and the extended portion of the active section may be notified from the gNB 100 or may be predefined in the radio communication system 10. The length of the extended portion of the active section may be notified from the gNB 100 or may be predefined in the radio communication system 10.

(3.1.4) Operation Example 3 Related to Extension of the Active Section

[0103] Operation Example 3 related to extension of the active section will be described. The UE 200 continuously extends the active section when the first condition is satisfied. In other words, the UE 200 extends the active section (on-duration timer) set in the UE 200. That is, the extended portion of the active section may be set without a sleep section after the active section that is set in the UE 200.

[0104] Here, the first condition may include a condition (hereinafter referred to as Condition 1B) that a notification instructing extension of the active section is received. The notification instructing extension of the active section may be executed according to the following options. The notification instructing extension of the active section may be executed by the DCI, the MAC, or the RRC.

[0105] In Option 1, as illustrated in FIG. 9, the UE 200 may receive a notification instructing extension of the active section in the active section. For example, the UE 200 may extend the active section for which a notification instructing extension of the active section is received.

[0106] In Option 2, the UE 200 may receive a notification instructing extension of the active section in a specific DCI format (for example, DCI format 2_6) receivable in the sleep section. For example, the UE 200 may extend the active section immediately after receiving the DCI format 2_6.

[0107] In Option 3, derived from Options 1 and 2, the notification instructing extension of the active section may include information specifying one or more active sections to be extended. For example, the one or more active sections to be extended may include active sections other than the active section for which the notification instructing extension of the active section is received. The one or more active sections to be extended may include active sections other than the active section immediately after receiving the DCI format 2_6.

[0108] In Operation Example 3, extension of the active section may be executed by the following options.

[0109] In Option 1, the length of the active section after extension may be notified from gNB 100 to UE 200. The notification of the length of the active section after extension may be executed together with the notification instructing extension of the active section, or may be executed before the notification instructing extension of the active section. The length of the active section after extension may be determined by a relative value to the length of the active section set in UE 200. The relative value represents the length of the extended portion of the active section, and may be determined in slots (XX slots) or milliseconds (YY ms). The length of the active section after extension may be determined by an absolute value of a total length of the active section after extension. The absolute value may be determined in slots (XX slots) or milliseconds (YY ms).

[0110] In Option 2, the UE 200 may extend the active section until the first communication described above is executed. In other words, the UE 200 may extend the active section until

Condition 1A described above is no longer satisfied.

(3.1.5) Operation Example 4 related to Extension of the Active Section

[0111] Operation Example 4 related to extension of the active section will now be described. As illustrated in FIG. 10, the UE 200 extends the active section discontinuously when the first condition is satisfied. In other words, the UE 200 sets a discontinuous active section (extended portion) separately from the active section (on-duration timer) set in the UE 200. The first condition is an example of a specific condition. That is, an extended portion of the active section may be set after the active section that set in the UE 200 with the sleep section in between. The first condition may include Condition B as in the operation example.

[0112] In Operation Example 4, the length of the sleep section between the active section in the UE 200 and the extended portion of the active section may be notified from the gNB 100 or may be predefined in the radio communication system 10. The notification of the length of the sleep section may be executed together with the notification instructing extension of the active section, or may be executed before the notification instructing extension of the active section. The length of the extended portion of the active section may be notified from the gNB 100, or may be predefined in the radio communication system 10. The notification of the length of the extended portion of the active section may be executed together with the notification instructing extension of the active section, or may be executed before the notification instructing extension of the active section.

(3.2) Shortening of the Active Section

(3.2.1) Problems Related to Shortening of the Active Section

[0113] Here, description will be made by taking traffic related to XR as an example. As illustrated in FIG. 11, it is assumed that XR traffic is periodically transmitted depending on frame per second (FPS).

[0114] On the other hand, depending on the jitter of XR traffic, XR traffic may arrive in the first half of the active section, and power consumption in the active section after receiving XR traffic may be wasted.

[0115] Under such a background, the inventors, as a result of careful study, have found that introducing an operation of shortening the active section can further reduce power consumption while suppressing traffic delay.

(3.2.2) Operation Example 1 Related to Shortening of the Active Section

[0116] Operation Example 1 related to shortening of the active section will be described below. The UE 200 shortens the active section when the second condition is satisfied, as illustrated in FIG. 12. In other words, the UE 200 transitions to a sleep mode without waiting for completion of the active section (on-duration timer) set in the UE 200. The second condition is an example of a specific condition. The second condition may include a condition (hereinafter referred to as Condition 2A) that the second communication is executed in the active section. The second communication may include one or more communications selected from the following communications.

[0117] Example 1. Reception of data addressed to the UE 200 (itself), which may include reception of data via SPS or dynamic scheduling)

[0118] Example 2. Reception of data related to XR traffic addressed to the UE 200 (itself), which may include reception of data via SPS or dynamic scheduling

[0119] Example 3. Transmission of UL (such as PUSCH, PUCCH) from the UE 200 (itself)

[0120] Example 4. Transmission of PUSCH with a configured grant

[0121] Example 5. Transmission of ACK for data addressed for the UE 200 (itself)

[0122] Example 6. Transmission of ACK for data on XR traffic addressed for the UE 200 (itself)

[0123] Further, Condition 2A may include the following options.

[0124] In Option 1, Condition 2A may include a condition that the second communication is executed a specific number of times (for example, X times) in the active section. That is, the UE 200 may shorten the active section when the number of times of the second communication in the active section is X times or more. The UE 200 may not shorten the active section when the number

of times of the second communication in the active section is less than X times.

[0125] The specific number of times (X times) may be notified from the gNB **100**, or may be defined in advance in the radio communication system **10**. The specific number of times (X times) may be determined separately for DL reception and UL transmission, may be determined for each type of the second communication, or may be determined for the second communication as a whole.

[0126] In Option 2, Condition 2A may include a condition that the second communication of a specific data size (for example, Y bytes) is executed in the active section. That is, the UE **200** may shorten the active section when the data size of the second communication is more than or equal to Y bytes in the active section. The UE **200** may not shorten the active section when the data size of the second communication is less than Y bytes in the active section.

[0127] The specific data size (Y bytes) may be notified from the gNB **100** or may be predefined in the radio communication system **10**. The specific data size (Y bytes) may be separately determined for DL reception and UL transmission, may be determined for each type of the second communication, or may be determined for the second communication as the whole.

[0128] In Option 3, Options 1 and 2 may be combined. For example, Condition 2A may include a condition that the second communication is executed a specific number of times (X times) in the active section, and that the second communication of a specific data size (Y bytes) is executed in the active section.

[0129] When the second communication is the reception of data related to XR traffic, information indicating whether or not the data is XR traffic may be notified. Such information may be a flag. Such information may be included in scheduling information related to XR traffic or in data related to XR traffic.

[0130] In Operation Example 1, after Condition 2A is satisfied, the UE **200** may shorten the active section and transition to a sleep mode. Here, the time from when Condition 2A is satisfied until transition to the sleep mode is made may be notified from the gNB **100** to the UE **200**, or may be predefined in the radio communication system **10**.

(3.2.3) Operation Example 2 Related to Shortening of the Active section

[0131] Operation Example 2 related to shortening of the active section will be described below. The UE **200** shortens the active section when the second condition is satisfied. In other words, the UE **200** transitions to the sleep mode without waiting for completion of the active period (on-duration timer) set in the UE **200**.

[0132] Here, the second condition may include a condition (hereinafter referred to as Condition 2B) that a notification instructing shortening of the active period is received. As illustrated in FIG. **13**, the UE **200** may receive a notification instructing shortening of the active period in the active period. For example, the UE **200** may shorten the active period for which a notification instructing shortening of the active period is received. The notification instructing shortening of the active period may be executed by the following options.

[0133] In Option 1, the notification instructing shortening of the active period may be included in the PDSCH for XR traffic. The notification instructing shortening of the active period may be a notification of an end of a burst related to XR traffic.

[0134] In Option 2, the notification instructing shortening of the active section may be executed by the DCI, the MAC, or the RRC. The DCI may be DCI that includes scheduling information, or may be DCI that does not include scheduling information.

[0135] In Option 3, the UE **200** may receive the notification instructing shortening of the active section in a specific DCI format (for example, DCI format 2_6) that can be received in the sleep section. For example, the UE **200** may shorten the active section immediately after receiving the DCI format 2_6.

[0136] In Option 4, derived from Options 1 to 3, the notification instructing shortening of the active section may include information specifying one or more active sections to be shortened. For

example, the one or more active sections to be shortened may include active sections other than the active section for which the notification instructing shortening of the active section is received. The one or more active sections to be shortened may include active sections other than the active section immediately after receiving the DCI format 2_6.

[0137] In Operation Example 2, the UE **200** may shorten the active section and transition to the sleep mode after the condition 2B described above is satisfied. Here, the time from when the condition 2B is satisfied until the transition to the sleep mode is made may be notified from the gNB **100** to the UE **200**, or may be predefined in the radio communication system **10**. When Option 3 or Option 4 is applied, the UE **200** may shorten the active section and transition to the sleep mode after the Condition 2A above is satisfied in the one or more active sections to be shortened. Here, the time from when the condition 2A is satisfied until the transition to the sleep mode is made may be notified from the gNB **100** to the UE **200**, or may be predefined in the radio communication system **10**.

(4) Operation and Effect

[0138] In the embodiments, the UE **200** extends the active section or shortens the active section when a specific condition is satisfied. According to such a configuration, it is possible to reduce power consumption while suppressing traffic delay by utilizing the CDRX, as appropriate.

[0139] For example, the UE **200** may extend the active section when a first condition is satisfied, including at least one of a condition that the first communication is not executed in the active section and a condition that a notification instructing extension of the active section is received. According to this configuration, when the CDRX is utilized, the delay of the traffic can be suppressed while the power consumption is reduced.

[0140] For example, the UE **200** may execute shortening of the active section when a second condition including at least one of a condition that the second communication is executed in the active section and a condition that a notification instructing shortening of the active section is received is satisfied. According to this configuration, when the CDRX is utilized, the power consumption can be further reduced while the delay of the traffic is suppressed.

(5) Other Embodiments

[0141] Although the contents of the present invention have been described above with reference to the embodiments, it is obvious to those skilled in the art that the present invention is not limited to these descriptions and that various modifications and improvements are possible.

[0142] Although not specifically mentioned in the above disclosure, at least one operation of extending the active section or shortening the active section may be applied to communications related to XR or may be applied to communications other than XR. For example, at least one operation of extending the active section or shortening the active section may be applied to applications in which UL or DL communications occur periodically.

[0143] Although not specifically mentioned in the above disclosure, the following UE capability may be defined. The following UE capability may be reported from the UE **200** to the gNB **100**.

[0144] The UE Capability may include an information element indicating whether or not the UE capability has a function to support extension of the active section. The UE capability may include an information element indicating whether or not the UE Capability has a function to support any one or more of Operation Example 1 to Operation Example 4 related to extension of the active section. The UE capability may include an information element indicating whether or not the UE capability has a function to support any one or more of the options related to extension of the active section.

[0145] The UE Capability may include an information element indicating whether or not the UE Capability has a function to support shortening of the active section. The UE Capability may include an information element indicating whether or not the UE Capability has a function to support any one or more of Operation Example 1 and Operation Example 2 related to shortening of the active section. The UE Capability may include an information element indicating whether the

UE has a function to support any one or more of options for shortening of the active section.

[0146] The UE Capability may include an information element related to the time (sleep transition time) from when the second condition (Condition 2A or Condition 2B) is satisfied until the transition to the sleep mode is made. Such information element may be any information element that explicitly or implicitly indicates the Sleep transition time.

[0147] Although not specifically mentioned in the foregoing disclosure, information to activate, enable, or set at least one operation (specific operation) of extending the active section and shortening the active section may be notified from the gNB **100** to the UE **200**. The UE **200** may execute the specific operation when the specific operation is activated, enabled, or set.

[0148] Although not specifically mentioned in the foregoing disclosure, information to deactivate, disable, or cancel at least one operation (specific operation) of extending the active section and shortening the active section may be notified from the gNB **100** to the UE **200**. The UE **200** may not execute a specific operation when the specific operation is deactivated, disabled, or canceled.

[0149] In the above disclosure, terms such as configure, activate, update, indicate, enable, specify, and select may be read interchangeably. Similarly, terms such as link, associate, correspond, and map may be read interchangeably, and terms such as allocate, assign, monitor, and map may be read interchangeably.

[0150] In addition, terms such as specific, dedicated, UE-specific, and UE-dedicated may be read interchangeably. Similarly, terms such as common, shared, group-common, UE-common, and UE-shared may be read interchangeably.

[0151] The block diagram (FIGS. **4** and **5**) used in the description of the above-described embodiment illustrates blocks in units of functions. Those functional blocks (components) can be realized by any combination of at least one of hardware and software. A realization method for each functional block is not particularly limited. That is, each functional block may be realized by using one device combined physically or logically. Alternatively, two or more devices separated physically or logically may be directly or indirectly connected (for example, wired, or wireless) to each other, and each functional block may be realized by these plural devices. The functional blocks may be realized by combining software with the one device or the plural devices mentioned above.

[0152] Functions include judging, deciding, determining, calculating, computing, processing, deriving, investigating, searching, confirming, receiving, transmitting, outputting, accessing, resolving, selecting, choosing, establishing, comparing, assuming, expecting, considering, broadcasting, notifying, communicating, forwarding, configuring, reconfiguring, allocating (mapping), assigning, and the like. However, the functions are not limited thereto. For example, a functional block (component) that makes a transmitting function work may be called a transmitting unit or a transmitter. For any of the above, as described above, the realization method is not particularly limited.

[0153] Further, the above-described gNB **100** and UE **200** (the device) may function as a computer that performs processing of a radio communication method of the present disclosure. FIG. **14** is a diagram illustrating an example of a hardware configuration of the device. As illustrated in FIG. **14**, the device may be configured as a computer device including a processor **1001**, a memory **1002**, a storage **1003**, a communication device **1004**, an input device **1005**, an output device **1006**, a bus **1007**, and the like.

[0154] Furthermore, in the following description, the term “device” can be read as meaning circuit, device, unit, or the like. The hardware configuration of the device may include one or more devices illustrated in the figure or may not include some of the devices.

[0155] Each of the functional blocks of the device (FIG. **4**) is implemented by means of any of hardware elements of the computer device or a combination of the hardware elements.

[0156] Each function in the device is realized by loading predetermined software (programs) on hardware such as the processor **1001** and the memory **1002** so that the processor **1001** performs

arithmetic operations to control communication via the communication device **1004** and to control at least one of reading and writing of data on the memory **1002** and the storage **1003**.

[0157] The processor **1001** operates, for example, an operating system to control the entire computer. The processor **1001** may be configured with a central processing unit (CPU) including interfaces with peripheral devices, control devices, arithmetic devices, registers, and the like.

[0158] Moreover, the processor **1001** reads a program (program code), a software module, data, and the like from at least one of the storage **1003** and the communication device **1004** into the memory **1002**, and executes various processes according to these. As the program, a program causing the computer to execute at least part of the operation described in the above embodiment is used. Alternatively, various processes described above may be executed by one processor **1001** or may be executed simultaneously or sequentially by two or more processors **1001**. The processor **1001** may be implemented by using one or more chips. Alternatively, the program may be transmitted from a network via a telecommunication line.

[0159] The memory **1002** is a computer readable recording medium and may be configured, for example, with at least one of a Read Only Memory (ROM), Erasable Programmable ROM (EPROM), Electrically Erasable Programmable ROM (EEPROM), Random Access Memory (RAM), and the like. The memory **1002** may be referred to as a register, cache, main memory (main storage device), and the like. The memory **1002** may store therein programs (program codes), software modules, and the like that can execute the method according to one embodiment of the present disclosure.

[0160] The storage **1003** is a computer readable recording medium. Examples of the storage **1003** include at least one of an optical disk such as Compact Disc ROM (CD-ROM), a hard disk drive, a flexible disk, a magneto-optical disk (for example, a compact disk, a digital versatile disk, Blu-ray (registered trademark) disk), a smart card, a flash memory (for example, a card, a stick, a key drive), a floppy (registered trademark) disk, a magnetic strip, and the like. The storage **1003** may be referred to as an auxiliary storage device. The recording medium may be, for example, a database including at least one of the memory **1002** and the storage **1003**, a server, or other appropriate medium.

[0161] The communication device **1004** is hardware (transmission/reception device) capable of performing communication between computers via at least one of a wired network and a wireless network. The communication device **1004** is also referred to as, for example, a network device, a network controller, a network card, a communication module, and the like.

[0162] The communication device **1004** may include a high-frequency switch, a duplexer, a filter, a frequency synthesizer, and the like in order to realize, for example, at least one of Frequency Division Duplex (FDD) and Time Division Duplex (TDD).

[0163] The input device **1005** is an input device (for example, a keyboard, a mouse, a microphone, a switch, a button, a sensor, and the like) that accepts input from the outside. The output device **1006** is an output device (for example, a display, a speaker, an LED lamp, and the like) that outputs data to the outside. Note that, the input device **1005** and the output device **1006** may have an integrated configuration (for example, a touch screen).

[0164] Also, the respective devices such as the processor **1001** and the memory **1002** are connected to each other with the bus **1007** for communicating information. The bus **1007** may be constituted by a single bus or may be constituted by different buses for each device-to-device.

[0165] Further, the device may be configured to include hardware such as a microprocessor, a Digital Signal Processor (DSP), an Application Specific Integrated Circuit (ASIC), a Programmable Logic Device (PLD), and a Field Programmable Gate Array (FPGA). Some or all of these functional blocks may be realized by means of this hardware. For example, the processor **1001** may be implemented by using at least one of the above-described items of hardware.

[0166] Further, notification of information is not limited to that in the aspect/embodiment described in the present disclosure, and may be performed by using other methods. For example, notification

of information may be performed by physical layer signaling (for example, Downlink Control Information (DCI), Uplink Control Information (UCI), higher layer signaling (for example, RRC signaling, Medium Access Control (MAC) signaling), broadcast information (Master Information Block (MIB), System Information Block (SIB)), other signals, or a combination thereof. The RRC signaling may also be referred to as an RRC message, for example, or may be an RRC Connection Setup message, an RRC Connection Reconfiguration message, or the like.

[0167] Each aspect/embodiment described in the present disclosure may be applied to at least one of Long Term Evolution (LTE), LTE-Advanced (LTE-A), SUPER 3G, IMT-Advanced, the 4th generation mobile communication system (4G), the 5th generation mobile communication system (5G), Future Radio Access (FRA), New Radio (NR), W-CDMA (registered trademark), GSM (registered trademark), CDMA2000, Ultra Mobile Broadband (UMB), IEEE 802.11 (Wi-Fi (registered trademark)), IEEE 802.16 (WiMAX (registered trademark)), IEEE 802.20, ultra-wideband (UWB), Bluetooth (registered trademark), a system using any other appropriate system, and a next-generation system that is expanded based on these. Further, a plurality of systems may be combined (for example, a combination of at least one of LTE and LTE-A with 5G) and applied.

[0168] The order of the processing procedures, sequences, flowcharts, and the like of each aspect/embodiment described in the present disclosure may be exchanged as long as there is no contradiction. For example, the methods described in the present disclosure present the elements of the various steps by using an exemplary order and are not limited to the presented specific order.

[0169] The specific operation that is performed by a base station in the present disclosure may be performed by its upper node in some cases. In a network constituted by one or more network nodes having a base station, it is obvious that the various operations performed for communication with the terminal may be performed by at least one of the base station and other network nodes other than the base station (for example, an MME, an S-GW, and the like may be considered, but there is not limited thereto). In the above, an example in which there is one network node other than the base station is explained; however, a combination of a plurality of other network nodes (for example, an MME and an S-GW) may be used.

[0170] Information and signals (information and the like) can be output from a higher layer (or lower layer) to a lower layer (or higher layer). These may be input and output via a plurality of network nodes.

[0171] The input/output information may be stored in a specific location (for example, a memory) or may be managed in a management table. The information to be input/output can be overwritten, updated, or added. The information may be deleted after outputting. The inputted information may be transmitted to another device.

[0172] The determination may be made by using a value (0 or 1) represented by one bit, by truth-value (Boolean: true or false), or by comparison of numerical values (for example, comparison with a predetermined value).

[0173] Each of the aspects/embodiment described in the present disclosure may be used separately or in combination, or may be switched in accordance with the execution. In addition, notification of predetermined information (for example, notification of “is X”) is not limited to being performed explicitly, and it may be performed implicitly (for example, without notifying the predetermined information).

[0174] Regardless of being referred to as software, firmware, middleware, microcode, hardware description language, or some other name, software should be interpreted broadly to mean instructions, an instruction set, code, a code segment, program code, a program, a subprogram, a software module, an application, a software application, a software package, a routine, a subroutine, an object, an executable file, an execution thread, a procedure, a function, and the like.

[0175] Further, software, instruction, information, and the like may be transmitted and received via a transmission medium. For example, when software is transmitted from a website, a server, or another remote source by using at least one of a wired technology (a coaxial cable, an optical fiber

cable, a twisted pair cable, a Digital Subscriber Line (DSL), or the like) and a wireless technology (infrared light, microwave, or the like), then at least one of these wired and wireless technologies is included within the definition of the transmission medium.

[0176] Information, signals, or the like described in the present disclosure may be represented by using any of a variety of different technologies. For example, data, an instruction, a command, information, a signal, a bit, a symbol, a chip, or the like that may be mentioned throughout the above description may be represented by a voltage, a current, an electromagnetic wave, a magnetic field or magnetic particles, an optical field or photons, or any combination thereof.

[0177] It should be noted that the terms described in the present disclosure and terms necessary for understanding the present disclosure may be replaced with terms having the same or similar meanings. For example, at least one of a channel and a symbol may be a signal (signaling). A signal may also be a message. Further, a Component Carrier (CC) may be referred to as a carrier frequency, a cell, a frequency carrier, or the like.

[0178] The terms “system” and “network” used in the present disclosure can be used interchangeably.

[0179] Furthermore, information, parameters, and the like described in the present disclosure may be represented by an absolute value, may be represented by a relative value from a predetermined value, or may be represented by corresponding other information. For example, a radio resource may be indicated using an index.

[0180] Names used for the above parameters are not restrictive names in any respect. In addition, formulas and the like using these parameters may be different from those explicitly disclosed in the present disclosure. Since the various channels (for example, a PUCCH, a PDCCH, or the like) and information elements can be identified by any suitable names, the various names allocated to these various channels and information elements shall not be restricted in any way.

[0181] In the present disclosure, the terms such as “base station (Base Station: BS)”, “radio base station”, “fixed station”, “NodeB”, “eNodeB (eNB)”, “gNodeB (gNB)”, “access point”, “transmission point”, “reception point”, “transmission/reception point”, “cell”, “sector”, “cell group”, “carrier”, “component carrier”, and the like can be used interchangeably. A base station may also be referred to with a term such as a macro cell, a small cell, a femtocell, or a pico cell.

[0182] A base station can accommodate one or more (for example, three) cells (also referred to as sectors). In a configuration in which a base station accommodates a plurality of cells, the entire coverage area of the base station can be divided into a plurality of smaller areas. In each of the smaller areas, a communication service can be provided by a base station subsystem (for example, a small base station for indoor use (remote radio head: RRH)).

[0183] The term “cell” or “sector” refers to a part or all of the coverage area of at least one of a base station and a base station subsystem that performs a communication service in this coverage.

[0184] In the present disclosure, a base station transmitting information to a terminal may be interpreted as the base station instructing the terminal to control or operate based on the information.

[0185] In the present disclosure, the terms such as “mobile station (Mobile Station: MS)”, “user terminal”, “user equipment (User Equipment: UE)”, and “terminal” can be used interchangeably.

[0186] A mobile station may be referred to as a subscriber station, a mobile unit, a subscriber unit, a wireless unit, a remote unit, a mobile device, a wireless device, a wireless communication device, a remote device, a mobile subscriber station, an access terminal, a mobile terminal, a wireless terminal, a remote terminal, a handset, a user agent, a mobile client, a client, or some other suitable terms by those skilled in the art.

[0187] At least one of a base station and a mobile station may be called a transmitting device, a receiving device, a communication device, or the like. Note that at least one of a base station and a mobile station may be a device mounted on a moving body, a moving body itself, or the like. The moving body may be a vehicle (for example, a car, an airplane, or the like), an unmanned moving

body (a drone, a self-driving car, or the like), or a robot (manned type or unmanned type). At least one of a base station and a mobile station also includes a device that does not necessarily move during the communication operation. For example, at least one of a base station and a mobile station may be an Internet of Things (IoT) device such as a sensor.

[0188] Also, a base station in the present disclosure may be read as meaning a mobile station (user terminal, hereinafter, the same). For example, each aspect/embodiment of the present disclosure may be applied to a configuration in which communication between a base station and a mobile station is replaced with communication between a plurality of mobile stations (which may be called Device-to-Device (D2D), Vehicle-to-Everything (V2X), or the like). In this case, the mobile station may have the function of a base station. In addition, words such as “uplink” and “downlink” may also be read as meaning words corresponding to inter-terminal communication (for example, “side”). For example, an uplink channel, a downlink channel, or the like may be read as meaning a side channel.

[0189] Similarly, the mobile station in the present disclosure may be read as meaning a base station. In this case, the base station may have the function of the mobile station.

[0190] A radio frame may be composed of one or more frames in the time domain. Each of the one or more frames in the time domain may be referred to as a subframe.

[0191] A subframe may be further composed of one or more slots in the time domain. The subframe may be a fixed time length (for example, 1 ms) independent of the numerology.

[0192] The numerology may be a communication parameter applied to at least one of transmission and reception of a certain signal or channel. The numerology may indicate at least one of, for example, subcarrier spacing (SCS), bandwidth, symbol length, cyclic prefix length, transmission time interval (TTI), the number of symbols per TTI, radio frame configuration, a specific filtering process performed by a transceiver in the frequency domain, a specific windowing process performed by a transceiver in the time domain, and the like.

[0193] A slot may be composed of one or more symbols (Orthogonal Frequency Division Multiplexing (OFDM)) symbols, Single Carrier Frequency Division Multiple Access (SC-FDMA) symbols, and the like) in the time domain. A slot may be a unit of time based on the numerology.

[0194] A slot may include a plurality of minislots. Each minislot may be composed of one or more symbols in the time domain. A minislot may be called a subslot. A minislot may be composed of fewer symbols than slots. A PDSCH (or PUSCH) transmitted in time units greater than the minislot may be referred to as a PDSCH (or PUSCH) mapping type A. A PDSCH (or PUSCH) transmitted using a minislot may be referred to as a PDSCH (or PUSCH) mapping type B.

[0195] Each of a radio frame, subframe, slot, minislot, and symbol represents a time unit for transmitting a signal. A radio frame, subframe, slot, minislot, and symbol may have respectively different names corresponding to them.

[0196] For example, one subframe may be called a transmission time interval (TTI), a plurality of consecutive subframes may be called a TTI, and one slot or one minislot may be called a TTI. That is, at least one of the subframe and TTI may be a subframe (1 ms) in the existing LTE, a period shorter than 1 ms (for example, 1 to 13 symbols), or a period longer than 1 ms. Note that, a unit representing TTI may be called a slot, a minislot, or the like instead of a subframe.

[0197] Here, a TTI refers to the minimum time unit of scheduling in radio communication, for example. For example, in the LTE system, the base station performs scheduling for allocating radio resources (frequency bandwidth, transmission power, and the like that can be used in each user terminal) to each user terminal in units of TTI. The definition of TTI is not limited to this.

[0198] A TTI may be a transmission time unit such as a channel-coded data packet (transport block), a code block, or a code word, or may be a processing unit such as scheduling or link adaptation. When a TTI is given, a time interval (for example, the number of symbols) in which a transport block, a code block, a code word, and the like are actually mapped may be shorter than TTI.

[0199] When one slot or one minislot is called a TTI, one or more TTIs (that is, one or more slots or one or more minislots) may be the minimum time unit of the scheduling. The number of slots (minislot number) constituting the minimum time unit of the scheduling may be controlled.

[0200] A TTI having a time length of 1 ms may be referred to as an ordinary TTI (TTI in LTE Rel. 8-12), a normal TTI, a long TTI, an ordinary subframe, a normal subframe, a long subframe, a slot, and the like. A TTI shorter than the ordinary TTI may be referred to as a shortened TTI, a short TTI, a partial TTI (partial or fractional TTI), a shortened subframe, a short subframe, a minislot, a subslot, a slot, and the like.

[0201] In addition, a long TTI (for example, ordinary TTI, subframe, and the like) may be read as meaning a TTI having a time length exceeding 1 ms, and a short TTI (for example, shortened TTI) may be read as meaning a TTI having a TTI length of less than a TTI length of a long TTI and a TTI length of 1 ms or more.

[0202] A resource block (RB) is a resource allocation unit in the time domain and the frequency domain, and may include one or more consecutive subcarriers in the frequency domain. The number of subcarriers included in the RB may be the same regardless of the numerology, and may be 12, for example. The number of subcarriers included in the RB may be determined based on the numerology.

[0203] Further, the time domain of an RB may include one or more symbols, and may have a length of 1 slot, 1 minislot, 1 subframe, or 1 TTI. Each TTI, subframe, or the like may be composed of one or more resource blocks.

[0204] Note that, one or more RBs may be called a physical resource block (PRB), a subcarrier group (SCG), a resource element group (REG), a PRB pair, a RB pair, and the like.

[0205] A resource block may be configured by one or more resource elements (REs). For example, one RE may be a radio resource domain of one subcarrier and one symbol.

[0206] A bandwidth part (BWP) (which may be called a partial bandwidth or the like) may represent a subset of consecutive common resource blocks (RBs) for a certain numerology in a certain carrier. Here, the common RB may be specified by an index of the RB based on the common reference point of the carrier. A PRB may be defined in a certain BWP and numbered within that BWP.

[0207] A BWP may include a BWP for UL (UL BWP) and a BWP for DL (DL BWP). One or more BWPs may be configured in one carrier for the UE.

[0208] At least one of the configured BWPs may be active, and the UE does not have to expect to transmit and receive predetermined signals/channels outside the active BWP. Note that “cell”, “carrier”, and the like in this disclosure may be read as meaning “BWP”.

[0209] The above-described structures such as a radio frame, a subframe, a slot, a minislot, and a symbol are merely examples. For example, structures such as the number of subframes included in a radio frame, the number of slots per subframe or radio frame, the number of minislots included in a slot, the number of symbols and RBs included in a slot or minislot, the number of subcarriers included in RBs, and the number of symbols included in a TTI, a symbol length, the cyclic prefix (CP) length, and the like can be changed in various manner.

[0210] The terms “connected”, “coupled”, or any variations thereof mean any direct or indirect connection or coupling between two or more elements, and can include that one or more intermediate elements are present between two elements that are “connected” or “coupled” to each other. The coupling or connection between the elements may be physical, logical, or a combination thereof. For example, “connection” may be read as meaning “access”. In the present disclosure, two elements can be “connected” or “coupled” to each other by using at least one of one or more wires, one or more cables, and one or more printed electrical connections, and as some non-limiting and non-exhaustive examples, by using electromagnetic energy having wavelengths in the radio frequency domain, a microwave region, and a light (both visible and invisible) region, and the like.

[0211] A reference signal may be abbreviated as RS and may be called a pilot according to

applicable standards.

[0212] As used in the present disclosure, the phrase “based on” does not mean “based only on” unless explicitly stated otherwise. In other words, the phrase “based on” means both “based only on” and “based at least on”.

[0213] “Means” in the configuration of each device above may be replaced with “unit”, “circuit”, “device”, and the like.

[0214] Any reference to elements using a designation such as “first”, “second”, or the like used in the present disclosure generally does not limit the amount or order of those elements. Such designations can be used in the present disclosure as a convenient method to distinguish between two or more elements. Thus, the reference to the first and second elements does not imply that only two elements can be adopted, or that the first element has to precede the second element in some or the other manner.

[0215] In the present disclosure, the used terms “include”, “including”, and variants thereof are intended to be inclusive in a manner similar to the term “comprising”. Furthermore, the term “or” used in the present disclosure is intended not to be an exclusive-OR.

[0216] Throughout the present disclosure, for example, during translation, if articles such as a, an, and the in English are added, the present disclosure may include that a noun following these articles is used in plural.

[0217] As used in this disclosure, the term “determining” may encompass a wide variety of actions. “determining” includes deeming that determining has been performed by, for example, judging, calculating, computing, processing, deriving, investigating, searching (looking up, search, inquiry) (for example, searching in a table, database, or another data structure), ascertaining, and the like. In addition, “determining” can include deeming that determining has been performed by receiving (for example, receiving information), transmitting (for example, transmitting information), inputting (input), outputting (output), access (accessing) (for example, accessing data in a memory), and the like. In addition, “determining” can include deeming that determining has been performed by resolving, selecting, choosing, establishing, comparing, the like. and That is, “determining” may include deeming that “determining” regarding some action has been performed. Moreover, “determining” may be read as meaning “assuming”, “expecting”, “considering”, and the like.

[0218] In the present disclosure, the wording “A and B are different” may mean “A and B are different from each other”. It should be noted that the wording may mean “A and B are each different from C”. Terms such as “separate”, “couple”, or the like may also be interpreted in the same manner as “different”.

[0219] FIG. 15 shows a configuration example of a vehicle **2001**. As shown in FIG. 15, the vehicle **2001** includes a drive **2002**, a steering **2003**, an accelerator pedal **2004**, a brake pedal **2005**, a shift lever **2006**, left and right front wheels **2007**, left and right rear wheels **2008**, an axle **2009**, an electronic controller **2010**, various sensors **2021** to **2029**, an information service unit **2012**, and a communication module **2013**.

[0220] Examples of the drive **2002** include, an engine, a motor, and a hybrid of an engine and a motor.

[0221] The steering **2003** includes at least a steering wheel (also called a handle) and steers at least one of the front and rear wheels based on an operation of a steering wheel operated by a user.

[0222] The electronic controller **2010** includes a microprocessor **2031**, a memory (ROM, RAM) **2032**, and a communication port (IO port) **2033**. The electronic controller **2010** receives signals from various sensors **2021** to **2027** provided in the vehicle. The electronic controller **2010** may be called an ECU (Electronic Control Unit).

[0223] The signals from the various sensors **2021** to **2028** include a current signal from a current sensor **2021** for sensing current of a motor, a rotation speed signal of a front wheel and a rear wheel acquired by the speed sensor **2022**, a pressure signal of a front wheel and a rear wheel acquired by

an air pressure sensor **2023**, a speed signal of a vehicle acquired by a speed sensor **2024**, an acceleration signal acquired by an acceleration sensor **2025**, an accelerator pedal pressed-amount signal acquired by an accelerator pedal sensor **2029**, a brake pedal pressed-amount signal acquired by a brake pedal sensor **2026**, an operation signal of the shift lever acquired by a shift lever sensor **2027**, and a detection signal acquired by an object detection sensor **2028** for detecting obstacles, vehicles, pedestrians, and the like.

[0224] The information service unit **2012** includes various devices such as a car navigation system, an audio system, a speaker, a television, and a radio for providing various information such as driving information, traffic information, and entertainment information, and one or more ECUs for controlling these devices. The information service unit **2012** provides various multimedia information and multimedia services to an occupant of the vehicle **1** by using information acquired from an external device through a communication module **2013** and the like.

[0225] A driver support system unit **2030** comprises various devices such as a millimeter wave radar, a light detection and ranging (LiDAR), a camera, a positioning locator (for example, GNSS), map information (for example, high-definition (HD) maps, autonomous vehicle (AV) maps, and the like), a gyroscopic system (for example, an inertial measurement unit (IMU), an inertial navigation system (INS), and the like), an artificial intelligence (AI) chip, and an AI processor for providing functions to prevent accidents or reduce a driving load of a driver, and one or more ECUs for controlling these devices. Further, the driver support system unit **2030** transmits and receives various kinds of information through the communication module **2013** to realize a driver support function or an automatic driving function.

[0226] The communication module **2013** can communicate with the microprocessor **2031** and components of the vehicle **1** through a communication port. For example, the communication module **2013** transmits and receives data through the communication port **2033** to and from the drive **2002**, steering **2003**, accelerator pedal **2004**, brake pedal **2005**, shift lever **2006**, left and right front wheels **2007**, left and right rear wheels **2008**, axle **2009**, microprocessor **2031** in the electronic control **2010**, memory (ROM, RAM) **2032**, and sensor **2021** to **2028**.

[0227] The communication module **2013** is a communication device that can be controlled by the microprocessor **2031** of the electronic controller **2010** and can communicate with an external device. For example, The communication module **2013** transmits and receives various kinds of information via radio communication with the external device. The communication module **2013** may be placed inside or outside the electronic control unit **2010**. Examples of the external device may include a base station, a mobile station, and the like.

[0228] The communication module **2013** transmits a current signal coming from a current sensor and input to the electronic controller **2010** to an external device via radio communication. Further, the communication module **2013** transmits a rotation speed signal of a front wheel and a rear wheel acquired by the speed sensor **2022**, a pressure signal of a front wheel and a rear wheel acquired by an air pressure sensor **2023**, a speed signal of a vehicle acquired by a speed sensor **2024**, an acceleration signal acquired by an acceleration sensor **2025**, an accelerator pedal pressed-amount signal acquired by an accelerator pedal sensor **2029**, a brake pedal pressed-amount signal acquired by a brake pedal sensor **2026**, an operation signal of the shift lever acquired by a shift lever sensor **2027**, and a detection signal acquired by an object detection sensor **2028** for detecting obstacles, vehicles, pedestrians, and the like input to the electronic controller **2010** to an external device via radio communication.

[0229] The communication module **2013** receives various information (traffic information, signal information, inter-vehicle information, and the like.) transmitted from the external device and displays on the information service unit **2012** provided in the vehicle. Further, the communication module **2013** stores various information received from the external device in a memory **2032** usable by the microprocessor **2031**. Based on the information stored in the memory **2032**, the microprocessor **2031** may control the drive **2002**, the steering **2003**, the accelerator pedal **2004**, the

brake pedal **2005**, the shift lever **2006**, the left and right front wheels **2007**, the left and right rear wheels **2008**, the axle **2009**, the sensors **2021** to **2028**, and the like. provided in the vehicle **2001**.
[0230] Although the present disclosure has been described in detail above, it will be obvious to those skilled in the art that the present disclosure is not limited to the embodiments described in the present disclosure. The present disclosure can be implemented as modifications and variations without departing from the spirit and scope of the present disclosure as defined by the claims. Therefore, the description of the present disclosure is for the purpose of illustration, and does not have any restrictive meaning to the present disclosure.

Appended Note

[0231] The foregoing disclosure may be expressed as follows.

[0232] A first feature is a terminal including: a communication unit that executes intermittent communication in which communication is executed in a periodic first section, and communication is not executed in a second section other than the first section; and a control unit that executes extension of the first section or shortening of the first section when specific condition is satisfied.

[0233] A second feature is a terminal in which, in the first feature, the control unit executes extension of the first section when a first condition including at least one of a condition that first communication is not executed in the first section and a condition that a notification instructing extension of the first section is received is satisfied.

[0234] A third feature is a terminal in which, in the first feature or the second feature, the control unit executes shortening of the first section when a second condition including at least one of a condition that second communication is executed in the first section and a condition that a notification instructing shortening of the first section is received is satisfied.

[0235] A fourth feature is a base station including: a communication unit that executes intermittent communication in which communication is executed in a periodic first section, and communication is not executed in a second section other than the first section; and a control unit that assumes that the terminal executes extension of the first section or shortening of the first section when a specific condition is satisfied.

[0236] A fifth feature is a radio communication device including a terminal and a base station, the terminal including a communication unit that executes intermittent communication in which communication is executed in a periodic first section, and communication is not executed in a second section other than the first section; and a control unit that executes extension of the first section or shortening of the first section when a specific condition is satisfied.

[0237] A sixth feature is a radio communication method including: a step of executing intermittent communication in which communication is executed in a periodic first section, and communication is not executed in a second section other than the first section; and a step of executing extension of the first section or shortening of the first section when a specific condition is satisfied.

REFERENCE SIGNS LIST

[0238] **10** Radio communication system [0239] **20** NG-RAN [0240] **100** gNB [0241] **110** Reception unit [0242] **120** Transmission unit [0243] **130** Control unit [0244] **200** UE [0245] **210** Radio signal transmission and reception unit [0246] **220** Amplifier unit [0247] **230** Modulation and demodulation unit [0248] **240** Control signal and reference signal processing unit [0249] **250** Encoding/decoding unit [0250] **260** Data transmission and reception unit [0251] **270** Control unit [0252] **1001** Processor [0253] **1002** Memory [0254] **1003** Storage [0255] **1004** Communication device [0256] **1005** Input device [0257] **1006** Output device [0258] **1007** Bus [0259] **2001** Vehicle [0260] **2002** Drive unit [0261] **2003** Steering unit [0262] **2004** Axle pedal [0263] **2005** Brake pedal [0264] **2006** Shift lever [0265] **2007** Left and right front wheels [0266] **2008** Left and right rear wheels [0267] **2009** Axles [0268] **2010** Electronic control unit [0269] **2012** Information service unit [0270] **2013** Communication module [0271] **2021** Current sensor [0272] **2022** Rotational speed sensor [0273] **2023** Air pressure sensor [0274] **2024** Vehicle speed sensor [0275] **2025** Acceleration sensor [0276] **2026** Brake pedal sensor [0277] **2027** Shift lever sensor [0278] **2028**

Claims

1. A terminal comprising: a communication unit that executes intermittent communication in which communication is executed in a periodic first section, and communication is not executed in a second section other than the first section; and a control unit that executes extension of the first section or shortening of the first section when a specific condition is satisfied.
 2. The terminal according to claim 1, wherein the control unit executes extension of the first section when a first condition including at least one of a condition that first communication is not executed in the first section and a condition that a notification instructing extension of the first section is received is satisfied.
 3. The terminal according to claim 1, wherein the control unit executes shortening of the first section when a second condition including at least one of a condition that second communication is executed in the first section and a condition that a notification instructing shortening of the first section is received is satisfied.
 4. A base station comprising: a communication unit that executes intermittent communication in which communication is executed in a periodic first section, and communication is not executed in a second section other than the first section; and a control unit that assumes that the terminal executes extension of the first section or shortening of the first section when a specific condition is satisfied.
 5. A radio communication device comprising a terminal and a base station, the terminal comprising: a communication unit that executes intermittent communication in which communication is executed in a periodic first section, and communication is not executed in a second section other than the first section; and a control unit that executes extension of the first section or shortening of the first section when a specific condition is satisfied.
 6. A radio communication method comprising: a step of executing intermittent communication in which communication is executed in a periodic first section, and communication is not executed in a second section other than the first section; and a step of executing extension of the first section or shortening of the first section when a specific condition is satisfied.
-