

# US Patent & Trademark Office

## Patent Public Search | Text View

---

|                      |                    |
|----------------------|--------------------|
| United States Patent | 12408385           |
| Kind Code            | B2                 |
| Date of Patent       | September 02, 2025 |
| Inventor(s)          | Seo; Jongoh et al. |

---

### Thin-film transistor substrate, manufacturing method thereof, and display apparatus employing the thin-film transistor substrate

---

#### Abstract

Provided are a thin-film transistor substrate, a manufacturing method thereof, and a display apparatus. The thin-film transistor substrate includes: a substrate; a buffer layer on the substrate; a semiconductor layer arranged on the buffer layer and including a first conductive area, a second conductive area, and a channel area between the first conductive area and the second conductive area; a first dopant doped in an upper portion of the channel area at a first concentration; a second dopant doped in a lower portion of the channel area at a second concentration and being of a different type from a type of the first dopant; a gate insulating layer covering the semiconductor layer; and a gate electrode overlapping the channel area in a plan view and disposed on the gate insulating layer.

---

**Inventors:** Seo; Jongoh (Yongin-si, KR), Kim; Janghyun (Yongin-si, KR), Baek; Jongjun (Yongin-si, KR), Lee; Dongmin (Yongin-si, KR)

**Applicant:** SAMSUNG DISPLAY CO., LTD. (Yongin-si, KR)

**Family ID:** 83593856

**Assignee:** SAMSUNG DISPLAY CO., LTD. (Gyeonggi-Do, KR)

**Appl. No.:** 17/845301

**Filed:** June 21, 2022

#### Prior Publication Data

|                            |                         |
|----------------------------|-------------------------|
| <b>Document Identifier</b> | <b>Publication Date</b> |
| US 20230395728 A1          | Dec. 07, 2023           |

#### Foreign Application Priority Data

|    |                 |               |
|----|-----------------|---------------|
| KR | 10-2021-0136893 | Oct. 14, 2021 |
|----|-----------------|---------------|

---

Publication Classification

Int. Cl.: H10D30/67 (20250101); H10D30/01 (20250101); H10K59/121 (20230101); H10K59/80 (20230101)

U.S. Cl.:

CPC H10D30/6757 (20250101); H10D30/0321 (20250101); H10K59/1213 (20230201); H10K59/1216 (20230201); H10K59/873 (20230201);

Field of Classification Search

CPC: H10D (30/0321); H10D (30/675); H10K (59/1213); H10K (59/873); H10K (59/1216)

References Cited

U.S. PATENT DOCUMENTS

| Patent No.   | Issued Date | Patentee Name | U.S. Cl.    | CPC              |
|--------------|-------------|---------------|-------------|------------------|
| 6392277      | 12/2001     | Mitani et al. | N/A         | N/A              |
| 8063453      | 12/2010     | Oh et al.     | N/A         | N/A              |
| 9412864      | 12/2015     | Liu           | N/A         | N/A              |
| 2001/0019862 | 12/2000     | Son et al.    | N/A         | N/A              |
| 2002/0190322 | 12/2001     | Mouli         | 257/69      | H01L<br>21/26513 |
| 2004/0142579 | 12/2003     | Morita        | 438/154     | H10D 30/801      |
| 2005/0116291 | 12/2004     | Koo           | 438/149     | H10K 59/124      |
| 2009/0212363 | 12/2008     | Krivokapic    | 438/157     | H01L<br>21/2652  |
| 2013/0009209 | 12/2012     | Yamazaki      | 257/E21.409 | H10D<br>30/6758  |
| 2013/0078777 | 12/2012     | Cheng         | 257/E21.409 | H10D 84/856      |
| 2015/0311468 | 12/2014     | An et al.     | N/A         | N/A              |
| 2019/0280068 | 12/2018     | Shin          | N/A         | H10D<br>30/6739  |
| 2019/0326378 | 12/2018     | Kim           | N/A         | H10K 77/111      |
| 2020/0098934 | 12/2019     | Shivaraman    | N/A         | H10D 30/031      |
| 2020/0295052 | 12/2019     | Hideo         | N/A         | H10D 86/423      |
| 2021/0091233 | 12/2020     | Yang          | N/A         | H10D<br>30/6715  |
| 2022/0115542 | 12/2021     | Yang          | N/A         | H10D 86/423      |

FOREIGN PATENT DOCUMENTS

| Patent No.    | Application Date | Country | CPC |
|---------------|------------------|---------|-----|
| 105870203     | 12/2015          | CN      | N/A |
| 1998261801    | 12/1997          | JP      | N/A |
| 1019990009998 | 12/1998          | KR      | N/A |
| 100312988     | 12/2001          | KR      | N/A |
| 1020070079115 | 12/2006          | KR      | N/A |

|               |         |    |     |
|---------------|---------|----|-----|
| 101060616     | 12/2010 | KR | N/A |
| 1020150125151 | 12/2014 | KR | N/A |
| 1020190122923 | 12/2018 | KR | N/A |

## OTHER PUBLICATIONS

The Extended European Search Report for EP Patent Application No. 22199462.7 dated Apr. 13, 2023; 9 pages. cited by applicant

Chuan-Hsing Chen, Investigation of Buried Channel PMOS, 1997, 15th Annual Microelectronic Engineering Conference. cited by applicant

*Primary Examiner:* Sengdara; Vongsavanh

*Attorney, Agent or Firm:* CANTOR COLBURN LLP

## Background/Summary

(1) This application claims priority to Korean Patent Application No. 10-2021-0136893, filed on Oct. 14, 2021, and all the benefits accruing therefrom under 35 U.S.C. § 119, the content of which in its entirety is herein incorporated by reference.

### BACKGROUND

#### 1. Field

(2) One or more embodiments relate to a thin-film transistor substrate, a manufacturing method thereof, and a display apparatus including the thin-film transistor substrate.

#### 2. Description of the Related Art

(3) A display apparatus is an apparatus which visually displays data. The display apparatus may be used as a display of a small-sized product such as a mobile phone, or may be used as a display of a large-sized product such as a television.

(4) The display apparatus includes a plurality of pixels receiving electrical signals to emit light to display an image to the outside. Each of the plurality of pixels includes a display element, for example, an organic light-emitting diode (“OLED”) in a case of an organic light-emitting display apparatus.

(5) In general, the display apparatus includes thin-film transistors and capacitors to control emission of the pixels. The thin-film transistor includes, for example, a semiconductor layer including polysilicon, and a gate electrode at least partially overlapping the semiconductor layer. The semiconductor layer includes a channel area and dopant-doped source/drain areas on opposite sides of a semiconductor area, respectively. As the display apparatus having high quality may be implemented according to characteristics of the thin-film transistor, many studies are conducted to improve the quality of the thin-film transistor.

### SUMMARY

(6) One or more embodiments include a thin-film transistor having high quality, and a display apparatus employing the same.

(7) Additional aspects will be set forth in part in the description which follows and, in part, will be apparent from the description, or may be learned by practice of the presented embodiments of the disclosure.

(8) According to one or more embodiments, a thin-film transistor substrate includes: a substrate; a buffer layer on the substrate; a semiconductor layer arranged on the buffer layer and including a first conductive area, a second conductive area, and a channel area between the first conductive area and the second conductive area; a first dopant doped in an upper portion of the channel area at

a first concentration; a second dopant doped in a lower portion of the channel area at a second concentration and being of a different type from a type of the first dopant; a gate insulating layer covering the semiconductor layer; and a gate electrode overlapping the channel area in a plan view and disposed on the gate insulating layer.

(9) According to an embodiment, the first dopant may be doped in the first conductive area and the second conductive area at a third concentration, and the third concentration may be greater than the first concentration.

(10) According to an embodiment, the third concentration may be about 100 times to about 1,000 times greater than the first concentration.

(11) According to an embodiment, the second dopant may be at least partially doped in an upper portion of the buffer layer.

(12) According to an embodiment, each of the first concentration of the first dopant and the second concentration of the second dopant in the channel area may be in a range from about  $1 \times 10^{11}$  ions/cm<sup>2</sup> to about  $1 \times 10^{13}$  ions/cm<sup>2</sup>.

(13) According to an embodiment, the substrate may include a first base layer, a first inorganic barrier layer, a second base layer, and a second inorganic barrier layer, which are sequentially stacked, and the first dopant may be doped in the second inorganic barrier layer.

(14) According to an embodiment, a concentration of the first dopant doped in the second inorganic barrier layer may be in a range from about  $1 \times 10^{11}$  ions/cm<sup>2</sup> to about  $1 \times 10^{13}$  ions/cm<sup>2</sup>.

(15) According to an embodiment, the thin-film transistor substrate may further include a barrier layer between the substrate and the buffer layer, where the first dopant may be doped in the barrier layer.

(16) According to an embodiment, the first dopant may be boron (B), and the second dopant may be phosphorus (P).

(17) According to an embodiment, a maximum concentration position of the first dopant in the channel area may be at a depth of about 50 angstroms (Å) to about 70 Å from the upper surface of the channel area, and a maximum concentration position of the second dopant in the channel area may be at a depth of about 200 Å to about 300 Å from the upper surface of the channel area.

(18) According to one or more embodiments, a method of manufacturing a thin-film transistor substrate includes: injecting a first dopant into a substrate with a first acceleration voltage; forming a buffer layer and a semiconductor layer on the substrate; injecting a second dopant into a boundary area between the buffer layer and the semiconductor layer with a second acceleration voltage; injecting the first dopant into a channel area of the semiconductor layer with a third acceleration voltage; and injecting the first dopant in a source area and a drain area of the semiconductor layer.

(19) According to an embodiment, the forming of the semiconductor layer may include crystallizing amorphous silicon on the substrate into crystalline silicon before the injecting of the second dopant.

(20) According to an embodiment, the second acceleration voltage may be greater than the third acceleration voltage.

(21) According to an embodiment, the second acceleration voltage may have a value from about 10 kilo-electronvolts (keV) to about 40 keV, and the third acceleration voltage may have a value from about 1 keV to about 5 keV.

(22) According to an embodiment, a concentration of the first dopant injected into the source area and the drain area of the semiconductor layer may be about 100 times to about 1,000 times greater than a concentration of the first dopant injected into the channel area of the semiconductor layer.

(23) According to one or more embodiments, a display apparatus includes: a substrate; a buffer layer on the substrate; a pixel circuit arranged on the buffer layer and including a thin-film transistor; and a display element electrically connected to the pixel circuit. Here, the thin-film transistor includes: a semiconductor layer including a first conductive area, a second conductive

area, and a channel area between the first conductive area and the second conductive area; a first dopant doped in an upper portion of the channel area at a first concentration; a second dopant doped in a lower portion of the channel area at a second concentration and being of a different type from a type of the first dopant; and a gate electrode overlapping the channel area in a plan view.

(24) According to an embodiment, the first dopant may be doped in the first conductive area and the second conductive area at a third concentration, and the third concentration may be greater than the first concentration.

(25) According to an embodiment, the second dopant may be at least partially doped in an upper portion of the buffer layer.

(26) According to an embodiment, the substrate may include a first base layer, a first inorganic barrier layer, a second base layer, and a second inorganic barrier layer, which are sequentially stacked, and the first dopant may be doped in the second inorganic barrier layer.

(27) According to an embodiment, the display apparatus may further include a barrier layer between the substrate and the buffer layer, where the first dopant may be doped in the barrier layer.

(28) According to an embodiment, the pixel circuit may further include a capacitor overlapping the thin-film transistor in the plan view.

(29) According to an embodiment, the capacitor may include a lower electrode and an upper electrode, and the lower electrode may be integrally provided with the gate electrode.

(30) According to an embodiment, the display element may include an organic light-emitting diode including a pixel electrode, an intermediate layer, and an opposite electrode.

(31) According to an embodiment, the display apparatus may further include a thin-film encapsulation layer covering the display element, where the thin-film encapsulation layer may include a first inorganic encapsulation layer, an organic encapsulation layer, and a second inorganic encapsulation layer.

---

## Description

### BRIEF DESCRIPTION OF THE DRAWINGS

- (1) The above and other aspects, features, and advantages of certain embodiments of the disclosure will be more apparent from the following description taken in conjunction with the accompanying drawings, in which:
- (2) FIG. 1A is a cross-sectional view schematically illustrating a thin-film transistor substrate according to an embodiment;
- (3) FIG. 1B is a cross-sectional view schematically illustrating a thin-film transistor substrate according to an embodiment;
- (4) FIGS. 2A and 2B are graphs each illustrating positions where dopants are injected into a thin-film transistor substrate according to an embodiment;
- (5) FIG. 3 is a flowchart illustrating a method of manufacturing a thin-film transistor substrate according to an embodiment;
- (6) FIGS. 4A to 4E are schematic cross-sectional views sequentially illustrating a method of manufacturing a thin-film transistor substrate according to an embodiment;
- (7) FIG. 5 is a plan view schematically illustrating a display apparatus according to various embodiments;
- (8) FIG. 6 is an equivalent circuit diagram illustrating a pixel circuit driving a pixel and a display element connected to the pixel circuit, according to an embodiment; and
- (9) FIG. 7 is a cross-sectional view schematically illustrating a display apparatus according to an embodiment.

### DETAILED DESCRIPTION

- (10) Reference will now be made in detail to embodiments, examples of which are illustrated in the

accompanying drawings, wherein like reference numerals refer to like elements throughout. In this regard, the present embodiments may have different forms and should not be construed as being limited to the descriptions set forth herein. Accordingly, the embodiments are merely described below, by referring to the figures, to explain aspects of the present description. As used herein, the term “and/or” includes any and all combinations of one or more of the associated listed items. Throughout the disclosure, the expression “at least one of a, b or c” indicates only a, only b, only c, both a and b, both a and c, both b and c, all of a, b, and c, or variations thereof.

(11) As the present disclosure allows for various changes and numerous embodiments, particular embodiments will be illustrated in the drawings and described in detail in the written description. Effects and features of the present disclosure and methods of achieving the same will be apparent with reference to embodiments and drawings described below in detail. The present disclosure may, however, be embodied in many different forms and should not be construed as being limited to the embodiments set forth herein.

(12) The disclosure will now be described more fully with reference to the accompanying drawings, in which embodiments of the disclosure are shown. Like reference numerals in the drawings denote like elements, and thus their description will be omitted. “About” or “approximately” as used herein is inclusive of the stated value and means within an acceptable range of deviation for the particular value as determined by one of ordinary skill in the art, considering the measurement in question and the error associated with measurement of the particular quantity (i.e., the limitations of the measurement system). For example, “about” can mean within one or more standard deviations, or within  $\pm 30\%$ ,  $20\%$ ,  $10\%$  or  $5\%$  of the stated value.

(13) It will be understood that, although the terms “first,” “second,” “third” etc. may be used herein to describe various elements, components, regions, layers and/or sections, these elements, components, regions, layers and/or sections should not be limited by these terms. These terms are only used to distinguish one element, component, region, layer or section from another element, component, region, layer or section. Thus, “a first element,” “component,” “region,” “layer” or “section” discussed below could be termed a second element, component, region, layer or section without departing from the teachings herein.

(14) In the following embodiments, an expression used in the singular encompasses the expression of the plural, unless it has a clearly different meaning in the context.

(15) In the following embodiments, it is to be understood that the terms such as “including,” “having,” and “comprising” are intended to indicate the existence of the features, or elements disclosed in the present disclosure, and are not intended to preclude the possibility that one or more other features or elements may exist or may be added.

(16) It will be understood that when a layer, region, or component is referred to as being formed on another layer, region, or component, it can be directly or indirectly formed on the other layer, region, or component. That is, for example, intervening layers, regions, or components may be present.

(17) Sizes of components in the drawings may be exaggerated for convenience of explanation. In other words, since sizes and thicknesses of components in the drawings are arbitrarily illustrated for convenience of explanation, the following embodiments are not limited thereto.

(18) When a certain embodiment may be implemented differently, a specific process order may be performed differently from the described order. For example, two consecutively described processes may be performed substantially at the same time or performed in an order opposite to the described order.

(19) As used herein, “a,” “an,” “the,” and “at least one” do not denote a limitation of quantity, and are intended to include both the singular and plural, unless the context clearly indicates otherwise. For example, “an element” has the same meaning as “at least one element,” unless the context clearly indicates otherwise. “At least one” is not to be construed as limiting “a” or “an.” “Or”

means “and/or”.

(20) It will be understood that when a layer, region, or component is referred to as being connected to another layer, region, or component, it can be directly or indirectly connected to the other layer, region, or component. That is, for example, intervening layers, regions, or components may be present. For example, it will be understood that when a layer, region, or component is referred to as being electrically connected to another layer, region, or component, it can be directly or indirectly electrically connected to the other layer, region, or component. That is, for example, intervening layers, regions, or components may be present.

(21) The x-axis (x direction), the y-axis (y direction) and the z-axis (z direction) are not limited to three axes of the rectangular coordinate system, and may be interpreted in a broader sense. For example, the x-axis, the y-axis, and the z-axis may be perpendicular to one another, or may represent different directions that are not perpendicular to one another. As used herein, “plan view” is a view from z direction.

(22) FIGS. 1A and 1B are cross sectional views each schematically illustrating a thin-film transistor substrate **10** according to an embodiment. FIGS. 2A and 2B are graphs each illustrating positions where dopants are injected into a thin-film transistor substrate according to embodiments.

(23) Referring to FIG. 1A, the thin-film transistor substrate **10** may include a substrate **100**, a buffer layer **111**, and a thin-film transistor TFT. In the present disclosure, the thin-film transistor substrate **10** may mean any device including the thin-film transistor TFT. For example, the thin-film transistor substrate **10** may be a thin-film transistor array substrate in which a plurality of thin-film transistors TFT are arranged, or a display apparatus such as an organic light-emitting display apparatus, an inorganic light-emitting display apparatus, a liquid crystal display apparatus, or the like.

(24) The thin-film transistor TFT according to the present embodiment includes a semiconductor layer **210** and a gate electrode **230** overlapping the semiconductor layer **210** in a plan view, where the semiconductor layer **210** includes a first dopant DP1 and a second dopant DP2, which are different types from each other.

(25) The substrate **100** may include a glass material, a ceramic material, a metal material, or a material having a flexible or bendable characteristic. In an embodiment, the substrate **100** is a flexible substrate, and may include a first base layer **101**, a first inorganic barrier layer **102**, a second base layer **103**, and a second inorganic barrier layer **104**, which are sequentially stacked. The first base layer **101** and the second base layer **103** may include a polymer resin such as polyethersulfone, polyacrylate, polyetherimide, polyethylene naphthalate, polyethylene terephthalate, polyphenylene sulfide, polyarylate, polyimide, polycarbonate, or cellulose acetate propionate.

(26) Each of the first inorganic barrier layer **102** and the second inorganic barrier layer **104** may be a barrier layer that prevents penetration of foreign substances from the outside. Each of the first inorganic barrier layer **102** and the second inorganic barrier layer **104** may include an inorganic material such as silicon oxide (SiO.sub.2), silicon nitride (SiN.sub.x), silicon oxynitride (SiON), and amorphous silicon (a-Si), and may have a single-layered structure or a multi-layered structure. In some embodiments, the first inorganic barrier layer **102** may be provided by stacking silicon oxide (SiO.sub.2) and an amorphous silicon layer.

(27) The buffer layer **111** may be on the substrate **100**. The buffer layer **111** may prevent diffusion of impurity ions and penetration of moisture or external air, and may provide a flat surface. The buffer layer **111** may include an inorganic material such as an oxide or a nitride, an organic material, or a composite of an organic material and an inorganic material, and may include a single-layered or multi-layered structure including the inorganic material and the organic material. In some embodiments, the buffer layer **111** may include silicon oxide (SiO.sub.2), silicon nitride (SiN.sub.x), or silicon oxynitride (SiO.sub.xN.sub.y).

(28) The thin-film transistor TFT may be on the buffer layer **111**. The thin-film transistor TFT may

include the semiconductor layer **210** on which a channel is formed, the gate electrode **230** for applying an electric field to form the channel, and a gate insulating layer **112** between the semiconductor layer **210** and the gate electrode **230**.

(29) The semiconductor layer **210** may include amorphous silicon or polysilicon. The semiconductor layer **210** may include a first conductive area **210a**, a second conductive area **210b**, and a channel area **210c**.

(30) In the present disclosure, the semiconductor layer **210** includes the first dopant **DP1** and the second dopant **DP2**, which are different types from each other. The first dopant **DP1** and the second dopant **DP2** may have different types of charges.

(31) When the thin-film transistor TFT is a P-type transistor, the first dopant **DP1** may be a P-type dopant such as a Group 13 element including boron (B), aluminum (Al), gallium (Ga), indium (In), or the like, and the second dopant **DP2** may be an N-type dopant such as a Group 15 element including nitrogen (N), phosphorus (P), arsenic (As), or the like. When the thin-film transistor TFT is an N-type transistor, the first dopant **DP1** may be an N-type dopant, and the second dopant **DP2** may be a P-type dopant.

(32) In the channel area **210c**, the first dopant **DP1** may be doped in an upper portion of the channel area **210c** far from the substrate **100** at a first concentration, and the second dopant **DP2** may be doped in a lower portion of the channel area **210c** close to the substrate **100** at a second concentration. Each of the first concentration and the second concentration may be in a range from about  $1\text{E}11$  ions/cm.<sup>sup.2</sup> to about  $1\text{E}13$  ions/cm.<sup>sup.2</sup> ( $1\times 10^{\text{sup.}11}$  to  $1\times 10^{\text{sup.}13}$ ).

(33) A position of the first dopant **DP1** and a position of the second dopant **DP2** may be adjusted by an acceleration voltage of a dopant during doping. As a doping operation is performed in an upper portion of the semiconductor layer **210**, an acceleration voltage injecting the second dopant **DP2** into the semiconductor layer **210** may be greater than an acceleration voltage injecting the first dopant **DP1**. In some embodiments, the acceleration voltage injecting the second dopant **DP2** into the semiconductor layer **210** may be about 10 kilo-electronvolts (keV) to about 40 keV, and the acceleration voltage injecting the first dopant **DP1** into the semiconductor layer **210** may be about 1 keV to about 5 keV.

(34) FIG. 2A is a graph obtained by measuring concentration distributions of the first dopant **DP1** and the second dopant **DP2** in a depth direction from an upper surface to a lower surface of the channel area **210c**. Here, the first dopant **DP1** may be boron (B) and injected from an upper surface of the channel area **210c** with an acceleration voltage of 3 keV, and the second dopant **DP2** may be phosphorus (P) and injected from the upper surface with an acceleration voltage of 23 keV. In FIGS. 2A and 2B, a unit of measuring ion concentrations of the first dopant **DP1** and the second dopant **DP2** is ion/cm<sup>3</sup>, which is different from a unit ions/cm.<sup>sup.2</sup> of an ion concentration presented in the present disclosure.

(35) Referring to FIG. 2A, it may be seen that the first dopant **DP1** is mostly arranged to a depth of 0 angstroms (Å) to 200 Å from the upper surface of channel area **210c**, and a maximum value of the concentration of the first dopant **DP1** is formed at a depth of about 50 Å to 70 Å. It may be seen that the second dopant **DP2** may be arranged at a depth of about 200 Å to 500 Å, which is a boundary area between the semiconductor layer **210** and the buffer layer **111**. That is, it may be seen that a maximum value of the concentration of the second dopant **DP2** is formed at a depth of about 230 Å to 300 Å. A maximum concentration position of the first dopant **DP1** and a maximum concentration position of the second dopant **DP2** may be formed separately.

(36) As the second dopant **DP2** is doped near the boundary between the semiconductor layer **210** and the buffer layer **111**, the second dopant **DP2** may also be partially doped in the buffer layer **111** below the semiconductor layer **210**. That is, the second dopant **DP2** may be at least partially doped in an upper portion of the buffer layer **111**.

(37) In the first conductive area **210a** and the second conductive area **210b**, the first dopant **DP1** may be entirely doped in the first conductive area **210a** and the second conductive area **210b** at a



third concentration. In this case, one of the first conductive area **210a** and the second conductive area **210b** may be a source area, and other one may be a drain area. The third concentration may be greater than the first concentration. For example, the third concentration may be about 100 times to about 1,000 times greater than the first concentration. The third concentration may be about  $1\text{E}14$  ions/cm.<sup>2</sup> to about  $1\text{E}15$  ions/cm.<sup>2</sup> ( $1 \times 10^{14}$  to  $1 \times 10^{15}$ ).

(38) As the first dopant **DP1** is doped near an upper surface of the channel area **210c**, a surface channel through which charges move from an upper surface of the channel area **210c** may be formed. As the surface channel is formed, a trap/de-trap phenomenon of carriers is effectively reduced. This means that a driving speed of the thin-film transistor TFT may be increased.

(39) In addition, formation of a buried channel in the channel area **210c** may be prevented by doping a lower portion of the channel area **210c** with the second dopant **DP2** having a different type of charge from the type of the first dopant **DP1**. If only the first dopant **DP1** is doped in the channel area **210c**, an undesired buried channel may be formed because the channel area **210c** is provided with a low doping concentration. However, in the present disclosure, a phenomenon of the buried channel may be effectively prevented by doping the second dopant **DP2** on the lower portion of the channel area **210c**.

(40) The gate insulating layer **112** may cover the semiconductor layer **210** and may be on the buffer layer **111**. The gate insulating layer **112** may include an inorganic insulating material such as silicon oxide ( $\text{SiO}_2$ ), silicon nitride ( $\text{SiN}_x$ ), silicon oxynitride ( $\text{SiON}$ ), aluminum oxide ( $\text{Al}_2\text{O}_3$ ), titanium oxide ( $\text{TiO}_2$ ), tantalum oxide ( $\text{Ta}_2\text{O}_5$ ), hafnium oxide ( $\text{HfO}_2$ ), or the like. The gate insulating layer **112** may include a single layer or a multi-layer, each including the above-stated inorganic insulating material.

(41) The gate electrode **230** may be on the gate insulating layer **112**. The gate electrode **230** may overlap at least a part of the semiconductor layer **210** in a plan view. The gate electrode **230** may be arranged to overlap the channel area **210c** of the semiconductor layer **210** in a plan view. The gate electrode **230** may include a single layer or a multi-layer, each including at least one metal selected from aluminum (Al), platinum (Pt), palladium (Pd), silver (Ag), magnesium (Mg), gold (Au), nickel (Ni), neodymium (Nd), iridium (Ir), chromium (Cr), lithium (Li), calcium (Ca), molybdenum (Mo), titanium (Ti), tungsten (W), and copper (Cu).

(42) In some embodiments, the second inorganic barrier layer **104** of the substrate **100** may be doped with the first dopant **DP1**. The first dopant **DP1** may be doped in the second inorganic barrier layer **104** at a concentration of about  $1\text{E}11$  ions/cm.<sup>2</sup> to about  $1\text{E}13$  ions/cm.<sup>2</sup>. The first dopant **DP1** may be doped such that a maximum concentration thereof is distributed in the middle of the second inorganic barrier layer **104** in a thickness direction (i.e., depth direction, z direction).

(43) FIG. 2B is a graph obtained by measuring the concentration distribution of the first dopant **DP1** in a depth direction from an upper surface to a lower surface of the second inorganic barrier layer **104**, according to an embodiment. Here, the first dopant **DP1** may be boron (B) and injected with an acceleration voltage of 25 keV.

(44) Referring to FIG. 2B, it may be seen that the first dopant **DP1** is distributed at a depth of about 1500 Å to 3500 Å with respect to the upper surface of the second inorganic barrier layer **104**. That is, a maximum concentration position of the first dopant **DP1** may be formed at a middle area of the second inorganic barrier layer **104** in the depth direction. A concentration of the first dopant **DP1** in the second inorganic barrier layer **104** may be about  $1\text{E}11$  ions/cm.<sup>2</sup> to about  $1\text{E}13$  ions/cm.<sup>2</sup>.

(45) As the first dopant **DP1** is doped in the second inorganic barrier layer **104**, a polarization phenomenon is induced in the second inorganic barrier layer **104** by an interaction with the second dopant **DP2** at the boundary between the semiconductor layer **210** and the buffer layer **111**, and a dielectric constant of the second inorganic barrier layer **104** may be improved. Accordingly, performance of the thin-film transistor TFT may be effectively improved.

(46) That is, as the first dopant DP1 in the second inorganic barrier layer **104**, the second dopant DP2 at the boundary between the semiconductor layer **210** and the buffer layer **111**, and the first dopant DP1 in the upper portion of the channel area **210c** interact, a channel of the channel area **210c** may be formed near the upper surface and the lower surface thereof, and an effect of reducing the trap/de-trap phenomenon of carriers may be maximized.

(47) Although FIG. 1A illustrates that the substrate **100** includes the first base layer **101**, the first inorganic barrier layer **102**, the second base layer **103**, and the second inorganic barrier layer **104**, which are stacked, and the first dopant DP1 is doped in the second inorganic barrier layer **104**, the present disclosure is not limited thereto.

(48) In another embodiment, as shown in FIG. 1B, a separate inorganic barrier layer **105** may be disposed between the substrate **100** and the buffer layer **111**, and the first dopant DP1 may also be doped into the inorganic barrier layer **105**. The inorganic barrier layer **105** may include silicon oxide (SiO.sub.2), silicon nitride (SiN.sub.x), or silicon oxynitride (SiO.sub.xN.sub.y). The first dopant DP1 may have a maximum doping concentration in a middle area of the inorganic barrier layer **105**, and the concentration of the first dopant DP1 may be about 1E11 ions/cm.sup.2 to about 1E13 ions/cm.sup.2.

(49) FIG. 3 is a flowchart illustrating a method of manufacturing a thin-film transistor substrate according to an embodiment, and FIGS. 4A to 4E are schematic cross-sectional views sequentially illustrating a method of manufacturing a thin-film transistor substrate according to an embodiment.

(50) First, referring to FIG. 4A, in operation S1, the first dopant DP1 is injected into the substrate **100**.

(51) The substrate **100** may be formed by sequentially stacking the first base layer **101**, the first inorganic barrier layer **102**, the second base layer **103**, and the second inorganic barrier layer **104**. The second inorganic barrier layer **104** may include an inorganic material such as silicon oxide (SiO.sub.2), silicon nitride (SiN.sub.x), silicon oxynitride (SiO.sub.xN.sub.y), or the like, and may be deposited through chemical vapor deposition ("CVD") or atomic layer deposition ("ALD").

(52) The first dopant DP1 may be injected to have a maximum concentration in the middle area of the second inorganic barrier layer **104** in a thickness direction thereof, where the second inorganic barrier layer **104** may corresponds to an upper portion of the substrate **100**. At this time, the first dopant DP1 may be doped with an acceleration voltage of about 10 keV to about 40 keV, and the doping concentration thereof may be about 1E11 ions/cm.sup.2 to about 1E13 ions/cm.sup.2. In some embodiments, the acceleration voltage of the first dopant DP1 may be about 25 keV, and the concentration thereof may be about 1E12 ions/cm.sup.2 (1×10.sup.12).

(53) Next, referring to FIG. 4B, in operation S2, the buffer layer **111** and an amorphous semiconductor layer are sequentially deposited on an upper surface of the substrate **100**.

(54) The buffer layer **111** may include an inorganic material such as silicon oxide (SiO.sub.2), silicon nitride (SiN.sub.x), silicon oxynitride (SiO.sub.xN.sub.y), or the like, and may be deposited through CVD or ALD. Then, the amorphous semiconductor layer, for example, an amorphous silicon layer, is deposited on the buffer layer **111**.

(55) Subsequently, in operation S3, the amorphous semiconductor layer is crystallized to form a crystalline semiconductor layer **210'**.

(56) The amorphous silicon layer may be crystallized by various methods, such as a rapid thermal annealing ("RTA") method, a solid phase crystallization ("SPC") method, an excimer laser annealing ("ELA") method, a metal induced crystallization ("MIC") method, a metal induced lateral crystallization ("MILC") method, a sequential lateral solidification ("SLS") method, or the like, to form a polysilicon layer (i.e., crystalline semiconductor layer **210'**).

(57) Then, in operation S4, the second dopant DP2 is injected into an upper portion of the crystalline semiconductor layer **210'**.

(58) The second dopant DP2 may be injected to have a maximum concentration in a boundary area between the buffer layer **111** and the crystalline semiconductor layer **210'**. At this time, the second

dopant DP2 may be doped with an acceleration voltage of about keV to about 40 keV, and the doping concentration thereof may be about  $1\text{E}11$  ions/cm.<sup>sup.2</sup> to about  $1\text{E}13$  ions/cm.<sup>sup.2</sup>. In some embodiments, the acceleration voltage of the second dopant DP2 may be about 23 keV, and the concentration thereof may be about ions/cm.<sup>sup.2</sup>.

(59) If the second dopant DP2 is injected before the amorphous semiconductor layer is crystallized and then the amorphous semiconductor layer is crystallized, a position of the semiconductor layer 210 may be shifted, and thus, it is preferable to inject the second dopant DP2 after the amorphous semiconductor layer is crystallized.

(60) Next, referring to FIG. 4C, in operation S5, the first dopant DP1 may be injected into the upper portion of the crystalline semiconductor layer 210'.

(61) The first dopant DP1 may be injected into the upper portion of the crystalline semiconductor layer 210' to have a maximum concentration. At this time, the first dopant DP1 may be doped with an acceleration voltage of about 1 keV to about 5 keV, and the doping concentration thereof may be about  $1\text{E}11$  ions/cm.<sup>sup.2</sup> to about  $1\text{E}13$  ions/cm.<sup>sup.2</sup>. In some embodiments, the acceleration voltage of the first dopant DP1 may be about 3 keV, and the concentration thereof may be about  $1.5\text{E}12$  ions/cm.<sup>sup.2</sup>.

(62) Then, referring to FIG. 4D, the semiconductor layer 210 is formed by patterning the crystalline semiconductor layer 210'. The crystalline semiconductor layer 210' may be patterned as the semiconductor layer 210 by a photolithography operation using a mask (not shown).

(63) Subsequently, in operation S6, the gate insulating layer 112 covering the semiconductor layer 210, and the gate electrode 230 are formed on the substrate 100, especially on the gate insulating layer 112.

(64) The gate insulating layer 112 may include an inorganic material such as silicon oxide ( $\text{SiO.sub.2}$ ), silicon nitride ( $\text{SiN.sub.x}$ ), silicon oxynitride ( $\text{SiON}$ ), aluminum oxide ( $\text{Al.sub.2O.sub.3}$ ), titanium oxide ( $\text{TiO.sub.2}$ ), tantalum oxide ( $\text{Ta.sub.2O.sub.5}$ ), hafnium oxide ( $\text{HfO.sub.2}$ ), or the like, and may be formed through CVD or ALD.

(65) The gate electrode 230 may be formed by forming a metal layer such as Mo and Ti by a deposition method, such as CVD, plasma enhanced CVD ("PECVD"), low pressure CVD ("LPCVD"), physical vapor deposition ("PVD"), sputtering, ALD, or the like, and then patterning the metal layer.

(66) Then, referring to FIG. 4E, in operation S7, the first dopant DP1 is injected in to the semiconductor layer 210 by using the gate electrode 230 as a mask.

(67) At this time, the first dopant DP1 may be doped with an acceleration voltage of about 10 keV to about 40 keV, and the doping concentration thereof may be about  $1\text{E}14$  ions/cm.<sup>sup.2</sup> to about  $1\text{E}15$  ions/cm.<sup>sup.2</sup>. Accordingly, the channel area 210c, the first conductive area 210a, and the second conductive area 210b may be formed in the semiconductor layer 210, where the first conductive area 210a and the second conductive area 210b are disposed on opposite sides of the channel area 210c, respectively. The first conductive area 210a and the second conductive area 210b may serve as source/drain areas, respectively.

(68) FIG. 5 is a plan view schematically illustrating a display apparatus 1 according to various embodiments.

(69) Referring to FIG. 5, the substrate 100 of the display apparatus 1 may be divided into a display area DA and a peripheral area PA around the display area DA. The display apparatus 1 may provide an image by using light emitted from a plurality of pixels P in the display area DA.

(70) Each of the plurality of pixels P includes a display element such as an organic light-emitting diode or an inorganic light-emitting diode, and may emit, for example, red, green, blue, or white light. That is, each pixel P may be connected to a pixel circuit including a thin-film transistor ("TFT"), a storage capacitor, or the like. The pixel circuit may be connected to a scan line SL, a data line DL crossing the scan line SL, and a driving voltage line PL. The scan line SL may extend in an x direction, and the data line DL and the driving voltage line PL may extend in a y direction.

(71) Each pixel P may emit light by driving the pixel circuit, and the display area DA may provide an image through light emitted from the plurality of pixels P. As described above, the pixel P in the present disclosure may be defined as an emission area emitting any one color of red, green, blue, or white light.

(72) The peripheral area PA is an area in which the plurality of pixels P are not arranged, and does not provide an image. A built-in driving circuit unit, a power supply line, a terminal unit to which a printed circuit board or a driver integrated circuit ("IC") including a driving circuit unit is connected, or the like, may be arranged in the peripheral area PA.

(73) The display apparatus 1 according to an embodiment of the present disclosure may include an organic light-emitting display apparatus, an inorganic electroluminescence ("EL") display apparatus, a quantum dot display apparatus, or the like. Hereinafter, although an organic light-emitting display apparatus is described as an example of a display apparatus according to an embodiment of the present disclosure, the display apparatus is not limited thereto, and characteristics to be described below may be applied to display apparatuses of various types as described above.

(74) FIG. 6 is an equivalent circuit diagram illustrating a pixel circuit PC1 driving a pixel and a display element connected to the pixel circuit PC1, according to an embodiment.

(75) Referring to FIG. 6, the pixel circuit PC1 according to an embodiment may include first to seventh thin-film transistors T1 to T7, and a capacitor Cst. The first to seventh thin-film transistors T1 to T7 and the capacitor Cst may be connected to first to third scan lines SL, SL-1, and SL+1 configured to transfer first to third scan signals Sn, Sn-1, and Sn+1, respectively, the data line DL configured to transfer a data voltage Dm, an emission control line EL configured to transfer an emission control signal En, the driving voltage line PL configured to transfer a driving voltage ELVDD, an initialization voltage line VL configured to transfer an initialization voltage Vint, and an opposite electrode to which a common voltage ELVSS is applied.

(76) The first thin-film transistor T1 may be a driving transistor in which a magnitude of a drain current thereof is determined according to a gate-source voltage, and the second to seventh thin-film transistor T2 to T7 may each be a switching transistor which is turned on/off according to a gate-source voltage and substantially a gate voltage.

(77) The first thin-film transistor T1 may be referred to as a driving thin-film transistor, the second thin-film transistor T2 may be referred to as a scan thin-film transistor, the third thin-film transistor T3 may be referred to as a compensation thin-film transistor, a fourth thin-film transistor T4 may be referred to as a gate initialization thin-film transistor, the fifth thin-film transistor T5 may be referred to as a first emission control thin-film transistor, the sixth thin-film transistor T6 may be referred to as a second emission control thin-film transistor, and the seventh thin-film transistor T7 may be referred to as an anode initialization thin-film transistor.

(78) The capacitor Cst is connected between the driving voltage line PL and a driving gate G1 of the driving thin-film transistor T1. The capacitor Cst may have an upper electrode CE2 connected to the driving voltage line PL, and a lower electrode CE1 connected to the driving gate G1 of the driving thin-film transistor T1.

(79) The driving thin-film transistor T1 may control a magnitude of a driving current I.sub.OLED flowing from the driving voltage line PL to an organic light-emitting diode OLED in accordance with a gate-source voltage. The driving thin-film transistor T1 may have the driving gate G1 connected to the lower electrode CE1 of the capacitor Cst, a driving source S1 connected to the driving voltage line PL via the first emission control thin-film transistor T5, and a driving drain D1 connected to the organic light-emitting diode OLED via the second emission control thin-film transistor T6.

(80) The driving thin-film transistor T1 may output the driving current I.sub.OLED to the organic light-emitting diode OLED in accordance with the gate-source voltage thereof. The magnitude of the driving current I.sub.OLED is determined based on a difference between the gate-source

voltage and a threshold voltage of the driving thin-film transistor T1. The organic light-emitting diode OLED may receive the driving current  $I_{\text{sub.OLED}}$  from the driving thin-film transistor T1 and emit light with a brightness according to the magnitude of the driving current  $I_{\text{sub.OLED}}$ . (81) The scan thin-film transistor T2 is configured to deliver the data voltage  $D_m$  to the driving source S1 of the driving thin-film transistor T1 in response to the first scan signal  $S_n$ . The scan thin-film transistor T2 may have a scan gate G2 connected to the first scan line SL, a scan source S2 connected to the data line DL, and a scan drain D2 connected to the driving source S1 of the driving thin-film transistor T1.

(82) The compensation thin-film transistors T3 are connected in series between the driving drain D1 and the driving gate G1 of the driving thin-film transistor T1 and connect the driving drain D1 and the driving gate G1 to each other of the driving thin-film transistor T1 in response to the first scan signal  $S_n$ . The compensation thin-film transistors T3 may have a compensation gate G3 connected to the first scan line SL, a compensation source S3 connected to the driving drain D1 of the driving thin-film transistor T1, and a compensation drain D3 connected to the driving gate G1 of the driving thin-film transistor T1. Although FIG. 6 illustrates that the compensation thin-film transistors T3 include two thin-film transistors connected to each other in series, the compensation thin-film transistor T3 may include one thin-film transistor.

(83) The gate initialization thin-film transistor T4 applies the initialization voltage  $V_{\text{int}}$  to the driving gate G1 of the driving thin-film transistor T1 in response to the second scan signal  $S_{n-1}$ . The gate initialization thin-film transistor T4 may have a first initialization gate G4 connected to the second scan line  $SL-1$ , a first initialization source S4 connected to the driving gate G1 of the driving thin-film transistor T1, and a first initialization drain D4 connected to the initialization voltage line VL. Although FIG. 6 illustrates that the gate initialization thin-film transistor T4 includes two thin-film transistors connected to each other in series, the gate initialization thin-film transistor T4 may include one thin-film transistor.

(84) The anode initialization thin-film transistor T7 applies the initialization voltage  $V_{\text{int}}$  to an anode of the organic light-emitting diode OLED in response to the third scan signal  $S_{n+1}$ . The anode initialization thin-film transistor T7 may have a second initialization gate G7 connected to the third scan line  $SL+1$ , a second initialization source S7 connected to the anode of the organic light-emitting diode OLED, and a second initialization drain D7 connected to the initialization voltage line VL.

(85) The first emission control thin-film transistor T5 may connect the driving voltage line PL and the driving source S1 of the driving thin-film transistor T1 to each other in response to the emission control signal  $E_n$ . The first emission control thin-film transistor T5 may have a first emission control gate G5 connected to the emission control line EL, a first emission control source S5 connected to the driving voltage line PL, and a first emission control drain D5 connected to the driving source S1 of the driving thin-film transistor T1.

(86) The second emission control thin-film transistor T6 may connect the driving drain D1 of the driving thin-film transistor T1 and the anode of the organic light-emitting diode OLED to each other in response to the emission control signal  $E_n$ . The second emission control thin-film transistor T6 may have a second emission control gate G6 connected to the emission control line EL, a second emission control source S6 connected to the driving drain D1 of the driving thin-film transistor T1, and the second emission control drain D6 connected to the organic light-emitting diode OLED.

(87) The second scan signal  $S_{n-1}$  may be substantially synchronized with the first scan signal  $S_n$  of a previous row. The third scan signal  $S_{n+1}$  may be substantially synchronized with the first scan signal  $S_n$ . According to another embodiment, the third scan signal  $S_{n+1}$  may be substantially synchronized with the first scan signal  $S_n$  of the next row.

(88) In an embodiment, the first to seventh thin-film transistors T1 to T7 may each include a semiconductor layer including silicon. For example, the first to seventh thin-film transistors T1 to

T7 may each include a semiconductor layer including low temperature poly-silicon ("LTPS").

(89) As another embodiment, some semiconductor layers of the first to seventh thin-film transistors T1 to T7 may include LTPS, and other semiconductor layers may also include an oxide semiconductor. The oxide semiconductor may include an oxide of at least one or more materials selected from a group including indium (In), gallium (Ga), tin (Sn), zirconium (Zr), vanadium (V), hafnium (Hf), cadmium (Cd), germanium (Ge), chromium (Cr), titanium (Ti), aluminum (Al), cesium (Cs), cerium (Ce), and zinc (Zn). For example, the oxide semiconductor may be an InSnZnO ("ITZO") semiconductor, an InGaZnO ("IGZO") semiconductor, or the like.

(90) Hereinafter, a detailed operation of one pixel of the display apparatus 1 according to an embodiment is described in detail. As shown in FIG. 6, it is assumed that the first to seventh thin-film transistors T1 to T7 are P-type metal-oxide-semiconductor field-effect transistors ("MOSFET").

(91) First, when the emission control signal  $E_n$  having a high level is received, the first emission control thin-film transistor T5 and the second emission control thin-film transistor T6 are turned off, the driving thin-film transistor T1 stops an output of the driving current  $I_{\text{sub.OLED}}$ , and the organic light-emitting diode OLED stops emitting light.

(92) Thereafter, during a gate initialization period in which the second scan signal  $S_{n-1}$  having a low level is received, the gate initialization thin-film transistor T4 is turned on, and the initialization voltage  $V_{\text{int}}$  is applied to the driving gate G1 of the driving thin-film transistor T1, that is, the lower electrode CE1 of the capacitor Cst. A difference  $ELVDD - V_{\text{int}}$  between the driving voltage ELVDD and the initialization voltage  $V_{\text{int}}$  is stored in the capacitor Cst.

(93) Then, during a data writing period in which the first scan signal  $S_n$  having a low level is received, the scan thin-film transistor T2 and the compensation thin-film transistor T3 are turned on, and the data voltage  $D_m$  is received by the driving source S1 of the driving thin-film transistor T1. The driving thin-film transistor T1 is diode-connected by the compensation thin-film transistor T3, and is biased in a forward direction. A gate voltage of the driving thin-film transistor T1 increases from the initialization voltage  $V_{\text{int}}$ . When the gate voltage of the driving thin-film transistor T1 becomes equal to a data compensation voltage  $D_m - |V_{\text{th}}|$  obtained by reducing an absolute value  $|V_{\text{th}}|$  of a threshold voltage of the driving thin-film transistor T1 from the data voltage  $D_m$ , an increase of the gate voltage of the driving thin-film transistor T1 is stopped while the driving thin-film transistor T1 is turned off. Accordingly, a difference  $ELVDD - D_m + |V_{\text{th}}|$  between the driving voltage ELVDD and the data compensation voltage  $D_m - |V_{\text{th}}|$  is stored in the capacitor Cst.

(94) In addition, during an anode initialization period in which the third scan signal  $S_{n+1}$  having a low level is received, the anode initialization thin-film transistor T7 is turned on, and the initialization voltage  $V_{\text{int}}$  is applied to the anode of the organic light-emitting diode OLED. By applying the initialization voltage  $V_{\text{int}}$  to the anode of the organic light-emitting diode OLED to completely non-emit the organic light-emitting diode OLED, a pixel receives the data voltage  $D_m$  corresponding to a black grayscale in a next frame, but a phenomenon in which the organic light-emitting diode OLED emits fine light may be eliminated.

(95) The first scan signal  $S_n$  and the third scan signal  $S_{n+1}$  may be substantially synchronized, and in this case, the data writing period and the anode initialization period may be the same period.

(96) Subsequently, when the emission control signal  $E_n$  having a low level is received, the first emission control thin-film transistor T5 and the second emission control thin-film transistor T6 may be turned on, the driving thin-film transistor T1 may output the driving current  $I_{\text{sub.OLED}}$  corresponding to a voltage  $ELVDD - D_m$  obtained by subtracting an absolute value of the threshold voltage  $|V_{\text{th}}|$  of the driving thin-film transistor T1 from a voltage stored in the capacitor Cst, that is, a source-gate voltage  $ELVDD - D_m + |V_{\text{th}}|$  of the driving thin-film transistor T1, and the organic light-emitting diode OLED may emit light with a brightness corresponding to the magnitude of the driving current  $I_{\text{sub.OLED}}$ .

(97) FIG. 7 is a cross-sectional view schematically illustrating a display apparatus according to an embodiment. In FIG. 7, the same reference numerals as those in FIG. 1A refer to the same members, and redundant descriptions thereof are omitted.

(98) Referring to FIG. 7, the display apparatus includes the substrate **100**, a pixel circuit PC on the substrate **100**, and the organic light-emitting diode OLED electrically connected to the pixel circuit PC. The pixel circuit PC may include the thin-film transistor TFT and the capacitor Cst.

(99) The thin-film transistor TFT may be the thin-film transistor TFT already described with reference to FIG. 1A, and may be a driving thin-film transistor. The first dopant DP1 and the second dopant DP2, which are different types from each other, may be included in the semiconductor layer **210** of the thin-film transistor TFT.

(100) The first dopant DP1 may be arranged in the upper portion of the channel area **210c** of the semiconductor layer **210**, and the second dopant DP2 may be arranged in the lower portion of the channel area **210c** of the semiconductor layer **210**. In the first conductive area **210a** and the second conductive area **210b** of the semiconductor layer **210**, the first dopant DP1 may be doped at a concentration greater than that of the first dopant DP1 doped in the channel area **210c**. The concentration of the first dopant DP1 doped in the channel area **210c** may be about  $1\text{E}11$  ions/cm.<sup>sup.2</sup> to about  $1\text{E}13$  ions/cm.<sup>sup.2</sup>. The concentration of the first dopant DP1 doped in the first conductive area **210a** and the second conductive area **210b** may be about  $1\text{E}14$  ions/cm.<sup>sup.2</sup> to about  $1\text{E}15$  ions/cm.<sup>sup.2</sup>. The concentration of the second dopant DP2 doped in the channel area **210c** may be about  $1\text{E}11$  ions/cm.<sup>sup.2</sup> to about  $1\text{E}13$  ions/cm.<sup>sup.2</sup>. In some embodiments, the first dopant DP1 may be boron (B), and the second dopant DP2 may be phosphorus (P).

(101) As the second dopant DP2 is doped at the boundary between the semiconductor layer **210** and the buffer layer **111**, the second dopant DP2 may also be arranged in an upper portion of the buffer layer **111**. The first dopant DP1 may be doped in the second inorganic barrier layer **104** of the substrate **100**. The concentration of the first dopant DP1 doped in the second inorganic barrier layer **104** may be about  $1\text{E}11$  ions/cm.<sup>sup.2</sup> to about  $1\text{E}13$  ions/cm.<sup>sup.2</sup>.

(102) An insulating layer **113** may be on the gate electrode **230** of the thin-film transistor TFT. The insulating layer **113** may include an inorganic insulating material such as silicon oxide ( $\text{SiO.sub.2}$ ), silicon nitride ( $\text{SiN.sub.x}$ ), silicon oxynitride ( $\text{SiO.sub.xN.sub.y}$ ), aluminum oxide ( $\text{Al.sub.2O.sub.3}$ ), titanium oxide ( $\text{TiO.sub.2}$ ), or the like. The insulating layer **113** may include a single layer or a multi-layer, each including the above-stated inorganic insulating material.

(103) The capacitor Cst may be formed above the gate electrode **230** of the thin-film transistor TFT by overlapping the gate electrode **230** in a plan view. The capacitor Cst includes the lower electrode CE1 and the upper electrode CE2. The insulating layer **113** may be disposed between the lower electrode CE1 and the upper electrode CE2. In this case, the gate electrode **230** may function not only as a gate electrode of the thin-film transistor TFT, but also as the lower electrode CE1 of the capacitor Cst. That is, the gate electrode **230** and the lower electrode CE1 may be integrally formed. The upper electrode CE2 may be arranged on the insulating layer **113** to at least partially overlap the lower electrode CE1 in a plan view.

(104) Each of the lower electrode CE1 and the upper electrode CE2 may include a single layer or a multi-layer, each including at least one metal selected from Al, Pt, Pd, Ag, Mg, Au, Ni, Nd, Ir, Cr, Li, Ca, Mo, Ti, W, and Cu.

(105) An interlayer insulating layer **115** covers the upper electrode CE2. A conductive layer CM may be on the interlayer insulating layer **115**. The conductive layer CM may be a connection electrode electrically connects one electrode of a plurality of transistors of the pixel circuit PC to a pixel electrode **310**.

(106) An organic insulating layer **120** may cover the conductive layer CM and be on the interlayer insulating layer **115**. The organic insulating layer **120** may include a single layer or a multi-layer.

(107) The organic insulating layer **120** may include photosensitive polyimide, polyimide, polystyrene ("PS"), polycarbonate, benzocyclobutene (BCB), hexamethyldisiloxane ("HMDSO"),

a general commercial polymer such as polymethylmethacrylate ("PMMA") or PS, a polymer derivative having a phenol group, an acrylic polymer, an imide polymer, an aryl ether polymer, an amide polymer, a fluorine polymer, a p-xylene polymer, a vinyl alcohol polymer, or the like. (108) Alternatively, the organic insulating layer **120** may include a siloxane-based organic material. The siloxane-based organic material may include HMDSO, octamethyltrisiloxane, decamethyltetrasiloxane, dodecamethylpentasiloxane, and polydimethylsiloxane. The organic insulating layer **120** may serve as a protective film covering the plurality of transistors of the pixel circuit PC.

(109) The organic light-emitting diode OLED including the pixel electrode **310**, an opposite electrode **330**, and an intermediate layer **320** arranged therebetween and including an emission layer may be on the organic insulating layer **120**.

(110) The pixel electrode **310** may be electrically connected to the conductive layer CM through a contact hole defined in the organic insulating layer **120**, and may be electrically connected to the plurality of thin-film transistors included in the pixel circuit PC through the conductive layer CM. The pixel electrode **310** may be directly connected to the first thin-film transistor T1, or may be indirectly connected to the first thin-film transistor T1 via another thin-film transistor (not shown) having a function of controlling emission.

(111) The pixel electrode **310** may include a conductive oxide material such as indium tin oxide ("ITO"), indium zinc oxide ("IZO"), zinc oxide (ZnO), indium oxide (In.sub.2O.sub.3), indium gallium oxide ("IGO"), or aluminum zinc oxide ("AZO"). The pixel electrode **310** may include a reflective film including Ag, Mg, Al, or a compound thereof. For example, the pixel electrode **310** may have a structure including films including ITO, IZO, ZnO, or In.sub.2O.sub.3 above/below the above-stated reflective film. In this case, the pixel electrode **310** may have a stacked structure of ITO/Ag/ITO.

(112) A pixel defining film **125** may be on the organic insulating layer **120**. The pixel defining film **125** covers an edge of the pixel electrode **310** and defines a pixel by having an opening through which a central portion of the pixel electrode **310** is exposed. In addition, the pixel defining film **125** prevents an arc or the like from being generated at the edge of the pixel electrode **310** by increasing a distance between the edge of the pixel electrode **310** and the opposite electrode **330** on the pixel electrode **310**. The pixel defining film **125** may be formed of an organic insulating material such as polyimide, polyamide, an acrylic resin, BCB, HMDSO, a phenol resin, or the like, in a spin coating method or the like.

(113) The intermediate layer **320** of the organic light-emitting diode OLED may include a low-molecular-weight material or a polymer material, and may emit red, green, blue, or white light. When the intermediate layer **320** includes a low-molecular-weight material, the intermediate layer **320** may have a structure in which a hole injection layer ("HIL"), a hole transport layer ("HTL"), an emission layer ("EML"), an electron transport layer ("ETL"), an electron injection layer ("EIL"), or the like are stacked in a single or complex structure, and may include various organic materials including copper phthalocyanine (CuPc), N,N'-Di(naphthalene-1-yl)-N,N'-diphenylbenzidine ("NPB"), tris-8-hydroxyquinoline aluminum (Alq.sub.3), or the like. The layers may be formed by a method of vacuum deposition.

(114) When the intermediate layer **320** includes a polymer material, the intermediate layer **320** may have a structure including the HTL and the EML. The HTL may include poly(3,4-ethylenedioxythiophene) ("PEDOT"), and the EML may include a polymer material such as poly(p-phenylene vinylene) ("PPV"), polyfluorene, or the like. The intermediate layer **320** may be formed by a screen printing method, an inkjet printing method, a laser induced thermal imaging ("LITI") method, or the like.

(115) The intermediate layer **320** is not limited thereto and may have various structures. In addition, the intermediate layer **320** may include an integral layer over a plurality of pixel electrodes **310**, or may include a layer patterned to correspond to each of the plurality of pixel



electrodes **310**.

(116) The opposite electrode **330** may be on the intermediate layer **320**. The opposite electrode **330** may include a conductive material having a low work function. For example, the opposite electrode **330** may include a (semi) transparent layer including Ag, Mg, Al, Pt, Li, Ca, alloys thereof, or the like. Alternatively, the opposite electrode **330** may further include a layer such as ITO, IZO, ZnO, or In.sub.2O.sub.3 above the (semi) transparent layer including the above-stated material. The opposite electrode **330** may be integrally formed over a plurality of organic light-emitting diodes OLED to correspond to the plurality of pixel electrodes **310**.

(117) A thin-film encapsulation layer **400** may be on the organic light-emitting diode OLED. Because the organic light-emitting diode OLED may be easily damaged by external moisture or oxygen, the organic light-emitting diode OLED may be protected by being covered by the thin-film encapsulation layer **400**. The thin-film encapsulation layer **400** may cover a display area and extend to the outside of the display area. The thin-film encapsulation layer **400** includes at least one organic encapsulation layer and at least one inorganic encapsulation layer. For example, the thin-film encapsulation layer **400** may include a first inorganic encapsulation layer **410**, an organic encapsulation layer **420**, and a second inorganic encapsulation layer **430**.

(118) The first inorganic encapsulation layer **410** may cover the opposite electrode **330**, and may include silicon oxide (SiO.sub.2), silicon nitride (SiN.sub.x), silicon oxynitride (SiON), or the like. Although not illustrated in FIG. 7, other layers such as a capping layer may also be between the first inorganic encapsulation layer **410** and the opposite electrode **330** when needed. Because the first inorganic encapsulation layer **410** is formed along an underlying structure, an upper surface of the first inorganic encapsulation layer **410** may not be flat. The organic encapsulation layer **420** may cover the first inorganic encapsulation layer **410**, and unlike the first inorganic encapsulation layer **410**, an upper surface of the organic encapsulation layer **420** may be formed substantially flat. In detail, the organic encapsulation layer **420** may have a substantially flat upper surface in a portion thereof corresponding to the display area. The organic encapsulation layer **420** may include one or more materials selected from a group including polyethylene terephthalate, polyethylene naphthalate, polycarbonate, polyimide, polyethylene sulfonate, polyoxymethylene, polyarylate, and HMDSO. The second inorganic encapsulation layer **430** may cover the organic encapsulation layer **420**, and may include silicon oxide (SiO.sub.2), silicon nitride (SiN.sub.x), silicon oxynitride (SiON), or the like.

(119) According to the above-stated multi-layered structure of the thin-film encapsulation layer **400**, even when cracks occur in the thin-film encapsulation layer **400**, the thin-film encapsulation layer **400** may prevent the cracks from connecting between the first inorganic encapsulation layer **410** and the organic encapsulation layer **420** or between the organic encapsulation layer **420** and the second inorganic encapsulation layer **430**. Accordingly, the formation of a path, through which external moisture or oxygen, or the like penetrates into the organic light-emitting diode OLED, may be prevented or minimized.

(120) As described above, a thin-film transistor included in a thin-film transistor substrate and a display apparatus according to an embodiment of the present disclosure includes a first dopant and a second dopant, which are different types from each other, in a channel area, thereby minimizing a trap/de-trap phenomenon of carriers. Accordingly, an instantaneous afterimage phenomenon may be improved in a display apparatus employing the same.

(121) It should be understood that embodiments described herein should be considered in a descriptive sense only and not for purposes of limitation. Descriptions of features or aspects within each embodiment should typically be considered as available for other similar features or aspects in other embodiments. While one or more embodiments have been described with reference to the figures, it will be understood by those of ordinary skill in the art that various changes in form and details may be made therein without departing from the spirit and scope as defined by the following claims.

## Claims

1. A thin-film transistor substrate comprising: a substrate; a buffer layer on the substrate; a semiconductor layer arranged on a top surface of the buffer layer and comprising a first conductive area, a second conductive area, and a channel area between the first conductive area and the second conductive area; a first dopant doped in an upper portion of the channel area at a first concentration; a second dopant doped in a lower portion of the channel area at a second concentration and being of a different type from a type of the first dopant; a gate insulating layer covering the semiconductor layer; a gate electrode overlapping the channel area in a plan view and disposed on the gate insulating layer; and a barrier layer disposed under a bottom surface of the buffer layer, wherein the first dopant is doped in the barrier layer.
2. The thin-film transistor substrate of claim 1, wherein the first dopant is doped in the first conductive area and the second conductive area at a third concentration, and the third concentration is greater than the first concentration.
3. The thin-film transistor substrate of claim 2, wherein the third concentration is about 100 to about 1,000 times greater than the first concentration.
4. The thin-film transistor substrate of claim 1, wherein the second dopant is at least partially doped in an upper portion of the buffer layer.
5. The thin-film transistor substrate of claim 1, wherein each of the first concentration of the first dopant and the second concentration of the second dopant in the channel area, is in a range from about  $1 \times 10^{11}$  ions/cm<sup>2</sup> to about  $1 \times 10^{13}$  ions/cm<sup>2</sup>.
6. The thin-film transistor substrate of claim 1, wherein the substrate comprises a first base layer, a first inorganic barrier layer, a second base layer, and a second inorganic barrier layer, which are sequentially stacked, and the first dopant is doped in the second inorganic barrier layer.
7. The thin-film transistor substrate of claim 6, wherein a concentration of the first dopant doped in the second inorganic barrier layer is in a range from about  $1 \times 10^{11}$  ions/cm<sup>2</sup> to about  $1 \times 10^{13}$  ions/cm<sup>2</sup>.
8. The thin-film transistor substrate of claim 1, wherein the first dopant is boron (B), and the second dopant is phosphorus (P).
9. The thin-film transistor substrate of claim 1, wherein a maximum concentration position of the first dopant in the channel area is at a depth of about 50 angstroms (Å) to about 70 Å from the upper surface of the channel area, and a maximum concentration position of the second dopant in the channel area is at a depth of about 200 Å to about 300 Å from the upper surface of the channel area.
10. A display apparatus comprising: a substrate; a buffer layer on the substrate; a barrier layer disposed under a bottom surface of the buffer layer; a pixel circuit arranged on a top surface of the buffer layer and comprising a thin-film transistor; and a display element electrically connected to the pixel circuit, wherein the thin-film transistor comprises: a semiconductor layer comprising a first conductive area, a second conductive area, and a channel area between the first conductive area and the second conductive area; a first dopant doped in an upper portion of the channel area at a first concentration; a second dopant doped in a lower portion of the channel area at a second concentration and being of a different type from a type of the first dopant; and a gate electrode overlapping the channel area in a plan view, wherein the first dopant is doped in the barrier layer.
11. The display apparatus of claim 10, wherein the first dopant is doped in the first conductive area and the second conductive area at a third concentration, and the third concentration is greater than the first concentration.
12. The display apparatus of claim 10, wherein the second dopant is at least partially doped in an upper portion of the buffer layer.
13. The display apparatus of claim 10, wherein the substrate comprises a first base layer, a first

inorganic barrier layer, a second base layer, and a second inorganic barrier layer, which are sequentially stacked, and the first dopant is doped in the second inorganic barrier layer.

14. The display apparatus of claim 10, further comprising: a barrier layer between the substrate and the buffer layer, wherein the first dopant is doped in the barrier layer.

15. The display apparatus of claim 10, wherein the pixel circuit further comprises a capacitor overlapping the thin-film transistor in the plan view.

16. The display apparatus of claim 15, wherein the capacitor comprises a lower electrode and an upper electrode, and the lower electrode is integrally provided with the gate electrode.

17. The display apparatus of claim 10, wherein the display element comprises an organic light-emitting diode comprising a pixel electrode, an intermediate layer, and an opposite electrode.

18. The display apparatus of claim 16, further comprising: a thin-film encapsulation layer covering the display element, wherein the thin-film encapsulation layer comprises a first inorganic encapsulation layer, an organic encapsulation layer, and a second inorganic encapsulation layer.

---