

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250280523

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

Chen; Jui-Lin et al.

INTEGRATED CIRCUIT DEVICE WITH REDUCED VIA RESISTANCE

Abstract

A device includes a substrate, a contact, a first gate, a second gate, a dielectric feature between the gates, a via, and a conductive line. The gates are each adjacent the contact and aligned lengthwise with each other along a first direction. A first sidewall of the dielectric feature defines an end-wall of the first gate. A second sidewall of the dielectric feature defines an end-wall of the second gate. The conductive line extends along a second direction. A projection of the conductive line onto a top surface of the dielectric feature passes between the first and second sidewalls. The via interfaces with the contact along a second plane. The via has a first dimension on the second plane along the second direction; the contact has a second dimension on the second plane along the second direction. The first dimension is greater than the second dimension.

Inventors: Chen; Jui-Lin (District Taipei City, TW), Lin; Yu-Kuan (Taipei City, TW), Wang; Ping-Wei (Hsinchu, TW)

Applicant: Taiwan Semiconductor Manufacturing Company, Ltd. (Hsin-Chu, TW)

Family ID: 85286374

Appl. No.: 19/204949

Filed: May 12, 2025

Related U.S. Application Data

parent US continuation 17461322 20210830 parent-grant-document US 12302543 child US 19204949

Publication Classification

Int. Cl.: H10B10/00 (20230101); H01L23/528 (20060101); H10D84/83 (20250101)

Background/Summary

PRIORITY DATA [0001] This application is a continuation application of U.S. patent application Ser. No. 17/461,322, filed Aug. 30, 2021, which is incorporated herein by reference in its entirety.

BACKGROUND

[0002] The integrated circuit (IC) industry has experienced exponential growth. Technological advances in IC materials and design have produced generations of ICs, where each generation has smaller and more complex circuits than the previous generation. In the course of IC evolution, functional density (i.e., the number of interconnected devices per chip area) has generally increased while geometry size (i.e., the smallest component (or line) that can be created using a fabrication process) has decreased. This scaling down process generally provides benefits by increasing production efficiency and lowering associated costs.

[0003] Such scaling down has also increased the complexity of IC processing and manufacturing. For these advances to be realized, similar developments in IC processing and manufacturing are needed. For example, as feature sizes continue to scale down, it has become increasingly challenging to balance between device reliability and device performance. Accordingly, although existing technologies are generally adequate for their intended purposes, they are not satisfactory in every aspect.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0004] The present disclosure is best understood from the following detailed description when read with the accompanying figures. It is emphasized that, in accordance with the standard practice in the industry, various features are not drawn to scale and are used for illustration purposes only. In fact, the dimensions of the various features may be arbitrarily increased or reduced for clarity of discussion.

[0005] FIG. 1 is a flow chart of a method for fabricating an IC device according to various aspects of the present disclosure.

[0006] FIG. 2 is a plan view of an example memory array fabricated according to aspects of the present disclosure.

[0007] FIG. 3 is a plan view of a memory cell, such as a memory cell of the example memory array of FIG. 2, in portion or entirety, according to various aspects of the present disclosure.

[0008] FIG. 4 is a three-dimensional (3D) perspective view of a memory cell, such as the memory cell of FIG. 3, according to various aspects of the present disclosure.

[0009] FIGS. 5, 6, and 7 are fragmentary cross-sectional views of the memory cell of FIG. 4 along various planes of FIG. 4, according to various aspects of the present disclosure.

[0010] FIGS. 8, 9, 10, 11, 12, and 13 are fragmentary cross-sectional views of device features of the memory cell of FIG. 4 along various cross-sectional planes of FIG. 7, according to various aspects of the present disclosure.

[0011] FIGS. 14A, 14B, 15A, 15B, 16A, 16B, 16C, 17A, and 17B are expanded fragmentary cross-sectional views of various device features of the memory cell, according to various aspects of the present disclosure.

DETAILED DESCRIPTION

[0012] The present disclosure relates generally to integrated circuit (IC) devices, and more particularly, to IC devices with reduced via resistances and improved device performances.

[0013] The following disclosure provides many different embodiments, or examples, for implementing different features of the provided subject matter. Specific examples of components and arrangements are described below to simplify the present disclosure. These are, of course, merely examples and are not intended to be limiting. For example, the formation of a first feature over or on a second feature in the description that follows may include embodiments in which the first and second features are formed in direct contact, and may also include embodiments in which additional features may be formed between the first and second features, such that the first and second features may not be in direct contact. In addition, the present disclosure may repeat reference numerals and/or letters in the various examples. This repetition is for the purpose of simplicity and clarity and does not in itself dictate a relationship between the various embodiments and/or configurations discussed.

[0014] Further, spatially relative terms, such as “beneath,” “below,” “lower,” “above,” “upper” and the like, may be used herein for ease of description to describe one element or feature's relationship to another element(s) or feature(s) as illustrated in the figures. The spatially relative terms are intended to encompass different orientations of the device in use or operation in addition to the orientation depicted in the figures. The apparatus may be otherwise oriented (rotated 90 degrees or at other orientations) and the spatially relative descriptors used herein may likewise be interpreted accordingly.

[0015] As IC devices continue to scale down, it has become increasingly challenging to balance between device reliability and device performance. For example, via features (e.g. VD) are formed on device-level contacts to connect source/drain features to overlaying conductive lines. Because gate structures are often immediately next to the source/drain features, such via features are often designed to have small sizes to avoid inadvertently contacting the gate structures and forming short circuits. In other words, a smaller via feature is desired for the purpose of reducing OFF-state leakage current. However, such smaller via features have increased electrical resistances which degrade the device performance in many aspects. This challenge is exacerbated for devices that have more complex device structures, such as for memories. The present disclosure proposes improved memory structures that include via features having different sizes, designed based on their respective local environments so as to balance between the competing needs for greater performance and for less shorting risk. The present disclosure includes multiple embodiments. Different embodiments may have different advantages, and no particular advantage is necessarily required of any embodiment. Moreover, embodiments of the present disclosure may be implemented in IC devices built with any type of suitable transistors, such as planar field-effect transistors (FETs), multi-gate transistors (planar or vertical), such as fin-like FET (FinFET) devices, nano-sheet-based devices (including gate-all-around (GAA) devices, multi-bridge channel (MBC) devices, and other similar devices), omega-gate (Ω -gate) devices, or pi-gate (Π -gate) devices, as well as strained-semiconductor devices, silicon-on-insulator (SOI) devices, partially-depleted SOI devices, fully-depleted SOI devices, or other devices. Furthermore, the devices presented herein may be a complementary metal-oxide-semiconductor (CMOS) device, a p-type metal-oxide-semiconductor (pMOS) device, or an n-type metal-oxide-semiconductor (nMOS) device. Still further, although the present disclosure uses memory structure as examples to illustrate aspects of the invention, it contemplates that one of ordinary skill may recognize other IC devices beyond memory structures that can also benefit from the structure and methods described herein.

[0016] FIG. 1 is a flow chart of a method **100** for fabricating an IC device according to various aspects of the present disclosure. At block **102** of FIG. 1, method **100** includes forming transistors of a static-random access memory (SRAM) structure. For example, a first, a second, and a third transistor are formed on a semiconductor substrate. The first transistor has a first gate structure and first source/drain features over a first fin structure on the semiconductor substrate; the second

transistor has a second gate structure and second source/drain features over a second fin structure on the semiconductor substrate; and a third transistor has a third gate structure and third source/drain features over a third fin structure on the semiconductor substrate. The first gate electrode extends lengthwise along a first direction, and an end of the first gate electrode is defined by a gate-cut feature. At block **104** of FIG. **1**, the method **100** proceeds to form a first device-level contact on the first source/drain features, a second device-level contact on the second source/drain features, and a third device-level contact on the third source/drain features. At block **106** of FIG. **1**, the method **100** proceeds to form a first via on the first device-level contact, a second via on the second device-level contact, and a third via on the third device-level contact. The first via is aligned with the gate-cut feature along a second direction that is perpendicular to the first direction. The first via has a first via dimension along the second direction, the second via has a second via dimension along the second direction, the third via has a third via dimension along the second direction, and the first via dimension is greater than the second and the third via dimension. At block **108**, the method **100** proceeds to form a first conductive line over and connecting the first via to a source supply voltage, a second conductive line over and connecting the second via to a drain supply voltage, and a third conductive line to connect the third via to a bit line. The first conductive line has a line dimension along the second direction that matches the first dimension of the first via feature. At block **110**, the method **100** proceeds to form additional features and complete the fabrication of the IC device. FIG. **1** has been simplified for the sake of clarity. These method steps may be better understood with reference to the following descriptions of device features.

[0017] FIG. **2** is a plan view of an example memory array **200** fabricated according to aspects of the present disclosure. As illustrated in FIG. **2**, the memory array **200** includes a plurality of memory cells **300** each bordering four additional cells (such as other memory cells **300** and/or dummy cells) on its boundaries. The memory cells **300** may be identical to, or symmetrically related to, each other. In some embodiments, some features of the memory cells **300** may be shared between the adjacent memory cells, such as across the cell boundaries. In the depicted embodiment, memory cell **300** is a static random access memory (SRAM) cells, thus is also referred to as SRAM **300**. However, the present disclosure contemplates embodiments, where memory cell **300** includes another type of memory, such as a dynamic random access memory (DRAM), a non-volatile random access memory (NVRAM), a flash memory, or other suitable memory. Memory array **200** may be included in a microprocessor, a memory, and/or other IC device. In some implementations, memory array **200** may be a portion of an IC chip, an SoC, or portion thereof, that includes various passive and active microelectronic devices such as resistors, capacitors, inductors, diodes, PFETs, NFETs, MOSFETs, CMOS transistors, BJTs, LDMOS transistors, high voltage transistors, high frequency transistors, other suitable components, or combinations thereof. FIG. **2** has been simplified for the sake of clarity to better understand the inventive concepts of the present disclosure. Additional features can be added in memory array **200**, and some of the features described can be replaced, modified, or eliminated from the memory array **200**.

[0018] The memory cells **300** are arranged in column 1 to column N each extending along a first direction (here, in an X-direction) and row 1 to row M each extending along a second direction (here, in a Y-direction), where N and M are positive integers. Column 1 to column N each include a bit line pair extending along the first direction, such as a bit line (BL) and a bit line bar (BLB) (also referred to as a complementary bit line), that facilitate reading data from and/or writing data to respective memory cells **300** in true form and complementary form on a column-by-column basis. Row 1 to row M each includes a word line (WL) (not shown) that facilitates access to respective memory structures **300** on a row-by-row basis. Each memory cell **300** is electrically connected to a respective BL, a respective BLB, and a respective WL, which are electrically connected to a controller **203**. Controller **203** is configured to generate one or more signals to select at least one WL and at least one bit line pair (here, BL and BLB) to access at least one of memory cells **300** for

read operations and/or write operations. Controller **203** includes any circuitry suitable to facilitate read/write operations from/to memory cells **300**, including but not limited to, a column decoder circuit, a row decoder circuit, a column selection circuit, a row selection circuit, a read/write circuit (for example, configured to read data from and/or write data to memory cells **300** corresponding to a selected bit line pair (in other words, a selected column)), other suitable circuit, or combinations thereof. In some implementations, the controller **203** includes at least one sense amplifier configured to detect and/or amplify a voltage differential of a selected bit line pair. In some implementations, the sense amplifier is configured to latch or otherwise store data values of the voltage differential. A perimeter of memory array **200** is configured with dummy cells, such as edge dummy cells **205A**, **205B**, and well strap cells **207A**, **207B**, to ensure uniformity in performance of memory array **200**. However, in some embodiments, the perimeter of memory arrays **200** may include functional memory cells, such as SRAM cells **300**.

[0019] The structures of the memory cells **300** are described below in detail. FIG. **3** is a plan view of a memory cell **300**, in portion or entirety, according to various aspects of the present disclosure. FIG. **4** is a three-dimensional (3D) perspective view of the memory cell **300**, according to various aspects of the present disclosure. FIG. **5** illustrates a fragmentary cross-sectional view of the memory cell **300** along the A-A plane of FIG. **4**. FIG. **6** illustrates a fragmentary cross-sectional view of the memory cell **300** along the B-B plane of FIG. **4**. FIG. **7** illustrates a fragmentary cross-sectional view of the memory cell **300** along the C-C plane of FIG. **4**.

[0020] Each memory cell **300** may be a single-port SRAM cell or a multi-port SRAM cell. Referring to FIG. **3**, in the depicted embodiments, the memory cell **300** is a single-port SRAM cell, and includes six transistors: a pass-gate transistor PG-**1**, a pass-gate transistor PG-**2**, a pull-up transistor PU-**1**, a pull-up transistor PU-**2**, a pull-down transistor PD-**1**, and a pull-down transistor PD-**2**. The memory cell **300** is thus alternatively referred to as a 6T SRAM cell **300**. In operation, pass-gate transistor PG-**1** and pass-gate transistor PG-**2** provide access to a storage portion of memory cell **300**, which includes a cross-coupled pair of inverters. One of the inverters includes pull-up transistor PU-**1** and pull-down transistor PD-**1**, and the other inverter includes pull-up transistor PU-**2** and pull-down transistor PD-**2**. In some implementations, pull-up transistors PU-**1**, PU-**2** are configured as p-type transistors, and pull-down transistors PD-**1**, PD-**2**, as well as pass-gate transistors PG-**1**, PG-**2**, are configured as n-type transistors. In the depicted embodiments, device features of the memory cell **300** are approximately symmetric around a center point of the memory cell **300**. Accordingly, the description below focuses on features of transistors PG-**1**, PD-**1**, and PU-**1**. However, in other embodiments, device features of the memory cell **300** may have include other types of symmetry or may be asymmetric.

[0021] The features of the memory cell **300** are further illustrated in FIG. **4**. Specifically, FIG. **4** illustrates the 3D perspective view of the memory cell **300**. Still referring to FIG. **3** and further referring to FIG. **4**, the memory cell **300** includes a substrate (wafer) **312**. In the depicted embodiment, substrate **312** includes silicon. Alternatively or additionally, substrate **312** includes another elementary semiconductor, such as germanium; a compound semiconductor, such as silicon carbide, silicon phosphide, gallium arsenide, gallium phosphide, indium phosphide, indium arsenide, and/or indium antimonide; an alloy semiconductor, such as SiGe, SiPC, GaAsP, AlInAs, AlGaAs, GaInAs, GaInP, and/or GaInAsP; or combinations thereof. Alternatively, substrate **312** is a semiconductor-on-insulator substrate, such as a silicon-on-insulator (SOI) substrate, a silicon germanium-on-insulator (SGOI) substrate, or a germanium-on-insulator (GOI) substrate. Semiconductor-on-insulator substrates can be fabricated using separation by implantation of oxygen (SIMOX), wafer bonding, and/or other suitable methods.

[0022] Substrate **312** includes various doped regions configured according to design requirements of memory cell **300**. In the depicted embodiment, substrate **312** includes an n-type doped region **314** (also referred to as an n-well) and two p-type doped regions **316A** and **316B** (also referred to as p-wells). N-type doped region **314** is configured for a pMOS transistor, such as a pull-up (PU)

transistor; and p-type doped regions **316A** and **316B** are each configured for an nMOS transistor, such as a pull-down (PD) transistor and a pass-gate (PG) transistor. N-type doped regions, such as n-type doped region **314**, are doped with n-type dopants, such as phosphorus, arsenic, other n-type dopant, or combinations thereof. P-type doped regions, such as p-type doped region **316**, are doped with p-type dopants, such as boron (for example, BF.sub.2), indium, other p-type dopant, or combinations thereof. In some implementations, substrate **312** includes doped regions formed with a combination of p-type dopants and n-type dopants. The various doped regions can be formed directly on and/or in substrate **312**, for example, providing a p-well structure, an n-well structure, a dual-well structure, a raised structure, or combinations thereof. An ion implantation process, a diffusion process, and/or other suitable doping process can be performed to form the various doped regions. In some implementations, n-type doped region **314** has an n-type dopant concentration of about $5 \times 10^{16} \text{ cm}^{-3}$ to about $5 \times 10^{19} \text{ cm}^{-3}$, and p-type doped regions **316A** and **316B** each has a p-type dopant concentration of about $5 \times 10^{16} \text{ cm}^{-3}$ to about $5 \times 10^{19} \text{ cm}^{-3}$.

[0023] As described above with respect to FIG. 3, memory cell **300** includes multiple transistors. For example, the memory cell **300** includes the pull-up transistor PU-1 and pull-up transistor PU-2 disposed over (and electrically connected to) n-well **314**; pass-gate transistor PG-1 and pull-down transistor PD-1 disposed over (and electrically connected to) p-well **316A**; and pass-gate transistor PG-2 and a pull-down transistor PD-2 disposed over (and electrically connected to) p-well **316B**. PU-1 and PU-2 are configured as p-type transistors, while PD-1, PD-2, PG-1, and PG-2 are configured as n-type transistors (as described in more details below). Each transistor includes a fin structure disposed over the substrate **312**. For example, pass-gate transistor PG-1 includes fin structure **320A** and **320A'**; pull-down transistor PD-1 includes the fin structures **320A** and **320A'**; pull-up transistor PU-1 includes a fin structure **320B**; pull-up transistor PU-2 includes a fin structure **320C**; pull-down transistor PD-2 includes fin structures **320D** and **320D'**; and pass-gate transistor PG-2 includes the fin structures **320D**, **320D'**. Fin structures **320A**, **320A'**, **320D**, and **320D'** include p-type doped fins; and fin structures **320B** and **320C** include n-type doped fins. While the transistors are illustrated with certain number of fin structures, this disclosure contemplates each transistor to be independently single-fin transistors or multi-fin transistors in order to achieve certain design needs, for example, to achieve designed drive current. Each transistor also includes a gate structure. For example, pass-gate transistor PG-1 includes gate structure **350A** disposed over fin structure **320A**, **320A'** (and between source/drain features); pull-down transistor PD-1 includes gate structure **350B** disposed over fin structure **320A**, **320A'** (and between source/drain features); pull-up transistor PU-2 includes gate structure **350C** disposed over fin structure **320C** (and between source/drain features); pull-up transistor PU-1 includes gate structure **350D** disposed over fin structure **320D**, **320D'** (and between source/drain features); pull-down transistor PD-2 includes gate structure **350E** disposed over fin structure **320B** (and between source/drain features); and pass-gate transistor PG-2 includes gate structure **350F** disposed over fin structure **320D**, **320D'** (and between source/drain features). These fin structures and gate structures are described below.

[0024] Fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'** each extend from the substrate **312** and orient substantially parallel to one another along the X-direction. The present disclosure contemplates variations in heights, widths, and/or lengths of fin structures that may arise from processing and fabrication of memory cell **300**. In the depicted embodiment, fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'** have substantially the same widths along their respective heights. However, in some embodiments, they may have tapered widths along their respective heights. Fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'** may each have an average width along their respective height from about 5 nm to about 15 nm. In some implementations, fin width varies depending on a position of a base fin relative to other fin structures and/or relative to other features of memory cell **300**. For example, widths of fin structures in the center of an array

may be greater than widths of fin structures on the edge of the array. In another example, alternatively, widths of fin structures in the center of an array may be less than widths of fin structures on the edge of the array.

[0025] Fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'** each have at least one channel region, at least one source region, and at least one drain region defined along their respective lengths in the x-direction, where a channel region is disposed between a source region and a drain region (generally and collectively referred to as source/drain regions). Each of the fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'** has at least one source feature and at least one drain feature (collectively, source/drain features **326A-326D**) in the source/drain region. The source/drain features **326A-326D** are described in more detail later. The channel regions of the respective fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'** each connect the respective pair of source/drain features **326A-326D**, and each engages with a gate structure (as described in detail below), such that current can flow between the respective source/drain regions through the channel regions during operation. For example, a pair of source/drain features **326A** are disposed over fin structures **320A** and **320A'** along the x-direction. The channel regions of the fin structures **320A**, **320A'** each engages with the gate structure **350B** (as described below), such that current can flow between the source/drain regions **326A** through the channel regions of the fin structures **320A**, **320A'** during the operation. Fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'** are formed over substrate **312** using any suitable process. In some implementations, a combination of deposition, lithography and/or etching processes are performed to define fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'**. In some embodiments, the fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'** are formed from a portion of substrate **312**, therefore having the same material as substrate **312**, such as silicon (Si).

[0026] Isolation feature(s) **324** is formed over and/or in substrate **312** to isolate various regions, such as various device regions of memory cell **300**. For example, isolation feature **324** separates and isolates fins from one another, such as fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'**. Isolation feature **324** includes silicon oxide, silicon nitride, silicon oxynitride, other suitable isolation material (for example, including silicon, oxygen, nitrogen, carbon, or other suitable isolation constituent), or combinations thereof. Isolation feature **324** can include different structures, such as shallow trench isolation (STI) structures, deep trench isolation (DTI) structures, and/or local oxidation of silicon (LOCOS) structures. In some implementations, STI features can be formed by etching a trench in substrate **312** (for example, by using a dry etch process and/or wet etch process) and filling the trench with insulator material (for example, by using a chemical vapor deposition process or a spin-on glass process). A chemical mechanical polishing (CMP) process may be performed to remove excessive insulator material and/or planarize a top surface of isolation feature **324**. In some implementations, STI features can be formed by depositing an insulator material over substrate **312** after forming fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'**, such that the insulator material layer fills gaps (trenches) between fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'**, and etching back the insulator material layer to form isolation feature **324**. In some implementations, isolation feature **324** includes a multi-layer structure that fills trenches, such as a bulk dielectric layer disposed over a liner dielectric layer, where the bulk dielectric layer and the liner dielectric layer include materials depending on design requirements (for example, a bulk dielectric layer that includes silicon nitride disposed over a liner dielectric layer that includes thermal oxide). In some implementations, isolation feature **324** includes a dielectric layer disposed over a doped liner layer (including, for example, boron silicate glass (BSG) or phosphosilicate glass (PSG)).

[0027] As noted, gate structures **350A-350F** are disposed over fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'**. Gate structures **350A-350F** each extend along the Y-direction (for example, substantially orthogonal to the lengthwise direction of fin structures). In the depicted embodiment, gate structure **350A** is disposed over and engages a channel region of fin structures

320A, **320A'** and interposes a pair of source/drain features **326A**; and gate structure **350B** is disposed over another channel region of fin structures **320A**, **320A'** and interposes another pair of source/drain features **326A**. During operation, current flows between source/drain features **326A** through the channel regions of the fin structures **320A**, **320A'**. In some embodiments, gate structures **350A** and **350B** are positioned such that at least one source/drain feature **326A** (for example, a common drain feature or one of two coupled drain features) is disposed between gate structure **350A** and gate structure **350B**. In some implementations, gate structure **350A** and a portion of fin structure **320A** and/or **320A'** form the pass-gate transistor PG-1; and gate structure **350B** and a portion of fin structure **320A** and/or **320A'** form the pull-down transistor PD-1. Similarly, gate structures **350E** and **350F** are each disposed over and engage a channel region of fin structure **320D**, **320D'** and interpose a respective pair of source/drain features **326D**. Current flows between source/drain regions of the fin structures **320D**, **320D'** during operation. In some embodiments, gate structures **350E** and **350F** are positioned such that at least one source/drain feature **326D** (for example, a common drain feature or one of two coupled drain features) is disposed between gate structure **350E** and gate structure **350F**. In some implementations, gate structure **350E** and a portion of fin structure **320D** and/or **320D'** form the pull-down transistor PD-2, and gate structure **350F** and a portion of fin structure **320D** and/or **320D'** form the pass-gate transistor PG-2. Additionally, gate structure **350C** is disposed over and engages a channel region of fin structure **320C**, interposing a pair of source/drain features **326C**. Current flows between source/drain features **320C** during operation. In some implementations, gate structure **350C** and a portion of fin structure **320C** form the pull-up transistor PU-2. Furthermore, gate structure **350D** is disposed over a channel region of fin structure **320B**, interposing a pair of source/drain features **326B**. Gate structure **350D** engages the channel region of the fin structure **320B** such that current can flow between source/drain features **326B** during operation. In some implementations, gate structure **350D** and a portion of fin structure **320B** form the pull-up transistor PU-1.

[0028] Gate structures **350A-350F** each include respective gate stacks configured to achieve desired functionality according to design requirements of memory cell **300**, such that gate structures **350A-350F** include the same or different layers and/or materials from one another. In the depicted embodiment, gate structures **350A-350F** have gate stacks that include gate dielectrics **325A-325F**, gate electrodes **330A-330F**, and hard mask layers. Although not specifically depicted, gate structures **350A-350F** may have different gate stacks formed in different doped regions, such as in n-type doped region **314** compared to in p-type doped regions **316A** and **316B**.

[0029] The gate stacks of gate structures **350A-350F** are fabricated according to a gate last process, a gate first process, or a hybrid gate last/gate first process. In gate last process implementations, one or more of gate structures **350A-350F** include dummy gate stacks that are subsequently replaced with metal gate stacks. The dummy gate stacks include, for example, an interfacial layer (including, for example, silicon oxide) and a dummy gate electrode layer (including, for example, polysilicon). In such implementations, the dummy gate electrode layer is removed to form openings (trenches) in which gate dielectric **325A-325F** and/or gate electrode **330A-330F** are subsequently formed. Gate last processes and/or gate first processes can implement deposition processes, lithography processes, etching processes, other suitable processes, or combinations thereof. The deposition processes include CVD, physical vapor deposition (PVD), atomic layer deposition (ALD), high density plasma CVD (HDPCVD), metal organic CVD (MOCVD), remote plasma CVD (RPCVD), plasma enhanced CVD (PECVD), low-pressure CVD (LPCVD), atomic layer CVD (ALCVD), atmospheric pressure CVD (APCVD), plating, other suitable methods, or combinations thereof. The lithography patterning processes include resist coating (for example, spin-on coating), soft baking, mask aligning, exposure, post-exposure baking, developing the resist, rinsing, drying (for example, hard baking), other suitable processes, or combinations thereof. Alternatively, the lithography exposure process is assisted, implemented, or replaced by other methods, such as maskless lithography, e-beam writing, or ion-beam writing. The etching processes

include dry etching processes, wet etching processes, other etching processes, or combinations thereof. A CMP process can be performed to remove any excess material of gate dielectrics **325A-325F**, gate electrodes **330A-330F**, and/or hard mask layers, planarizing gate structures **350A-350F**. [0030] Gate dielectrics **325A-325F** are conformally disposed over the channel regions of the fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'** and over isolation feature **324**, such that gate dielectrics **325A-325F** have a substantially uniform thickness. Gate dielectrics **325A-325F** include a dielectric material, such as silicon oxide, high-k dielectric material, other suitable dielectric material, or combinations thereof. In the depicted embodiment, gate dielectrics **325A-325F** include a high-k dielectric layer including, for example, hafnium, aluminum, zirconium, lanthanum, tantalum, titanium, yttrium, oxygen, nitrogen, other suitable constituent, or combinations thereof. In some implementations, the high-k dielectric layer includes HfO₂, HfSiO, HfSiON, HfTaO, HfTiO, HfZrO, ZrO₂, Al₂O₃, HfO₂—Al₂O₃, TiO₂, Ta₂O₅, La₂O₃, Y₂O₃, other suitable high-k dielectric material, or combinations thereof. High-k dielectric material generally refers to dielectric materials having a high dielectric constant, for example, greater than that of silicon oxide ($\epsilon \approx 3.9$). In some implementations, gate dielectrics **325A-325F** each further include an interfacial layer (including a dielectric material, such as silicon oxide) disposed between the high-k dielectric layer and the respective fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'**, and isolation feature **324**.

[0031] Gate electrodes **330A-330F** are disposed over gate dielectrics **325A-325F**. Gate electrodes **330A-330F** each include an electrically conductive material. In some implementations, gate electrodes **330A-330F** each include multiple layers, such as one or more capping layers, work function layers, glue/barrier layers, and/or metal fill (or bulk) layers. A capping layer can include a material that prevents or eliminates diffusion and/or reaction of constituents between gate dielectrics **325A-325F** and other layers of gate structures **350A-350F** (in particular, gate layers including metal). In some implementation, the capping layer includes a metal and nitrogen, such as titanium nitride (TiN), tantalum nitride (TaN), tungsten nitride (W₂N), titanium silicon nitride (TiSiN), tantalum silicon nitride (TaSiN), or combinations thereof. A work function layer can include a conductive material tuned to have a desired work function (such as an n-type work function or a p-type work function), such as n-type work function materials and/or p-type work function materials. P-type work function materials include TiN, TaN, Ru, Mo, Al, WN, ZrSi₂, MoSi₂, TaSi₂, NiSi₂, WN, other p-type work function material, or combinations thereof. N-type work function materials include Ti, Al, Ag, Mn, Zr, TiAl, TiAlC, TaC, TaCN, TaSiN, TaAl, TaAlC, TiAlN, other n-type work function material, or combinations thereof. A glue/barrier layer can include a material that promotes adhesion between adjacent layers, such as the work function layer and the metal fill layer, and/or a material that blocks and/or reduces diffusion between gate layers, such as the work function layer and the metal fill layer. For example, the glue/barrier layer includes metal (for example, W, Al, Ta, Ti, Ni, Cu, Co, other suitable metal, or combinations thereof), metal oxides, metal nitrides (for example, TiN), or combinations thereof. A metal fill layer can include a suitable conductive material, such as Al, W, and/or Cu. In some embodiments, one or more of gate electrodes **330A**, **330B**, **330E**, and **330F** include an n-type work function metal with a work function of about 4.0 eV to about 4.6 eV. In some embodiments, one or both gate electrodes **330C** and **330D** include a p-type work function metal with a work function of about 4.5 eV to about 5 eV.

[0032] Gate structures **350A-350F** further include respective gate spacers **340A-340F** disposed adjacent to (for example, along sidewalls of) the respective gate stacks. Gate spacers **340A-340F** are formed by any suitable process and include a dielectric material. The dielectric material can include silicon, oxygen, carbon, nitrogen, other suitable material, or combinations thereof (for example, silicon oxide, silicon nitride, silicon oxynitride, or silicon carbide). For example, in the depicted embodiment, a dielectric layer including silicon and nitrogen, such as a silicon nitride

layer, can be deposited over substrate **312** and subsequently anisotropically etched to form gate spacers **340A-340F**. In some implementations, gate spacers **340A-340F** include a multi-layer structure, such as a first dielectric layer that includes silicon nitride and a second dielectric layer that includes silicon oxide. In some implementations, gate spacers **340A-340F** include more than one set of spacers, such as seal spacers, offset spacers, sacrificial spacers, dummy spacers, and/or main spacers, formed adjacent to the gate stacks. In such implementations, the various sets of spacers can include materials having different etch rates. For example, a first dielectric layer including silicon and oxygen can be deposited over substrate **312** and subsequently anisotropically etched to form a first spacer set adjacent to the gate stacks, and a second dielectric layer including silicon and nitrogen can be deposited over substrate **312** and subsequently anisotropically etched to form a second spacer set adjacent to the first spacer set. Implantation, diffusion, and/or annealing processes may be performed to form lightly doped source and drain (LDD) features and/or heavily doped source and drain (HDD) features before and/or after forming gate spacers **340A-340F**.

[0033] In some embodiments, gate structures **350A-350F** are partially defined by dielectric features **380**. The dielectric features **380** cut through the otherwise contiguous gate material layers and separate them into independent and distinct gate structures. For example, dielectric features **380** separates gate structure **350A** from gate structure **350C**, and separates gate structure **350D** from gate structure **350F**. The dielectric features **380** may include any suitable materials, such as silicon oxide, silicon nitride, oxynitride, a dielectric material having a dielectric constant (k) lower than thermal silicon oxide (therefore referred to as low-k dielectric material), and/or other suitable dielectric material layer. The dielectric feature **380** may be formed using any suitable methods. In some embodiments, a patterned hard mask is formed over the gate electrode layer. The patterned hard mask has an opening defining a line-cut (or gate-cut) at the location where the dielectric features **380** are to be formed later. The exposed portions of the gate electrode layer (along with gate spacers and other adjacent auxiliary layers) are removed through the opening to form a line-cut. The line-cut may extend to the isolation features **324** and divide the two portions of the gate electrode (and in some implementations, gate dielectric layers) into electrically isolated gate structures. The removal may implement a wet etch, a dry etch, and/or a combination thereof. Subsequently, the line-cut is filled with proper materials to form the dielectric feature **380**, using deposition methods, for example, CVD, ALD, spin-on coating, or other suitable techniques. A CMP may be performed to polish back the dielectric features **380** thereby providing a substantially planar top surface with respect to the gate structures. In other words, the dielectric features **380** are formed on end-walls of the gate structures, and each have a top surface that extends in parallel to a top surface of the substrate **312** and along the top surfaces of the adjacent gate structures. The dielectric features **380** may interchangeably and alternatively be referred to as the gate-cut feature **380** an/or line-cut feature **380**. In some embodiments, the dielectric feature **380** has a width dimension **488** along the Y-direction (see FIG. **15A**).

[0034] Epitaxial source features and epitaxial drain features **326A-326D** (referred to as epitaxial source/drain features **326A-326D**) are disposed over the source/drain regions of fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'**. For example, semiconductor material is epitaxially grown on fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'**, forming epitaxial source/drain features **326A-326D**. In the depicted embodiment, a fin recess process (for example, an etch back process) is performed on source/drain regions of fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'**. In such implementations, epitaxial source/drain features **326A-326D** are grown from the top surface of recessed fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'**. In furtherance of the depicted embodiment, epitaxial source/drain features **326A-326D** each extend (grow) laterally (e.g., substantially perpendicular to the lengthwise direction of fin structures **320A-320D**), such that epitaxial source/drain features **326A-326D** have a greater lateral width than fin structures **320A**, **320A'**, **320B**, **320C**, **320D**, and **320D'**. In the depicted embodiments, the lateral growth of the epitaxial features on top surface of the recessed fin structures **320A**, **320A'** merge

with each other, such that the epitaxial source/drain feature **326A** spans over both fin structures **320A** and **320A'**; and the lateral growth of the epitaxial features on top surface of the recessed fin structures **320D**, **320D'** merge with each other such that the epitaxial source/drain feature **326D** spans over fin structures **320D** and **320D'**. An epitaxy process can implement CVD deposition techniques (for example, vapor-phase epitaxy (VPE), ultra-high vacuum CVD (UHV-CVD), LPCVD, and/or PECVD), molecular beam epitaxy, other suitable SEG processes, or combinations thereof. The epitaxy process can use gaseous and/or liquid precursors, which interact with the composition of fin structures. Epitaxial source/drain features **326A-326D** are doped with n-type dopants and/or p-type dopants. For example, epitaxial source/drain features **326A** and **326D** (for n-type transistors **PG-1**, **PD-1**, **PD-2**, and **PG-2**) each include an n-type dopant and are formed from epitaxial layers including silicon and/or carbon, where silicon-containing epitaxial layers or silicon-carbon-containing epitaxial layers are doped with phosphorous, arsenic, other n-type dopant, or combinations thereof (for example, forming a Si:P epitaxial layer, a Si:C epitaxial layer, or a Si:C:P epitaxial layer). In furtherance of the example, the epitaxial source/drain features **326B** and **326C** (for p-type transistors **PU-1** and **PU-2**) each include a p-type dopant and are formed from epitaxial layers including silicon and/or germanium, where the silicon germanium containing epitaxial layers are doped with boron, carbon, other p-type dopant, or combinations thereof (for example, forming a Si:Ge:B epitaxial layer or a Si:Ge:C epitaxial layer). In some implementations, epitaxial source/drain features **326A-326D** include materials and/or dopants that achieve desired tensile stress and/or compressive stress in the channel region. In some implementations, epitaxial source/drain features **326A-326D** are doped during deposition by adding impurities to a source material of the epitaxy process. In some implementations, epitaxial source/drain features **326A-326D** are doped by an ion implantation process subsequent to a deposition process. In some implementations, annealing processes are performed to activate dopants in epitaxial source/drain features **326A-326D** and/or other source/drain regions, such as HDD regions and/or LDD regions. In some implementations, silicide layers are formed on epitaxial source/drain features **326A-326D**. In some implementations, silicide layers are formed by depositing a metal layer over epitaxial source/drain features **326A-326D**. The metal layer includes any material suitable for promoting silicide formation, such as nickel, platinum, palladium, vanadium, titanium, cobalt, tantalum, ytterbium, zirconium, other suitable metal, or combinations thereof. Memory cell **300** is then heated (for example, subjected to an annealing process) to cause constituents of epitaxial source/drain features **326A-326D** (for example, silicon and/or germanium) to react with the metal. The silicide layers thus include metal and a constituent of epitaxial source/drain features **326A-326D** (for example, silicon and/or germanium). In some implementations, the silicide layers include nickel silicide, titanium silicide, or cobalt silicide. Any un-reacted metal, such as remaining portions of the metal layer, is selectively removed by any suitable process, such as an etching process. In some implementations, the silicide layers and epitaxial source/drain features **326A-326D** are collectively referred to as the epitaxial source/drain features of transistors of memory cell **300**.

[0035] A multilayer interconnect (MLI) feature **356** is disposed over the substrate **312**. MLI feature **356** electrically couples various devices (for example, p-type transistors **PU-1** and **PU-2**, n-type transistors **PG-1**, **PD-1**, **PD-2**, and **PG-2**, other transistors, resistors, capacitors, and/or inductors) and/or components (for example, gate structures (for example, gate structures **350A-350F**) and/or source/drain features (for example, epitaxial source/drain features **326A-326D**)) of memory cell **300**, such that the various devices and/or components can operate as specified by design requirements of memory cell **300**. MLI feature **356** includes a combination of dielectric layers and electrically conductive layers (for example, metal layers) configured to form various interconnect structures. The conductive layers are configured to form vertical interconnect features, such as device-level contacts and/or vias, and/or horizontal interconnect features, such as conductive lines. Vertical interconnect features typically connect horizontal interconnect features in different layers

(or different planes) of MLI feature **356**. During operation of memory cell **300**, the interconnect features are configured to route signals between the devices and/or the components of memory cell **300** and/or distribute signals (for example, clock signals, voltage signals, and/or ground signals) to the devices and/or the components of memory cell **300**. MLI feature **356** is only partially illustrated in FIG. **4**. For example, only metal lines but not dielectric features (such as interlayer dielectric layers) are illustrated in FIG. **4**. It is further noted that though MLI feature **356** is depicted with a given number of dielectric layers and conductive layers, the present disclosure contemplates MLI feature **356** having more or fewer dielectric layers and/or conductive layers. The components of the MLI feature **356** are further illustrated in FIGS. **5-14B**.

[0036] FIG. **5** illustrates the device layer (e.g., the layer including the transistors PD-1, PU-1, PG-1, PD-2, PU-2, and PG-2), such as the cross-section marked by the A-A line in FIG. **4**. FIG. **6** illustrates the first metal layer (e.g. the M0 layer, including, for example, the source supply voltage (V.sub.SS) lines, the drain supply voltage (V.sub.DD) line, and the bit lines), such as the cross-section marked by the B-B line in FIG. **4**. FIG. **7** illustrates the plane that cuts across the via features (such as gate vias (VG) **376**, **376'**, **378**, **378'**, and source/drain vias (VD) **370**, **372**, **374**, **370'**, **372'**, and **374'**) between the first metal layer and the device layer, such as the cross-section marked by the C-C line in FIG. **4**. It is noted that, in addition to showing features on the respective cross-sections, FIGS. **5** and **6** further include projections of the via features (such as VG and VD), along the Z-direction, on the respective cross-sections. This is solely for the ease of description (such as to clearly indicate the positions of the various features on the cross-sections in relation to the via features). It does not suggest physical presence of those via features on the cross-sections. Moreover, FIG. **8** illustrates a cross-sectional view of the device features, along an X-Z plane (such as the X-Z plane marked by the D.sub.x-D.sub.x line of FIG. **7**) around the via feature **370**; FIG. **9** illustrates a cross-sectional view of the device features, along a Y-Z plane (such as the Y-Z plane marked by the D.sub.y-D.sub.y line of FIG. **7**) around the via feature **370**; FIG. **10** illustrates a cross-sectional view of the device features, along an X-Z plane (such as the X-Z plane marked by the B.sub.x-B.sub.x line of FIG. **7**) around the via feature **372**; FIG. **11** illustrates a cross-sectional view of the device features, along a Y-Z plane (such as the Y-Z plane marked by the B.sub.y-B.sub.y line of FIG. **7**) around the via feature **372**; FIG. **12** illustrates a cross-sectional view of the device features, along an X-Z plane (such as the X-Z plane marked by the S.sub.x-S.sub.x line of FIG. **7**) around the via feature **374**; FIG. **13** illustrates a cross-sectional view of the device features, along a Y-Z plane (such as the Y-Z plane marked by the S.sub.y-S.sub.y line of FIG. **7**) around the via feature **374**. FIGS. **5-13** have been abbreviated for simplicity and clarity.

[0037] As illustrated in FIGS. **8-13**, MLI feature **356** includes one or more dielectric layers, such as an interlayer dielectric layer **352** (ILD-0) disposed over substrate **312**, an interlayer dielectric layer **353** (ILD-1) disposed over ILD layer **352**, an ILD layer **354** (ILD-2) disposed over ILD layer **353**, an intermetal dielectric layer (IMD) **355**, as well as additional ILD layers (not shown) disposed over IMD layer **355**. It is noted that the IMD layer **355** is also interchangeably referred to as the ILD layer **355** for simplicity. ILD layers **352-355** include a dielectric material including, for example, silicon oxide, silicon nitride, silicon oxynitride, TEOS formed oxide, PSG, BPSG, low-k dielectric material, other suitable dielectric material, or combinations thereof. Exemplary low-k dielectric materials include FSG, carbon doped silicon oxide, Black Diamond® (Applied Materials of Santa Clara, California), Xerogel, Aerogel, amorphous fluorinated carbon, Parylene, BCB, SILK® (Dow Chemical, Midland, Michigan), polyimide, other low-k dielectric material, or combinations thereof. In the depicted embodiment, ILD layers **352-355** are dielectric layers that include a low-k dielectric material (generally referred to as low-k dielectric layers). In some implementations, low-k dielectric material generally refers to materials having a dielectric constant (k) that is less than 3. ILD layers **352-355** can include a multilayer structure having multiple dielectric materials. MLI feature **356** can further include one or more contact etch stop layers (CESLs) disposed between ILD layers, such as a CESL **351** disposed between ILD layer **352** and

ILD layer **353**, a CESL **351** disposed between ILD layer **353** and ILD layer **354**, etc. In some implementations, a CESL is disposed between substrate **312** and/or isolation feature **324** and ILD layer **352**. CESLs include a material different than ILD layers **352-355**. For example, where ILD layers **352-354** include a low-k dielectric material, CESLs include silicon and nitrogen, such as silicon nitride or silicon oxynitride. ILD layers **352-355** are formed over substrate **312** by a deposition process, such as CVD, PVD, ALD, HDPCVD, MOCVD, RPCVD, PECVD, LPCVD, ALCVD, APCVD, plating, other suitable methods, or combinations thereof. In some implementations, ILD layers **352-355** are formed by a flowable CVD (FCVD) process that includes, for example, depositing a flowable material (such as a liquid compound) over substrate **312** and converting the flowable material to a solid material by a suitable technique, such as thermal annealing and/or ultraviolet radiation treating. Subsequent to the deposition of ILD layers **352-355**, a CMP process and/or other planarization process is performed, such that ILD layers **352-355** have substantially planar surfaces.

[0038] Device-level contacts **360A-360H** are disposed in ILD layers **353** to form a part of MLI feature **356**. Device-level contacts **360A-360H** include any suitable electrically conductive material, such as Ta, Ti, Al, Cu, Co, W, TiN, TaN, other suitable conductive materials, or combinations thereof. Various conductive materials can be combined to provide device-level contacts **360A-360H** with various layers, such as a barrier layer, an adhesion layer, a liner layer, a bulk layer, other suitable layer, or combinations thereof. In some implementations, device-level contacts **360A-360H** include Ti, TiN, and/or Co, and are formed by patterning ILD layer **353** and/or ILD layer **352**. Patterning ILD layers **353** and/or **352** can include lithography processes and/or etching processes to form openings (trenches), such as contact openings, in ILD layers **353** and/or **352**. In some implementations, the lithography processes include forming a resist layer over ILD layer **353**, exposing the resist layer to patterned radiation, and developing the exposed resist layer, thereby forming a patterned resist layer that can be used as a masking element for etching opening(s) in ILD layers **353** and/or **352**. The etching processes include dry etching processes, wet etching processes, other etching processes, or combinations thereof. Thereafter, the opening(s) are filled with one or more conductive materials. The conductive material(s) can be deposited by PVD, CVD, ALD, electroplating, electroless plating, other suitable deposition process, or combinations thereof. Thereafter, any excess conductive material(s) can be removed by a planarization process, such as a CMP process, thereby planarizing a top surface of ILD layer **353** and a top surface of device-level contacts **360A-360H**. In some embodiments, as depicted in FIG. 5, the device-level contacts **360C** and **360D** each has a dimension **474** along the X-direction; the device-level contacts **360E** and **360F** each has a dimension **472** along the X-direction; and the device-level contacts **360G** and **360H** each has a dimension **476** along the X-direction.

[0039] Device-level contacts **360A-360H** (also referred to as local interconnects or local contacts) electrically couple and/or physically couple IC device features, such as features of p-type transistors PU-1 and PU-2, and n-type transistors PG-1, PD-1, PD-2, and PG-2, to other components of MLI feature **356**, for example, vias of the MLI feature (not shown). For example, device-level contacts **360A-360H** are metal-to-device (MD) contacts, which generally refer to contacts to a conductive region, such as source/drain regions, of memory cell **300**. Device-level contacts **360A-360H** extend through ILD layer **353**, though the present disclosure contemplates embodiments where device-level contacts **360A-360H** extend through more ILD layers and/or CESLs of MLI feature **356**. For example, as illustrated in FIGS. 9 and 11, the device-level contacts **360A-360H** may further extend downward into the ILD layer **352**.

[0040] MLI feature **356** further includes via structures (also interchangeably referred to as vias or via features) formed on device-level contacts **360A-360H**. For example, vias **370** and **370'** are formed on device-level contacts **360C** and **360D**, respectively. The vias **370** and **370'** each connects the device features (such as source/drain features **326B** and **326C**, respectively) with conductive line **390**. Moreover, vias **372** and **372'** are formed on device-level contacts **360G** and **360H**,

respectively. The vias **372** and **372'** connect the device features (such as source/drain features **326A** and **326D**, respectively) with bit lines **392** and **392'**, respectively. Furthermore, vias **374** and **374'** are formed on device-level contacts **360E** and **360F**, respectively. The vias **374** and **374'** connect the device features (such as source/drain features **326A** and **326D**, respectively) with conductive lines **394** and **394'**, respectively. Still further, the MLI feature **356** includes via features **376**, **376'**, **378** and **378'** to complete the circuit and to facilitate the device operations.

[0041] The via features may be formed by any suitable methods. In some embodiments, via openings are formed in ILD layer **354** (and, in some implementations, in CESL **351**) by a patterning process. The patterning process includes lithography processes and/or etching processes. For example, forming via openings includes performing a lithography process to form a patterned resist layer over ILD layer **354** and performing an etching process to transfer a pattern defined in the patterned resist layer to ILD layer **354**. The lithography process can include forming a resist layer on ILD layer **354** (for example, by spin coating), performing a pre-exposure baking process, performing an exposure process using a mask, performing a post-exposure baking process, and performing a developing process. During the exposure process, the resist layer is exposed to radiation energy (such as ultraviolet (UV) light, deep UV (DUV) light, or extreme UV (EUV) light), where the mask blocks, transmits, and/or reflects radiation to the resist layer depending on a mask pattern of the mask and/or mask type (for example, binary mask, phase shift mask, or EUV mask), such that an image is projected onto the resist layer that corresponds with the mask pattern. Since the resist layer is sensitive to radiation energy, exposed portions of the resist layer chemically change, and exposed (or non-exposed) portions of the resist layer are dissolved during the developing process depending on characteristics of the resist layer and characteristics of a developing solution used in the developing process. After development, the patterned resist layer includes a resist pattern that corresponds with the mask. The etching process uses the patterned resist layer as an etch mask to remove portions of ILD layer **354**. The etching process can include a dry etching process (for example, a reactive ion etching (RIE) process), a wet etching process, other suitable etching process, or combinations thereof. After the etching process, the patterned resist layer is removed from ILD layer **354**, for example, by a resist stripping process. In some implementations, the patterned resist layer is used as an etch mask to remove portions of CESL **351** and/or capping layers to extend the via openings, thereby exposing the underlying device-level contacts **360A-360H**. Various selective etching processes can be performed. Alternatively, the exposure process can be implemented or replaced by other methods, such as maskless lithography, electron-beam (e-beam) writing, ion-beam writing, and/or nanoimprint technology.

[0042] Subsequently, vias **372-376** and **372'-376'** are formed in the via openings. The vias **372-376** and **372'-376'** may include any suitable via materials, such as cobalt (Co), ruthenium (Ru), copper (Cu), tantalum (Ta), titanium (Ti), iridium (Ir), tungsten (W), aluminum (Al), tantalum nitride (TaN), titanium nitride (TiN), other suitable metals, or combinations thereof. Although not depicted, the vias may include multiple layers, such as via barrier layers, via seed layers, and/or via bulk layers. The layers for the vias **370-378** and **370'-378'** may be formed by any suitable methods, such as ALD, CVD, PVD, electroplating, electroless plating, other suitable deposition process, or combinations thereof. In some embodiments, various layers of the vias **370-378** and **370'-378'** may be conformal. Moreover, in some embodiments, a CMP process and/or other planarization process is performed to form a planarized top surface.

[0043] MLI feature **356** further includes conductive lines **390**, **392**, **392'**, **394**, and **394'**, each extending along the X-direction. Conductive line **390** is disposed over via **370** and **370'**; conductive lines **392** and **392'** are disposed over via features **372** and **372'**, respectively; conductive lines **394** and **394'** are disposed over via features **374** and **374'**, respectively. Moreover, conductive lines **394** and **394'** are disposed over via features **378** and **378'**, respectively. Furthermore, conductive line **392** is connected to the via **376** through contact **377**; and conductive line **392'** is connected to the via **376'** through contact **377'**. The conductive lines **390**, **392**, **392'**, **394**, and **394'** may include any

suitable conductive materials, and may include the same or different materials from one another. For example, the conductive lines **390**, **392**, **392'**, **394**, and **394'** may include copper, copper alloy, tantalum, tantalum nitride, titanium, titanium nitride, aluminum, tungsten, polysilicon, cobalt, other suitable conductive materials, or combinations thereof. The conductive lines **390**, **392**, **392'**, **394**, and **394'** may be formed by any suitable methods. In some embodiments, the conductive lines **390**, **392**, **392'**, **394**, and **394'** are formed in the same metal layer, such as the first metal layer **M0**. In some embodiments, the conductive lines have different line widths. For example, the conductive lines **394** and **394'** each has line width **484**; the conductive lines **390** and **390'** each has line width **480**; and the conductive lines **392** and **392'** each has line width **482**. In some embodiments, line width **482** is greater than the line widths **484** and **480**. Moreover, referring to FIG. 6, the conductive lines **390**, **392**, **392'**, **394**, and **394'** have different line lengths along the X-direction. For example, the conductive lines **394** and **394'** each have line lengths **4440** defined by adjacent dielectric features **382** and **382'**, such as between a sidewall **542** of the dielectric feature **382** of the memory cell **300** and a sidewall **544** of the dielectric feature **382** of an adjacent memory cell **300**. As illustrated in FIG. 6, a distance between the two dielectric features **382** and **382'** define the length **4440** of the conductive line **394**. Similarly, although not specifically depicted, conductive line **394'** similarly has the length **4440** defined by the dielectric features **382** and **382'**. The dielectric features **382** are substantially similar to the dielectric features **380** described above and may be fabricated using substantially similar methods. In some embodiments, as illustrated in FIG. 4, additional conductive lines are formed over the conductive lines **390**, **392**, **392'**, **394**, and **394'**, for example, along a direction perpendicular to the conductive lines **390**, **392**, **392'**, **394**, and **394'**. These additional conductive lines form the second metal layer **M1**.

[0044] In some embodiments, the device-level contacts **360A-360H** and/or the via features **370-378**, **370'-378'** may have tapered profiles along their respective height along the Z-direction. Referring to FIGS. 8-13, the device-level contacts **360A-360H** and/or the via features **372-376**, **372'-376'** may have top surfaces that are wider than their respective bottom surfaces. However, this present disclosure contemplates any suitable profile for the device-level contacts **360A-360H** and/or the via features **370-378**, **370'-378'**. The present disclosure further contemplates different configurations of device-level contacts, vias, and/or conductive lines, depending on design requirements of memory cell **300**.

[0045] A drain region of pull-down transistor **PD-1** (formed by n-type epitaxial source/drain features **326A**) and a drain region of pull-up transistor **PU-1** (formed by p-type epitaxial source/drain features **326B**) are electrically connected by device-level contact **360A**, such that a common drain of pull-down transistor **PD-1** and pull-up transistor **PU-1** form a storage node, which is further electrically connected to a drain region of pass-gate transistor **PG-1** (formed by n-type epitaxial source/drain features **326A**) by device-level contact **360A**. A drain region of pull-down transistor **PD-2** (formed by n-type epitaxial source/drain features **326D**) and a drain region of pull-up transistor **PU-2** (formed by p-type epitaxial source/drain features **326C**) are electrically connected by device-level contact **360B**, such that a common drain of pull-down transistor **PD-2** and pull-up transistor **PU-2** form another storage node, which is further electrically connected to a drain region of pass-gate transistor **PG-2** (formed by n-type epitaxial source/drain features **326D**) by device-level contact **360B**. A source region of pull-up transistor **PU-1** (formed by p-type epitaxial source/drain features **326B**) is electrically connected to a drain supply voltage **V_{sub}.DD** by device-level contact **360C**, via feature **370**, and conductive line **390**; and a source region of pull-up transistor **PU-2** (formed by p-type epitaxial source/drain features **326C**) is electrically connected to drain supply voltage **V_{sub}.DD** by device-level contact **360D**, via feature **370'** and the conductive line **390**. A source region of pull-down transistor **PD-1** (formed by n-type epitaxial source/drain features **326A**) is electrically connected to a source supply voltage **V_{sub}.SS** by device-level contact **360E**, via feature **374**, and conductive line **394**; and a source region of pull-down transistor **PD-2** (formed by n-type epitaxial source/drain features **326D**) is electrically connected to source supply

voltage V.sub.SS by device-level contact **360F**, via feature **374'**, and conductive line **394'**. A source region of pass-gate transistor PG-1 (formed by n-type epitaxial source/drain features **326A**) is electrically connected to a bit line **392** by device-level contact **360G** and via feature **372**; and a source region of pass-gate transistor PG-2 (formed by n-type epitaxial source/drain features **326D**) is electrically connected to another bit line **392'** by device-level contact **360H** and via feature **372'**. The gates of pass-gate transistors PG-1, PG-2 are electrically coupled with a word line. In some implementations, pass-gate transistors PG-1, PG-2 provide access to storage nodes during read operations and/or write operations. For example, pass-gate transistors PG-1, PG-2 couple storage nodes to the respective bit lines in response to voltage applied to the gates of pass-gate transistors PG-1, PG-2 by word lines.

[0046] Referring now to FIG. 7, in some embodiments, the vias **370**, **370'** have a dimension **404** along the X-direction, and a dimension **406** along the Y-direction; the vias **372**, **372'** have a dimension **424** along the X-direction, and a dimension **426** along the Y-direction; the vias **374**, **374'** have a dimension **444** along the X-direction, and a dimension **446** along the Y-direction. In some embodiments, it may be desirable to design the dimensions of the via features along the X-direction to be less than the dimension of the underlying device-level contacts. As described above, in forming the via features, an etching process opens up a portion of the ILD layer **354** above the device-level contacts. If the dimensions of the via features along the X-direction (which determines the dimensions of the openings) is greater than the dimension of the underlying device-level contacts, the etching process may cause a portion of the opening (such as the portion that is beyond the top surface of the device-level contact) to extend past the sidewall of the device-level contact and into the ILD layer **353**. In some embodiments, the opening may further extend through the CESL **351** to reach the gate structures adjacent to the device-level contacts. Subsequently formed via features, therefore, are formed partially on the gate structures, thereby causing leakage. Additionally, in some embodiments, the via features are designed to have dimensions along the Y-direction that is about the same or less than the dimension of the overlaying conductive lines, so as not to unnecessarily occupy valuable chip space.

[0047] FIGS. **14A** and **14B** illustrate the features on both ends of the via features **370** and **372**, respectively, without showing the via features themselves for clarity. Referring to FIG. **14A** and FIGS. **7**, **8**, and **9**, the dimensions **406** of the via feature **370** along the Y-direction is designed to be the same as or less than the smaller dimension of the conductive line **390** overlaying the via feature **370** and the dimension of the device-level contacts **360C** underlying the via feature **370**. In other words, the dimension **406** is designed to be less than or the same as the dimension **480**. Similarly, the dimension **404** of the via feature **370** along the X-direction is designed to be the same as or less than the smaller dimension of the conductive line **390** overlaying the via feature **370** and the dimension of the device-level contacts **360C** underlying the via feature **370**. In other words, the dimension **404** is designed to be less than or the same as the dimension **474**. Accordingly, the via feature **370** is confined within the boundary planes defined by the sidewalls **562** and **564** of the device-level contact **360C**, as well as those defined by the sidewalls **566** and **568** of the conductive line **390**, such that the via feature **370** is confined with the region **500**. In the depicted embodiments, the region **500** may be described as an overlapped region between the top surface of the device-level contacts **360C** with a projection along the Z-direction of the bottom surface of the overlaying conductive line **390** onto the top surface of the device-level contacts **360C**. Moreover, referring to FIG. **14B** and FIGS. **7**, **10**, and **11**, the dimensions **426** and **424** of the via features **372** are designed to each be less than or the same as the dimension **482** of the overlaying conductive line **392** and the dimension **476** of the underlying device-level contact **360G**, respectively. Accordingly, the via feature **372** is confined within the boundary planes defined by the sidewalls **572** and **574** of the device-level contact **360G**, as well as those defined by the sidewalls **576** and **578** of conductive line **392**, such that the via feature **372** is confined with the region **502**. In the depicted embodiments, the region **502** may be described as an overlapped region between the top

surface of the device-level contacts **360G** with a projection along the Z-direction of the bottom surface of the overlaying conductive line **392** onto the top surface of the device-level contacts **360G**. If the via features **370** extends beyond the region **500**, such as when the dimension **404** is greater than the dimension **474**; or if the via features **372** extends beyond the region **502**, such as when the dimension **424** is greater than the dimension **476**, the etching process forming openings for the via features **370**, **372** may extend onto top surfaces of the gate structures **350D**, **350A**, respectively. Accordingly, the via features **370** and **372** formed therein will bridge with the gate structures.

[0048] In some embodiments, a ratio of the dimension **406** to the dimension **480** may be about 0.8 to 1:1; a ratio of the dimension **404** to the dimension **474** may be about 0.8 to 1:1; a ratio of the dimension **426** to the dimension **482** may be about 0.8 to 1:1; a ratio of the dimension **424** to the dimension **476** may be about 0.8 to 1:1. If one or more of these ratios are too small, such as less than 0.8, the via feature may not have the maximal dimension and thereby not having the lowest resistance necessary to optimize device performance. If the ratios are too large, such as greater than 1:1, any improvement in the resistance may be offset by the risk of shorting with adjacent gate structures thereby causing function failure.

[0049] FIGS. **15A** and **15B** illustrate the design of the via feature **374** and its surrounding features of memory cell **300**, such as gate structures **350B**, dielectric feature **380**, conductive line **394**, and dielectric feature **382**. FIGS. **15A** and **15B** further include some of the relevant features from neighboring memory cells **300'**, such as gate structures **350B'**. The neighboring memory cell **300'** includes features that may be a mirror image to those of the memory cell **300**. For example, the memory cell **300'** includes another gate structure **350B'**, another dielectric feature **380'**, and another dielectric feature **382'**. The gate structure **350B'** may be identical to the gate structure **350B**; the dielectric feature **380'** may be identical to the dielectric feature **380**; and the dielectric feature **382'** may be identical to the dielectric feature **382**. In the depicted embodiments, the dielectric features **380** and **380'** are separated by a distance **4450** along the X-direction; and the dielectric features **382** and **382'** are separated by a distance **4440** along the X-direction. Moreover, the conductive line **394** extends across the boundary **301** between the memory cell **300** and the memory cell **300'**.

[0050] In some approaches, the via feature **374** is designed in a way similar to the via features **372** and **370**. In other words, referring to FIGS. **15A**, **15B**, and FIGS. **7**, **12**, and **13**, the dimensions **446** and **444** of the via features **374** may each be less than or the same as the dimension **484** of the overlaying conductive line **394** and the dimension **472** of the underlaying device-level contact **360E**, respectively. Accordingly, the via feature **374** is confined within the boundary planes defined by the sidewalls **552** and **554** of the device-level contact **360E**, as well as those defined by the sidewalls **556** and **558** of conductive line **394**, such that the via feature **374** is confined with the region **504**. In the depicted embodiments, the region **504** may be described as an overlapped region between the top surface of the device-level contacts **360E** with a projection along the Z-direction of the bottom surface of the overlaying conductive line **394** onto the top surface of the device-level contacts **360E**. Unlike via features **372** and **370**, however, the via feature **374** is situated on a charge carrier pathway that largely determines the operation speeds of the memory cell. Specifically, the via feature **374** electronically connects a source feature of an nMOS to a source supply voltage ($V_{sub,SS}$). Resistances on the source side and the supply side may have a larger impact on the device performances than resistances elsewhere. For example, power coming from the source side and/or the supply side may be designed to feed into two or more drain features or components, such that a higher voltage level and/or a higher current level may be desirable. Accordingly, high resistance in the via feature **374** due to size confinement asserts substantially greater adverse impact to the performance of the memory cell **300**.

[0051] In some approaches (not shown), the overlaying conductive lines **394** may extend along the X-direction but offset from the dielectric features **380** along the Y-direction; and/or the overlaying conductive lines **394** may have a width dimension **484** that is greater than the width dimension **488**

of the dielectric features **380**. In some embodiments, the dielectric features **380** directly interfaces with gate structures on two sidewalls (such as along Y-Z planes). Accordingly, at least a portion of the overlaying conductive line **394** is vertically over a respective gate structure along the Z-direction. In such approaches, forming the via feature **374** that extends beyond the region **504** may cause similar issues as those described above with respect to via features **370** and **372**. In other words, bridging between the via feature **374** and the gate structure therebeneath may cause leakages. According to some embodiments of the present disclosure, the conductive line **394** is formed over a portion of the dielectric features **380**. Moreover, the dimension **488** of the dielectric feature **380** is greater than the dimension **484** of the conductive line **394**. Furthermore, the entirety of the conductive line **394**, as well as the sidewall surfaces **556** and **558** of the conductive line **394** each extend between the sidewall surfaces **566** and **568** of the dielectric feature **380**. As a result, a vertical projection of the conductive line **394** along the Z-direction do not land on the gate structures **350B** or any other gate structures (such as adjacent gate structures **350B'**, **350B''**, and **350B'''** of adjacent memory cells **300**). For example, a vertical projection of a bottom surface of the conductive line **394** onto a plane that extends along the top surface of the dielectric feature **380** land either on the dielectric features **380**, the isolation structure **352**, or on the device-level contact **360E**. In other words, the width dimension (e.g. along the Y-direction) of the vertical projection fits entirely within the width dimension of the dielectric features **380**.

[0052] The via feature **374** is formed below and interfacing directly with the conductive line **394**. Accordingly, having the conductive line **394** extending over the dielectric features **380** and not the gate structures allows the via feature **374** immediately below it to also avoid contacting with the gate structures, as long as the via feature **374** stays within the vertical projection of the conductive line **394**. In such a design, the dimension **444** of the via feature **374** may increase beyond the dimension **472** of the underlaying device-level contact **360E** without the concern to bridge with the adjacent gate structures. As described above, the increase in the size of the via features **374** reduces the resistance and improves the device performance. In some embodiments, the dimension **444** is greater than the dimension **472** of the device-level contact **360E**. For example, a ratio of the dimension **444** to the dimension **472** is at least 1.1:1, for example about 1.2:1 to about 3:1. If the dimension **444** is too small, such as less than about 10% greater than the dimension **472**, the improvement in reduction of resistance within the via feature **374** (and the consequent performance gain) may be too small to justify the extra cost for fabricating cost. Meanwhile, the dimension **444** of the via feature **374** may be less than the length dimension **4440** of the conductive line **394** (which is also the separation between the adjacent dielectric features **382** and **382'**). If the dimension **444** is greater than the length dimension **4440**, the via feature **374** may be too close to neighboring conductive lines, such as conductive lines **396**, such that inadvertent misalignment may lead to shorting. Accordingly, the via feature **374** may have a size that is confined to the region **512**. Referring to FIG. 15B, the region **512** may be defined by the sidewalls **556** and **558** of the conductive line **394**, and the sidewalls **542** and **544** of the conductive line **394** (which are also sidewalls of the dielectric feature **382**). In other words, the size and profile of the via feature **374** may be confined by the size and profile of the overlaying conductive line **394**. In other words, a maximum size of the via feature **374** matches the size of the conductive line **394**. The region **512** is substantially greater in surface area than the regions **500**, **502**, and **504**.

[0053] In some embodiments, a ratio of the dimension **446** to the dimension **484** is about 0.8:1 to about 1:1. Furthermore, the dimension **444** of via feature **374** is substantially greater than the dimension **446** of via feature **374**. For example, an aspect ratio of the via feature **374** is about 1.2:1 to about 3:1. Here, the term aspect ratio is defined as the length dimension (along the X-direction) of a feature to the width dimension (along the Y-direction). In other words, a ratio of the dimension **444** to the dimension **446** is about 1.2:1 to about 3:1. If the aspect ratio is too small, such as less than about 1.2:1, the dimension **444** may be too small to have minimal resistance thereby not reaching the best performance; while if the aspect ratio is too large, the dimension **446** may be too

small to have the minimal resistance thereby also fail to reach the best performance. Conversely, the aspect ratio of the via feature **370** may be about 0.8:1 to about 1.2:1; and the aspect ratio of the via feature **372** may be about 0.8:1 to about 1.2:1. Therefore, the top surface of the via feature **374** more resembles a rectangle than a square.

[0054] FIGS. **16A**, **16B**, and **16C** illustrate example via feature **374** in relation to the adjacent features. FIGS. **16A**, **16B**, and **16C** generally resembles the FIG. **15B** with the exception that projection of the via feature **374** is also illustrated. Referring to FIG. **16A**, the via feature **374** has a dimension **446** that matches the dimension **484** of the conductive line **492**. For example, referring to FIG. **16A**, the via feature **374** have a dimension **444** that is greater than the dimension **472** of the device-level contact **360E**, but less than the dimension **4440** of the conductive line **394**. Moreover, the dimension **444** is less than the distance **4450** between gate structures **350B** and **350B'**.

Referring to FIG. **16B**, the dimension **444** of the via feature **374** is also greater than the dimension **472** of the device-level contact **360E**, but less than the dimension **4440** of the conductive line **394**. In this instance, the dimension **444** is about the same as the distance **4450** between gate structures **350B** and **350B'**. Referring to FIG. **16C**, and further referring to FIG. **13**, the dimension **444** of the via feature **374** is still greater than the dimension **472** of the device-level contact **360E**, but less than the dimension **4440** of the conductive line **394**. In this instance, the dimension **444** is also greater than the distance **4450** between gate structures **350B** and **350B'**. In other words, the via feature **374** overhangs from edges of the device-level contacts **360E** and is partially vertically over the dielectric feature **380**. Accordingly, a vertical projection of the via feature **374** along the Z-direction onto a plane that extends along the top surface of the dielectric feature **380** overlaps with the top surface of the dielectric feature **380**. In such a design, even if the etching operation that forms openings for the via feature **374** over etches into the ILD layer **353** and through the CESL layer **351**, the via feature **374** lands on the dielectric feature **380** rather than any gate structures. Accordingly, shorting will not occur.

[0055] FIGS. **17A** and **17B** generally resemble FIGS. **14A** and **14B**, respectively, except that the via features **370** and **372** are also illustrated. Unlike FIG. **16C**, where the dielectric features **380** provide safe landing area in case of over-etching in via opening formation, such over-etching will cause the via features **370** and **372** to be bridged with the underlaying gate structures **350D** and **350A**, respectively (see FIGS. **8** and **10**, respectively). Accordingly, as described above with respect to FIGS. **14A** and **14B**, the via features **370** and **372** are each confined within the regions **500** and **502**, respective. Therefore, the dimension **444** of the via feature **374** is greater than the dimension **404** of the via feature **370** and is greater than the dimension **424** of the via feature **372**. In some embodiments, a ratio of the dimension **444** to the dimension **404** may be about 1.2:1 to about 3:1; and a ratio of the dimension **444** to the dimension **424** may be about 1.2:1 to about 3:1. If the ratios are too small, such as less than about 1.2:1, the resistance within the via feature **374** may not have been optimized and the device performance may not have been maximized. If the ratios are too large, such as greater than about 3:1, the reduction in resistance may have saturated and further increase in size no longer provide sufficient benefit to justify its cost. Moreover, unlike via features **374**, the sidewall surfaces of the via features **370** and **372** along the X-direction, each extend to intersect with the gate structures **350D**, **350A**, respectively.

[0056] As described above, the present disclosure provides device structures that balance the competing needs for lower feature resistance and for minimizing leakage current. For example, the present disclosure recognizes that resistances of features on the source side and supply side are more impactful to the device performances. Accordingly, the present disclosure prioritizes the resistance optimization for via features **374**. The memory cell **300** has certain characteristics. For example, the via feature **374** has a dimension along the X-direction that is substantially greater than via features **370** and **372**. The via feature **374** has an aspect ratio that is about 1.2:1 to about 3:1, while the aspect ratio of the via features **370** and **372** are each about 0.8:1 to about 1.2:1. Moreover, the conductive line **394** is routed vertically over the dielectric features **380**, and a width dimension

of the conductive line **394** along the Y-direction is less than the width dimension of the dielectric features **380**.

[0057] Though not intended to be limiting, embodiments of the present disclosure offer benefits for semiconductor processing and semiconductor devices, as compared to conventional devices. For example, the dimensions for the via feature **374** are greater than other approaches not implementing the structures provided herein. As a result, resistances within the via features **374** are lower, and current level is higher. Because the via feature **374** connects the source feature of an n-type device to a source supply voltage, the higher current level results in substantially higher device speed. Device characteristics are therefore improved. Meanwhile, due to the unique design of the present disclosure, the increased size of the via feature **374** does not increase the risk of forming bridge between the via features **374** and adjacent gate structures.

[0058] The present disclosure provides for many different embodiments. One general aspect includes a device. The device includes a semiconductor substrate, a device-level contact over the semiconductor substrate, and a first gate structure and a second gate structure over the semiconductor substrate. The first gate structure and the second gate structure are each adjacent the device-level contact and each extend along a first direction. The first gate structure is aligned lengthwise with the second gate structure. The device also includes a dielectric feature between the first gate structure and the second gate structure. The dielectric feature has a top surface extending along a first plane. A first sidewall of the dielectric feature defines an end-wall of the first gate structure. A second sidewall of the dielectric feature defines an end-wall of the second gate structure. The device further includes a conductive line extending along a second direction over the device-level contact and over the dielectric feature. A projection of the conductive line along a third direction onto the first plane passes between the first sidewall and the second sidewall of the dielectric feature, where the third direction extends perpendicular to the first plane. The device additionally includes a via feature vertically connecting the device-level contact and the conductive line. The via feature interfaces with the device-level contact along a second plane extending parallel to a top surface of the semiconductor substrate. The via feature has a first dimension along the second direction on the second plane, the device-level contact has a second dimension along the second direction on the second plane, and the first dimension is greater than the second dimension.

[0059] In some embodiments, a ratio of the first dimension to the second dimension is about 1.2:1 to about 3:1. In some embodiments, the conductive line has a third dimension along the second direction, and the first dimension is less than the third dimension. In some embodiments, the conductive line includes a first side surface extending in parallel to the first sidewall of the dielectric feature and along a first vertical surface. Moreover, the conductive line further includes a second side surface extending in parallel to the second sidewall of the dielectric feature and along a second vertical surface. The first vertical surface and the second vertical surface each extend between the first sidewall and the second sidewall of the dielectric feature. In some embodiments, a projection of the via feature along the third direction onto the first plane overlaps with the top surface of the dielectric feature. In some embodiments, the dielectric feature is a first dielectric feature. The device further includes a third gate structure and a fourth gate structure each extending adjacent the device-level contact and along the first direction. The third gate structure is aligned lengthwise with the fourth gate structure. Moreover, the device additionally includes a second dielectric feature between the third gate structure and the fourth gate structure. The second dielectric feature has a top surface extending along the first plane. A third sidewall of the second dielectric feature defines an end-wall of the third gate structure, and a fourth sidewall of the second dielectric feature defines an end-wall of the fourth gate structure. Furthermore, the first dielectric feature and the second dielectric feature is separated by a first distance along the second direction. The first dimension is less than the first distance. In some embodiments, the third gate structure and the first gate structure is separated by a second distance. The second distance is less than the first dimension. In some embodiments, the conductive line is connected to a source supply voltage. In

some embodiments, the via feature is a first via feature and the device-level contact is a first device-level contact. The device further includes a second via feature connecting a bit line and a second device-level contact. The second device-level contact has a fourth dimension along the second direction, the second via feature has a fifth dimension along the second direction, and the fifth dimension is not greater than the fourth dimension. In some embodiments, the conductive line is a first conductive line. Moreover, the device further includes a third via feature connecting a second conductive line and a third device-level contact. The second conductive line is connected to a drain power supply voltage. Furthermore, the third device-level contact has a sixth dimension along the second direction, the third via feature has a seventh dimension along the second direction, and the seventh dimension is not greater than the sixth dimension.

[0060] One general aspect includes a device. The device includes a first gate structure and a second gate structure over a semiconductor substrate. The first gate structure extends along a first direction, and the second gate structure extends in parallel to the first gate structure. The second gate structure has a top surface extending along a first plane. The device also includes a dielectric feature on an end-wall of the second gate structure. The dielectric feature has a top surface extending along the first plane and two side surfaces extending perpendicular to the first direction. The device further includes a first device-level contact and a second device-level contact. The first device-level contact has a first contact dimension along a second direction perpendicular to the first direction. The second device-level contact has a second contact dimension along the second direction. Moreover, the device includes a first via feature connecting the first device-level contact to a bit line, and a second via feature connecting the second device-level contact to a source supply voltage. The first via feature has a first via dimension along the second direction. Additionally, the first via feature has a first sidewall extending along a first plane perpendicular to the first direction and a second sidewall extending along a second plane perpendicular to the first direction. The second via feature has a second via dimension along the second direction. Additionally, the second via feature has a third sidewall extending along a third plane perpendicular to the first direction and a fourth sidewall extending along a fourth plane perpendicular to the first direction. The first plane and the second plane each intersect with the first gate structure, and the third plane and the fourth plane each pass between the first side surface and the second side surface. Still further, the first via dimension is less than the second via dimension.

[0061] In some embodiments, the second via feature has a third via dimension along the first direction. A ratio of the second via dimension to the third via dimension is about 1.2:1 to about 3:1. In some embodiments, a ratio of the second via dimension to the first via dimension is about 1.2:1 to about 3:1. In some embodiments, a vertical projection of the second via feature onto the first plane includes a portion interposed between the second gate structure and another gate structure along the first direction. In some embodiments, a projection along a third direction onto the first plane overlaps with the top surface of the dielectric feature. The third direction is perpendicular to the first direction and to the second direction. In some embodiments, the device further includes a conductive line connecting the second via feature to the source supply voltage. A size of the via feature matches the size of the conductive line. In some embodiments, the device also includes a third gate structure over the semiconductor substrate. The third gate structure extends in parallel to the first gate structure and further connected to the second gate structure. Moreover, the device includes a third device-level contact and a third via feature. The third device-level contact has a third contact dimension along the second direction. The third via feature connects the third device-level contact to a drain supply voltage. Furthermore, the third via feature has a fourth via dimension along the second direction. Still further, the third via feature has a fifth sidewall extending along a fifth plane perpendicular to the first direction and a sixth sidewall extending along a sixth plane perpendicular to the first direction. A ratio of the second via dimension to the fourth via dimension is about 1.2:1 to about 3:1. The fifth plane and the sixth plane each intersect with the third gate structure.

[0062] One general aspect includes a memory structure. The memory structure includes a semiconductor substrate, a pull-down transistor, a pull-up transistor, and a pass-gate transistor formed on the semiconductor substrate. The memory structure also includes a first via feature, a second via feature and a third via feature. The first via feature has a first dimension along a first direction and connects the pull-down transistor to a source supply voltage. The second via feature has a second dimension along a first direction and connects the pull-up transistor to a drain supply voltage. The third via feature has a third dimension along a first direction and connects the pass-gate transistor to a bit line. The first dimension is greater than the second dimension and the third dimension.

[0063] In some embodiments, the pull-down transistor includes a first gate structure that is aligned lengthwise along a second direction. The second direction is perpendicular to the first direction. The device further includes a gate-cut feature on an end-wall of the first gate structure. The first via feature has a first sidewall that extends along a first plane perpendicular to the second direction. The first via feature also has a second sidewall that extends along a second plane perpendicular to the second direction. Both the first plane and the second plane intersect with the gate-cut feature. In some embodiments, a projection of the first via feature overlaps with a top surface of the gate-cut feature.

[0064] The foregoing outlines features of several embodiments so that those skilled in the art may better understand the aspects of the present disclosure. Those skilled in the art should appreciate that they may readily use the present disclosure as a basis for designing or modifying other processes and structures for carrying out the same purposes and/or achieving the same advantages of the embodiments introduced herein. Those skilled in the art should also realize that such equivalent constructions do not depart from the spirit and scope of the present disclosure, and that they may make various changes, substitutions, and alterations herein without departing from the spirit and scope of the present disclosure.

Claims

1. A device structure, comprising: a first gate structure extending along a first direction; a second gate structure and a third gate structure spaced apart from one another along the first direction by a gate isolation feature; a first source/drain contact extending along sidewalls of the second gate structure and the third gate structure; a gate contact via disposed over the first gate structure; a first source/drain contact via disposed over the first source/drain contact; a first conductive line disposed over the gate contact via; and a second conductive line disposed over the first source/drain contact via, wherein the first conductive line and the second conductive line extend lengthwise along a second direction perpendicular to the first direction, wherein a top surface of the gate contact via comprises a first dimension along the second direction, wherein a top surface of the first source/drain contact via comprises a second dimension along the second direction, wherein the second dimension is greater than the first dimension.
2. The device structure of claim 1, wherein the first conductive line and the second conductive line are insulated from one another along the second direction by a dielectric feature.
3. The device structure of claim 1, further comprising: an active region extending lengthwise along the second direction, wherein the first gate structure and the second gate structure extend over the active region.
4. The device structure of claim 3, wherein the active region comprises two fin structures.
5. The device structure of claim 3, wherein the first source/drain contact extends over the active region.
6. The device structure of claim 3, further comprising: a second source/drain contact extending along a sidewall of the first gate structure away from the second gate structure; and a third conductive line extending lengthwise along the second direction and disposed over the active

region, wherein the second source/drain contact is electrically coupled to the third conductive line by way of a second source/drain contact via.

7. The device structure of claim 6, wherein a top surface of the second source/drain contact via comprises a third dimension along the second direction, wherein the third dimension is greater than the second dimension.

8. The device structure of claim 7, wherein a ratio of the second dimension to the third dimension is between about 1.2 and about 3.

9. The device structure of claim 6, wherein the first conductive line and the second conductive line comprise a first width, wherein the third conductive line comprises a second width greater than the first width.

10. A semiconductor device, comprising: a first p-well and a second p-well; an n-well disposed between the first p-well and the second p-well along a first direction; a first active region disposed over the first p-well and extending lengthwise along a second direction perpendicular to the first direction; a second active region and a third active region disposed over the n-well and extending lengthwise along the second direction; a fourth active region disposed over the second p-well and extending lengthwise along the second direction; a first gate structure extending along the first direction over the first active region; a second gate structure extending along the first direction over the third active region and the fourth active region; a third gate structure extending along the first direction over the first active region and the second active region; a fourth gate structure extending along the first direction over the fourth active region; a first source/drain contact disposed over the first active region and extending alongside the third gate structure; a second source/drain contact disposed over the first active region and extending alongside the first gate structure; a first source/drain contact via landing on the first source/drain contact; and a second source/drain contact via landing on the second source/drain contact, wherein a top surface of the first source/drain contact via comprises a first dimension along the second direction, wherein a top surface of the second source/drain contact via comprises a second dimension along the second direction, wherein the second dimension is greater than the first dimension.

11. The semiconductor device of claim 10, wherein a ratio of the second dimension to the first dimension is between about 1.2 and about 3.

12. The semiconductor device of claim 10, wherein the first gate structure is insulated from the second gate structure by a first gate-cut feature, wherein the third gate structure is insulated from the fourth gate structure by a second gate-cut feature.

13. The semiconductor device of claim 10, further comprising: a gate contact via landing on the first gate structure; a first conductive line extending over and electrically coupled to the gate contact via; and a second conductive line extending over and electrically coupled to the first source/drain contact via.

14. The semiconductor device of claim 13, where the first conductive line is insulated from the second conductive line by a dielectric feature.

15. The semiconductor device of claim 13, where the first conductive line is aligned with the second conductive line along the first direction.

16. The semiconductor device of claim 10, Wherein each of the first active region and the fourth active region comprises two fin structures, Wherein each of the second active region and the third active region comprises one fin structure.

17. A semiconductor device, comprising: a substrate; a first fin structure and a second fin structure disposed over the substrate and extending lengthwise along a first direction; a first gate structure and a second gate structure extending along a second direction over the first fin structure and the second fin structure, the second direction being perpendicular to the first direction; a first source/drain contact disposed along a sidewall of the first gate structure and extending over the first fin structure and the second fin structure; a second source/drain contact disposed along a sidewall of the second gate structure and extending over the first fin structure and the second fin structure; a

first source/drain contact via landing on the first source/drain contact; and a second source/drain contact via landing on the second source/drain contact, wherein a top surface of the first source/drain contact via comprises a first dimension along the second direction, wherein a top surface of the second source/drain contact via comprises a second dimension along the second direction, wherein the second dimension is greater than the first dimension.

18. The semiconductor device of claim 17, wherein a ratio of the second dimension to the first dimension is between about 1.2 and about 3.

19. The semiconductor device of claim 17, further comprising: a first conductive line disposed over and in contact with the first source/drain contact via; and a second conductive line disposed over and in contact with the second source/drain contact via.

20. The semiconductor device of claim 19, wherein the first conductive line comprises a first width, wherein the second conductive line comprises a second width greater than the first width.
