

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12399207
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Hunter; Patrick Phillip

System and method for detecting cable system signal ingress

Abstract

An apparatus is disclosed to identify defects in a cable plant including a cable comprises a carriage and a roller attached to the carriage. The roller is configured to sit on a cable plant. A motor is attached to the carriage and is coupled to the roller to cause rotation of the roller in at least a first direction, to cause movement of the carriage across the cable plant. A transmitter is attached to the carriage and an antenna is coupled to the transmitter. The antenna is configured to emit an RF signal under the control of the transmitter. If there is a defect in the cable, the RF signal may enter the cable through a defect. Detection of the RF signal in the cable is indicative of the presence of a defect in the cable and the location of the defect. Methods and systems are also disclosed.

Inventors:	Hunter; Patrick Phillip (Saint Charles, MO)
Applicant:	Charter Communications Operating, LLC (St. Louis, MO)
Family ID:	1000008779783
Assignee:	Charter Communications Operating, LLC (St. Louis, MO)
Appl. No.:	18/383382
Filed:	October 24, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240061032 A1	Feb. 22, 2024

Related U.S. Application Data

continuation parent-doc US 17398633 20210810 US 11846666 child-doc US 18383382

Publication Classification

Int. Cl.: G01R31/12 (20200101); G01R31/08 (20200101); G01R31/52 (20200101)

U.S. Cl.:

CPC G01R31/1272 (20130101); G01R31/083 (20130101); G01R31/52 (20200101);

Field of Classification Search

CPC: G01R (31/1272); G01R (31/083); G01R (31/52)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
3155897	12/1963	Rice	N/A	N/A
3185443	12/1964	Eitel	N/A	N/A
3831086	12/1973	Pesto	N/A	N/A
4072899	12/1977	Shimp	348/192	G01R 31/083
4886980	12/1988	Fernandez	N/A	N/A
5777662	12/1997	Zimmerman	N/A	N/A
6062542	12/1999	Delaney	N/A	N/A
6805333	12/2003	Delaney	N/A	N/A
9991651	12/2017	Burris	N/A	N/A
11271650	12/2021	Bonen	N/A	H04B 10/2575
2003/0033609	12/2002	Zimmerman	N/A	N/A
2004/0174309	12/2003	Terreault	N/A	N/A
2006/0248565	12/2005	Shimp	N/A	N/A
2012/0046799	12/2011	Alex	N/A	N/A
2014/0204197	12/2013	Olsson	N/A	N/A
2015/0077129	12/2014	Zinevich	324/512	G01S 5/06
2016/0137101	12/2015	Eckle	N/A	N/A
2016/0173195	12/2015	Nielsen	N/A	N/A
2017/0019148	12/2016	Williams	N/A	N/A
2017/0077988	12/2016	Flask	N/A	N/A
2017/0141845	12/2016	Totten	N/A	N/A
2019/0107572	12/2018	Williams	N/A	N/A
2020/0011921	12/2019	Jenny	N/A	N/A
2021/0285841	12/2020	Bouchard	N/A	N/A
2021/0341548	12/2020	Cencula	N/A	N/A
2022/0294201	12/2021	Bouchard	N/A	N/A
2022/0294202	12/2021	Bouchard	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
102323331	12/2010	CN	N/A
112213668	12/2020	CN	N/A
112213668	12/2020	CN	N/A
20030059762	12/2002	KR	N/A
20030059762	12/2002	KR	N/A

OTHER PUBLICATIONS

Hranac, Ron, "Tackling Serious Ingress, Communications Technology," May 2004. cited by applicant

Primary Examiner: Rodak; Lee E

Assistant Examiner: Pretlow; Demetrius R

Background/Summary

RELATED APPLICATION (1) The present application is a continuation of U.S. patent application Ser. No. 17/398,633, which was filed on Aug. 10, 2021, is assigned to the assignee of the present patent application, and is incorporated by reference herein.

FIELD OF THE INVENTION

(1) Detecting cable system signal ingress, and, more particularly, detecting cable signal ingress by emitting an RF signal by a device that crawls along the cable and monitoring the signals carried by the cable for the emitted signal.

BACKGROUND OF THE INVENTION

(2) The radio frequencies ("RF") used by cable television ("TV") system operators coincide with open air RF signals, such as air traffic control, navigation, cellular services, and the like. Federal regulations therefore require cable TV systems to maintain a low degree of cable system RF signal egress. CFR Title 47, Part 76, Subpart K-Technical Standards define requires that when operating in the in the frequency bands of 108-137 MHz and 225-400 MHz, where cable TV transmissions take place, RF leakage or egress be no more than 20 $\mu\text{V}/\text{m}$ when measured at 3 meters (§ 76.610, § 76.611).

(3) To decrease RF signal egress to below the threshold defined above, the cables used in cable TV systems to convey audio-visual signals from a headend to subscriber locations and convey messages from subscriber locations to the headend, such as coaxial cables, are typically shielded. Common types of cable shielding include foil, braid, and multilayer shielding configurations including both foil and braid, for example.

(4) Shielding can deteriorate or may be damaged by environmental conditions, such as wind, a tree falling on the cable, rubbing between the cable and a utility pole, lightning strikes, for example. Shielding may also be damaged by animals by natural deterioration due to age or animals that chew on the cable, for example. Such deterioration and damage may result in signal egress that may interfere with open air RF signals used by the other systems noted above. Signal egress points also allow for ambient signal ingress into the cable, which may also interfere with signals being transmitted along the cable and may be deleterious to the performance cable TV systems.

(5) Various techniques have been used to identify signal egress points so that they may be repaired. In one example, repair people are sent into the field with a bucket truck and a leak detector, such as a spectrum analyzer or RF meter. When a signal is detected that is above an allowable threshold, indicating excessive signal egress, the location of the signal egress is located, and the cable is repaired. Repair people may also walk under or near cables with an RF meter or other such leak detector, or drive by cables with an antenna mounted on a roof of a vehicle, for example, to detect excessive signal egress. Planes and drones carrying leak detectors spectrum are also used. Signal egress has also been identified by detecting a signal injected into the cable by the headend.

(6) In U.S. Pat. No. 5,777,662, an antenna mounted in a vehicle that emits a tone that can enter a cable via a flaw. The tone is detected by a monitoring receiver in the head end of the cable

communications system. A receiving antenna on the vehicle may also detect egress signals. A GPS antenna may also be provided on the vehicle so that location data may be correlated with detected egress signals.

SUMMARY OF THE INVENTION

(7) Since RF signals carried by cable television ("CATV) cables coincide with open air RF signals, it is difficult to differentiate between RF signals leaking from an egress point of the CATV cable RF signals from other sources. It is difficult to locate signal egress/ingress points merely by walking or driving along cable systems with metering devices. Further localization efforts are therefore required before repairs can be made. This is also true for flying leak detectors. The addition of GPS data location systems still requires time and effort to precisely locate signal egress/ingress points.

(8) Improved signal egress systems that more precisely detect and isolate the locations of signal egress/ingress points along a cable would be advantageous. The signal egress/ingress may be due to a compromise of the integrity of the shielding, such as a defect caused by environmental conditions, deterioration due to age, animals, etc. Loose components of the tap, amplifier, or other components of the cable system may also cause signal egress/ingress. Loose components are also referred to as defects herein.

(9) In accordance with an embodiment of the invention, signal ingress/egress points in a coaxial cable of a cable transmission system, such as a cable TV transmission system, are identified by exposing the coaxial cable to an RF signal with a known characteristic emitted by an antenna on a device traversing the cable and monitoring the signals in the cable for the inserted RF signal.

(10) In accordance with an embodiment of the invention, an apparatus is disclosed comprising a carriage and a roller attached to the carriage. The roller is configured to sit on a cable plant, which includes a strand, a cable, and a lashing wire lashing the cable to the strand. The apparatus further comprises a motor attached to the carriage. The motor is coupled to the roller to cause rotation of the roller in at least a first direction, to cause movement of the carriage across the cable plant in at least the first direction. A transmitter is attached to the carriage and an antenna is coupled to the transmitter. The antenna is configured to emit an RF signal under the control of the transmitter. A processing device is coupled to the motor to cause the motor to rotate in at least the first direction. The processing device is coupled to the antenna to control operation of the antenna.

(11) The processing device may be configured to turn the transmitter on and off in response to a control signal. The processing device may be further configured to cause the motor to selectively rotate in the first direction or in a second direction opposite the first direction, in response to a control signal. This causes rotation of the roller in the first direction and in the second direction, to cause movement of the carriage across the cable plant in the first direction and in the second direction. The apparatus may further include a receiver to receive the control signal.

(12) The motor may be at least one reversible motor, and the apparatus may further comprise a second roller attached to the carriage and coupled to the at least one reversible motor. The motor may then cause rotation of the first roller and a second roller in the first direction and in the second direction opposite the first direction.

(13) At least one third roller may be attached to the carriage, below the first roller and the second roller. The first roller, the second roller, and the third roller may be positioned on the carriage so that when the apparatus is placed on the cable, the first roller and the second roller are placed on an upper surface of the cable and the third roller is positioned below the cable. The position of the third roller may be adjustable so that after placement of the apparatus on the cable, the third roller is movable with respect to the cable to be brought close to or in contact with a lower surface of the cable. The carriage may define a groove through the carriage, and the second roller may include a rod perpendicular to a rotational axis of the roller. The rod may protrude from the second roller, through the groove and is moveable within the groove to adjust the position of the second roller. A connector may be provided to secure the second roller in position in the groove, in contact with the

lower surface of the cable. The rod may be threaded, and the connector may comprise a wingnut to secure the second roller to the carriage in the position. A pivoting arm may be coupled to the carriage. The pivoting arm may have a first position rotated away from the cable plant and a second position rotated toward the cable plant, to secure the apparatus to the cable plant.

(14) In accordance with another embodiment of the invention, a method of identifying a signal ingress point in a cable is disclosed comprising moving an antenna along a span of the cable in a first direction and emitting a radio-frequency signal toward the cable, by the antenna, while moving the antenna across the cable. Signals within the cable are monitored while moving the antenna across the cable. It is determined whether there is a signal ingress point based, at least in part, on whether the emitted radio-frequency signal is detected within the cable.

(15) The antenna may be supported by a carriage and the method may comprise moving the antenna across the span by moving the carriage across the cable by a motor driven roller. The signals may be monitored on a display on a control device coupled to a cable tap, for example. The signals may be monitored by identifying a peak or near peak in the displayed signal, wherein the peak is indicative of signal ingress in the cable proximate the location of the antenna. The peak may be identified automatically, for example. Automatic identification may include automatically identifying a first received signal as a peak when a second received signal received after the first received signal has a characteristic different from the characteristic of the first received signal by at least a predetermined amount. The signals may be filtered by the control device to remove signals conveyed by the cable in normal operation, and not removing the emitted signal.

(16) Movement of the antenna may be selectively controlled in the first direction and in a second a second direction opposite to the first direction, via the control device. The control device may be controlled by an operator or may be controlled automatically, based, at least in part, on the detected signal, by a processing device. If it is determined that there is a signal ingress point, the method further includes repairing the signal ingress point.

(17) In accordance with another embodiment of the invention, a system for identifying a signal ingress point in a cable is disclosed comprising a self-propelled apparatus movable on the cable. The apparatus comprises an antenna and a control device to control operation of the self-propelled apparatus. The control device comprises a transmitter to transmit control signals to the self-propelled apparatus, an electrical connector to be coupled to the cable, a receiver to receive signals from the cable, via the connector, and a display to display signals received from the cable.

(18) The self-propelled apparatus may further comprise a carriage, wherein the antenna is coupled to the carriage. At least one roller is coupled to the carriage. At least one motor is coupled to the at least one roller. The motor may be configured to cause rotation of the at least one roller in at least a first direction, to propel the self-propelled apparatus along the cable.

(19) At least one second roller may be coupled to the carriage below the at least one first roller. In this example, the first roller is configured to sit on top of the cable and the position of the second roller on the carriage is adjustable to bring the second roller into contact with a bottom of the cable. The control device may further comprise a keypad for entry of control signals by an operator.

(20) It is noted that reference to the carriage sitting on the cable includes the carriage sitting on the cable and vice a versa.

Description

BRIEF DESCRIPTION OF THE FIGURES

- (1) FIG. 1 is a side view of an example of a section of a cable plant of the cable transmission system suspended between two utility poles in a cable TV system, in which embodiments of the present invention may be used;
- (2) FIG. 2 is an enlarged side view of a portion of the cable plant of FIG. 1, showing a cable lashed

to a strand by a lashing wire;

(3) FIG. 3 is a perspective view of a CATV coaxial cable **300** including a conductor **302**, such as a copper clad aluminum conductor, for example;

(4) FIG. 4 is a side view of an example of a section of a cable plant of the cable transmission system suspended between two utility poles in a cable TV system, as in FIG. 1, including a robot or a robotic apparatus, referred to herein as a span crawler or span crawler unit, and a control device for the span crawler unit, in accordance with an embodiment of the invention;

(5) FIG. 5 is a side view of a span crawler unit corresponding to the span crawler of FIG. 4, along the cable plant;

(6) FIG. 6 is a cross-sectional view of an example of a first roller, through line **6-6** of FIG. 5;

(7) FIG. 7 is a second example of a span crawler on a segment of a cable plant, in accordance with an embodiment of the invention;

(8) FIG. 8A is a side view of a span crawler unit corresponding to the span crawler of FIG. 7, along the cable plant;

(9) FIG. 8B is rear view of the span crawler of FIG. 8A;

(10) FIG. 9A is a side view of an additional example of a span crawler, in accordance with an embodiment of the invention, including a pivot arm to secure the span crawler to a cable plant;

(11) FIG. 9B is a side view of an additional example of a span crawler, in accordance with an embodiment of the invention, including a pivot arm to secure the span crawler to a cable plant;

(12) FIG. 10 is a block diagram of an example of a control device that controls operation of a span crawler, in accordance with an embodiment of the invention;

(13) FIG. 11 is a block diagram of an example of a span crawler control device that is located on the span crawler;

(14) FIGS. 12A-12D are examples of outputs of the spectrum analyzer of FIG. 10 on the display of the control unit in FIG. 4, as the span crawler moves across a cable plant including a defect, such as a radial defect, during operation;

(15) FIG. 13 is a flowchart of an example of a method for operating a span crawler, in accordance with an embodiment of the invention; and

(16) FIG. 14 is a flowchart of an example of a method for operation of a span crawler, in accordance with an embodiment of the invention.

DESCRIPTION OF PREFERRED EMBODIMENTS

(17) FIG. 1 is a side view of an example of a section **100** of a cable plant **102** of the cable transmission system suspended between two utility poles **104**, **106** in a cable TV system, in which embodiments of the present invention may be used. Utility poles are typically from about 30 feet to about 50 feet apart, but may be up to about 500 feet apart, for example. The cable plant **102** includes a strand **108** of the cable system, which may be made of steel, that is attached to the two utility poles **104**, **106** by a clamp **110**, **112** mounted to the utility poles, as is known in the art. The cable plant **102** further includes a cable TV (“CATV”) coaxial cable **114** (hereinafter referred to as the “cable”) lashed to the cable system strand **108** by a lashing wire **116**. The lashing wire **116** may also be made of steel, for example. Lashing of the coaxial cable **114** to the strand **108** is shown in more detail in FIG. 2. As used herein, the term “cable plant” **102** refers to the combination of the strand **108**, the cable **114**, and the lashing wire **116**.

(18) A tap **120** of the cable system hangs from the cable system strand **108** proximate the utility pole **104**. The cable **114** is not lashed to the strand **108** proximate the tap **120** to facilitate connection of an end of the cable to the tap, as shown in FIG. 1. The tap **120** includes multiple ports **121** for the connection of the cable **114** to subscriber's homes and for the connection of monitoring equipment, for example.

(19) An amplifier **122** is suspended from the cable system strand **108** proximate the utility pole **108**. The coaxial cable **114** is similarly not lashed to the strand **108** proximate the cable system amplifier **122** to facilitate connection of an end of the coaxial cable to the amplifier, as is also

shown in FIG. 1.

(20) FIG. 2 is an enlarged side view of a portion **200** of the cable plant **102** of FIG. 1, proximate that tap **120** (not shown in FIG. 2), showing a cable **202** lashed to a strand **204** by a lashing wire **206**. A lashing wire clamp **208** including washers **210** is shown, for provide a termination for the lashing wire **206**, as is known in the art. A strap and spacer **212** are also shown. As is known in the art, the strap and spacer **212** assists in preventing movement of the cable **202** against the utility pole **104**, **106** shown in FIG. 1. The strap and spacer **212** may be about five (5) feet from the tap **120** in FIG. 1, for example. Another lashing wire clamp and strap and spacer may similarly be provided about five (5) feet from the amplifier **122** in FIG. 1, for example.

(21) FIG. 3 is a perspective view of a CATV coaxial cable **300** including a conductor **302**, such as a copper clad aluminum conductor, for example. Around the conductor **302** is a dielectric insulator **304**, such as a polyethylene foam. A semi-rigid shield **306**, which also acts as an outer conductor, may comprise semi-rigid aluminum, for example. A radial crack **308** that causes exposure of the dielectric insulator **304**, which may enable signal egress and signal ingress, is also shown.

(22) FIG. 4 is a side view of a section **400** of a cable plant **102** corresponding to the section **100** of FIG. 1, in which components common to FIG. 1 and FIG. 2 are commonly numbered. A system in accordance with this embodiment of the invention includes a robot or a robotic apparatus **402**, referred to herein as a span crawler **402**, and a control device **404** for the span crawler. The span crawler **402** is attached to the cable **114**, over the lashing wire **116**. An input **406** of the control device **404** is attached to a port **407** of the tap **120**, to receive RF signals from within the cable **114**.

(23) The span crawler **402** in this example includes two upper rollers **408**, for causing the span crawler **402** to move across the cable **114**. In the example of FIG. 4, the upper rollers are attached to an upper portion of a carriage **410**. When the span crawler **402** is attached to the cable **114**, between the lashing wire clamps **208**, **209** the upper rollers **408** are configured to sit on an upper surface of the cable plant. In other examples, the upper rollers may sit on the cable itself. As used herein, reference to the upper rollers **408** sitting on the cable includes sitting on the cable, and vice a versa. The upper rollers **408** may each be rubber wheels, plastic wheels, or a combination of rubber and plastic wheels, for example. Other materials may also be used. An example of an upper roller is discussed below with respect to FIG. 6. The first roller **406** and the second roller **408** are coupled to the same or different motors, which are not shown in this view. In other example, more or fewer upper rollers may be provided. In one example, the two upper rollers **408** and the motors may be configured to cause the span crawler **402** to move at a speed up to about 1.0 feet per second. In another example, the two upper rollers **408** and the motors may be configured to cause the span crawler **402** to move at a speed up to about 0.50 feet per second.

(24) The span crawler **402** is configured so that a lower portion of the carriage **410** extends below the cable **114** when the span crawler is attached to the cable. The second portion of the carriage **410** supports a transmitter **412** and an antenna **414**. The span crawler **402** is shown in more detail in FIG. 5.

(25) Rotation of the upper rollers **408** in a first rotational direction, such as clockwise, causes the span crawler unit **202** to move in a first direction across the cable **114**, in this example toward the cable system amplifier **122**. Rotation of the upper rollers **408** in a second rotational direction opposite the first direction, here counterclockwise, causes the span crawler unit **402** to move in a second direction across the CATV coaxial cable **114**, in this example toward the tap **120**.

(26) While the span crawler **202** is moved across the cable **114**, the transmitter **412** causes the antenna **414** to emit RF signals. If there is a defect in the cable **114**, such as a hole, radial crack (such as the radial crack **308** shown in FIG. 3) partial radial crack, or loose component, for example, the emitted RF waves may enter the cable **114** and be detected by the span crawler control unit **202**. As the span crawler **202** moves close to the tap **120** and the **122**, the emitted RF waves may enter the cable **114** through loose components, such as loose connectors, for example. It is noted that the span crawler **402** need not be directly positioned over the defect for emitted RF

waves to enter the cable **114**. The control unit **404** in this example is a portable, handheld unit.

(27) In accordance with certain examples of embodiments of the invention, the span crawler **402** may be up to about fifty (50) feet from a defect for enough RF waves to enter the coaxial cable **114** to be detected. In other examples, the span crawler **102** may be configured so that emitted RF waves may be detected if the span crawler is closer to or farther from a respective defect. A span crawler **402** adjacent to the lashing wire clamps **208** could, therefore, emit RF waves that would enter a defect in the cable **114** between the respective lashing wire clamp **208** and the tap **120** or the lashing wire **209** and the amplifier **122**, or loose components of the tap or the amplifier.

Alternatively, the span crawler **402** may be placed on the section of the cable **114** between the lashing wire clamp **208** and the tap **120**, and on the section of the cable **114** between the lashing wire clamp **209** and the amplifier **122**.

(28) Detection of a characteristic of the emitted RF signals, such as the amplitude or frequency of the RF signals, is indicative of a defect in the cable **114**. Detection of the characteristic and identification of the location of the defect are discussed further below. The characteristic of the emitted RF signals may be different from a corresponding characteristic the RF signals normally carried by the cable **114**, to facilitate detection of the emitted RF signals. For example, the emitted RF signals may have an amplitude different from the amplitudes of the RF signals carried by the cable **114**, such as higher amplitude, for example. The amplitude of the emitted signal may be about 10 decibels or more above the amplitude of the RF signals carried by the cable **114** in normal operation, for example. In addition to or instead of a different amplitude, the emitted RF signals may have a frequency different from the frequencies of the RF signals normally carried by the cable **114**. The RF signals carried by the cable **114** may also be filtered by the span crawler control **202** to facilitate detection by the span crawler control, as discussed further below.

(29) The control unit **404** includes a display **418**, a keypad **420**, and arrow keys **422**. The arrow keys **422** enable an operator, such as a cable repair person, to control operation of the span crawler control unit **402**. The control unit **404** includes a spectrum analyzer, a signal level meter, or similarly functioning device (not shown in FIG. 4), as discussed below with respect to FIG. 10, for example. The control unit **404** may communicate with the span crawler **402** wirelessly, such as via WIFI or Bluetooth, for example. Other wireless techniques that may be used include Ble, Zigbee, Z-Wave, 6LoWPAN, NFC, WiFi Direct, GSM, LTE, LoRa, NB-IoT, or LTE-M, for example.

(30) FIG. 5 is a side view of a span crawler unit **500** corresponding to the span crawler **402** of FIG. 4, along the cable plant **102**. The strand **108**, the cable **114**, and the lashing wire **116** are shown in cross-section. Above the cable plant **102** is a first upper roller **502** coupled to a carriage **504**. A second upper roller, which is not shown in this view, is behind the first upper roller **502**. The first upper roller **502** is shown connected to a carriage **504**.

(31) In this example, the first upper roller **502** includes opposing sidewalls **506**, **508** and an optional concave curved surface **510** between the side walls. The curvature of the concave curved surface **510** matches the curvature of the portion of the cable plant **102** engaged by the first upper roller **802** so that the first upper roller **502** fits on the cable plant. Horizontal lines **512** following the curvature of the concave curved surface **510** represent optional protrusions on the concave curved surface, which may facilitate engagement of the first roller **502** with the lashing wire **116** and the remainder of the cable plant **102**. The protrusions **512** may be grooves, teeth, or pointy tips, for example. The protrusions **512** may have the configuration shown in FIG. 6, for example, as discussed further below. A second upper roller, which has the same configuration as the first upper roller **502**, is behind the first upper roller and is not shown in this view. The first upper roller **502** (and the second upper roller) be rubber wheels, plastic wheels, or a combination of rubber and plastic wheels, for example. Other materials may also be used. An example of an upper roller is discussed below with respect to FIG. 6. While the concave curved surface **510** would be in contact with the cable plant **102** when the span crawler **500** is placed on the cable plant, in FIG. 5, the concave curved surface **510** and the cable plant are shown separated for illustrative purposes.

(32) FIG. 6 is a cross-sectional view of an example of a first roller **600**, through line 6-6 of FIG. 5. The first roller **600** includes a central opening **602** for receipt of an axle or rod coupled to a motor, as discussed further below. A curved concave surface **604**, which is a circle in this view, has a series of rectangular protrusions **606** with flat tips **608**. Eight (8) protrusions **606** are shown in this example. More or fewer protrusions **606** may be provided. Each protrusion may extend up to one-quarter inch from the curved concave surface **604**, for example. In the example of FIG. 6, the first roller **600** includes an inner portion **610**, which may be a hard plastic, and an outer portion **612**, which may be rubber, such as a soft rubber, for example. Other materials may be used as well.

(33) Returning to FIG. 5, a transmitter **514** is mounted to the carriage **504**. An antenna **516** is electrically coupled to the transmitter **510**, between the transmitter and the first upper roller **502**. The span crawler **500** is configured so that the antenna **512** faces the underside of the cable **114** when the span crawler **500** is attached to the cable plant **102**. RF waves **518** are shown in FIG. 5 being emitted from the antenna **512** toward the cable **114**. While in this example the transmitter **510** and the antenna **512** are shown below the cable **114** when the span crawler **500** is attached to the cable, in other configurations the transmitter and the antenna may be above the cable, adjacent to the first upper roller **306**, the second upper roller, or between the upper rollers, for example.

(34) A motor **520** is connected to an opposite side of the carriage **504** than the first upper roller **502**. The motor **520** is coupled to the first upper roller through the carriage, via an axle or rod **505**. The motor **520** selectively causes rotation of the first upper roller in a first direction and in a second direction opposite the first direction. While in this example the motor **508** is on an opposite side of the carriage **504** than the first upper roller **502**, in other configurations, the motor and the first upper roller may be mounted on the same side of the carriage. In this case, the motor may cause rotation of the first roller **306** by one or more pulleys and/or gears, for example. The motor **508** may also drive the second upper roller by one or more pulleys and/or gears, or a separate motor may be provided to drive the second upper roller.

(35) A span crawler control device **522** is provided on the carriage **504** for receiving control signals from a control device, such as the control device **404** of FIG. 4. The span crawler control device **516**, which may be a printed circuit board (PCB), may be connected to the first motor **520**, the second motor, and the transmitter **510** via wires, conductive strips, or wirelessly, for example. FIG. 11 is a block diagram of an example of the span crawler device **522** of FIG. 5.

(36) In one example, a lower portion or half **524** of the span crawler **500** below the cable plant **102** is heavier than the upper portion or half **526** above the cable plant, to assist in maintaining the proper orientation of the span crawler while the span crawler is moving along the cable plant. The span crawler **700** may weigh from about 3 pounds to about 5 pounds, for example, and the lower portion **514** may be at least about 1.5 times heavier than the upper portion **526**, for example.

(37) FIG. 7 is a second example of a span crawler **700** on a segment of a cable plant **702**, in accordance with an embodiment of the invention. In addition to the two upper rollers **704** connected to a carriage **706**, one or more lower rollers **708**, are positioned below the upper rollers, under the cable plant **102** when the span crawler is positioned on the cable plant. In this example, the span crawler **700** includes two lower rollers **708**. Also supported by the carriage are a transmitter **710**. An antenna **712** protrudes from the transmitter **710**, toward the cable plant **102**, as discussed above with respect to FIG. 4 and FIG. 5. The lower rollers **704** in this example secure the span crawler **700** to the cable plant **102**. They may also assist in maintaining the span crawler in a desired orientation on the cable plant, as discussed below.

(38) FIG. 8A is a side view of a span crawler unit **800** corresponding to the span crawler **700** of FIG. 7, along the cable plant **102**. Cross-sections of the strand **108**, the cable **114**, and the lashing wire **116** of the hardline are shown. In this example, a first upper roller **802**, which has the same configuration as the first roller **502** of FIG. 5, is coupled to a carriage **804**. A second upper roller, which has the same configuration as the first upper roller **802**, is behind the first upper roller and is not shown in this view. The first upper roller **802** (and the second upper roller) may be made of

molded rubber or plastic, or a combination of materials, for example, as discussed above.

(39) A first motor **806** is attached to an opposite side of the carriage **804** as the first upper roller **802** and is coupled to the first upper roller via an axle or rod **808**. The first motor **808** is configured to selectively drive the first upper roller **802** in a clockwise direction and in a counterclockwise direction. A second motor (not shown in this view) is similarly provided for driving the second upper roller in a clockwise and in a counterclockwise direction.

(40) A first lower roller **810** is provided on the carriage **804**, below the first upper roller **802**, to secure the span crawler to the cable plant **102**. The first lower roller **810** is rotatable about an axle or rod **812** that extends through the carriage **804**. The first lower roller **810** may each be rubber wheels, plastic wheels, or a combination of rubber and plastic wheels, for example. Other materials may also be used. A second lower roller, not shown in this view, may be provided below the second upper roller. The surface of the first lower roller **810** (and the second lower roller) may be flat, as shown in FIG. **8A** or may be concave, as in the first upper roller **802**.

(41) It would be apparent to one of ordinary skill in the art that there must be sufficient space between the first upper roller **802** and the first lower roller **810** for the span crawler **800** to be placed on the cable plant **102**. The vertical position of the first lower roller **810** is therefore adjustable so that it can be positioned a sufficient distance away from the first upper roller **802** so that the span crawler can be placed onto the cable plant **102** and then moved closer to or in contact with the cable plant after the span crawler is placed on the cable plant. In this example, at least a portion of the axle or rod **812** is threaded and the first lower roller **810** is secured to the carriage **804** in a desired vertical position via a wingnut **813**. The adjustment mechanism is discussed in more detail below with respect to FIG. **8B**.

(42) A transmitter **820** is also shown connected to the carriage **804**. An antenna **822** is shown coupled to the transmitter **820**. RF waves **823** are shown schematically, being emitted by the antenna **822**. A span crawler control device **824** is provided on the carriage **804** for receiving control signals from a control device, such as the control device **404** of FIG. **4**. The span crawler control device **824** may be a printed circuit board (PCB) and may be connected to the first motor **806** and the transmitter **820** via wires, conductive strips, or wirelessly, for example.

(43) FIG. **8B** is rear view of the span crawler **800** of FIG. **8A**, showing an example of a mechanism for adjusting the vertical position of a first lower roller **810** and a second lower roller **822** on the carriage **804**. The mechanism in this example includes a first vertical groove **825** and a second vertical groove **826**, each defined through the carriage **804**. The axle or rod **812** of the first lower roller **810** and an axle or rod **828** of the second lower roller **822** each extend through a respective first and second vertical groove **825**, **826**. The portion of the axle or rods **812**, **828** extending through the respective first and second vertical grooves **825**, **826**, respectively, are threaded. Wingnuts **813**, **830** are on the threaded axles or rods **812**, **828**.

(44) The vertical position of the first lower roller **810** and the second lower roller **822** within the respective first and second vertical grooves **825**, **826** may be adjusted by a user when the span crawler **800** is placed on the cable plant **102** by manually moving the respective wingnut **813**, **830** vertically up and down within the respective first and second vertical grooves **825**, **826**. The respective axles or rods **812**, **828** may also be grasped and moved along with or instead of the respective wingnuts **813**, **830** to move the first lower roller **810** and the second lower roller **822** vertically up and down. Portions of the axle or rod **812**, **828** extending through to the rear of the carriage **804**, behind the wingnuts **813**, **830**, may also be attached to each other by a horizontally extending beam (not shown) so that the first lower roller **810** and the second lower roller **822** may be moved vertically up and down together by grasping and moving the horizontally extending beam. In another example, a single lower roller may be used, centered between and vertically below the first upper roller **924** and the second upper roller **928**. When the first lower roller **810** and the second lower roller **822** are in a desired position, the respective wingnuts **813**, **830** may be tightened, securing the respective axles **812**, **828** to the carriage **804**. It would be understood by

those of ordinary skill in the art that additional structures may be provided on the first axle or rod **812, 828**. For example, a washer (not shown) may be fixed to the axle or rod **812, 828** on the front side of the carriage **804** so that when the wingnuts **813, 830** are tightened, the axle or rod will be secured to the carriage. Another washer (not shown) may also be provided between each wingnut **813, 830** and the carriage **804**.

(45) FIG. **8B** also shows a first motor **834** for driving the first upper roller **802** (shown in phantom) and a second motor **836** for driving a second upper roller **838** (also shown in phantom). The first upper roller **802** and the second upper roller **838** are shown in phantom because they are behind the carriage **804** in this view. The motors **834, 836** are configured to selectively rotate the first upper roller **924** and the second upper roller **928** clockwise and counterclockwise.

(46) Instead of the wingnuts **813, 830**, a clamp, such as cam clamp, attached to the portion of the axles or rods **812, 828** extending through the carriage **804**, may be used to tighten the first lower roller **810** and the second lower roller **822**, respectively, to the carriage, for example. In another example, one or more springs may be mounted on or within the carriage **804** to push the first lower roller **810** and the second lower roller **822** toward and against the cable plant **102**. The first lower roller **810** and the second lower roller **822** may be moved downward manually, against the force of the spring, during attachment of the span crawler to the coaxial cable **102**. After positioning the span crawler **800** on the cable plant **102** and releasing the downward force on the first lower roller **810** and the second lower roller **822**, the springs will push the first lower roller and the second lower roller against the cable plant **102**.

(47) The weight of the span crawler **800** causes sufficient contact between the concave curved surface of the first roller **802** and the cable plant **102** for rotation of the first roller **302** (and the second upper roller) to cause the span crawler **800** to move across the cable. The span crawler **800** may weigh from about 3 pounds to about 5 pounds, for example. As above, the lower portion or half of the span crawler **800** may be at least about 1.5 times heavier than the upper portion or half, for example.

(48) The first lower roller **814** (and the second lower roller) are positioned to bear against the cable **114** so that the first lower roller (and the second lower roller) rotate as the span crawler **800** moves across the cable. The first lower roller **814** (and the second lower roller) are not positioned to bear so tightly against cable plant **102** that movement of the span crawler **800** is impeded.

(49) The weight of the span crawler **800** causes sufficient contact between the concave curved surface of the first roller **802** and the cable plant **102** for rotation of the first roller **810** and the second upper roller **822** to cause the span crawler **800** to move across the cable. The span crawler **800** may weigh from about 3 pounds to about 5 pounds, for example. As above, the lower portion or half of the span crawler **800** may be at least about 1.5 times heavier than the upper portion or half, for example.

(50) To further secure the span crawler **800** to the cable plant **102**, the first lower roller **810** and the second lower roller **822** may be moved to be within about 3 inches of the cable plant **102**, such as within 2 inches or within 1 inch of the cable plant, for example. In this case, the first lower roller **810** and the second lower roller **822** may periodically come into contact with the cable plant **102** as the span crawler moves across the cable plant. When in contact with the cable plant **102**, the first lower roller **810** and the second lower roller **822** may rotate as the span crawler moves along the cable plant. The first lower roller **810** and the second lower roller **822** may also be positioned to bear against the cable plant **102**, in which case the first lower roller and the second lower roller would rotate as the span crawler **800** moves across the cable plant. The first lower roller **810** and the second lower roller **822** should not be positioned to bear so tightly against cable plant **102** that movement of the span crawler **800** is impeded.

(51) FIG. **9A** is a side view of another example of a span crawler **900A** that is similar to the span crawler **500** of FIG. **5** and the span crawler **800** of FIG. **7**, FIG. **8A**, and FIG. **8B**, except that instead of the second roller or rollers **708** (FIG. **7**), the span crawler is secured to the cable plant

102 via a pivoting arm, in accordance with an embodiment of the invention. Components common to FIG. 5, FIG. 7, FIG. **8A**, and FIG. **8B** that are not discussed with respect to FIG. **9A**, are not numbered in FIG. **9A**. The span crawler **900A** includes a pivoting arm **902** to secure the span crawler to the cable plant **102**. The pivoting arm **902** in this example has been an L-shaped arm including a first portion **904** and a second portion **906** transverse to the first arm. The pivoting arm **902** may also have other shapes. The pivoting arm **902** pivots about a pivot point **908** on the carriage **910**. In one example, the pivot point **908** may be a rod extending from the side of the carriage **910**, while pivoting arm **902** may have a collar that rotates around the rod, for example. A second pivoting arm may also be similarly coupled to the opposite side of the carriage, which is not shown in this view.

(52) The pivoting arm **902** has a first position away from the cable plant **102**. An example of a first position is shown in solid line in FIG. **9A**. The pivoting arm **902** also has a second position, shown in phantom, where the pivoting arm is rotated about the pivot point **908** so that the first portion **904** is close to or in contact with a lower portion of the cable plant **102** and the second arm **906** is close to or in contact with an outer side of the cable plant. As with the first lower roller **814** discussed above, the second portion **906** may be within about 3 inches of the cable plant **102**, such as within 2 inches or within 1 inch of the cable plant, for example. In this example, when in the second position, the first portion **904** is in a horizontal position and the second arm **906** is perpendicular to the first arm. Through holes through the rod and the collar may be positioned so that they are aligned when the pivoting arm is in the second position. The pivoting arm **902** may then be locked into position by a cotter pin or a split pin **914** inserted through aligned openings in the collar and the rod, for example.

(53) FIG. **9B** is a side view of another example of a span crawler **900B** that is similar to the span crawler **900A** of FIG. **9A**. Components common to FIG. **9A** are commonly numbered. Components common to FIG. 5, FIG. 7, FIG. **8A**, and FIG. **8B** that are not discussed with respect to FIG. **9B** are not numbered in FIG. **9B**. In the example of FIG. **9B**, the pivoting arm **902** is coupled to a pivot point **908** that is located on a portion of the axle or rod **916** that extends through the first upper roller **918**. The pivoting arm **902** in this example is an L-shaped arm including a first portion **904** and a second portion **906** transverse to the first arm, as in FIG. **9A**. The pivoting arm **902** may also have other shapes. The pivot point **908** may be a rod extending through the axle or rod **916**, while the pivoting arm **902** may have a collar that rotates around the rod, as in FIG. **9A**, for example. A second pivoting arm may also be similarly coupled to an axle or rod extending through a second upper roller behind the first upper roller, which are not shown in this view. The pivoting arm **902** has a first position away from the cable plant **102**, shown in solid line in FIG. **9A**, and a second position, shown in phantom. In the second position, the pivoting arm **902** is rotated about the pivot point **908** so that the second portion **906** is close to or in contact with a lower portion of the cable plant **102** and the first portion **904** is close to or in contact with an outer side of the cable plant. As in FIG. **9A**, discussed above, the second portion **906** may be within about 3 inches of the cable plant **102**, such as within 2 inches or within 1 inch of the cable plant, for example. Through holes through the rod and the collar may be positioned so that they are aligned when the pivoting arm is in the second position. The pivoting arm **902** may then be locked into position by a cotter pin or a split pin **914** inserted through aligned openings in the collar and the rod, for example.

(54) FIG. **10** is a block diagram of an example of a control device **1000** that controls operation of a span crawler, in accordance with an embodiment of the invention. The control device **1000** provides control signals to the span crawler to control the operation of the motors (on/off, rotate clockwise/counterclockwise) and the transmitter (turn transmitter on/off), which controls the signals emitted by the antenna. The control unit **1000** includes a processing device **1002** controlled by inputs provided by a user via a keypad **1004** and/or in accordance with software stored in ROM **1006**, for example. The processing device **1002** may be a microprocessor, a microcontroller, or another such control device or circuit, for example. RAM **1007** is also provided to store

information received from monitoring the signals carried by the cable **1008** via the tap **1010**, for example, such as amplitudes of frequencies, for example, as discussed below. At least certain of the components of the control device **1000** may be on one or more printed circuit boards (PCBs), for example.

(55) A wireless transmitter **1012** is provided for wirelessly sending control signals to the span crawler. The processing device **1002** sends digital control signals to the transmitter **1012**, which converts the digital signals into analog signals for transmission by an antenna **1014**. A digital-to-analog converter may be provided between the processing device **1002** and the transmitter **1012** to convert the digital signals to analog signals, for example. In one example, the transmitter **1012** may be configured to generate and transmit RF signals in one of the eighty (80) channels defined by 47 CFR Part 95, Radio Control Radio Service, between 72.0 MHz and 76.0 MHz. Each channel is 8 kHz wide. The transmitter may be configured to generate and transmit RF signals having a frequency centered at 72.0 MHz, ± 4 kHz for example. It is noted that the additional six (6) channels defined by 47 CFR Part 95, Radio Control Radio Service in the range of 26.995 MHz to 27.255 MHz could, in an example discussed below interfere with the signals injected by the span crawler and would not, therefore, be used. If a different RF frequency is injected by the span crawler, then the transmitter **1012** could be configured to generate and transmit RF signals in one of those six (6) channels. Other frequencies and frequency bands may be used, as well.

(56) A receiver **1016** is provided for receiving RF signals from the cable **1008** via the tap **1010**. In this example, analog signals received by the receiver **1016** are provided to an optional band pass filter **1018** to remove the signals carried by the cable **1008** in normal operation, such as cable programming signals, for example. This facilitates detection of the RF signal emitted by the span crawler. If the band pass filter **1018** is not provided, then detection may be facilitated by emitting an RF signal with a characteristic having a greater difference from the characteristics of the signals carried by the cable, **1008**, such as a much higher amplitude and/or higher/lower frequency than if the band pass filter **1018** is included, as discussed above.

(57) A receiver **1016** is provided for receiving RF signals from the cable **1008** via the tap **1010**. In this example, analog signals received by the receiver **1016** are provided to an optional band pass filter **1018** to remove the signals carried by the cable **1008** in normal operation, such as cable programming signals, for example. This facilitates detection of the RF signal emitted by the span crawler. If the band pass filter **1018** is not provided, then detection may be facilitated by emitting an RF signal with a characteristic having a greater difference from the characteristics of the signals carried by the cable, **1008**, such as a much higher amplitude and/or higher or lower frequency than if the band pass filter **1018** is included, as discussed above.

(58) The filtered signal in this example is provided to an analog-to-digital converter **1020**. The resulting digital signal is provided to a spectrum analyzer **1022**. Alternatively, the resulting digital signal may be provided to another device for signal analysis, such as a signal level meter, for example. The analyzed signals are provided to the processing device **1002**, which further analyze the signals and configure the signals for display. The processing device **1002** outputs digital signals based on the received signals, which may be converted to analog signals for display by a digital-to-analog converter **1024**. The analog signals are displayed on the display **1026**. A battery **1028** is provided in this example to provide power to the components of the control device **1000**. An On/Off button **1030** is provided in the casing of the control device **1000** to turn the control device On and Off. If the processing device **1000** is programmed to operate automatically, the On/Off button **1030** may also be used to start automatic operation of the control device **1000**, as discussed further below.

(59) FIG. 11 is a block diagram of an example of a span crawler control device **1100** that is located on the span crawler and receives control signals from the control unit **1000** of FIG. 10, for example, to control operation of the motors **1102**, transmitter **1104**, and antenna **1106** of the span crawler, as discussed herein. The span crawler control **1100** receives the control signals via a

receiver **1108**, such as a wireless receiver, for example. If the received signals are analog signals, an analog-to-digital converter **1110** is provided to convert the received control signals to digital signals, which are then provided to a processing device **1112**. Based on the control signals, the processing device **1112** controls the one or more motors **1102** along line **1114** and the transmitter **1104** along line **1116**, which may be a wires or conductive strips. Alternatively, either or both lines **114**, **1116** may represent wireless connections. In this case, one or more transmitters would be provided in the span crawler control **1100** and receivers would be provided on the motors **1102** and/or transmitter **1104**.

(60) The transmitter **1104** causes the antenna **1106** to emit RF signals to identify an ingress point, as discussed above. In one example, the transmitter **1104** is configured to generate and transmit RF signals in any of the forty (40) channels in the range of 26.965 MHz to 27.405 MHz defined by 47 CFR Part 95, Citizens Band Radio Service, except for Channel 9 (27.065 MHz), which is reserved for emergency communications. The forty (40) channels are ten (10) kHz wide. In one example, the transmitter **1104** is configured to generate and transmit RF signals having a frequency centered at 27.125 MHz $\pm$ 5 kHz. Other frequencies and frequency bands may be used, as well.

(61) A memory **1118** may be provided, if necessary. The memory **1118** may store software for controlling the operation of the span crawler, for example. The processing device **1112** may be a microprocessor, a microcontroller, or another such control device or circuit, for example. A battery **1120** is provided in this example to provide power to the components of the span crawler **1100**, including the motor(s) **1102**, the transmitter **1104**, and the processing device **1112**.

(62) FIG. 12A-12D are examples of outputs of the spectrum analyzer **1022** of FIG. 10 on the display **418** of the control unit **404** in FIG. 4, as the span crawler **410** (or the span crawler **700** of FIG. 7) moves across a cable plant **102** including a defect, such as a radial defect, during operation. The X-axis is a Frequency F of the detected signal, and the Y-axis is the amplitude A of the detected signal. In this example, the RF cable signals normally carried by the cable have been filtered by a band pass filter **1018**, as discussed above with respect to FIG. 10. In FIG. 12A, the span crawler is so far from the defect that not enough of the RF signals emitted by the span crawler enter the cable through the defect to be detected. In one example, if the span crawler is over about 50 feet from the defect, then the emitted RF signal will not be detected. The detected filtered signal line **1202** is therefore at a baseline or at zero (0), as shown in FIG. 12A, for example.

(63) FIG. 12B is an example of the output of the spectrum analyzer **1022** on the display **418** when the span crawler **410**, **700** is close enough to the defect for some of the emitted RF signals to be injected into the cable **114** through the defect. An increasing amount of RF signals enters the cable, as indicated by the rising portion of the line **1204**. A low amplitude signal A1 is detected at the frequency band of the injected signal.

(64) FIG. 12C is an example of the output of the spectrum analyzer **1022** on the display **418** when the span crawler **410**, **700** is close to or at the location of the defect. A high amplitude signal A2 is detected that is greater than A1, at the frequency band of the injected signal. If the span crawler **410**, **700** is at the location of the defect, then the detected amplitude will be a peak amplitude.

(65) FIG. 12D is an example of the output of the spectrum analyzer **1022** on the display **418** when the span crawler **410**, **700** has passed the location of the defect. Since the span crawler **410**, **700** is farther from the defect, less of the emitted RF signal is injected into the cable **114** through the defect. A lower amplitude signal is therefore detected than the detected signal in FIG. 12C. In this example, the detected signal is again A1 because the span crawler **410**, **700** is at about the same distance beyond the defect that the span crawler was in front of the defect when the signal was detected in FIG. 12B. As the span crawler **410**, **700** continues farther past the defect, the output of the spectrum analyzer **1022** on the display **418** may return to zero (0), as in FIG. 12A.

(66) In one example, the user may visually identify the approximate location of the defect based on the location of the span crawler **410**, **700** on the cable plant **102** when a peak or near peak amplitude A2 is detected and displayed. The near peak may be within 10% to 30% of the peak

amplitude, for example, such as between 10% to 20%, for example. The user would then examine the cable **114** in the visually identified area of the span crawler **410, 700** to locate the defect or loose component and repair the defect, in a manner known in the art. The user may stop the span crawler **410, 700** when the peak or near peak is located and go to the location of the span crawler to find the defect. Alternatively, the user may note the approximate location of the defect and continue the traversal of the cable plant **102** with the span crawler **410, 700** to locate other defects before proceeding to repair the defect or defects in the cable.

(67) In another example, when the user notices on the display the decrease in the detected amplitude A (that a peak A is passed and the amplitude is decreasing), the user may reverse the direction of the span crawler **410, 700** to more precisely locate the defect. The user may reverse the direction when the detected amplitude is observed to drop from about 10% to about 20% from the peak amplitude, for example.

(68) The example of FIGS. **12A-12D** is described with respect to a user visually observing the display and controlling the movement of the span crawler. In another example, the analysis of the received signal and control of the movement of the span crawler may be performed automatically under the control of the processing device **1002** of the control unit of FIG. **10**, for example, or by the processing device **1112** of the span crawler control **1100** of FIG. **11**. The software controlling operation of the respective processing device **1002, 1112**, may analyze the detected signals, store detected amplitudes, such as in the RAM **1007** and/or the memory **1118**, for example, and compare a current detected amplitude to prior detected amplitudes, for example.

(69) The software may cause the span crawler to stop or may cause the span crawler to reverse when a current detected amplitude is less than the highest prior detected amplitude. The difference between a current detected amplitude and the highest prior detected amplitude may be greater than a threshold before the highest prior detected amplitude is considered to be a peak amplitude. The threshold may be 5% or 10% or may be in a range of from 5% to about 10%, for example. Other thresholds and threshold ranges may be used. Amplitudes may be detected at predetermined time intervals, such as from about every 1 second to about every 60 seconds after the span crawler **410, 700** starts to emit RF signals, for example. The prior detected amplitude may be detected 1 second, 5 seconds, 10 seconds earlier, 30 seconds earlier, or 60 seconds earlier, for example. In another example, one of the processing devices **1002, 1112** may analyze the detected signals and provide notice to the user when the change in the detected characteristic is from about 5% to about 10%, for example. As discussed above, other characteristics of the detected signals may be used besides the amplitude of the frequency. Automatic analysis of the signals allows for more detection of smaller differences than would visual analysis.

(70) FIG. **13** is a flowchart of an example of a method **1300** for operating a span crawler, such as the span crawler **410, 700**, in accordance with an embodiment of the invention. In this embodiment of the invention, the operation of the span crawler is controlled by a user, via a control device, such as the control device **404, 1000**. The order of the blocks in the method **1300** may be varied. In this example, the span crawler **410, 700** is placed on the cable plant **102**, in block **1302**, and the control device **404, 1000** is electrically connected to the cable **114**, such as through a tap port **121** of the tap **120, 1010**, by a user.

(71) After turning on the span crawler **410, 700** via the On/Off button **1120** and turning on the control device **404, 1000** via the On/Off button **1030**, for example, the user turns on the transmitter **412, 514, 710** of the span crawler **410, 700**, via the control device **404, 1000**, in block **1306**. The user causes the span crawler to move across the cable plant **102** in a first direction, in block **1308**, via the control device **494, 700**, in block **1308**, by causing rotation of the one or more first rollers **408, 502, 704, 802, 838** on the span crawler.

(72) Signals received from the cable **114** are detected by the control device **404, 700**, via the receiver **1016**, in block **1310**, and are displayed by the processing device **1002** of the control device on the display **418, 1026**, in block **1310**. The user visually identifies a peak or near peak amplitude

by observing the amplitude of the displayed signal rise and start to fall, in block **1312**. A visual observation of a decrease in amplitude of from about 20% to about 30% is sufficient to visually identify a peak in this example.

(73) When the peak is identified on the display **1026**, the span crawler may be stopped, in block **1314**. The location on the cable **114** corresponding to the peak in amplitude may be approximately located by the user, in block **1316**. The direction of the span crawler **410, 700** may be reversed by the user, via the control device **404, 700**, to better identify the location corresponding to the peak, if desired. The area of the cable **114** that resulted in the peak may be physically examined by a user to locate the defect, in a manner known in the art, in block **1318**. The defect may then be repaired, in block **1320**, also in a manner known in the art.

(74) FIG. **14** is a flowchart of an example of a method **1400** for operation of a span crawler, such as the span crawler **410, 700**, in accordance with an embodiment of the invention. In this embodiment of the invention, the operation of the span crawler is automatically controlled by the processing device **1002** of the control device **1000**, for example, in accordance with a program stored in the ROM **1006**, for example. As in FIG. **13**, the order of the blocks in the method **1400** may be varied. The method **1400** will be described with respect to common blocks in FIG. **13**.

(75) In this example, the method **1400** starts with performance of blocks **1302-1304** of FIG. **13** by a user. The user then activates the span crawler **410, 700** to start operation, such as by turning on an “On/Off” button **1030** on the control device **404, 1000**, for example. The control device then automatically turns on the transmitter, in block **1306**, causes the span crawler **410, 700** to move across the cable in a first direction, in block **1308**, and detects signals from the cable **114**, in block **1310**. The method then proceeds to the method **1400** of FIG. **14**.

(76) Amplitudes of detected signals are stored, such as in the RAM **1007**, in block **1402**. The amplitude of a current detected signal is compared to prior detected amplitudes stored in the RAM **1007**, by the processing device **1002**, in block **1406**. It is then determined whether the amplitude of a current detected signal is less than the highest prior detected amplitude, in block **1406**. If not (No in block **1406**), then blocks **1404** and **1406** are repeated until it is determined that the amplitude of a current detected signal is less than the highest prior detected amplitude (Yes in block **1406**). Block **1406** may determine whether the amplitude of a current detected signal is less than the highest prior detected amplitude by a predetermined amount, such as five (5) or ten (10) percent less, for example.

(77) When the amplitude of a current detected signal is less than the highest prior detected amplitude or less by the predetermined amount (Yes in block **1406**), the method **1400** returns to block **1314** of FIG. **13** to stop the span crawler, identify the location of the span crawler corresponding to the peak amplitude (in block **1316**), locate the defect (in block **1318**), and repair the defect (in block **1318**), as discussed above.

(78) Examples of implementations of embodiments of the invention are described above. Modifications may be made to those examples without departing from the scope of the invention, which is defined by the claims, below.

Claims

1. A method of identifying a signal ingress point in a cable including shielding around a conductor, the method comprising: moving an antenna along a span of the cable in a first direction by a carriage supported by the cable; emitting a radio-frequency signal toward the cable, by the antenna, while moving the antenna across the cable; monitoring the signals within the cable while moving the antenna across the cable; and determining whether there is a signal ingress point through the shielding based, at least in part, on whether the emitted radio-frequency signal is detected within the conductor.

2. The method of claim 1, wherein the antenna is supported by a carriage, the method comprising

moving the antenna across the span by: moving the carriage across the cable by a motor driven roller.

3. The method of claim 1, comprising: monitoring the detected signals on a display on a control device coupled to a cable tap.
4. The method of claim 3, wherein monitoring the signals on the display comprises: identifying a peak or near peak in the displayed signal, wherein the peak or near peak is indicative of signal ingress in the cable proximate the location of the antenna.
5. The method of claim 4, comprising: automatically identifying the peak by a processing device.
6. The method of claim 5, comprising: automatically identifying a first received signal as a peak or near peak when a second received signal received after the first received signal has a characteristic different from the characteristic of the first received signal by at least a predetermined amount.
7. The method of claim 3, further comprising: filtering the signals by the control device to remove signals conveyed by the conductor in normal operation, and not removing the emitted signal.
8. The method of claim 1, further comprising: selectively controlling movement of the carriage across the cable in the first direction and in a second direction opposite to the first direction, via a control device.
9. The method of claim 8, further comprising: operating the control device by an operator; or operating the control device automatically based, at least in part, on the detected signal, by a processing device.
10. The method of claim 1, further comprising: if it is determined that there is a signal ingress point, repairing the signal ingress point.
11. The method of claim 1, wherein the signal ingress point comprises a defect in the shielding.
12. A system for identifying a signal ingress point in a cable, the system comprising: a self-propelled apparatus movable along a span of the cable, the apparatus comprising: an antenna configured to emit an RF signal toward the cable; and a control device to control operation of the self-propelled apparatus, the control device comprising: a transmitter to transmit control signals to the self-propelled apparatus; an electrical connector to be coupled to the cable; a receiver to receive signals from the cable, via the connector; and a display to display signals received from the cable, wherein the display of the emitted RF signal on the display is indicative of signal ingress in the cable proximate the location of the antenna with respect to the cable.
13. The system of claim 12, wherein the self-propelled apparatus further comprises: a carriage supporting the antenna; at least one roller coupled to the carriage; and at least one motor coupled to the at least one roller, the motor being configured to cause rotation of the at least one roller in at least a first direction, to cause movement of the self-propelled apparatus along the cable.
14. The system of claim 13, further comprising: at least one second roller coupled to the carriage below the at least one first roller, wherein the first roller is configured to sit on top of the cable and the position of the second roller on the carriage is adjustable to bring the second roller close to or into contact with a bottom of the cable.
15. The system of claim 12, further comprising: a pivoting arm coupled to the carriage, the pivoting arm having a first position rotated away from the cable and a second position rotated toward the cable when the apparatus is positioned on the cable, to secure the apparatus to the cable.
16. The system of claim 12, wherein: the apparatus or the control device further comprise a processing device configured to identify a first received signal as a peak or near peak signal when a second received signal received after the first received signal has a characteristic different from the characteristic of the first received signal by a predetermined amount; and the peak or near peak is indicative of signal ingress in the cable proximate the location of the antenna.
17. The system of claim 16, wherein the apparatus or the control device further comprises a processing device configured to filter the signals to remove signals conveyed by the cable in normal operation, and not remove the emitted signal.
18. The system of claim 12, wherein the cable includes shielding, and the signal ingress point

comprises a defect in the shielding.

19. The system of claim 12, wherein the signal ingress point comprises a loose component of the cable.

20. An apparatus comprising: a carriage; a first roller attached to the carriage, the first roller being configured to sit on an upper surface of a cable plant including a cable, a strand, and a lashing wire lashing the cable to the strand; a second roller attached to the carriage below the first roller, wherein the second roller is positioned on the carriage so that when the apparatus is placed on the cable plant, the second roller is positioned below the cable plant, the position of the second roller being adjustable so that after placement of the apparatus on the cable plant, the third second roller is positionable close to or in contact with a lower surface of the cable plant, to secure the apparatus to the cable plant; a motor attached to the carriage, the motor being coupled to the first roller to cause rotation of the first roller in at least a first direction, to cause movement of the carriage across the cable plant in at least the first direction; a transmitter attached to the carriage; an antenna coupled to the transmitter, the antenna being configured to emit an RF signal under the control of the transmitter toward the cable plant when the carriage is placed on the cable plant; and a processing device coupled to the motor and to the transmitter, the processing device configured to: cause the motor to rotate in at least the first direction; and control operation of the transmitter.

21. The apparatus of claim 20, wherein: the carriage defines a groove through the carriage; the second roller includes a rod perpendicular to a rotational axis of the roller, the rod protruding from the second roller, through the groove, the rod being moveable within the groove to adjust the position of the second roller; and a connector for securing the second roller in position in the groove, close to or in contact with the lower surface of the cable when the apparatus is placed on the cable plant.

22. The method of claim 1, comprising: moving the antenna along a bottom of the span of the cable by the carriage.

23. The system of claim 20, wherein: the carriage extends longitudinally in a first direction; and the first roller and the second roller are configured to move the carriage in a second direction perpendicular to the first direction, along the cable plant.

24. The apparatus of claim 23, wherein: the first and second rollers are attached to a first portion of the carriage; and the transmitter is attached to a second portion of the carriage opposite the first portion, the second portion being positioned below the cable plant when the carriage is placed on the cable plant such that the antenna is positioned below the cable plant when the carriage is placed on the cable plant.
