

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12401466
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Dinan; Esmael Hejazi

Uplink control information transmission in a wireless network

Abstract

A physical uplink control channel (PUCCH) may comprise a plurality of sets of PUCCH resource blocks overlapping in time in a time interval. A plurality of channel state information (CSI) reports may be used for transmission via the PUCCH resource blocks overlapping in time in the time interval. Selection of PUCCH resource blocks for transmission of at least one CSI report may be based on a size of the CSI report and on size of the sets of PUCCH resource blocks.

Inventors:	Dinan; Esmael Hejazi (McLean, VA)
Applicant:	Comcast Cable Communications, LLC (Philadelphia, PA)
Family ID:	1000008779689
Assignee:	Comcast Cable Communications, LLC (Philadelphia, PA)
Appl. No.:	18/185108
Filed:	March 16, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20230283416 A1	Sep. 07, 2023

Related U.S. Application Data

continuation parent-doc US 15091289 20160405 US 11641255 child-doc US 18185108
us-provisional-application US 62143177 20150405
us-provisional-application US 62147243 20150414

Publication Classification

Int. Cl.: H04L5/00 (20060101); **H04B7/04** (20170101); **H04L1/00** (20060101); **H04W8/24** (20090101); **H04W72/23** (20230101)

U.S. Cl.:

CPC H04L5/00 (20130101); **H04B7/04** (20130101); **H04L1/0029** (20130101); H04L1/0026 (20130101); H04W8/24 (20130101); H04W72/23 (20230101)

Field of Classification Search

CPC: H04B (7/0626); H04B (7/0632); H04W (72/1268); H04W (24/10)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9713087	12/2016	Asterjadhi et al.	N/A	N/A
9736795	12/2016	Dinan	N/A	N/A
9872336	12/2017	Dinan	N/A	N/A
9894681	12/2017	Dinan	N/A	N/A
11641255	12/2022	Dinan	370/329	H04L 5/0094
2009/0257390	12/2008	Ji et al.	N/A	N/A
2009/0290550	12/2008	Bhattad et al.	N/A	N/A
2010/0291937	12/2009	Hu et al.	N/A	N/A
2010/0303035	12/2009	Gao et al.	N/A	N/A
2010/0309876	12/2009	Khandekar et al.	N/A	N/A
2011/0081932	12/2010	Astely et al.	N/A	N/A
2011/0134774	12/2010	Pelletier et al.	N/A	N/A
2011/0228731	12/2010	Luo et al.	N/A	N/A
2011/0228732	12/2010	Luo et al.	N/A	N/A
2011/0243016	12/2010	Zhang et al.	N/A	N/A
2011/0249578	12/2010	Nayeb Nazar	370/252	H04L 5/0053
2011/0249634	12/2010	Lee et al.	N/A	N/A
2011/0305179	12/2010	Wang et al.	N/A	N/A
2012/0039275	12/2011	Chen et al.	N/A	N/A
2012/0039279	12/2011	Chen et al.	N/A	N/A
2012/0069802	12/2011	Chen et al.	N/A	N/A
2012/0082088	12/2011	Dalsgaard et al.	N/A	N/A
2012/0083284	12/2011	Harrison et al.	N/A	N/A
2012/0092989	12/2011	Baldemair et al.	N/A	N/A
2012/0113913	12/2011	Tirola et al.	N/A	N/A
2012/0182879	12/2011	Tamura et al.	N/A	N/A
2012/0213163	12/2011	Lee et al.	N/A	N/A
2012/0257570	12/2011	Jang et al.	N/A	N/A
2012/0329461	12/2011	Teyeb et al.	N/A	N/A
2013/0010619	12/2012	Fong et al.	N/A	N/A
2013/0028198	12/2012	Yamada	N/A	N/A

2013/0044653	12/2012	Yang	370/280	H04W 72/21
2013/0094392	12/2012	Kim et al.	N/A	N/A
2013/0114472	12/2012	Tamaki et al.	N/A	N/A
2013/0155914	12/2012	Wang et al.	N/A	N/A
2013/0188570	12/2012	Zhao et al.	N/A	N/A
2013/0188612	12/2012	Dinan	N/A	N/A
2013/0194981	12/2012	Wang et al.	N/A	N/A
2013/0215848	12/2012	Kato et al.	N/A	N/A
2013/0223301	12/2012	Lee et al.	N/A	N/A
2013/0235768	12/2012	Earnshaw et al.	N/A	N/A
2013/0250893	12/2012	Li et al.	N/A	N/A
2013/0250901	12/2012	Oizumi et al.	N/A	N/A
2013/0272232	12/2012	Dinan	N/A	N/A
2013/0272233	12/2012	Dinan	N/A	N/A
2013/0272241	12/2012	Ohta et al.	N/A	N/A
2013/0279433	12/2012	Dinan	N/A	N/A
2013/0286990	12/2012	Park et al.	N/A	N/A
2013/0301446	12/2012	Chen et al.	N/A	N/A
2013/0322376	12/2012	Marinier et al.	N/A	N/A
2013/0336214	12/2012	Sayana et al.	N/A	N/A
2014/0016593	12/2013	Park et al.	N/A	N/A
2014/0036659	12/2013	Gao	N/A	N/A
2014/0036664	12/2013	Han et al.	N/A	N/A
2014/0050113	12/2013	Rosa et al.	N/A	N/A
2014/0056220	12/2013	Poitau et al.	N/A	N/A
2014/0086084	12/2013	Bi et al.	N/A	N/A
2014/0092865	12/2013	Heo et al.	N/A	N/A
2014/0119284	12/2013	Baldemair	370/328	H04L 5/003
2014/0133373	12/2013	Han et al.	N/A	N/A
2014/0161060	12/2013	Nam et al.	N/A	N/A
2014/0161117	12/2013	Sebire et al.	N/A	N/A
2014/0269595	12/2013	Lee et al.	N/A	N/A
2014/0348078	12/2013	Kim et al.	N/A	N/A
2014/0349713	12/2013	Yamada	N/A	N/A
2015/0003418	12/2014	Rosa et al.	N/A	N/A
2015/0016350	12/2014	Moulsley et al.	N/A	N/A
2015/0078286	12/2014	Kim et al.	N/A	N/A
2015/0098340	12/2014	Oizumi	N/A	N/A
2015/0098400	12/2014	Lee et al.	N/A	N/A
2015/0110029	12/2014	Hwang et al.	N/A	N/A
2015/0117342	12/2014	Loehr et al.	N/A	N/A
2015/0124670	12/2014	Park	N/A	N/A
2015/0146588	12/2014	Park	N/A	N/A
2015/0155928	12/2014	Seo et al.	N/A	N/A
2015/0181590	12/2014	Park	N/A	N/A
2015/0215079	12/2014	Park	N/A	N/A
2015/0215977	12/2014	Yamazaki	N/A	N/A
2015/0223213	12/2014	Moon et al.	N/A	N/A
2015/0245307	12/2014	Chen et al.	N/A	N/A

2015/0245346	12/2014	Yokomakura et al.	N/A	N/A
2015/0245347	12/2014	Yi et al.	N/A	N/A
2015/0271811	12/2014	Kim et al.	N/A	N/A
2015/0282020	12/2014	Pajukoski et al.	N/A	N/A
2015/0289179	12/2014	Liu et al.	N/A	N/A
2015/0312930	12/2014	Han et al.	N/A	N/A
2015/0319754	12/2014	Ishida et al.	N/A	N/A
2015/0327230	12/2014	Takeda et al.	N/A	N/A
2016/0014753	12/2015	Wu et al.	N/A	N/A
2016/0021646	12/2015	Hu et al.	N/A	N/A
2016/0044617	12/2015	Vajapeyam et al.	N/A	N/A
2016/0044655	12/2015	Park et al.	N/A	N/A
2016/0044737	12/2015	Kwon	N/A	N/A
2016/0066284	12/2015	Kwon et al.	N/A	N/A
2016/0100397	12/2015	Wen et al.	N/A	N/A
2016/0150485	12/2015	Yi et al.	N/A	N/A
2016/0157191	12/2015	Yokomakura et al.	N/A	N/A
2016/0183244	12/2015	Papasakellariou	N/A	N/A
2016/0192388	12/2015	Ekpenyong et al.	N/A	N/A
2016/0197687	12/2015	Song et al.	N/A	N/A
2016/0205681	12/2015	Kim et al.	N/A	N/A
2016/0212661	12/2015	Basu Mallick et al.	N/A	N/A
2016/0227541	12/2015	Damnjanovic et al.	N/A	N/A
2016/0241377	12/2015	Takeda et al.	N/A	N/A
2016/0242153	12/2015	Chen et al.	N/A	N/A
2016/0262118	12/2015	Kim et al.	N/A	N/A
2016/0277987	12/2015	Chen et al.	N/A	N/A
2016/0285716	12/2015	Pelletier et al.	N/A	N/A
2016/0286555	12/2015	Papasakellariou	N/A	N/A
2016/0294531	12/2015	Loehr et al.	N/A	N/A
2016/0302177	12/2015	Kwon et al.	N/A	N/A
2016/0365959	12/2015	Dinan	N/A	N/A
2016/0366675	12/2015	Dinan	N/A	N/A
2016/0366681	12/2015	Dinan	N/A	N/A
2016/0381681	12/2015	Nogami et al.	N/A	N/A
2017/0005770	12/2016	Shimezawa	N/A	N/A
2017/0006559	12/2016	Kim et al.	N/A	N/A
2017/0064541	12/2016	Uchino et al.	N/A	N/A
2017/0111159	12/2016	Lee et al.	N/A	N/A
2017/0118658	12/2016	Hwang et al.	N/A	N/A
2017/0141901	12/2016	Rico Alvarino et al.	N/A	N/A
2017/0215160	12/2016	Lohr et al.	N/A	N/A
2017/0230928	12/2016	Basu Mallick et al.	N/A	N/A
2017/0251454	12/2016	Yang et al.	N/A	N/A
2017/0303240	12/2016	Basu Mallick et al.	N/A	N/A
2017/0318565	12/2016	Golitschek Edler von Elbwart et al.	N/A	N/A
2017/0353965	12/2016	Zhang	N/A	N/A
2017/0367103	12/2016	Suzuki et al.	N/A	N/A
2017/0367115	12/2016	Sebire	N/A	N/A

2018/0014285	12/2017	Nishio et al.	N/A	N/A
2018/0014291	12/2017	Takeda et al.	N/A	N/A
2018/0020473	12/2017	Suzuki et al.	N/A	N/A
2018/0027548	12/2017	Suzuki et al.	N/A	N/A
2018/0063832	12/2017	Yamada et al.	N/A	N/A
2018/0123766	12/2017	Ahn et al.	N/A	N/A
2018/0131494	12/2017	Li et al.	N/A	N/A
2019/0037601	12/2018	Noh et al.	N/A	N/A
2020/0344780	12/2019	Choi et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
20140058599	12/2013	KR	N/A
2013162247	12/2012	WO	N/A
2013168969	12/2012	WO	N/A
2013/179590	12/2012	WO	N/A
2016157797	12/2015	WO	N/A

OTHER PUBLICATIONS

3GPP TS 36.211 V12.4.0 (Dec. 2014), Technical Specification, 3rd Generation Partnership Project; Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Physical channels and modulation, 3GPP, Valbonne, France. cited by applicant

3GPP TS 36.212 V12.3.0 (Dec. 2014), Technical Specification, 3rd Generation Partnership Project; Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Multiplexing and channel coding, 3GPP, Valbonne, France. cited by applicant

3GPP TS 36.213 V12.4.0 (Dec. 2014), Technical Specification, 3rd Generation Partnership Project; Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer procedures, Valbonne, France. cited by applicant

3GPP TS 36.300 V12.4.0 (Dec. 2014), Technical Specification, 3rd Generation Partnership Project; Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA) and Evolved Universal Terrestrial Radio Access Network (E-UTRAN); Overall description; Stage 2, Valbonne, France. cited by applicant

3GPP TS 36.321 V12.4.0 (Dec. 2014), Technical Specification, 3rd Generation Partnership Project; Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Medium Access Control (MAC) protocol specification, Valbonne, France. cited by applicant

3GPP TS 36.331 V12.4.1 (Dec. 2014), Technical Specification, 3rd Generation Partnership Project; Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC); Protocol specification, Valbonne, France. cited by applicant

3GPP TSG RAN WG1 #80 R1-150358, Athens, Greece, Feb. 9-13, 2015, Agenda item: 7.2.2.2.1, Source: Samsung, Title: Necessary mechanisms for supporting CA with up to 32 CCs. cited by applicant

3GPP TSG RAN WG1 #80 R1-150359, Athens, Greece, Feb. 9-13, 2015, Agenda item: 7.2.2.2.2, Source: Samsung, Title: Enhancements to DL control signaling for CA with up to 32 CCs. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150104, Athens, Greece, Feb. 9-13, 2015, Source: CATT, Title: Enhancements to DL control signaling for Rel-13 CA. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150137, Athens, Greece, Feb. 9-13, 2015, Source: ZTE, Title: PDCCH/EPDCCH enhancements for Carrier Aggregation. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150169, Athens, Greece, Feb. 9-13, 2015, Agenda item: 7.2.2.2.2, Source: Alcatel-Lucent Shanghai Bell, Alcatel-Lucent, Title: Enhancements to DL control signalling for up to 32 component carriers. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150170, Athens, Greece, Feb. 9-13, 2015, Source: Alcatel-Lucent Shanghai Bell, Alcatel-Lucent, Title: DL PHICH enhancement to support up to 32 carriers aggregation. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150277, Athens, Greece, Feb. 9-13, 2015, Source: Sharp, Title: Considerations on DL Control Signaling for Rel-13 CA. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150291, Athens, Greece, Feb. 9-13, 2015, Agenda item: 7.2.2.1, Source: NEC, Title: Initial considerations on SCell PUCCH for CA. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150293, Athens, Greece, Feb. 9-13, 2015, Agenda item: 7.2.2.2.2, Source: NEC, Title: Discussion on DL control signaling enhancements. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150315, Athens, Greece, Feb. 9-13, 2015, Source: Panasonic, Title: Identified DL aspects for CA beyond 5 carriers. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150437, Athens, Greece, Feb. 9-13, 2015, Source: CMCC, Title: Design principle to support CA up to 32 carriers. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150523, Athens, Greece, Feb. 9-13, 2015, Agenda item: 7.2.2.2.2, Source: HTC, Title: DL control signaling for CA up to 32 CCs. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150593, Athens, Greece, Feb. 9-13, 2015, Source: NTT DOCOMO, Inc., Title: Necessary enhancements to enable LTE CA of up to 32CCs for DL and UL. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150824, Athens, Feb. 9-13, 2015, Title: Observations on Necessary Enhancements to DL control signaling, Source: Nokia Corporation, Nokia Networks, NTT DOCOMO. cited by applicant

3GPP TSG RAN WG2 Meeting #89 R2-150038, Athens, Greece, Feb. 9-13, 2015, Title: LS on RAN1 agreements on PUCCH on SCell for CA, Release: Rel-13, Work Item: LTE_CA_enh_b5C-Core, Source: TSG RAN WG1. cited by applicant

3GPP TSG RAN WG2 Meeting #89 R2-150263, Athens, Greece, Feb. 9-13, 2015, Source: CATT, Title: Introduction of PUCCH Cell Group. cited by applicant

3GPP TSG RAN WG2 Meeting #89 R2-150264, Athens, Greece, Feb. 9-13, 2015, Source: CATT, Title: Discussion on the functionality of PUCCH SCell. cited by applicant

3GPP TSG-RAN WG1 Meeting #80 R1-150495, Athens, Greece, Feb. 9-13, 2015, Agenda item: 7.2.2.2.2, Source: Nokia Corporation, Nokia Networks, Title: On DL control signalling for up to 32 component carriers. cited by applicant

3GPP TSG-RAN WG1#80 R1-150323, Athens, Greece, Feb. 9-13, 2015, Source: Ericsson, Title: DL control signaling enhancements for up to 32 CCs. cited by applicant

3GPP TSG-RAN WG2 meeting #89 R2-150149, Athens, Greece, Feb. 9-13, 2015, Source: ZTE, Title: The principle of grouping PUCCH cell. cited by applicant

3GPP TSG-RAN2 #89 Meeting R2-150289, Athens, Greece, Feb. 9-13, 2015, Source: MediaTek Inc., Title: Cross-carrier scheduling for CA enhancement beyond 5CCs. cited by applicant

3GPP TSG-RAN2 #89 Meeting R2-150290, Athens, Greece, Feb. 9-13, 2015, Source: MediaTek Inc., Title: PUCCH on SCell for CA enhancement beyond 5CCs. cited by applicant

3GPP TSG RAN WG1 #80 R1-150357, Athens, Greece, Feb. 9-13, 2015, Agenda item: 7.2.2.1, Source: Samsung, Title: PUCCH Transmission on SCell for CA. cited by applicant

3GPP TSG RAN WG1 #80 R1-150361, Athens, Greece, Feb. 9-13, 2015, Agenda item: 7.2.2.2.3, Source: Samsung, Title: CSI Transmission for Enhanced CA. cited by applicant

3GPP TSG RAN WG1 #80 R1-150468, Feb. 9-Feb. 13, 2015, Athens, Greece, Agenda item: 7.2.2.1, Source: Qualcomm Incorporated, Title: PUCCH on SCell. cited by applicant

3GPP TSG RAN WG1 #80 R1-150473, Feb. 9-Feb. 13, 2015, Athens, Greece, Agenda item: 7.2.2.2.3, Source: Qualcomm Incorporated, Title: CSI feedback for up to 32 component carriers.

cited by applicant
3GPP TSG RAN WG1 #80 R1-150742, Feb. 9-Feb. 13, 2015, Athens, Greece, Agenda item: 7.2.2.2.3, Source: Qualcomm Incorporated, Title: HARQ ACK for up to 32 DL Carriers. cited by applicant
3GPP TSG RAN WG1 #80 R1-150823, Athens, Greece, Feb. 9-13, 2015, Title: WF on PUCCH on SCell for CA, Source: NTT DOCOMO, NEC, Sharp, Softbank Mobile, Intel, Ericsson, KDDI. cited by applicant
3GPP TSG RAN WG1 #80, Athens, Greece, Feb. 9-13, 2015, R1-150822, Title: Way Forward on PUCCH on SCell for CA, Source: Ericsson, NEC, Sharp, NTT DOCOMO, ZTE. cited by applicant
3GPP TSG RAN WG1 #80, Athens, Greece, Feb. 9-13, 2015, R1-150926, Title: WF on target scenarios for UCI feedback design, Source: Ericsson, CATT. cited by applicant
3GPP TSG RAN WG1 Meeting #80 R1-150101, Athens, Greece, Feb. 9-13, 2015, Source: CATT, Title: PUCCH on SCell for Rel-13 CA. cited by applicant
3GPP TSG RAN WG1 Meeting #80 R1-150103, Athens, Greece, Feb. 9-13, 2015, Source: CATT, Title: Enhancements to support carrier aggregation with up to 32 component carriers. cited by applicant
3GPP TSG RAN WG1 Meeting #80 R1-150106, Athens, Greece, Feb. 9-13, 2015, Source: CATT, Title: Periodic CSI feedback for Rel-13 CA. cited by applicant
3GPP TSG RAN WG1 Meeting #80 R1-150168, Athens, Greece, Feb. 9-13, 2015, Source: Alcatel-Lucent Shanghai Bell, Alcatel-Lucent, Title: CA enhancement to support up to 32 carrier aggregation. cited by applicant
3GPP TSG RAN WG1 Meeting #80 R1-150171, Athens, Greece, Feb. 9-13, 2015, Agenda item: 7.2.2.2.2, Source: Alcatel-Lucent Shanghai Bell, Alcatel-Lucent, Title: Enhancements to UL control signalling for up to 32 component carriers. cited by applicant
3GPP TSG RAN WG1 Meeting #80 R1-150207, Athens, Greece, Feb. 9-13, 2015, Agenda Item: 7.2.2.2.1, Source: LG Electronics, Title: Necessary mechanisms and enhancements to support CA of up to 32 carriers. cited by applicant
3GPP TSG RAN WG1 Meeting #80 R1-150276, Athens, Greece, Feb. 9-13, 2015, Source: Sharp, Title: Considerations on PUCCH for Rel-13 CA. cited by applicant
3GPP TSG RAN WG1 Meeting #80 R1-150294, Athens, Greece, Feb. 9-13, 2015, Agenda item: 7.2.2.2.3, Source: NEC, Title: Discussion on UL control signaling enhancements. cited by applicant
3GPP TSG RAN WG1 Meeting #80 R1-150390, Athens, Greece, Feb. 9-13, 2015, Agenda Item: 7.2.2.2.1, Source: Huawei, HiSilicon, Title: On CA enhancements supporting up to 32 component carriers. cited by applicant
3GPP TSG RAN WG1 Meeting #80 R1-150412, Athens, Greece, Feb. 9-13, 2015, Agenda Item: 7.2.2.2.3, Source: Huawei, HiSilicon, Title: CSI feedback enhancement for carrier aggregation enhancement beyond 5 carriers. cited by applicant
3GPP TSG RAN WG1 Meeting #80 R1-150489, Athens, Greece, Nov. 17-21, 2014, Source: ITL Inc., Title: Uplink control signaling enhancements for b5C CA. cited by applicant
3GPP TSG RAN WG1 Meeting #80 R1-150509, Athens, Greece, Feb. 9-13, 2015, Source: NTT DOCOMO, NC., Title: PUCCH on SCell for UEs supporting UL-CA. cited by applicant
3GPP TSG RAN WG1 Meeting #80 R1-150510, Athens, Greece, Feb. 9-13, 2015, Source: NTT DOCOMO, NC., Title: Initial views on CA enhancements to support up to 32 component carriers. cited by applicant
3GPP TSG RAN WG1 Meeting #80 R1-150699, Athens, Greece, Feb. 9-13, 2015, Agenda item: 7.2.2.2.2, Source: Alcatel-Lucent Shanghai Bell, Alcatel-Lucent, Title: Enhancements to UL control signalling for up to 32 component carriers. cited by applicant
Jul. 9, 2018—Chinese Office Action—CN 201680014760.5. cited by applicant
Sep. 5, 2018—Chinese Office Action—CN 201680014404.7. cited by applicant
Sep. 18, 2018—Japanese Office Action—JP 2017-546998. cited by applicant

Nov. 23, 2018—Korean Notice of Allowance—KR 20177025339. cited by applicant

Feb. 22, 2019—Chinese Office Action—CN 201680014760.5. cited by applicant

Jun. 5, 2019—Chinese Second Office Action—CN 201680014414.7. cited by applicant

Jun. 18, 2019—Chinese Office Action—201680014760.5. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150825, Athens, Feb. 9-13, 2015, Title: Observations on Necessary Enhancements to UL control signaling, Source: Nokia Networks, Nokia Corporation, NTT DOCOMO. cited by applicant

3GPP TSG-RAN WG1 #80 R1-150086, Athens, Greece, Feb. 9-13, 2015, Source: Intel Corporation, Title: Discussion on CA enhancement for release 13. cited by applicant

3GPP TSG-RAN WG1 #80 R1-150537, Athens, Greece, Feb. 9-13, 2015, Agenda Item: 7.2.2.2.1, Source: InterDigital Communications, Title: Enabling LTE carrier aggregation of up to 32 component carriers. cited by applicant

3GPP TSG-RAN WG1 Meeting #80 R1-150454, Athens, Greece, Feb. 9-13, 2015, Agenda item: 7.2.2.2.3, Source: Nokia Networks, Nokia Corporation, Title: PUCCH Enhancements for Carrier Aggregation Enhancement Beyond 5 Carriers. cited by applicant

3GPP TSG-RAN WG1 Meeting #80 R1-150455, Athens, Greece, Feb. 9-13, 2015, Agenda item: 7.2.2.2.3, Source: Nokia Networks, Nokia Corporation, Title: CSI reporting for Carrier Aggregation Enhancement Beyond 5 Carriers. cited by applicant

3GPP TSG-RAN WG1#80 R1-150324, Athens, Greece, Feb. 9-13, 2015, Source: Ericsson, Title: UL control signaling enhancements for up to 32 CCs. cited by applicant

3GPP TSG-RAN WG2 Meeting#89 R2-150134, Feb. 9-13, 2015, Athens, Greece, Source: Institute for Information Industry (111), Title: Partition UGI feedback. cited by applicant

Samsung, “Text Proposal for PHR in dual connectivity”, May 19-23, 2014, pp. 1-7, 3GPP TSG RAN WG2 #86, R2-142275, Seoul, Korea. cited by applicant

Japanese Office Action mailed Jan. 30, 2018 in Japanese Patent Application No. 2017-546998. cited by applicant

R2-140066, 3GPP TSG RAN WG2 Meeting #85, Prague, Czech Republic, Feb. 10-14, 2014, Title: Consideration on PHR for TDD eIMTA. cited by applicant

3GPP TSG RAN meeting #67, Shanghai, China, Mar. 9-12, 2015, RP-150272, Status Report to TSG, Agenda item: 11.3.4, Title: LTE Carrier Aggregation Enhancement Beyond 5 Carriers. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150102, Athens, Greece, Feb. 9-13, 2015, Source: CATT, Title: Uplink power control to support PUCCH on SCell for Rel-13 CA. cited by applicant

3GPP TSG RAN WG1 Meeting #80bis R1-15xxxx, Belgrade, Serbia, Apr. 20-24, 2015, Source: MCC Support, Title: Draft Report of 3GPP TSG RAN WGI #80 v0.2.0, Athens, Greece, Feb. 9-13, 2015. cited by applicant

3GPP TSG RAN WG2 Meeting #89 R2-150169, Athens, Greece, Feb. 9-13, 2015, Source: Intel Corporation, Title: Considerations for PUCCH on SCell in carrier aggregation. cited by applicant

3GPP TSG-RAN WG1 #80 R1-150085, Athens, Greece, Feb. 9-13, 2015, Source: Intel Corporation, Title: Support of PUCCH on SCell for CA. cited by applicant

3GPP TSG-RAN WG1#80 R1-150321, Athens, Greece, Feb. 9-13, 2015, Source: Ericsson, Title: PUCCH on SCell or carrier aggregation. cited by applicant

3GPP TSG-RAN WG2 #89 R2-150112, Feb. 9-13, 2015, Athens, Greece, Source: NTT DOCOMO, Inc., Title: Discussion on PUCCH on SCell. cited by applicant

3GPP TSG-RAN WG2 #89 Tdoc R2-150389, Athens, Greece, Feb. 9-13, 2015, Source: Ericsson, Title: PUCCH on SCell. cited by applicant

3GPP TSG-RAN WG2 Meeting #80 R1-150167, Athens, Greece, Feb. 9-13, 2015, Source: Alcatel-Lucent, Alcatel-Lucent Shanghai Bell, Title: PUCCH on SCell for CA enhancement. cited by applicant

3GPP TSG-RAN WG2 Meeting #89 R2-150527, Athens, Greece, Feb. 9-13, 2015, Source:

Qualcomm Incorporated, Title: General principles for the support of PUCCH on SCell. cited by applicant

3GPP TSG-RAN WG2 Meeting #89 R2-150151, Athens, Greece, Feb. 9-13, 2015, Source: ZTE, Title: Discussion on the impact for the support of PUCCH on SCell, Agenda item: 7.2. cited by applicant

3GPP TSG-RAN WG2 Meeting #89 R2-150406, Athens, Greece, Feb. 9-13, 2015, Source: Alcatel-Lucent, Alcatel-Lucent Shanghai Bell, Title: Considerations on PUCCH on SCell. cited by applicant

3GPP TSG-RAN WG2 Meeting #89 R2-150410, Athens, Greece, Feb. 9-13, 2015, Agenda item: 7.2, Source: Nokia Corporation, Nokia Networks, Title: PHR for SCell with PUCCH, WID/SID: LTE_CA_enh_b5G-Core-Release 13. cited by applicant

3GPP TSG-RAN WG2 Meeting #89 R2-150372, Athens, Greece, Feb. 9-13, 2015, Source: Huawei, HiSilicon, Title: Introduce PUCCH on SCell for CA beyond 5 carriers. cited by applicant

3GPP TSG RAN WG1 Meeting #81 R1-153295, Fukuoka, Japan, May 25-29, 2015, Source: Institute for Information Industry (III), Title: Discussion on Dynamic Selection of SR PUCCH Resources. cited by applicant

3GPP TSG RAN WG2 Meeting RAN2#89, Athens, Greece, Feb. 9-13, 2015, R2-150403, Agenda Item: 7.2, Source: NEC, Title: PUCCH on SCell. cited by applicant

3GPP TSG-RAN WG2 Meeting #89 R2-150129, Athens, Greece, Feb. 9-13, 2015, Agenda Item: 7.2, Source: Nokia Networks, Nokia Corporation, Title: SR on SCell, WID/SID: LTE_CA_enh_b5C-Core Release 13. cited by applicant

3GPP TSG-RAN WG2 Meeting #89 R2-150278, Athens, Greece, Feb. 9-Feb. 13, 2015, Source: Microsoft Corporation, Title: SCell PUCCH for CA. cited by applicant

3GPP TSG-RAN WG2 Meeting #90 R2-152513, Fukuoka, Japan, May 25-29, 2015, Title: SR on PUCCH-SCell, Source to WG: Ericsson. cited by applicant

3GPP TSG-RAN2 Meeting #64bis, Ljubljana, Slovenia, Jan. 12-16, 2009, R2-090659, Title: S PRC Parameters for MAG and RLG, Source to WG: Nokia Siemens Networks, Nokia Corporation, Source to TSG: R2, Work item code: LTE-L23. cited by applicant

3GPP TSG-RAN2#72 meeting Tdoc XR2-106513, Jacksonville, U.S. Nov. 15-19, 2010, Agenda Item: 7.1.4.3, Source: Samsung, Title: SR handling in CA. cited by applicant

Jan. 24, 2018—Japanese Office Action—JP 2017-546843. cited by applicant

Apr. 5, 2018—Korean Office Action—KR 2017-7025399. cited by applicant

3GPP TS 36.133 V12.6.0 (Dec. 2014), Technical Specification, 3rd Generation Partnership Project; Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Requirements for support of radio resource management, Valbonne, France. cited by applicant

3GPP TSG RAN WG2 Meeting #89 R2-150150, Athens, Greece, Feb. 9-13, 2015, Source: ZTE, Title: Activation/Deactivation for SCell carrying PUCCH. cited by applicant

3GPP TSG-RAN WG2 #87, Aug. 18-22, 2014, Dresden, Germany, R2-143073, Update of R2-141967, Source: NTT DOCOMO, Inc, Title: Support of PUCCH on SCell for CA-RAN2 aspects. cited by applicant

3GPP TSG-RAN WG2 Meeting #72bis, Dublin, Ireland, Jan. 17-21, 2011, R2-110113, Agenda item: 7.1.4, Source: Huawei, Title: CQI Reporting at Activation. cited by applicant

3GPP TSG-RAN WG2 Meeting #87, Aug. 18-22, 2014, Dresden, Germany, R2-143117, Agenda Item: 6.1.2, Source: Samsung, Title: Discussion on PHR triggering due to SCell activation. cited by applicant

3GPP TSG-RAN WG2 Meeting #89 R2-150186, Athens, Greece, Feb. 9-13, 2015, Source: Nokia Corporation, Nokia Networks, Title: PUCCH SCell RLM and activation/deactivation. cited by applicant

3GPP TSG-RAN WG2 Meeting #89 R2-150277, Athens, Greece, Feb. 9-13, 2015, Source: KT

Corp., Title: Activation/deactivation of SCell carrying PUCCH. cited by applicant

3GPP TSG-RAN WG2 Meeting#89 R2-150238, Athens, Greece, Feb. 9-13, 2015, Agenda Item: 7.2, Source: Fujitsu, Title: Discussion on the PUCCH support on SCell. cited by applicant

3GPP TSG-RAN WG4 Meeting #68, Barcelona, Spain, Aug. 19-23, 2013, R4-134045, Agenda item: 5.2.3, Source: NSN, Nokia Corporation, Title: Remaining issues on SCell Activation Delay Requirements. cited by applicant

3GPP TSG-RAN1#63bis meeting R1-110069, Dublin, Ireland, Jan. 17-21, 2011, Agenda Item: 6.2.1, Source: Samsung, Title: CSI reporting and SRS timing upon SCell activation/deactivation. cited by applicant

3GPP TSG-RAN1#64 meeting R1-110721, Taipei, Taiwan, Feb. 21-25, 2011, Agenda item: 4, Source: Samsung, Title: CQI reporting at SCell activation. cited by applicant

3GPP TSG-RAN WG2 Meeting #89 R2-150380, Athens, Greece, Feb. 9-Feb. 13, 2015, Source: LG Electronics Inc., Title: Potential issues in MAC for CA enhancement. cited by applicant

3GPP TSG RAN WG2 #89 bis R2-151304, Apr. 20 to May 24, 2015, Bratislava, Slovakia, Source: ITRI, Title: Discussion on SR on PUCCH SCell. cited by applicant

3GPP TSG RAN WG2 #89bis R2-151637, Apr. 20 to 24, 2015, Bratislava, Slovakia, Source: Samsung, Title: SR support for CA enhancements. cited by applicant

3GPP TSG RAN WG2 #90 R2-152712, May 25 to 29, 2015, Fukuoka, Japan, Source: Samsung, Title: How to support SR in PUCCH SCell. cited by applicant

3GPP TSG RAN WG2 Meeting #89b R2-151430, Bratislava, Slovakia, Apr. 20-24, 2015, Source: NEC, Title: SR on PUCCH SCell. cited by applicant

3GPP TSG RAN WG2 Meeting #89bis R2-151104, Bratislava, Slovakia, Apr. 20-24, 2015, Source: Intel Corporation, Title: Control plane aspects of support PUCCH on SCell. cited by applicant

3GPP TSG RAN WG2 Meeting #89bis R2-151342, Bratislava, Slovakia, Apr. 20-24, 2015, Source: CATT, Title: D-SR on PUCCH SCell. cited by applicant

3GPP TSG RAN WG2 Meeting #90 R2-152277, Fukuoka, Japan, May 25-29, 2015, Source: CATT, Title: D-SR on PUCCH SCell. cited by applicant

3GPP TSG RAN WG2 Meeting #90 R2-152512, Fukuoka, Japan, May 25-29, 2015, Source: NEC, Title: Potential issues of SR on PUCCH SCell. cited by applicant

3GPP TSG RAN2 Meeting #90 R2-152524, Fukuoka, Japan, May 25-29, 2015, Source: NEC, Title: Overlapping of D-SR resources. cited by applicant

3GPP TSG-RAN WG2 #89bis R2-151495, Bratislava, Slovakia, Apr. 20-24, 2015, Source: HTC, Title: PUCCH SCell management. cited by applicant

3GPP TSG-RAN WG2 #89bis Tdoc R2-151488, Bratislava, Slovakia, Apr. 20-24, 2015, Source: Ericsson, Title: SR on PUCCH SCell. cited by applicant

3GPP TSG-RAN WG2 #90 R2-152418, Fukuoka, Japan, May 25-29, 2015, Source: HTC, Title: Managing PUCCH resources on a deactivated PUCCH SCell. cited by applicant

3GPP TSG-RAN WG2 #90 Tdoc R2-152530, Fukuoka, Japan, May 25-29, 2015, Source: Ericsson, Title: SR on PUCCH SCell. cited by applicant

3GPP TSG-RAN WG2 Meeting #89bis R2-151211, Bratislava, Slovakia, Apr. 20-24, 2015, Source: Nokia Networks, Title: SR on SCell. cited by applicant

3GPP TSG-RAN WG2 Meeting #89bis R2-151324, Bratislava, Slovakia, Apr. 20-24, 2015, Source: Huawei, HiSilicon, Title: Leftover issues for PUCCH on SCell. cited by applicant

3GPP TSG-RAN WG2 Meeting #89bis R2-151469, Bratislava, Slovakia, Apr. 20-24, 2015, Source: Alcatel-Lucent Shanghai Bell, Alcatel-Lucent, Title: SR transmissions on SCell PUCCH. cited by applicant

3GPP TSG-RAN WG2 Meeting #90 R2-152273, Fukuoka, Japan, May 25-29, 2015, Source: Huawei, HiSilicon, Title: Issues for SR on PUCCH SCell. cited by applicant

3GPP TSG-RAN WG2 Meeting #90 R2-152302, Fukuoka, Japan, May 25-29, 2015, Source: Nokia Networks, Title: SR on PUCCH SCell. cited by applicant

3GPP TSG-RAN WG2 Meeting #90 R2-152310, Fukuoka, Japan, May 25-29, 2015, Source: Nokia Networks, Title: PUCCH SCell pre-activation. cited by applicant

3GPP TSG-RAN WG2 Meeting #90 R2-152366, Fukuoka, Japan, May 25-May 29, 2015, Source: LG Electronics Inc., Title: SR for CA enhancement. cited by applicant

3GPP TSG-RAN WG2 Meeting #90 R2-152742, Fukuoka, Japan, May 25-29, 2015, Source: Qualcomm Incorporated, Title: Dual SR Procedures. cited by applicant

3GPP TSG-RAN2 #89bis Meeting R2-151252, Bratislava, Slovakia, Apr. 20-24, 2015, Source: MediaTek Inc., Title: Remaining issues for PUCCH on SCell. cited by applicant

3GPP TSG-RAN2 #90 Meeting R2-152138, Fukuoka, Japan, May 25-29, 2015, Source: MediaTek Inc., Title: Remaining UP issues for PUCCH on SCell. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150067, Athens, Greece, Feb. 9-13, 2015, Source: Huawei, HiSilicon, Title: Support of PUCCH on SCell based on dual connectivity mechanism. cited by applicant

3GPP TSG RAN WG1 Meeting #80 R1-150135, Athens, Greece, Feb. 9-13, 2015, Source: ZTE, Title: Further CA enhancement to support PUCCH on SCell. cited by applicant

3GPP TS 36.211 V13.3.0 (Jun. 2016), Technical Specification 3rd Generation Partnership Project; Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Physical channels and modulation (Release 13). cited by applicant

3GPP TS 36.212 V13.3.0 (Sep. 2016), Technical Specification, 3rd Generation Partnership Project; Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Multiplexing and channel coding (Release 13). cited by applicant

3GPP TS 36.213 V13.3.0 (Sep. 2016), Technical Specification, 3rd Generation Partnership Project; Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer procedures (Release 13). cited by applicant

3GPP TS 36.300 V13.5.0 (Sep. 2016), Technical Specification, 3rd Generation Partnership Project; Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA), and Evolved Universal Terrestrial Radio Access Network (E-UTRAN); Overall description; Stage 2 (Release 13). cited by applicant

3GPP TS 36.321 V13.2.0 (Jun. 2016), Technical Specification, 3rd Generation Partnership Project; Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Medium Access Control (MAC) protocol specification (Release 13). cited by applicant

3GPP TS 36.331 V13.2.0 (Jun. 2016), Technical Specification, 3rd Generation Partnership Project; Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC); Protocol specification (Release 13). cited by applicant

R1-160561, GPP TSG RAN WG1 Meeting #84, St Julian's, Malta, Feb. 15-19, 2016, Agenda item: 7.3.1.1, Source: Samsung, Title: Discussion on UL power control for UL LAA. cited by applicant

IEEE 802 Interim Session, Atlanta, USA, Jan. 11-16, 2015, Title: 3GPP & unlicensed spectrum. cited by applicant

R1-152739, 3GPP TSG RAN WG1 meeting #81, Fukuoka, Japan, May 25-29, 2015, Agenda Item: 6.2.4.3, Source: LG Electronics, Title: UL power control in LAA. cited by applicant

R1-155472, 3GPP TSG RAN WG1 #82bis, Malmo, Sweden, Oct. 5-9, 2015, Agenda item: 7.2.3.3, Source: Samsung, Title: Impact of LAA dynamic power control. cited by applicant

R1-160886, 3GPP TSG RAN WG1 #84, Feb. 15-19, 2016, St. Julian's, Malta, Agenda item: 7.3.1.1, Source: Qualcomm Incorporated, Title: PUSCH power control. cited by applicant

R1-162476, 3GPP TSG RAN WG1 meeting #84bis, Busan, Korea, Apr. 11-15, 2016, Agenda Item: 7.3.1.6, Source: LG Electronics, Title: Power control in LAA uplink. cited by applicant

R1-162662, 3GPP TSG RAN WG1 Meeting #84bis, Busan, Korea Apr. 11-15, 2016, Agenda Item: 7.3.1.1 Source: Samsung, Title: Discussion on UL power control for UL LAA. cited by applicant

R1-163023, 3GPP TSG RAN WG1 #84bis, Apr. 11-15, 2016, Busan, Korea, Agenda item: 7.3.1.1, Source: Qualcomm Incorporated, Title: PUSCH power control. cited by applicant

R1-163762, 3GPP TSG RAN WG1 #84bis, Busan, Korea, Apr. 11-15, 2016, Agenda item: 7.3.1.6, WF on uplink power control in LAA. cited by applicant
R1-164918, 3GPP TSG-RAN WG1 Meeting #85, Nanjing, China, May 23-27, 2016, Agenda item: 6.2.1.1, Source: Nokia, Alcatel-Lucent Shanghai Bell, Title: On PUSCH Transmit Power on LAA SCells. cited by applicant
R1-165557, 3GPP TSG RAN WG1 #85, Nanjing, China, May 23-27, 2016, Agenda item: 6.2.1.1, WF on uplink power control in LAA. cited by applicant
R1-167026, 3GPP TSG-RAN WG1 Meeting #86, Gothenburg, Sweden, Aug. 22-26, 2016, Agenda item: 7.2.1.1, Source: Nokia, Alcatel-Lucent Shanghai Bell, Title: Remaining Issues on LAA SCell PUSCH Transmit Power. cited by applicant
RP-141188, 3GPP TSG RAN Meeting #65, Edinburgh, Scotland, Sep. 9-12, 2014, Source: ZTE, Title: Supporting dual connectivity in LTE-U. cited by applicant
RP-151725, 3GPP TSG RAN Meeting #70, Sitges, Spain, Dec. 7-10, 2015, Source: ZTE, Xinwei Title: Supporting dual connectivity in LAA. cited by applicant
RP-151978, 3GPP TSG RAN Meeting #70, Sitges, Spain, Dec. 7-10, 2015, revision of RP-yynnnn, Source: Ericsson, Huawei, Title: New Work Item on enhanced LAA for LTE. cited by applicant
RP-151979, 3GPP TSG RAN Meeting #70, Sitges, Spain, Dec. 7-10, 2015, Agenda item 14.1.1, Motivation For Enhanced Licensed Assisted Access For LTE in Rel-14. cited by applicant
RP-160926, 3GPP TSG RAN Meeting #72, Busan, Korea, Jun. 13-17, 2016, Source: ZTE, Title: Discussion on further enhancement of LAA for LTE. cited by applicant
RP-161036, 3GPP TSG RAN Meeting #72, Busan, Korea, Mar. 13-16, 2016, Title: Motivation for New Work Item for Enhancing Utilization of CA for LTE, Source: Nokia, Alcatel-Lucent Shanghai Bell, Agenda Item: 10.1.2. cited by applicant
RP-161150, 3GPP TSG RAN Meeting #72, Busan, Korea, Jun. 13-16, 2016, Source: Qualcomm Incorporated Title: New WI proposal on LTE standalone and dual connectivity operation in unlicensed spectrum. cited by applicant
RP-161701, 3GPP TSG RAN Meeting #73, New Orleans, Sep. 19-22, 2016, Source: ZTE, Title: New WI proposal Further enhancement on FeLAA. cited by applicant
RP-161702, 3GPP TSG RAN Meeting #73, New Orleans, USA, Sep. 19-22, 2016, Motivation for New WI Further Enhancement on FeLAA. cited by applicant
Aug. 19, 2016—International Search Report and Written Opinion—PCT/US2016/021201. cited by applicant
Aug. 16, 2016—International Search Report and Written Opinion—PCT/2016/021227. cited by applicant
Feb. 21, 2017—European Office Action—EP16716078.7. cited by applicant

Primary Examiner: Lam; Yee F

Attorney, Agent or Firm: Banner & Witcoff, Ltd.

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. application Ser. No. 15/091,289, filed Apr. 5, 2016, which claims the benefit of U.S. Provisional Application No. 62/143,177, filed Apr. 5, 2015, and U.S. Provisional Application No. 62/147,243, filed Apr. 14, 2015, each of which is hereby incorporated by reference in its entirety.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWINGS

(1) Examples of several of the various embodiments of the present invention are described herein

with reference to the drawings.

(2) FIG. 1 is a diagram depicting example sets of OFDM subcarriers as per an aspect of an embodiment of the present invention.

(3) FIG. 2 is a diagram depicting an example transmission time and reception time for two carriers in a carrier group as per an aspect of an embodiment of the present invention.

(4) FIG. 3 is a diagram depicting OFDM radio resources as per an aspect of an embodiment of the present invention.

(5) FIG. 4 is a block diagram of a base station and a wireless device as per an aspect of an embodiment of the present invention.

(6) FIG. 5A, FIG. 5B, FIG. 5C and FIG. 5D are example diagrams for uplink and downlink signal transmission as per an aspect of an embodiment of the present invention.

(7) FIG. 6 is an example diagram for a protocol structure with CA and DC as per an aspect of an embodiment of the present invention.

(8) FIG. 7 is an example diagram for a protocol structure with CA and DC as per an aspect of an embodiment of the present invention.

(9) FIG. 8 shows example TAG configurations as per an aspect of an embodiment of the present invention.

(10) FIG. 9 is an example message flow in a random access process in a secondary TAG as per an aspect of an embodiment of the present invention.

(11) FIG. 10 is an example grouping of cells into PUCCH groups as per an aspect of an embodiment of the present invention.

(12) FIG. 11 illustrates example groupings of cells into one or more PUCCH groups and one or more TAGs as per an aspect of an embodiment of the present invention.

(13) FIG. 12 illustrates example groupings of cells into one or more PUCCH groups and one or more TAGs as per an aspect of an embodiment of the present invention.

(14) FIG. 13 is an example MAC PDU as per an aspect of an embodiment of the present invention.

(15) FIG. 14 shows example PUCCH configurations as per an aspect of an embodiment of the present invention.

(16) FIG. 15 is an example flow diagram as per an aspect of an embodiment of the present invention.

(17) FIG. 16 is an example flow diagram as per an aspect of an embodiment of the present invention.

Description

DETAILED DESCRIPTION OF EMBODIMENTS

(1) Example embodiments of the present invention enable operation of carrier aggregation. Embodiments of the technology disclosed herein may be employed in the technical field of multicarrier communication systems. More particularly, the embodiments of the technology disclosed herein may relate to transmission and reception of control and/or data in a multi-carrier wireless network.

(2) The following Acronyms are used throughout the present disclosure: ASIC application-specific integrated circuit BPSK binary phase shift keying CA carrier aggregation CSI channel state information CDMA code division multiple access CSS common search space CPLD complex programmable logic devices CC component carrier DL downlink DCI downlink control information DC dual connectivity EPC evolved packet core E-UTRAN evolved-universal terrestrial radio access network FPGA field programmable gate arrays FDD frequency division duplexing HDL hardware description languages HARQ hybrid automatic repeat request IE information element LTE long term evolution MCG master cell group MeNB master evolved node

B MIB master information block MAC media access control MME mobility management entity NAS non-access stratum OFDM orthogonal frequency division multiplexing PDCP packet data convergence protocol PDU packet data unit PHY physical PDCCH physical downlink control channel PHICH physical HARQ indicator channel PUCCH physical uplink control channel PUSCH physical uplink shared channel PCell primary cell PCC primary component carrier PSCell primary secondary cell pTAG primary timing advance group QAM quadrature amplitude modulation QPSK quadrature phase shift keying RBG Resource Block Groups RLC radio link control RRC radio resource control RA random access RB resource blocks SCC secondary component carrier SCell secondary cell SCG secondary cell group SeNB secondary evolved node B sTAGs secondary timing advance group SDU service data unit S-GW serving gateway SRB signaling radio bearer SC-OFDM single carrier-OFDM SFN system frame number SIB system information block TAI tracking area identifier TAT time alignment timer TDD time division duplexing TDMA time division multiple access TA timing advance TAG timing advance group TB transport block UL uplink UE user equipment VHDL VHSIC hardware description language

(3) Example embodiments of the invention may be implemented using various physical layer modulation and transmission mechanisms. Example transmission mechanisms may include, but are not limited to: CDMA, OFDM, TDMA, Wavelet technologies, and/or the like. Hybrid transmission mechanisms such as TDMA/CDMA, and OFDM/CDMA may also be employed. Various modulation schemes may be applied for signal transmission in the physical layer. Examples of modulation schemes include, but are not limited to: phase, amplitude, code, a combination of these, and/or the like. An example radio transmission method may implement QAM using BPSK, QPSK, 16-QAM, 64-QAM, 256-QAM, and/or the like. Physical radio transmission may be enhanced by dynamically or semi-dynamically changing the modulation and coding scheme depending on transmission requirements and radio conditions.

(4) FIG. 1 is a diagram depicting example sets of OFDM subcarriers as per an aspect of an embodiment of the present invention. As illustrated in this example, arrow(s) in the diagram may depict a subcarrier in a multicarrier OFDM system. The OFDM system may use technology such as OFDM technology, SC-OFDM technology, or the like. For example, arrow **101** shows a subcarrier transmitting information symbols. FIG. 1 is for illustration purposes, and a typical multicarrier OFDM system may include more subcarriers in a carrier. For example, the number of subcarriers in a carrier may be in the range of 10 to 10,000 subcarriers. FIG. 1 shows two guard bands **106** and **107** in a transmission band. As illustrated in FIG. 1, guard band **106** is between subcarriers **103** and subcarriers **104**. The example set of subcarriers A **102** includes subcarriers **103** and subcarriers **104**. FIG. 1 also illustrates an example set of subcarriers B **105**. As illustrated, there is no guard band between any two subcarriers in the example set of subcarriers B **105**. Carriers in a multicarrier OFDM communication system may be contiguous carriers, non-contiguous carriers, or a combination of both contiguous and non-contiguous carriers.

(5) FIG. 2 is a diagram depicting an example transmission time and reception time for two carriers as per an aspect of an embodiment of the present invention. A multicarrier OFDM communication system may include one or more carriers, for example, ranging from 1 to 10 carriers. Carrier A **204** and carrier B **205** may have the same or different timing structures. Although FIG. 2 shows two synchronized carriers, carrier A **204** and carrier B **205** may or may not be synchronized with each other. Different radio frame structures may be supported for FDD and TDD duplex mechanisms. FIG. 2 shows an example FDD frame timing. Downlink and uplink transmissions may be organized into radio frames **201**. In this example, radio frame duration is 10 msec. Other frame durations, for example, in the range of 1 to 100 msec may also be supported. In this example, each 10 ms radio frame **201** may be divided into ten equally sized subframes **202**. Other subframe durations such as including 0.5 msec, 1 msec, 2 msec, and 5 msec may also be supported. Subframe(s) may consist of two or more slots (e.g. slots **206** and **207**). For the example of FDD, 10 subframes may be available for downlink transmission and 10 subframes may be available for uplink transmissions in

each 10 ms interval. Uplink and downlink transmissions may be separated in the frequency domain. Slot(s) may include a plurality of OFDM symbols **203**. The number of OFDM symbols **203** in a slot **206** may depend on the cyclic prefix length and subcarrier spacing.

(6) FIG. **3** is a diagram depicting OFDM radio resources as per an aspect of an embodiment of the present invention. The resource grid structure in time **304** and frequency **305** is illustrated in FIG. **3**. The quantity of downlink subcarriers or RBs (in this example 6 to 100 RBs) may depend, at least in part, on the downlink transmission bandwidth **306** configured in the cell. The smallest radio resource unit may be called a resource element (e.g. **301**). Resource elements may be grouped into resource blocks (e.g. **302**). Resource blocks may be grouped into larger radio resources called Resource Block Groups (RBG) (e.g. **303**). The transmitted signal in slot **206** may be described by one or several resource grids of a plurality of subcarriers and a plurality of OFDM symbols. Resource blocks may be used to describe the mapping of certain physical channels to resource elements. Other pre-defined groupings of physical resource elements may be implemented in the system depending on the radio technology. For example, 24 subcarriers may be grouped as a radio block for a duration of 5 msec. In an illustrative example, a resource block may correspond to one slot in the time domain and 180 kHz in the frequency domain (for 15 KHz subcarrier bandwidth and 12 subcarriers).

(7) FIG. **5A**, FIG. **5B**, FIG. **5C** and FIG. **5D** are example diagrams for uplink and downlink signal transmission as per an aspect of an embodiment of the present invention. FIG. **5A** shows an example uplink physical channel. The baseband signal representing the physical uplink shared channel may perform the following processes. These functions are illustrated as examples and it is anticipated that other mechanisms may be implemented in various embodiments. The functions may comprise scrambling, modulation of scrambled bits to generate complex-valued symbols, mapping of the complex-valued modulation symbols onto one or several transmission layers, transform precoding to generate complex-valued symbols, precoding of the complex-valued symbols, mapping of precoded complex-valued symbols to resource elements, generation of complex-valued time-domain SC-FDMA signal for each antenna port, and/or the like.

(8) Example modulation and up-conversion to the carrier frequency of the complex-valued SC-FDMA baseband signal for each antenna port and/or the complex-valued PRACH baseband signal is shown in FIG. **5B**. Filtering may be employed prior to transmission.

(9) An example structure for Downlink Transmissions is shown in FIG. **5C**. The baseband signal representing a downlink physical channel may perform the following processes. These functions are illustrated as examples and it is anticipated that other mechanisms may be implemented in various embodiments. The functions include scrambling of coded bits in each of the codewords to be transmitted on a physical channel; modulation of scrambled bits to generate complex-valued modulation symbols; mapping of the complex-valued modulation symbols onto one or several transmission layers; precoding of the complex-valued modulation symbols on each layer for transmission on the antenna ports; mapping of complex-valued modulation symbols for each antenna port to resource elements; generation of complex-valued time-domain OFDM signal for each antenna port, and/or the like.

(10) Example modulation and up-conversion to the carrier frequency of the complex-valued OFDM baseband signal for each antenna port is shown in FIG. **5D**. Filtering may be employed prior to transmission.

(11) FIG. **4** is an example block diagram of a base station **401** and a wireless device **406**, as per an aspect of an embodiment of the present invention. A communication network **400** may include at least one base station **401** and at least one wireless device **406**. The base station **401** may include at least one communication interface **402**, at least one processor **403**, and at least one set of program code instructions **405** stored in non-transitory memory **404** and executable by the at least one processor **403**. The wireless device **406** may include at least one communication interface **407**, at least one processor **408**, and at least one set of program code instructions **410** stored in non-

transitory memory **409** and executable by the at least one processor **408**. Communication interface **402** in base station **401** may be configured to engage in communication with communication interface **407** in wireless device **406** via a communication path that includes at least one wireless link **411**. Wireless link **411** may be a bi-directional link. Communication interface **407** in wireless device **406** may also be configured to engage in a communication with communication interface **402** in base station **401**. Base station **401** and wireless device **406** may be configured to send and receive data over wireless link **411** using multiple frequency carriers. According to some of the various aspects of embodiments, transceiver(s) may be employed. A transceiver is a device that includes both a transmitter and receiver. Transceivers may be employed in devices such as wireless devices, base stations, relay nodes, and/or the like. Example embodiments for radio technology implemented in communication interface **402**, **407** and wireless link **411** are illustrated are FIG. **1**, FIG. **2**, FIG. **3**, FIG. **5**, and associated text.

(12) An interface may be a hardware interface, a firmware interface, a software interface, and/or a combination thereof. The hardware interface may include connectors, wires, electronic devices such as drivers, amplifiers, and/or the like. A software interface may include code stored in a memory device to implement protocol(s), protocol layers, communication drivers, device drivers, combinations thereof, and/or the like. A firmware interface may include a combination of embedded hardware and code stored in and/or in communication with a memory device to implement connections, electronic device operations, protocol(s), protocol layers, communication drivers, device drivers, hardware operations, combinations thereof, and/or the like.

(13) The term configured may relate to the capacity of a device whether the device is in an operational or non-operational state. Configured may also refer to specific settings in a device that effect the operational characteristics of the device whether the device is in an operational or non-operational state. In other words, the hardware, software, firmware, registers, memory values, and/or the like may be “configured” within a device, whether the device is in an operational or nonoperational state, to provide the device with specific characteristics. Terms such as “a control message to cause in a device” may mean that a control message has parameters that may be used to configure specific characteristics in the device, whether the device is in an operational or non-operational state.

(14) According to some of the various aspects of embodiments, an LTE network may include a multitude of base stations, providing a user plane PDCP/RLC/MAC/PHY and control plane (RRC) protocol terminations towards the wireless device. The base station(s) may be interconnected with other base station(s) (e.g. employing an X2 interface). The base stations may also be connected employing, for example, an S1 interface to an EPC. For example, the base stations may be interconnected to the MME employing the S1-MME interface and to the S-G) employing the S1-U interface. The S1 interface may support a many-to-many relation between MMEs/Serving Gateways and base stations. A base station may include many sectors for example: 1, 2, 3, 4, or 6 sectors. A base station may include many cells, for example, ranging from 1 to 50 cells or more. A cell may be categorized, for example, as a primary cell or secondary cell. At RRC connection establishment/re-establishment/handover, one serving cell may provide the NAS (non-access stratum) mobility information (e.g. TAI), and at RRC connection re-establishment/handover, one serving cell may provide the security input. This cell may be referred to as the Primary Cell (PCell). In the downlink, the carrier corresponding to the PCell may be the Downlink Primary Component Carrier (DL PCC), while in the uplink, it may be the Uplink Primary Component Carrier (UL PCC). Depending on wireless device capabilities, Secondary Cells (SCells) may be configured to form together with the PCell a set of serving cells. In the downlink, the carrier corresponding to an SCell may be a Downlink Secondary Component Carrier (DL SCC), while in the uplink, it may be an Uplink Secondary Component Carrier (UL SCC). An SCell may or may not have an uplink carrier.

(15) A cell, comprising a downlink carrier and optionally an uplink carrier, may be assigned a

physical cell ID and a cell index. A carrier (downlink or uplink) may belong to only one cell. The cell ID or Cell index may also identify the downlink carrier or uplink carrier of the cell (depending on the context it is used). In the specification, cell ID may be equally referred to a carrier ID, and cell index may be referred to carrier index. In implementation, the physical cell ID or cell index may be assigned to a cell. A cell ID may be determined using a synchronization signal transmitted on a downlink carrier. A cell index may be determined using RRC messages. For example, when the specification refers to a first physical cell ID for a first downlink carrier, the specification may mean the first physical cell ID is for a cell comprising the first downlink carrier. The same concept may apply to, for example, carrier activation. When the specification indicates that a first carrier is activated, the specification may equally mean that the cell comprising the first carrier is activated.

(16) Embodiments may be configured to operate as needed. The disclosed mechanism may be performed when certain criteria are met, for example, in a wireless device, a base station, a radio environment, a network, a combination of the above, and/or the like. Example criteria may be based, at least in part, on for example, traffic load, initial system set up, packet sizes, traffic characteristics, a combination of the above, and/or the like. When the one or more criteria are met, various example embodiments may be applied. Therefore, it may be possible to implement example embodiments that selectively implement disclosed protocols.

(17) A base station may communicate with a mix of wireless devices. Wireless devices may support multiple technologies, and/or multiple releases of the same technology. Wireless devices may have some specific capability(ies) depending on its wireless device category and/or capability(ies). A base station may comprise multiple sectors. When this disclosure refers to a base station communicating with a plurality of wireless devices, this disclosure may refer to a subset of the total wireless devices in a coverage area. This disclosure may refer to, for example, a plurality of wireless devices of a given LTE release with a given capability and in a given sector of the base station. The plurality of wireless devices in this disclosure may refer to a selected plurality of wireless devices, and/or a subset of total wireless devices in a coverage area which perform according to disclosed methods, and/or the like. There may be a plurality of wireless devices in a coverage area that may not comply with the disclosed methods, for example, because those wireless devices perform based on older releases of LTE technology.

(18) FIG. 6 and FIG. 7 are example diagrams for protocol structure with CA and DC as per an aspect of an embodiment of the present invention. E-UTRAN may support Dual Connectivity (DC) operation whereby a multiple RX/TX UE in RRC_CONNECTED may be configured to utilize radio resources provided by two schedulers located in two eNBs connected via a non-ideal backhaul over the X2 interface. eNBs involved in DC for a certain UE may assume two different roles: an eNB may either act as an MeNB or as an SeNB. In DC a UE may be connected to one MeNB and one SeNB. Mechanisms implemented in DC may be extended to cover more than two eNBs. FIG. 7 illustrates one example structure for the UE side MAC entities when a Master Cell Group (MCG) and a Secondary Cell Group (SCG) are configured, and it may not restrict implementation. Media Broadcast Multicast Service (MBMS) reception is not shown in this figure for simplicity.

(19) In DC, the radio protocol architecture that a particular bearer uses may depend on how the bearer is setup. Three alternatives may exist, an MCG bearer, an SCG bearer and a split bearer as shown in FIG. 6. RRC may be located in MeNB and SRBs may be configured as a MCG bearer type and may use the radio resources of the MeNB. DC may also be described as having at least one bearer configured to use radio resources provided by the SeNB. DC may or may not be configured/implemented in example embodiments of the invention.

(20) In the case of DC, the UE may be configured with two MAC entities: one MAC entity for MeNB, and one MAC entity for SeNB. In DC, the configured set of serving cells for a UE may comprise of two subsets: the Master Cell Group (MCG) containing the serving cells of the MeNB, and the Secondary Cell Group (SCG) containing the serving cells of the SeNB. For a SCG, one or

more of the following may be applied: at least one cell in the SCG has a configured UL CC and one of them, named PSCell (or PCell of SCG, or sometimes called PCell), is configured with PUCCH resources; when the SCG is configured, there may be at least one SCG bearer or one Split bearer; upon detection of a physical layer problem or a random access problem on a PSCell, or the maximum number of RLC retransmissions has been reached associated with the SCG, or upon detection of an access problem on a PSCell during a SCG addition or a SCG change: a RRC connection re-establishment procedure may not be triggered, UL transmissions towards cells of the SCG are stopped, a MeNB may be informed by the UE of a SCG failure type, for split bearer, the DL data transfer over the MeNB is maintained; the RLC AM bearer may be configured for the split bearer; like PCell, PSCell may not be de-activated; PSCell may be changed with a SCG change (e.g. with security key change and a RACH procedure); and/or neither a direct bearer type change between a Split bearer and a SCG bearer nor simultaneous configuration of a SCG and a Split bearer are supported.

(21) With respect to the interaction between a MeNB and a SeNB, one or more of the following principles may be applied: the MeNB may maintain the RRM measurement configuration of the UE and may, (e.g. based on received measurement reports or traffic conditions or bearer types), decide to ask a SeNB to provide additional resources (serving cells) for a UE; upon receiving a request from the MeNB, a SeNB may create a container that may result in the configuration of additional serving cells for the UE (or decide that it has no resource available to do so); for UE capability coordination, the MeNB may provide (part of) the AS configuration and the UE capabilities to the SeNB; the MeNB and the SeNB may exchange information about a UE configuration by employing of RRC containers (inter-node messages) carried in X2 messages; the SeNB may initiate a reconfiguration of its existing serving cells (e.g., PUCCH towards the SeNB); the SeNB may decide which cell is the PSCell within the SCG; the MeNB may not change the content of the RRC configuration provided by the SeNB; in the case of a SCG addition and a SCG SCell addition, the MeNB may provide the latest measurement results for the SCG cell(s); both a MeNB and a SeNB may know the SFN and subframe offset of each other by OAM, (e.g., for the purpose of DRX alignment and identification of a measurement gap). In an example, when adding a new SCG SCell, dedicated RRC signalling may be used for sending required system information of the cell as for CA, except for the SFN acquired from a MIB of the PSCell of a SCG.

(22) According to some of the various aspects of embodiments, serving cells having an uplink to which the same time alignment (TA) applies may be grouped in a TA group (TAG).

(23) Serving cells in one TAG may use the same timing reference. For a given TAG, user equipment (UE) may use one downlink carrier as a timing reference at a given time. The UE may use a downlink carrier in a TAG as a timing reference for that TAG. For a given TAG, a UE may synchronize uplink subframe and frame transmission timing of uplink carriers belonging to the same TAG. According to some of the various aspects of embodiments, serving cells having an uplink to which the same TA applies may correspond to serving cells hosted by the same receiver. A TA group may comprise at least one serving cell with a configured uplink. A UE supporting multiple TAs may support two or more TA groups. One TA group may contain the PCell and may be called a primary TAG (pTAG). In a multiple TAG configuration, at least one TA group may not contain the PCell and may be called a secondary TAG (sTAG). Carriers within the same TA group may use the same TA value and the same timing reference. When DC is configured, cells belonging to a cell group (MCG or SCG) may be grouped into multiple TAGs including a pTAG and one or more sTAGs.

(24) FIG. 8 shows example TAG configurations as per an aspect of an embodiment of the present invention. In Example 1, pTAG comprises PCell, and an sTAG comprises SCell1. In Example 2, a pTAG comprises a PCell and SCell1, and an sTAG comprises SCell2 and SCell3. In Example 3, pTAG comprises PCell and SCell1, and an sTAG1 includes SCell2 and SCell3, and sTAG2 comprises SCell4. Up to four TAGs may be supported in a cell group (MCG or SCG) and other

example TAG configurations may also be provided. In various examples in this disclosure, example mechanisms are described for a pTAG and an sTAG. The operation with one example sTAG is described, and the same operation may be applicable to other sTAGs. The example mechanisms may be applied to configurations with multiple sTAGs.

(25) According to some of the various aspects of embodiments, TA maintenance, pathloss reference handling and a timing reference for a pTAG may follow LTE release 10 principles in the MCG and/or SCG. The UE may need to measure downlink pathloss to calculate uplink transmit power. A pathloss reference may be used for uplink power control and/or transmission of random access preamble(s). UE may measure downlink pathloss using signals received on a pathloss reference cell. For SCell(s) in a pTAG, the choice of a pathloss reference for cells may be selected from and/or be limited to the following two options: a) the downlink SCell linked to an uplink SCell using system information block 2 (SIB2), and b) the downlink pCell. The pathloss reference for SCells in a pTAG may be configurable using RRC message(s) as a part of an SCell initial configuration and/or reconfiguration. According to some of the various aspects of embodiments, a PhysicalConfigDedicatedSCell information element (IE) of an SCell configuration may include a pathloss reference SCell (downlink carrier) for an SCell in a pTAG. The downlink SCell linked to an uplink SCell using system information block 2 (SIB2) may be referred to as the SIB2 linked downlink of the SCell. Different TAGs may operate in different bands. For an uplink carrier in an sTAG, the pathloss reference may be only configurable to the downlink SCell linked to an uplink SCell using the system information block 2 (SIB2) of the SCell.

(26) To obtain initial uplink (UL) time alignment for an sTAG, an eNB may initiate an RA procedure. In an sTAG, a UE may use one of any activated SCells from this sTAG as a timing reference cell. In an example embodiment, the timing reference for SCells in an sTAG may be the SIB2 linked downlink of the SCell on which the preamble for the latest RA procedure was sent. There may be one timing reference and one time alignment timer (TAT) per TA group. A TAT for TAGs may be configured with different values. In a MAC entity, when a TAT associated with a pTAG expires: all TATs may be considered as expired, the UE may flush HARQ buffers of serving cells, the UE may clear any configured downlink assignment/uplink grants, and the RRC in the UE may release PUCCH/SRS for all configured serving cells. When the pTAG TAT is not running, an sTAG TAT may not be running. When the TAT associated with an sTAG expires: a) SRS transmissions may be stopped on the corresponding SCells, b) SRS RRC configuration may be released, c) CSI reporting configuration for corresponding SCells may be maintained, and/or d) the MAC in the UE may flush the uplink HARQ buffers of the corresponding SCells.

(27) An eNB may initiate an RA procedure via a PDCCH order for an activated SCell. This PDCCH order may be sent on a scheduling cell of this SCell. When cross carrier scheduling is configured for a cell, the scheduling cell may be different than the cell that is employed for preamble transmission, and the PDCCH order may include an SCell index. At least a non-contention based RA procedure may be supported for SCell(s) assigned to sTAG(s).

(28) FIG. 9 is an example message flow in a random access process in a secondary TAG as per an aspect of an embodiment of the present invention. An eNB transmits an activation command **600** to activate an SCell. A preamble **602** (Msg1) may be sent by a UE in response to a PDCCH order **601** on an SCell belonging to an sTAG. In an example embodiment, preamble transmission for SCells may be controlled by the network using PDCCH format 1A. Msg2 message **603** (RAR: random access response) in response to the preamble transmission on the SCell may be addressed to RA-RNTI in a PCell common search space (CSS). Uplink packets **604** may be transmitted on the SCell in which the preamble was transmitted.

(29) According to some of the various aspects of embodiments, initial timing alignment may be achieved through a random access procedure. This may involve a UE transmitting a random access preamble and an eNB responding with an initial TA command NTA (amount of timing advance) within a random access response window. The start of the random access preamble may be aligned

with the start of a corresponding uplink subframe at the UE assuming $NTA=0$. The eNB may estimate the uplink timing from the random access preamble transmitted by the UE. The TA command may be derived by the eNB based on the estimation of the difference between the desired UL timing and the actual UL timing. The UE may determine the initial uplink transmission timing relative to the corresponding downlink of the sTAG on which the preamble is transmitted.

(30) The mapping of a serving cell to a TAG may be configured by a serving eNB with RRC signaling. The mechanism for TAG configuration and reconfiguration may be based on RRC signaling. According to some of the various aspects of embodiments, when an eNB performs an SCell addition configuration, the related TAG configuration may be configured for the SCell. In an example embodiment, an eNB may modify the TAG configuration of an SCell by removing (releasing) the SCell and adding(configuring) a new SCell (with the same physical cell ID and frequency) with an updated TAG ID. The new SCell with the updated TAG ID may initially be inactive subsequent to being assigned the updated TAG ID. The eNB may activate the updated new SCell and start scheduling packets on the activated SCell. In an example implementation, it may not be possible to change the TAG associated with an SCell, but rather, the SCell may need to be removed and a new SCell may need to be added with another TAG. For example, if there is a need to move an SCell from an sTAG to a pTAG, at least one RRC message, for example, at least one RRC reconfiguration message, may be send to the UE to reconfigure TAG configurations by releasing the SCell and then configuring the SCell as a part of the pTAG (when an SCell is added/configured without a TAG index, the SCell may be explicitly assigned to the pTAG). The PCell may not change its TA group and may always be a member of the pTAG.

(31) The purpose of an RRC connection reconfiguration procedure may be to modify an RRC connection, (e.g. to establish, modify and/or release RBs, to perform handover, to setup, modify, and/or release measurements, to add, modify, and/or release SCells). If the received RRC Connection Reconfiguration message includes the sCellToReleaseList, the UE may perform an SCell release. If the received RRC Connection Reconfiguration message includes the sCellToAddModList, the UE may perform SCell additions or modification.

(32) In LTE Release-10 and Release-11 CA, a PUCCH is only transmitted on the PCell (PSCell) to an eNB. In LTE-Release 12 and earlier, a UE may transmit PUCCH information on one cell (PCell or PSCell) to a given eNB.

(33) As the number of CA capable UEs and also the number of aggregated carriers increase, the number of PUCCHs and also the PUCCH payload size may increase. Accommodating the PUCCH transmissions on the PCell may lead to a high PUCCH load on the PCell. A PUCCH on an SCell may be introduced to offload the PUCCH resource from the PCell. More than one PUCCH may be configured for example, a PUCCH on a PCell and another PUCCH on an SCell. FIG. 10 is an example grouping of cells into PUCCH groups as per an aspect of an embodiment of the present invention. In the example embodiments, one, two or more cells may be configured with PUCCH resources for transmitting CSI/ACK/NACK to a base station. Cells may be grouped into multiple PUCCH groups, and one or more cell within a group may be configured with a PUCCH. In an example configuration, one SCell may belong to one PUCCH group. SCells with a configured PUCCH transmitted to a base station may be called a PUCCH SCell, and a cell group with a common PUCCH resource transmitted to the same base station may be called a PUCCH group.

(34) In Release-12, a PUCCH can be configured on a PCell and/or a PSCell, but cannot be configured on other SCells. In an example embodiment, a UE may transmit a message indicating that the UE supports PUCCH configuration on a PCell and SCell. Such an indication may be separate from an indication of of dual connectivity support by the UE. In an example embodiment, a UE may support both DC and PUCCH groups. In an example embodiment, either DC or PUCCH groups may be configured, but not both. In another example embodiment, more complicated configurations comprising both DC and PUCCH groups may be supported.

(35) When a UE is capable of configuring PUCCH groups, and if a UE indicates that it supports

simultaneous PUCCH/PUSCH transmission capability, it may imply that the UE supports simultaneous PUCCH/PUSCH transmission on both PCell and SCell. When multiple PUCCH groups are configured, a PUCCH may be configured or not configured with simultaneous PUCCH/PUSCH transmission.

(36) In an example embodiment, PUCCH transmission to a base station on two serving cells may be realized as shown in FIG. 10. A first group of cells may employ a PUCCH on the PCell and may be called PUCCH group 1 or a primary PUCCH group. A second group of cells may employ a PUCCH on an SCell and may be called PUCCH group 2 or a secondary PUCCH group. One, two or more PUCCH groups may be configured. In an example, cells may be grouped into two PUCCH groups, and each PUCCH group may include a cell with PUCCH resources. A PCell may provide PUCCH resources for the primary PUCCH group and an SCell in the secondary PUCCH group may provide PUCCH resources for the cells in the secondary PUCCH group. In an example embodiment, no cross-carrier scheduling between cells in different PUCCH groups may be configured. When cross-carrier scheduling between cells in different PUCCH groups is not configured, ACK/NACK on PHICH channel may be limited within a PUCCH group. Both downlink and uplink scheduling activity may be separate between cells belonging to different PUCCH groups.

(37) A PUCCH on an SCell may carry HARQ-ACK and CSI information. A PCell may be configured with PUCCH resources. In an example embodiment, RRC parameters for an SCell PUCCH Power Control for a PUCCH on an SCell may be different from those of a PCell PUCCH. A Transmit Power Control command for a PUCCH on an SCell may be transmitted in DCI(s) on the SCell carrying the PUCCH.

(38) UE procedures on a PUCCH transmission may be different and/or independent between PUCCH groups. For example, determination of DL HARQ-ACK timing, PUCCH resource determination for HARQ-ACK and/or CSI, Higher-layer configuration of simultaneous HARQ-ACK+CSI on a PUCCH, Higher-layer configuration of simultaneous HARQ-ACK+SRS in one subframe may be configured differently for a PUCCH PCell and a PUCCH SCell.

(39) A PUCCH group may be a group of serving cells configured by a RRC and use the same serving cell in the group for transmission of a PUCCH. A Primary PUCCH group may be a PUCCH group containing a PCell. A secondary PUCCH group may be a PUCCH cell group not containing the PCell. In an example embodiment, an SCell may belong to one PUCCH group. When one SCell belongs to a PUCCH group, ACK/NACK or CSI for that SCell may be transmitted over the PUCCH in that PUCCH group (over PUCCH SCell or PUCCH PCell). A PUCCH on an SCell may reduce the PUCCH load on the PCell. A PUCCH SCell may be employed for UCI transmission of SCells in the corresponding PUCCH group.

(40) In an example embodiment, a flexible PUCCH configuration in which control signalling is sent on one, two or more PUCCHs may be possible. Beside the PCell, it may be possible to configure a selected number of SCells for PUCCH transmission (herein called PUCCH SCells). Control signalling information conveyed in a certain PUCCH SCell may be related to a set of SCells in a corresponding PUCCH group that are configured by the network via RRC signalling.

(41) PUCCH control signalling carried by a PUCCH channel may be distributed between a PCell and SCells for off-loading or robustness purposes. By enabling a PUCCH in an SCell, it may be possible to distribute the overall CSI reports for a given UE between a PCell and a selected number of SCells (e.g. PUCCH SCells), thereby limiting PUCCH CSI resource consumption by a given UE on a certain cell. It may be possible to map CSI reports for a certain SCell to a selected PUCCH SCell. An SCell may be assigned a certain periodicity and time-offset for transmission of control information. Periodic CSI for a serving cell may be mapped on a PUCCH (on the PCell or on a PUCCH-SCell) via RRC signalling. The possibility of distributing CSI reports, HARQ feedbacks, and/or Scheduling Requests across PUCCH SCells may provide flexibility and capacity improvements. HARQ feedback for a serving cell may be mapped on a PUCCH (on the PCell or on

a PUCCH SCell) via RRC signalling.

(42) In example embodiments, PUCCH transmission may be configured on a PCell, as well as one SCell in CA. An SCell PUCCH may be realized using the concept of PUCCH groups, where aggregated cells are grouped into two or more PUCCH groups. One cell from a PUCCH group may be configured to carry a PUCCH. More than 5 carriers may be configured. In the example embodiments, up to n carriers may be aggregated. For example, n may be 16, 32, or 64. Some CCs may have non-backward compatible configurations supporting only advanced UEs (e.g. support licensed assisted access SCells). In an example embodiment, one SCell PUCCH (e.g. two PUCCH groups) may be supported. In another example embodiment, a PUCCH group concept with multiple (more than one) SCells carrying PUCCH may be employed (e.g., there can be more than two PUCCH groups).

(43) In an example embodiment, a given PUCCH group may not comprise serving cells of both MCG and SCG. One of the PUCCHs may be configured on the PCell. In an example embodiment, PUCCH mapping of serving cells may be configured by RRC messages. In an example embodiment, a maximum value of an SCellIndex and a ServCellIndex may be 31 (ranging from 0 to 31). In an example, a maximum value of stag-Id may be 3. The CIF for a scheduled cell may be configured explicitly. A PUCCH SCell may be configured by giving a PUCCH configuration for an SCell. A HARQ feedback and CSI report of a PUCCH SCell may be sent on the PUCCH of that PUCCH SCell. The HARQ feedback and CSI report of a SCell may be sent on a PUCCH of a PCell if no PUCCH SCell is signalled for that SCell. The HARQ feedback and CSI report of an SCell may be sent on the PUCCH of one PUCCH SCell; hence they may not be sent on the PUCCH of different PUCCH SCell. The UE may report a Type 2 PH for serving cells configured with a PUCCH. In an example embodiment, a MAC activation/deactivation may be supported for a PUCCH SCell. An eNB may manage the activation/deactivation status for SCells. A newly added PUCCH SCell may be initially deactivated.

(44) In an example embodiment, independent configuration of PUCCH groups and TAGs may be supported. FIG. 11 and FIG. 12 show example configurations of TAGs and PUCCH groups. For example, one TAG may contain multiple serving cells with a PUCCH. For example, each TAG may only comprise cells of one PUCCH group. For example, a TAG may comprise the serving cells (without a PUCCH) which belong to different PUCCH groups.

(45) There may not be a one-to-one mapping between TAGs and PUCCH groups. For example, in a configuration, a PUCCH SCell may belong to primary TAG. In an example implementation, the serving cells of one PUCCH group may be in different TAGs and serving cells of one TAG may be in different PUCCH groups. Configuration of PUCCH groups and TAGs may be left to eNB implementation. In another example implementation, restriction(s) on the configuration of a PUCCH cell may be specified. For example, in an example embodiment, cells in a given PUCCH group may belong to the same TAG. In an example, an sTAG may only comprise cells of one PUCCH group. In an example, one-to-one mapping between TAGs and PUCCH groups may be implemented. In implementation, cell configurations may be limited to some of the examples. In other implementations, some or all the below configurations may be allowed.

(46) In an example embodiment, for an SCell in a pTAG, the timing reference may be a PCell. For an SCell in an sTAG, the timing reference may be any activated SCell in the sTAG. For an SCell (configured with PUCCH or not) in a pTAG, a pathloss reference may be configured to be a PCell or an SIB-2 linked SCell. For an SCell in a sTAG, the pathloss reference may be the SIB-2 linked SCell. When a TAT associated with a pTAG is expired, the TAT associated with sTAGs may be considered as expired. When a TAT of an sTAG containing PUCCH SCell expires, the MAC may indicate to an RRC to release PUCCH resource for the PUCCH group. When the TAT of an sTAG containing a PUCCH SCell is not running, the uplink transmission (PUSCH) for SCells in the secondary PUCCH group not belonging to the sTAG including the PUCCH SCell may not be impacted. The TAT expiry of an sTAG containing a PUCCH SCell may not trigger TAT expiry of

other TAGs to which other SCells in the same PUCCH group belong. When the TAT associated with sTAG not containing a PUCCH SCell is not running, the wireless device may stop the uplink transmission for the SCell in the sTAG and may not impact other TAGs.

(47) In an example embodiment, a MAC entity may have a configurable timer `timeAlignmentTimer` per TAG. The `timeAlignmentTimer` may be used to control how long the MAC entity considers the Serving Cells belonging to the associated TAG to be uplink time aligned. The MAC entity may, when a Timing Advance Command MAC control element is received, apply the Timing Advance Command for the indicated TAG; start or restart the `timeAlignmentTimer` associated with the indicated TAG. The MAC entity may, when a Timing Advance Command is received in a Random Access Response message for a serving cell belonging to a TAG and/or if the Random Access Preamble was not selected by the MAC entity, apply the Timing Advance Command for this TAG and start or restart the `timeAlignmentTimer` associated with this TAG. Otherwise, if the `timeAlignmentTimer` associated with this TAG is not running, the Timing Advance Command for this TAG may be applied and the `timeAlignmentTimer` associated with this TAG started. When the contention resolution is considered not successful, a `timeAlignmentTimer` associated with this TAG may be stopped. Otherwise, the MAC entity may ignore the received Timing Advance Command.

(48) Example embodiments of the invention may enable operation of multiple PUCCH groups. Other example embodiments may comprise a non-transitory tangible computer readable media comprising instructions executable by one or more processors to cause operation of PUCCH groups. Yet other example embodiments may comprise an article of manufacture that comprises a non-transitory tangible computer readable machine-accessible medium having instructions encoded thereon for enabling programmable hardware to cause a device (e.g. wireless communicator, UE, base station, etc.) to enable operation of PUCCH groups. The device may include processors, memory, interfaces, and/or the like. Other example embodiments may comprise communication networks comprising devices such as base stations, wireless devices (or user equipment: UE), servers, switches, antennas, and/or the like. In an example embodiment one or more TAGs may be configured along with PUCCH group configuration.

(49) FIG. 13 is an example MAC PDU as per an aspect of an embodiment of the present invention. In an example embodiment, a MAC PDU may comprise of a MAC header, zero or more MAC Service Data Units (MAC SDU), zero or more MAC control elements, and optionally padding. The MAC header and the MAC SDUs may be of variable sizes. A MAC PDU header may comprise one or more MAC PDU subheaders. A subheader may correspond to either a MAC SDU, a MAC control element or padding. A MAC PDU subheader may comprise header fields R, F2, E, LCID, F, and/or L. The last subheader in the MAC PDU and subheaders for fixed sized MAC control elements may comprise the four header fields R, F2, E, and/or LCID. A MAC PDU subheader corresponding to padding may comprise the four header fields R, F2, E, and/or LCID.

(50) In an example embodiment, LCID or Logical Channel ID field may identify the logical channel instance of the corresponding MAC SDU or the type of the corresponding MAC control element or padding. There may be one LCID field for a MAC SDU, MAC control element or padding included in the MAC PDU. In addition to that, one or two additional LCID fields may be included in the MAC PDU when single-byte or two-byte padding is required but cannot be achieved by padding at the end of the MAC PDU. The LCID field size may be, e.g. 5 bits. L or the Length field may indicate the length of the corresponding MAC SDU or variable-sized MAC control element in bytes. There may be one L field per MAC PDU subheader except for the last subheader and subheaders corresponding to fixed-sized MAC control elements. The size of the L field may be indicated by the F field and F2 field. The F or the Format field may indicate the size of the Length field. There may be one F field per MAC PDU subheader except for the last subheader and subheaders corresponding to fixed-sized MAC control elements and expect for when F2 is set to 1. The size of the F field may be 1 bit. In an example, if the F field is included, and/or if

the size of the MAC SDU or variable-sized MAC control element is less than 128 bytes, the value of the F field is set to 0, otherwise it is set to 1. The F2 or the Format2 field may indicate the size of the Length field. There may be one F2 field per MAC PDU subheader. The size of the F2 field may be 1 bit. In an example, if the size of the MAC SDU or variable-sized MAC control element is larger than 32767 bytes and if the corresponding subheader is not the last subheader, the value of the F2 field may be set to 1, otherwise it is set to 0. The E or the Extension field may be a flag indicating if more fields are present in the MAC header or not. The E field may be set to “1” to indicate another set of at least R/F2/E/LCID fields. The E field may be set to “0” to indicate that either a MAC SDU, a MAC control element or padding starts at the next byte. R or reserved bit, set to “0”.

(51) MAC PDU subheaders may have the same order as the corresponding MAC SDUs, MAC control elements and padding. MAC control elements may be placed before any MAC SDU. Padding may occur at the end of the MAC PDU, except when single-byte or two-byte padding is required. Padding may have any value and the MAC entity may ignore it. When padding is performed at the end of the MAC PDU, zero or more padding bytes may be allowed. When single-byte or two-byte padding is required, one or two MAC PDU subheaders corresponding to padding may be placed at the beginning of the MAC PDU before any other MAC PDU subheader. In an example, a maximum of one MAC PDU may be transmitted per TB per MAC entity, a maximum of one MCH MAC PDU can be transmitted per TTI.

(52) At least one RRC message may provide configuration parameters for at least one cell and configuration parameters for PUCCH groups. The information elements in one or more RRC messages may provide mapping between configured cells and PUCCH SCells. Cells may be grouped into a plurality of cell groups and a cell may be assigned to one of the configured PUCCH groups. There may be a one-to-one relationship between PUCCH groups and cells with configured PUCCH resources. At least one RRC message may provide mapping between an SCell and a PUCCH group, and PUCCH configuration on PUCCH SCell.

(53) System information (common parameters) for an SCell may be carried in a RadioResourceConfigCommonSCell in a dedicated RRC message. Some of the PUCCH related information may be included in common information of an SCell (e.g. in the RadioResourceConfigCommonSCell). Dedicated configuration parameters of SCell and PUCCH resources may be configured by dedicated RRC signaling using, for example, RadioResourceConfigDedicatedSCell.

(54) The IE PUCCH-ConfigCommon and IE PUCCH-ConfigDedicated may be used to specify the common and the UE specific PUCCH configuration respectively.

(55) In an example, PUCCH-ConfigCommon may include: deltaPUCCH-Shift: ENUMERATED {ds1, ds2, ds3}; nRB-CQI: INTEGER (0 . . . 98); nCS-AN: INTEGER (0 . . . 7); and/or n1PUCCH-AN: INTEGER (0 . . . 2047). The parameter deltaPUCCH-Shift ($\Delta_{\text{sub.shift.sup.PUCCH}}$), nRB-CQI ($N_{\text{sub.RB.sup.(2)}}$), nCS-An ($N_{\text{sub.cs.sup.(1)}}$), and n1PUCCH-AN ($N_{\text{sub.PUCCH.sup.(1)}}$) may be physical layer parameters of PUCCH.

(56) PUCCH-ConfigDedicated may be employed. PUCCH-ConfigDedicated may include: ackNackRepetition CHOICE {release: NULL, setup: SEQUENCE {repetitionFactor: ENUMERATED {n2, n4, n6, spare1}, n1PUCCH-AN-Rep: INTEGER (0 . . . 2047)}}, tdd-AckNackFeedbackMode: ENUMERATED {bundling, multiplexing} OPTIONAL}. ackNackRepetitionj parameter indicates whether ACK/NACK repetition is configured. n2 corresponds to repetition factor 2, n4 to 4 for repetitionFactor parameter ($N_{\text{sub.ANRep}}$). n1PUCCH-AN-Rep parameter may be $n_{\text{sub.PUCCH,ANRep.sup.(1,p)}}$ for antenna port P0 and for antenna port P1. dd-AckNackFeedbackMode parameter may indicate one of the TDD ACK/NACK feedback modes used. The value bundling may correspond to use of ACK/NACK bundling whereas, the value multiplexing may correspond to ACK/NACK multiplexing. The same value may apply to both ACK/NACK feedback modes on PUCCH as well as on PUSCH.

(57) The parameter PUCCH-ConfigDedicated may include simultaneous PUCCH-PUSCH parameter indicating whether simultaneous PUCCH and PUSCH transmissions is configured. An E-UTRAN may configure this field for the PCell when the nonContiguousUL-RA-WithinCC-Info is set to supported in the band on which PCell is configured. The E-UTRAN may configure this field for the PSCell when the nonContiguousUL-RA-WithinCC-Info is set to supported in the band on which PSCell is configured. The E-UTRAN may configure this field for the PUCCH SCell when the nonContiguousUL-RA-WithinCC-Info is set to supported in the band on which PUCCH SCell is configured.

(58) A UE may transmit radio capabilities to an eNB to indicate whether UE support the configuration of PUCCH groups. The simultaneous PUCCH-PUSCH in the UE capability message may be applied to both a PCell and an SCell. Simultaneous PUCCH+PUSCH may be configured separately (using separate IEs) for a PCell and a PUCCH SCell. For example, a PCell and a PUCCH SCell may have different or the same configurations related to simultaneous PUCCH+PUSCH.

(59) The eNB may select the PUCCH SCell among current SCells or candidate SCells considering cell loading, carrier quality (e.g. using measurement reports), carrier configuration, and/or other parameters. From a functionality perspective, a PUCCH Cell group management procedure may include a PUCCH Cell group addition, a PUCCH cell group release, a PUCCH cell group change and/or a PUCCH cell group reconfiguration. The PUCCH cell group addition procedure may be used to add a secondary PUCCH cell group (e.g., to add PUCCH SCell and one or more SCells in the secondary PUCCH cell group). In an example embodiment, cells may be released and added employing one or more RRC messages. In another example embodiment, cells may be released employing a first RRC message and then added employing a second RRC messages.

(60) SCells including PUCCH SCell may be in a deactivated state when they are configured. A PUCCH SCell may be activated after an RRC configuration procedure by an activation MAC CE. An eNB may transmit a MAC CE activation command to a UE. The UE may activate an SCell in response to receiving the MAC CE activation command.

(61) In example embodiments, a timer is running once it is started, until it is stopped or until it expires; otherwise it may not be running. A timer can be started if it is not running or restarted if it is running. For example, a timer may be started or restarted from its initial value.

(62) In the example embodiments, up to n carriers may be aggregated. For example, n may be 16, 32, or 64. The schemes for self-scheduling and cross-carrier scheduling may be supported. The corresponding UL/DL control signaling is needed to be enhanced to support aggregation of a large number of carriers. Example embodiments for up to 32 carriers are presented. Example embodiments may be extended to support higher or lower number of carriers. For self-carrier scheduling, DL control signaling for Rel-10/11/12 carrier aggregation (CA) may be reused to support scheduling up to 32 component carriers.

(63) LTE-A R-12 supports configuration of up to 5 serving cells. A cell is identified by a serving cell index (identifier). Cross-carrier scheduling in Rel-12 is supported by a carrier indication field (CIF) of 3 bits in DL/UL DCI formats to indicate a serving cell with DL/UL data transmission among 5 cells. The DCI transmitted in a scheduling cell includes a CIF field. The CIF field indicates the serving cell index (identifier) of the scheduled cell. The CIF in the DCI employs 3 bits. The CIF has a length of 3 bits and is a number smaller than 8. Serving cell index (identifier) in R-12 employs 3 bits and is a number smaller than 8. In R-12, each of the CIF and Serving cell index (identifier) is encoded employing 3 bits.

(64) In R-13 and beyond, up to 32 cells may be supported. Identifying a serving cell when up to 32 cells can be configured may require at least 5 bits. In an example embodiment, a serving cell identifier (index) may employ five bits and be a number smaller than 32. In an example embodiment, a serving cell identifier may employ five bits, e.g. 2 bits of group ID, and 3 bits of cell ID. Various example encoding mechanisms may be employed to identify a serving cell among

32 serving cells. A serving cell among up to 32 serving cells may be identified employing a serving cell identifier of at least five bits.

(65) In order to support cross-carrier scheduling and PUCCH transmission for CA with up to 32 serving cells, 2 additional bits can be added to the CIF for UE-specific DL/UL DCI formats to support full flexibility for cross-carrier scheduling. The capacity of PUCCH can be increased to support up to 32 carriers. An increase of the CIF size from 3 bits to 5 bits may introduce an increase in the number of DL/UL DCI format size (length in bits) that a UE needs to monitor. If the CIF is extended to 5 bits in the DCI signal, then up to 32 carriers may be scheduled by one scheduling carrier. An eNB may flexibly configure the scheduling relationship between the component carriers. This approach may introduce more cost on DCI overhead. The new CIF size of five bits may increase the DCI size to be supported by a UE and may result in more DCI size padding. There is a need to maintain the DCI and/or CIF size, when the number of configured cells increases, e.g. up to 32 cells.

(66) In an example embodiment, the PUCCH capacity of the primary cell may be increased to support up to 32 carriers. This may be technically possible, but may reduce available resources for uplink data transmission on the primary carrier. There is a need to provide additional PUCCH capacity on other serving cells in addition to the PCell when a large number of cells are configured.

(67) In Rel-10, cross carrier scheduling is supported for UE specific search space for SCells. Since maximum of 5 carriers may be configured for one UE, maximum of 4 carriers may be cross scheduled on other than the scheduling carrier like PCell. The search space for a cross scheduled carrier may be determined by the serving cell index. With the increase of number of carriers, 3 bits CIF field in the DCI may not be enough to indicate the carrier index of cross scheduled carriers. 3 OFDM symbols for PDCCH region or ePDCCH resources may not be enough to cross-carrier schedule so many carriers. Example embodiments of the invention may provide solutions to these issues.

(68) In case the number of possible aggregated cells is increased, full flexibility in cross-CC scheduling among a maximum of 32 cells may not be needed. An example embodiment may maintain the Rel-12 CIF size and limit cross-carrier scheduling from a serving cell to another serving cell in a group of cells. This is a cross-carrier scheduling group with at most 8 cells. Taking into account the number of both scheduled and scheduling cells, and the number of cells in a cell group, an eNB may divide cells into cross-carrier scheduling groups (or subgroups) and then may configure cross-carrier scheduling between cells within a cross-carrier scheduling group (or subgroup).

(69) In example embodiments, a PUCCH cell grouping may be introduced to resolve some issues related limited PUCCH capacity on PCell. In example embodiments, a cross-carrier scheduling cell grouping may be introduced to resolve some of issues related CIF size and cross carrier scheduling. In an example implementation, PUCCH grouping may be performed without grouping the cells into cross-carrier scheduling groups. In an example implementation, cross-carrier scheduling grouping may be performed without grouping the cells into PUCCH groups. In an example implementation, cells may be grouped in PUCCH groups, and cells in each PUCCH group may be grouped into one or more cross-carrier scheduling groups.

(70) The same CIF may be reused in different cross-carrier scheduling groups. A cross-carrier scheduling group including only one cell may not require a CIF (a cell may schedule itself). The PCell may schedule other cells in a group and itself (PCell). DCI transmitted on PCell and scheduling PCell may not include a CIF field. In an example, a DCI transmitted on a serving cell to schedule one or more TBs on the same serving cell may not include a CIF. Cross carrier scheduling may or may not be configured for cells in a PUCCH cell group.

(71) Cells are grouped into PUCCH groups according to some example embodiments. In an example embodiment, cells may be grouped in two PUCCH groups. Cells in a PUCCH group may be grouped into cross-carrier scheduling subgroups. A PUCCH group may include one cell with

PUCCH resources. The primary PUCCH group includes PCell with PUCCH resources, and the secondary PUCCH group may include a secondary PUCCH SCell. Uplink control information related to cells in a PUCCH group is transmitted on the associated PUCCH cell in the group.

(72) In an example embodiment, a cross-carrier scheduling group (subgroup) includes cells within a single PUCCH group. Cross-carrier scheduling may be configured within a subgroup. Subgroups may not include cells from two different PUCCH groups. Cross-carrier scheduling within a subgroup may be supported by a CIF of 3 bits in DL/UL DCI formats to indicate a serving cell with DL/UL data transmission among up to 8 cells. A cell in a cross-carrier scheduling subgroup may be identified by a number from 0 to 7 within that subgroup. The same CIF may be reused in different cross-carrier scheduling subgroups. In this specification, a group of one or more cells within another group may be called a group or a subgroup of one or more cells. The term group or subgroup may be used inter-changeably and refer to a group of one or more cells.

(73) An example embodiment may provide grouping mechanisms for downlink cross carrier scheduling as well as uplink control channel transmission. A set of constraints may be introduced in PUCCH transmission, cross carrier scheduling and subgrouping cells within the same PUCCH group. These constraints may provide a mechanism for PUCCH information transmission as well as cross carrier scheduling configuration. Cross carrier scheduling is limited within a cross-carrier scheduling group (subgroup) and a 3 bit CFI may be employed for cross carrier scheduling. A PUCCH group may include one PUCCH cell for uplink PUCCH information transmission for cells within the PUCCH group. A cross-carrier scheduling group may include a cell that carries scheduling information for all the cells within the cross-carrier scheduling group.

(74) In an example embodiment, PUCCH resources of the PUCCH cell in a PUCCH group may comprise resources for UCI transmission of different sets of cells. PUCCH resources may be divided in time, frequency (Resource Blocks), and/or codes and a set of cells may share the assigned PUCCH resources. In an example embodiment, PUCCH sets of resources may be allocated to different CSI processes of different cells.

(75) In an example embodiment, cells may be grouped in PUCCH groups. A PUCCH group may include one cell with PUCCH resources. The primary PUCCH group may include PCell with PUCCH resources, and a secondary PUCCH group may include a secondary PUCCH SCell. Control information related to cells in a PUCCH group is transmitted on the associated PUCCH cell in the group. In an example embodiment, cross carrier scheduling may be permitted only within a PUCCH group. Cross-carrier scheduling within a PUCCH group may be supported by a CIF of 3 bits in DL/UL DCI formats to indicate a serving cell with DL/UL data transmission among up to 8 cells. A cell in a PUCCH group may be identified by a number from 0 to 7 within that subgroup.

(76) The cells are configured and assigned to different cell groups via a semi-static manner using RRC control messages. In an example embodiment, the size of CIF may be 3 bits. This may restrict the maximum number of carriers scheduled by one carrier. Up to 8 PDSCH/PUSCH cells may be linked to one (e)PDCCH cell. In an example embodiment, the cells may be divided into different groups. In an example embodiment, the maximum cell number of a cross-carrier scheduling group (or subgroup) may be limited to 8. Cross-carrier scheduling may be permitted within a cross-carrier scheduling group (or subgroup).

(77) With this grouping, a pair of scheduling cell and scheduled cell may be within the same cross-carrier scheduling group (or subgroup). Groups may be semi-statically configured and the mapping relationship of one or more cells to a scheduling cell may be signaled via higher layer signaling (via RRC control messages). The cross-carrier scheduling may happen within a cross-carrier scheduling group. A 3-bit CIF field may be employed to support cross-CC scheduling.

(78) In an example embodiment, the group ID of a cross-carrier scheduling group is the same as the scheduling cell index (identifier). In an example embodiment, signaling overhead for DCI control signaling may be reduced. Cell groups for cross-carrier scheduling may be configured by higher

layer signaling. A cell in a cross-carrier scheduling group may be configured as a scheduling cell with (E)PDCCH. The scheduling cell may carry scheduling information (DCI) for itself (the scheduling cell) and one or more other cells in the cross-carrier scheduling group.

(79) In an example embodiment, the eNB may transmit to a UE one or more RRC messages comprising configuration parameters of a plurality of cells. The one or more messages may comprise information about configuration of a plurality of PUCCH groups. The one or more messages may comprise information about cross-carrier scheduling groups. In an example embodiment, the configuration parameters for a cell may include a cross carrier scheduling configuration information element (IE). The configuration parameters (e.g. the cross-carrier scheduling configuration IE) of a cell may comprise: a cell identifier (index) of the scheduling cell, and a CIF identifying the scheduled cell (the cell). The cell identifier may employ 5 bits (have a length of 5 bits) and the CIF may employ 3 bits (have a length of 3 bits). The cell identifier may be a number smaller than 32, and the CIF may be a number less than 8. The configuration parameters may indicate that the scheduling cell is employed for cross carrier scheduling of the scheduled cell (e.g. the cell). The wireless device may receive a DCI on a control channel ((e)PDCCH) of the scheduling cell for at least one packet transmitted/received on the scheduled cell. The DCI may comprise the CIF for the scheduled cell. The wireless device may transmit/receive at least one packet on the scheduled cell on radio resources identified by the DCI.

(80) In an example embodiment, the cross carrier scheduling configuration IE of a cell may include one or more of the following parameters: a parameter indicating whether cross carrier scheduling is configured for the cell, the cell identifier (index) of the scheduling cell, the CIF identifying the cell, and/or a starting OFDM symbol number of the physical downlink shared channel of the cell. The CIF field indicates the CIF value used in the scheduling cell to indicate the cell. If the parameter indicates that cross carrier scheduling is not configured for the cell, the UE may decode the (e)PDCCH of the cell to decode DCI for the cell. The cell identifier (index) of the scheduling cell may indicate which cell signals the downlink allocations and uplink grants for the SCell.

(81) In an example embodiment, PUCCH resources of a PUCCH cell in a PUCCH group may comprise resources for uplink control information (UCI) transmission of different sets of cells. PUCCH resources may be divided in time, frequency (Resource Blocks), and/or code and a set of cells may share an assigned PUCCH resources. Different sets may not transmit PUCCH information employing the same resources. In an example embodiment, a grouping mechanism may be introduced for PUCCH resource sets on a PUCCH cell.

(82) In an example embodiment, an eNB may transmit to a UE one or more RRC messages comprising configuration parameters of a plurality of cells. The plurality of cells may be grouped into one or more PUCCH groups. When there is one PUCCH group, it may imply that PUCCH is configured on the PCell, and CSI of activated cells are reported on the PCell. In an example embodiment, a PUCCH group may include one or more cells. A cell may be configured with one or more CSI processes. CSI reports corresponding to CSI process(es) of cell(s) of a PUCCH group is transmitted on a PUCCH cell of the corresponding PUCCH group.

(83) PUCCH resources of a PUCCH cell may be divided in time, frequency (Resource Blocks), and/or code. A set of CSI process(s) of cell(s) of the PUCCH group may share the assigned PUCCH resources and transmit CSI reports in a subframe of a PUCCH resources of the PUCCH cell.

(84) Configuration parameters of a cell may comprise configuration parameters of CSI processes of the cell. Configuration parameters of a CSI process may comprise CSI reference signal radio resource parameters (subcarriers/RBs, symbols, subframe offset and/or periodicity), and/or interference measurement (IM) radio resource parameters (subcarriers/RBs, symbols, subframe offset and/or periodicity). A UE may measure CSI based on CSI resources and/or IM resources of a cell. The CSI may include rank indicator (RI), precoding matrix indicator (PMI), and/or channel quality index (CQI). Example embodiments may be implemented regardless of whether PUCCH

groups are configured or not. In an example embodiment, CSI of activated cells may be transmitted on the PCell and no PUCCH secondary cell and secondary PUCCH group may be configured.

(85) PUCCH resources of a PUCCH cell may be divided into groups of resources in time, resource blocks and/or code. This is a grouping within PUCCH resources of a cell. The CSI processes of cells and/or cells may be semi-statically grouped and CSI may be transmitted for a group of cell(s) on a PUCCH. For example, the configuration parameters may indicate that one or more CSI reports of one or more cells may be reported with a subframe periodicity and offset on PUCCH resources of a PUCCH cell.

(86) In an example embodiment, one or more sets of PUCCH resource block(s) may be configured in parallel for PUCCH on the same PUCCH cell. PUCCH resources of a PUCCH cell may be divided into set of resources in time (different subframes), frequency (different RBs) or code (different CDMA codes). In an example embodiment, a set may be assigned one or more RBs (for example, RBs non-overlapping with RBs of a different set of CSI processes(s) of another one or more cell(s)). In an example embodiment, CSI process(s) of one or more cell(s) may be assigned one or more subframes (for example, subframes non-overlapping with subframes of a different set of CSI processes(s) of one or more cell(s)). In an example embodiment, CSI process(s) of one or more cell(s) may be assigned one or more CDMA codes (for example, codes non-overlapping with codes of a different set of CSI processes(s) of another one or more cell(s)). Cells in a PUCCH group may employ different set of PUCCH resources on a PUCCH cell.

(87) Example FIG. 14 shows example PUCCH resource configuration and CSI transmission in some example embodiments. PUCCH1 resources of a first cell comprises one or more RB(s). CSI-A, CSI-B, CSI-C, and CSI-D reports of one or more cells are transmitted in a first subframe. The UE may select CSI-A, CSI-B, CSI-C, CSI-D reports of one or more cells for transmission in the first subframe (e.g. based on RRC configuration). CSI-E, CSI-F, CSI-G, and CSI-H reports of one or more cells are transmitted in a second subframe. The UE may select CSI-E, CSI-F, CSI-G, and CSI-H reports of one or more cells for transmission in the second subframe (e.g. based on RRC configuration). Multiple CSIs may be transmitted in a subframe.

(88) Example FIG. 14 shows PUCCH2 resources of a second cell comprises multiple sets of one or more RB(s). One or more RRC messages may comprise configuration parameters of PUCCH resources. Configuration parameters may comprise a sequence of one or more RB parameters. The one or more RB parameters in the sequence may indicate a set of one or more resource blocks. For example, one or more RB parameters may include a starting RB number and/or number of RB(s).

(89) In an example embodiment, periodic CSI reporting may be configured for a group of cells and cells within the group may share PUCCH resources. Reporting of CSI for more than one cell in a subframe may be supported. As shown in FIG. 14, more than one CSI may be reported in a subframe of a PUCCH cell. New UCI formats capable of transmitting more bits in a subframe of PUCCH resource may be defined for implementation of an example embodiment. New UCI format may have the capability to transmit a higher number of bits compared with existing UCI transmission formats in release-12.

(90) When a relatively large number of cells are configured, CSI collision may increase. In case of CSI collision among CSI reports of a cell group, prioritization among CSI reports may be based on a report type, cell index and/or CSI process IDs. For example, when a plurality of CSI reports are configured for transmission in a subframe of PUCCH resources of a PUCCH cell, the UE may select a first plurality of CSI report(s) from the plurality of CSI reports for transmission. The selection is performed when there is not enough PUCCH resource capacity to transmit the configured plurality of CSI reports in a subframe. The UE may select one set of PUCCH RB(s) among one or more sets of PUCCH RB(s) for transmission of the selected CSIs. The UE may transmit the selected CSIs on the selected PUCCH RB(s).

(91) In an example implementation, the CSI report type may be the same across cells of a group. If the reporting type of the colliding CSI reports is the same, a cell index of a CSI report may be

employed for prioritization. In an example embodiment, CSI report type, the serving cell index, and/or CSI process ID, and/or other parameters may be employed for prioritization of CSI reports, when there is not enough PUCCH resource capacity to transmit the configured CSI reports in a subframe. In an example, a group that contains a cell with smaller value of cell index and/or group index may have a higher priority. In an example implementation, the CSI reporting type may be the same across cells within a cell group. In an example, the CSI priority may be determined according to a predetermined formula based on CSI report type, the serving cell index, and/or CSI process ID, and/or other parameters.

(92) If a UE is configured to transmit multiple CSI reports in a subframe of PUCCH resources of a PUCCH cell, the UE may transmit one or more available CSI reports in the subframe. If there is one CSI report in the subframe, the CSI report of a given PUCCH reporting type may be transmitted on the PUCCH resource employing UE specific RRC configuration parameter for the serving cell.

(93) If there are more than one CSI reports in the subframe, and if the UE is configured with a single PUCCH resource according to higher layer RRC configuration parameter, the PUCCH resource may be used for transmission of the CSI report(s), as shown in PUCCH1 of FIG. 14. If there are more than one CSI reports in the subframe, and if the UE is configured with two PUCCH resources according to higher layer RRC configuration, the UE may select one of the two PUCCH resources and transmit the CSI reports on the selected PUCCH resources. In an example implementation, if CSI reports can be transmitted on PUCCH resource with smaller number RBs, the PUCCH resource with smaller number RBs may be used for transmission of the CSI report(s), otherwise, the PUCCH resource with larger number of RBs may be used for transmission of the CSI report(s).

(94) If a UE is configured to transmit a number of periodic CSI reports in a subframe and the PUCCH resource does not have enough capacity to transmit the CSI reports, the UE may select one or more CSI reports from the CSI report(s) for transmission according to a priority (e.g. in ascending order of priority). PUCCH resources have a limited capacity to transmit k bits in a subframe. K may depend on the number of RBs configured for PUCCH and/or PUCCH configuration parameters. The CSI priority for a CSI report of a serving cell may be determined for the CSI report according to a predetermine formula employing CSI report type, CSI process ID, serving cell index, and/or CSI subframe set number (C.sub.CSI,0 and C.sub.CSI,1). The UE may select one of the one or more PUCCH Resources (e.g. RBs and/or codes) and transmit the selected CSIs on the selected PUCCH resources. If one set of RBs is configured for PUCCH, then the one set of RBs is selected. If two or more sets of RBs is selected, the UE may select one of the two or more sets of RBs, e.g. based on the required PUCCH capacity and/or RRC configurations. The selected CSI may be transmitted on the selected PUCCH resources.

(95) FIG. 15 is an example flow diagram as per an aspect of an embodiment of the present invention. A wireless device may receive at least one message from a base station at 1510. The message(s) may comprise configuration parameters of a physical uplink control channel (PUCCH) of a cell in a plurality of cells. The configuration parameters may indicate a sequence of radio resources for the PUCCH. Each of the radio resources in the sequence may comprise one or more resource blocks in a plurality of subframes.

(96) According to an embodiment, the plurality of cells may be grouped into a plurality of PUCCH groups. The PUCCH groups may comprise a primary PUCCH group. The primary PUCCH group may comprise a primary cell with a primary PUCCH transmitted to a base station. The PUCCH groups may comprise a secondary PUCCH group. The secondary PUCCH group may comprise a PUCCH secondary cell with a secondary PUCCH transmitted to a base station. According to an embodiment, the PUCCH may comprise at least one of the primary PUCCH or the secondary PUCCH. According to an embodiment, the first plurality of cells may be in at least one of the primary PUCCH group or the secondary PUCCH group.

(97) At **1520**, the wireless device may compute a plurality of channel state information (CSI) reports. The CSI reports may employ first signals received on a first plurality of cells in the plurality of cells. The plurality of CSI reports may be computed for transmission in a first subframe in the plurality of subframes. At **1530**, the wireless device may select a first radio resource from the sequence of radio resources. A first plurality of CSI reports may be selected from the plurality of CSI reports at **1540**. The wireless device may transmit the first plurality of CSI reports at **1550** on the first radio resource and in the first subframe. According to an embodiment, the wireless device may compute a second plurality of channel state information (CSI) reports employing second signals received on a second plurality of cells in the plurality of cells. The second plurality of CSI reports may be computed for transmission in a second subframe in the plurality of subframes.

(98) According to an embodiment, the first plurality of CSI reports may comprise the plurality of CSI reports. According to an embodiment, a CSI report in the first plurality of CSI reports may be selected according to at least a CSI report priority that depends, at least in part, on a report type of the CSI report, and/or on a first cell index of a first cell associated with the CSI report. According to an embodiment, the first plurality of the CSI reports may comprise fewer CSI reports than the plurality of CSI reports when the wireless device does not have sufficient resources to transmit the plurality of CSI reports. According to an embodiment, the first plurality of cells in the plurality of cells may be configured to transmit one or more CSI reports in the first subframe. According to an embodiment, each of the first plurality of cells may be configured with one or more CSI processes.

(99) FIG. **16** is an example flow diagram as per an aspect of an embodiment of the present invention. A wireless device may receive at least one message from a base station at **1610**. The message(s) may comprise configuration parameters of a physical uplink control channel (PUCCH) of a cell in a plurality of cells. The configuration parameters may indicate a sequence of radio resources for the PUCCH. Each of the radio resources in the sequence may comprise one or more resource blocks in a plurality of subframes.

(100) According to an embodiment, the plurality of cells may be grouped into a plurality of PUCCH groups. The plurality of PUCCH groups may comprise a primary PUCCH group. The primary PUCCH group may comprise a primary cell with a primary PUCCH transmitted to a base station. The plurality of PUCCH groups may comprise a secondary PUCCH group. The secondary PUCCH group may comprise a PUCCH secondary cell with a secondary PUCCH transmitted to the base station. According to an embodiment, the PUCCH may comprise at least one of the primary PUCCH or the secondary PUCCH. According to an embodiment, the first plurality of cells maybe in at least one of the primary PUCCH group or the secondary PUCCH group.

(101) The wireless device may compute a plurality of channel state information (CSI) reports employing first signals received on a first plurality of cells in the plurality of cells. At **1620**. The plurality of CSI reports may be computed for transmission in a first subframe in the plurality of subframes. At **1630**, the wireless device may select one or more radio resources from the sequence of radio resources. At **1640**, the wireless device may select a first plurality of CSI reports from the plurality of CSI reports. At **1650**, the wireless device may transmit the first plurality of CSI reports on the one or more radio resources and in the first subframe. According to an embodiment, the wireless device may compute a second plurality of channel state information (CSI) reports employing second signals received on a second plurality of cells in the plurality of cells. The second plurality of CSI reports may be computed for transmission in a second subframe in the plurality of subframes.

(102) According to an embodiment, the first plurality of CSI reports may comprise the plurality of CSI reports. According to an embodiment, a CSI report in the first plurality of CSI reports may be selected according to at least a CSI report priority that may depends, at least in part, on: a report type of the CSI report, and/or a first cell index of a first cell associated with the CSI report. According to an embodiment, the first plurality of the CSI reports may comprise fewer CSI reports than the plurality of CSI reports when the wireless device does not have sufficient resources to

transmit the plurality of CSI reports. According to an embodiment, the first plurality of cells in the plurality of cells may be configured to transmit one or more CSI reports in the first subframe. According to an embodiment, each of the first plurality of cells may be configured with one or more CSI processes.

(103) In this specification, “a” and “an” and similar phrases are to be interpreted as “at least one” and “one or more.” In this specification, the term “may” is to be interpreted as “may, for example.” In other words, the term “may” is indicative that the phrase following the term “may” is an example of one of a multitude of suitable possibilities that may, or may not, be employed to one or more of the various embodiments. If A and B are sets and every element of A is also an element of B, A is called a subset of B. In this specification, only non-empty sets and subsets are considered. For example, possible subsets of $B=\{\text{cell1}, \text{cell2}\}$ are: $\{\text{cell1}\}$, $\{\text{cell2}\}$, and $\{\text{cell1}, \text{cell2}\}$.

(104) In this specification, parameters (Information elements: IEs) may comprise one or more objects, and each of those objects may comprise one or more other objects. For example, if parameter (IE) N comprises parameter (IE) M, and parameter (IE) M comprises parameter (IE) K, and parameter (IE) K comprises parameter (information element) J, then, for example, N comprises K, and N comprises J. In an example embodiment, when one or more messages comprise a plurality of parameters, it implies that a parameter in the plurality of parameters is in at least one of the one or more messages, but does not have to be in each of the one or more messages.

(105) Many of the elements described in the disclosed embodiments may be implemented as modules. A module is defined here as an isolatable element that performs a defined function and has a defined interface to other elements. The modules described in this disclosure may be implemented in hardware, software in combination with hardware, firmware, wetware (i.e. hardware with a biological element) or a combination thereof, all of which are behaviorally equivalent. For example, modules may be implemented as a software routine written in a computer language configured to be executed by a hardware machine (such as C, C++, Fortran, Java, Basic, Matlab or the like) or a modeling/simulation program such as Simulink, Stateflow, GNU Octave, or LabVIEWMathScript. Additionally, it may be possible to implement modules using physical hardware that incorporates discrete or programmable analog, digital and/or quantum hardware. Examples of programmable hardware comprise: computers, microcontrollers, microprocessors, application-specific integrated circuits (ASICs); field programmable gate arrays (FPGAs); and complex programmable logic devices (CPLDs). Computers, microcontrollers and microprocessors are programmed using languages such as assembly, C, C++ or the like. FPGAs, ASICs and CPLDs are often programmed using hardware description languages (HDL) such as VHSIC hardware description language (VHDL) or Verilog that configure connections between internal hardware modules with lesser functionality on a programmable device. Finally, it needs to be emphasized that the above mentioned technologies are often used in combination to achieve the result of a functional module.

(106) The disclosure of this patent document incorporates material which is subject to copyright protection. The copyright owner has no objection to the facsimile reproduction by anyone of the patent document or the patent disclosure, as it appears in the Patent and Trademark Office patent file or records, for the limited purposes required by law, but otherwise reserves all copyright rights whatsoever.

(107) While various embodiments have been described above, it should be understood that they have been presented by way of example, and not limitation. It will be apparent to persons skilled in the relevant art(s) that various changes in form and detail can be made therein without departing from the spirit and scope. In fact, after reading the above description, it will be apparent to one skilled in the relevant art(s) how to implement alternative embodiments. Thus, the present embodiments should not be limited by any of the above described exemplary embodiments. In particular, it should be noted that, for example purposes, the above explanation has focused on the example(s) using FDD communication systems. However, one skilled in the art will recognize that

embodiments of the invention may also be implemented in a system comprising one or more TDD cells (e.g. frame structure 2 and/or frame structure 3-licensed assisted access). The disclosed methods and systems may be implemented in wireless or wireline systems. The features of various embodiments presented in this invention may be combined. One or many features (method or system) of one embodiment may be implemented in other embodiments. Only a limited number of example combinations are shown to indicate to one skilled in the art the possibility of features that may be combined in various embodiments to create enhanced transmission and reception systems and methods.

(108) In addition, it should be understood that any figures which highlight the functionality and advantages, are presented for example purposes only. The disclosed architecture is sufficiently flexible and configurable, such that it may be utilized in ways other than that shown. For example, the actions listed in any flowchart may be re-ordered or only optionally used in some embodiments.

(109) Further, the purpose of the Abstract of the Disclosure is to enable the U.S. Patent and Trademark Office and the public generally, and especially the scientists, engineers and practitioners in the art who are not familiar with patent or legal terms or phraseology, to determine quickly from a cursory inspection the nature and essence of the technical disclosure of the application. The Abstract of the Disclosure is not intended to be limiting as to the scope in any way.

(110) Finally, it is the applicant's intent that only claims that include the express language “means for” or “step for” be interpreted under 35 U.S.C. 112, paragraph 6. Claims that do not expressly include the phrase “means for” or “step for” are not to be interpreted under 35 U.S.C. 112.

Claims

1. A method comprising: receiving, by a wireless device and from a base station, configuration of a physical uplink control channel (PUCCH) for the wireless device, wherein the PUCCH comprises a first set of PUCCH resource blocks in a time interval and a second set of PUCCH resource blocks overlapping in time in the time interval with the first set of PUCCH resource blocks; selecting, by the wireless device, the second set of PUCCH resource blocks for transmitting one or more channel state information (CSI) reports, wherein the selecting is based on: a comparison involving a size of the one or more CSI reports and a size of the first set of PUCCH resource blocks; and giving preference to the first set of PUCCH resource blocks based on the first set of PUCCH resource blocks comprising a smaller size than the second set of PUCCH resource blocks; and transmitting the one or more CSI reports via the selected second set of PUCCH resource blocks.

2. The method of claim 1, further comprising selecting, by the wireless device and based on the first set of PUCCH resource blocks having a smaller size than the second set of PUCCH resource blocks, the first set of PUCCH resource blocks for transmission of at least one other CSI report.

3. The method of claim 1, further comprising selecting the one or more CSI reports according to at least a CSI report priority that is based, at least in part, on a CSI process identification (ID).

4. The method of claim 1, further comprising determining a plurality of CSI reports, for transmission via the time interval, based on signals received via a plurality of cells that are configured for the wireless device to transmit CSI reports.

5. The method of claim 1, further comprising selecting the one or more CSI reports according to at least a CSI report priority that is based, at least in part, on a CSI subframe set number.

6. The method of claim 1, further comprising determining a plurality of CSI reports, for transmission via the time interval, based on signals received via a plurality of cells that are grouped into a plurality of PUCCH groups comprising: a primary PUCCH group comprising a primary cell with a primary PUCCH transmitted to the base station; and a secondary PUCCH group comprising a secondary cell with a secondary PUCCH transmitted to the base station.

7. The method of claim 1, wherein the PUCCH is at least one of: a primary PUCCH, of a primary cell of a primary PUCCH group, transmitted to the base station; or a secondary PUCCH, of a

secondary cell of a secondary PUCCH group, transmitted to the base station.

8. The method of claim 1, further comprising determining a plurality of CSI reports, for transmission via the time interval, based on signals received via a plurality of cells that are in at least one of: a primary PUCCH group comprising a primary cell with a primary PUCCH transmitted to the base station; or a secondary PUCCH group comprising a secondary cell with a secondary PUCCH transmitted to the base station.

9. The method of claim 1, further comprising determining, by the wireless device and based on signals received via a plurality of cells, a plurality of CSI reports for transmission via a second time interval.

10. The method of claim 1, further comprising transmitting at least one other CSI report via the first set of PUCCH resource blocks.

11. The method of claim 1, wherein the one or more CSI reports comprises a plurality of CSI reports, wherein the selecting is based on a size of the plurality of CSI reports, and wherein the transmitting comprises transmitting the plurality of CSI reports.

12. A wireless device comprising: one or more processors; and memory storing instructions that, when executed by the one or more processors, configure the wireless device to: receive, from a base station, configuration of a physical uplink control channel (PUCCH) for the wireless device, wherein the PUCCH comprises a first set of PUCCH resource blocks in a time interval and a second set of PUCCH resource blocks overlapping in time in the time interval with the first set of PUCCH resource blocks; select the second set of PUCCH resource blocks for transmitting one or more channel state information (CSI) reports, wherein the selecting is based on: a comparison involving a size of the one or more CSI reports and a size of the first set of PUCCH resource blocks; and giving preference to the first set of PUCCH resource blocks based on the first set of PUCCH resource blocks comprising a smaller size than the second set of PUCCH resource blocks; and transmit the one or more CSI reports via the selected second set of PUCCH resource blocks.

13. The wireless device of claim 12, wherein the instructions, when executed by the one or more processors, further configure the wireless device to select, based on the first set of PUCCH resource blocks having a smaller size than the second set of PUCCH resource blocks, the first set of PUCCH resource blocks for transmission of at least one other CSI report.

14. The wireless device of claim 12, wherein the instructions, when executed by the one or more processors, further configure the wireless device to select the one or more CSI reports according to at least a CSI report priority that is based, at least in part, on a CSI process identification (ID).

15. The wireless device of claim 12, wherein the instructions, when executed by the one or more processors, further configure the wireless device to determine a plurality of CSI reports, for transmission via the time interval, based on signals received via a plurality of cells that are configured for the wireless device to transmit CSI reports.

16. The wireless device of claim 12, wherein the instructions, when executed by the one or more processors, further configure the wireless device to select the one or more CSI reports according to at least a CSI report priority that is based, at least in part, on a CSI subframe set number.

17. The wireless device of claim 12, wherein the instructions, when executed by the one or more processors, further configure the wireless device to determine a plurality of CSI reports, for transmission via the time interval, based on signals received via a plurality of cells that are grouped into a plurality of PUCCH groups comprising: a primary PUCCH group comprising a primary cell with a primary PUCCH transmitted to the base station; and a secondary PUCCH group comprising a secondary cell with a secondary PUCCH transmitted to the base station.

18. The wireless device of claim 12, wherein the PUCCH is at least one of: a primary PUCCH, of a primary cell of a primary PUCCH group, transmitted to the base station; or a secondary PUCCH, of a secondary cell of a secondary PUCCH group, transmitted to the base station.

19. The wireless device of claim 12, wherein the instructions, when executed by the one or more processors, further configure the wireless device to determine a plurality of CSI reports, for

transmission via the time interval, based on signals received via a plurality of cells that are in at least one of: a primary PUCCH group comprising a primary cell with a primary PUCCH transmitted to the base station; or a secondary PUCCH group comprising a secondary cell with a secondary PUCCH transmitted to the base station.

20. The wireless device of claim 12, wherein the instructions, when executed by the one or more processors, further configure the wireless device to determine, based on signals received via a plurality of cells, a plurality of CSI reports for transmission via a second time interval.

21. The wireless device of claim 12, wherein the instructions, when executed by the one or more processors, further configure the wireless device to transmit at least one other CSI report via the first set of PUCCH resource blocks.

22. The wireless device of claim 12, wherein the one or more CSI reports comprises a plurality of CSI reports, wherein the selecting is based on a size of the plurality of CSI reports, and wherein the transmitting comprises transmitting the plurality of CSI reports.

23. A system comprising: a wireless device configured to: receive, from a base station, configuration of a physical uplink control channel (PUCCH) for the wireless device, wherein the PUCCH comprises a first set of PUCCH resource blocks in a time interval and a second set of PUCCH resource blocks overlapping in time in the time interval with the first set of PUCCH resource blocks; select the second set of PUCCH resource blocks for transmitting one or more channel state information (CSI) reports, wherein the selecting is based on: a comparison involving a size of the one or more CSI reports and a size of the first set of PUCCH resource blocks; and giving preference to the first set of PUCCH resource blocks based on the first set of PUCCH resource blocks comprising a smaller size than the second set of PUCCH resource blocks; and transmit the one or more CSI reports via the selected second set of PUCCH resource blocks; and a base station configured to transmit the PUCCH configuration of the wireless device.

24. The system of claim 23, wherein the wireless device is configured to select, based on the first set of PUCCH resource blocks having a smaller size than the second set of PUCCH resource blocks, the first set of PUCCH resource blocks for transmission of at least one other CSI report.

25. The system of claim 23, wherein the wireless device is configured to select the one or more CSI reports according to at least a CSI report priority that is based, at least in part, on a CSI process identification (ID).

26. The system of claim 23, wherein the wireless device is configured to determine a plurality of CSI reports, for transmission via the time interval, based on signals received via a plurality of cells that are configured for the wireless device to transmit CSI reports.

27. The system of claim 23, wherein the wireless device is configured to select the one or more CSI reports according to at least a CSI report priority that is based, at least in part, on a CSI subframe set number.

28. The system of claim 23, wherein the wireless device is configured to determine a plurality of CSI reports, for transmission via the time interval, based on signals received via a plurality of cells that are grouped into a plurality of PUCCH groups comprising: a primary PUCCH group comprising a primary cell with a primary PUCCH transmitted to the base station; and a secondary PUCCH group comprising a secondary cell with a secondary PUCCH transmitted to the base station.

29. The system of claim 23, wherein the PUCCH is at least one of: a primary PUCCH, of a primary cell of a primary PUCCH group, transmitted to the base station; or a secondary PUCCH, of a secondary cell of a secondary PUCCH group, transmitted to the base station.

30. The system of claim 23, wherein the wireless device is configured to determine a plurality of CSI reports, for transmission via the time interval, based on signals received via a plurality of cells that are in at least one of: a primary PUCCH group comprising a primary cell with a primary PUCCH transmitted to the base station; or a secondary PUCCH group comprising a secondary cell with a secondary PUCCH transmitted to the base station.

31. The system of claim 23, wherein the wireless device is configured to determine, based on signals received via a plurality of cells, a plurality of CSI reports for transmission via a second time interval.
32. The system of claim 23, wherein the wireless device is configured to transmit at least one other CSI report via the first set of PUCCH resource blocks.
33. The system of claim 23, wherein the one or more CSI reports comprises a plurality of CSI reports, wherein the selecting is based on a size of the plurality of CSI reports, and wherein the transmitting comprises transmitting the plurality of CSI reports.
34. One or more non-transitory, computer-readable media storing instructions that, when executed, configure a wireless device to: receive, from a base station, configuration of a physical uplink control channel (PUCCH) for the wireless device, wherein the PUCCH comprises a first set of PUCCH resource blocks in a time interval and a second set of PUCCH resource blocks overlapping in time in the time interval with the first set of PUCCH resource blocks; select the second set of PUCCH resource blocks for transmitting one or more channel state information (CSI) reports, wherein the selecting is based on: a comparison involving a size of the one or more CSI reports and a size of the first set of PUCCH resource blocks; and giving preference to the first set of PUCCH resource blocks based on the first set of PUCCH resource blocks comprising a smaller size than the second set of PUCCH resource blocks; and transmit the one or more CSI reports via the selected second set of PUCCH resource blocks.
35. The one or more non-transitory, computer-readable media of claim 34, wherein the instructions, when executed, further configure the wireless device to select, based on the first set of PUCCH resource blocks having a smaller size than the second set of PUCCH resource blocks, the first set of PUCCH resource blocks for transmission of at least one other CSI report.
36. The one or more non-transitory, computer-readable media of claim 34, wherein the instructions, when executed, further configure the wireless device to select the one or more CSI reports according to at least a CSI report priority that is based, at least in part, on a CSI process identification (ID).
37. The one or more non-transitory, computer-readable media of claim 34, wherein the instructions, when executed, further configure the wireless device to determine a plurality of CSI reports, for transmission via the time interval, based on signals received via a plurality of cells that are configured for the wireless device to transmit CSI reports.
38. The one or more non-transitory, computer-readable media of claim 34, wherein the instructions, when executed, further configure the wireless device to select the one or more CSI reports according to at least a CSI report priority that is based, at least in part, on a CSI subframe set number.
39. The one or more non-transitory, computer-readable media of claim 34, wherein the instructions, when executed, further configure the wireless device to determine a plurality of CSI reports, for transmission via the time interval, based on signals received via a plurality of cells that are grouped into a plurality of PUCCH groups comprising: a primary PUCCH group comprising a primary cell with a primary PUCCH transmitted to the base station; and a secondary PUCCH group comprising a secondary cell with a secondary PUCCH transmitted to the base station.
40. The one or more non-transitory, computer-readable media of claim 34, wherein the PUCCH is at least one of: a primary PUCCH, of a primary cell of a primary PUCCH group, transmitted to the base station; or a secondary PUCCH, of a secondary cell of a secondary PUCCH group, transmitted to the base station.
41. The one or more non-transitory, computer-readable media of claim 34, wherein the instructions, when executed, further configure the wireless device to determine a plurality of CSI reports, for transmission via the time interval, based on signals received via a plurality of cells that are in at least one of: a primary PUCCH group comprising a primary cell with a primary PUCCH transmitted to the base station; or a secondary PUCCH group comprising a secondary cell with a

secondary PUCCH transmitted to the base station.

42. The one or more non-transitory, computer-readable media of claim 34, wherein the instructions, when executed, further configure the wireless device to determine, based on signals received via a plurality of cells, a plurality of CSI reports for transmission via a second time interval.

43. The one or more non-transitory, computer-readable media of claim 34, wherein the instructions, when executed, further configure the wireless device to transmit at least one other CSI report via the first set of PUCCH resource blocks.

44. The one or more non-transitory, computer-readable media of claim 34, wherein the one or more CSI reports comprises a plurality of CSI reports, wherein the selecting is based on a size of the plurality of CSI reports, and wherein the transmitting comprises transmitting the plurality of CSI reports.
