

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413802
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Kubo; Shota et al.

Reproduction device, reproduction device control method, and recording medium

Abstract

A reproduction device includes: an HDMI transmitter that detects a power state of a display device; a first communication module that establishes communication with a terminal device that is externally located, when the HDMI transmitter does not detect that the display device is in a power-on state; and a controller that performs first settings with the terminal device, when the communication is established between the terminal device and the first communication module, the first settings being settings relating to the reproduction device.

Inventors:	Kubo; Shota (Osaka, JP), Fukuda; Hideki (Nara, JP), Takao; Naoya (Hyogo, JP), Iwasaki; Shiro (Osaka, JP), Kubo; Norimichi (Osaka, JP)
Applicant:	Panasonic Intellectual Property Management Co., Ltd. (Osaka, JP)
Family ID:	80845314
Assignee:	PANASONIC INTELLECTUAL PROPERTY MANAGEMENT CO., LTD. (Osaka, JP)
Appl. No.:	18/026745
Filed (or PCT Filed):	September 14, 2021
PCT No.:	PCT/JP2021/033650
PCT Pub. No.:	WO2022/065124
PCT Pub. Date:	March 31, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230345071 A1	Oct. 26, 2023

Foreign Application Priority Data

JP 2020-161479 Sep. 25, 2020

Publication Classification

Int. Cl.: H04N21/41 (20110101); H04N21/436 (20110101)

U.S. Cl.:

CPC H04N21/41265 (20200801); H04N21/43615 (20130101);

Field of Classification Search

CPC: H04N (21/43615); H04N (21/41265)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9510201	12/2015	Shimoon	N/A	H04W 12/06
9736541	12/2016	Nijim	N/A	H04N 21/41265
10448080	12/2018	Nijim	N/A	H04N 21/6131
2004/0117390	12/2003	Karaoguz	348/E7.071	H04N 21/6582
2005/0073518	12/2004	Bontempi	348/E5.127	H04N 5/63
2005/0144640	12/2004	Fritsch	348/E7.071	H04N 21/47214
2008/0098450	12/2007	Wu	725/132	H04N 21/4622
2008/0109734	12/2007	Castagno	715/740	H04N 21/8166
2009/0002568	12/2008	Konda	348/E5.057	H04N 5/765
2009/0135309	12/2008	DeGeorge	348/732	H04N 21/4345
2009/0165060	12/2008	Lawrence	725/81	H04N 21/42224
2009/0165075	12/2008	Rhodes	725/153	H04N 21/6143
2010/0070994	12/2009	Yun	340/687	H04N 21/6543
2010/0125890	12/2009	Levine	725/151	H04N 21/2393
2010/0265413	12/2009	Seo	370/313	H04N 21/42204
2011/0156879	12/2010	Matsushita	340/10.1	H04L 63/08
2011/0273625	12/2010	McMahon	348/734	H04N 21/4227
2011/0273627	12/2010	Tsuji	348/739	H04N 21/47
2013/0005250	12/2012	Kim	455/41.1	G08C 23/04
2013/0117442	12/2012	Mountain	709/224	H04N 21/454
2013/0176500	12/2012	Nagata	348/723	H04N 21/8586
2013/0279471	12/2012	Kito	370/331	H04W 36/08
2014/0079374	12/2013	Gehring	725/38	H04N 21/8586
2014/0173584	12/2013	Gayard	717/173	H04L 63/062
2014/0310742	12/2013	Kim	725/110	H04N 21/485

2015/0074047	12/2014	Gardes	707/610	G06F 16/178
2015/0078362	12/2014	Kunieda	370/338	H04W 76/20
2015/0350773	12/2014	Yang	381/77	H04N 21/439
2015/0358760	12/2014	Kehm	455/41.3	H04W 8/005
2016/0044385	12/2015	Kareeson	725/27	H04N 21/658
2016/0080806	12/2015	Ozeki	725/14	H04H 60/32
2017/0255431	12/2016	Yu	N/A	H04N 21/4312
2017/0289638	12/2016	Mok	N/A	N/A
2018/0067711	12/2017	Koga	N/A	G06F 3/1229
2018/0206122	12/2017	Bradley	N/A	G06F 21/604
2018/0324684	12/2017	Onohara et al.	N/A	N/A
2019/0149871	12/2018	Yoshizawa	348/734	H04N 21/436
2019/0373320	12/2018	Balsamo	N/A	G06F 3/0485
2019/0394524	12/2018	Latini	N/A	H04N 21/4424
2020/0128289	12/2019	Machida	N/A	H04N 21/42225
2021/0219023	12/2020	Sheng	N/A	A61B 5/6801
2022/0303612	12/2021	Reddy	N/A	G10L 19/167
2023/0345071	12/2022	Kubo	N/A	H04N 21/41407

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
3016438	12/2018	EP	H04W 4/80
2013-247539	12/2012	JP	N/A
2014-171192	12/2013	JP	N/A

OTHER PUBLICATIONS

International Search Report issued on Nov. 30, 2021 in International Patent Application No. PCT/JP2021/033650, with English translation. cited by applicant

Extended European Search Report dated Mar. 7, 2024 issued in the corresponding European Patent Application No. 21872254.4. cited by applicant

Primary Examiner: Sheleheda; James R

Attorney, Agent or Firm: Rimón P.C.

Background/Summary

CROSS-REFERENCE OF RELATED APPLICATIONS

(1) This application is the U.S. National Phase under 35 U.S.C. § 371 of International Patent Application No. PCT/JP2021/033650, filed on Sep. 14, 2021, which in turn claims the benefit of Japanese Patent Application No. 2020-161479, filed on Sep. 25, 2020, the entire disclosures of which Applications are incorporated by reference herein.

TECHNICAL FIELD

(2) The present disclosure relates to a reproduction device, a reproduction device control method, and a recording medium.

Background Art

(3) There is known a reproduction device that outputs a video signal onto a display device (see, for

example, Patent Literature (PTL) 1). When a reproduction device of this kind is powered on for the first time after the purchase, initial settings for the reproduction device need to be performed. To perform the initial settings, an initial settings screen outputted from the reproduction device is displayed on a display device, with the reproduction device and the display device interconnected via a cable. The user operates a remote control of the reproduction device to perform the initial settings for the reproduction device on the initial settings screen displayed on the display device.

CITATION LIST

Patent Literature

(4) [PTL 1] Japanese Unexamined Patent Application Publication No. 2014-171192

SUMMARY OF INVENTION

Technical Problem

(5) The present disclosure provides a reproduction device, a reproduction device control method, and a recording medium that enable predetermined settings to be performed without using a display device.

Solution to Problem

(6) The reproduction device in the present disclosure is a reproduction device that is connectable to a display device and outputs a video signal to the display device. The reproduction device includes: a detector that detects a power state of the display device; a first communicator that establishes communication with a terminal device that is externally located, when the detector does not detect that the display device is in a power-on state; and a controller that performs first settings with the terminal device, when the communication is established between the terminal device and the first communicator, the first settings being settings relating to the reproduction device.

Advantageous Effects of Invention

(7) The reproduction device and so forth in the present disclosure enable predetermined settings to be performed without using a display device.

Description

BRIEF DESCRIPTION OF DRAWINGS

- (1) FIG. 1 is a conceptual diagram showing a system according to an embodiment.
- (2) FIG. 2 is a block diagram showing the functional configuration of the system according to the embodiment.
- (3) FIG. 3 is a flowchart showing the flow of initial settings for a reproduction device according to the embodiment.
- (4) FIG. 4 is a diagram showing an example screen displayed on a display device according to the embodiment.
- (5) FIG. 5 is a sequence diagram showing the flow of network settings performed between the reproduction device and a terminal device according to the embodiment.
- (6) FIG. 6 is a diagram showing an example screen displayed on terminal device according to the embodiment.
- (7) FIG. 7 is a diagram showing an example personal identification number code displayed on the reproduction device according to the embodiment.
- (8) FIG. 8 is a diagram showing an example screen displayed on the terminal device according to the embodiment.
- (9) FIG. 9 is a diagram showing an example screen displayed on the terminal device according to the embodiment.
- (10) FIG. 10 is a diagram showing an example screen displayed on the terminal device according to the embodiment.
- (11) FIG. 11 is a sequence diagram showing the flow of tuner reception settings performed between

the reproduction device and the terminal device according to the embodiment.

(12) FIG. 12 is a diagram showing an example screen displayed on the terminal device according to the embodiment.

(13) FIG. 13 is a diagram showing an example screen displayed on the terminal device according to the embodiment.

(14) FIG. 14 is a sequence diagram showing the flow of network settings to be performed between the reproduction device and the terminal device according to a variation of the embodiment.

DESCRIPTION OF EMBODIMENT

(15) The following describes in detail the embodiment with reference to the drawings where appropriate. Note, however, that detailed description more than necessary may be omitted. For example, detailed description of a well-known matter or repetitive description of substantially the same configuration may be omitted. This is to prevent the following description from becoming unnecessarily redundant and to facilitate the understanding of those skilled in the art.

(16) Also note that the inventors provide the accompanying drawings and the following description for those skilled in the art to fully understand the present disclosure, and thus that these do not intend to limit the subject recited in the claims.

Embodiment

(17) With reference FIG. 1 thorough FIG. 14, an embodiment will be described.

(18) [1-1. System Overview]

(19) With reference to FIG. 1, the following describes an overview of system 2 according to the embodiment. FIG. 1 is a conceptual diagram showing system 2 according to the embodiment.

(20) As shown in FIG. 1, system 2 according to the embodiment includes reproduction device 4, display device 6, and terminal device 8.

(21) Reproduction device 4 is, for example, a Blu-ray Disc (BD)/hard disc drive (HDD) recorder that reproduces video content recorded in an optical disc, such as a BD and a digital versatile disc (DVD), or an HDD, and records a broadcast program. Front panel display 10 for displaying various information is disposed at the front of reproduction device 4.

(22) Display device 6 is, for example, a liquid crystal television receiver for viewing broadcast programs. Display device 6 is connected to reproduction device 4 via cable 12. Display device 6 includes display 14 for displaying, for example, video content reproduced by reproduction device 4. Note that cable 12 is a high-definition multimedia interface (HDMI)® cable.

(23) Terminal device 8 is, for example, a mobile terminal such as a smartphone and a tablet terminal. Terminal device 8 is capable of wirelessly communicating with reproduction device 4. An application for performing initial settings for reproduction device 4 is installed in terminal device 8. As is described later, the user is able to perform the initial settings for reproduction device 4, using terminal device 8, even when display device 6 connected to reproduction device 4 is in the power-off state. Note that the initial settings are various settings (including network settings and tuner reception settings to be described later) that are performed at the first power on of reproduction device 4 after the purchase of reproduction device 4.

(24) [1-2. Functional Configuration of System]

(25) With reference to FIG. 2, the following describes the functional configuration of system 2 according to the embodiment. FIG. 2 is a block diagram showing the functional configuration of system 2 according to the embodiment.

(26) As shown in FIG. 2, the functional configuration of reproduction device 4 includes tuner 16, recording processing circuit 18, reproduction processing circuit 20, graphic module 22, video signal processing circuit 24, front panel display 10, remote control signal receiver 26 (an example of a receiver), first communication module 28 (an example of the first communicator), second communication module 30 (an example of a second communicator), wired local area network interface (LAN I/F) 32, universal serial bus interface (USB I/F) 34, controller 36 (an example of the controller), and HDMI transmitter 38 (an example of the detector).

(27) Antenna **40** is disposed outside of reproduction device **4**. Antenna **40** is connected to tuner **16**, and receives broadcast waves (digital broadcast signal) transmitted from a broadcast station. Note that the broadcast waves include, for example, radio waves for broadcasting digital terrestrial broadcasts, digital broadcasting satellites (BS) broadcast, and digital communication satellites (CS) broadcasts.

(28) Tuner **16** receives a broadcast program (digital broadcast program) included in the broadcast waves from antenna **40**.

(29) Recording processing circuit **18** performs processing for recording, onto recording medium **42**, the broadcast program received by tuner **16**. Note that recording medium **42** is, for example, an optical disc inserted inside of reproduction device **4**, such as a BD and a DVD, or an HDD included in reproduction device **4**.

(30) Reproduction processing circuit **20** performs processing for reproducing video content, such as a broadcast program, recorded in recording medium **42**.

(31) Graphic module **22** generates various screens to be displayed on display device **6**.

(32) Video signal processing circuit **24** generates a video signal and an audio signal representing the video content reproduced by reproduction processing circuit **20**, and outputs the generated video signal and audio signal to HDMI transmitter **38**. Video signal processing circuit **24** also generates video signals representing various screens generated by graphic module **22**, and outputs the generated video signals to HDMI transmitter **38**.

(33) Front panel display **10** is a liquid crystal display for displaying various information.

(34) Remote control signal receiver **26** receives an instruction inputted by the user using a remote control (not illustrated) of reproduction device **4**. Remote control signal receiver **26** receives a remote control signal from the remote control, and outputs the received remote control signal to controller **36**.

(35) First communication module **28** is a communication module for communicating with terminal device **8** by, for example, near-field communication such as Bluetooth® low energy (BLE).

(36) Second communication module **30** is a communication module for wirelessly communicating with wireless network **44** (an example of a network). Wireless network **44** is, for example, a wireless LAN compliant with IEEE802.11 series of standards, and is 2.4 GHz or 5 GHz WiFi®. Wireless network **44** includes wireless access point (AP) **46** connected to the Internet line. Suppose here that the service set identifier (SSID) of wireless access point **46** is, for example, “abcd012”, and the passcode is “xxxxyyyy”. Also suppose that wireless communication is established between terminal device **8** and wireless access point **46**, and that terminal device **8** is connected to wireless network **44**.

(37) Wired LAN I/F **32** is a communication interface via which reproduction device **4** and wireless access point **46** are interconnected by wire. Wired LAN I/F **32** is connected to wireless access point **46** via a wired network that includes, for example, a wireless LAN which uses an Ethernet® cable.

(38) USB I/F **34** is a communication interface via which reproduction device **4** and a USB device (not illustrated) are interconnected.

(39) Controller **36** controls the operation of reproduction device **4**, on the basis of the remote control signal from remote control signal receiver **26** and a control signal from HDMI transmitter **38** (to be described later). More specifically, controller **36** performs, for example, various processes for the initial settings for reproduction device **4**. Controller **36** also controls displaying of various information on front panel display **10**. Controller **36** also provides graphic module **22** with an instruction for generating various screens to be displayed on display device **6**. Controller **36** also controls first communication module **28** and second communication module **30**. Controller **36** also transmits and receives various data via wired LAN I/F **32** and USB I/F **34**.

(40) HDMI transmitter **38** is connected to HDMI receiver **50** of display device **6** via cable **12** (see FIG. 1). HDMI transmitter **38** transmits, to HDMI receiver **50** of display device **6**, the video signal and the audio signal through transition-minimized differential signaling (TMDS) channels via cable

12. HDMI transmitter **38** transmits and receives a control signal (consumer electronics control (CEC) command) through the CEC channel via cable **12**.

(41) Note that the HDMI standards specify CEC for linking a plurality of HDMI devices with one another. CEC commands are bilaterally communicated between a plurality of HDMI devices in accordance with CEC. This communication is referred to as CEC communication. Through this CEC communication, HDMI transmitter **38** is able to detect, for example, the power state (power-on state or power-off state) of display device **6** connected to reproduction device **4**.

(42) Also, as shown in FIG. 2, display device **6** includes display **14**, controller **48**, and HDMI receiver **50**.

(43) Display **14** is a liquid crystal display panel for displaying, for example, various screens.

(44) Controller **48** controls the operation of display device **6**, on the basis of the control signal from HDMI receiver **50**. Controller **48** also controls, for example, displaying of various screens on display **14**.

(45) HDMI receiver **50** receives the video signal and the audio signal from HDMI transmitter **38** of reproduction device **4** through the TMDS channels via cable **12**. HDMI receiver **50** also transmits and receives the control signal to and from HDMI transmitter **38** of reproduction device **4** through the CEC channel via cable **12**.

(46) [1-3. Flow of Initial Settings for Reproduction Device]

(47) With reference to FIG. 3 and FIG. 4, the following describes the flow of the initial settings for reproduction device **4** according to the embodiment. FIG. 3 is a flowchart showing the flow of the initial settings for reproduction device **4** according to the embodiment. FIG. 4 is a diagram showing an example screen displayed on display device **6** according to the embodiment.

(48) The following describes the case where the user connects reproduction device **4** and display device **6** via cable **12**, and powers on reproduction device **4** for the first time after purchasing reproduction device **4**.

(49) As shown in FIG. 3, the user powers on reproduction device **4** (S101), in response to which reproduction device **4** outputs a grey out screen onto display device **6** (S102). This grey out screen is generated by graphic module **22**, and outputted onto display device **6** by HDMI transmitter **38**.

(50) HDMI transmitter **38** detects the power state of display device **6**, on the basis of the control signal from display device **6** (S103). When the power state of display device **6** is the power-off state (i.e., when HDMI transmitter **38** does not detect that display device **6** is in the power-on state) ("Power-off state" in S103), first communication module **28** transmits a beacon signal using BLE (S104). Stated differently, BLE advertising starts, and first communication module **28** enters a state of waiting for a connection request from terminal device **8** (S105).

(51) The beacon signal from first communication module **28** is received by terminal device **8** that is present near reproduction device **4**. The following describes the case where terminal device **8** that has received the beacon signal performs an operation for transmitting a connection request to reproduction device **4**. Through this, terminal device **8** that has received the beacon signal transmits a connection request to reproduction device **4**.

(52) When first communication module **28** receives the connection request from terminal device **8** that has received the beacon signal (YES in S105), first communication module **28** stops the transmission of the beacon signal (S106), and starts near-field communication using BLE with terminal device **8** that has received the beacon signal (S107). Stated differently, near-field communication is established between first communication module **28** and terminal device **8**.

(53) After that, controller **36** performs, with terminal device **8**, network settings (an example of the first settings that are settings relating to reproduction device **4**) that are the settings for connecting reproduction device **4** to wireless network **44** by second communication module **30** (S108).

Through this, second communication module **30** establishes wireless communication with wireless access point **46**, and reproduction device **4** is connected to wireless network **44**.

(54) After that, controller **36** performs, with terminal device **8**, tuner reception settings (an example

of second settings) that are settings relating to the settings for tuner **16** (S109). After the completion of the tuner reception settings, reproduction device **4** is powered off (S110).

(55) Returning to step S105 described above, the following describes the case where the user performs an operation for aborting the transmission of the connection request to reproduction device **4**, using terminal device **8** that has received the beacon signal (NO in S105, YES in S111). In this case, terminal device **8** that has received the beacon signal transmits an abort request to reproduction device **4**. First communication module **28** receives the abort request from terminal device **8** that has received the beacon signal, thereby stopping the transmission of the beacon signal (S112). After that, reproduction device **4** is powered off (S110).

(56) Note that when the user does not perform the operation for aborting the transmission of the connection request to reproduction device **4**, using terminal device **8** that has received the beacon signal (NO in S111), the processing returns to step S105 described above.

(57) Returning to step S103 described above, and when the power state of display device **6** is the power-on state (“Power-on state” in S103), reproduction device **4** outputs an initial settings start screen onto display device **6** (S113). Such initial settings start screen is generated by graphic module **22**, and outputted onto display device **6** by HDMI transmitter **38**. The user operates the remote control of reproduction device **4** to perform various settings for reproduction device **4** (S114). More specifically, the various settings for reproduction device **4** include, for example, (a) settings relating to the remote control of reproduction device **4**, (b) settings relating to connections of display device **6**, and (c) settings for checking whether display device **6** is 4K/60p-capable.

(58) After the completion of the various settings for reproduction device **4**, reproduction device **4** outputs inquiry screen **52** onto display device **6** (S115) that is a screen for inquiring whether the user performs the network settings using terminal device **8**. Such inquiry screen **52** is generated by graphic module **22**, and outputted onto display device **6** by HDMI transmitter **38**. Through this, inquiry screen **52** as shown in (a) in FIG. 4, for example, is displayed on display **14** of display device **6**. Displayed on inquiry screen **52** is, for example, a message saying “Would you like to perform network settings with your smartphone?”, together with selectable “Yes” and “No” buttons.

(59) When the user selects “Yes” button on inquiry screen **52**, using the remote control of reproduction device **4**, that is, when the user wishes to perform the network settings using terminal device **8** (YES in S116), first communication module **28** transmits a beacon signal using BLE (S117).

(60) At this time, reproduction device **4** outputs guidance screen **54** onto display device **6** (S118) that is a screen for prompting the user to perform an operation on terminal device **8** (operation for transmitting a connection request to reproduction device **4**). Such guidance screen **54** is generated by graphic module **22**, and outputted onto display device **6** by HDMI transmitter **38**. Through this, guidance screen **54** as shown in (b) in FIG. 4, for example, is displayed on display **14** of display device **6**. Displayed on guidance screen **54** is, for example, a message saying “Please make connection request with your smartphone”, together with a selectable “Cancel” button.

(61) After that, BLE advertising starts, and first communication module **28** enters a state of waiting for a connection request from terminal device **8** (S105). Thereafter, the processes of steps S105 through S112 are performed as in the foregoing description. Note that when step S105 is followed by step S111, and the user performs an operation for selecting “Cancel” button on guidance screen **54** using the remote control of reproduction device **4**, the processing proceeds to step S112.

(62) Meanwhile, when step S105 is followed by step S106, reproduction device **4** outputs guidance screen **56** onto display device **6** that is a screen for prompting the user to perform the network settings and the tuner reception settings by operating terminal device **8**. Such guidance screen **56** is generated by graphic module **22**, and outputted onto display device **6** by HDMI transmitter **38**. Through this, guidance screen **56** as shown in (c) in FIG. 4, for example, is displayed on display **14** of display device **6**. Displayed on guidance screen **56** is, for example, a message saying “Please

operate your smartphone to perform settings for the device”.

(63) Also, after step **S109**, reproduction device **4** outputs notification screen **58** onto display device **6** that is a screen for notifying the user of the completion of the initial settings. Such notification screen **58** is generated by graphic module **22**, and outputted onto display device **6** by HDMI transmitter **38**. Through this, notification screen **58** as shown in (d) in FIG. **4**, for example, is displayed on display **14** of display device **6**. Displayed on notification screen **58** is, for example, a message saying “Settings completed. The device will be powered off”.

(64) Returning to step **S116** described above, and when the user performs an operation for selecting “No” button on inquiry screen **52**, using the remote control of reproduction device **4**, that is, when the user does not wish to perform the network settings using terminal device **8** (NO in **S116**), the user performs the network settings on the screen displayed on display device **6** by operating the remote control of reproduction device **4** (**S119**), and then performs the tuner reception settings (**S120**). After that, reproduction device **4** is powered off (**S110**).

(65) [1-4. Flow of Network Settings]

(66) With reference to FIG. **5** through FIG. **10**, the following specifically describes the flow of the network settings performed between reproduction device **4** and terminal device **8**. FIG. **5** is a sequence diagram showing the flow of the network settings performed between reproduction device **4** and terminal device **8** according to the embodiment. FIG. **6** is a diagram showing an example screen displayed on terminal device **8** according to the embodiment. FIG. **7** is a diagram showing an example personal identification number (PIN) code displayed on reproduction device **4** according to the embodiment. FIG. **8** through FIG. **10** are diagrams, each showing an example screen displayed on terminal device **8** according to the embodiment.

(67) The following describes the flow of the network settings to be performed when display device **6** connected to reproduction device **4** is in the power-off state.

(68) First, as shown in FIG. **5**, the user starts an application installed in terminal device **8** by operating terminal device **8** (**S201**). Through this, registration screen **60** is displayed on terminal device **8** as shown in FIG. **6** (**S202**). A selectable “Perform initial settings with smartphone” button is displayed on registration screen **60**. The user taps “Perform initial settings with smartphone” button, in response to which terminal device **8** enters a state of waiting for receiving a beacon signal from reproduction device **4** (**S203**).

(69) Also, the user powers on reproduction device **4** (**S204**). Reproduction device **4** detects that display device **6** is not in the power-on state, on the basis of the control signal from display device **6** (**S205**), and transmits a beacon signal using BLE (**S206**).

(70) Terminal device **8** receives the beacon signal from reproduction device **4**, and transmits a connection request to reproduction device **4** (**S207**). Note that when terminal device **8** fails to receive a beacon signal from reproduction device **4** after a predetermined time has elapsed, as a result of which a timeout occurs, a message is displayed, on terminal device **8**, saying, for example, that “Connection failed. Please power off the recorder”.

(71) Reproduction device **4** receives the connection request from terminal device **8** that has received the beacon signal (**S208**), and stops the transmission of the beacon signal (**S209**). Through this, near-field communication using BLE is established between reproduction device **4** and terminal device **8** (**S210**, **S211**).

(72) After that, reproduction device **4** displays the PIN code on front panel display **10** as shown in FIG. **7** (**S212**). The PIN code is, for example, a four-digit number such as “1108”. At this time, PIN code entry screen **62** is displayed on terminal device **8** as shown in FIG. **8**. Displayed on PIN code entry screen **62** is, for example, a message saying “Please enter four-digit number displayed on front panel of recorder”, together with the PIN code entry field and the entry keys. The user enters the PIN code displayed on front panel display **10** of reproduction device **4** onto PIN code entry screen **62** (**S213**). In response to this, terminal device **8** transmits the entered PIN code to reproduction device **4** (**S214**).

(73) Reproduction device **4** receives the PIN code transmitted from terminal device **8**, and determines whether the received PIN code is correct (S215). When the PIN code is not correct (NO in S215), reproduction device **4** updates the PIN code (S216), and displays an updated new PIN code onto front panel display **10** (S212). Note that reproduction device **4** forcefully turns the power off when a total of three incorrect PIN codes are received.

(74) The following describes the case where reproduction device **4** receives the correct PIN code (YES in S215). Terminal device **8** requests reproduction device **4** for the transmission of an access point (AP) list (S216). In response to this, reproduction device **4** performs AP scanning to create an AP list, and transmits the created AP list to terminal device **8** (S217).

(75) Terminal device **8** receives the AP list from reproduction device **4** (S218). At this time, AP list screen **64** is displayed on terminal device **8** on the basis of the received AP list as shown in FIG. **9**. Displayed on AP list screen **64** is, for example, a message saying “Please select the same network as your smartphone”, together with the SSIDs of the wireless access points detected by AP scanning, “abcd012”, “bbef034”, “ccgh056”, and “bcde123”.

(76) On AP list screen **64**, the user selects the SSID “abcd012” of wireless access point **46** with which wireless communication is established with terminal device **8** (S219). In response to this, passcode entry screen **66** is displayed on terminal device **8** as shown in FIG. **10**. Displayed on passcode entry screen **66** is, for example, a message saying “Please enter passcode of abcd012”, together with the passcode entry field and the numeric keypad. The user enters the passcode “xxxxyyy” of the SSID “abcd012” onto passcode entry screen **66** (S219). In response to this, terminal device **8** transmits, to reproduction device **4**, the SSID and the passcode entered by the user (S220).

(77) Reproduction device **4** receives the SSID and the passcode transmitted from terminal device **8** (S221). In response to this, the near-field communication between reproduction device **4** and terminal device **8** is disconnected (S222, S223), and reproduction device **4** establishes wireless communication with wireless access point **46**, on the basis of the received SSID and passcode (S224) to start the connection with wireless network **44**.

(78) After this, terminal device **8** searches for reproduction device **4** via wireless network **44** (S225), and connects to reproduction device **4** via wireless network **44** (S226). After this, the tuner reception settings is performed between reproduction device **4** and terminal device **8** in a manner to be described below.

(79) [1-5. Flow of Tuner Reception Settings]

(80) With reference to FIG. **11** through FIG. **13**, the following specifically describes the flow of the tuner reception settings performed between reproduction device **4** and terminal device **8**. FIG. **11** is a sequence diagram showing the flow of the tuner reception settings performed between reproduction device **4** and terminal device **8** according to the embodiment. FIG. **12** and FIG. **13** are diagrams, each showing an example screen displayed on terminal device **8** according to the embodiment.

(81) When reproduction device **4** has been able to obtain, from display device **6**, postal code information that is required to perform the tuner reception settings, reproduction device **4** performs the tuner reception settings on the basis of the postal code information obtained from display device **6**. The following describes the case where reproduction device **4** fails to obtain postal code information from display device **6**. The postal code information is information indicating a postal code of the area where reproduction device **4** is located.

(82) As shown in FIG. **11**, terminal device **8** provides reproduction device **4**, via wireless network **44**, with an instruction for obtaining the postal code information (S301). Reproduction device **4** tries obtaining the postal code information from display device **6** by CEC (S302), and notifies, via wireless network **44**, terminal device **8** of the failure of obtaining the postal code information (S303).

(83) Terminal device **8** receives the notification from reproduction device **4** (S304), and determines

whether other existing reproduction devices (not illustrated) are present for which tuner reception settings have been completed (S305). When no existing reproduction device is present (NO in S305), postal code entry screen 68 is displayed on terminal device 8 as shown in FIG. 12.

Displayed on postal code entry screen 68 is, for example, a message saying "Please enter seven-digit postal code of your residence", together with the postal code entry field and the entry keys. The user enters the postal code of his/her residential area onto postal code entry screen 68, such as, for example, "571-8501" (S306). In response to this, terminal device 8 transmits, to reproduction device 4, the postal code information indicating the postal code entered by the user (S307).

(84) Returning to step S305 described above, and when an existing reproduction device is present (YES in S305), terminal device 8 obtains postal code information from the existing reproduction device via wireless network 44 (S308). In response to this, terminal device 8 transmits, to reproduction device 4, the postal code information indicating the postal code obtained from the existing reproduction device (S307).

(85) Reproduction device 4 receives the postal code information transmitted from terminal device 8 (S309), and enters a state of waiting for channel scanning instruction (S310). Terminal device 8 provides reproduction device 4, via wireless network 44, with a channel scanning instruction (S311), in response to which reproduction device 4 performs the area settings from the received postal code information, and starts channel scanning (S312). In response to this, terminal device 8 enters a state of waiting for the completion of channel scanning (S313). At this time, standby screen 70 is displayed on terminal device 8 that is a screen indicating that the completion of channel scanning is waited as shown in FIG. 13. Displayed on standby screen 70 is, for example, a message saying "Channel settings in progress Digital terrestrial channel scanning in progress", together with the progress bar showing the progress of the channel scanning.

(86) When the channel scanning is completed, reproduction device 4 transmits, via wireless network 44, a completion notification to terminal device 8 (S314) that notifies the completion of the channel scanning. Terminal device 8 receives the completion notification transmitted from reproduction device 4 (S315). The tuner reception settings are completed as in the foregoing manner.

(87) [1-6. Effects]

(88) As described above, reproduction device 4 in the present embodiment is a reproduction device that is connectable to display device 6 and outputs a video signal to display device 6. Reproduction device 4 includes: HDMI transmitter 38 that detects a power state of display device 6; first communication module 28 that establishes communication with terminal device 8 that is externally located, when HDMI transmitter 38 does not detect that display device 6 is in a power-on state; and controller 36 that performs first settings with terminal device 8, when the communication is established between terminal device 8 and first communication module 28, the first settings being settings relating to reproduction device 4.

(89) With this, it is possible to perform the first settings between terminal device 8 and reproduction device 4 by establishing communication between terminal device 8 and first communication module 28, when HDMI transmitter 38 does not detect that display device 6 is in the power-on state. This enables the first settings to be performed without using display device 6, thereby increasing the user convenience.

(90) Also, in the present embodiment, first communication module 28 transmits a beacon signal to terminal device 8 and establishes the communication with terminal device 8 that has received the beacon signal, when HDMI transmitter 38 does not detect that display device 6 is in the power-on state.

(91) With this, it is possible to easily establish communication between terminal device 8 and first communication module 28, using a beacon signal.

(92) Also, reproduction device 4 in the present embodiment further includes remote control signal receiver 26 that receives an instruction from a user. First communication module 28 transmits the

beacon signal to terminal device **8** and establishes the communication with terminal device **8** that has received the beacon signal, when HDMI transmitter **38** detects that display device **6** is in the power-on state and remote control signal receiver **26** receives, from the user, the instruction indicating that the first settings are to be performed using terminal device **8**.

(93) With this, it is possible to establish communication between terminal device **8** and first communication module **28**, when the user wishes to perform the first settings using terminal device **8**, even in the case where HDMI transmitter **38** detects that display device **6** is in the power-on state.

(94) Also, reproduction device **4** in the present embodiment further includes second communication module **30** that communicates with wireless network **44**. The first settings are settings for connecting reproduction device **4** to wireless network **44** by second communication module **30**.

(95) With this, it is possible to use terminal device **8** to perform the first settings for connecting reproduction device **4** to wireless network **44** by second communication module **30**.

(96) Also, in the present embodiment, wireless network **44** is a wireless LAN. First communication module **28** receives the SSID of wireless access point **46** of the wireless LAN from terminal device **8** to which the user has entered the SSID. Controller **36** performs the first settings, based on the SSID received by first communication module **28**.

(97) With this, it is possible to perform the first settings, on the basis of the SSID entered by the user to terminal device **8**.

(98) Also, reproduction device **4** in the present embodiment further includes tuner **16** that receives broadcast waves. Second communication module **30** establishes communication with terminal device **8** via wireless network **44**, when reproduction device **4** is connected to wireless network **44**. When controller **36** has obtained, from display device **6**, postal code information indicating a postal code of an area where reproduction device **4** is located, controller **36** performs second settings relating to settings for tuner **16**, based on the postal code information obtained. When controller **36** fails to obtain the postal code information from display device **6**, second communication module **30** provides an instruction to terminal device **8** via wireless network **44**, the instruction being an instruction for obtaining the postal code information from another reproduction device for which the second settings have been completed.

(99) With this, it is possible for terminal device **8** to obtain postal code information from another reproduction device for which the second settings have been completed, even when controller **36** fails to obtain the postal code information from display device **6**.

(100) Also, in the present embodiment, the reproduction device control method is a control method of controlling reproduction device **4** that is connectable to display device **6** and outputs a video signal to display device **6**. The reproduction device control method includes: detecting a power state of display device **6**; establishing communication with terminal device **8** that is externally located, when display device **6** is not detected to be in a power-on state; and performing first settings between terminal device **8** and reproduction device **4**, when the communication is established between terminal device **8** and reproduction device **4**.

(101) With this, it is possible to perform the first settings without using display device **6**, thereby increasing the user convenience as described above.

(102) Also, in the present embodiment, the program causes a computer to perform the foregoing reproduction device control method of controlling reproduction device **4**.

(103) [1-7. Variation]

(104) With reference to FIG. **14**, the following describes the flow of network settings performed between reproduction device **4** and terminal device **8** according to a variation of the embodiment. FIG. **14** is a sequence diagram showing the flow of the network settings performed between reproduction device **4** and terminal device **8** according to the variation of the embodiment.

(105) As shown in FIG. **14**, steps **S216** through **S219** that are described with reference to FIG. **5** are replaced by steps **S401** and **S402** in the present variation.

(106) When step S215 is Yes, terminal device **8** requests, via wireless network **44**, another existing reproduction device (not illustrated) for which network settings have been performed for the SSID and the passcode (S401), and receives the SSID and the passcode from such existing reproduction device (S402). After that, terminal device **8** transmits, to reproduction device **4**, the SSID and the passcode received from the existing reproduction device (S220).

(107) In the present variation, wireless network **44** is a wireless LAN. First communication module **28** receives, from terminal device **8**, the SSID of wireless access point **46** of the wireless LAN obtained by terminal device **8** from the other reproduction device for which first settings have been completed. Controller **36** performs the first settings, on the basis of the SSID received by first communication module **28**.

(108) This enables the first settings to be performed on the basis of the SSID obtained by terminal device **8** from the other reproduction device for which the first settings have been completed. This eliminates the necessity of the user having to enter the SSID and the passcode, thereby increasing the user convenience.

(109) [Variation and Others]

(110) The embodiment has been described above to illustrate the technology disclosed in the present application. However, the technology of the present discourse is not limited to the embodiment and thus also applicable to the embodiment to which modification, replacement, addition, omission, and so forth are applied where necessary. Also, elements described in the foregoing embodiment can be combined to serve as a new embodiment.

(111) In view of the above, other embodiments will be described below.

(112) In the foregoing embodiment, HDMI transmitter **38** detects the power state of display device **6**. When HDMI transmitter **38** detects that display device **6** is in the power-off state, however, display device **6** does not necessarily have to be connected to reproduction device **4**. Stated differently, HDMI transmitter **38** cannot detect that display device **6** is in the power-on state, when display device **6** is not connected to reproduction device **4**. In this case, reproduction device **4** performs processing in accordance with the following algorithm: (i) check the state of HDMI connection with HDMI receiver **50**, and the power-on state of display device **6**; (ii) transfer an input to display device **6** to reproduction device **4** by a CEC command; (iii) determine whether the input is transferred to reproduction device **4** by a CEC command; and (iv) determine whether display device **6** is in active source state by a CEC command.

(113) Also, in the foregoing embodiment, reproduction device **4** is wirelessly connected to wireless access point **46** by second communication module **30**, but the present disclosure is not limited to this. Reproduction device **4** may thus be connected to wireless access point **46** by wire via wired LAN I/F **32**. In this case, immediately before step S216 in the flowchart of FIG. 5, an inquiry screen may be displayed on terminal device **8** that is a screen for inquiring whether the user wishes to connect to wireless access point **46** by a wireless LAN or by a wired LAN. When the user selects the connection by a wireless LAN, controller **36** invalidates wired LAN I/F **32** and validates second communication module **30**. In this case, the processes of step S217 and after in the flowchart of FIG. 5 are performed as in the foregoing description. Meanwhile, when the user selects the connection by a wired LAN, controller **36** validates wired LAN I/F **32** and invalidates second communication module **30**. In this case, the processes of step S217 and after in the flowchart of FIG. 5 will not be performed, and a wired connection is established between reproduction device **4** and wireless access point **46**. The near-field connection between reproduction device **4** and terminal device **8** is thus disconnected.

(114) Also, in the foregoing embodiment, near-field communication using BLE is established between reproduction device **4** and terminal device **8**, but USB communication may be established between reproduction device **4** and terminal device **8** instead. In this case, terminal device **8** is connected to USB I/F **34** via a USB cable, which eliminates the necessity of the foregoing authentication processing that uses a PIN code.

(115) In the foregoing embodiment, near-field communication using BLE is established between reproduction device **4** and terminal device **8**. Instead of this, however, reproduction device **4** may be set to parent device mode (AP mode) to directly communicate with terminal device **8** (ad hoc communication) to set information about wireless access point **46** from terminal device **8**. After that, the settings of reproduction device **4** may be changed to slave device mode to connect to wireless access point **46** by infrastructure communication.

(116) Each of the elements in the foregoing embodiment may be configured in the form of an exclusive hardware product, or may be realized by executing a software program suitable for the element. Each of the elements may be realized by means of a program executing unit, such as a CPU and a processor, reading and executing the software program recorded on a non-transitory recording medium such as a hard disk or a semiconductor memory.

(117) Also, some or all of the functions of reproduction device **4** according to the foregoing embodiment may be realized by a processor, such as a CPU, executing the program.

(118) The embodiment has been described above to illustrate the technology of the present disclosure, for which the accompanying drawings and detailed description have been provided.

(119) To illustrate the above technology, the elements described in the accompanying drawings and detailed description can thus include not only the elements essential to solve the problem, but also elements not essential to solve the problem. Therefore, the fact that such non-essential elements are illustrated in the accompanying drawings and detailed description should not lead to the immediate conclusion that such elements are essential.

(120) Also note that the foregoing embodiment is intended for illustrating the technology of the present disclosure, and thus allows for various modifications, replacements, additions, omissions, and so forth made thereto within the scope of the claims and its equivalent scope.

INDUSTRIAL APPLICABILITY

(121) The reproduction device in the present disclosure is applicable for use as, for example, a BD recorder that is connected to a television receiver via a cable.

Claims

1. A reproduction device that is connectable to a display device and outputs a video signal to the display device, the reproduction device comprising: a detector configured to detect a power state of the display device; a first communicator configured to establish communication with a terminal device that is externally located; a receiver configured to receive an instruction from a user; and a controller configured to perform first settings with the terminal device, the first settings being settings relating to the reproduction device, wherein the controller is configured to perform the first settings with the terminal device, (a) after the communication is established by the first communicator between the terminal device and the first communicator without user instruction when the detector does not detect that the display device is in the power-on state, and (b) after the communication is established by the first communicator between the terminal device and the first communicator in response to (i) when the detector detects that the display device is in the power-on state, and (ii) when the receiver receives the user instruction indicating that the first settings are to be performed using the terminal device.

2. The reproduction device according to claim 1, wherein: in case of (a), the first communicator transmits a beacon signal, without user instruction, to the terminal device and establishes the communication with the terminal device that has received the beacon signal, when the detector does not detect that the display device is in the power-on state, and in case of (b), after the receiver receives the user instruction indicating that the first settings are to be performed using the terminal device, the first communicator transmits the beacon signal to the terminal device and establishes the communication with the terminal device that has received the beacon signal.

3. The reproduction device according to claim 1, further comprising: a second communicator that

communicates with a network, wherein the first settings are settings for connecting the reproduction device to the network by the second communicator.

4. The reproduction device according to claim 3, wherein the network is a wireless local area network (LAN), the first communicator receives a service set identifier (SSID) of an access point of the wireless LAN from the terminal device to which a user has entered the SSID, and the controller performs the first settings, based on the SSID received by the first communicator.

5. The reproduction device according to claim 3, wherein the network is a wireless LAN, the first communicator receives an SSID of a wireless access point of the wireless LAN from the terminal device that has obtained the SSID from another reproduction device for which the first settings have been completed, and the controller performs the first settings, based on the SSID received by the first communicator.

6. The reproduction device according to claim 3, further comprising: a tuner that receives broadcast waves, wherein the second communicator establishes communication with the terminal device via the network, when the reproduction device is connected to the network, when the controller has obtained, from the display device, postal code information indicating a postal code of an area where the reproduction device is located, the controller performs second settings relating to settings for the tuner, based on the postal code information obtained, and when the controller fails to obtain the postal code information from the display device, the second communicator provides an instruction to the terminal device via the network, the instruction being an instruction for obtaining the postal code information from another reproduction device for which the second settings have been completed.

7. A reproduction device control method of controlling a reproduction device that is connectable to a display device and outputs a video signal to the display device, the reproduction device control method comprising: detecting a power state of the display device; establishing communication with a terminal device that is externally located; receiving an instruction from a user; and performing first settings with the terminal device, the first settings being settings relating to the reproduction device after; (a) the communication is established between the terminal device and a communicator without user instruction in response to not detecting that the display device is in a power-on state, and (b) the communication is established between the terminal device and the communicator in response to (i) when detecting that the display device is in the power-on state, and (ii) when receiving the user instruction indicating that the first settings are to be performed using the terminal device.

8. A non-transitory computer-readable recording medium having recorded thereon a computer program for causing a computer to execute the reproduction device control method according to claim 7.

9. A reproduction device that is connectable to a display device and outputs a video signal to the display device, the reproduction device comprising: a tuner that receives broadcast waves, a detector that detects a power state of the display device; a communicator that establishes communication with a terminal device that is externally located, when the detector does not detect that the display device is in a power-on state; and a controller that, after the communication is established between the terminal device and the communicator, when the controller has obtained postal code information indicating a postal code of an area where the reproduction device is located, the controller performs settings relating to settings for the tuner, based on the postal code information obtained, wherein, when the controller fails to obtain the postal code information, the communicator provides an instruction to the terminal device, the instruction being an instruction for obtaining the postal code information from another reproduction device for which the settings relating to settings for the tuner have been completed.
