

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12404978
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Doubek; David E. et al.

Lighting devices and methods for installing and repairing the same

Abstract

A lighting device includes a housing, a plurality of clips, a ferromagnetic strip, a light source, and a lens. The housing includes a base, a first side wall, a second side wall defining an interior cavity. Each of the plurality of clips is coupled to the housing and includes a magnet. The ferromagnetic strip is coupled to the housing via the magnets of the plurality of clips. The light source is disposed within the interior cavity of the housing and coupled to the ferromagnetic strip. The lens is disposed within the interior cavity of the housing.

Inventors: Doubek; David E. (Indian Head Park, IL), Goldstein; Noah (Indian Head Park, IL)

Applicant: Dado Lighting, LLC (Indian Head Park, IL)

Family ID: 92636228

Assignee: Dado Lighting, LLC (Indian Head Park, IL)

Appl. No.: 18/598290

Filed: March 07, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240302007 A1	Sep. 12, 2024

Related U.S. Application Data

us-provisional-application US 63489651 20230310

Publication Classification

Int. Cl.: F21V17/10 (20060101); F21S4/20 (20160101); F21S4/28 (20160101); F21V17/16 (20060101); F21V23/00 (20150101); F21V29/70 (20150101); F21Y113/00 (20160101); F21Y115/10 (20160101)

U.S. Cl.:

CPC F21S4/20 (20160101); F21S4/28 (20160101); F21V17/105 (20130101); F21V17/164 (20130101); F21V23/001 (20130101); F21V29/70 (20150115); F21Y2113/00 (20130101); F21Y2115/10 (20160801)

Field of Classification Search

CPC: F21V (17/164); F21V (17/105); F21V (19/003); F21S (4/20); F21S (4/28)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
10190738	12/2018	James	N/A	F21S 4/28
11149933	12/2020	Shi	N/A	H05K 1/18
11473743	12/2021	Lin	N/A	F21V 17/12
12098828	12/2023	Irons	N/A	F21V 15/015
2016/0356470	12/2015	Noh	N/A	F21V 29/74
2016/0369958	12/2015	Kohshima	N/A	F21S 4/28

Primary Examiner: Eide; Eric T

Attorney, Agent or Firm: Nixon Peabody LLP

Background/Summary

CROSS REFERENCE TO RELATED APPLICATIONS (1) This application claims the benefit of, and priority to, U.S. Provisional Application No. 63/489,651, filed Mar. 10, 2023, which is hereby incorporated by reference herein in its entirety.

TECHNICAL FIELD

(1) The present disclosure relates generally to lighting devices, and more particularly, to lighting devices including a plurality of clips for supporting a removable ferromagnetic strip, and methods for installing the same.

BACKGROUND

(2) Lighting devices are often integrated in a structure such as a wall or ceiling. Many of these lighting devices include a light emitting diode (LED) strip within a housing that is covered by a lens. In some examples, the housing is installed, then the LED strip unrolled and attached within the housing (e.g., using an adhesive), and then covered (e.g., by the lens). Often, after installation, one or more of the LEDs in the LED strip will fail such that either the entire LED strip or at least a portion of the LED strip will no longer illuminate. In this case, it is necessary to replace the failed LED strip. However, once the lighting device is installed (e.g., in a ceiling or wall), it is difficult to remove the LED strip from within the housing to replace it. It is especially difficult to remove the LED strip when the housing is very thin (e.g., only about 3 inches wide). Further, when adhered to

the housing, it is difficult to remove all of the residual adhesive after removing the LED strip. This residual adhesive can inhibit contact between a new LED strip and the housing. The present disclosure is directed to solving these and other problems.

SUMMARY

(3) According to some implementations of the present disclosure, a lighting device includes a housing, a plurality of clips, a ferromagnetic strip, a light source, and a lens. The housing includes a base, a first side wall, a second side wall defining an interior cavity. Each of the plurality of clips is coupled to the housing and includes a magnet. The ferromagnetic strip is coupled to the housing via the magnets of the plurality of clips. The light source is disposed within the interior cavity of the housing and coupled to the ferromagnetic strip. The lens is disposed within the interior cavity of the housing.

(4) According to some implementations of the present disclosure, a method for installing a lighting device includes positioning a housing within a slot in an external structure. The method also includes coupling a plurality of clips to the housing. Each of the plurality of clips includes a magnet. The method also includes coupling a ferromagnetic strip to the housing via the magnets of the plurality of clips. A light source is coupled to the ferromagnetic strip. The method also includes coupling a lens to the housing subsequent to coupling the ferromagnetic strip to the plurality of clips.

(5) According to some implementations of the present disclosure, a method for repairing an installed lighting device includes decoupling a lens from a housing, the housing being positioned within a slot in an external structure. The method also includes decoupling a first ferromagnetic strip from a plurality of clips, each of the plurality of clips being coupled to the housing and including a magnet, wherein a first light source is coupled to the ferromagnetic strip. The method also includes decoupling a first ferromagnetic strip from a plurality of clips. Each of the plurality of clips being coupled to the housing and including a magnet, wherein a first light source is coupled to the first ferromagnetic strip. The method also includes coupling a second ferromagnetic strip to the plurality of clips, wherein a second light source is coupled to the ferromagnetic strip. The method also includes re-coupling the lens to the housing.

(6) The above summary is not intended to represent each implementation or every aspect of the present disclosure. Additional features and benefits of the present disclosure are apparent from the detailed description and figures set forth below.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is an assembled perspective view of a lighting device, according to some implementations of the present disclosure;

(2) FIG. 2 is an exploded perspective view of the lighting device of FIG. 1, according to some implementations of the present disclosure;

(3) FIG. 3 is a cross-sectional view of the lighting device of FIG. 1, according to some implementations of the present disclosure;

(4) FIG. 4A is a first perspective view of a clip of the lighting device of FIG. 1, according to some implementations of the present disclosure;

(5) FIG. 4B is a second perspective view of the clip of the lighting device of FIG. 1;

(6) FIG. 5 is an assembled perspective view of the lighting device of FIG. 1 installed in a slot in an external structure, according to some implementations of the present disclosure;

(7) FIG. 6A is a first perspective view of an end cap of the lighting device of FIG. 1, according to some implementations of the present disclosure;

(8) FIG. 6B is a second perspective view of the end cap of the lighting device of FIG. 1, according

to some implementations of the present disclosure;

(9) FIG. 7A is a cross-sectional view of a lighting device according to some implementations of the present disclosure;

(10) FIG. 7B is a perspective view of a heat sink bracket of the lighting device of FIG. 7A, according to some implementations of the present disclosure;

(11) FIG. 8 is a process flow diagram for a method of installing the lighting device of FIG. 1, according to some implementations of the present disclosure; and

(12) FIG. 9 is a process flow diagram for a method of repairing the lighting device of FIG. 1, according to some implementations of the present disclosure.

(13) While the present disclosure is susceptible to various modifications and alternative forms, specific implementations and embodiments thereof have been shown by way of example in the drawings and will herein be described in detail. It should be understood, however, that it is not intended to limit the present disclosure to the particular forms disclosed, but on the contrary, the present disclosure is to cover all modifications, equivalents, and alternatives falling within the spirit and scope of the present disclosure as defined by the appended claims.

DETAILED DESCRIPTION

(14) Referring to FIGS. 1 and 2, a lighting device **100** according to some implementations of the present disclosure is illustrated. The lighting device **100** includes a housing **110**, a pair of end caps **120A-120B**, an external power cable **130**, a plurality of clips **140A-140B**, a ferromagnetic strip **150**, a light source **160**, and a lens **170**. As described herein, the lighting device **100** can be mounted with a slot formed in an external structure (e.g., a ceiling, a wall, furniture, etc.) such that the lens **170** is generally flush with a finished surface of the external structure.

(15) Referring to FIG. 3, the housing **110** includes a base **112**, a first side wall **114A**, and a second side wall **114B**. The first side wall **114A** and the second side wall **114B** generally extend from the base **112** and define an internal cavity of the housing **110**. The first side wall **114A** includes a first flange **116A** that protrudes into the internal cavity and the second side wall **114B** includes a second flange **116B** that also protrudes into the internal cavity. The first flange **116A** and the second flange **116B** generally aid in coupling the plurality of clips **140A-140B** to the housing **110** (e.g., via a snap fit connection).

(16) The first side wall **114A** includes a first protrusion **118A** that protrudes into the internal cavity and the second side wall **114B** includes a second protrusion **118B** that also protrudes into the internal cavity. The first protrusion **118A** and the second protrusion **118B** have a generally semi-circular shape and generally aid in coupling the lens **170** to the housing **110** (e.g., via a snap fit connection).

(17) The first side wall **114A** and the second side wall **114B** also include a first bracket **122A** and a second bracket **122B**, respectively. The first bracket **122A** and the second bracket **122B** define a groove that extends along the length of an upper surface of the base **112** of the housing **110**. As described herein, the first bracket **122A** and the second bracket **122B** aid in coupling the first end cap **120A** and the second end cap **120B** to the housing **110** (e.g., via a press or interference fit connection) and/or coupling additional mounting brackets to the housing **110** (e.g., for coupling or mounting the housing **110** to a surface or structure).

(18) As shown in FIGS. 1 and 2, the housing **110** includes an aperture formed through the base **112** (FIG. 3) to allow a portion of the external power cable **130** to be disposed within the housing **110**. The external power cable **130** includes a connector **132** that can be coupled to a corresponding connector **164** of a power cable **162** of the light source **160** to power the light source **160** (FIG. 2). The external power cable **130** is connected to an external power source or supply (e.g., an AC electrical power source). In some implementations, the external power cable **130** includes or is coupled to a AC/DC converter for converting power from an AC electrical outlet. In some implementations, the lighting device **100** further includes a power supply enclosure that includes one or more constant voltage or constant current drivers (e.g., three drivers) for powering the light

source **160**. As described herein, the lighting device **100** can be used in system including multiple lighting devices. In such implementations, the external power cable **130** can be coupled to a power supply enclosure that is also coupled to power cables from one or more additional lighting devices that are the same as, or similar to, the lighting device **100**.

(19) The housing **110** comprises a material (e.g., aluminum, steel, stainless steel, etc.) that aids in absorbing and/or distributing heat generated by the light source **160** so that the housing **110** acts a heat sink. As shown, the housing **110** is a unitary and/or monolithic component. In other implementations, the housing **110** can comprise one or more components that are coupled (e.g., welded) together. In some implementations, the housing **110** has a width of about 0.625 inches, a length of about 72 inches, and a height of about 1.5 inches. In some implementations, the housing **110** also includes a scribed line extending along a surface of the base **112**. For example, the scribed line can be a notch or channel that extends along the longitudinal axis of the housing **110** that aids in drilling one or more aperture in the base **112** of the housing **110** for one or more fasteners.

(20) Referring to FIGS. **6A** and **6B**, the first end cap **120A** includes a first tongue portion **122A** and a second tongue portion **124A**. The first tongue portion **122A** is sized and shaped to engage the groove defined by the first bracket **122A** and the second bracket **122B** of the housing **110** (FIG. **3**) to couple the first end cap **120A** to the housing **110** (e.g., via a press or interference fit). The second tongue portion **124A** is sized and shaped to engage a portion of one of the plurality of clips **140A-140B**. The first end cap **120A** also includes a first pair of notches **126a-126b** and a second pair of notches **128a-128b**. The first pair of notches **126a-126b** are sized and shaped to engage the first flange **116A** and second flange **116B** of the housing **110** (FIG. **3**) to aid in coupling the first end cap **120A** to the housing **110**. Similarly, the second pair of notches **128a-128b** are sized and shaped to engage the first protrusion **118A** and second protrusion **118B** of the housing **110** (FIG. **3**) to aid in coupling the first end cap **120A** to the housing **110**. The second end cap **120B** (FIGS. **1-2**) is the same as, or similar to, the first end cap **120A** and is coupled to the opposite end of the housing **110**.

(21) Referring to FIGS. **4A** and **4B**, a first clip **140A** includes a base **142A**, a first deflectable arm **144a**, a second deflectable arm **144b**, and a magnet **148A**. The first clip **140A** and the second clip **140B** can be removably coupled to the housing **110** and are generally configured to support the ferromagnetic strip **150** within the housing **110**. The magnet **148A** is generally circular and coupled to the base **142A**. As described herein, the magnet **148A** couples the clip **140A** to the ferromagnetic strip **150** via a magnetic connection. The first deflectable arm **144a** is moveable relative to the base **142A** and includes a first hook **146a**. As shown in FIG. **3**, the first hook **146a** engages the first flange **116A** of the housing **110** to aid in coupling the first clip **140A** to the housing **110**. Similarly, the second deflectable arm **144b** is moveable relative to the base **142A** and includes a second hook **146b** that engages the second flange **116B** of the housing **110** to aid in coupling the first clip **140A** to the housing **110**. The space between the first deflectable arm **144a** and the second deflectable arm **144b** allows a portion of the power cable **130** and/or the power cable **162** to pass through the first clip **140A** when the first clip **140A** is coupled to the housing **110** (e.g., as shown in FIGS. **3** and **5**).

(22) Referring back to FIG. **2**, the second clip **140B** is the same as or similar to the first clip **140A**. While the lighting device **100** is shown as including two clips (the first clip **140A** and the second clip **140B**), more generally, the lighting device **100** can include any suitable number of clips (e.g., 1 clip, 3 clips, 5 clips, 10 clips, etc.) for supporting the ferromagnetic strip **150** within the housing **110**. Similarly, the plurality of clips **140A** and **140B** can be coupled to the housing **110** at any suitable location along the length of the housing **110**. For example, the plurality of clips **140A** and **140B** can be spaced by a predetermined distance (e.g., between about 1 foot and about 3 feet, between about 2 feet and about 6 feet, between about 1 foot and 10 feet, etc.) to aid in supporting the ferromagnetic strip **150**. The plurality of clips **140A-140B** can comprise a polymer material, spring steel, brass, bronze, or any combination thereof.

(23) Referring to FIGS. **2-3** and **5**, the ferromagnetic strip **150** has a generally rectangular shape

and comprises a ferromagnetic material (e.g., steel, ultra-low carbon steel, iron, nickel, alloys thereof, etc.). The ferromagnetic strip **150** is sized and shaped so that it can be disposed within the internal cavity of the housing **110** between the first side wall **114A** and the second side wall **114B**. As shown in FIGS. **3** and **5**, the ferromagnetic strip **150** is removably coupled to the housing **110** via the magnets of the plurality of clips **140A-140B** (e.g., the magnet **148A** of the first clip **140A**). The magnetic coupling between the plurality of clips **140A-140B** is strong enough to support the weight of the ferromagnetic strip **150** and the light source **160** coupled thereto, while also allowing a user to remove the ferromagnetic strip **150** and light source **160** from the housing **110** by pulling the ferromagnetic strip **150** down away from the plurality of clips **140A-140B**. In some implementations, the ferromagnetic strip **150** extends along substantially the entire length of the housing **110**. In other implementations, the lighting device **100** can include a plurality of ferromagnetic strips that are the same as, or similar to, the ferromagnetic strip **150** that collectively extend along substantially the entire length of the housing **110**.

(24) In some implementations, the ferromagnetic strip **150** includes a protective coating that aids in dissipating heat from the ferromagnetic strip **150** that was transferred from the light source **160** and also aids in inhibiting corrosion of the ferromagnetic strip **150** (e.g., in humid or outdoor environments). In such implementations, the protective coating on the ferromagnetic strip **150** can be, for example, a Zn and Al alloy.

(25) Referring to FIGS. **2-3** and **5**, the light source **160** includes a power cable **162** (FIG. **3**) and is generally used to illuminate light. The power cable **162** includes a connector **164** (FIG. **3**) that is configured to electrically couple the light source **160** to the power cable **130** via the connector **132** to power the light source **160** for illumination. The light source **160** is coupled to the ferromagnetic strip **150** via at least one adhesive strip **152** (e.g., two adhesive strips, five adhesive strips, 10 adhesive strips, 25 adhesive strips, etc.). As shown in FIGS. **3** and **5**, when coupled to the ferromagnetic strip **150**, the light source **160** is positioned to emit light towards the lens **170**.

(26) The adhesive strip **152** is a double-sided adhesive that adheres to both the ferromagnetic strip **150** and the light source **160**. In some implementations, the adhesive strip **152** can have a width of about 0.75 inches and a length of about 3 inches. In some cases, heat generated by the light source **160** may cause degradation of the adhesive strip **152** (e.g., reducing its holding power). Thus, the adhesive strip **152** preferably has a heat resistance rating of about 120 degrees Fahrenheit. To secure the light source **160** to the ferromagnetic strip **150**, the adhesive strip **152** can have a peel adhesion that is between about 35 oz/in (N/100 mm) and about 70 oz/in (N/100 mm). The adhesive strip **152** can have a first side having a first peel adhesion value and a second opposing side having a second peel adhesion value that is different than the first peel adhesion value to aid in securing the light source **160** to the ferromagnetic strip **150**. Such double-sided tapes are particularly advantageous for coupling the light source **160** to the ferromagnetic strip **150**, for example, due to their holding power, heat resistance, heat sinking properties, thermal bond properties, etc. While the lighting device **100** is shown as including one adhesive strip **152**, more generally, the lighting device **100** can include any suitable number of adhesive strips that are the same as, or similar to, the adhesive strip **152** (e.g., two adhesive strips, five adhesive strips, ten adhesive strips, etc.).

(27) In some implementations, the light source **160** includes a support substrate and a plurality of light emitting diodes (LEDs) coupled to the support substrate. The light source **160** can also include an encapsulant (e.g., comprising silicon) that at least partially surrounds the plurality of LEDs. The support substrate can be a rigid board or plate, a flexible strip or film, a printed circuit board, etc. The plurality of LEDs can include white LEDs, blue LEDs (e.g., III-nitride LEDs), red LEDs, green LEDs, yellow LEDs, amber LEDs, orange LEDs, infrared LEDs, ultraviolet LEDs, or any combination thereof. The plurality of LEDs can be dimmable (e.g., together or individually controllable). The plurality of LEDs can be mounted to the support substrate using any suitable packaging technique (e.g., a surface mount package, a through-pin package, etc.). Further, the plurality of LEDs can be electrically coupled to one another using any suitable mechanism or

technique (e.g., in series, in parallel, via wiring, via traces, etc.). The encapsulant protects the plurality of LEDs (e.g., from mechanical damage) and/or modifies the light emission characteristics. For example, the encapsulant can include a wavelength converter (e.g., a phosphor material) that converts a first wavelength of light emitted by the LEDs (e.g., blue) to a second wavelength of light (e.g., white), which is then emitted from encapsulant. In some implementations, the power of the light source **160** is about 1 Watt per foot (e.g., sometimes referred to as ultra-low wattage).

(28) While the lighting device **100** is shown as including one light source **160**, in some implementations, the lighting device **100** includes a plurality of light sources that are the same as, or similar to, the light source. In such implementations, a first one of the light sources can be positioned within the housing **110** (e.g., coupled to the housing **110** via one or more ferromagnetic strips and clips). In such implementations, the light first light source can emit a first wavelength of light (e.g., white light) and the second light source can emit a second wavelength of light or a plurality of wavelengths of light (e.g., red light, blue light, green light, etc.). The plurality of light sources can be tuned or adjusted to create a white or warm dim effect that avoids the pink effect that is visible when the color delta is greater than 2000K and the dimming curve no longer follows the black body dimming curve.

(29) Referring to FIG. 3, the lens **170** includes a first notch **172A** and a second notch **172B** on opposing sides of the lens **170**. As shown, the first notch **172A** engages the first protrusion **118A** of the housing **110** and the second notch **172B** engages the second protrusion **118B** of the housing **110** to removably couple the lens **170** to the housing **110** (e.g., via a snap fit connection). Further, as shown, the lens **170** is generally flush with the ends of the side walls **114A** and **114B** when coupled to the housing **110**. Thus, the lens **170** is generally flush with a surface of the external structure in which the lighting device **100** is inserted when installed. Once coupled to the housing **110**, the lens **170** can be removed (e.g., by inserting a tool or shim between an edge of the lens **170** and the housing **110**) and then re-coupled to the housing **110** (e.g., to facilitate removing the ferromagnetic strip **150** from within the housing **110**, as described below).

(30) The lens **170** generally comprises a material (e.g., a polymer) for allowing light to pass through so that light emitted from the light source **160** is emitted outside of the lens **170**. Generally, the lens **170** aids in diffusing or distributing light emitted by the light source **150** outside of the lighting device **100**. In some implementations, the lens **170** comprises a generally flexible material that permits deflection of the first notch **172A** and/or the second notch **172B** to aid in forming a snap fit coupling between the lens **170** and the housing **110**. In some implementations, the lens **170** comprises a generally rigid material that is biased against flexing or deflection. In some implementations, the lens **170** includes a frosted surface or material (e.g., a material that is roughened, textured, or patterned) to aid in diffusing light in all directions. In some implementations, the lens **170** has a width and a length that is substantially equal to the length and width of the housing.

(31) As shown, the ends of the lighting device **100** are generally straight (e.g., the housing **110** and the lens **170** have a generally rectangular profile). However, in some implementations, the lighting device **100** can include one or more mitered ended. In such implementations, the mitered end(s) appear as if cut at an angle that is, for example, between about 30 degrees and about 80 degrees (e.g., 45 degrees, 60 degrees, 75 degrees, etc.). A first lighting device with a mitered end can be positioned to abut another lighting device with a mitered end to form a miter joint such that a longitudinal axis of the first lighting device is at angle (e.g., 90 degrees) relative to a longitudinal axis of the second lighting device.

(32) Referring to FIGS. 7A and 7B, a lighting device **700** according to some implementations of the present disclosure is illustrated. The lighting device **700** is similar to the lighting device **100** and includes a housing **710**, a plurality of clips (including clip **740A**), a ferromagnetic strip **750**, a light source **760**, and a lens **770**, each of which being the same as, or similar to, the housing **110**,

the clip **140A**, the ferromagnetic strip **150**, the light source **160**, and the lens **170** described herein. (33) As described herein, the light source of the lighting device generates heat during operation and the housing and/or ferromagnetic strip can act as a heat sink to aid in preventing overheating of the light source (e.g., which may cause the light source to fail or reduce its lifetime). In the lighting device **100**, the ferromagnetic strip **150** coupled to the light source **160** is not in direct contact with the housing **110**, so there is no direct, conductive heat transfer between the light source **160** and ferromagnetic strip **150** and the housing **110** (e.g., the dominant heat transfer mechanism between the ferromagnetic strip **150** and the housing **110** is radiation in the lighting device **100**). In some implementations, the light source **160** of the lighting device **100** has a power of about 1 Watt per foot, while the light source **760** of the lighting device **700** has a power of about 10 Watts per foot. In the case of the light source **760**, the additional heat generated by the light source **760** may not effectively transfer from the light source **760** to the housing **710** (e.g., by radiation heat transfer alone).

(34) The lighting device **700** differs from the lighting device **100** in that the lighting device **700** includes a heat sink bracket **790**. As shown in FIG. 7A, the heat sink bracket **790** is coupled to the ferromagnetic strip **750** and contacts a portion of the housing **710**. The heat sink bracket **790** can be coupled to the ferromagnetic strip **750**, for example, via an adhesive connection, welding, one or more fasteners, etc. Specifically, in the example illustrated in FIG. 7A, a first portion of the heat sink bracket **790** is positioned between the ferromagnetic strip **750** and the light source **760**, and a second portion of the heat sink bracket **790** contacts the first side wall **714A** of the housing **710**. The contact between the heat sink bracket **790** and the housing **710** permits heat transfer (e.g., conduction) between the light source **760** and the housing **710**. The second portion of the heat sink bracket **790** is not coupled to the first side wall **714A** of the housing **710** such that the ferromagnetic strip **750** and the light source **760** can be removed from the housing **710** (e.g., as described below in connection with the method **900**). The heat sink bracket **790** can comprise a metal material (e.g., aluminum, alloys thereof, etc.). The heat sink bracket **790** and the housing **710** can comprise the same material, or different materials.

(35) As shown in FIG. 7B, the heat sink bracket **790** is generally L-shaped and includes a first score line **792** and a second score line **794**. The first score line **792** and the second score line **794** aid in aligning the light source **760** in the center of the heat sink bracket **790** based on the width of the light source **760**. While the heat sink bracket **790** is shown as described herein being generally L-shaped, in some implementations, the heat sink bracket **790** can be generally U-shaped such that a first portion of the heat sink bracket **790** contacts the first side wall **714A** of the housing **710**, a second portion of the heat sink bracket **790** contacts the second side wall **714B** of the housing **710**, and a third portion of the heat sink bracket **790** is coupled to the ferromagnetic strip **750**. Similarly, while the heat sink bracket **790** is position in FIG. 7A so that one portion contacts the first side wall **714A** of the housing **710**, the heat sink bracket **790** can be reversed such that this portion contacts the first side wall **714B** of the housing **710** instead of the first side wall **714A**.

(36) Referring to FIG. 8, a method **800** for installing a light device according to some implementations of the present disclosure is illustrated. The method **800** can be performed using, for example, the lighting device **100** or the lighting device **700** described herein.

(37) Step **801** of the method **800** includes positioning a housing of a lighting device within a slot or opening formed in an external structure. The external structure can be, for example, a wall (e.g., dry wall supported by wooden or metal studs) or a ceiling (e.g., a drywall ceiling, a drop ceiling, etc.). Referring to FIG. 6, an external structure **200** includes a first portion and a second portion defining and opening or slot. The opening or slot can be a generally rectangular slot formed in the external structure having a width that is substantially equal to the width of the housing **110** of the lighting device **100**.

(38) In some implementations, step **801** also includes coupling the housing **110** of the lighting device **100** within the slot via one or more fasteners. For example, referring to FIG. 6, the housing

110 can be secured within the slot **606** or opening via the fastener **180** (e.g., a threaded screw), which extends through an aperture in the housing **110**. In some implementations, step **801** includes drilling one or more apertures in the base **112** of the housing **110** for receiving the one or more fasteners therein. For example, step **801** can include drilling a plurality of apertures along the scribed line (described above) of the base **112** of the housing **110**.

(39) Step **802** of the method **800** includes coupling a plurality of clips to the housing of the lighting device. For example, as shown and described herein, the plurality of clips **140A-140B** can be coupled to the housing **110**. In some implementations, step **802** is after step **801**. In other implementations, step **802** is before step **801**.

(40) Step **803** of the method **800** includes coupling the ferromagnetic strip to the housing of the lighting device. For example, as described above, the ferromagnetic strip **150** (to which the light source **160** is coupled) can be coupled to the housing **110** via the corresponding magnets of the plurality of clips **140A-140B**. Step **803** can also include coupling the connector **164** of the power cable **162** of the light source **160** to the connector **132** of the external power cable **130** to form an electrical connection for powering the light source **160**. In some implementations, the connector **164** and connector **132** are coupled prior to coupling the ferromagnetic strip **150** to the plurality of clips **140A-140B**. In other implementations, the connector **164** and connector **132** are coupled subsequent to coupling the ferromagnetic strip **150** to the plurality of clips **140A-140B**.

(41) Step **804** of the method **800** includes coupling a lens to the housing subsequent to coupling the ferromagnetic strip to the housing. Referring to FIGS. **3** and **5**, the lens **170** is coupled to the housing **110** via a snap fit coupling. For example, an installer can position the lens **170** so that the first notch **172A** engages the first protrusion **118A** of the housing **110**, then push the lens **170** so that the second notch **172B** engages the second protrusion **118B** of the housing **110** (or vice versa). In some implementations, step **804** includes measuring and cutting the lens **170** (e.g., from a roll or spool) so that the length of the lens **170** is substantially equal to the length of the housing **110**.

(42) Referring to FIG. **9**, a method **900** for repairing a lighting device according to some implementations of the present disclosure is illustrated. The method **900** can be performed using, for example, the lighting device **100** or the lighting device **700** described herein after having been installed according to method **700**.

(43) Step **901** of the method **900** includes decoupling a lens from a housing of an installed lighting device. For example, as described herein, the lens **170** of the lighting device **100** can be decoupled from the housing **110** subsequent to being initially coupled to the housing **110** (e.g., via a snap fit coupling). In some implementations, step **901** is performed by a user (e.g., the can remove the lens **170** with their hands). In other implementations, step **901** is performed using a tool (e.g., a shim, a flat head screwdriver, or the like, etc.) to aid in removing the lens **170** from the housing **110**. In some implementations, step **901** includes removing the entire lens **170** from the housing **110**. In other implementations, step **901** includes removing a portion of the lens **170** from the housing **110** (e.g., one segment of the lens **170** is decoupled from the housing **110** while a second segment of the lens **170** remains coupled to the housing **110**).

(44) Step **902** of the method **900** includes decoupling a ferromagnetic strip from a plurality of clips, where each of the plurality of clips is coupled to the housing. For example, as described herein, the ferromagnetic strip **150** can be decoupled from the plurality of clips **140A-140B** once the lens **170** is removed from the housing **110**. In some implementations, step **802** includes decoupling the connector **164** of the power cable **162** of the light source **160** from the connector **132** of the external power cable **130**. The decoupling of the connector **164** and connector **132** can be before or after removing the ferromagnetic strip **150** from the plurality of clips **140A-140B**.

(45) Step **903** of the method **900** includes coupling a second ferromagnetic strip coupled to a second light source to the housing. The second ferromagnetic strip and the second light source are the same as, or similar to the first ferromagnetic strip and the first light source, respectively.

(46) Step **904** of the method **900** includes re-coupling the lens to the housing after coupling the

ferromagnetic strip and the second light source to the housing via the plurality of clips. Step **806** is the same as, or similar to, step **704** of the method **700** (FIG. 7) described above.

(47) In some implementations, the method **900** does not include coupling a second ferromagnetic strip to the housing. Instead, the method **900** can include decoupling the first light source from the first ferromagnetic strip and coupling a second light source to the first ferromagnetic strip. For example, the light source **160** can be pulled from the adhesive strip **152** coupling it to the ferromagnetic strip **150** (e.g., manually by a user or using a tool). In some cases, a portion of the adhesive strip **152** or residue remains on the ferromagnetic strip **150**. Thus, in some implementations, the method **900** removing the remaining portion of the adhesive strip **152** mechanically (e.g., scraping using a tool), chemically (e.g., that aids in removing the adhesive), or both. It would be difficult to remove residual from the ferromagnetic strip **150** while it is inside of the housing **110**. Thus, removing the first ferromagnetic strip is advantageous because it facilitates removal of the adhesive strip so that another adhesive strip can be attached, as described below. In such implementations, the method **900** also includes re-coupling the first ferromagnetic strip and the second light source to the housing via the plurality of clips.

(48) One or more elements or aspects or steps, or any portion(s) thereof, from one or more of any of the claims below can be combined with one or more elements or aspects or steps, or any portion(s) thereof, from one or more of any of the other claims or combinations thereof, to form one or more additional implementations and/or claims of the present disclosure.

(49) While the present disclosure has been described with reference to one or more particular embodiments or implementations, those skilled in the art will recognize that many changes may be made thereto without departing from the spirit and scope of the present disclosure. Each of these implementations and obvious variations thereof is contemplated as falling within the spirit and scope of the present disclosure. It is also contemplated that additional implementations according to aspects of the present disclosure may combine any number of features from any of the implementations described herein.

Claims

1. A lighting device comprising: a housing including a base, a first side wall, a second side wall defining an interior cavity; a plurality of clips, each of the plurality of clips being coupled to the housing and including a magnet; a ferromagnetic strip coupled to the housing via the magnets of the plurality of clips; a light source disposed within the interior cavity of the housing and coupled to the ferromagnetic strip; a lens disposed within the interior cavity of the housing; the first side wall of the housing includes a first flange extending into the interior cavity and the second side wall of the housing includes a second flange extending into the interior cavity; each of the plurality of clips includes a base, a first deflectable arm, and a second deflectable arm; and the first deflectable arm of each of the plurality of clips includes a first hook configured to engage the first flange and the second deflectable arm of each of the plurality of clips includes a second hook configured to engage the second flange to couple the one or more clips to the housing.
2. The lighting device of claim 1, wherein each of the plurality of clips comprises a polymer material.
3. A lighting device comprising: a housing including a base, a first side wall, a second side wall defining an interior cavity; a plurality of clips, each of the plurality of clips being coupled to the housing and including a magnet; a ferromagnetic strip coupled to the housing via the magnets of the plurality of clips; a light source disposed within the interior cavity of the housing and coupled to the ferromagnetic strip; a lens disposed within the interior cavity of the housing; the first side wall of the housing includes a first flange extending into the interior cavity and the second side wall of the housing includes a second flange extending into the interior cavity; and a power cable configured to deliver electrical power from a power supply to the light source, wherein a first

- portion of the power cable is disposed within the internal cavity of the housing and extends between the first deflectable arm and the second deflectable arm of at least one of the one or more clips.
4. The lighting device of claim 3, wherein the base of the housing includes aperture and a second portion of the power cable extend through the aperture outside of the internal cavity of the housing.
 5. The lighting device of claim 3, wherein a first end of the power cable includes a connector.
 6. The lighting device of claim 5, wherein the plurality of clips includes a first clip and a second clip and the connector is disposed within the internal cavity of the housing between the first clip and the second clip.
 7. The lighting device of claim 1, wherein the lens comprises a flexible material.
 8. The lighting device of claim 1, wherein the lens comprises a rigid material.
 9. The lighting device of claim 1, wherein the lens comprises polymethyl methacrylate (PMMA).
 10. The lighting device of claim 1, wherein the first side wall of the housing includes a first protrusion extending into the internal cavity and the second side wall of the housing includes a second protrusion extending into the internal cavity.
 11. The lighting device of claim 10, wherein a first side of the lens includes a first groove configured to engage the first protrusion and a second side of the lens includes a second groove configured to engage the second protrusion to couple the lens to the housing.
 12. The lighting device of claim 1, further comprising one or more double-sided adhesive strips configured to couple the light source to the ferromagnetic strip.
 13. The lighting device of claim 1, wherein the light source includes a plurality of light emitting diodes (LEDs) coupled to a support substrate, wherein the support substrate is coupled to the ferromagnetic strip.
 14. The lighting device of claim 1, further comprising a first end cap coupled to a first end of the housing and second end cap coupled to a second end of the housing.
 15. The lighting device of claim 14, wherein the housing includes an upper groove extending between the first end and the second end of the housing, the first end cap includes a first tongue configured to engage the upper groove to aid in coupling the first end cap to the first end of the housing, and the second end cap includes a second tongue configured to engage the upper groove to aid in coupling the second end cap to the second end of the housing.
 16. The lighting device of claim 1, wherein the ferromagnetic strip includes a protective coating comprising a zinc and aluminum alloy.
 17. The lighting device of claim 1, further comprising a heat sink bracket configured to aid in transferring heat generated by the light source from the ferromagnetic strip to the housing, wherein a first portion of the heat sink bracket is positioned between the light source and the ferromagnetic strip and a second portion of the heat sink bracket directly contacts the first side wall or the second side wall of the housing.
 18. The lighting device of claim 3, wherein the lens comprises a flexible material.
 19. The lighting device of claim 3, wherein the lens comprises a rigid material.
 20. The lighting device of claim 3, wherein the lens comprises polymethyl methacrylate (PMMA).
 21. The lighting device of claim 3, wherein the first side wall of the housing includes a first protrusion extending into the internal cavity and the second side wall of the housing includes a second protrusion extending into the internal cavity.
 22. The lighting device of claim 21, wherein a first side of the lens includes a first groove configured to engage the first protrusion and a second side of the lens includes a second groove configured to engage the second protrusion to couple the lens to the housing.
 23. The lighting device of claim 3, further comprising one or more double-sided adhesive strips configured to couple the light source to the ferromagnetic strip.
 24. The lighting device of claim 3, wherein the light source includes a plurality of light emitting diodes (LEDs) coupled to a support substrate, wherein the support substrate is coupled to the

ferromagnetic strip.

25. The lighting device of claim 3, further comprising a first end cap coupled to a first end of the housing and second end cap coupled to a second end of the housing.

26. The lighting device of claim 25, wherein the housing includes an upper groove extending between the first end and the second end of the housing, the first end cap includes a first tongue configured to engage the upper groove to aid in coupling the first end cap to the first end of the housing, and the second end cap includes a second tongue configured to engage the upper groove to aid in coupling the second end cap to the second end of the housing.

27. The lighting device of claim 3, wherein the ferromagnetic strip includes a protective coating comprising a zinc and aluminum alloy.

28. The lighting device of claim 3, further comprising a heat sink bracket configured to aid in transferring heat generated by the light source from the ferromagnetic strip to the housing, wherein a first portion of the heat sink bracket is positioned between the light source and the ferromagnetic strip and a second portion of the heat sink bracket directly contacts the first side wall or the second side wall of the housing.
